

ETSI TS 101 726 V7.6.0 (2001-12)

Technical Specification

**Digital cellular telecommunications system (Phase 2+);
Serving Mobile Location Centre -
Base Station System (SMLC-BSS) interface;
Layer 3 specification
(3GPP TS 08.71 version 7.6.0 Release 1999)**

GSM®
GLOBAL SYSTEM FOR
MOBILE COMMUNICATIONS

3GPP

ETSI 

Reference

RTS/TSGG-020871Q7R6

Keywords

GSM

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

Individual copies of the present document can be downloaded from:

<http://www.etsi.org>

The present document may be made available in more than one electronic version or in print. In any case of existing or perceived difference in contents between such versions, the reference version is the Portable Document Format (PDF). In case of dispute, the reference shall be the printing on ETSI printers of the PDF version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at

<http://portal.etsi.org/tb/status/status.asp>

If you find errors in the present document, send your comment to:

editor@etsi.fr

Copyright Notification

No part may be reproduced except as authorized by written permission.
The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2001.
All rights reserved.

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://webapp.etsi.org/IPR/home.asp>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities, UMTS identities or GSM identities. These should be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between GSM, UMTS, 3GPP and ETSI identities can be found under www.etsi.org/key.

Contents

| | |
|--|-----------|
| Intellectual Property Rights | 2 |
| Foreword..... | 2 |
| Foreword..... | 4 |
| 1 Scope | 5 |
| 1.1 References | 5 |
| 1.2 Abbreviations | 5 |
| 2 Messages functional definitions and contents | 6 |
| 2.1 General | 6 |
| 2.2 Messages | 6 |
| 2.2.1 TA Request | 7 |
| 2.2.2 TA Response..... | 7 |
| 2.2.3 TOA Request | 7 |
| 2.2.4 TOA Response..... | 7 |
| 2.2.5 Reject..... | 8 |
| 2.2.6 Reset | 8 |
| 2.2.7 Abort..... | 9 |
| 2.2.8 TA Layer3..... | 9 |
| 2.2.9 MS Position Command | 9 |
| 2.2.10 MS Position Response | 9 |
| 3 Information element encodings | 10 |
| 3.1 Message Type IE..... | 10 |
| 3.2 Timing Advance IE | 11 |
| 3.3 Handover Type IE | 11 |
| 3.4 Cell Identity IE | 11 |
| 3.5 Starting Time IE | 12 |
| 3.6 Neighbor Cell Identity IE..... | 12 |
| 3.7 Neighbor Starting Time IE | 12 |
| 3.8 Channel Description IE..... | 12 |
| 3.9 Frequency List IE | 13 |
| 3.10 Handover Reference IE | 13 |
| 3.11 MS Power IE | 13 |
| 3.12 Measurement Report IE..... | 13 |
| 3.13 Delta Timer | 13 |
| 3.14 Cause IE | 14 |
| 3.15 RRLP Flag IE..... | 14 |
| 3.16 RRLP IE..... | 14 |
| Annex A (informative): Change History | 15 |
| History | 16 |

Foreword

This Technical Specification (TS) has been produced by the Special Mobile Group (SMG).

The present document defines the coding of information necessary for support of location service operation on the SMLC-BSS interface layer 3 within the digital cellular telecommunications system.

The contents of the present document are subject to continuing work within SMG and T1P1 and may change following formal SMG and T1P1 approval. Should SMG or T1P1 modify the contents of the present document it will then be re-issued with an identifying change of release date and an increase in version number as follows:

Version 7.x.y

where:

- 7 GSM Phase 2+ Release 1998;
- x the second digit is incremented for all other types of changes, i.e. technical enhancements, corrections, updates, etc.;
- y the third digit is incremented when editorial only changes have been incorporated in the specification.

1 Scope

The present document contains the coding of information necessary for support of location service operation on the SMLC-BSS interface layer 3.

Clause 2 gives the functional definitions and contents of messages for location service operations. Clause 3 gives the general format and coding for messages used for location service and the format and coding of information elements used for location service operations.

1.1 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TS 01.04: "Digital cellular telecommunications system (Phase 2+); Abbreviations and acronyms".
- [2] 3GPP TS 03.71: "Digital cellular telecommunications system (Phase 2+); Location Services (LCS); (Functional description) - Stage 2".
- [3] 3GPP TS 04.07: "Digital cellular telecommunications system (Phase 2+); Mobile radio interface signalling layer 3; General aspects".
- [4] 3GPP TS 04.08: "Digital cellular telecommunications system (Phase 2+); Mobile radio interface layer 3 specification".
- [5] 3GPP TS 05.08: "Digital cellular telecommunications system (Phase 2+); Radio subsystem link control".
- [6] 3GPP TS 08.08: "Digital cellular telecommunications system (Phase 2+); Mobile-services Switching Centre - Base Station System (MSC-BSS) interface; Layer 3 specification".

1.2 Abbreviations

Abbreviations used in the present document are listed in 3GPP TS 01.04.

2 Messages functional definitions and contents

2.1 General

This clause defines the structure of the messages of the SMLC-BSS layer 3 protocol defined in 3GPP TS 03.71.

Each definition includes:

- a) a brief description of the message;
- b) a table listing the information elements in the order of their appearance in the message.

For each IE the table indicates:

- 1) the name of the IE (which gives an idea of the semantics of the element), which is used in this and other specifications as a reference to the IE within the message;
 - 2) the name of the type of the IE (which indicates the coding of the value part of the IE), and a reference to a description of the value part of the IE;
 - 3) the presence requirement indication (M, C or O) for the IE, as defined in 3GPP TS 04.07;
 - 4) the format of the IE (T, V, TV, LV, TLV) as defined in 3GPP TS 04.07;
 - 5) the length of the IE (or permissible range of lengths), in octets, in the message. The value of the length gives the number of octets in the IE following the length and element identifier. Where the length is encoded using more than one octet, the high order bit is bit 8 of the first (lowest numbered octet) and the low order bit is bit 1 of the last (highest numbered octet).
- c) subclauses specifying conditions for IEs with presence requirement C or O in the relevant message. Together with other conditions specified in 3GPP TS 03.71 this defines when the IE shall be included or not, what non-presence of such IEs means, and (for IEs with presence requirement C) the static conditions for presence and/or non-presence of the IEs (see 3GPP TS 03.71).

2.2 Messages

The following Location Services related messages are exchanged between the SMLC and the BSS, with the VMSC acting as a relay.

1. TA Request
2. TA Response
3. TOA Request
4. TOA Response
5. Reject
6. Reset
7. Abort
8. TA Layer3
9. MS Position Command
10. MS Position Response

On the A interface the messages are contained in the Location Information IE which is encapsulated in the BSSMAP-LE Connection Oriented Information message as specified in 3GPP TS 08.08. On the Ls interface the messages are contained in the Location Information IE which is encapsulated in the BSSMAP-LE Connection Oriented Information message as specified in 3GPP TS 09.31.

2.2.1 TA Request

The TA Request is a message from the SMLC to the BSS, requesting BSS to return the timing advance (or access delay) of the MS.

Table 2.1: TA Request message content

| Information element | Type/Reference | Presence | Format | Length |
|---------------------|---------------------|----------|--------|--------|
| Message Type | Message Type IE 3.1 | M | V | 1 |

2.2.2 TA Response

The TA Response is a message from the BSS to the SMLC. It is a response to TA Request message and contains the following information elements.

Table 2.2: TA Response message content

| Information element | Type/Reference | Presence | Format | Length |
|-----------------------|----------------------------|----------|--------|--------|
| Message Type | Message Type IE 3.1 | M | V | 1 |
| Serving Cell Identity | Cell Identity IE 3.4 | M | TV | 3 |
| Timing Advance | Timing Advance IE 3.2 | M | TV | 2 |
| Measurement Report | Measurement Report IE 3.12 | O | TLV | 18 |

2.2.3 TOA Request

The TOA Request is a message from the SMLC to the BSS. It contains the following information elements.

Table 2.3: TOA Request message content

| Information element | Type/Reference | Presence | Format | Length |
|------------------------|-------------------------------|----------|--------|--------|
| Message Type | Message Type IE 3.1 | M | V | 1 |
| Delta Timer | Delta Timer IE 3.13 | M | TV | 2 |
| Handover Type | Handover Type IE 3.3 | M | TV | 2 |
| Serving Cell Identity | Cell Identity IE 3.4 | M | TV | 3 |
| Serving Starting Time | Starting Time IE 3.5 | M | TV | 3 |
| Neighbor Cell Identity | Neighbor Cell Identity IE 3.6 | O | TLV | 4-n |
| Neighbor Starting Time | Neighbor Starting Time IE 3.7 | O | TLV | 4-n |

2.2.4 TOA Response

The TOA Response is a message from the BSS to the SMLC. It is a response to the TOA Request message. It contains the following information elements.

Table 2.4: TOA Response message content

| Information element | Type/Reference | Presence | Format | Length |
|-----------------------|----------------------------|----------|--------|--------|
| Message Type | Message Type IE 3.1 | M | V | 1 |
| Channel Description | Channel Description IE 3.8 | M | TV | 4 |
| Frequency List | Frequency List IE 3.9 | M | TLV | 3-n |
| Handover Reference | Handover Reference IE 3.10 | M | TV | 2 |
| Target Cell Identity | Cell Identity IE 3.4 | M | TV | 3 |
| Serving Cell Identity | Cell Identity IE 3.4 | M | TV | 3 |
| Timing Advance | Timing Advance IE 3.2 | M | TV | 2 |
| MS Power | MS Power IE 3.11 | M | TV | 2 |
| Measurement Report | Measurement Report IE 3.12 | O | TLV | 18 |

2.2.5 Reject

The Reject is a message from the BSS to the SMLC. It is a possible response to TOA Request, TA Request or MS Position Command and contains the following information elements.

Table 2.5: Reject message content

| Information element | Type/Reference | Presence | Format | Length |
|---------------------|---------------------|----------|--------|--------|
| Message Type | Message Type IE 3.1 | M | V | 1 |
| Cause | Cause IE 3.14 | M | TV | 2 |

The following are the expected cause values for Reject message:

- congestion;
- channel Mode not supported;
- positioning procedure not supported;
- failure for other radio related events;
- incorrect serving cell identity.
- BSSAP-LE Segmentation error

2.2.6 Reset

The Reset is a message from the BSS to the SMLC. It is sent when the Response message contents for a positioning request are invalidated (e.g. due to handover) before the positioning procedure was completed. The message may also be sent instead of a Reject when a TOA Request cannot be performed due to an error in the serving cell identity.

Table 2.6: Reset message content

| Information element | Type/Reference | Presence | Format | Length |
|---------------------|----------------------------|----------|--------|--------|
| Message Type | Message Type IE 3.1 | M | V | 1 |
| Cell ID | Cell Identity IE 3.4 | M | TV | 3 |
| Timing Advance | Timing Advance IE 3.2 | M | TV | 2 |
| Channel description | Channel Description IE 3.8 | M | TV | 4 |
| Cause | Cause IE 3.14 | M | TV | 2 |
| Measurement Report | Measurement Report IE 3.12 | O | TLV | 18 |

The following are the expected cause values for Reset message:

- intra-BSS handover;
- failure for other radio related events;
- supervision Timer Expired;
- incorrect serving cell identity.

2.2.7 Abort

The Abort is a message either from the BSS to the SMLC or SMLC to the BSS. Upon receiving this signal, either SMLC or BSS shall abort ongoing positioning procedure.

Table 2.7: Abort message content

| Information element | Type/Reference | Presence | Format | Length |
|---------------------|---------------------|----------|--------|--------|
| Message Type | Message Type IE 3.1 | M | V | 1 |
| Cause | Cause IE 3.14 | M | TV | 2 |

The following are the expected cause values for Abort message:

- failure for other radio related events;
- supervision Timer Expired;
- inter BSS handover;
- loss of signalling connection to MS.

2.2.8 TA Layer3

The TA Layer3 is an optional encapsulated message from the BSS to the SMLC that adds the following information in Complete layer 3 Information as described in 3GPP TS 08.08.

Table 2.8: TA Layer3 message content

| Information element | Type/Reference | Presence | Format | Length |
|---------------------|----------------------------|----------|--------|--------|
| Message Type | Message Type IE 3.1 | M | V | 1 |
| Timing Advance | Timing Advance IE 3.2 | M | TV | 2 |
| Measurement Report | Measurement Report IE 3.12 | O | TLV | 18 |

2.2.9 MS Position Command

The BSSLAP MS Position Command is the message from the SMLC to BSS that contains the following information elements.

Table 2.9: MS Position Command message content

| Information element | Type/Reference | Presence | Format | Length |
|---------------------|---------------------|----------|--------|--------|
| Message Type | Message Type IE 3.1 | M | V | 1 |
| flag | RRLP flag IE 3.15 | M | TV | 2 |
| RRLP Info | RRLP IE 3.16 | M | TLV | 3 to N |

2.2.10 MS Position Response

The BSSLAP MS Position Response is a message from the BSS to the SMLC that contain the following information elements.

Table 2.10: MS Position Response message content

| Information element | Type/Reference | Presence | Format | Length |
|---------------------|----------------------------|----------|--------|--------|
| Message Type | Message Type IE 3.1 | M | V | 1 |
| flag | RRLP flag IE 3.15 | M | TV | 2 |
| RRLP Info | RRLP IE 3.16 | M | TLV | 3 to N |
| Timing Advance | Timing Advance IE 3.2 | O | TLV | 2 |
| Measurement Report | Measurement Report IE 3.12 | O | TLV | 18 |

3 Information element encodings

This paragraph contains the coding of the signalling elements used.

The following conventions are assumed for the sequence of transmission of bits and bytes:

- each bit position is marked as 1 to 8. Bit 1 is the least significant bit and is transmitted first;
- in an element octets are identified by number, octet 1 is transmitted first, then octet 2 etc.

When a field extends over more than one octet, the order of bit values progressively decreases as the octet number increases. The least significant bit of the field is represented by the lowest numbered bit of the highest numbered octet of the field.

- For variable length elements a length indicator is included, this indicates the number of octets following in the element.
- All fields within Information Elements are mandatory unless otherwise specified. The Information Element Identifier shall always be included.

All spare bits are set to 0.

The elements used and their coding are:

| Element Identifier Coding | Element name | Reference |
|---------------------------|------------------------|-----------|
| 0000 0001 | Timing Advance | 3.2 |
| 0000 1000 | Handover Type | 3.3 |
| 0000 1001 | Cell Identity | 3.4 |
| 0000 1010 | Starting Time | 3.5 |
| 0000 1011 | Neighbor Cell Identity | 3.6 |
| 0000 1100 | Neighbor Starting Time | 3.7 |
| 0001 0000 | Channel Description | 3.8 |
| 0001 0001 | Frequency List | 3.9 |
| 0001 0010 | Handover Reference | 3.10 |
| 0001 0011 | MS Power | 3.11 |
| 0001 0100 | Measurement Report | 3.12 |
| 0001 0101 | Delta Timer | 3.13 |
| 0001 1000 | Cause | 3.14 |
| 0001 1001 | RRLP Flag | 3.15 |
| 0001 1011 | RRLP IE | 3.16 |

All unassigned codes are spare.

3.1 Message Type IE

Message Type uniquely identifies the message being sent. It is a single octet element, mandatory in all messages.

All unassigned codes are spare.

| 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | |
|---|---|---|---|---|---|---|---|----------------------|
| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | Reserved. |
| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 1 | TA REQUEST |
| 0 | 0 | 0 | 0 | 0 | 0 | 1 | 0 | TA RESPONSE |
| 0 | 0 | 0 | 0 | 0 | 1 | 0 | 0 | TOA REQUEST |
| 0 | 0 | 0 | 0 | 1 | 0 | 1 | | TOA RESPONSE |
| 0 | 0 | 0 | 1 | 0 | 1 | 0 | | REJECT |
| 0 | 0 | 0 | 1 | 0 | 1 | 1 | | RESET |
| 0 | 0 | 0 | 1 | 1 | 0 | 0 | | ABORT |
| 0 | 0 | 0 | 1 | 1 | 0 | 1 | | TA LAYER3 |
| 0 | 0 | 0 | 1 | 1 | 1 | 1 | | MS Position Command |
| 0 | 0 | 1 | 0 | 0 | 0 | 0 | | MS Position Response |

3.2 Timing Advance IE

This element contains the Timing Advance measured by the BTS.

| 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | |
|--------------------|---|---|---|---|---|---|---|---------|
| Element identifier | | | | | | | | octet 1 |
| Timing Advance | | | | | | | | octet 2 |

The coding of the timing advance value field is the binary representation of the timing advance in bit periods; 1 bit period = 48/13 us, as described in 3GPP TS 04.08 with the difference that all 8 bits are significant (instead of the normal 6 bits), which is necessary in order to report TA from extended range cells. To be correct, values over 63 do not correspond to a TA used by the MS (maximum is 63). Instead values over 63 correspond to the access delay measured by the BTS.

3.3 Handover Type IE

This IE defines the preferred type of handover for positioning.

| 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | |
|--------------------|---|---|---|---|---|---|---|---------|
| Element identifier | | | | | | | | octet 1 |
| Handover Type | | | | | | | | octet 2 |

The coding of the handover type field is as follows:

- 0000 0000 Intra-cell handover to same channel;
- 0000 0001 Intra-cell handover to new channel;
- 0000 0010 Inter-cell handover;
- 0000 0011 BSS selects handover type;
- all other values reserved.

3.4 Cell Identity IE

This element defines the cell identity of the MS serving cell.

| 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | |
|--------------------|---|---|---|---|---|---|---|-----------|
| Element identifier | | | | | | | | octet 1 |
| Cell Identity | | | | | | | | octet 2-3 |

The coding of the Cell Identity field is as defined in 3GPP TS 04.08 clause 10.5.1.1 Cell Identity (excluding IEI).

3.5 Starting Time IE

This element defines the starting frame number for handover.

| | | | | | | | | |
|--------------------|---|---|---|---|---|---|---|-----------|
| 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | |
| Element identifier | | | | | | | | octet 1 |
| Starting Time | | | | | | | | octet 2-3 |

The coding of the Starting Time field is as defined in 3GPP TS 04.08 clause 10.5.2.38 Starting Time (excluding IEI).

3.6 Neighbor Cell Identity IE

This element defines the cell identity of the candidate neighbor cells for positioning handover.

| | | | | | | | | |
|--------------------|---|---|---|---|---|---|---|--------------------|
| 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | |
| Element identifier | | | | | | | | octet 1 |
| Length | | | | | | | | octet 2 |
| Cell Identity (1) | | | | | | | | octets 3-4 |
| : | | | | | | | | |
| Cell Identity (n) | | | | | | | | octets 2n+1 - 2n+2 |

The coding of the Cell Identity field is as defined in in 3GPP TS 04.08 subclause 10.5.1.1 Cell Identity (excluding IEI's).

3.7 Neighbor Starting Time IE

This element defines the starting frame number for handover to neighboring cells.

| | | | | | | | | |
|--------------------|---|---|---|---|---|---|---|--------------------|
| 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | |
| Element identifier | | | | | | | | octet 1 |
| Length | | | | | | | | octet 2 |
| Starting Time (1) | | | | | | | | octets 3-4 |
| : | | | | | | | | |
| Starting Time (n) | | | | | | | | octets 2n+1 - 2n+2 |

The coding of the Starting Time field is as defined in 3GPP TS 04.08 clause 10.5.2.38 Starting Time (excluding IEI).

3.8 Channel Description IE

This element defines the physical channel allocation of the MS.

| | | | | | | | | |
|---------------------|---|---|---|---|---|---|---|------------|
| 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | |
| Element identifier | | | | | | | | octet 1 |
| Channel Description | | | | | | | | octets 2-4 |

The coding of Channel Description field is as defined in 3GPP TS 04.08 clause 10.5.2.5a Channel Description (excluding IEI).

3.9 Frequency List IE

The Frequency List IE contains a list of frequencies used by the MS.

| | | | | | | | | |
|--------------------|---|---|---|---|---|---|---|------------|
| 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | |
| Element identifier | | | | | | | | octet 1 |
| Length | | | | | | | | octet 2 |
| Frequency List | | | | | | | | octets 3-n |

The coding of Frequency List field is as defined in 3GPP TS 04.08 subclause 10.5.2.13 Frequency List (excluding IEI and length field).

3.10 Handover Reference IE

This element defines the handover reference number used by the MS.

| | | | | | | | | |
|--------------------|---|---|---|---|---|---|---|---------|
| 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | |
| Element identifier | | | | | | | | octet 1 |
| Handover Reference | | | | | | | | octet 2 |

The coding of Handover Reference field is as defined in 3GPP TS 04.08 subclause 10.5.2.15 Handover Reference (excluding IEI).

3.11 MS Power IE

This element contains the MS power.

| | | | | | | | | |
|--------------------|---|---|---|---|---|---|---|---------|
| 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | |
| Element identifier | | | | | | | | octet 1 |
| MS Power | | | | | | | | octet 2 |

The MS Power field is encoded as in 3GPP TS 04.08 subclause 10.5.2.28 Power Command (excluding IEI) and 3GPP TS 05.08.

3.12 Measurement Report IE

This element contains the measurement report from the BSS.

| | | | | | | | | |
|---------------------|---|---|---|---|---|---|---|------------|
| 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | |
| Element identifier | | | | | | | | octet 1 |
| Length | | | | | | | | octet 2 |
| Measurement Results | | | | | | | | octet 2-17 |

The Measurement Results field is encoded as in 3GPP TS 04.08 subclause 10.5.2.20 Measurement Result (excluding IEI).

3.13 Delta Timer

This element contains the value of the delta timer. The coding is as follows.

| | | | | | | | | |
|--------------------|---|---|---|---|---|---|---|---------|
| 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | |
| Element identifier | | | | | | | | octet 1 |
| Timer Value | | | | | | | | octet 2 |

The Timer Value field is expressed in units of 0,05 s.

3.14 Cause IE

This element contains the cause value.

| | | | | | | | | |
|--------------------|---|---|---|---|---|---|---|---------|
| 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | |
| Element identifier | | | | | | | | octet 1 |
| Cause value | | | | | | | | octet 2 |

The cause field is coded as follows:

| | |
|---------------------------------|--|
| 0000 0000 | Congestion |
| 0000 0001 | Channel Mode not supported |
| 0000 0010 | Positioning procedure not supported |
| 0000 0011 | Failure for other radio related events |
| 0000 0100 | Intra-BSS handover |
| 0000 0101 | Supervision Timer Expired |
| 0000 0110 | Inter-BSS handover |
| 0000 0111 | Loss of signalling connection to MS |
| 0000 1000 | Incorrect serving cell identity |
| 0000 1001 | BSSAP-LE Segmentation error |
| All unassigned codes are spare. | |

3.15 RRLP Flag IE

This element is coded as:

| | | | | | | | | |
|--------------------|---|---|---|---|---|---|-------|---------|
| 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | |
| Element identifier | | | | | | | | octet 1 |
| SPARE | | | | | | | Flag1 | octet 2 |

The fields are coded as follows:

Flag 1 (Octet 2, bit 1)

0 – Position Command (SMLC to BSC) or final response (BSC to SMLC)

1 – Not a Positioning Command or final response

3.16 RRLP IE

RRLP IE is coded as:

| | | | | | | | | |
|---------------------------|---|---|---|---|---|---|---|-----------|
| 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | |
| Element identifier | | | | | | | | octet 1 |
| Length | | | | | | | | octet 2-3 |
| RRLP APDU (3GPP TS 04.31) | | | | | | | | octet 4-N |

Annex A (informative): Change History

| Meeting | CR | Rev | Subject/Comment | New version |
|-----------|------|-----|---|-------------|
| SMG#29 | - | | Approved at SMG#29 as Release 98 | 7.0.0 |
| SMG#30bis | A001 | | Addition of further LCS functionality in GSM Release 98. | 7.1.1 |
| SMG#31 | A002 | 2 | Correction of Segmentation Support, other minor corrections | 7.2.0 |
| SMG#31bis | A003 | | Addition of new error cause and other minor corrections | 7.2.0 |
| GP-02 | A005 | | Corrections to LCS BSSLAP Protocol | 7.4.0 |
| - | - | - | Minor formatting corrections. Update to 3GPP template and format. | 7.4.0 |
| GP-06 | A013 | | Addition of a missing cause value in BSSLAP for segmentation errors (R98) | 7.5.0 |
| GP-07 | A018 | | Correction of Cause IE reference | 7.6.0 |

History

| Document history | | |
|-------------------------|----------------|-------------|
| V7.0.0 | August 1999 | Publication |
| V7.1.1 | January 2000 | Publication |
| V7.2.0 | February 2000 | Publication |
| V7.3.0 | May 2000 | Publication |
| V7.4.0 | November 2000 | Publication |
| V7.5.0 | September 2001 | Publication |
| V7.6.0 | December 2001 | Publication |