ETSITS 125 423 V10.10.0 (2014-01)



Universal Mobile Telecommunications System (UMTS); UTRAN lur interface Radio Network Subsystem Application Part (RNSAP) signalling (3GPP TS 25.423 version 10.10.0 Release 10)



Reference
RTS/TSGR-0325423vaa0

Keywords
UMTS

ETSI

650 Route des Lucioles F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C Association à but non lucratif enregistrée à la Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

The present document may be made available in more than one electronic version or in print. In any case of existing or perceived difference in contents between such versions, the reference version is the Portable Document Format (PDF). In case of dispute, the reference shall be the printing on ETSI printers of the PDF version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at http://portal.etsi.org/tb/status/status.asp

If you find errors in the present document, please send your comment to one of the following services: http://portal.etsi.org/chaircor/ETSI_support.asp

Copyright Notification

No part may be reproduced except as authorized by written permission. The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2013.
All rights reserved.

DECT[™], **PLUGTESTS**[™], **UMTS**[™] and the ETSI logo are Trade Marks of ETSI registered for the benefit of its Members. **3GPP**[™] and **LTE**[™] are Trade Marks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

GSM® and the GSM logo are Trade Marks registered and owned by the GSM Association.

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (http://ipr.etsi.org).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities, UMTS identities or GSM identities. These should be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between GSM, UMTS, 3GPP and ETSI identities can be found under http://webapp.etsi.org/key/queryform.asp.

Contents

Intelle	ntellectual Property Rights	
Forew	vord	2
Forew	vord	23
1	Scope	24
2	References	24
3	Definitions, Symbols and Abbreviations	26
3.1	Definitions	26
3.2	Symbols	27
3.3	Abbreviations	28
4	General	
4.1	Procedure Specification Principles	
4.2	Forwards and Backwards Compatibility	
4.3	Source Signalling Address Handling	
4.4	Specification Notations	31
5	RNSAP Services	32
5.1	RNSAP Procedure Modules	32
5.2	Parallel Transactions	33
6	Services Expected from Signalling Transport	33
7	Functions of RNSAP	33
7.1	RNSAP functions and elementary procedures for Iur-g.	
	,	
8	RNSAP Procedures	
8.1	Elementary Procedures	
8.2	Basic Mobility Procedures	
8.2.1	Uplink Signalling Transfer	
8.2.1.1 8.2.1.2		
8.2.1.2 8.2.1.3	- · · · · · · · · · · · · · · · · · · ·	
8.2.1. 8.2.1 <i>A</i>		
8.2.1 <i>A</i>		
8.2.1A		
8.2.1A	*	
8.2.2	Downlink Signalling Transfer	
8.2.2.1		
8.2.2.1		
8.2.2.2		
8.2.2.2		
8.2.2.3		
8.2.2.3	3.1 Abnormal Conditions for Iur-g	43
8.2.3	Relocation Commit	43
8.2.3.1	1 General	43
8.2.3.2	ı	
8.2.3.2		
8.2.3.3		
8.2.4	Paging	
8.2.4.1		
8.2.4.2		
8.2.4.2	ı	
8.2.4.3		
8.2.4.3 8.2.5	3.1 Abnormal Conditions for Iur-g	
0.2.3 8 2 5 1		43

8.2.5.2	Successful Operation	
8.2.5.3	Abnormal Conditions	
8.2.6	Enhanced Relocation Resource Allocation[1.28Mcps TDD]	
8.2.6.1	General	
8.2.6.2	Successful Operation	
8.2.6.3	Unsuccessful Operation	47
8.2.6.4	Abnormal Conditions	47
8.2.7	Enhanced Relocation Resource Release[1.28Mcps TDD]	47
8.2.7.1	General	47
8.2.7.2	Successful Operation	47
8.2.7.3	Abnormal Conditions	47
8.3	Dedicated Procedures	48
8.3.1	Radio Link Setup	48
8.3.1.1	General	48
8.3.1.2	Successful Operation	48
8.3.1.3	Unsuccessful Operation	76
8.3.1.4	Abnormal Conditions	78
8.3.2	Radio Link Addition	81
8.3.2.1	General	81
8.3.2.2	Successful Operation	81
8.3.2.3	Unsuccessful Operation	111
8.3.2.4	Abnormal Conditions	113
8.3.3	Radio Link Deletion	116
8.3.3.1	General	116
8.3.3.2	Successful Operation	117
8.3.3.3	Unsuccessful Operation	117
8.3.3.4	Abnormal Conditions	117
8.3.4	Synchronised Radio Link Reconfiguration Preparation	
8.3.4.1	General	117
8.3.4.2	Successful Operation	118
8.3.4.3	Unsuccessful Operation	
8.3.4.4	Abnormal Conditions	163
8.3.5	Synchronised Radio Link Reconfiguration Commit	
8.3.5.1	General	168
8.3.5.2	Successful Operation	168
8.3.5.3	Abnormal Conditions	
8.3.6	Synchronised Radio Link Reconfiguration Cancellation	169
8.3.6.1	General	169
8.3.6.2	Successful Operation	170
8.3.6.3	Abnormal Conditions	170
8.3.7	Unsynchronised Radio Link Reconfiguration	170
8.3.7.1	General	170
8.3.7.2	Successful Operation	170
8.3.7.3	Unsuccessful Operation	207
8.3.7.4	Abnormal Conditions	208
8.3.8	Physical Channel Reconfiguration	212
8.3.8.1	General	212
8.3.8.2	Successful Operation	213
8.3.8.3	Unsuccessful Operation	214
8.3.8.4	Abnormal Conditions	214
8.3.9	Radio Link Failure	214
8.3.9.1	General	214
8.3.9.2	Successful Operation	215
8.3.9.3	Abnormal Conditions	216
8.3.10	Radio Link Restoration	216
8.3.10.1	General	216
8.3.10.2	Successful Operation	216
8.3.10.3	Abnormal Conditions	216
8.3.11	Dedicated Measurement Initiation	216
8.3.11.1	General	216
8.3.11.2	Successful Operation	217
8 3 11 3	Unsuccessful Operation	220

8.3.11.4	Abnormal Conditions	220
8.3.12	Dedicated Measurement Reporting.	
8.3.12.1	General	
8.3.12.2	Successful Operation	
8.3.12.3	Abnormal Conditions	
8.3.13	Dedicated Measurement Termination	
8.3.13.1	General	
8.3.13.2	Successful Operation	
8.3.13.3	Abnormal Conditions	
8.3.14	Dedicated Measurement Failure	
8.3.14.1	General	
8.3.14.2	Successful Operation	
8.3.14.3	Abnormal Conditions	
8.3.15	Downlink Power Control [FDD]	
8.3.15.1	General	
8.3.15.2	Successful Operation	
8.3.15.3	Abnormal Conditions	
8.3.16	Compressed Mode Command [FDD]	
8.3.16.1	General	
8.3.16.2	Successful Operation	
8.3.16.3	Abnormal Conditions	
8.3.17	Downlink Power Timeslot Control [TDD]	
8.3.17.1	General	
8.3.17.2	Successful Operation	
8.3.17.3	Abnormal Conditions	
8.3.18	Radio Link Pre-emption	
8.3.18.1	General	
8.3.18.2	Successful Operation	
8.3.18.3	Abnormal Conditions	
8.3.19	Radio Link Congestion	
8.3.19.1	General	
8.3.19.2	Successful Operation	
8.3.19.3	Abnormal Conditions	
8.3.20	Radio Link Activation	
8.3.20.1	General	
8.3.20.2	Successful Operation	
8.3.20.3	Abnormal Conditions	
8.3.21	Radio Link Parameter Update	
8.3.21.1	General	
8.3.21.2	Successful Operation.	
8.3.21.3	Abnormal Conditions	
8.3.22	UE Measurement Initiation [TDD]	
8.3.22.1	General	
8.3.22.2	Successful Operation	
8.3.22.3	Unsuccessful Operation	
8.3.22.4	Abnormal Conditions	
8.3.23	UE Measurement Reporting [TDD]	
8.3.23.1	General	
8.3.23.2	Successful Operation	
8.3.23.3	Abnormal Conditions	
8.3.24	UE Measurement Termination [TDD]	
8.3.24.1	General	
8.3.24.2	Successful Operation	
8.3.24.3	Abnormal Conditions	
8.3.25	UE Measurement Failure [TDD]	
8.3.25.1	General	
8.3.25.2	Successful Operation	
8.3.25.3	Abnormal Conditions	
8.3.26	Iur Invoke Trace	
8.3.26.1	General	
8.3.26.2	Successful Operation	
8 3 26 3	Abnormal Conditions	235

8.3.27	Iur Deactivate Trace	236
8.3.27.1	General	
8.3.27.1	Successful Operation	
8.3.27.3	•	
	Abnormal Conditions	
8.3.28	Enhanced Relocation	
8.3.28.1	General	
8.3.28.2	Successful Operation	
8.3.28.3	Unsuccessful Operation	
8.3.28.4	Abnormal Conditions	
8.3.29	Enhanced Relocation Cancel	237
8.3.29.1	General	237
8.3.29.2	Successful Operation	237
8.3.29.3	Unsuccessful Operation	238
8.3.29.4	Abnormal Conditions	238
8.3.30	Enhanced Relocation Signalling Transfer	
8.3.30.1	General	
8.3.30.2	Successful Operation	
8.3.30.3	Abnormal Conditions	
8.3.31	Enhanced Relocation Release	
8.3.31.1	General	
8.3.31.2	Successful Operation	
8.3.31.3	Abnormal Conditions	
8.3.32	Secondary UL Frequency Reporting [FDD]	
8.3.32.1	General	
8.3.32.2	Successful Operation	
8.3.32.3	Abnormal Conditions	
8.3.33	Secondary UL Frequency Update [FDD]	240
8.3.33.1	General	240
8.3.33.2	Successful Operation	240
8.3.33.3	Abnormal Conditions	240
8.4	Common Transport Channel Procedures	
8.4.1	Common Transport Channel Resources Initialisation	
8.4.1.1	General	
8.4.1.2	Successful Operation	
8.4.1.3	Unsuccessful Operation	
8.4.1.4	Abnormal Conditions	
8.4.2	Common Transport Channel Resources Release	
8.4.2.1	General	
8.4.2.2	Successful Operation	
8.4.2.3	Abnormal Conditions	
8.5	Global Procedures	
8.5.1	Error Indication	
8.5.1.1	General	
8.5.1.2	Successful Operation	
8.5.1.2.1	Successful Operation for Iur-g	244
8.5.1.3	Abnormal Conditions	244
8.5.2	Common Measurement Initiation	245
8.5.2.1	General	245
8.5.2.2	Successful Operation	245
8.5.2.2.1	Successful Operation for Iur-g	
8.5.2.3	Unsuccessful Operation	
8.5.2.4	Abnormal Conditions	
8.5.2.4.1	Abnormal Conditions for Iur-g	
8.5.3	Common Measurement Reporting	
8.5.3.1	ž v	
	General Suppose for Construction	
8.5.3.2	Successful Operation	
8.5.3.2.1	Successful Operation for Iur-g	
8.5.3.3	Abnormal Conditions	
8.5.4	Common Measurement Termination	
8.5.4.1	General	
8.5.4.2	Successful Operation	
8.5.4.2.1	Successful Operation for Jur-g	256

8.5.4.3	Abnormal Conditions	
8.5.5	Common Measurement Failure	
8.5.5.1	General	
8.5.5.2	Successful Operation	
8.5.5.2.1		
8.5.5.3	Abnormal Conditions	
8.5.6	Information Exchange Initiation	
8.5.6.1	General	
8.5.6.2	Successful Operation	
8.5.6.2.1	Successful Operation for Iur-g	261
8.5.6.3	Unsuccessful Operation	
8.5.6.4	Abnormal Conditions	
8.5.6.4.1	Abnormal Conditions for Iur-g	263
8.5.7	Information Reporting	263
8.5.7.1	General	
8.5.7.2	Successful Operation	264
8.5.7.2.1	Successful Operation for Iur-g	
8.5.7.3	Abnormal Conditions	
8.5.8	Information Exchange Termination	
8.5.8.1	General	264
8.5.8.2	Successful Operation	264
8.5.8.2.1	Successful Operation for Iur-g	264
8.5.8.3	Abnormal Conditions	265
8.5.9	Information Exchange Failure	
8.5.9.1	General	265
8.5.9.2	Successful Operation	265
8.5.9.2.1	Successful Operation for Iur-g	265
8.5.10	Reset	265
8.5.10.1	General	265
8.5.10.2	Successful Operation	265
8.5.10.3	Abnormal Conditions	266
8.5.11	Direct Information Transfer	266
8.5.11.1	General	266
8.5.11.2	Successful Operation	266
8.5.12	Information Transfer Control	267
8.5.12.1	General	267
8.5.12.2	Successful Operation	267
8.5.12.3	Abnormal Conditions	268
8.6	MBMS Procedures	268
8.6.1	MBMS Attach	268
8.6.1.1	General	268
8.6.1.2	Successful Operation	268
8.6.1.3	Abnormal Conditions	268
8.6.2	MBMS Detach	269
8.6.2.1	General	269
8.6.2.2	Successful Operation	269
8.6.2.3	Abnormal Conditions	269
0 E	1	266
	llements for RNSAP Communication	
9.1	Message Functional Definition and Content	
9.1.1	General	
9.1.2	Message Contents	
9.1.2.1	Presence	
9.1.2.2	Criticality	
9.1.2.3	Range	
9.1.2.4	Assigned Criticality	
9.1.3	RADIO LINK SETUP REQUEST	
9.1.3.1	FDD Message	
9.1.3.2	TDD Message	
9.1.4	RADIO LINK SETUP RESPONSE	
9.1.4.1	FDD Message	
9142	TDD Message	282

9.1.5	RADIO LINK SETUP FAILURE	289
9.1.5.1	FDD Message	
9.1.5.2	TDD Message	
9.1.6	RADIO LINK ADDITION REQUEST	
9.1.6.1	FDD Message	
9.1.6.2	TDD Message	
9.1.7	RADIO LINK ADDITION RESPONSE	
9.1.7.1	FDD Message	
9.1.7.2	TDD Message	
9.1.8	RADIO LINK ADDITION FAILURE	
9.1.8.1	FDD Message	
9.1.8.2	TDD Message	
9.1.9	RADIO LINK DELETION REQUEST	
9.1.10	RADIO LINK DELETION RESPONSE	
9.1.11	RADIO LINK RECONFIGURATION PREPARE	
9.1.11.1	FDD Message	
9.1.11.2	TDD Message	
9.1.12	RADIO LINK RECONFIGURATION READY	
9.1.12.1	FDD Message	
9.1.12.1	TDD Message	
9.1.13	RADIO LINK RECONFIGURATION COMMIT	
9.1.14	RADIO LINK RECONFIGURATION COMMIT	
9.1.15	RADIO LINK RECONFIGURATION CANCEL	
9.1.16	RADIO LINK RECONFIGURATION CANCEL	
9.1.16.1	FDD Message	
9.1.16.1	· · · · · · · · · · · · · · · · · · ·	
9.1.10.2	TDD MessageRADIO LINK RECONFIGURATION RESPONSE	
9.1.17 9.1.17.1	FDD Message	
9.1.17.1	TDD Message	
9.1.17.2	RADIO LINK FAILURE INDICATION	
9.1.18 9.1.19	RADIO LINK RESTORE INDICATION	
9.1.19	DL POWER CONTROL REQUEST [FDD]	
9.1.20	PHYSICAL CHANNEL RECONFIGURATION REQUEST	
9.1.21	FDD MessageFDD Message	
9.1.21.1	TDD Message	
9.1.21.2	PHYSICAL CHANNEL RECONFIGURATION COMMAND	
9.1.22	PHYSICAL CHANNEL RECONFIGURATION COMMANDPHYSICAL CHANNEL RECONFIGURATION FAILURE	
9.1.23 9.1.24	UPLINK SIGNALLING TRANSFER INDICATION PAILURE	
9.1.24 9.1.24.1		
9.1.24.1	FDD Message	
9.1.24.2 9.1.24A	GERAN UPLINK SIGNALLING TRANSFER INDICATION	
9.1.24A 9.1.25	DOWNLINK SIGNALLING TRANSFER REQUEST	
	RELOCATION COMMIT	
9.1.26		
9.1.27	PAGING REQUEST DEDICATED MEASUREMENT INITIATION REQUEST	
9.1.28		
9.1.29	DEDICATED MEASUREMENT INITIATION RESPONSE	
9.1.30	DEDICATED MEASUREMENT INITIATION FAILURE	
9.1.31	DEDICATED MEASUREMENT REPORT	
9.1.32	DEDICATED MEASUREMENT TERMINATION REQUEST	
9.1.33	DEDICATED MEASUREMENT FAILURE INDICATION	
9.1.34	COMMON TRANSPORT CHANNEL RESOURCES RELEASE REQUEST	
9.1.35	COMMON TRANSPORT CHANNEL RESOURCES REQUEST	
9.1.36	COMMON TRANSPORT CHANNEL RESOURCES RESPONSE	
9.1.36.1	FDD Message	
9.1.36.2	TDD Message	
9.1.37	COMMON TRANSPORT CHANNEL RESOURCES FAILURE	
9.1.38	COMPRESSED MODE COMMAND [FDD]	
9.1.39	ERROR INDICATION	
9.1.40	DL POWER TIMESLOT CONTROL REQUEST [TDD]	
9.1.41	RADIO LINK PREEMPTION REQUIRED INDICATION	
9.1.42	RADIO LINK CONGESTION INDICATION	365 366

9.1.44	COMMON MEASUREMENT INITIATION RESPONSE	368
9.1.45	COMMON MEASUREMENT INITIATION FAILURE	369
9.1.46	COMMON MEASUREMENT REPORT	
9.1.47	COMMON MEASUREMENT TERMINATION REQUEST	
9.1.48	COMMON MEASUREMENT FAILURE INDICATION	370
9.1.49	INFORMATION EXCHANGE INITIATION REQUEST	
9.1.50	INFORMATION EXCHANGE INITIATION RESPONSE	372
9.1.51	INFORMATION EXCHANGE INITIATION FAILURE	
9.1.52	INFORMATION REPORT	
9.1.53	INFORMATION EXCHANGE TERMINATION REQUEST	
9.1.54	INFORMATION EXCHANGE FAILURE INDICATION	
9.1.55	RESET REQUEST	375
9.1.56	RESET RESPONSE	
9.1.57	RADIO LINK ACTIVATION COMMAND	
9.1.57.1	FDD Message	
9.1.57.2	TDD Message	
9.1.58	RADIO LINK PARAMETER UPDATE INDICATION	
9.1.58.1	FDD Message	
9.1.58.2	TDD Message	
9.1.59	UE MEASUREMENT INITIATION REQUEST [TDD]	
9.1.60	UE MEASUREMENT INITIATION RESPONSE [TDD]	
9.1.61	UE MEASUREMENT INITIATION FAILURE [TDD]	
9.1.62	UE MEASUREMENT REPORT [TDD]	
9.1.63	UE MEASUREMENT TERMINATION REQUEST [TDD]	
9.1.64	UE MEASUREMENT FAILURE INDICATION [TDD]	
9.1.65	IUR INVOKE TRACE	
9.1.66	IUR DEACTIVATE TRACE	
9.1.67	MBMS ATTACH COMMAND	
9.1.68	MBMS DETACH COMMAND	
9.1.69	DIRECT INFORMATION TRANSFER	
9.1.70	ENHANCED RELOCATION REQUEST	
9.1.71	ENHANCED RELOCATION RESPONSE	
9.1.72	ENHANCED RELOCATION GANGEL	
9.1.73	ENHANCED RELOCATION CANCEL	
9.1.74	ENHANCED RELOCATION SIGNALLING TRANSFERENHANCED RELOCATION RELEASE	
9.1.75 9.1.76	MBSFN MCCH INFORMATION (FDD)	
9.1.76	SECONDARY UL FREQUENCY REPORT	
9.1.77		
9.1.77.1	FDD MessageSECONDARY UL FREQUENCY UPDATE INDICATION	205
9.1.78	FDD Message	
9.1.79	ENHANCED RELOCATION RESOURCE REQUEST [TDD]	
9.1.79	ENHANCED RELOCATION RESOURCE RESPONSE [TDD]	385
9.1.81	ENHANCED RELOCATION RESOURCE FAILURE [TDD]	
9.1.82	ENHANCED RELOCATION RESOURCE RELEASE COMMAND [TDD]	
9.1.83	ENHANCED RELOCATION RESOURCE RELEASE COMPLETE [TDD]	
9.1.84	INFORMATION TRANSFER CONTROL REQUEST	
9.2	Information Element Functional Definition and Contents	
9.2.0	General	
9.2.1	Common Parameters	
9.2.1.1	Allocation/Retention Priority	
9.2.1.2	Allowed Queuing Time	
9.2.1.2A	Allowed Rate Information	
9.2.1.2B	Altitude and Direction	
9.2.1.2C	Antenna Co-location Indicator	388
9.2.1.2D	Alternative Format Reporting Indicator	388
9.2.1.3	Binding ID	389
9.2.1.4	BLER	
9.2.1.4A	Block STTD Indicator	
9.2.1.4B	Burst Mode Parameters	
9.2.1.5	Cause	
9.2.1.5A	Cell Geographical Area Identity (Cell GAI)	395

9.2.1.5B	Cell Geographical Area Additional Shapes (Cell GAI Additional Shapes)	
9.2.1.5C	Cell Capacity Class Value	
9.2.1.5D	Cell Global Identifier (CGI)	
9.2.1.6	Cell Identifier (C-ID)	
9.2.1.7	Cell Individual Offset	
9.2.1.8	Cell Parameter ID	
9.2.1.9	CFN	
9.2.1.10	CFN Offset	
9.2.1.11	CN CS Domain Identifier	
9.2.1.11A	CN Domain Type	399
9.2.1.12	CN PS Domain Identifier	399
9.2.1.12A	Common Measurement Accuracy	
9.2.1.12B	Common Measurement Object Type	400
9.2.1.12C	Common Measurement Type	400
9.2.1.12D	Common Measurement Value	
9.2.1.12E	Common Measurement Value Information	401
9.2.1.12F	Common Transport Channel Resources Initialisation Not Required	402
9.2.1.12G	Coverage Indicator	402
9.2.1.13	Criticality Diagnostics	402
9.2.1.14	C-RNTI	404
9.2.1.14A	CTFC	404
9.2.1.15	DCH Combination Indicator	
9.2.1.16	DCH ID	
9.2.1.16A	DCH Information Response	
9.2.1.17	Dedicated Measurement Object Type	
9.2.1.18	Dedicated Measurement Type	
9.2.1.19	Dedicated Measurement Value	
9.2.1.19A	Dedicated Measurement Value Information	
9.2.1.19Aa	Delayed Activation	
9.2.1.19Ab	Delayed Activation Update	
9.2.1.19R0	DGPS Corrections	
9.2.1.19C	Discard Timer	
9.2.1.20	Diversity Control Field	
9.2.1.21	Diversity Indication.	
9.2.1.21A	DL Power	
9.2.1.21	Downlink SIR Target	
9.2.1.23	DPCH Constant Value	
9.2.1.24	D-RNTI	
9.2.1.25	D-RNTI Release Indication	
9.2.1.26	DRX Cycle Length Coefficient.	
9.2.1.26A	DSCH ID	
9.2.1.26Aa	DSCH Initial Window Size	
9.2.1.26Aa 9.2.1.26B	DSCH Flow Control Information.	
9.2.1.26Ba		
	DSCH-RNTI Extended GSM Cell Individual Offset	
9.2.1.26Bb	FACH Flow Control Information	
9.2.1.26C	FACH Initial Window Size	
9.2.1.27		
9.2.1.28	FACH Priority Indicator	
9.2.1.28A	FN Reporting Indicator	
9.2.1.29	Frame Handling Priority	
9.2.1.30	Frame Offset	
9.2.1.30A	GA Point with Uncertainty	
9.2.1.30B	GA Ellipsoid Point with Uncertainty Ellipse	
9.2.1.30C	GA Ellipsoid Point with Altitude	
9.2.1.30D	GA Ellipsoid Point with Altitude and Uncertainty Ellipsoid	
9.2.1.30E	GA Ellipsoid Arc	
9.2.1.30F	Geographical Coordinates	
9.2.1.30Fa	GERAN Cell Capability	
9.2.1.30Fb	GERAN Classmark	
9.2.1.30Fc	GERAN System Information	
9.2.1.30G	GPS Almanac	
9.2.1.30H	GPS Ionospheric Model	418

9.2.1.30I	GPS Navigation Model and Time Recovery	418
9.2.1.30J	GPS Real-Time Integrity	419
9.2.1.30K	GPS Receiver Geographical Position (GPS RX Pos)	420
9.2.1.30L	GPS UTC Model	
9.2.1.30M	Guaranteed Rate Information	
9.2.1.30N	HCS Prio	
9.2.1.30NA	HS-DSCH Information To Modify Unsynchronised	
9.2.1.30Na	HS-DSCH Initial Capacity Allocation	
9.2.1.30Nb	HS-DSCH Initial Window Size	
9.2.1.300	HS-DSCH MAC-d Flow ID	
9.2.1.30OA	HS-DSCH MAC-d Flows Information	
9.2.1.30OB	HS-DSCH MAC-d Flows To Delete	
9.2.1.30OC	HS-DSCH MAC-d PDU Size Format	
9.2.1.30Oa	HS-DSCH Physical Layer Category	
9.2.1.30P	HS-DSCH-RNTI	
9.2.1.30Q	HS-DSCH Information To Modify	
9.2.1.30R	HS-SCCH Code Change Indicator	
9.2.1.30S	HS-SCCH Code Change Grant	
9.2.1.30T	IMEI	
9.2.1.30U	IMEISV	
9.2.1.30V	HS-PDSCH Code Change Indicator [FDD]	
9.2.1.30W	HS-PDSCH Code Change Grant [FDD]	
9.2.1.31	IMSI	
9.2.1.31A	Information Exchange ID.	
9.2.1.31B	Information Exchange Object Type	
9.2.1.31C	Information Report Characteristics	
9.2.1.31D	Information Threshold	
9.2.1.31E	Information Type	
9.2.1.31F	IPDL Parameters	
9.2.1.31G	Inter-frequency Cell Information	
9.2.1.32	L3 Information	
9.2.1.33	Limited Power Increase	
9.2.1.33A	Load Value	
9.2.1.34	MAC-c/sh SDU Length	
9.2.1.34A	MAC-d PDU Size	
9.2.1.34Aa	MAC-hs Guaranteed Bit Rate	
9.2.1.34Ab	MAC-hs Reordering Buffer Size for RLC-UM.	
9.2.1.34B	MAC-hs Reset Indicator	
9.2.1.34C	MAC-hs Window Size	
9.2.1.34D	MAC PDU Size Extended	
9.2.1.35	Maximum Allowed UL Tx Power	
9.2.1.35A	Measurement Availability Indicator	
9.2.1.35B	Measurement Change Time	
9.2.1.36	Measurement Filter Coefficient	
9.2.1.36A	Measurement Hysteresis Time	
9.2.1.37	Measurement ID	
9.2.1.37	Measurement Increase/Decrease Threshold	
9.2.1.38A	Measurement Recovery Behavior	
9.2.1.38B	Measurement Recovery Reporting Indicator	
9.2.1.38D 9.2.1.38C	Measurement Recovery Support Indicator	
9.2.1.39	Measurement Threshold	
9.2.1.39 9.2.1.39A	Message Structure	
9.2.1.39A 9.2.1.40	Message Type	
9.2.1.40	Multiple URAs Indicator	
9.2.1.41 9.2.1.41a	NACC Related Data	
9.2.1.41a 9.2.1.41A	Neighbouring UMTS Cell Information	
9.2.1.41A 9.2.1.41B		
9.2.1.41B 9.2.1.41C	Neighbouring FDD Cell Information	
9.2.1.41C 9.2.1.41D	Neighbouring GSM Cell Information	
	Neighbouring TDD Cell Information	
9.2.1.41Dd	Neighbouring F LITPA Call Information LCR	
9.2.1.41De	Neighbouring E-UTRA Cell Information	433 157

9.2.1.41E	Paging Cause	
9.2.1.41F	Paging Record Type	458
9.2.1.41Fa	Partial Reporting Indicator	
9.2.1.41G	Neighbouring FDD Cell Measurement Information	458
9.2.1.41H	Neighbouring TDD Cell Measurement Information	
9.2.1.41I	NRT Load Information Value	
9.2.1.42	Payload CRC Present Indicator	
9.2.1.43	PCCPCH Power	
9.2.1.44	Primary CPICH Power	
9.2.1.45	Primary Scrambling Code	
9.2.1.45A	Priority Queue ID	
9.2.1.45B	Process Memory Size	
9.2.1.46	Puncture Limit	
9.2.1.46A	QE-Selector	
9.2.1.47	RANAP Relocation Information	
9.2.1.48	Report Characteristics	
9.2.1.48a	Report Periodicity	
9.2.1.48A	Requested Data Value	
9.2.1.48B	Requested Data Value Information	
9.2.1.48C 9.2.1.48D	Restriction State Indicator	
9.2.1.48D 9.2.1.49	RL ID	
9.2.1.49 9.2.1.49A	RL Specific DCH Information	
9.2.1.49A 9.2.1.50	RNC-ID	
9.2.1.50a	Extended RNC-ID	
9.2.1.50a 9.2.1.50A	SAT ID	
9.2.1.50B	RT Load Value	
9.2.1.50 D	SCH Time Slot	
9.2.1.51A	Scheduling Priority Indicator	
9.2.1.52	Service Area Identifier (SAI)	
9.2.1.52A	SFN	
9.2.1.52B	SFN-SFN Measurement Threshold Information	
9.2.1.52C	SFN-SFN Measurement Value Information	468
9.2.1.52Ca	Shared Network Area (SNA) Information	469
9.2.1.52D	SID	470
9.2.1.53	S-RNTI	
9.2.1.53a	S-RNTI Group	
9.2.1.54	Sync Case	
9.2.1.54A	T1	
9.2.1.55	TFCI Presence	
9.2.1.56	Time Slot	
9.2.1.56A	TNL QoS	
9.2.1.57	ToAWE	
9.2.1.58	ToAWS	
9.2.1.58a 9.2.1.58b	Trace Depth	
9.2.1.58c	Trace Recording Session Reference Trace Reference	
9.2.1.58A	Traffic Class	
9.2.1.50A 9.2.1.59	Transaction ID	
9.2.1.59A	Transmitted Carrier Power	
9.2.1.59B	T _{UTRAN-GPS} Accuracy Class	
9.2.1.59C	T _{UTRAN-GPS} Measurement Threshold Information	
9.2.1.59D	T _{UTRAN-GPS} Measurement Value Information	
9.2.1.60	Transport Bearer ID	
9.2.1.61	Transport Bearer Request Indicator	
9.2.1.62	Transport Layer Address	476
9.2.1.63	Transport Format Combination Set (TFCS)	476
9.2.1.64	Transport Format Set	477
9.2.1.65	TrCH Source Statistics Descriptor	
9.2.1.66	UARFCN	
9.2.1.66A	UE Identity	
9 2 1 67	III FP Mode	170

9.2.1.68	UL Interference Level	
9.2.1.68A	Uncertainty Ellipse	480
9.2.1.68B	Unidirectional DCH Indicator	
9.2.1.69	Uplink SIR	480
9.2.1.70	URA ID	
9.2.1.70A	UTRAN Access Point Position	480
9.2.1.70B	URA Information	481
9.2.1.70C	User Plane Congestion Fields Inclusion	481
9.2.1.71	UTRAN Cell Identifier (UC-ID)	482
9.2.1.72	Neighbouring TDD Cell Information LCR	482
9.2.1.73	Permanent NAS UE Identity	
9.2.1.74	SFN-SFN Measurement Reference Point Position	483
9.2.1.75	UTRAN Access Point Position with Altitude	
9.2.1.76	SFN-SFN Measurement Time Stamp	483
9.2.1.77	SFN-SFN Value	
9.2.1.78	SCTD Indicator	484
9.2.1.79	Congestion Cause	484
9.2.1.80	TMGI	484
9.2.1.81	Transmission Mode	485
9.2.1.82	Access Point Name	485
9.2.1.83	IP Multicast Address	
9.2.1.84	MBMS Bearer Service Full Address	486
9.2.1.85	Provided Information	486
9.2.1.86	MBMS Channel Type Information	486
9.2.1.87	MBMS Preferred Frequency Layer Information	
9.2.1.88	E-DCH DDI Value	487
9.2.1.89	E-DCH MAC-d Flow Multiplexing List	
9.2.1.90	E-DCH MAC-d Flows To Delete	488
9.2.1.91	E-DCH MAC-d Flow ID	488
9.2.1.91A	E-DCH MAC-d PDU Size Format	488
9.2.1.92	E-DCH Logical Channel Information	489
9.2.1.93	E-DCH Logical Channel To Modify	490
9.2.1.94	E-RNTI	490
9.2.1.95	E-DCH Processing Overload Level	
9.2.1.96	E-DCH Power Offset for Scheduling Info	491
9.2.1.97	Logical channel ID	
9.2.1.98	MAC-es Guaranteed Bit Rate	
9.2.1.99	MAC-e Reset Indicator	491
9.2.1.100	Maximum Number of Retransmissions for E-DCH	
9.2.1.101	Scheduling Information	492
9.2.1.102	DGANSS Corrections	492
9.2.1.103	GANSS Almanac	494
9.2.1.104	GANSS Clock Model	
9.2.1.104a	GANSS Additional Clock Models	498
9.2.1.105	GANSS Ionospheric Model	
9.2.1.105a	GANSS Additional Ionospheric Model	501
9.2.1.106	GANSS Navigation Model	501
9.2.1.107	GANSS Orbit Model	
9.2.1.107a	GANSS Additional Orbit Models	502
9.2.1.108	GANSS Real Time Integrity	506
9.2.1.109	GANSS Receiver Geographical Position (GANSS RX Pos)	507
9.2.1.110	GANSS Time Model	507
9.2.1.110a	GANSS Additional Time Models	508
9.2.1.111	GANSS UTC Model	
9.2.1.111a	GANSS Additional UTC Models	
9.2.1.112	T _{UTRAN-GANSS} Accuracy Class	
9.2.1.113	T _{UTRAN-GANSS} Measurement Threshold Information	
9.2.1.114	T _{UTRAN-GANSS} Measurement Value Information	
9.2.1.115	GANSS Reference Time	513
9.2.1.116	HARQ Memory Partitioning	514
9.2.1.117	Multiple PLMN List	515
9.2.1.118	GANSS Data Bit Assistance	515

9.2.1.119	GANSS ID	
9.2.1.119a	GANSS Time ID	
9.2.1.120	GANSS Navigation Model And Time Recovery	
9.2.1.120a	GANSS Additional Navigation Models And Time Recovery	
9.2.1.121	GANSS Signal ID	518
9.2.1.122	GANSS Transmission Time	
9.2.1.122a	GANSS Earth Orientation Parameters	518
9.2.1.122b	SBAS ID	
9.2.1.122c	GANSS Auxiliary Information	519
9.2.1.122d	Additional Ionospheric Model Request	520
9.2.1.122e	Earth Orientation Parameters Request	
9.2.1.122f	GANSS Additional Navigation Models And Time Recovery Request	520
9.2.1.122g	GANSS Additional UTC Models Request	
9.2.1.122h	GANSS Auxiliary Information Request	521
9.2.1.123	SixtyfourQAM DL Support Indicator	521
9.2.1.124	RANAP Enhanced Relocation Information Request	521
9.2.1.125	RANAP Enhanced Relocation Information Response	521
9.2.1.126	Released CN Domain	
9.2.1.127	Secondary CCPCH system information MBMS	
9.2.1.128	MBSFN Cluster Identity	522
9.2.1.129	MBSFN Scheduling Transmission Time Interval	
9.2.1.130	MAC-ehs Reset Timer	522
9.2.1.131	Enhanced FACH Support Indicator	522
9.2.1.132	Enhanced PCH Capability	523
9.2.1.133	Priority Queue Information for Enhanced FACH/PCH	
9.2.1.134	MIMO Activation Indicator	523
9.2.1.135	MIMO Mode Indicator	523
9.2.1.136	DL RLC PDU Size Format	523
9.2.1.137	UE Aggregate Maximum Bit Rate	524
9.2.1.138	DGNSS Validity Period	524
9.2.1.139	MDT Configuration	525
9.2.1.140	MDT Report parameters	527
9.2.1.141	Neighbouring UMTS Cell Information Extension	527
9.2.1.142	Source ID	
9.2.1.143	Target ID	528
9.2.1.144	MS Classmark 2	
9.2.1.145	MS Classmark 3	
9.2.1.146	Speech Version	529
9.2.1.147	Controlled Object Scope	
9.2.1.148	ANR Report Indication	
9.2.1.149	ANR Cell Information.	530
9.2.1.150	ANR FDD Cell Information	530
9.2.1.151	ANR TDD Cell Information	
9.2.1.152	ANR TDD Cell Information LCR	531
9.2.1.153	ANR Multiple PLMN List	532
9.2.2	FDD Specific Parameters	
9.2.2.a	ACK-NACK Repetition Factor	532
9.2.2.b	ACK Power Offset	
9.2.2.A	Active Pattern Sequence Information	
9.2.2.B	Adjustment Period	
9.2.2.C	Adjustment Ratio	
9.2.2.Ca	Bundling Mode Indicator	
9.2.2.D	Cell Capability Container FDD	
9.2.2.E	Cell Portion ID	
9.2.2.1	Chip Offset	
9.2.2.2	Closed Loop Mode1 Support Indicator	
9.2.2.3	Closed Loop Mode2 Support Indicator	
9.2.2.3A	Closed Loop Timing Adjustment Mode	
9.2.2.4	Compressed Mode Method	
9.2.2.4A	DCH FDD Information	
9.2.2.4B	E-DCH FDD Information	
9.2.2.4C	E-DCH FDD Information Response	539

9.2.2.4D	E-DCH FDD DL Control Channel Information	540
9.2.2.4E	E-DCH RL Indication	542
9.2.2.4F	E-DCH FDD Information To Modify	
9.2.2.4G	E-DCH Transport Format Combination Set Information (E-TFCS Information)	
9.2.2.4J	E-TTI	
9.2.2.4K	E-DPCCH Power Offset	
9.2.2.4KA	Void	
9.2.2.4L	E-DCH HARQ Power Offset FDD	
9.2.2.4M	Void	
9.2.2.4MA	Void	
9.2.2.4MB	Void	
9.2.2.4MC	E-DCH MAC-d Flows Information	
9.2.2.4MD	Void	
9.2.2.4ME	Void	
9.2.2.4MF	Void	
9.2.2.4MG	E-DCH Maximum Bitrate	
9.2.2.4MH	Void	
9.2.2.4MI	E-DCH Reference Power Offset	
9.2.2.4MJ	Void	
9.2.2.4N	Maximum Number of Bits per MAC-e PDU for Non-scheduled Transmission	
9.2.2.40	HARQ Process Allocation For 2ms TTI	
9.2.2.4P	Reference E-TFCI Power Offset	
9.2.2.4Q	Extended Reference E-TFCI Power Offset	
9.2.2.4R	Extended Maximum Number of Bits per MAC-e PDU for Non-scheduled Transmission	
9.2.2.4S	Transport Bearer Not Requested Indicator	
9.2.2.4T	Transport Bearer Not Setup Indicator	
9.2.2.5	D-Field Length	
9.2.2.6	Diversity Control Field	
9.2.2.7	Diversity Indication	
9.2.2.8	Diversity Mode	
9.2.2.9	DL DPCH Slot Format	
9.2.2.9A	DL DPCH Timing Adjustment	
9.2.2.10	DL Power	
9.2.2.10A	DL Power Balancing Information	
9.2.2.10B	DL Power Balancing Activation Indicator	
9.2.2.10C	DL Reference Power Information	553
9.2.2.10D	DL Power Balancing Updated Indicator	554
9.2.2.11	DL Scrambling Code	554
9.2.2.12	Downlink Frame Type	554
9.2.2.12A	DPC Mode	554
9.2.2.13	DRAC Control	554
9.2.2.13A	DSCH FDD Information	
9.2.2.13B	DSCH FDD Information Response	
9.2.2.13Bb	DSCH-RNTI	
9.2.2.13C	FDD DCHs To Modify	555
9.2.2.13D	Enhanced DSCH PC	
9.2.2.13E	Enhanced DSCH PC Counter	
9.2.2.13F	Enhanced DSCH PC Indicator	
9.2.2.13G	Enhanced DSCH PC Wnd	555
9.2.2.13H	Enhanced DSCH Power Offset	
9.2.2.13I	Enhanced Primary CPICH Ec/No	
9.2.2.14	FDD DL Channelisation Code Number	
9.2.2.14A	FDD DL Code Information	
9.2.2.15	FDD S-CCPCH Offset	
9.2.2.16	FDD TPC Downlink Step Size	
9.2.2.16A	First RLS Indicator	
9.2.2.17	Gap Position Mode	
9.2.2.18	Gap Period (TGP)	
9.2.2.19	Gap Starting Slot Number (SN)	
9.2.2.19a	HS-DSCH FDD Information	
9.2.2.19aa	HS-DSCH FDD Secondary Serving Information	
9 2 2 19h	HS-DSCH FDD Information Response	560

9.2.2.19ba	HS-DSCH FDD Secondary Serving Information Response	
9.2.2.19bb	HS-DSCH FDD Secondary Serving Information To Modify	
9.2.2.19bc	HS-DSCH FDD Secondary Serving Information To Modify Unsynchronised	
9.2.2.19c	HS-DSCH FDD Update Information	564
9.2.2.19ca	HS-DSCH FDD Secondary Serving Update Information	
9.2.2.19C	HS-DSCH configured indicator	
9.2.2.19d	HS-SCCH Power Offset	
9.2.2.19e	E-DCH FDD Update Information	
9.2.2.19f	HS-DSCH Serving Cell Change Information	
9.2.2.19g	HS-DSCH Serving Cell Change Information Response	
9.2.2.19ga 9.2.2.19G	HS-DSCH Secondary Serving Cell Change Information Response	
9.2.2.19G 9.2.2.19h	E-DCH Serving Cell Change Information Response	
9.2.2.1911	IB_SG_POS	
9.2.2.20	IB_SG_REP	
9.2.2.21 9.2.2.21a	Inner Loop DL PC Status	
9.2.2.21b	Initial DL DPCH Timing Adjustment Allowed	
9.2.2.21A	Limited Power Increase.	
9.2.2.21B	IPDL FDD Parameters	
9.2.2.21C	Length of TFCI2	
9.2.2.21D	Void	
9.2.2.21E	Void	
9.2.2.21F	Void	
9.2.2.22	Max Adjustment Period	
9.2.2.23	Max Adjustment Step	
9.2.2.24	Max Number of UL DPDCHs	
9.2.2.24a	CQI Feedback Cycle k	569
9.2.2.24b	CQI Power Offset	569
9.2.2.24c	CQI Repetition Factor	569
9.2.2.24d	Measurement Power Offset	
9.2.2.24e	Maximum Set of E-DPDCHs	570
9.2.2.24f	Void	
9.2.2.24A	Min DL Channelisation Code Length	
9.2.2.25	Min UL Channelisation Code Length	
9.2.2.26	Multiplexing Position	
9.2.2.26a	NACK Power Offset	
9.2.2.26A	Number of DL Channelisation Codes	
9.2.2.27	Pattern Duration (PD)	
9.2.2.27a	PC Preamble	
9.2.2.27A	PDSCH Code Mapping	
9.2.2.27B	Phase Reference Update Indicator	
9.2.2.28	Power Adjustment Type	
9.2.2.29	Power Control Mode (PCM)	
9.2.2.30	Power Offset	
9.2.2.31	Power Resume Mode (PRM)	
9.2.2.31A	Preamble Signatures	
9.2.2.32 9.2.2.32A	Primary CPICH Hoogs For Channel Estimation	
9.2.2.32A 9.2.2.33	Primary CPICH Usage For Channel Estimation Propagation Delay (PD)	
9.2.2.33 9.2.2.33a	Extended Propagation Delay.	
9.2.2.33A	PRACH Minimum Spreading Factor	
9.2.2.33A 9.2.2.34	QE-Selector	
9.2.2.34 9.2.2.34a	Qth-Selector Qth Parameter	
9.2.2.34A	RACH Sub Channel Numbers	
9.2.2.34A 9.2.2.35	RL Set ID	
9.2.2.35a	RL Sec ID	
9.2.2.35A	Received Total Wide Band Power	
9.2.2.36	S-Field Length	
9.2.2.36A	Void	
9.2.2.37	Scrambling Code Change	
9.2.2.37A	Scrambling Code Number	
9.2.2.37B	Secondary CCPCH Info	

9.2.2.38	Secondary CCPCH Slot Format	574
9.2.2.38A	Secondary CPICH Information	574
9.2.2.38B	Secondary CPICH Information Change	
9.2.2.38C	Serving E-DCH RL	575
9.2.2.39	Slot Number (SN)	
9.2.2.39a	Split Type	575
9.2.2.39A	SRB Delay	
9.2.2.40	SSDT Cell Identity	575
9.2.2.40A	SSDT Cell Identity for EDSCHPC	
9.2.2.41	SSDT Cell Identity Length	575
9.2.2.42	SSDT Indication	
9.2.2.43	SSDT Support Indicator	
9.2.2.44	STTD Indicator	
9.2.2.45	STTD Support Indicator	576
9.2.2.45A	Synchronisation Indicator	
9.2.2.46	TFCI Signalling Mode	
9.2.2.46A	TFCI PC Support Indicator	
9.2.2.47	Transmission Gap Distance (TGD)	
9.2.2.47A	Transmission Gap Pattern Sequence Information	
9.2.2.47B	Transmission Gap Pattern Sequence Scrambling Code Information	
9.2.2.48	Transmit Diversity Indicator	
9.2.2.49	Transmit Gap Length (TGL)	
9.2.2.50	Tx Diversity Indicator	
9.2.2.50A	UE Support Of Dedicated Pilots For Channel Estimation	
9.2.2.50B	UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH	
9.2.2.51	UL/DL Compressed Mode Selection	
9.2.2.52	UL DPCCH Slot Format	
9.2.2.52A	UL DPDCH Indicator for E-DCH operation	
9.2.2.53	UL Scrambling Code	
9.2.2.54	Uplink Delta SIR	
9.2.2.55	Uplink Delta SIR After	
9.2.2.56	DPC Mode Change Support Indicator	
9.2.2.57	HARQ Preamble Mode	
9.2.2.58	HARQ Preamble Mode Activation Indicator	
9.2.2.59	Frequency Band Indicator	
9.2.2.60	E-RGCH Release Indicator	
9.2.2.61	E-AGCH Power Offset	
9.2.2.61A	E-AGCH Table Choice	
9.2.2.62	E-RGCH Power Offset	
9.2.2.63	E-HICH Power Offset	
9.2.2.64	E-RGCH 2-Index-Step Threshold	
9.2.2.65	E-RGCH 3-Index-Step Threshold	
9.2.2.66	HARQ Info for E-DCH	
9.2.2.67	DCH Indicator For E-DCH-HSDPA Operation	
9.2.2.68	E-RGCH and E-HICH Channelisation Code Validity Indicator	
9.2.2.69	E-DCH Minimum Set E-TFCI Validity Indicator	
9.2.2.70	Fast Reconfiguration Mode	
9.2.2.71	Fast Reconfiguration Permission	
9.2.2.72	Continuous Packet Connectivity DTX-DRX Information	
9.2.2.73	Continuous Packet Connectivity DTX-DRX Information To Modify	
9.2.2.74	Continuous Packet Connectivity HS-SCCH less Information	
9.2.2.75	Continuous Packet Connectivity HS-SCCH less Information Response	
9.2.2.75A	Continuous Packet Connectivity HS-SCCH Less Deactivate Indicator	
9.2.2.76	MIMO Activation Indicator	
9.2.2.77	MIMO Mode Indicator.	
9.2.2.78	MIMO Information Response	
9.2.2.79	SixtyfourQAM DL Support Indicator	
9.2.2.79A	Sixtyfour QAM Usage Allowed Indicator	
9.2.2.79B	SixtyfourQAM DL Usage Indicator	
9.2.2.80	Enhanced FACH Support Indicator	
9.2.2.81	Enhanced PCH Support Indicator	
9.2.2.82	Priority Queue Information for Enhanced FACH/PCH	
	y =	

9.2.2.83	SixteenQAM UL Information	
9.2.2.84	SixteenQAM UL Information To Modify	
9.2.2.85	F-DPCH Slot Format	
9.2.2.86	F-DPCH Slot Format Support Request	589
9.2.2.87	Max UE DTX Cycle	589
9.2.2.88	Enhanced PCH Capability	589
9.2.2.89	MAC-ehs Reset Timer	590
9.2.2.90	SixteenQAM UL Operation Indicator	590
9.2.2.91	E-TFCI Boost Information	590
9.2.2.92	Common E-DCH Support Indicator	
9.2.2.93	Common E-DCH MAC-d Flow Specific Information	
9.2.2.94	Counting Information	
9.2.2.95	Transmission Mode Information	
9.2.2.96	MBMS Neighbouring Cell Information	
9.2.2.97	RLC Sequence Number	
9.2.2.98	Time Stamp	
9.2.2.99	HS-DSCH Preconfiguration Info	
9.2.2.100	HS-DSCH Preconfiguration Setup	
9.2.2.101	Secondary Serving Cell List	
9.2.2.102	Minimum Reduced E-DPDCH Gain Factor	
9.2.2.103	UE Support Indicator Extension	
9.2.2.104	Power Offset For S-CPICH for MIMO	
9.2.2.105	Power Offset For S-CPICH for MIMO Request Indicator	
9.2.2.106	Single Stream MIMO Activation Indicator	
9.2.2.107	Single Stream MIMO Mode Indicator	
9.2.2.108	HS-DSCH MAC-ehs Format	
9.2.2.109	Activation Information	
9.2.2.110	Additional E-DCH FDD Setup Information	
9.2.2.111	Additional E-DCH Configuration Change Information	
9.2.2.112	Additional E-DCH FDD Information	
9.2.2.113	Multicell E-DCH Transport Bearer Mode.	
9.2.2.114	Multicell E-DCH Information	
9.2.2.114	Additional E-DCH RL Specific Information To Setup	
9.2.2.116	Additional E-DCH RL Specific Information To Setup Additional E-DCH RL Specific Information To Add	
9.2.2.117	Additional E-DCH RL Specific Information To Modify	
9.2.2.117	Additional E-DCH MAC-d Flow Specific Information	
9.2.2.119	Multicell E-DCH RL Specific Information	
9.2.2.119	Additional E-DCH FDD Information Response	
9.2.2.120	Additional Modified E-DCH FDD Information Response	
9.2.2.121	Additional E-DCH FDD Update Information	
	•	
9.2.2.123	Cell Capability Container Extension FDD	
9.2.2.124	Non-Serving RL Preconfiguration Setup	
9.2.2.125	Non-Serving RL Preconfiguration Info	
9.2.2.126	Void	
9.2.2.127	Usefulness of Battery Optimization	
9.2.2.128	M1 Report	
9.2.2.129	Support of Dynamic DTXDRX Related HS-SCCH Order	
9.2.3	TDD Specific Parameters	
9.2.3.a	Alpha Value	
9.2.3.A	Block STTD Indicator	
9.2.3.1	Burst Type	
9.2.3.1a	Cell Capability Container TDD	
9.2.3.1b	Cell Capability Container TDD LCR	
9.2.3.2	CCTrCH ID.	
9.2.3.2A	DCH TDD Information	
9.2.3.2B	DCH TDD Information Response	
9.2.3.2C	DL Timeslot Information	
9.2.3.2D	DL Time Slot ISCP Info	
9.2.3.2E	DL Timeslot Information LCR	
9.2.3.2F	DL Time Slot ISCP Info LCR	
9.2.3.3	DPCH ID	
9.2.3.3a	DSCH TDD Information	615

9.2.3.3aa	HS-DSCH TDD Information	616
9.2.3.3ab	HS-DSCH TDD Information Response	618
9.2.3.3ac	HS-DSCH TDD Update Information	622
9.2.3.3ad	HS-SICH ID	622
9.2.3.3ae	DSCH ID	622
9.2.3.3af	DSCH Initial Window Size	622
9.2.3.3ag	DSCH Flow Control Information	623
9.2.3.3ah	DSCH-RNTI	623
9.2.3.3ai	TSN-Length	623
9.2.3.3A	Maximum Number of Timeslots	623
9.2.3.3B	Maximum Number of UL Physical Channels per Timeslot	624
9.2.3.3C	Maximum Number of DL Physical Channels	
9.2.3.3D	Maximum Number of DL Physical Channels per Timeslot	624
9.2.3.4	Midamble Shift And Burst Type	624
9.2.3.4A	Minimum Spreading Factor	625
9.2.3.4B	IPDL TDD parameters	
9.2.3.4Bb	IPDL TDD parameters LCR	
9.2.3.4C	Midamble shift LCR	
9.2.3.4D	Neighbouring TDD Cell Information LCR	627
9.2.3.5	Primary CCPCH RSCP	627
9.2.3.5a	Primary CCPCH RSCP Delta	627
9.2.3.5A	PRACH Midamble	627
9.2.3.5B	RB Identity	627
9.2.3.6	Repetition Length	627
9.2.3.7	Repetition Period	628
9.2.3.7A	Rx Timing Deviation	628
9.2.3.7B	Secondary CCPCH Info TDD	628
9.2.3.7C	Secondary CCPCH TDD Code Information	
9.2.3.7D	Special Burst Scheduling	
9.2.3.7E	Synchronisation Configuration	629
9.2.3.7F	Secondary CCPCH Info TDD LCR	
9.2.3.7G	Secondary CCPCH TDD Code Information LCR	
9.2.3.7H	Support of 8PSK	
9.2.3.7I	TDD ACK NACK Power Offset	
9.2.3.8	TDD Channelisation Code	
9.2.3.8a	TDD Channelisation Code LCR	
9.2.3.8A	TDD DPCH Offset	
9.2.3.8B	TDD DCHs To Modify	
9.2.3.8C	TDD DL Code Information	
9.2.3.8D	TDD DL Code Information LCR	
9.2.3.8E	TDD DL DPCH Time Slot Format LCR	
9.2.3.9	TDD Physical Channel Offset	
9.2.3.10	TDD TPC Downlink Step Size	
9.2.3.10a	TDD TPC Uplink Step Size	
9.2.3.10A	TDD UL Code Information	
9.2.3.10B	TDD UL Code Information LCR	
9.2.3.10C	TDD UL DPCH Time Slot Format LCR	
9.2.3.10D	1.28 Mcps TDD uplink physical channel capability	
9.2.3.11	TFCI Coding	
9.2.3.12	DL Timeslot ISCP	
9.2.3.12a	Time Slot LCR	
9.2.3.12A	Timing Advance Applied	
9.2.3.13	Transport Format Management	
9.2.3.13A	UL Timeslot ISCP	
9.2.3.13B	UL PhysCH SF Variation	
9.2.3.13C	UL Time Slot ISCR Info	
9.2.3.13D	UL Time Slot ISCP Info	
9.2.3.13E	TSTD Support Indicator	
9.2.3.13F	TSTD Support Indicator	
9.2.3.13Fa	UE Measurement Hysteresis Time	
9.2.3.13Fb	UE Measurement Parameter Modification Allowed	

9.2.3.13Fd	UE Measurement Threshold	
9.2.3.13Fe	UE Measurement Timeslot Information HCR	
9.2.3.13Ff	UE Measurement Timeslot Information LCR	
9.2.3.13Fg	UE Measurement Time to Trigger	
9.2.3.13Fh	UE Measurement Type	
9.2.3.13Fi	UE Measurement Value	
9.2.3.13Fj	UE Measurement Value Information	
9.2.3.13G	UL Timeslot Information LCR	
9.2.3.13H	UL Time Slot ISCP Info LCR	
9.2.3.13I	Uplink Synchronisation Frequency	
9.2.3.13J	Uplink Synchronisation Step Size	
9.2.3.13K	Uplink Timing Advance Control LCR	
9.2.3.13L	USCH ID	
9.2.3.14	USCH Information	
9.2.3.16	Support of PLCCH	
9.2.3.17	PLCCH Information	
9.2.3.18	PLCCH Sequence Number	
9.2.3.19	Minimum Spreading Factor 7.68Mcps	
9.2.3.20	Maximum Number of DL Physical Channels 7.68Mcps	
9.2.3.21	Maximum Number of DL Physical Channels per Timeslot 7.68Mcps	
9.2.3.22	Secondary CCPCH Info 7.68Mcps TDD	
9.2.3.23	Midamble Shift And Burst Type 7.68Mcps	
9.2.3.24	Secondary CCPCH TDD Code Information 7.68Mcps	647
9.2.3.25	TDD Channelisation Code 7.68Mcps	
9.2.3.26	UL Timeslot Information 7.68Mcps	
9.2.3.27	TDD UL Code Information 7.68Mcps	
9.2.3.28	DL Timeslot Information 7.68Mcps	
9.2.3.29	TDD DL Code Information 7.68Mcps	
9.2.3.30	Rx Timing Deviation 7.68Mcps	
9.2.3.31	Cell Capability Container 7.68 Mcps TDD	
9.2.3.32	Neighbouring TDD Cell Measurement Information 7.68Mcps	
9.2.3.33	UE Measurement Timeslot Information 7.68Mcps	
9.2.3.34	DPCH ID 7.68Mcps	
9.2.3.35	Rx Timing Deviation 3.84Mcps Extended	
9.2.3.36	E-PUCH Information	
9.2.3.36a	E-PUCH Information LCR	
9.2.3.37	E-TFCS Information TDD	
9.2.3.38	E-DCH MAC-d Flows Information TDD E-DCH Non-scheduled Grant Information TDD	
9.2.3.39 9.2.3.39a	E-DCH Non-scheduled Grant Information LCR TDD	
9.2.3.40 9.2.3.40a	E-DCH TDD Information E-DCH TDD Information LCR	
9.2.3.40a 9.2.3.41	E-DCH TDD Information ICR. E-DCH TDD Information Response	
9.2.3.41 9.2.3.41a	E-DCH TDD Information Response 1.28Mcps	
9.2.3.41a	E-DCH TDD Information to Modify	
9.2.3.42	E-DCH Grant Type	
9.2.3.44	Timeslot Resource Related Information.	
9.2.3.44a	Timeslot Resource Related Information LCR.	
9.2.3.44	Power Resource Related Information.	
9.2.3.46	E-PUCH Offset	
9.2.3.47	E-DCH TDD Maximum Bitrate	
9.2.3.47	E-HICH Time Offset	
9.2.3.48a	E-HICH Time Offset LCR	
9.2.3.49	E-DCH HARQ Power Offset TDD.	
9.2.3.49a	E-DCH MAC-d Flow Retransmission Timer	
9.2.3.49a	E-DCH Non-scheduled Grant Information 7.68Mcps TDD	
9.2.3.50	E-DCH TDD Information 7.68Mcps	
9.2.3.51	E-DCH TDD Information 7.06Weps	
9.2.3.53	E-DCH TDD Maximum Bitrate 7.68Mcps	
9.2.3.54	E-DCH Physical Layer Category LCR	
9.2.3.54A	Extended E-DCH Physical layer Category LCR	
9.2.3.54B	Multi-Carrier E-DCH Physical Layer Category LCR	663

9.2.3.55	UpPCH Information LCR	
9.2.3.56	UpPCH Position LCR	
9.2.3.57	Common E-DCH MAC-d Flow ID	
9.2.3.58	Common E-DCH MAC-d Flow Specific Information LCR	
9.2.3.59	MAC-es Maximum Bit Rate LCR	
9.2.3.60 9.2.3.61	Idle Interval Information Continuous Packet Connectivity DRX Information LCR	
9.2.3.61	Continuous Packet Connectivity DRX Information To Modify LCR	
9.2.3.62	Continuous Packet Connectivity DRX Information Response LCR	
9.2.3.64	HS-DSCH Semi-Persistent scheduling Information LCR	
9.2.3.65	HS-DSCH Semi-Persistent scheduling Information to modify LCR	668
9.2.3.66	E-DCH Semi-Persistent scheduling Information LCR.	
9.2.3.67	E-DCH Semi-Persistent scheduling Information to modify LCR	
9.2.3.68	HS-DSCH Semi-Persistent scheduling Information Response LCR	
9.2.3.69	E-DCH Semi-Persistent scheduling Information Response LCR	
9.2.3.70	HS-DSCH Semi-Persistent scheduling Deactivate Indicator LCR	
9.2.3.71	E-DCH Semi-Persistent scheduling Deactivate Indicator LCR	673
9.2.3.72	HS-SICH Reference Signal Information	
9.2.3.73	Cell Portion LCR ID	
9.2.3.74	TS0 HS-PDSCH Indication LCR	
9.2.3.75	DCH Measurement Occasion Information	
9.2.3.76	DCH Measurement Type Indicator	
9.2.3.77	Multi-Carrier E-DCH Information LCR	
9.2.3.78	Multi-Carrier E-DCH Information Response LCR	
9.2.3.79	Multi-Carrier E-DCH Transport Bearer Mode LCR	
9.2.3.80	Cell Capability Container Extension TDD LCR	
9.2.3.81 9.2.3.82	MU-MIMO Information	
9.2.3.82	M2 Report	
9.2.3.84	UE RF Band Capability LCR	
9.3	Message and Information Element Abstract Syntax (with ASN.1)	
9.3.0	General	
9.3.1	Usage of Private Message Mechanism for Non-standard Use	
9.3.2	Elementary Procedure Definitions	
9.3.3	PDU Definitions	
9.3.4	Information Element Definitions	865
9.3.5	Common Definitions	1066
9.3.6	Constant Definitions	
9.3.7	Container Definitions	
9.4	Message Transfer Syntax	
9.5	Timers	1090
10 H	andling of Unknown, Unforeseen and Erroneous Protocol Data	1090
10.1	General	
10.2	Transfer Syntax Error	
10.3	Abstract Syntax Error	
10.3.1	General	
10.3.2	Criticality Information	1091
10.3.3	Presence Information	1092
10.3.4	Not Comprehended IE/IE Group	
10.3.4.1	Procedure ID	
10.3.4.1 <i>A</i>		
10.3.4.2	IEs Other Than the Procedure ID and Type of Message	
10.3.5	Missing IE or IE Group	
10.3.6	IEs or IE Groups Received in Wrong Order or With Too Many Occurrences or Erroneously P.	
10.4	Logical Error	
10.5	Exceptions	1096
Annex A	A (normative): Allocation and Pre-emption of Radio Links in the DRNS	1097
	eriving Allocation Information for a Radio Link	
A.1.1 A.1.2	Establishment of a New Radio Link	
A. L. /.	INIQUID CAUCH OF AN EXISTING NATIO FILE	

A.2	Deriving Retention Information for a Radio Link	1098
A.3	The Allocation/Retention Process	1098
A.4	The Pre-emption Process	1099
Anne	ex B (informative): Measurement Reporting	1100
Anne	ex C (informative): Guidelines for Usage of the Criticality Diagnostics IE	1105
C.1	EXAMPLE MESSAGE Layout	1105
C.2	Example on a Received EXAMPLE MESSAGE	1106
C.3 C.3.1 C.3.2 C.3.3 C.3.4 C.3.5	Example 2 Example 3 Example 4	1107 1108 1109
C.4	ASN.1 of EXAMPLE MESSAGE	1111
Anne	ex D (normative): DRNS Behaviour at SRNC or RNSAP Signalling Bearer Failure	1114
D.1 D.1.1 D.1.2		1114
D.2	DRNC Actions at UE Context Termination	1114
Anne	ex E (informative): Change History	1115
Histo		1117

Foreword

This Technical Specification (TS) has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- Y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

1 Scope

The present document specifies the radio network layer signalling procedures of the control plane between RNCs in UTRAN, between RNC in UTRAN and BSS in GERAN Iu mode and between BSSs in GERAN Iu mode.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.
- [1] 3GPP TS 23.003: "Numbering, addressing and identification". [2] 3GPP TS 25.413: "UTRAN Iu Interface RANAP Signalling". 3GPP TS 25.426: "UTRAN Iur and Iub Interface Data Transport & Transport Layer Signalling for [3] DCH Data Streams". [4] 3GPP TS 25.427: "UTRAN Iur and Iub Interface User Plane Protocols for DCH Data Streams". [5] 3GPP TS 25.435: "UTRAN Iub interface User Plane Protocols for Common Transport Channel Data Streams". [6] 3GPP TS 25.104: "UTRA (BS) FDD; Radio transmission and Reception". 3GPP TS 25.105: "UTRA (BS) TDD; Radio Transmission and Reception". [7] [8] 3GPP TS 25.211: "Physical Channels and Mapping of Transport Channels onto Physical Channels (FDD)". 3GPP TS 25.212: "Multiplexing and Channel Coding (FDD)". [9] [10] 3GPP TS 25.214: "Physical Layer Procedures (FDD)". 3GPP TS 25.215: "Physical Layer – Measurements (FDD)". [11] [12] 3GPP TS 25.221: "Physical Channels and Mapping of Transport Channels onto Physical Channels (TDD)". 3GPP TS 25.223: "Spreading and Modulation (TDD)". [13] 3GPP TS 25.225: "Physical Layer - Measurements (TDD)". [14] 3GPP TS 25.304: "UE Procedures in Idle Mode" [15] [16] 3GPP TS 25.331: "RRC Protocol Specification". 3GPP TS 25.402: "Synchronisation in UTRAN, Stage 2". [17] ITU-T Recommendation X.680 (2002-07): "Information technology – Abstract Syntax Notation [18] One (ASN.1): Specification of basic notation". [19] ITU-T Recommendation X.681 (2002-07): "Information technology – Abstract Syntax Notation

One (ASN.1): Information object specification".

[20]	ITU-T Recommendation X.691 (2002-07): "Information technology – ASN.1 encoding rules – Specification of Packed Encoding Rules (PER)".
[21]	3GPP TS 25.213: "Spreading and modulation (FDD)".
[22]	3GPP TS 25.224: "Physical Layer Procedures (TDD)".
[23]	3GPP TS 25.133: "Requirements for support of Radio Resource management (FDD)".
[24]	3GPP TS 25.123: "Requirements for support of Radio Resource management (TDD)".
[25]	3GPP TS 23.032: "Universal Graphical Area Description (GAD)".
[26]	3GPP TS 25.302: "Services Provided by the Physical Layer".
[27]	3GPP TS 25.213: "Spreading and modulation (FDD)".
[28]	3GPP TR 25.921 (version.7.0.0): "Guidelines and Principles for Protocol Description and Error Handling".
[29]	Void
[30]	ICD-GPS-200: "Navstar GPS Space Segment/Navigation User Interface".
[31]	RTCM-SC104: "RTCM Recommended Standards for Differential GNSS Service (v.2.2)".
[32]	3GPP TS 25.425: "UTRAN Iur and Iub Interface User Plane Protocols for Common Transport Channel data streams".
[33]	IETF RFC 2460 (1998-12): "Internet Protocol, Version 6 (Ipv6) Specification".
[34]	IETF RFC 768 (1980-08): "User Datagram Protocol".
[35]	3GPP TS 25.424: "UTRAN Iur Interface Data Transport & Transport Signalling for Common Transport Channel Data Streams".
[36]	3GPP TS 44.118: "Mobile radio interface layer 3 specification; Radio Resource Control (RRC) Protocol Iu mode".
[37]	Void
[38]	3GPP TS 48.008: "Mobile-services Switching Centre – Base Station System (MSC – BSS) interface; Layer 3 specification".
[39]	3GPP TS 43.051: "GSM/EGDE Radio Access Network; Overall description – Stage 2".
[40]	3GPP TS 25.401: "UTRAN Overall Description".
[41]	3GPP TS 25.321: "MAC protocol specification".
[42]	3GPP TS 25.306: "UE Radio Access capabilities".
[43]	3GPP TS 25.101: "User Equipment (UE) radio transmission and reception (FDD)".
[44]	IETF RFC 2474 (1998-12): "Definition of the Differentiated Services Field (DS Field) in the Ipv4 and Ipv6 Headers".
[45]	IETF RFC 2475 (1998-12): "An Architecture for Differentiated Services".
[46]	3GPP TS 25.222: "Multiplexing and Channel Coding (TDD)".
[47]	3GPP TS 44.060: "General Packet Radio Service (GPRS); Mobile Station (MS) – Base Station System (BSS) interface; Radio Link Control/Medium Access Control (RLC/MAC) protocol".
[48]	3GPP TS 32.421: "Subscriber and equipment trace: Trace concepts and requirements".
[49]	3GPP TS 32.422: "Subscriber and equipment trace: Trace control and Configuration Management".

[50]	3GPP TS 25.346: "Introduction of the Multimedia Broadcast Multicast Service (MBMS) in the Radio Access Network (Stage-2) ".
[51]	3GPP TS 23.246: "Multimedia Broadcast Multicast Service; Architecture and Functional Description".
[52]	3GPP TS 25.319: "Enhanced Uplink; Overall description; Stage 2".
[53]	Galileo OS Signal in Space ICD (OS SIS ICD), Draft 0, Galileo Joint Undertaking, May 23 rd , 2006. In this version of the specification, Galileo Information Elements are not used.
[54]	3GPP TS 23.251: "Network Sharing: Architecture and functional description".
[55]	IS-GPS-200, Revision D, Navstar GPS Space Segment/Navigation User Interfaces, March 7 th , 2006.
[56]	IS-GPS-705, Navstar GPS Space Segment/User Segment L5 Interfaces, September 22, 2005.
[57]	IS-GPS-800, Navstar GPS Space Segment/User Segment L1C Interfaces, March 31, 2008.
[58]	Specification for the Wide Area Augmentation System (WAAS), US Department of Transportation, Federal Aviation Administration, DTFA01-96-C-00025, 2001.
[59]	IS-QZSS, Quasi Zenith Satellite System Navigation Service Interface Specifications for QZSS, Ver.1.0, June 17, 2008.
[60]	Global Navigation Satellite System GLONASS Interface Control Document, Version 5, 2002.
[61]	3GPP TS 36.401: "Evolved Universal Terrestrial Radio Access Network (E-UTRAN); Architecture Description".
[62]	3GPP TS 36.104: "Base Station (BS) radio transmission and reception ".
[63]	3GPP TS 25.308: "High Speed Downlink Packet Access (HSDPA); Overall description; Stage 2".
[64]	3GPP TS 36.133: "Requirements for support of radio resource management".
[65]	3GPP TS 23.195: "Provision of UE Specific Behaviour Information to Network Entities".
[66]	3GPP TS 24.008: "Mobile radio interface Layer 3 specification; Core network protocols; Stage 3".
[67]	3GPP TS 44.108: "Mobile radio interface layer 3 specification; Radio Resource Control (RRC) protocol".
[68]	3GPP TS 25.422: "UTRAN Iur interface signalling transport".
[69]	3GPP TS 45.005: "Technical Specification Group GSM/EDGE Radio Access Network; Radio transmission and reception"

3 Definitions, Symbols and Abbreviations

3.1 Definitions

For the purposes of the present document, the following terms and definitions apply:

Elementary Procedure: RNSAP protocol consists of Elementary Procedures (Eps). An Elementary Procedure is a unit of interaction between two RNCs. An EP consists of an initiating message and possibly a response message. Two kinds of Eps are used:

- Class 1: Elementary Procedures with response (success or failure);
- Class 2: Elementary Procedures without response.

For Class 1 Eps, the types of responses can be as follows:

Successful

- A signalling message explicitly indicates that the elementary procedure has been successfully completed with the receipt of the response.

Unsuccessful

- A signalling message explicitly indicates that the EP failed.

Class 2 Eps are considered always successful.

Prepared Reconfiguration: A Prepared Reconfiguration exists when the Synchronised Radio Link Reconfiguration Preparation procedure has been completed successfully. The Prepared Reconfiguration does not exist anymore only after either of the procedures Synchronised Radio Link Reconfiguration Commit or Synchronised Radio Link Reconfiguration Cancellation has been completed. In particular, the Prepared Reconfiguration still exists if the object (e.g. Radio Link) concerned by the Synchronised Radio Link Reconfiguration (e.g. in the case of an HS-DSCH Setup) is removed, but the UE Context still exists.

UE Context: The UE Context contains the necessary information for the DRNC/DBSS to communicate with a specific UE. The UE Context is created by the Radio Link Setup procedure or by the Uplink Signalling Transfer procedure when the UE makes its first access in a cell controlled by the DRNS/DBSS or by Enhanced Relocation procedure when the procedure is the first dedicated RNSAP procedure for the UE. The UE Context is deleted by the Radio Link Deletion procedure, by the Common Transport Channel Resources Release procedure, or by the Downlink Signalling Transfer procedure when neither any Radio Links nor any common transport channels are established towards the concerned UE. The UE Context is identified by the SCCP Connection for messages using connection oriented mode of the signalling bearer and the D-RNTI for messages using connectionless mode of the signalling bearer, unless specified otherwise in the procedure text.

Distant RNC Context: The Distant RNC context is created by the first Common Measurement Initiation Procedure or Information Exchange Initiation Procedure initiated by one RNC/BSS and requested from another RNC/BSS. The Distant RNC Context is deleted after the Common Measurement Termination, the Common Measurement Failure, the Information Exchange Termination or the Information Exchange Failure procedure when there is no more Common Measurement and no more Information to be provided by the requested RNC/BSS to the requesting RNC/BSS. The Distant RNC Context is identified by a connection oriented signalling bearer (See TS 25.422 [68]) as, for common measurements and information exchange, only the connection oriented mode of the signalling bearer is used.

Signalling radio bearer 2: The signalling radio bearer 2 is used by the UE to access a GERAN cell in order to perform RRC procedures (TS 44.118 [36]).

UE Link: see definition in TS 25.346 [50].

URA Link: see definition in TS 25.346 [50].

MBMS Bearer Service: see defintion in TS 23.246 [51].

MBMS session: see defintion in TS 25.346 [50].

MBMS session start: see defintion in TS 25.346 [50].

MBMS session stop: see defintion in TS 25.346 [50].

MBMS Selected Services: see defintion in TS 25.346 [50].

PUESBINE feature: as defined in TS 23.195 [65].

3.2 Symbols

Void.

3.3 Abbreviations

For the purposes of the present document, the following abbreviations apply:

A-GPS Assisted-GPS

ALCAP Access Link Control Application Part

APN Access Point Name

ASN.1 Abstract Syntax Notation One

BER Bit Error Rate
BLER Block Error Rate
BSS Base Station Subsystem
CBSS Controlling BSS

CCCH Common Control Channel

CCPCH Common Control Physical Channel CCTrCH Coded Composite Transport Channel

CFN Connection Frame Number

C-ID Cell Identifier

CM Compressed Mode

CN Core Network

CPICH Common Pilot Channel CRNC Controlling RNC

DBSS Drift BSS

C-RNTI Cell Radio Network Temporary Identifier

CS Circuit Switched

CTFC Calculated Transport Format Combination DCH Dedicated Channel

DGANSS Differential GANSS
DGPS Differential GPS
DL Downlink

DPC Downlink Power Control

DPCCH Dedicated Physical Control Channel
DPCH Dedicated Physical Channel
DPDCH Dedicated Physical Data Channel

DRNC Drift RNC
DRNS Drift RNS

D-RNTI Drift Radio Network Temporary Identifier

DRX Discontinuous Reception
DSCH Downlink Shared Channel
Ec Energy in single Code

E-AGCH E-DCH Absolute Grant Channel

E-DCH Enhanced UL DCH

E-HICH E-DCH HARQ Acknowledgement Indicator Channel E-PUCH Enhanced Uplink Physical Channel (TDD only)

E-RNTI E-DCH RNTI

E-RUCCH E-DCH Random Access Uplink Control Channel (TDD only)

E-TFCI E-DCH Transport Format Combination Indicator
E-UCCH E-DCH Uplink Control Channel (TDD only)

E-UTRA Evolved UTRA

EDSCHPC Enhanced Downlink Shared Channel Power Control EGNOS European Geostationary Navigation Overlay Service

EP Elementary Procedure FACH Forward Access Channel FDD Frequency Division Duplex

F-DPCH Fractional DPCH FN Frame Number FP Frame Protocol

GANSS Galileo and Additional Navigation Satellite Systems

GERAN GSM EDGE Radio Access Network

GA Geographical Area

GAGAN GPS Aided Geo Augmented Navigation

GAI Geographical Area Identifier

GLONASS GLObal'naya Navigatsionnaya Sputnikovaya Sistema (Engl.: Global Navigation Satellite System)

GNSS Global Navigation Satellite System

GPS Global Positioning System
GRA GERAN Registration Area
GSM Global System Mobile
GWCN Gateway Core Network

HSDPA High Speed Downlink Packet Access

HW Hardware

IB Information Block

ICD Interface Control Document

ID Identity or Identifier IE Information Element

IMSI International Mobile Subscriber Identity

IP Internet Protocol
IPDL Idle Period DownLink

ISCP Interference Signal Code Power

LAC Location Area Code
LCR Low Chip Rate (1.28 Mcps)

LCS Location Services
MAC Medium Access Control

MBMS Multimedia Broadcast Multicast Service

MDT Minimization of Drive Tests MOCN Multi-Operator Core Network

MRNC MBMS Master RNC MS Mobile Station

MSAS Multi-functional Satellite Augmentation System

NACC Network Assissted Cell Change

NAS Non Access Stratum
No Reference Noise
NRT Non Real Time

O&M Operation and Maintenance

P(-)CCPCH Primary CCPCH PCH Paging Channel

OTD Observed Time Difference

P(-)CPICH Primary CPICH

PCS Personal Communication Services
PDSCH Physical Downlink Shared Channel

PDU Protocol Data Unit PhCH Physical Channel

PICH Paging Indication Channel

PLCCH Physical Layer Common Control Channel

Pos Position or Positioning

PRACH Physical Random Access Channel

PTP Point To Point PTM Point To Multipoint PS Packet Switched

PUESBINE Provision of UE Specific Behaviour Information to Network Entities

QE Quality Estimate

QZSS Quasi-Zenith Satellite System

RAC Routing Area Code
RACH Random Access Channel
RAN Radio Access Network

RANAP Radio Access Network Application Part

RB Radio Bearer RL Radio Link

RLC Radio Link Control
RLS Radio Link Set
RM Rate Matching

RNC Radio Network Controller RNS Radio Network Subsystem

RNSAP Radio Network Subsystem Application Part RNTI Radio Network Temporary Identifier

RRC Radio Resource Control

RT Real Time

RSCP Received Signal Code Power

SBAS Satellite Based Augmentation System

SBSS Serving BSS

Rx Receive or Reception

Sat Satellite

SCCP Signalling Connection Control Part

S(-)CCPCH Secondary CCPCH
SCH Synchronisation Channel
SCTD Space Code Transmit Diversity

SDU Service Data Unit SF System Frame

SFN System Frame Number
SHCCH Shared Control Channel
SIR Signal-to-Interference Ratio
SNA Shared Network Area
SRB2 Signalling radio bearer 2

SRNC Serving RNC SRNS Serving RNS

S-RNTI Serving Radio Network Temporary Identifier

STTD Space Time Transmit Diversity

TDD Time Division Duplex TF Transport Format

TFCI Transport Format Combination Indicator
TFCS Transport Format Combination Set

TFS Transport Format Set

TGCFN Transmission Gap Connection Frame Number

TMGI Temporary Mobile Group Identity
ToAWE Time of Arrival Window Endpoint
ToAWS Time of Arrival Window Startpoint

TPC Transmit Power Control
TrCH Transport Channel

TS Time Slot

TSG Technical Specification Group
TSTD Time Switched Transmit Diversity
TTI Transmission Time Interval
TX Transmit or Transmission

UARFCN UTRA Absolute Radio Frequency Channel Number

UDP User Datagram Protocol
UC-ID UTRAN Cell Identifier
UE User Equipment

UL Uplink

UMTS Universal Mobile Telecommunications System

URA UTRAN Registration Area

U-RNTI UTRAN Radio Network Temporary Identifier

USCH Uplink Shared Channel
UTC Universal Coordinated Time
UTRA Universal Terrestrial Radio Access

UTRAN Universal Terrestrial Radio Access Network

WAAS Wide Area Augmentation System

4 General

4.1 Procedure Specification Principles

The principle for specifying the procedure logic is to specify the functional behaviour of the DRNC/CRNC exactly and completely. The SRNC functional behaviour is left unspecified. The Physical Channel Reconfiguration procedure, [TDD – the UE Measurement Initiation, the UE Measurement Reporting, UE Measurement Termination, UE Measurement Failure,] and the Reset procedure are an exception from this principle.

The following specification principles have been applied for the procedure text in subclause 8:

- The procedure text discriminates between:
 - 1) Functionality which "shall" be executed

The procedure text indicates that the receiving node "shall" perform a certain function Y under a certain condition. If the receiving node supports procedure X but cannot perform functionality Y requested in the REQUEST message of a Class 1 EP, the receiving node shall respond with the message used to report unsuccessful outcome for this procedure, containing an appropriate cause value.

04. ☐ Functionality which "shall, if supported" be executed

The procedure text indicates that the receiving node "shall, if supported," perform a certain function Y under a certain condition. If the receiving node supports procedure X, but does not support functionality Y, the receiving node shall proceed with the execution of the EP, possibly informing the requesting node about the not supported functionality.

Any required inclusion of an optional IE in a response message is explicitly indicated in the procedure text. If the procedure text does not explicitly indicate that an optional IE shall be included in a response message, the optional IE shall not be included. For requirements for including *Criticality Diagnostics* IE, see section 10. For examples on how to use the *Criticality Diagnostics* IE, see Annex C.

4.2 Forwards and Backwards Compatibility

The forwards and backwards compatibility of the protocol is assured by a mechanism in which all current and future messages, and IEs or groups of related IEs, include ID and criticality fields that are coded in a standard format that will not be changed in the future. These parts can always be decoded regardless of the standard version.

4.3 Source Signalling Address Handling

The sender of an RNSAP messages shall include the Source Signalling Address, i.e. the Signalling Address of the sending node.

4.4 Specification Notations

For the purposes of the present document, the following notations apply:

I	r r	8
[FDD]	This tagging of a word indicates that the word preceding the tag "[FDD]" applies only to FDD. This tagging of a heading indicates that the heading preceding the tag "[FDD]" and the section following the heading applies only to FDD.
[TDD]	This tagging of a word indicates that the word preceding the tag "[TDD]" applies only to TDD, including 3.84Mcps TDD, 7.68Mcps TDD and 1.28Mcps TDD. This tagging of a heading indicates that the heading preceding the tag "[TDD]" and the section following the heading applies only to TDD, including 3.84Mcps TDD, 7.68Mcps TDD and 1.28Mcps TDD.
[3.84]	Mcps TDD]	This tagging of a word indicates that the word preceding the tag "[3.84Mcps TDD]" applies only to 3.84Mcps TDD. This tagging of a heading indicates that the heading preceding the tag "[3.84Mcps TDD]" and the section following the heading applies only to 3.84Mcps TDD.
[1.28]	Mcps TDD]	This tagging of a word indicates that the word preceding the tag "[1.28Mcps TDD]" applies only to 1.28Mcps TDD. This tagging of a heading indicates that the heading preceding the tag "[1.28Mcps TDD]" and the section following the heading applies only to 1.28Mcps TDD.
[7.68]	Mcps TDD]	This tagging of a word indicates that the word preceding the tag "[7.68Mcps TDD]" applies only to 7.68Mcps TDD. This tagging of a heading indicates that the heading preceding the tag

"[7.68Mcps TDD]" and the section following the heading applies only to 7.68Mcps TDD.

[FDD]	This tagging indicates that the enclosed text following the "[FDD – " applies only to FDD.
	Multiple sequential paragraphs applying only to FDD are enclosed separately to enable
	insertion of TDD specific (or common) paragraphs between the FDD specific paragraphs.

[TDD - ...] This tagging indicates that the enclosed text following the "[TDD – " applies only to TDD including 3.84Mcps TDD, 7.68Mcps TDD and 1.28Mcps TDD. Multiple sequential paragraphs applying only to TDD are enclosed separately to enable insertion of FDD specific (or common) paragraphs between the TDD specific paragraphs.

[3.84Mcps TDD - ...] This tagging indicates that the enclosed text following the "[3.84Mcps TDD – " applies only to 3.84Mcps TDD. Multiple sequential paragraphs applying only to 3.84Mcps TDD are enclosed separately to enable insertion of FDD and TDD specific (or common) paragraphs between the 3.84Mcps TDD specific paragraphs.

[1.28Mcps TDD - ...] This tagging indicates that the enclosed text following the "[1.28Mcps TDD – " applies only to 1.28Mcps TDD. Multiple sequential paragraphs applying only to 1.28Mcps TDD are enclosed separately to enable insertion of FDD and TDD specific (or common) paragraphs between the 1.28Mcps TDD specific paragraphs.

[7.68Mcps TDD - ...] This tagging indicates that the enclosed text following the "[7.68Mcps TDD – " applies only to 7.68Mcps TDD. Multiple sequential paragraphs applying only to 7.68Mcps TDD are enclosed separately to enable insertion of FDD and TDD specific (or common) paragraphs between the 7.68Mcps TDD specific paragraphs.

Procedure When referring to an elementary procedure in the specification, the Procedure Name is written with the first letters in each word in upper case characters followed by the word "procedure", e.g. Radio Link Setup procedure.

Message When referring to a message in the specification, the MESSAGE NAME is written with all letters in upper case characters followed by the word "message", e.g. RADIO LINK SETUP REQUEST message.

When referring to an information element (IE) in the specification, the *Information Element Name* is written with the first letters in each word in upper case characters and all letters in Italic font followed by the abbreviation "IE", e.g. *Transport Format Set* IE.

When referring to the value of an information element (IE) in the specification, the "Value" is written as it is specified in subclause 9.2 enclosed by quotation marks, e.g. "Abstract Syntax Error (Reject)".

5 RNSAP Services

ΙE

Value of an IE

5.1 RNSAP Procedure Modules

The Iur interface RNSAP procedures are divided into five modules as follows:

- 1. RNSAP Basic Mobility Procedures;
- 2. RNSAP Dedicated Procedures;
- 3. RNSAP Common Transport Channel Procedures;
- 4. RNSAP Global Procedures;
- 5. RNSAP MBMS Procedures.

The Basic Mobility Procedures module contains procedures used to handle the mobility within UTRAN, within GERAN and between UTRAN and GERAN.

The Dedicated Procedures module contains procedures that are used to handle DCHs, [FDD – F-DPCH,] [TDD – DSCHs, USCHs], HS-DSCH and E-DCH between two RNSs. If procedures from this module are not used in a specific

Iur, then the usage of DCH, [FDD – F-DPCH,] [TDD – DSCH, USCH,] HS-DSCH and E-DCH traffic between corresponding RNSs is not possible.

The Common Transport Channel Procedures module contains procedures that are used to control common transport channel data streams (excluding the DSCH, HS-DSCH and USCH) over Iur interface.

The Global Procedures module contains procedures that are not related to a specific UE. The procedures in this module are in contrast to the above modules involving two peer CRNCs/CBSSs.

The MBMS Procedures module contains procedures that are specific to MBMS and used for cases that cannot be handled by other modules.

5.2 Parallel Transactions

Unless explicitly indicated in the procedure specification, at any instance in time one protocol peer shall have a maximum of one ongoing RNSAP Dedicated procedure related to a certain UE.

6 Services Expected from Signalling Transport

The signalling transport shall provide two different service modes for the RNSAP.

- Connection oriented data transfer service. This service is supported by a signalling connection between two RNCs. It shall be possible to dynamically establish and release signalling connections based on the need. Each active UE shall have its own signalling connection. The signalling connection shall provide in sequence delivery of RNSAP messages. RNSAP shall be notified if the signalling connection breaks.
- 2. Connectionless data transfer service. RNSAP shall be notified in case a RNSAP message did not reach the intended peer RNSAP entity.

7 Functions of RNSAP

The RNSAP protocol provides the following functions:

- Radio Link Management. This function allows the SRNC to manage radio links using dedicated resources in a DRNS;
- Physical Channel Reconfiguration. This function allows the DRNC to reallocate the physical channel resources for a Radio Link;
- Radio Link Supervision. This function allows the DRNC to report failures and restorations of a Radio Link;
- Compressed Mode Control [FDD]. This function allows the SRNC to control the usage of compressed mode within a DRNS;
- Measurements on Dedicated Resources. This function allows the SRNC to initiate measurements on dedicated resources in the DRNS. The function also allows the DRNC to report the result of the measurements;
- DL Power Drifting Correction [FDD]. This function allows the SRNC to adjust the DL power level of one or more Radio Links in order to avoid DL power drifting between the Radio Links;
- DCH Rate Control. This function allows the DRNC to limit the rate of each DCH configured for the Radio Link(s) of a UE in order to avoid congestion situations in a cell;
- CCCH Signalling Transfer. This function allows the SRNC and DRNC to pass information between the UE and the SRNC on a CCCH controlled by the DRNS;
- GERAN Signalling Transfer. This function allows the SBSS and DBSS, the SRNC and DBSS or the SBSS and DRNC to pass information between the UE/MS and the SRNC/SBSS on an SRB2/CCCH controlled by the DBSS/DRNC;

- Paging. This function allows the SRNC/SBSS to page a UE in a URA/GRA or a cell in the DRNS;
- Common Transport Channel Resources Management. This function allows the SRNC to utilise Common Transport Channel Resources within the DRNS;
- Relocation Execution. This function allows the SRNC/SBSS to finalise a Relocation previously prepared via other interfaces:
- Reporting of General Error Situations. This function allows reporting of general error situations, for which function specific error messages have not been defined.
- DL Power Timeslot Correction [TDD]. This function enables the DRNS to apply an individual offset to the transmission power in each timeslot according to the downlink interference level at the UE.
- Measurements on Common Resources. This function allows an RNC/BSS to request from another RNC/BSS to initiate measurements on Common Resources. The function also allows the requested RNC/BSS to report the result of the measurements.
- Information Exchange. This function allows an RNC to request from another RNC the transfer of information. The function also allows the requested RNC to report the requested information.
- Resetting the Iur. This function is used to completely or partly reset the Iur interface.
- UE Measurement Forwarding[TDD]. This function allows the DRNC to request and receive UE measurements from the SRNC.
- Tracing. This function allows the SRNC to activate or deactivate trace in a DRNC.
- MBMS UE Linking/De-linking. This function allows the SRNC to provide/update/remove the UE Link to/in/from the DRNC.
- MBMS URA Linking/De-linking. This function allows the SRNC to provide/update/remove the URA Link to/in/from the DRNC.
- MBMS Channel Type Indication. This function allows the DRNC to indicate to the SRNC the selected channel type for an MBMS bearer service within certain cells in the DRNS.
- MBMS Preferred Frequency Layer Indication. This function allows the DRNC to indicate to the SRNC the preferred frequency layer for an MBMS bearer service within certain cells in the DRNS.
- MBMS MCCH Information Control. This function allows an MRNC to distribute the MCCH Information to CRNC within the MBSFN cluster.
- Direct Information Transfer. This function allows an RNC to transfer information to another RNC.
- Relocating serving RNC. This function enables to change the serving RNC functionality as well as the related Iu resources (RAB(s) and Signalling connection) from one RNC to another.
- Exchanging information about the secondary UL frequency. This function allows the SRNC to transfer information about the secondary UL frequency to the DRNS and the DRNS to transfer information about the secondary UL frequency to SRNC in Dual-Cell E-DCH operation.
- Radio Resource Reserve Handover [1.28Mcps TDD]. This function allows the SRNC to request allocation of radio resources in the target BSS prior to the HANDOVER REQUEST message is received from the Core Network.
- Automatic Neighbour Relation Management: This function enables RNC to distribute ANR reports, configure ANR neighbour relations, and control the ANR report distribution.

The mapping between the above functions and RNSAP elementary procedures is shown in the Table 1.

Table 1: Mapping between functions and RNSAP elementary procedures

Function	Elementers, Dress descript
Function Dadie Link Management	Elementary Procedure(s)
Radio Link Management	a) Radio Link Setup b) Radio Link Addition
	c) Radio Link Addition
	d) Unsynchronised Radio Link Reconfiguration
	e) Synchronised Radio Link Reconfiguration
	Preparation
	f) Synchronised Radio Link Reconfiguration
	Commit
	g) Synchronised Radio Link Reconfiguration
	Cancellation
	h) Radio Link Pre-emptioni) Radio Link
	Activation
	j) Radio Link Parameter Update
Physical Channel Reconfiguration	Physical Channel Reconfiguration
Radio Link Supervision	a) Radio Link Failure
O	b) Radio Link Restoration
Compressed Mode Control [FDD]	a) Radio Link Setup
	b) Radio Link Addition
	c) Compressed Mode Command d) Unsynchronised Radio Link Reconfiguration
	e) Synchronised Radio Link Reconfiguration
	Preparation
	f) Synchronised Radio Link Reconfiguration
	Commit
	g) Synchronised Radio Link Reconfiguration
	Cancellation
Measurements on Dedicated Resources	a) Dedicated Measurement Initiation
	b) Dedicated Measurement Reporting
	c) Dedicated Measurement Termination
	d) Dedicated Measurement Failure
DL Power Drifting Correction [FDD]	Downlink Power Control
DCH Rate Control	a) Radio Link Setup
	b) Radio Link Addition
	c) Unsynchronised Radio Link Reconfiguration
	d) Synchronised Radio Link Reconfiguration
	Preparation
CCCH Signalling Transfer	e) Radio Link Congestion a) Uplink Signalling Transfer
CCCH Signalling Transfer	b) Downlink Signalling Transfer
GERAN Signalling Transfer	a) GERAN Uplink Signalling Transfer
GENAN Signalling Transfer	b) Downlink Signalling Transfer
Paging	Paging
Common Transport Channel Resources	a) Common Transport Channel Resources
Management	Initiation
	b) Common Transport Channel Resources
	Release
Relocation Execution	Relocation Commit
Reporting of General Error Situations	Error Indication
Measurements on Common Resources	a) Common Measurement Initiation
	b) Common Measurement Reporting
	c) Common Measurement Termination
	d) Common Measurement Failure
Information Exchange	a) Information Exchange Initiation
	b) Information Reporting
	c) Information Exchange Termination
DL Power Timeslet Correction (TDD)	d) Information Exchange Failure
DL Power Timeslot Correction [TDD]	Downlink Power Timeslot Control Reset
Reset	
UE Measurement Forwarding[TDD]	a) UE Measurement Initiation b) UE Measurement Reporting
	c) UE Measurement Termination
	d) UE Measurement Failure
Trace	a) lur Invoke Trace
	b) Iur Deactivate Trace
<u> </u>	-,

Function	Elementary Procedure(s)
MBMS UE Linking/De-linking	a) Common Transport Channel Resources
	Initiation
	b) Radio Link Setup
	c) Downlink Signalling Transfer
	d) MBMS Attach
	e) MBMS Detach
MBMS Channel Type Indication	a) Direct Information Transfer
	b) Uplink Signalling Transfer
	c) Radio Link Setup
	d) Radio Link Addition
	e) Common Transport Channel Resources
	Initiation
MBMS Preferred Frequency Layer Indication	a) Direct Information Transfer
	b) Radio Link Setup
	d) Radio Link Addition
MBMS URA Linking/De-linking	a) Downlink Signalling Transfer
	b) MBMS Attach
	c) MBMS Detach
MBMS MCCH Information Control	a) MBSFN MCCH Information
Direct Information Transfer	a) Direct Information Transfer
Relocating serving RNC	a) Enhanced Relocation
	b) Enhanced Relocation Cancel
	c) Enhanced Relocation Signalling Transfer
	d) Enhanced Relocation Release
Exchanging information about the secondary	a) Secondary UL Frequency Reporting
UL frequency [FDD]	b) Secondary UL Frequency Update
Radio Resource Reserve Handover [1.28Mcps	a) Enhanced Relocation Resource Allocation
TDD]	b) Enhanced Relocation Resource Release
Automatic Neighbour Relation Management	a) Direct Information Transfer
	b) Information Exchange Initiation
	c) Information Reporting
	d) Information Exchange Termination
	e) Information Exchange Failure
	f) Information Transfer Control

7.1 RNSAP functions and elementary procedures for lur-g.

The functions and RNSAP elementary procedures, which are applicable on the Iur-g interface are shown in the Table 1A.

Table 1A: RNSAP elementary procedures applicable on the lur-g interface

Function	Elementary Procedure(s)
GERAN Signalling Transfer	a) GERAN Uplink Signalling Transfer
	b) Downlink Signalling Transfer
Paging	Paging
Relocation Execution	Relocation Commit
Reporting of General Error Situations	Error Indication
Measurements on Common Resources	a) Common Measurement Initiation
	b) Common Measurement Reporting
	c) Common Measurement Termination
	d) Common Measurement Failure
Information Exchange	a) Information Exchange Initiation
	b) Information Reporting
	c) Information Exchange Termination
	d) Information Exchange Failure
Radio Resource Reserve Handover [1.28Mcps	a) Enhanced Relocation Resource Allocation
TDD]	b) Enhanced Relocation Resource Release

NOTE: In the connection with the functions related to the GERAN and UTRAN, the term RNC shall refer to RNC/BSS.

8 RNSAP Procedures

8.1 Elementary Procedures

In the following tables, all Eps are divided into Class 1 and Class 2 Eps.

Table 2: Class 1 Elementary Procedures

Elementary	Initiating Message	Successful Outcome	Unsuccessful Outcome
Procedure		Response message	Response message
Radio Link Setup	RADIO LINK SETUP REQUEST	RADIO LINK SETUP RESPONSE	RADIO LINK SETUP FAILURE
Radio Link Addition	RADIO LINK ADDITION REQUEST	RADIO LINK ADDITION RESPONSE	RADIO LINK ADDITION FAILURE
Radio Link Deletion	RADIO LINK DELETION REQUEST	RADIO LINK DELETION RESPONSE	
Synchronised Radio Link Reconfiguration Preparation	RADIO LINK RECONFIGURATION PREPARE	RADIO LINK RECONFIGURATION READY	RADIO LINK RECONFIGURATION FAILURE
Unsynchronised Radio Link Reconfiguration	RADIO LINK RECONFIGURATION REQUEST	RADIO LINK RECONFIGURATION RESPONSE	RADIO LINK RECONFIGURATION FAILURE
Physical Channel Reconfiguration	PHYSICAL CHANNEL RECONFIGURATION REQUEST	PHYSICAL CHANNEL RECONFIGURATION COMMAND	PHYSICAL CHANNEL RECONFIGURATION FAILURE
Dedicated Measurement Initiation	DEDICATED MEASUREMENT INITIATION REQUEST	DEDICATED MEASUREMENT INITIATION RESPONSE	DEDICATED MEASUREMENT INITIATION FAILURE
Common Transport Channel Resources Initialisation	COMMON TRANSPORT CHANNEL RESOURCES REQUEST	COMMON TRANSPORT CHANNEL RESOURCES RESPONSE	COMMON TRANSPORT CHANNEL RESOURCES FAILURE
Common Measurement Initiation	COMMON MEASUREMENT INITIATION REQUEST	COMMON MEASUREMENT INITIATION RESPONSE	COMMON MEASUREMENT INITIATION FAILURE
Information Exchange Initiation	INFORMATION EXCHANGE INITIATION REQUEST	INFORMATION EXCHANGE INITIATION RESPONSE	INFORMATION EXCHANGE INITIATION FAILURE
Reset	RESET REQUEST	RESET RESPONSE	
UE Measurement Initiation[TDD]	UE MEASUREMENT INITIATION REQUEST	UE MEASUREMENT INITIATION RESPONSE	UE MEASUREMENT INITIATION FAILURE
Enhanced Relocation	ENHANCED RELOCATION REQUEST	ENHANCED RELOCATION RESPONSE	ENHANCED RELOCATION FAILURE
Enhanced Relocation Resource Allocation[1.28Mc ps TDD]	ENHANCED RELOCATION RESOURCE REQUEST	ENHANCED RELOCATION RESOURCE RESPONSE	ENHANCED RELOCATION RESOURCE FAILURE
Enhanced Relocation Resource Release[1.28Mcp s TDD]	ENHANCED RELOCATION RESOURCE RELEASE COMMAND	ENHANCED RELOCATION RESOURCE RELEASE COMPLETE	

Table 3: Class 2 Elementary Procedures

Elementary Procedure	Initiating Message	
Uplink Signalling Transfer	UPLINK SIGNALLING TRANSFER INDICATION	
GERAN Uplink Signalling Transfer	GERAN UPLINK SIGNALLING TRANSFER INDICATION	
Downlink Signalling Transfer	DOWNLINK SIGNALLING TRANSFER REQUEST	
Relocation Commit	RELOCATION COMMIT	
Paging	PAGING REQUEST	
Synchronised Radio Link Reconfiguration Commit	RADIO LINK RECONFIGURATION COMMIT	
Synchronised Radio Link Reconfiguration Cancellation	RADIO LINK RECONFIGURATION CANCEL	
Radio Link Failure	RADIO LINK FAILURE INDICATION	
Radio Link Restoration	RADIO LINK RESTORE INDICATION	
Dedicated Measurement Reporting	DEDICATED MEASUREMENT REPORT	
Dedicated Measurement Termination	DEDICATED MEASUREMENT TERMINATION REQUEST	
Dedicated Measurement Failure	DEDICATED MEASUREMENT FAILURE INDICATION	
Downlink Power Control [FDD]	DL POWER CONTROL REQUEST	
Compressed Mode Command [FDD]	COMPRESSED MODE COMMAND	
Common Transport Channel Resources Release	COMMON TRANSPORT CHANNEL RESOURCES RELEASE REQUEST	
Error Indication	ERROR INDICATION	
Downlink Power Timeslot Control [TDD]	DL POWER TIMESLOT CONTROL REQUEST	
Radio Link Pre-emption	RADIO LINK PREEMPTION REQUIRED INDICATION	
Radio Link Congestion	RADIO LINK CONGESTION INDICATION	
Common Measurement Reporting	COMMON MEASUREMENT REPORT	
Common Measurement Termination	COMMON MEASUREMENT TERMINATION REQUEST	
Common Measurement Failure	COMMON MEASUREMENT FAILURE INDICATION	
Information Reporting	INFORMATION REPORT	
Information Exchange Termination	INFORMATION EXCHANGE TERMINATION REQUEST	
Information Exchange Failure	INFORMATION EXCHANGE FAILURE INDICATION	
MBMS Attach	MBMS ATTACH COMMAND	
MBMS Detach	MBMS DETACH COMMAND	
Radio Link Parameter Update	RADIO LINK PARAMETER UPDATE INDICATION	
UE Measurement Reporting [TDD]	UE MEASUREMENT REPORT	
UE Measurement Termination [TDD]	UE MEASUREMENT TERMINATION REQUEST	
UE Measurement Failure [TDD]	UE MEASUREMENT FAILURE INDICATION	
Iur Invoke Trace	IUR INVOKE TRACE	
Iur Deactivate Trace	IUR DEACTIVATE TRACE	
Direct Information Transfer	DIRECT INFORMATION TRANSFER	
Enhanced Relocation Cancel	ENHANCED RELOCATION CANCEL	
Enhanced Relocation Signalling Transfer	ENHANCD RELOCATION SIGNALLING TRANSFER	
Enhanced Relocation Release	ENHANCD RELOCATION RELEASE	
MBSFN MCCH Information	MBSFN MCCH INFORMATION	
Secondary UL Frequency Reporting [FDD]	SECONDARY UL FREQUENCY REPORT	
Secondary UL Frequency Update[FDD]	SECONDARY UL FREQUENCY UPDATE INDICATION	
Information Transfer Control	INFORMATION TRANSFER CONTROL REQUEST	

8.2 Basic Mobility Procedures

8.2.1 Uplink Signalling Transfer

8.2.1.1 General

The procedure is used by the DRNC to forward a Uu message received on the CCCH to the SRNC.

This procedure shall use the connectionless mode of the signalling bearer.

8.2.1.2 Successful Operation




Figure 1: Uplink Signalling Transfer procedure, Successful Operation

When the DRNC receives an Uu message on the CCCH in which the UE addressing information is U-RNTI, i.e. S-RNTI and SRNC-ID, DRNC shall send the UPLINK SIGNALLING TRANSFER INDICATION message to the SRNC identified by the SRNC-ID received from the UE.

If at least one URA Identity is being broadcast in the cell where the Uu message was received (the accessed cell), the DRNC shall include a URA Identity for this cell in the *URA ID* IE, the *Multiple URAs Indicator* IE indicating whether or not multiple URA Identities are being broadcast in the accessed cell, and the RNC Identity of all other RNCs that are having at least one cell within the URA where the Uu message was received in the *URA Information* IE in the UPLINK SIGNALLING TRANSFER INDICATION message.

The DRNC shall include in the message the C-RNTI that it allocates to identify the UE in the radio interface in the accessed cell. If there is no valid C-RNTI for the UE in the accessed cell, the DRNS shall allocate a new C-RNTI for the UE [FDD – and in case Enhanced FACH operation is activated in the accessed cell the DRNC shall allocate the HS-DSCH-RNTI to the UE and shall include the *HS-DSCH-RNTI* IE in the message. And in case Common E-DCH operation is activated in the accessed cell the DRNC shall include the E-RNTI received from Node B and shall include the *E-RNTI* IE in the message]. [1.28Mcps TDD – and in case Enhanced FACH operation is activated in the accessed cell the DRNC shall allocate the HS-DSCH-RNTI to the UE and shall include the *HS-DSCH-RNTI* IE in the message and the DRNC shall include the E-RNTI received from Node B and shall include the *E-RNTI* IE in the message]. If the DRNS allocates a new C-RNTI it shall also release any C-RNTI previously allocated for the UE.

If the DRNS has any RACH and/or FACH resources allocated for the UE identified by the U-RNTI in another cell than the accessed cell in which the Mac SDU sizes, flow control settings (including credits) and/or transport bearer are different from those in the old cell, then the DRNS shall not include the *Common Transport Channel Resources Initialisation Not Required* IE in the UPLINK SIGNALLING TRANSFER INDICATION message. In addition the DRNS shall release these RACH and/or FACH resources in old cell.

If the DRNS has any RACH and/or FACH resources allocated for the UE identified by the U-RNTI in another cell than the accessed cell in which the Mac SDU sizes, flow control settings (including credits) and transport bearer are the same as in the old cell, there is no need for Common Transport Channel Resources Initialisation to be initiated. In that case, DRNC may include the *Common Transport Channel Resources Initialisation Not Required* IE in the UPLINK SIGNALLING TRANSFER INDICATION message. In addition, the DRNS shall move these RACH and/or FACH resources to the new cell. If no Common Transfer Channel Resources Initialisation procedure is executed, the currently applicable Mac SDU sizes, flow control settings (including credits) and transport bearer shall continue to be used while the UE is in the new cell.

If no context exists for this UE in the DRNC, the DRNC shall create a UE Context for this UE, allocate a D-RNTI for the UE Context, and include the *D-RNTI* IE and the identifiers for the CN CS Domain and CN PS Domain that the DRNC is connected to in the UPLINK SIGNALLING TRANSFER INDICATION message. These CN Domain Identifiers shall be based on the LAC and RAC respectively of the cell where the message was received from the UE.

Depending on local configuration in the DRNS, it may include the geographical co-ordinates of the cell, represented either by the *Cell GAI* IE or by the *Cell GA Additional Shapes* IE, in which the Uu message was received in the UPLINK SIGNALLING TRANSFER INDICATION message. If the DRNC includes the *Cell GA Additional Shapes* IE in the UPLINK SIGNALLING TRANSFER INDICATION message, it shall also include the *Cell GAI* IE.

[FDD – The DRNC shall include the *DPC Mode Change Support Indicator* IE in the UPLINK SIGNALLING TRANSFER INDICATION message if the accessed cell supports DPC mode change.]

The DRNC shall include [FDD – the *Cell Capability Container FDD* IE] [3.84Mcps TDD – the *Cell Capability Container TDD* IE] [1.28Mcps TDD – the *Cell Capability Container TDD LCR* IE] [7.68Mcps TDD – the *Cell Capability Container TDD LCR* IE] [7.68Mcps TDD – the *Cell Capability Container Extension FDD* IE] in the UPLINK SIGNALLING TRANSFER INDICATION message if the accessed cell supports any functionalities listed in [FDD – 9.2.2.D] [3.84Mcps TDD – 9.2.3.1a] [1.28Mcps TDD – 9.2.3.1b] [7.68Mcps TDD – 9.2.3.31] [FDD – 9.2.2.123].

[FDD – If the cell is multicell adjacent carrier operation capable and if the cell can be the serving HS-DSCH then the possible cells to serve multicell adjacent carrier operation (same sector) that can act as secondary serving HS-DSCH shall be listed in the *Secondary Serving Cell List* IE. For each cell in the *Secondary Serving Cell List* IE that is Multi Cell E-DCH capable, indicated in the *Cell Capability Container Extension FDD* IE by the Multi Cell E-DCH Support Indicator bit = "1", and is restricted for use as an Additional E-DCH on the secondary uplink frequency with the accessed cell as the corresponding cell of the primary uplink frequency, the DRNS shall, if supported, include the *Multicell E-DCH Restriction* IE set to "TRUE". If the *Secondary Serving Cell List* IE is not present, the multicell (adjacent carrier operation) capable cell can only serve as a secondary serving HS-DSCH cell in single band operation.]

[FDD – If the cell is dual band capable and if the cell can be the serving HS-DSCH then the possible cells to serve dual band carrier operation (same sector) that can act as secondary serving HS-DSCH shall be listed in the *Dual Band Secondary Serving Cell List* IE. If the *Dual Band Secondary Serving Cell List* IE is not present, the dual band capable cell can only serve as a secondary serving HS-DSCH cell in dual band operation.]

If MOCN or GWCN network sharing configuration is used then the DRNC shall include the broadcasted PLMN identities of the concerned cell in the *Multiple PLMN List* IE in the UPLINK SIGNALLING TRANSFER INDICATION message.

If available, the DRNC shall include the SNA Information IE for the concerned cell.

When receiving the *SNA Information* IE, the SRNC should use it to restrict cell access based on SNA information. See also TS 25.401 [40] for a broader description of the SNA access control.

[FDD – The DRNC shall include the *Cell Portion ID* IE in the UPLINK SIGNALLING TRANSFER INDICATION message if available.]

[1.28 Mcps TDD – The DRNC shall include the *Cell Portion LCR ID* IE in the UPLINK SIGNALLING TRANSFER INDICATION message if available.]

[FDD – If the propagation delay value exceeds the range of the *Propagation Delay* IE then the DRNC shall if supported include the *Extended Propagation Delay* IE and set the *Propagation Delay* IE to its maximum value.]

If the *D-RNTI* IE is not to be included in the UPLINK SIGNALLING TRANSFER INDICATION message and the UE Link is currently stored in the UE Context in the DRNC, the DRNC shall assume that the UE changes the cell under which it camps in the DRNS (see TS 25.346 [50], section 5.1.6 on intra-DRNC cell change). In this case, if an MBMS session for some MBMS bearer services contained in the UE Link is ongoing in the cell identified by the *UC-ID* IE, the DRNC shall include in the *Active MBMS Bearer Service List* IE the *Transmission Mode* IE for each of these active MBMS bearer services. Or else, if the DRNC receives a Uu message on the CCCH in which the short identities for MBMS Selected Services are included, and the Uu message requests for MBMS PtP radio bearer establishment, the DRNC shall determine which TMGIs correspond with the short identities and shall include in the *Active MBMS Bearer Service List* IE the *TMGI* IE together with the *Transmission Mode* IE for each of these MBMS Selected Services.

If the CCCH message contains Measurement results for monitored cells on non-used frequencies IE in Measured Result on RACH IE, the DRNC may include in the UPLINK SIGNALLING TRANSFER INDICATION message the Inter-

frequency Cell List IE for each of the measured inter-frequency cells. The order of cells in Measurement results for monitored cells on non-used frequencies IE in the CCCH message shall be preserved in Inter-frequency Cell List IE. If the UL UARFCN IE in the Inter-frequency Cell List IE is not present, the default duplex distance defined for the operating frequency band shall be used in the SRNC (see TS 25.101 [43]).

[3.84 Mcps TDD – the DRNC shall include the *Rx Timing Deviation* IE unless the cell to which the CCCH message was sent is configured to use the extended timing advance in which case *Rx Timing Deviation 3.84Mcps Extended* IE shall be included.]

[7.68 Mcps TDD – the DRNC shall include the Rx Timing Deviation 7.68Mcps IE.]

8.2.1.3 Abnormal Conditions

_

8.2.1A GERAN Uplink Signalling Transfer

8.2.1A.1 General

The procedure is used by the DBSS to forward an Um message received on the SRB2 to the SBSS/SRNC. The procedure is also used by the DRNC to forward a Uu message received on the CCCH to the SBSS.

This procedure shall use the connectionless mode of the signalling bearer.

8.2.1A.2 Successful Operation




Figure 1A: GERAN Uplink Signalling Transfer procedure, Successful Operation

When the DBSS receives an Um message on the SRB2 in which the MS addressing information is G-RNTI, i.e. S-RNTI and BSC-ID, DBSS shall send the GERAN UPLINK SIGNALLING TRANSFER INDICATION message to the SBSS/SRNC identified by the BSC-ID received from the MS.

Alternatively, when the DRNC receives an Uu message on the CCCH in which the UE addressing information is U-RNTI, i.e. S-RNTI and SRNC-ID, and in which the SRNC-ID points to a GERAN BSS, the DRNC shall send the GERAN UPLINK SIGNALLING TRANSFER INDICATION message to the SBSS identified by SRNC-ID received from the UE.

If at least one GRA/URA Identity is being broadcast in the cell where the Um/Uu message was received (the accessed cell), the DBSS/DRNC shall include a GRA/URA Identity for this cell in the *URA ID* IE, the *Multiple URAs Indicator* IE indicating whether or not multiple GRA/URA Identities are being broadcast in the accessed cell, and the RNC/BSS Identity of all other RNC/BSSs that are having at least one cell within the GRA/URA where the Um/Uu message was received in the *URA Information* IE in the GERAN UPLINK SIGNALLING TRANSFER INDICATION message.

If no context exists for this UE/MS in the DBSS/DRNC, the DBSS/DRNC shall create a UE Context for this UE/MS, allocate a D-RNTI for the UE Context, and include the *D-RNTI* IE and the identifiers for the CN CS Domain and CN PS Domain that the DBSS/DRNC is connected to in the GERAN UPLINK SIGNALLING TRANSFER INDICATION message. These CN Domain Identifiers shall be based on the LAC and RAC respectively of the cell where the message was received from the UE/MS.

8.2.1A.3 Abnormal Conditions

-

8.2.2 Downlink Signalling Transfer

8.2.2.1 General

The procedure is used by the SRNC to request to the DRNC the transfer of a Uu message on the CCCH in a cell. When used, the procedure is in response to a received Uplink Signalling Transfer procedure.

This procedure shall use the connectionless mode of the signalling bearer.

8.2.2.1.1 Downlink Signalling Transfer for lur-g

The procedure is used by the SRNC/SBSS to request to the DBSS the transfer of an Um message on the SRB2 in a cell.

The procedure is used by the SBSS to request to the DRNC the transfer of a Uu message on the CCCH in a cell.

8.2.2.2 Successful Operation



Figure 2: Downlink Signalling Transfer procedure, Successful Operation

The procedure consists of the DOWNLINK SIGNALLING TRANSFER REQUEST message sent by the SRNC to the DRNC.

The message contains the Cell Identifier (C-ID) contained in the received UPLINK SIGNALLING TRANSFER INDICATION message and the D-RNTI.

Upon receipt of the message, the DRNC shall send the L3 Information on the CCCH in the cell indicated by the *C-ID* IE to the UE identified by the *D-RNTI* IE.

If the *D-RNTI Release Indication* IE is set to "Release D-RNTI" and the DRNS has no dedicated resources (DCH, [TDD – USCH and/or DSCH]) allocated for the UE, the DRNS shall release the D-RNTI, the UE Context and any RACH and FACH resources and any C-RNTI allocated to the UE Context upon receipt of the DOWNLINK SIGNALLING TRANSFER REQUEST message. If a UE Link is currently stored in the UE Context, the DRNC shall perform UE De-linking as specified in TS 25.346 [50], section 5.1.6.

If the *D-RNTI Release Indication* IE is set to "Release D-RNTI" and the DRNS has dedicated resources allocated for the UE, the DRNS shall only release any RACH and FACH resources and any C-RNTI allocated to the UE Context upon receipt of the DOWNLINK SIGNALLING TRANSFER REQUEST message.

If the *MBMS Bearer Service List* IE is included and *URA-ID* IE is not included in the DOWNLINK SIGNALLING TRANSFER REQUEST message, the DRNC shall perform the UE Linking as specified in TS 25.346 [50], section 5.1.6.

If the *MBMS Bearer Service List* IE is included and the *URA-ID* IE is included in the DOWNLINK SIGNALLING TRANSFER REQUEST message, the DRNC shall perform the URA Linking as specified in TS 25.346 [50], section 5.1.10.

If the *MBMS Bearer Service List* IE is included and the *Old URA-ID* IE is included in the DOWNLINK SIGNALLING TRANSFER REQUEST message, the DRNC shall perform URA De-linking for the URA identified by the *Old URA-ID* IE as specified in TS 25.346 [50], section 5.1.10.

[FDD – If the *Enhanced PCH Capability* IE is included in the message, the DRNC should store the information. If the *Enhanced PCH Capability* IE is not included in the message, the DRNC shall use the information to release an RRC Connection for the UE in cells supporting Enhanced PCH.]

[1.28Mcps TDD – If the *Enhanced PCH Capability* IE is included in the message, the DRNC should store the information. If the *Enhanced PCH Capability* IE is not included in the message, the DRNC shall use the information to release an RRC Connection for the UE in cells supporting Enhanced PCH.]

8.2.2.2.1 Successful Operation for lur-g

The procedure consists of the DOWNLINK SIGNALLING TRANSFER REQUEST message sent by the SRNC/SBSS to the DBSS or by the SBSS to the DRNC.

The message contains the Cell Identifier (C-*ID*) contained in the received UPLINK SIGNALLING TRANSFER INDICATION message and the D-RNTI.

Upon receipt of the message, the DBSS shall send the L3 Information on the SRB2 in the cell indicated by the *C-ID* IE to the UE/MS identified by the *D-RNTI* IE.

Upon receipt of the message, the DRNC shall send the L3 Information on the CCCH in the cell indicated by the *C-ID* IE to the UE/MS identified by the *D-RNTI* IE.

8.2.2.3 Abnormal Conditions

If the user identified by the *D-RNTI* IE has already accessed another cell controlled by the DRNC than the cell identified by the *C-ID* IE in the DOWNLINK SIGNALLING TRANSFER REQUEST message, the message shall be ignored.

8.2.2.3.1 Abnormal Conditions for lur-g

If the user identified by the *D-RNTI* IE has already accessed another cell controlled by the DRNC/DBSS than the cell identified by the *C-ID* IE in the DOWNLINK SIGNALLING TRANSFER REQUEST message, the message shall be ignored.

If the DRNC receives from the SBSS the DOWNLINK SIGNALLING TRANSFER REQUEST message, in which the *D-RNTI Release Indication* IE is set to "not Release D-RNTI", the DRNC shall ignore this IE and release the D-RNTI.

If the DBSS receives from the SBSS/SRNC the DOWNLINK SIGNALLING TRANSFER REQUEST message, in which the *D-RNTI Release Indication* IE is set to "not Release D-RNTI", the DBSS shall ignore this IE and release the D-RNTI.

8.2.3 Relocation Commit

8.2.3.1 General

The Relocation Commit procedure is used by source RNC to execute the Relocation. This procedure supports the Relocation procedures described in TS 25.413 [2].

This procedure shall use the signalling bearer mode specified below.

8.2.3.2 Successful Operation



Figure 3: Relocation Commit procedure, Successful Operation

The source RNC sends the RELOCATION COMMIT message to the target RNC to request the target RNC to proceed with the Relocation. When the UE is utilising one or more radio links in the DRNC the message shall be sent using the connection oriented service of the signalling bearer and no further identification of the UE Context in the DRNC is required. If on the other hand, the UE is not utilising any radio link the message shall be sent using the connectionless service of the signalling bearer and the *D-RNTI* IE shall be included in the message to identify the UE Context in the DRNC.

Upon receipt of the RELOCATION COMMIT message from the source RNC the target RNC finalises the Relocation. If the message contains the transparent *RANAP Relocation Information* IE the target RNC shall use this information when finalising the Relocation.

8.2.3.2.1 Successful Operation for lur-g

The source RNC/BSS sends the RELOCATION COMMIT message to the target RNC/BSS to request the target RNC/BSS to proceed with the Relocation.

The message shall be sent using the connectionless service of the signalling bearer and the *D-RNTI* IE shall be included in the message to identify the UE/MS context in the DBSS.

Upon receipt of the RELOCATION COMMIT message from the source RNC/BSS, the target RNC/BSS finalises the Relocation. If the message contains the transparent *RANAP Relocation Information* IE the target RNC/BSS shall use this information when finalising the Relocation.

8.2.3.3 Abnormal Conditions

-

8.2.4 Paging

8.2.4.1 General

This procedure is used by the SRNC to indicate to a CRNC that a UE shall be paged in a cell or URA that is under the control of the CRNC.

This procedure shall use the connectionless mode of the signalling bearer.

8.2.4.2 Successful Operation



Figure 4: Paging procedure, Successful Operation

The procedure is initiated with a PAGING REQUEST message sent from the SRNC to the CRNC.

If the message contains the *C-ID* IE, the CRNC shall page in the indicated cell. Alternatively, if the message contains the *URA-ID* IE, the CRNC shall page in all cells that it controls in the indicated URA.

If the PAGING REQUEST message includes the *CN Originated Page to Connected Mode UE* IE, the CRNC shall include the information contained in the *CN Originated Page to Connected Mode UE* IE when paging the UE.

The CRNC shall calculate the Paging Occasions from the *IMSI* IE and the *DRX Cycle Length Coefficient* IE according to specification in TS 25.304 [15] and apply transmission on PICH and PCH [FDD – or HS-DSCH] [1.28Mcps TDD – or HS-DSCH] accordingly.

[FDD – If the PAGING REQUEST message includes the *Enhanced PCH Capability* IE, the CRNC shall use the information to page the UE in cells supporting Enhanced PCH.]

[1.28Mcps TDD – If the PAGING REQUEST message includes the *Enhanced PCH Capability* IE, the CRNC shall use the information to page the UE in cells supporting Enhanced PCH.]

8.2.4.2.1 Successful Operation for lur-g

The procedure is initiated with a PAGING REQUEST message sent from the SBSS to the CRNC/CBSS or from the SRNC to the CBSS.

If the message contains the *URA-ID* IE, the CRNC/CBSS shall page in all cells that it controls in the indicated URA/GRA.

If the PAGING REQUEST message includes the *CN Originated Page to Connected Mode UE* IE, the CRNC/CBSS shall include the information contained in the *CN Originated Page to Connected Mode UE* IE when paging the UE.

The CBSS shall calculate the Paging Occasions from the *IMSI* IE and the *GERAN DRX Cycle Length Coefficient* IE according to specification in TS 44.118 [36] and apply transmission on PCCCH or PACCH accordingly.

8.2.4.3 Abnormal Conditions

8.2.4.3.1 Abnormal Conditions for lur-g

If the DRNC receives a PAGING REQUEST message from the SBSS, which contains the *C-ID* IE, the message shall be ignored.

If the DBSS receives a PAGING REQUEST message from the SBSS/SRNC, which contains the *C-ID* IE, the message shall be ignored.

8.2.5 MBSFN MCCH Information

8.2.5.1 General

The procedure is used by the MRNC to inform the CRNC of the MCCH configuration and scheduling information used in MRNC.

This procedure shall use the connectionless mode of the signalling bearer.

8.2.5.2 Successful Operation




Figure 4A: MBSFN MCCH Information procedure, Successful Operation

The procedure is used for MBSFN operation when a MRNC is used.

The message contains the MCCH message list sent on the MRNC and the MCCH configuration information of the MRNC.

Upon receipt of the message, if the *MCCH Configuration* IE exists, the CRNC shall setup or reconfigure the MCCH of all cells in the MBSFN cluster with the configuration contained in this IE, and update the System Information of these cells.

The CRNC shall decode the *L3 Information* IE contained in the *MCCH Message List* IE and apply the RLC/MAC/PHY configuration specified by relative MCCH Message to setup the RB information of MTCH, and then send the *L3 Information* IE on the MCCH in the receiving sequence at the beginning of the first MCCH modification period following the CFN indicated by the *CFN* IE.

In case MRNC is used and TDM multiplexing is used over air interface, the *MBSFN Scheduling Transmission Time Interval info List* IE shall be contained to show the scheduling transmission time interval for MBMS service which is configured with MBSFN TDM multiplexing. The CRNC shall schedule received data packets in the scheduling transmission time interval following the time point indicated by the timestamp.

8.2.5.3 Abnormal Conditions

-

8.2.6 Enhanced Relocation Resource Allocation[1.28Mcps TDD]

8.2.6.1 General

The purpose of this procedure is to inform the BSS to pre-allocate resource for UE relocation from UTRAN to GERAN.

This procedure shall use the signalling bearer connection for the relevant UE context.

8.2.6.2 Successful Operation



Figure 4B: Enhanced Relocation Resource Allocation Procedure, Successful Operation

The RNC initiates the Enhanced Relocation Resource Allocation procedure by sending the ENHANCED RELOCATION RESOURCE REQUEST message to the BSS to request the BSS to prepare resource for the relocation.

Upon receipt of the ENHANCED RELOCATION RESOURCE REQUEST message form the RNC, the BSS finalises the relocation resource preparation and sends ENHANCED RELOCATION RESOURCE RESPONSE message to the RNC.

8.2.6.3 Unsuccessful Operation



Figure 4C: Enhanced Relocation Resource Allocation Procedure, Unsuccessful Operation

If the BSS is not able to finalise the relocation resource preparation or can not accept the relocation resource request during the handover procedure, the BSS shall send the ENHANCED RELOCATION RESOURCE FAILURE message to the RNC.

8.2.6.4 Abnormal Conditions

-

8.2.7 Enhanced Relocation Resource Release[1.28Mcps TDD]

8.2.7.1 General

This procedure is used by the RNC to infom BSS that related resource pre-allocated for UE shall be released due to failure of the enhanced relocation from UTRAN TDD to GERAN.

This procedure shall use the signalling bearer connection for the relevant UE context.

8.2.7.2 Successful Operation



Figure 4D: Enhanced Relocation Resource Release Procedure, Successful Operation

The Enhanced Relocation Resource Release procedure is initiated by sending the ENHANCED RELOCATION RESOURCE RELEASE COMMAND message from the RNC to the BSS.

Upon reception of the ENHANCED RELOCATION RESOURCE RELEASE COMMAND message, the BSS shall release related resource pre-allocated for UE, and then responsed with the ENHANCD RELOCATION RESOURCE RELEASE COMPLETE meassage.

8.2.7.3 Abnormal Conditions

_

8.3 Dedicated Procedures

8.3.1 Radio Link Setup

8.3.1.1 General

This procedure is used for establishing the necessary resources in the DRNS for one or more radio links.

The connection-oriented service of the signalling bearer shall be established in conjunction with this procedure.

8.3.1.2 Successful Operation




Figure 5: Radio Link Setup procedure: Successful Operation

When the SRNC makes an algorithmic decision to add the first cell or set of cells from a DRNS to the active set of a specific UE-UTRAN connection, the RADIO LINK SETUP REQUEST message is sent to the corresponding DRNC to request establishment of the radio link(s). The Radio Link Setup procedure is initiated with this RADIO LINK SETUP REQUEST message sent from the SRNC to the DRNC.

Upon receipt of the RADIO LINK SETUP REQUEST message, the DRNS shall reserve the necessary resources and configure the new RL(s) according to the parameters given in the message. Unless specified below, the meaning of parameters is specified in other specifications.

The DRNS shall prioritise resource allocation for the RL(s) to be established according to Annex A.

If the RADIO LINK SETUP REQUEST message includes the *Allowed Queuing Time* IE the DRNS may queue the request for a time period not to exceed the value of the *Allowed Queuing Time* IE before starting to execute the request.

If the *UE Aggregate Maximum Bit Rate* IE is contained in the RADIO LINK SETUP REQUEST message, the DRNS shall, if supported, store the received UE Aggregate Maximum Bit Rate parameters to control the aggregate data rate of non GBR traffic for this UE.

If the *Usefulness of Battery Optimization* IE is contained in the RADIO LINK SETUP REQUEST message, the DRNC may store the received value and use it to determine whether this UE can benefit from battery optimization techniques.

Transport Channels Handling:

DCH(s):

[TDD – If the *DCH Information* IE is present in the RADIO LINK SETUP REQUEST message, the DRNS shall configure the new DCHs according to the parameters given in the message.]

If the RADIO LINK SETUP REQUEST message includes a *DCH Information* IE with multiple *DCH Specific Info* IEs, then the DRNS shall treat the DCHs in the *DCH Information* IE as a set of co-ordinated DCHs.

If the *DCH Specific Info* IE includes the *Unidirectional DCH Indicator* IE set to "Uplink DCH only", the DRNS shall ignore the *Transport Format Set* IE for the downlink for this DCH. As a consequence this DCH is not included as a part of the downlink CCTrCH.

If the *DCH Specific Info* IE includes the *Unidirectional DCH Indicator* IE set to "Downlink DCH only", the DRNS shall ignore the *Transport Format Set* IE for the uplink for this DCH. As a consequence this DCH is not included as a part of the uplink CCTrCH.

[FDD – For each DCH which do not belong to a set of co-ordinated DCHs, and which includes a *QE-Selector* IE set to "selected", the DRNS shall use the Transport channel BER from that DCH for the QE in the UL data frames. If no Transport channel BER is available for the selected DCH, the DRNS shall use the Physical channel BER for the QE, TS 25.427 [4]. If the *QE-Selector* IE is set to "non-selected", the DRNS shall use the Physical channel BER for the QE in the UL data frames, TS 25.427 [4].]

For a set of co-ordinated DCHs, the DRNS shall use the Transport channel BER from the DCH with the *QE-Selector* IE set to "selected" for the QE in the UL data frames, TS 25.427 [4]. [FDD – If no Transport channel BER is available for the selected DCH, the DRNS shall use the Physical channel BER for the QE, TS 25.427 [4]. If all DCHs have *QE-Selector* IE set to "non-selected", the DRNS shall use the Physical channel BER for the QE, TS 25.427 [4].] [TDD – If no Transport channel BER is available for the selected DCH, the DRNS shall use 0 for the QE, TS 25.427 [4].]

The DRNS shall use the included *UL DCH FP Mode* IE for a DCH or a set of co-ordinated DCHs as the DCH FP Mode in the Uplink of the user plane for the DCH or the set of co-ordinated DCHs.

The DRNS shall use the included *ToAWS* IE for a DCH or a set of co-ordinated DCHs as the Time of Arrival Window Startpoint in the user plane for the DCH or the set of co-ordinated DCHs.

The DRNS shall use the included *ToAWE* IE for a DCH or a set of co-ordinated DCHs as the Time of Arrival Window Endpoint in the user plane for the DCH or the set of co-ordinated DCHs.

The *Frame Handling Priority* IE defines the priority level that should be used by the DRNS to prioritise between different frames of the data frames of the DCHs in the downlink on the radio interface in congestion situations once the new RL(s) have been activated.

The *Traffic Class* IE may be used to determine the transport bearer characteristics to apply between DRNC and Node B for the related DCH or set of co-ordinated DCHs. The DRNC should ignore the *Traffic Class* IE if the *TrCH Source Statistics Descriptor* IE indicates the value "RRC".

If the *TNL QoS* IE is included for a DCH or a set of co-ordinated DCHs and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink for the related DCH or set of co-ordinated DCHs.

If the *DCH Information* IE contains a *DCH Specific Info* IE which includes the *Guaranteed Rate Information* IE, the DRNS shall treat the included IEs according to the following:

- If the *Guaranteed Rate Information* IE includes the *Guaranteed UL Rate* IE, the DRNS shall apply the Guaranteed Rate in the uplink of this DCH. The DRNS may decide to request the SRNC to limit the user rate of the uplink of the DCH at any point in time. The DRNS may request the SRNC to reduce the user rate of the uplink of the DCH below the guaranteed bit rate, however, whenever possible the DRNS should request the SRNC to only reduce the user rate between the maximum bit rate and the guaranteed bit rate. If the *DCH Specific Info* IE in the *DCH Information* IE does not include the *Guaranteed UL Rate* IE, the DRNS shall not limit the user rate of the uplink of the DCH.
- If the Guaranteed Rate Information IE includes the Guaranteed DL Rate IE, the DRNS shall apply the Guaranteed Rate in the downlink of this DCH. The DRNS may decide to request the SRNC to limit the user rate of the downlink of the DCH at any point in time. The DRNS may request the SRNC to reduce the user rate of the downlink of the DCH below the guaranteed bit rate, however, whenever possible the DRNS should request the SRNC to only reduce the user rate between the maximum bit rate and the guaranteed bit rate. If the DCH Specific Info IE in the DCH Information IE does not include the Guaranteed DL Rate IE, the DRNS shall not limit the user rate of the downlink of the DCH.

[FDD – If the RADIO LINK SETUP REQUEST message includes the *Transport Bearer Not Requested Indicator* IE set to "Transport Bearer shall not be Established" for a DCH, then the DRNC shall not establish a transport bearer for the concerned DCH and shall include the *Transport Bearer Not Setup Indicator* IE for the corresponding DCH in the RADIO LINK SETUP RESPONSE message.]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *Transport Bearer Not Requested Indicator* IE set to "Transport Bearer may not be Established" for a DCH and:]

- [FDD if the DRNC establishes a transport bearer for the concerned DCH, the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Binding ID* IE and *Transport Layer Address* IE for establishment of a transport bearer for the DCH being established.]
- [FDD if the DRNC does not establish a transport bearer for the concerned DCH, the DRNC shall
 include the *Transport Bearer Not Setup Indicator* IE for the corresponding DCH in the RADIO LINK
 SETUP RESPONSE message.]

[TDD - DSCH(s):]

[TDD – If the *DSCH Information* IE is included in the RADIO LINK SETUP REQUEST message, the DRNC shall establish the requested DSCHs. If the *Transport Layer Address* IE and *Binding ID* IE are included in the *DSCH Information* IE the DRNC may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for the DSCH. In addition, the DRNC shall send a valid set of *DSCH Scheduling Priority* IE and *MAC-c/sh SDU Length* IE parameters to the SRNC in the RADIO LINK SETUP RESPONSE message. If the *PDSCH RL ID* IE indicates a radio link in the DRNS, then the DRNC shall allocate a DSCH-RNTI to the UE Context and include the *DSCH-RNTI* IE in the RADIO LINK SETUP RESPONSE message.]

[TDD – If the *DSCH Information* IE is included in the RADIO LINK SETUP REQUEST message, the DRNS may use the *Traffic Class* IE to determine the transport bearer characteristics to apply between DRNC and Node B for the related DSCHs.]

[TDD – The DRNC shall include the *DSCH Initial Window Size* IE in the RADIO LINK SETUP RESPONSE message for each DSCH, if the DRNS allows the SRNC to start transmission of MAC-c/sh SDUs before the DRNS has allocated capacity on user plane as described in TS 25.425 [32].]

[TDD – If the RADIO LINK SETUP REQUEST message includes the *TNL QoS* IE in the *DSCH TDD Information* IE and if ALCAP is not used, the DRNS may use the *TNL QoS* IE to determine the transport bearer characteristics to apply in the uplink for the related DSCH.]

[TDD – USCH(s):]

[TDD – The DRNS shall use the list of RB Identities in the *RB Info* IE in the *USCH information* IE to map each *RB Identity* IE to the corresponding USCH. If the *Transport Layer Address* IE and *Binding ID* IE are included in the *USCH Information* IE the DRNC may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for the USCH.]

[TDD – If the *USCH Information* IE is included in the RADIO LINK SETUP REQUEST message, the DRNS may use the *Traffic Class* IE to determine the transport bearer characteristics to apply between DRNC and Node B for the related USCHs.]

[TDD – If the *USCH Information* IE is included in the RADIO LINK SETUP REQUEST message and contains the *TNL QoS* IE, and if ALCAP is not used, the DRNS may use the *TNL QoS* IE to determine the transport bearer characteristics to apply in the uplink for the related USCH.]

[TDD – If the *USCH Information* IE is included in the RADIO LINK SETUP REQUEST message, the DRNS shall establish the requested USCHs, and the DRNC shall provide the [3.84 Mcps TDD – *USCH Information Response* IE] [1.28 Mcps TDD – USCH Information Response LCR IE] [7.68 Mcps TDD – *USCH Information Response 7.68 Mcps* IE] in the RADIO LINK SETUP RESPONSE message.]

[TDD - CCTrCH Handling:]

[TDD – If the *UL CCTrCH Information* IE is present in the RADIO LINK SETUP REQUEST message, the DRNS shall configure the new UL CCTrCH(s) according to the parameters given in the message.]

[1.28Mcps TDD – If the *UL CCTrCH Information LCR* IE includes the *TDD TPC Uplink Step Size* IE, the DRNS shall configure the uplink TPC step size according to the parameters given in the message.]

[TDD – If the *DL CCTrCH Information* IE is present in the RADIO LINK SETUP REQUEST message, the DRNS shall configure the new DL CCTrCH(s) according to the parameters given in the message.]

[TDD – If the *TPC CCTrCH List* IE is present in the RADIO LINK SETUP REQUEST message, the DRNS shall configure the identified UL CCTrCHs with TPC according to the parameters given in the message.]

HS-DSCH:

If the HS-DSCH Information IE is present in the RADIO LINK SETUP REQUEST message, then:

- The DRNS shall setup the requested HS-PDSCH resources on the Serving HS-DSCH Radio Link indicated by the *HS-PDSCH RL ID* IE.
- The DRNC shall include the *HARQ Memory Partitioning* IE in the [FDD *HS-DSCH FDD Information Response* IE] [TDD *HS-DSCH TDD Information Response* IE] in the RADIO LINK SETUP RESPONSE message. [FDD The *HARQ Memory Partitioning* IE shall either contain the *HARQ Memory Partitioning Information Extension For MIMO* IE or the *Number of Processes* IE set to a value higher than "8", if the *MIMO Activation Indicator* IE is included in the *HS-DSCH Information* IE.] [1.28Mcps TDD– The *HARQ Memory Partitioning* IE shall either contain the *HARQ Memory Partitioning Information Extension For MIMO* IE or the *Number of Processes* IE set to a value higher than "8", if the *MIMO Activation Indicator* IE is included in the *HS-DSCH Information* IE.]
- The DRNC shall allocate an HS-DSCH-RNTI to the UE Context and include the *HS-DSCH-RNTI* IE in the RADIO LINK SETUP RESPONSE message.
- The DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Binding ID* IE and *Transport Layer Address* IE for establishment of transport bearer for every HS-DSCH MAC-d flow being established.
- If the RADIO LINK SETUP REQUEST message includes the *Transport Layer Address* IE and *Binding ID* IE in the *HS-DSCH Information* IE for an HS-DSCH MAC-d flow, then the DRNC may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for the concerned HS-DSCH MAC-d flow.
- The DRNS may use the *Traffic Class* IE for a specific HS-DSCH MAC-d flow to determine the transport bearer characteristics to apply between DRNC and Node B. If *TrCH Source Statistics Descriptor* IE is present with the value "RRC" in the *HS-DSCH MAC-d Flows Information* IE, then the DRNC should ignore the *Traffic Class* IE.
- If fields are to be included in the User Plane by the SRNC to handle TNL Congestion Control for HSDPA in the DRNS, then the DRNC shall include the *User Plane Congestion Fields Inclusion* IE in the *HS-DSCH Information Response* IE.
- If the RADIO LINK SETUP REQUEST message includes the *MAC-hs Guaranteed Bit Rate* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, then the DRNS shall use this information to optimise MAC-hs scheduling decisions for the related HSDPA Priority Queue.
- If the RADIO LINK SETUP REQUEST message includes the *Discard Timer* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, then the DRNS shall use this information to discard out-of-date MAC-hs SDUs from the related HSDPA Priority Queue.
- If the RADIO LINK SETUP REQUEST message includes the *Maximum MAC-d PDU Size Extended* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, then the DRNS shall ignore the *SID* IE and *MAC-d PDU Size* IE in the *MAC-d PDU Size Index* IE and use *Maximum MAC-d PDU Size Extended* IE to optimise capacity allocation for the related HSDPA Priority Queue.
- The DRNC shall include the *HS-DSCH Initial Capacity Allocation* IE in the [FDD *HS-DSCH FDD Information Response* IE] [TDD *HS-DSCH TDD Information Response* IE] in the RADIO LINK SETUP RESPONSE message for every HS-DSCH MAC-d flow being established, if the DRNS allows the SRNC to start transmission of MAC-d PDUs before the DRNS has allocated capacity on user plane as described in TS 25.425 [32]. If RADIO LINK SETUP REQUEST message includes *HS-DSCH MAC-d PDU Size Format* IE in the *HS-DSCH Information* IE set to the value "Flexible MAC-d PDU Size", then DRNC shall only set in the *HS-DSCH Initial Capacity Allocation* IE the values for the peer of *Scheduling Priority Indicator* IE and *Maximum MAC-d PDU Size Extended* IE to the values of the corresponding peer I in RADIO LINK SETUP REQUEST in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE for a Priority Queue including *Scheduling Priority Indicator* IE and *Maximum MAC-d PDU Size Extended* IE.

- [FDD If the RADIO LINK SETUP REQUEST message includes the *HS-SCCH Power Offset* IE in the *HS-DSCH Information* IE, then the DRNS may use this value to determine the HS-SCCH power. The HS-SCCH Power Offset should be applied for any HS-SCCH transmission to this UE.]
- [FDD The DRNC shall include the *Measurement Power Offset* IE in the *HS-DSCH Information Response* IE in the RADIO LINK SETUP RESPONSE message.]
- FDD The DRNS shall allocate HS-SCCH codes corresponding to the HS-DSCH and the DRNC shall include the *HS-SCCH Specific Information Response* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK SETUP RESPONSE message.]
- [TDD The DRNS shall allocate HS-SCCH parameters corresponding to the HS-DSCH and the DRNC shall include the [3.84Mcps TDD HS-SCCH Specific Information Response IE] [1.28Mcps TDD HS-SCCH Specific Information Response LCR IE] [7.68 Mcps TDD HS-SCCH Specific Information Response 7.68 Mcps IE] in the HS-DSCH TDD Information Response IE in the RADIO LINK SETUP RESPONSE message.]
- [TDD The DRNC shall include the [3.84 Mcps TDD *HS-PDSCH Timeslot Specific Information Response* IE] [1.28 Mcps TDD *HS-PDSCH Timeslot Specific Information Response LCR* IE] [7.68 Mcps TDD *HS-PDSCH Timeslot Specific Information Response* IE] in the *HS-DSCH Information Response* IE in the RADIO LINK SETUP RESPONSE message.]
- [FDD The DRNC shall include the *HS-PDSCH And HS-SCCH Scrambling Code* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK SETUP RESPONSE message.]
- [FDD If the RADIO LINK SETUP REQUEST message includes the HARQ Preamble Mode IE in the HS-DSCH Information IE, then the DRNS shall use the indicated HARQ Preamble Mode as described in TS 25.214 [10], if HS-DPCCH ACK/NACK preamble and postamble is supported. Then, in this case, if the mode 1 is applied, the DRNC shall include the HARQ Preamble Mode Activation Indicator IE in the HS-DSCH Information Response IE in the RADIO LINK SETUP RESPONSE message. If the HARQ Preamble Mode IE is not included or if the mode 0 is applied, then the DRNC shall not include the HARQ Preamble Mode Activation Indicator IE in the RADIO LINK SETUP RESPONSE message.]
- If the RADIO LINK SETUP REQUEST message includes the *HS-DSCH MAC-d PDU Size Format* IE in the *HS-DSCH Information* IE, then the DRNS shall use the indicated format in user plane frame structure for HS-DSCH channels (TS 25.425 [32]) and MAC-hs (TS 25.321 [41]).
- [FDD If the *TNL QoS* IE is included for a MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink between the DRNS and the SRNC for the related MAC-d flow.]
- [FDD If the Serving Cell Change CFN IE is included in the RADIO LINK SETUP REQUEST message, then the DRNS shall activate the resources that are allocated for the new serving HS-DSCH Radio Link at the next coming CFN with a value equal to the value requested by the SRNC.]
- [FDD If the MIMO Activation Indicator IE is included in the HS-DSCH FDD Information IE, then]
 - [FDD The DRNS shall activate the MIMO mode for the HS-DSCH Radio Link.]
 - [FDD The DRNS shall decide the pilot configuration and the UE reporting configuration (N/M ratio) according to TS 25.214 [10] for MIMO and include the *MIMO Information Response* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK SETUP RESPONSE message.]
 - [FDD If the *Power Offset For S-CPICH for MIMO Request Indicator* IE is included, the DRNC shall, if supported and MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where the Serving HS-DSCH Radio Link is established, include the *Power Offset For S-CPICH for MIMO* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK SETUP RESPONSE message. If zero power offset the DRNC may include the *Power Offset For S-CPICH for MIMO* IE.]
- [1.28 Mcps TDD If the MIMO Activation Indicator IE is included in the HS-DSCH TDD Information IE, then]
 - [1.28 Mcps TDD The DRNS shall activate the MIMO mode for the HS-DSCH Radio Link.]

- [1.28 Mcps TDD The DRNS shall decide the SF mode for HS-PDSCH dual stream and include the *MIMO SF Mode for HS-PDSCH dual stream* IE in the *HS-DSCH TDD Information Response* IE in the RADIO LINK SETUP RESPONSE message.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Information IE, then the DRNS may if the value is set to "allowed" use 64 QAM for the HS-DSCH Radio Link, and the DRNS shall include the SixtyfourQAM DL Usage Indicator IE in the HS-DSCH FDD Information Response IE in the RADIO LINK SETUP RESPONSE message.]
- [FDD If the *Sixtyfour QAM Usage Allowed Indicator* IE is included in the *HS-DSCH FDD Information* IE with value set to "not allowed", then the DRNS shall not use 64 QAM for the HS-DSCH Radio Link.]
- [FDD If the RADIO LINK SETUP REQUEST message includes the HS-DSCH MAC-d PDU Size Format IE set to "Flexible MAC-d PDU Size" and if Sixtyfour QAM will not be used, the DRNS shall include the HS-DSCH TB Size Table Indicator IE in the RADIO LINK SETUP RESPONSE message if it decides to use the octet aligned table defined in TS 25.321 [41] for HS-DSCH Transport Block Size signalling.]
- [FDD If the *UE with enhanced HS-SCCH support indicator* IE is included in the *HS-DSCH FDD Information* IE, then the DRNS may use:]
 - [FDD a different HS-SCCH in consecutive TTIs for this UE]
 - [FDD HS-SCCH orders for the case of HS-SCCH-less operation to this UE]
- [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH FDD Information* IE the DRNS may use the supported HSDPA functions for this UE.]
- [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH FDD Information* IE with the bit *UE DTXDRX related HS-SCCH orders uniform behavior indicator* set to 0, then the DRNS shall, if supported, include the *Support of dynamic DTXDRX related HS-SCCH order* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK SETUP RESPONSE message.]
- [FDD The DRNS shall include the *SixtyfourQAM DL Support Indicator* IE in the RADIO LINK SETUP RESPONSE message. This *SixtyfourQAM DL Support Indicator* IE is related to the HS-DSCH Radio Link.]
- [1.28 Mcps TDD The DRNS shall include the *SixtyfourQAM DL Support Indicator* IE in the RADIO LINK SETUP RESPONSE message.]
- If the RADIO LINK SETUP REQUEST message includes the *DL RLC PDU Size Format* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, the *DL RLC PDU Size Format* IE may be used by the DRNS to determine the allocated capacity on user plane as described in TS 25.425 [32].
- [FDD If the RADIO LINK SETUP REQUEST message includes the *UE Aggregate Maximum Bit Rate Enforcement Indicator* IE in the *Priority Queue Information* IE in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, the DRNS shall, if supported, consider the data of the related HSDPA Priority Queue for UE Aggregate Maximum Bit Rate Enforcement.]
- [FDD If the *Single Stream MIMO Activation Indicator* IE is included in the *HS-DSCH FDD Information* IE, then the DRNS shall activate the Single Stream MIMO for the HS-DSCH Radio Link.]
- [1.28 Mcps TDD If the *UE TSO Capability LCR* IE is included in the *HS-DSCH TDD Information* IE, then the DRNC may include the *TSO HS-PDSCH Indication LCR* IE in the RADIO LINK SETUP RESPONSE message if HS-PDSCH resources could be allocated on TS0 for the UE.]

[FDD – Secondary Serving HS-DSCH:]

[FDD – If the *Additional HS Cell Information RL Setup* IE is present in the RADIO LINK SETUP REQUEST message, then:]

- [FDD The DRNS shall setup the requested HS-PDSCH resources on the Serving HS-DSCH Radio Link indicated by the *HS-PDSCH RL ID* IE. Non cell specific secondary serving Radio Link and non cell specific secondary serving HS-DSCH parameters take the same values as for the serving HS-DSCH cell.]
- [FDD The DRNC shall allocate an HS-DSCH-RNTI to the UE Context and include the *HS-DSCH-RNTI* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK SETUP RESPONSE message.]
- [FDD If the RADIO LINK SETUP REQUEST message includes the *HS-SCCH Power Offset* IE in the *HS-DSCH Secondary Serving Information* IE, then the DRNS may use this value to determine the HS-SCCH power. The HS-SCCH Power Offset should be applied for any secondary serving HS-SCCH transmission to this UE.]
- [FDD The DRNC shall include the *Measurement Power Offset* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK SETUP RESPONSE message.]
- [FDD The DRNS shall allocate HS-SCCH codes corresponding to the HS-DSCH and the DRNC shall include the *HS-SCCH Specific Secondary Serving Information Response* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK SETUP RESPONSE message.]
- [FDD The DRNC shall include the *HS-PDSCH And HS-SCCH Scrambling Code* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK SETUP RESPONSE message.]
- [FDD If the *Serving Cell Change CFN* IE is included in the RADIO LINK SETUP REQUEST message, then the DRNS shall activate the resources that are allocated for the new serving HS-DSCH Radio Link at the next coming CFN with a value equal to the value requested by the SRNC.]
- [FDD If the MIMO Activation Indicator IE is included in the HS-DSCH FDD Secondary Serving Information IE, then the DRNS shall activate the MIMO mode for the secondary serving HS-DSCH Radio Link and the DRNS shall decide the pilot configuration and the UE reporting configuration (N/M ratio) according to TS 25.214 [10] for MIMO for the secondary serving HS-DSCH Radio Link and include the MIMO Information Response IE in the HS-DSCH FDD Secondary Serving Information Response IE in the Additional HS Cell Information Response IE in the RADIO LINK SETUP RESPONSE message.]
- [FDD If the *Power Offset For S-CPICH for MIMO Request Indicator* IE is included, the DRNC shall, if supported and MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where the Secondary Serving HS-DSCH Radio Link is established, include the *Power Offset For S-CPICH for MIMO* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the RADIO LINK SETUP RESPONSE message. If zero power offset the DRNC may include the *Power Offset For S-CPICH for MIMO* IE.]
- [FDD If the *Single Stream MIMO Activation Indicator* IE is included in the *HS-DSCH FDD Secondary Serving Information* IE, then the DRNS shall activate the Single Stream MIMO mode for the secondary serving HS-DSCH Radio Link.]
- [FDD If the *Ordinal Number Of Frequency* IE is included in the *HS-DSCH FDD Secondary Serving Information* IE, and more than one secondary serving HS-DSCH Radio Link is setup, then the DRNS shall use this value in the physical layer.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Secondary Serving Information IE, then the DRNS may if the value is set to "allowed" use 64 QAM for the secondary serving HS-DSCH Radio Link, and the DRNS shall include the SixtyfourQAM DL Usage Indicator IE in the HS-DSCH FDD Secondary Serving Information Response IE in the Additional HS Cell Information Response IE in the RADIO LINK SETUP RESPONSE message.]
- [FDD If the *Sixtyfour QAM Usage Allowed Indicator* IE is included in the *HS-DSCH FDD Secondary Serving Information* IE with value set to "not allowed", then the DRNS shall not use 64 QAM for the secondary serving HS-DSCH Radio Link.]

- [FDD If Sixtyfour QAM will not be used for the secondary serving HS-DCSH, the DRNS shall include the HS-DSCH TB Size Table Indicator IE in the HS-DSCH FDD Secondary Serving Information Response IE in the Additional HS Cell Information Response IE in the RADIO LINK SETUP RESPONSE message if it decides to use the octet aligned table defined in TS 25.321 [41] for the secondary serving HS-DSCH Transport Block Size signalling.]
- [FDD The DRNS shall include the *SixtyfourQAM DL Support Indicator* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK SETUP RESPONSE message.]

[FDD – E-DCH:]

[FDD – If the *E-TFCS Information* IE in the *E-DPCH Information* IE contains the *E-DCH Minimum Set E-TFCI Validity Indicator* IE the DRNS shall ignore the value in *E-DCH Minimum Set E-TFCI* IE. If the *E-DCH Minimum Set E-TFCI validity indicator* IE is absent DRNS shall use the value for the related resource allocation operation.]

[FDD – If the *E-TFCS Information IE in the E-DPCH Information* IE contains the *E-DPDCH Power Interpolation* IE, the DRNS shall use the value to determine the applicable E-DPDCH power formula defined in TS 25.214 [10]. If the *E-DPDCH Power Interpolation* IE is not present, the DRNS shall use the E-DPDCH power extrapolation formula defined in TS 25.214 [10].]

[FDD – If the *E-TFCS Information* IE in the *E-DPCH Information* IE contains the *E-TFCI Boost Information* IE, the DRNS shall use the information according to TS 25.214 [10]. If the *E-TFCI Boost Information* IE is not present, the DRNS shall use the value "127" in the algorithm defined in TS 25.214 [10].]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *E-DPCH Information* IE, which contains the *Minimum Reduced E-DPDCH Gain Factor* IE, then the DRNS shall use the value to determine the applicable minimum gain factor ($\beta_{ed,k,reduced,min}$) defined in TS 25.214 [10]. For the case the *Minimum Reduced E-DPDCH Gain Factor* IE is not available for the UE Context, the DRNS may use the default value defined in TS 25.331 [16].]

[FDD – If the *E-DCH FDD Information* IE is present in the RADIO LINK SETUP REQUEST message then:]

- [FDD The DRNS shall setup the requested E-DCH resources on the Radio Links indicated by the *E-DCH RL Indication* IE, set to "E-DCH", in the *RL Information* IE.]
- [FDD If the RADIO LINK SETUP REQUEST message includes the *HARQ Process Allocation For 2ms Scheduled Transmission Grant* IE, the DRNS shall use this information for the related resource allocation operation.]
- [FDD If the RADIO LINK SETUP REQUEST message includes the Transport Layer Address IE and Binding ID IE in the RL specific E-DCH Information IE for an E-DCH MAC-d flow, then if the Transport Bearer Not Requested Indicator IE is not included for this E-DCH MAC-d flow, the DRNC may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for the concerned E-DCH MAC-d flow. The DRNC shall include in the RADIO LINK SETUP RESPONSE message the Binding ID IE and Transport Layer Address IE for establishment of a transport bearer for every E-DCH MAC-d flow being established for which the Transport Bearer Not Requested Indicator IE was not included.]
- [FDD If the RADIO LINK SETUP REQUEST message includes the *Transport Bearer Not Requested Indicator* IE set to "Transport Bearer shall not be Established" for an E-DCH MAC-d flow, then the DRNC shall not establish a transport bearer for the concerned E-DCH MAC-d flow and shall include the *Transport Bearer Not Setup Indicator* IE for the corresponding E-DCH MAC-d flow in the RADIO LINK SETUP RESPONSE message.]
- [FDD If the RADIO LINK SETUP REQUEST message includes the *Transport Bearer Not Requested Indicator* IE set to "Transport Bearer may not be Established" for an E-DCH MAC-d flow and:]
 - [FDD if the DRNC establishes a transport bearer for the concerned E-DCH MAC-d flow, the
 DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Binding ID* IE and
 Transport Layer Address IE for establishment of a transport bearer for the E-DCH MAC-d flow
 being established.]

- [FDD if the DRNC does not establish a transport bearer for the concerned E-DCH MAC-d flow, the DRNC shall include the *Transport Bearer Not Setup Indicator* IE for the corresponding E-DCH MAC-d flow in the RADIO LINK SETUP RESPONSE message.]
- [FDD The DRNS may use the *Traffic Class* IE for a specific E-DCH MAC-d flow to determine the transport bearer characteristics to apply between DRNC and Node B. If *TrCH Source Statistics Descriptor* IE is present with the value "RRC" in the *E-DCH MAC-d Flows Information* IE, then the DRNC should ignore the *Traffic Class* IE.]
- [FDD If the RADIO LINK SETUP REQUEST message includes the *MAC-es Guaranteed Bit Rate* IE in the *E-DCH Logical Channel Information* IE in the *E-DCH MAC-d Flow Specific Information* IE in the *E-DCH FDD Information* IE, then the DRNS shall use this information to optimise MAC-e scheduling decisions.]
- [FDD If the RADIO LINK SETUP REQUEST message includes UE Aggregate Maximum Bit Rate
 Enforcement Indicator IE in the E-DCH Logical Channel Information IE in the E-DCH MAC-d Flow
 Specific Information IE in the E-DCH FDD Information IE, the DRNS shall, if supported, consider
 the data of the related E-DCH Logical Channel for UE Aggregate Maximum Bit Rate Enforcement.]
- [FDD If the RADIO LINK SETUP REQUEST message includes the *Maximum MAC-d PDU Size Extended* IE for a E-DCH Logical Channel in the *E-DCH MAC-d Flows Information* IE in the *E-DCH FDD Information* IE, then the DRNS shall ignore the *MAC-d PDU Size* IE in the *MAC-d PDU Size List* IE and use *Maximum MAC-d PDU Size Extended* IE to optimise capacity allocation for the related E-DCH Logical Channel and use the indicated format in user plane frame structure for E-DCH channels (TS 25.425 [32]) and MAC (TS 25.321 [41]).]
- [FDD If the RADIO LINK SETUP REQUEST message includes the *E-DCH MAC-d Flow Multiplexing List* IE for an E-DCH MAC-d flow the DRNS shall use this information for the related resource allocation operation.]
- [FDD If in the RADIO LINK SETUP REQUEST message the E-DCH Grant Type is indicated as being "E-DCH Non-Scheduled Transmission Grant" for an E-DCH MAC-d flow the DRNS shall assume non-scheduled grants being configured for that E-DCH MAC-d flow and shall use the information within the HARQ Process Allocation For 2ms Non-Scheduled Transmission Grant IE, if included, for the related resource allocation operation.]
- [FDD If in the RADIO LINK SETUP REQUEST message the E-DCH Grant Type is indicated as being "E-DCH Scheduled Transmission Grant" for an E-DCH MAC-d flow the DRNS shall assume scheduled grants being configured for that E-DCH MAC-d flow.]
- [FDD If the *TNL QoS* IE is included for a E-DCH MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink for the related MAC-d flow.]
- [FDD The DRNC may include the *E-AGCH And E-RGCH/E-HICH FDD Scrambling Code* IE and shall include the *E-RGCH/E-HICH Channelisation Code* IE and the corresponding *E-HICH Signature Sequence IE* and the DRNC may include the corresponding *E-RGCH Signature Sequence* IE in the *E-DCH FDD DL Control Channel Information* IE in the RADIO LINK SETUP RESPONSE message, for every RL indicated by the *E-DCH RL Indication* IE, set to "E-DCH", in the *RL Information* IE.]
 - [FDD If the RADIO LINK SETUP REQUEST message includes the *E-DCH ReferencePower Offset* IE, then the DRNS may use this value as a default HARQ power offset if it is not able to decode the MAC-e PDU and to determine the value of the actual HARQ power offset.]
- [FDD If the RADIO LINK SETUP REQUEST message includes the *E-DCH Power Offset for Scheduling Info* IE, then the DRNS shall use this value as a power offset for the transmission of scheduling information without any MAC-d PDUs.]
- [FDD If the RADIO LINK SETUP REQUEST message contains the *Serving E-DCH RL* IE indicating that the Serving E-DCH RL is in this DRNS:]
 - [FDD The DRNS shall allocate a primary E-RNTI identifier or a secondary E-RNTI identifier or both and include these E-RNTI identifiers and the Channelisation Code of the corresponding E-

AGCH in the *E-DCH FDD DL Control Channel Information* IE in the *RL Information Response* IE for the indicated RL in the RADIO LINK SETUP RESPONSE message.]

- [FDD The DRNS may include the Serving Grant Value IE and Primary/Secondary Grant Selector IE in the RADIO LINK SETUP RESPONSE message for the initial grant for the serving E-DCH RL.]
- [FDD If the E-DCH HARQ process allocation for 2ms TTI for scheduled and/or non-scheduled transmission shall be changed, the DRNS shall allocate resources according to the new/changed configuration and include the new/changed configuration in the *E-DCH FDD Information Response* IE in the RADIO LINK SETUP RESPONSE message.]
- [FDD If a serving cell change is performed the RADIO LINK SETUP RESPONSE message may contain invalid data (see 9.2.2.4C).]
- [FDD If the DRNS has no valid data for the *E-RGCH/E-HICH Channelisation Code* IE in the *E-DCH FDD DL Control Channel Information* IE in the RADIO LINK SETUP RESPONSE message, then it shall insert the *E-RGCH and E-HICH Channelisation Code Validity Indicator* IE in the *E-DCH FDD DL Control Channel Information* IE, to indicate that the *E-RGCH/E-HICH Channelisation Code* IE contains invalid data.]
- [FDD The DRNS may include the *Default Serving Grant in DTX Cycle 2* IE in the RADIO LINK SETUP RESPONSE message for the serving E-DCH RL.]
- [FDD If the RADIO LINK SETUP REQUEST message includes the *Bundling Mode Indicator* IE for a E-DCH MAC-d flow in the *E-DCH MAC-d Flow Specific Information* IE in the *E-DCH FDD Information* IE and the *Bundling Mode Indicator* IE is set to "Bundling" and the *E-TTI* IE is set to "2ms", then the DRNS shall use the bundling mode for the E-DCH UL data frames for the related MAC-d flow, otherwise the DRNS shall use the non-bundling mode for the E-DCH UL data frames for the related MAC-d flow.]
- [FDD If the RADIO LINK SETUP REQUEST message includes the *E-DCH Maximum Bitrate* IE for an E-DCH, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
- [FDD If the RADIO LINK SETUP REQUEST message includes the *E-DCH Processing Overload Level* IE, then if the DRNS could not decode the E-DPCCH/E-DPDCH for the last consecutive number of TTIs, indicated in the *E-DCH Processing Overload Level* IE, because of processing issue, the DRNS shall notify the SRNC by initiating the Radio Link Failure procedure.]
- [FDD If the RADIO LINK SETUP REQUEST message includes the *E-AGCH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-AGCH power. The E-AGCH Power Offset should be applied for any E-AGCH transmission to this UE.]
- [FDD If the RADIO LINK SETUP REQUEST message includes the *E-RGCH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-RGCH power for the RL. The E-RGCH Power Offset should be applied for any E-RGCH transmission to this UE.]
- [FDD If the RADIO LINK SETUP REQUEST message includes the *E-HICH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-HICH power for the RL. The E-HICH Power Offset should be applied for any E-HICH transmission to this UE.]
- [FDD If the *Serving Cell Change CFN* IE is included in the RADIO LINK SETUP REQUEST message, then the DRNS shall activate the resources that are allocated for the new serving E-DCH Radio Link at the next coming CFN with a value equal to the value requested by the SRNC.]
- [FDD If the RADIO LINK SETUP REQUEST message includes the *SixteenQAM UL Operation Indicator* IE, the DRNS shall activate/deactivate SixteenQAM UL Operation for the RL in accordance with the *SixteenQAM UL Operation Indicator* IE.]
 - [FDD If SixteenQAM UL Operation is activated, then the DRNS shall base the handling of the Relative Grant signalling on Scheduling Grant Table 2 according to TS 25.321 [41]. If

SixteenQAM UL Operation is deactivated, then the DRNS shall base the handling of the Relative Grant signalling on Scheduling Grant Table 1 according to TS 25.321 [41].]

[FDD – Additional E-DCH Setup:]

[FDD – If the *Additional E-DCH Cell Information RL Setup Req* IE is present in the RADIO LINK SETUP REQUEST message, then the *Additional E-DCH Cell Information Setup* IE defines the new configuration and then:]

- [FDD The DRNS shall setup the E-DCH on the secondary uplink frequency and setup the requested E-DCH resources on the Radio Links and in the cells indicated by the *E-DCH Additional RL ID* IE and the *C-ID* IE in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE in the *Additional E-DCH Cell Information Setup* IE. Non cell specific Radio Link related parameters and non cell specific E-DPCH, UL DPCH, E-DCH and F-DPCH parameters shall take the same values as for the corresponding cell of the Primary uplink frequency.]
- [FDD If the *UL SIR Target* IE in the *UL DPCH Information* IE in the *Additional E-DCH FDD Setup Information* IE in the *Additional E-DCH Cell Information Setup* IE and/or the *DL Power Balancing Information* IE and/or the *Minimum Reduced E-DPDCH Gain Factor* IE in the *Multicell E-DCH Information* IE in the *Additional E-DCH FDD Setup Information* IE are present, the DRNS shall use the information in the same same way as for the information used on Primary uplink frequency.]
- [FDD If the Secondary UL Frequency Activation State IE is present in the Multicell E-DCH Information IE in the Additional E-DCH FDD Setup Information IE, the DRNS shall use the information as initial activation state of the Radio Links on the secondary uplink frequency.]
- [FDD If the *Propagation Delay* IE, the *Initial DL Tx Power* IE, *Primary CPICH Ec/No* IE, the *E-AGCH Power Offset* IE, the *E-RGCH Power Offset* IE and/or the *E-HICH Power Offset* IE is included in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE in the *Additional E-DCH Cell Information Setup* IE, the DRNS shall use the information in the same way as for the information used on Primary uplink frequency.]
- [FDD If the Extended Propagation Delay IE and/or Enhanced Primary CPICH Ec/No IE is included in the Multicell E-DCH RL Specific Information IE in the Additional E-DCH Secondary RL Specific Information To Setup IE in the Additional E-DCH FDD Setup Information IE in the Additional E-DCH Cell Information Setup IE, the DRNS shall use the information in the same way as for the information used on Primary uplink frequency.]
- [FDD If the *F-DPCH Slot Format Support Request* IE in the *F-DPCH Information* IE in the *Additional E-DCH FDD Setup Information* IE in the *Additional E-DCH Cell Information Setup* IE is included, the DRNS shall configure the concerned UE Context for F-DPCH Slot Format operation according to TS 25.211 [8] and include the *F-DPCH Slot Format* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Respone* IE in the RADIO LINK SETUP RESPONSE message. If the *Multicell E-DCH Information* IE in the *Additional E-DCH FDD Setup Information* IE includes the *F-DPCH Slot Format* IE, the DRNS may use the *F-DPCH Slot Format* IE to determine the F-DPCH slot format.]
- [FDD If the HARQ Process Allocation For 2ms Scheduled Transmission Grant IE, the E-DCH Maximum Bitrate IE, the E-DCH Minimum Set E-TFCI IE and/or the E-DCH Processing Overload Level IE are present in the Additional E-DCH FDD Information IE in the Additional E-DCH FDD Setup Information IE in the Additional E-DCH Cell Information Setup IE, the DRNS shall use the information in same way as for the information used on Primary uplink frequency.]
- [FDD If the *Multicell E-DCH Transport Bearer Mode* IE for an Additional E-DCH to be Setup is set to "Separate Iur Transport Bearer Mode" the DRNS shall use this mode in the new configuration and apply separate transport bearers for the MAC-d flows.]
- [FDD if the *Multicell E-DCH Transport Bearer Mode* IE for an Additional E-DCH to be Setup is set to "UL Flow Multiplexing Mode" the DRNS shall use this mode in the new configuration and multiplex MAC-d flows on the transport bearers.]
- [FDD if Separate Iur Transport Bearer Mode is used in the new configuration, then:]

- [FDD The DRNS shall follow the rules defined in this procedure for single carrier mode of operation for establishment of the transport bearer for a MAC-d flow and use the *Transport Bearer Not Requested Indicator* IE in the *RL Specific E-DCH Information* IE in the *RL Information* IE received for the corresponding Radio Link(s) of the Primary Uplink Frequency to determine the transport bearer configuration in the new configuration for the radio links of the Secondary Uplink Frequency.]
- [FDD If the Transport Layer Address IE and Binding ID IE is included for an E-DCH MAC-d flow in the Additional E-DCH MAC-d Flows Specific Information IE in the Additional E-DCH RL Specific Information To Setup IE in the Additional E-DCH FDD Setup Information IE in the Additional E-DCH Cell Information Setup IE, then the DRNS may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for the concerned E-DCH MAC-d flow. If the DRNS establishes a transport bearer for the concerned E-DCH MAC-d flow the DRNS shall include in the RADIO LINK SETUP RESPONSE message the Binding ID IE and Transport Layer Address IE in the Additional E-DCH MAC-d Flow Specific Information Response IE in the Additional E-DCH Cell Information Response IE in the Additional E-DCH Cell Information Response IE for establishment of a transport bearer for every E-DCH MAC-d flow being established.]
- [FDD If activation of power balancing for the Additional E-DCH RL by the RADIO LINK SETUP REQUEST message is supported by the DRNS, the DRNS shall include the *DL Power Balancing Activation Indicator* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response* IE in the RADIO LINK SETUP RESPONSE message.]
- [FDD For each Additional E-DCH RL not having a common generation of the TPC commands in the DL with another Additional E-DCH RL, the DRNS shall set the *RL Set ID* IE included in the *Additional E-DCH FDD Information Response* IE in the RADIO LINK SETUP RESPONSE message to a value that uniquely identifies the RL as a RL Set within the UE Context. The generation of E-HICH related information for Additional E-DCH RLs in different RL Sets shall not be common.]
- [FDD For all Additional E-DCH RLs having a common generation of the TPC commands in the DL with another Additional E-DCH RL, the DRNS shall assign to each Additional E-DCH RL the same value for the *RL Set ID* IE included in the *Additional E-DCH FDD Information Response* IE in the RADIO LINK SETUP RESPONSE message. This value shall uniquely identify these Additional E-DCH RLs as members of the same RL Set within the UE Context. The generation of E-HICH information for all Additional E-DCH RLs in a RL Set shall be common.]
- [FDD For each Additional E-DCH RL which has or can have a common generation of E-RGCH information with another Additional E-DCH RL (current or future) when the DRNS would contain the Additional E-DCH serving RL, the DRNS shall set a same value to the *E-DCH RL Set ID* IE for the Additional E-DCH RL in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response* IE in the RADIO LINK SETUP RESPONSE message]
- [FDD For every additional E-DCH RL indicated in the Additional E-DCH RL Specific Information To Setup IE in the Additional E-DCH FDD Setup Information IE the DRNS may include the E-AGCH And E-RGCH/E-HICH FDD Scrambling Code IE and shall include the E-RGCH/E-HICH Channelisation Code IE and the corresponding E-HICH Signature Sequence IE and the DRNS may include the corresponding E-RGCH Signature Sequence IE for each Additional E-DCH RL in the E-DCH FDD DL Control Channel Information IE in the Additional E-DCH FDD Information Response IE in the Additional E-DCH Cell Information Response IE in the RADIO LINK SETUP RESPONSE message and if DRNS has no valid data for the E-RGCH/E-HICH Channelisation Code IE, then it shall insert the E-RGCH and E-HICH Channelisation Code Validity Indicator IE to indicate that the E-RGCH/E-HICH Channelisation Code IE contains invalid data.]
- [FDD If the Additional Serving E-DCH Radio Link is configured in the DRNS, then:]
 - [FDD The DRNS shall allocate a primary E-RNTI identifier or a secondary E-RNTI identifier or both for the corresponding RL and include these E-RNTI identifiers and the channelisation code of the corresponding E-AGCH in the E-DCH FDD DL Control Channel Information IE in the Additional E-DCH FDD Information Response IE in the Additional E-DCH Cell Information Response IE in the RADIO LINK SETUP RESPONSE message.]
 - [FDD The DRNS may include in the *E-DCH FDD DL Control Channel Information* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information*

Response IE in the RADIO LINK SETUP RESPONSE message the Serving Grant Value IE and Primary/Secondary Grant Selector IE for the initial grant for the Additional serving E-DCH RL and may include the Default Serving Grant in DTX Cycle 2 IE.]

- [FDD If the E-DCH HARQ process allocation for 2ms TTI for scheduled transmission shall be changed, the DRNS shall allocate resources according to the new/changed configuration and include the new/changed configuration in the *HARQ Process Allocation For 2ms Scheduled Transmission Grant* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response* IE in the RADIO LINK SETUP RESPONSE message.]
- [FDD If the Serving Cell Change CFN IE is included in the RADIO LINK SETUP REQUEST message, then the DRNS shall activate the resources that are allocated for the new additional serving E-DCH Radio Link at the next coming CFN with a value equal to the value requested by the SRNC. If the Serving Cell Change CFN IE is not included then the DRNS shall activate immediately the resources that are allocated for the new additional serving E-DCH Radio Link]
- [FDD If the *D-RNTI* IE was included in the RADIO LINK SETUP REQUEST message the DRNS shall include in the RADIO LINK SETUP RESPONSE message the *Primary Scrambling Code* IE, the *UL UARFCN* IE and the *DL UARFCN* IE for the secondary UL frequency in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response* IE in the RADIO LINK SETUP RESPONSE message.]
- [FDD If Primary CPICH is not to be used as a Phase Reference for this Radio Link on the secondary UL frequency, the DRNS shall include the *Primary CPICH Usage For Channel Estimation* IE set to the value "Primary CPICH shall not be used" in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response* IE RADIO LINK SETUP RESPONSE message.]
- [FDD If Secondary CPICH may be used as a Phase Reference for this Radio Link on the secondary UL frequency, the DRNS shall include the *Secondary CPICH Information* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response* IE in the RADIO LINK SETUP RESPONSE message. If the DRNS doesn't include the *Secondary CPICH Information* IE, it shall not include the *Primary CPICH Usage For Channel Estimation* IE set to the value "Primary CPICH shall not be used".]

[FDD - E-DCH -HS-DSCH:]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *DCH Indicator For E-DCH-HSDPA Operation* IE, then the DRNS shall ignore the *DCH Information* IE in the RADIO LINK SETUP REQUEST message.]

[1.28 Mcps TDD - Multi-Carrier E-DCH Setup:]

[1.28Mcps TDD - If the *Multi-Carrier E-DCH Information* IE is present in the RADIO LINK SETUP REQUEST message, then the *Multi-Carrier E-DCH Information* IE defines the new configuration and then:]

- [1.28Mcps TDD The DRNS shall setup the requested E-DCH resource on the uplink frequecies indicated by the *UARFCN* IE in the *Multi-Carrier E-DCH Information LCR* IE.]
- [1.28Mcps TDD The DRNS shall use the corresponding *PRXdes_base* IE for power control on each uplink frequency according to TS 25.331 [16].]
- [1.28Mcps TDD If the *SNPL Carrier Group Indicator* IE is present in the *Multi-Carrier E-DCH Information LCR* IE, the DRNS shall use the information to determine which SNPL Carrier Group each frequency indicated by the *UARFCN* IE belongs to.]
- [1.28Mcps TDD If the *Multi-Carrier E-DCH Transport Bearer Mode LCR* IE is set to "Separate Iur transport bearer mode", the DRNS shall use this mode in the new configuration and apply separate transport bearers for the MAC-d flows.]
- [1.28Mcps TDD If the *Multi-Carrier E-DCH Transport Bearer Mode LCR* IE is set to "E-DCH UL flow multiplexing mode", the DRNS shall use this mode in the new configuration and multiplex MAC-d flow received on the different carriers on one Iur transport bearer.]
- [1.28Mcps TDD If the Separate Iur transport bearer mode is used in the new configuration, then the DRNS shall include the *Binding ID* IE and *Transport Layer Address* IE in the *Multi-Carrier E-DCH*

Information Response LCR IE in the RADIO LINK SETUP RESPONSE message for establishment of a transport bearer for every E-DCH MAC-d flow being established.]

- [1.28Mcps TDD - If the E-DCH UL flow multiplexing mode is used in the new configuration, then the DRNS shall include the *Binding ID* IE and *Transport Layer Address* IE in the *E-DCH TDD Information Response* 1.28Mcps IE in the RADIO LINK SETUP RESPONSE message for establishment of a transport bearer for every E-DCH MAC-d flow being established.]

Physical Channels Handling:

[FDD - Compressed Mode:]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *Transmission Gap Pattern Sequence Information* IE, the DRNS shall store the information about the Transmission Gap Pattern Sequences to be used in the Compressed Mode Configuration. This Compressed Mode Configuration shall be valid in the DRNS until the next Compressed Mode Configuration is configured in the DRNS or the last Radio Link is deleted.]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *Transmission Gap Pattern Sequence Information* IE and the *Active Pattern Sequence Information* IE, the DRNS shall use the information to activate the indicated Transmission Gap Pattern Sequence(s) in the new RL. The received *CM Configuration Change CFN* IE refers to latest passed CFN with that value. The DRNS shall treat the received *TGCFN* IEs as follows:]

- [FDD If any received *TGCFN* IE has the same value as the received *CM Configuration Change CFN* IE, the DRNS shall consider the concerned Transmission Gap Pattern Sequence as activated at that CFN.]
- [FDD If any received *TGCFN* IE does not have the same value as the received *CM Configuration Change CFN* IE but the first CFN after the CM Configuration Change CFN with a value equal to the *TGCFN* IE has already passed, the DRNS shall consider the concerned Transmission Gap Pattern Sequence as activated at that CFN.]
- [FDD For all other Transmission Gap Pattern Sequences included in the *Active Pattern Sequence Information* IE, the DRNS shall activate each Transmission Gap Pattern Sequence at the first CFN after the CM Configuration Change CFN with a value equal to the *TGCFN* IE for the Transmission Gap Pattern Sequence.]

[FDD – If the *Downlink Compressed Mode Method* IE in one or more Transmission Gap Pattern Sequence is set to "SF/2" in the RADIO LINK SETUP REQUEST message and the UE Context is configured to use DPCH in the downlink, the DRNS shall include the *Transmission Gap Pattern Sequence Scrambling Code Information* IE in the RADIO LINK SETUP RESPONSE message indicating for each DL Channelisation Code whether the alternative scrambling code shall be used or not.]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *Transmission Gap Pattern Sequence Information* IE and the *Active Pattern Sequence Information* IE and the concerned UE Context is configured to use F-DPCH in the downlink, the DRNS shall ignore, when activating the Transmission Gap Pattern Sequence(s), the information provided by the *Downlink Compressed Mode Method* IE if included for the concerned Transmission Gap Pattern Sequence(s).]

[FDD - If the RADIO LINK SETUP REQUEST message includes the *Affected HS-DSCH serving cell List* IE in the *Active Pattern Sequence Information* IE, the concerned Transmission Gap Pattern Sequence shall be applied to HS-DSCH serving cells associated with *C-ID* IE included in *Affected HS-DSCH serving cell List* IE. Otherwise the concerned Transmission Gap Pattern Sequence shall be applied to all the configured serving cells.]

[FDD – DL Code Information:]

[FDD – When more than one DL DPDCH are assigned per RL, the segmented physical channel shall be mapped on to DL DPDCHs according to TS 25.211 [8]. When *p* number of DL DPDCHs are assigned to each RL, the first pair of DL Scrambling Code and FDD DL Channelisation Code Number corresponds to "*PhCH number 1*", the second to "*PhCH number 2*", and so on until the *p*th to "*PhCH number p*".]

[FDD - Phase Reference Handling:]

[FDD – If Primary CPICH is not to be used as a Phase Reference for this Radio Link, the DRNC shall include the *Primary CPICH Usage For Channel Estimation* IE set to the value "Primary CPICH shall not be used" in the RADIO LINK SETUP RESPONSE message.]

[FDD – If Secondary CPICH may be used as a Phase Reference for this Radio Link, the DRNC shall include the *Secondary CPICH Information* IE in the RADIO LINK SETUP RESPONSE message.]

[FDD – If the DRNC doesn't include the *Secondary CPICH Information* IE in the RADIO LINK SETUP RESPONSE message, it shall not include the *Primary CPICH Usage For Channel Estimation* IE set to the value "Primary CPICH shall not be used" in the RADIO LINK SETUP RESPONSE message.]

General:

[FDD – If the *Propagation Delay* IE and optionally the *Extended Propagation Delay* IE are included, the DRNS may use this information to speed up the detection of UL synchronisation on the Uu interface.]

[FDD – If the received *Limited Power Increase* IE is set to "Used", the DRNS shall, if supported, use Limited Power Increase according to TS 25.214 [10] subclause 5.2.1 for the inner loop DL power control.]

[TDD – If the RADIO LINK SETUP REQUEST message includes the [1.28 Mcps TDD and 3.84 Mcps TDD – *Maximum Number of DL Physical Channels per Timeslot* IE] [7.68 Mcps TDD – *Maximum Number of DL Physical Channels per Timeslot* 7.68 Mcps IE] the DRNC shall take this value into account when allocating physical resources, otherwise the DRNC can assume that this UE capability is consistent with the other signalled UE capabilities.]

[1.28Mcps TDD – If the RADIO LINK SETUP REQUEST message includes the *Support for 8PSK* IE within the *DL Physical Channel Information* IE or *UL Physical Channel Information* IE, the DRNC shall take this into account in the specified direction when allocating physical resources, otherwise the DRNC can assume that this UE does not support 8PSK resource allocation.]

[1.28Mcps TDD – If the RADIO LINK SETUP REQUEST message includes the *Support for PLCCH* IE within the *DL Physical Channel Information* IE, the DRNC shall take this into account when allocating PLCCH sequence numbers, otherwise the DRNC can assume that this UE does not support PLCCH.]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *DL DPCH Information* IE, then the DRNS shall configure the concerned UE Context to use DPCH in the downlink, i.e. with a DL DPCCH and a DL DPDCH.]

[FDD – If the RADIO LINK SETUP REOUEST message includes the F-DPCH Information IE, then:]

- [FDD The DRNS shall configure the concerned UE Context to use F-DPCH in the downlink, i.e. with transmission of only the TPC field.]
- [FDD If the *F-DPCH Information* IE includes the *F-DPCH Slot Format Support Request* IE, then the DRNS shall configure the concerned UE Context for F-DPCH Slot Format operation according to TS 25.211 [8] and include the *F-DPCH Slot Format* IE in the RADIO LINK SETUP RESPONSE message. If the *F-DPCH Information* IE includes the *F-DPCH Slot Format* IE, the DRNC may use the *F-DPCH Slot Format* IE to determine the F-DPCH slot format.]

[FDD – E-DPCH Handling:]

[FDD – If the *UL DPDCH Indicator for E-DCH operation* IE is included in the *UL DPCH Information* IE and set to "UL-DPDCH not present" the *Min UL Channelisation Code Length* IE, the *Puncture Limit* IE and the *TFCS* IE, within the *UL DPCH Information* IE shall be ignored and no UL DPDCH resources shall be allocated.]

[FDD - Continuous Packet Connectivity Handling:]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *Continuous Packet Connectivity DTX-DRX Information* IE, then:]

- [FDD – The DRNS shall configure the concerned UE Context for Continuous Packet Connectivity DTX operation according to TS 25.214 [10].]

- [FDD – If *DRX Information* IE is included in the *Continuous Packet Connectivity DTX-DRX Information* IE, then the DRNS shall configure the concerned UE Context for Continuous Packet Connectivity DRX operation according to TS 25.214 [10].]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *Continuous Packet Connectivity HS-SCCH less Information* IE, then:]

- [FDD The DRNS shall configure the Serving HS-DSCH Radio Link indicated by the *HS-PDSCH RL ID* IE for Continuous Packet Connectivity HS-SCCH less operation according to TS 25.214 [10].]
- [FDD The DRNS shall allocate the HS-PDSCH codes needed for HS-SCCH less operation and include the *Continuous Packet Connectivity HS-SCCH less Information Response* IE in the RADIO LINK SETUP RESPONSE message.]
- [FDD If at least one of *HS-PDSCH Second Code Support* IE is set to "True", then the DRNC shall include *HS-PDSCH Second Code Index* IE in the RADIO LINK SETUP RESPONSE message.]

[1.28 Mcps TDD – Continuous Packet Connectivity Handling:]

[1.28 Mcps TDD – If the RADIO LINK SETUP REQUEST message includes the *Continuous Packet Connectivity DRX Information LCR* IE, then the DRNS shall take account into these parameters to decide the DRX operation related parameters and configure the concerned UE Context for DRX operation according to TS 25.224 [22] and include the parameter(s) in the *Continuous Packet Connectivity DRX Information Response LCR* IE in the RADIO LINK SETUP RESPONSE message.]

[1.28 Mcps TDD – If the *Inactivity Threshold for UE DRX Cycle Ext* IE is included in the *Continuous Packet Connectivity DRX Information LCR* IE, then the DRNS may use this value to determine the Inactivity Threshold for UE DRX Cycle according to TS 25.224 [22].]

[1.28 Mcps TDD – If the RADIO LINK SETUP REQUEST message includes the *HS-DSCH Semi-Persistent scheduling Information LCR* IE, then:]

- [1.28 Mcps TDD The DRNS shall configure the Serving HS-DSCH Radio Link indicated by the *HS-PDSCH RL ID* IE for HS-DSCH Semi-Persistent scheduling operation according to TS 25.224 [22].]
- [1.28 Mcps TDD The DRNS shall allocate the HS-SICH information needed for HS-DSCH Semi-Persistent scheduling operation and include the HS-DSCH Semi-Persistent scheduling Information Response LCR IE in the RADIO LINK SETUP RESPONSE message.]
- [1.28 Mcps TDD If the *HS-DSCH Semi-Persistent Resource Reservation Indicator* IE is included in the *HS-DSCH Semi-Persistent scheduling Information LCR* IE, then the DRNS shall include *Allcoated HS-PDSCH Semi-persistent resource* IE in the RADIO LINK SETUP RESPONSE message.]
- [1.28 Mcps TDD The DRNS shall include the *Buffer Size for HS-DSCH Semi-Persistent scheduling* IE in the RADIO LINK SETUP RESPONSE message.]
- [1.28 Mcps TDD The DRNS shall include the *Number of Processes for HS-DSCH Semi-Persistent scheduling* IE in the RADIO LINK SETUP RESPONSE message.]
- [1.28 Mcps TDD If the HS-DSCH Semi-Persistent scheduling operation Indicator IE is included in the HS-DSCH Semi-Persistent scheduling Information LCR IE, then the DRNS shall apply this information for HS-DSCH Semi-Persistent scheduling operation.]

[1.28 Mcps TDD – If the RADIO LINK SETUP REQUEST message includes the *E-DCH Semi-Persistent scheduling Information LCR* IE, then:]

- [1.28 Mcps TDD The DRNS shall configure the Serving E-DCH Radio Link indicated by the *E-DCH Serving RL* IE for E-DCH Semi-Persistent scheduling operation according to TS 25.224 [22].]
- [1.28 Mcps TDD If the *E-DCH Semi-Persistent Resource Reservation Indicator* IE is included in the *E-DCH Semi-Persistent scheduling Information LCR* IE, then the DRNS shall include *Allcoated E-DCH Semi-persistent resource* IE in the RADIO LINK SETUP RESPONSE message.]
- [1.28 Mcps TDD If the *E-DCH Semi-Persistent scheduling Indicator* IE is included in the *E-DCH Semi-Persistent scheduling Information LCR* IE, then the DRNS shall apply this information for E-DCH Semi-Persistent scheduling operation.]

[1.28 Mcps TDD - MU-MIMO Handling:]

[1.28Mcps TDD - If the RADIO LINK SETUP REQUEST message includes the *MU-MIMO Indicator* IE, then:]

- [1.28 Mcps TDD The DRNS may use the MU-MIMO for the radio link according to the MU-MIMO Usage Indicator IE and shall include the MU-MIMO Information IE in the RADIO LINK SETUP RESPONSE message.]
- [1.28 Mcps TDD If the Standalone Midamble Channel Indicator IE is set to "Used", then the DRNS shall include Standalone Midamble Channel information in the RADIO LINK SETUP RESPONSE message. Else, the DRNS shall not include Standalone Midamble Channel information in the RADIO LINK SETUP RESPONSE message.]

Radio Link Handling:

Diversity Combination Control:

[FDD – The *Diversity Control Field* IE indicates for each RL except for the first RL whether the DRNS shall combine the RL with any of the other RLs or not.]

- [FDD If the *Diversity Control Field* IE is set to "May" (be combined with another RL), the DRNS shall decide for any of the alternatives.]
- [FDD If the *Diversity Control Field* IE is set to "Must", the DRNS shall combine the RL with one of the other RL.]
- [FDD If the *Diversity Control Field* IE is set to "Must not", the DRNS shall not combine the RL with any other existing RL.]

[FDD – When an RL is to be combined, the DRNS shall choose which RL(s) to combine it with.]

[FDD – The *Diversity Control Field* IE is only applicable for DCHs, in case of E-DCH it shall always be assumed to be set to "May".]

[FDD – In the RADIO LINK SETUP RESPONSE message, the DRNC shall indicate for each RL with the Diversity Indication in the *RL Information Response* IE whether the RL is combined or not.]

- [FDD In case of not combining with a RL previously listed in the RADIO LINK SETUP RESPONSE message or for the first RL in the RADIO LINK SETUP RESPONSE message, the DRNC shall]
 - [FDD in case of requested DCHs, include in the *DCH Information Response* IE in the RADIO LINK SETUP RESPONSE message for which the *Transport Bearer Not Requested Indicator* IE was not included the *Binding ID* IE and *Transport Layer Address* IE for the transport bearer to be established for each DCH of this RL.]
 - [FDD in case of requested DCHs, include in the RADIO LINK SETUP RESPONSE message the *Transport Bearer Not Setup Indicator* IE for every DCH for which establishment of a transport bearer has not taken place as a result of information in the *Transport Bearer Not Requested Indicator* IE in the RADIO LINK SETUP REQUEST message.]
 - [FDD in case of a requested E-DCH, include in the *E-DCH FDD Information Response* IE in the RADIO LINK SETUP RESPONSE for which the *Transport Bearer Not Requested Indicator* IE was not included message the *Binding ID* IE and the *Transport Layer Address* IE for the establishment of transport bearers for every E-DCH MAC-d flow being established.]
 - [FDD in case of a requested E-DCH, include in the RADIO LINK SETUP RESPONSE message the *Transport Bearer Not Setup Indicator* IE for every E-DCH MAC-d flow for which establishment of a transport bearer has not taken place as a result of information in the *Transport Bearer Not Requested Indicator* IE in the RADIO LINK SETUP REQUEST message.]
- [FDD Otherwise in case of combining, the *RL ID* IE indicates (one of) the RL(s) previously listed in this RADIO LINK SETUP RESPONSE message with which the concerned RL is combined and if the ALCAP is not used and the transport bearer for the DCH is already established, the *Transport Layer Address* IE and the *Binding ID* IE in the *RL Specific DCH Information* IE included in the *RL Information* IE for a specific RL in the RADIO LINK SETUP REQUEST message, shall not be used. In case of

combining an E-DCH RL, one of the RLs previously listed in this RADIO LINK SETUP RESPONSE message including the *E-DCH FDD Information Response* IE and part of the same Radio Link Set shall be regarded as the RL with which the concerned E-DCH RL is combined and if the ALCAP is not used, the *Transport Layer Address* IE and the *Binding ID* IE in the *RL SpecificE-DCH Information* IE included in the *RL Information* IE for a specific RL in the RADIO LINK SETUP REQUEST message, shall not be used.]

[TDD – The DRNC shall always include in the RADIO LINK SETUP RESPONSE message both the *Transport Layer Address* IE and the *Binding ID* IE for the transport bearer to be established for each DCH, DSCH and USCH of the RL.]

In the case of a set of co-ordinated DCHs requiring a new transport bearer the *Binding ID* IE and the *Transport Layer Address* IE shall be included in the RADIO LINK SETUP RESPONSE message for only one of the DCHs in the set of co-ordinated DCHs [FDD – where the *Transport Bearer Not Requested Indicator* IE was not included].

[FDD – Transmit Diversity:]

[FDD – If the cell in which the RL is being set up is capable to provide Close loop Tx diversity, the DRNC shall include the *Closed Loop Timing Adjustment Mode* IE in the RADIO LINK SETUP RESPONSE message indicating the configured Closed loop timing adjustment mode of the cell.]

[FDD – When the *Diversity Mode* IE is set to "STTD", or "Closed loop mode1", the DRNC shall activate/deactivate the Transmit Diversity for each Radio Link in accordance with the *Transmit Diversity Indicator* IE.]

[FDD – If the *Diversity Mode* IE is included in the *HS-DSCH FDD Secondary Serving Information* IE in the *Additional HS Cell Information RL Setup* IE in the RADIO LINK SETUP REQUEST message, the DRNS shall apply cell specific transmit diversity configuration and if the *Diversity Mode* IE is not set to "None" the DRNS shall activate/deactivate the Transmit Diversity for the secondary serving HS-DSCH Radio Link in accordance with the *Transmit Diversity Indicator* IE in the *HS-DSCH FDD Secondary Serving Information* IE.]

DL Power Control:

[FDD – If both the *Initial DL TX Power* IE and *Uplink SIR Target* IE are included in the message, the DRNS shall use the indicated DL TX Power and Uplink SIR Target as initial value. If the value of the *Initial DL TX Power* IE is outside the configured DL TX power range, the DRNS shall apply these constraints when setting the initial DL TX power. The DRNS shall also include the configured DL TX power range defined by *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the RADIO LINK SETUP RESPONSE message. The DRNS shall not transmit with a power higher than indicated by the *Maximum DL TX Power* IE or lower than indicated by the *Minimum DL TX Power* IE on any DL DPCH or on the F-DPCH of the RL except, if the UE Context is configured to use DPCH in the downlink, during compressed mode, when the δP_{curr}, as described in TS 25.214 [10] subclause 5.2.1.3, shall be added to the maximum DL power for the associated compressed frame.]

[FDD – If both the *Initial DL TX Power* and the *Uplink SIR Target* IEs are not included in the RADIO LINK SETUP REQUEST message, then DRNC shall determine the initial Uplink SIR Target and include it in the *Uplink SIR Target* IE in the RADIO LINK SETUP RESPONSE message.]

[TDD – The DRNC shall use the *Uplink SIR Target CCTrCH* IEs in the RADIO LINK SETUP RESPONSE message to indicate for any UL CCTrCH an Uplink SIR Target value in case this is deviating from the value included in the *Uplink SIR Target* IE specified for the Radio Link. If in any [3.84Mcps TDD – *UL CCTrCH Information* IE] [1.28Mcps TDD – *UL CCTrCH Information LCR* IE] [7.68Mcps TDD – *UL CCTrCH Information 7.68 Mcps* IE] the *Uplink SIR Target CCTrCH* IE is not included, the value of the *Uplink SIR Target* IE shall apply to the respective UL CCTrCH.]

[FDD – If the *Primary CPICH Ec/No* IE is present, the DRNC should use the indicated value when deciding the Initial DL TX Power. If the *Enhanced Primary CPICH Ec/No* IE is present, the DRNC should use the indicated value when deciding the Initial DL Tx Power.]

[TDD – If [3.84Mcps TDD and 7.68 Mcps TDD – the *DL Time Slot ISCP Info* IE] [1.28Mcps TDD – the *DL Time Slot ISCP Info LCR* IE] is present, the DRNSshould use the indicated value when deciding the Initial DL TX Power for the Radio Link. The DRNS shall use the indicated DL Timeslot ISCP when determining

the initial DL power per timeslot as specified in TS 25.224 [22], i.e. it shall reduce the DL TX power in those downlink timeslots of the radio link where the interference is low, and increase the DL TX power in those timeslots where the interference is high, while keeping the total downlink power in the radio link unchanged.]

[TDD – If the *Primary CCPCH RSCP Delta* IE is included, the DRNS should assume that the reported value for Primary CCPCH RSCP is in the negative range as per TS 25.123 [24], and the value is equal to the *Primary CCPCH RSCP Delta* IE. If the *Primary CCPCH RSCP Delta* IE is not included and the *Primary CCPCH RSCP* IE is included, the DRNS should assume that the reported value is in the non-negative range as per TS 25.123 [24], and the value is equal to the *Primary CCPCH RSCP* IE. The DRNS should use the indicated value when deciding the Initial DL TX Power for the Radio Link.]

[3.84 Mcps TDD and 7.68 Mcps TDD – The DL TX power upper and lower limit is configured in the following way:

- The DRNC shall include the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the RADIO LINK SETUP RESPONSE message. If the maximum or minimum power needs to be different for particular DCH type CCTrCHs, the DRNC shall include the value(s) for that CCTrCH in the *CCTrCH Maximum DL TX Power* IE and *CCTrCH Minimum DL TX Power* IE. The DRNS shall not transmit with a higher power than indicated by the appropriate *Maximum DL TX Power* IE/CCTrCH Maximum DL TX Power IE or lower than indicated by the appropriate Minimum DL TX Power IE/CCTrCH Minimum DL TX Power IE on any DL DPCH within each CCTrCH of the RL.]

[1.28 Mcps TDD – The DL TX power upper and lower limit is configured in the following way:

- The DRNC shall include the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the RADIO LINK SETUP RESPONSE message. If the maximum or minimum power needs to be different for particular timeslots within a DCH type CCTrCH, the DRNC shall include the value(s) for that timeslot in the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE within the *DL Timeslot Information LCR* IE. The DRNS shall not transmit with a higher power than indicated by the appropriate *Maximum DL TX Power* IE or lower than indicated by the appropriate *Minimum DL TX Power* IE on any DL DPCH within each timeslot of the RL.]

[1.28McpsTDD – If the *TSTD Support Indicator* IE is present, the DRNS shall apply this information when configuring the transmit diversity for the new radio link.]

[FDD – The DRNS shall start any DL transmission using the indicated DL TX power level (if received) or the decided DL TX power level on each DL channelisation code or on the F-DPCH of a RL until UL synchronisation is achieved on the Uu interface for the concerned RLS or Power Balancing is activated. No inner loop power control or power balancing shall be performed during this period. The DL power shall then vary according to the inner loop power control (see TS 25.214 [10] subclause 5.2.1.2) and the power control procedure (see 8.3.15).]

[TDD – The DRNS shall start any DL transmission using the decided DL TX power level on each DL channelisation code and on each Time Slot of a RL until UL synchronisation is achieved on the Uu interface for the concerned RL. No inner loop power control shall be performed during this period. Then after UL synchronisation, the DL power shall vary according to the inner loop power control (see TS 25.224 [22] subclause 4.2.3.3).]

[FDD – If the received *Inner Loop DL PC Status* IE is set to "Active", the DRNS shall activate the inner loop DL power control for all RLs. If *Inner Loop DL PC Status* IE is set to "Inactive", the DRNS shall deactivate the inner loop DL power control for all RLs according to TS 25.214 [10].]

[FDD – If the *DPC Mode* IE is present in the RADIO LINK SETUP REQUEST message, the DRNC shall apply the DPC mode indicated in the message, and be prepared that the DPC mode may be changed during the lifetime of the RL. If the *DPC Mode* IE is not present in the RADIO LINK SETUP REQUEST message, DPC mode 0 shall be applied (see TS 25.214 [10]).]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *DL Power Balancing Information* IE and the *Power Adjustment Type* IE is set to "Common" or "Individual", the DRNS shall activate the power balancing, if activation of power balancing by the RADIO LINK SETUP REQUEST message is supported, according to subclause 8.3.15, using the *DL Power Balancing Information* IE. If the DRNS starts the DL transmission and the activation of the power balancing at the same CFN, the initial power of the power balancing i.e. *P_{init}* shall be set to the power level indicated by the *Initial DL TX Power* IE (if received) or the

decided DL TX power level on each DL channelisation code of a RL based on the *Primary CPICH Ec/No* IE or the *Enhanced Primary CPICH Ec/No* IE.]

[FDD – If activation of power balancing by the RADIO LINK SETUP REQUEST message is supported by the DRNS, the DRNC shall include the *DL Power Balancing Activation Indicator* IE in the *RL Information Response* IE in the RADIO LINK SETUP RESPONSE message.]

Neighbouring Cell Handling:

If there are UMTS neighbouring cell(s) to the cell in which a Radio Link was established then:

- The DRNC shall include in the RADIO LINK SETUP RESPONSE message the Neighbouring FDD Cell Information IE and/or Neighbouring TDD Cell Information IE in the Neighbouring UMTS Cell Information IE for each neighbouring FDD cell and/or TDD cell respectively. In addition, if the information is available, the DRNC shall include in the RADIO LINK SETUP RESPONSE message the Frame Offset IE, Primary CPICH Power IE, Cell Individual Offset IE, STTD Support Indicator IE, Closed Loop Model Support Indicator IE, Coverage Indicator IE, Antenna Co-location Indicator IE and HCS Prio IE in the Neighbouring FDD Cell Information IE, and the Frame Offset IE, Cell Individual Offset IE, DPCH Constant Value IE, the PCCPCH Power IE, Coverage Indicator IE, Antenna Co-location Indicator IE and HCS Prio IE in the Neighbouring TDD Cell Information IE or the Neighbouring TDD Cell Information IE includes the Sync Case IE for the set to "Case1", the DRNC shall include the Time Slot For SCH IE in the Neighbouring TDD Cell Information IE. If the Neighbouring TDD Cell Information IE includes Sync Case IE set to "Case2", the DRNC shall include the SCH Time Slot IE in the Neighbouring TDD Cell Information IE.
- If a UMTS neighbouring cell is not controlled by the same DRNC, the DRNC shall also include in the RADIO LINK SETUP RESPONSE message the *CN PS Domain Identifier* IE and/or *CN CS Domain Identifier* IE which are the identifiers of the CN nodes connected to the RNC controlling the UMTS neighbouring cell.
- If the information is available, the DRNC shall include in the RADIO LINK SETUP RESPONSE
 message the DPC Mode Change Support Indicator IE for each neighbour cell in the Neighbouring FDD
 Cell Information IE
- The DRNC shall include the *Cell Capability Container FDD* IE, the *Cell Capability Container TDD* IE, the *Cell Capability Container TDD LCR* IE and/or the *Cell Capability Container Extension FDD* IE if the DRNC is aware that the neighbouring cell supports any functionality listed in 9.2.2.D, 9.2.3.1a, 9.2.3.1b and/or the *Cell Capability Container Extension FDD* IE.
- [FDD The DRNC shall, if supported, include the *Cell List Validity Indicator* IE if the neighbouring cell is multi cell capable and/or dual band capable but the cell can not be the serving HS-DSCH in a multicell and/or dual band configuration. Hence the cell can only serve as the secondary serving HS-DSCH cell. When *Cell List Validity Indicator* IE is included the SRNC should ignore the indicated cell list(s).]
- [FDD For each cell in the *Secondary Serving Cell List* IE that is Multi Cell E-DCH capable, indicated in the *Cell Capability Container Extension FDD* IE by the "Multi Cell E-DCH Support Indicator" bit = "1", and is restricted for use as an Additional E-DCH on the secondary uplink frequency with the cell identified by the *C-ID* IE as the corresponding cell of the primary uplink frequency, the DRNS shall, if supported, include the *Multicell E-DCH Restriction* IE set to "TRUE".]
- For the UMTS neighbouring cells which are controlled by the DRNC, the DRNC shall report in the RADIO LINK SETUP RESPONSE message the restriction state of those cells, otherwise the *Restriction State Indicator* IE may be absent. The DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Restriction State Indicator* IE for the neighbouring cells which are controlled by the DRNC in the *Neighbouring FDD Cell Information* IE, the *Neighbouring TDD Cell Information* IE and the *Neighbouring TDD Cell Information LCR* IE.
- If MOCN or GWCN network sharing configuration is used then the DRNC shall include the broadcasted PLMN identities of the concerned neighbouring cells in the *Multiple PLMN List* IE in the *Neighbouring FDD Cell Information* IE, the *Neighbouring TDD Cell Information* IE and the *Neighbouring TDD Cell Information LCR* IE.

- If available, the DRNC shall include the *SNA Information* IE for the concerned neighbouring cells in the *Neighbouring FDD Cell Information* IE, the *Neighbouring TDD Cell Information* IE and the *Neighbouring TDD Cell Information LCR* IE.
- If available, the DRNC shall include the *Frequency Band Indicator* IE for the concerned neighbouring cells in the *Neighbouring FDD Cell Information* IE.
- If the number of neighbouring UMTS RNCs is beyond the predefined maximum number, the DRNC shall, if supported, include the remaining neighbouring information in the *Neighbouring UMTS Cell Information Extension* IE. The IE filling rules in the Neighbouring UMTS Cell Information shall also apply to the *Neighbouring UMTS Cell Information Extension* IE.

If there are GSM neighbouring cells to the cell(s) where a radio link is established, the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Neighbouring GSM Cell Information* IE for each of the GSM neighbouring cells. If available the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Cell Individual Offset* IE, and if the *Cell Individual Offset* IE alone cannot represent the value of the offset, the DRNC shall also include the *Extended GSM Cell Individual Offset* IE in the *Neighbouring GSM Cell Information* IE. If available the DRNC shall also include in the RADIO LINK SETUP RESPONSE message the *Coverage Indicator* IE, *Antenna Co-location Indicator* IE and *HCS Prio* IE in the *Neighbouring GSM Cell Information* IE. If available, the DRNC shall also include the *SNA Information* IE for the concerned neighbouring cells in the *Neighbouring GSM Cell Information* IE.

When receiving the *SNA Information* IE in the RADIO LINK SETUP RESPONSE message, the SRNC should use it to restrict cell access based on SNA information. See also TS 25.401 [40] for a broader description of the SNA access control.

If there are GERAN neighbouring cells to the cell(s) where a radio link is established, the DRNC shall include the *GERAN Cell Capability* IE in the *Neighbouring GSM Cell Information* IE that is included in the RADIO LINK SETUP RESPONSE message for each of the GERAN cells.

If there are GERAN Iu-mode neighbouring cells to the cell(s) where a radio link is established, the DRNC shall include, if available, the *GERAN Classmark* IE in the *Neighbouring GSM Cell Information* IE that is included in the RADIO LINK SETUP RESPONSE message for each of the GERAN Iu-mode neighbouring cells. TS 43.051 [39] defines when the transmission of the *GERAN Classmark* IE will be required at the initiation of the Relocation Preparation procedure.

If there are E-UTRA neighbouring cells to the cell(s) where a radio link is established, the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Neighbouring E-UTRA Cell Information* IE for each of the E-UTRA neighbouring cells, and may also include the *PCI* IE, *TAC* IE and *PLMN List* IE in the *Neighbouring E-UTRA Cell Information* IE in the RADIO LINK SETUP RESPONSE message.

[1.28Mcps TDD – Uplink Synchronisation Parameters LCR:]

[1.28Mcps TDD – If the *Uplink Synchronisation Parameters LCR* IE is present, the DRNC shall use the indicated values of *Uplink synchronisation stepsize* IE and *Uplink synchronisation frequency* IE when evaluating the timing of the UL synchronisation.]

[1.28Mcps TDD – Shared physical channels Synchronisation Detection:]

[1.28Mcps TDD – If HS-PDSCH and E-PUCH are configured but no DPCH is configured for the UE, then the DRNS shall also include the *Out-of-sync Detection Window* IE in the *HS-DSCH TDD Information Response* IE in the RADIO LINK SETUP RESPONSE message.]

[1.28Mcps TDD – Uplink Timing Advance Control LCR:]

[1.28Mcps TDD – The DRNC shall include the *Uplink Timing Advance Control LCR* IE in the RADIO LINK SETUP RESPONSE message.]

[1.28Mcps TDD – PowerControl GAP:]

[1.28Mcps TDD – If applied in the DRNS, the DRNC may include the *PowerControl GAP* IE in the RADIO LINK SETUP RESPONSE message.]

[1.28Mcps TDD – E-UTRAN Inter-RAT measurement:]

[1.28Mcps TDD – If the RADIO LINK SETUP REQUEST message includes the *Idle Interval Configuration Indicator* IE, if supported, the DRNC shall include the *Idle Interval Information* IE in the RADIO LINK SETUP RESPONSE message.]

[1.28Mcps TDD – RNTI Allocation Indicator:]

[1.28Mcps TDD – If the RADIO LINK SETUP REQUEST message includes the *RNTI Allocation Indicator* IE, if supported, the DRNS may allocate an E-RNTI and/or an H-RNTI for UE to use in CELL_FACH state.]

[1.28Mcps TDD – Inter-frequency/ Inter-RAT measurement:]

[1.28Mcps TDD – If the RADIO LINK SETUP REQUEST message includes the *DCH Measurement Type indicator* IE, if supported, the DRNS shall include the *Measurement purpose* IE and the *Measurement occasion pattern sequence parameters* IE in the *DCH Measurement Occasion Information* IE in the RADIO LINK SETUP RESPONSE message to configure the measurement occasion pattern(s) indicated by the *DCH Measurement Type indicator* IE.]

MBMS Handling:

If the *MBMS Bearer Service List* IE is included in the RADIO LINK SETUP REQUEST message, the DRNC shall, if supported, perform the UE Linking as specified in TS 25.346 [50], section 5.1.6. If the UE Link is currently stored in the UE Context or the *MBMS Bearer Service List* IE is included in the RADIO LINK SETUP REQUEST message and if an MBMS session for some MBMS bearer services contained in the UE Link is ongoing in some of the cells identified by the *C-ID* IEs in the RADIO LINK SETUP REQUEST message, the DRNC shall include for each of these active MBMS bearer services in the *Active MBMS Bearer Service List* IE the *Transmission Mode* IE in the concerned *RL Information Response* IEs in the RADIO LINK SETUP RESPONSE message.

If the UE Link is currently stored in the UE Context or the *MBMS Bearer Service List* IE is included in the RADIO LINK SETUP REQUEST message and if an MBMS preferred frequency layer for some active MBMS bearer services contained in the UE Link is set in some of the cells identified by the *C-ID* IEs in the RADIO LINK SETUP REQUEST message, the DRNC shall include for each of these active MBMS bearer services in the *Active MBMS Bearer Service List* IE the *Preferred Frequency Layer* IE in the concerned *RL Information Response* IEs in the RADIO LINK SETUP RESPONSE message.

[FDD – HS-DSCH Preconfiguration for Enhanced HS Serving Cell Change]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *HS-DSCH Preconfiguration Setup* IE in the *RL Information* IE for a Radio Link not indicated by the *HS-PDSCH RL ID* IE the DRNS shall if supported preconfigure the indicated cells for Enhanced HS Serving Cell Change according to TS 25.308 [63]:

- [FDD The DRNS shall preconfigure sets of HS-SCCH codes on the cells preconfigured for HS-DSCH, primary serving HS-DSCH cell, as well as on the secondary serving HS-DSCH cells. The primary serving HS-DSCH cell is designated through the *C-ID* IE part of the *RL Information* IE in the RADIO LINK SETUP REQUEST message. The list of secondary serving HS-DSCH cells is designated by the list of *Secondary C-ID* IEs in the *HS-DSCH Preconfiguration Setup* IE part of the *RL Information* IE in the RADIO LINK SETUP REQUEST message.]
- [FDD The number of HS-SCCH codes to preconfigure for each cell may be optionally specified:]
 - [FDD by the *Num Primary HS-SCCH Codes* IE in the *HS-DSCH Preconfiguration Setup* IE, for the primary serving HS-DSCH cell]
 - [FDD by the *Num Secondary HS-SCCH Codes* IE in the *Secondary Cells* IE in the *HS-DSCH Preconfiguration Setup* IE for each of the secondary serving HS-DSCH cells]
- [FDD –If *Num Primary HS-SCCH Codes* IE or *Num Secondary HS-SCCH Codes* IE is not included in the message the number and distribution of codes on primary and any secondary cells shall be preconfigured to satisfy any limitations in TS 25.214 [10].
- [FDD The DRNS shall return these codes in the *Sets of HS-SCCH Codes IE* along with the corresponding per-cell *HS-DSCH-RNTI* IE in the *HS-DSCH Preconfiguration Info* IE in the *RL Information Response* IE of the RADIO LINK SETUP RESPONSE message or in the *Successful RL Information Response* IE of the RADIO LINK SETUP FAILURE message.]

- [FDD The DRNS shall use the first in the numbered list of the primary serving HS-DSCH cell's HS-SCCH codes in the *HS-SCCH Preconfigured Codes* IE sent to the SRNC to signal the Target Cell HS-SCCH Order defined in TS 25.331 [16].]
- [FDD The DRNS shall include, in the HS-DSCH Preconfiguration Info IE in the RL Information Response IE in the RADIO LINK SETUP RESPONSE message or in the Successful RL Information Response IE of the RADIO LINK SETUP FAILURE message, IEs according to the rules defined for HS-DSCH setup and:]
 - [FDD if *HARQ Preamble Mode* IE is included in the *HS-DSCH Preconfiguration Setup* IE the *HARQ Preamble Mode Activation Indicator* IE]
 - [FDD if *MIMO Activation Indicator* IE is included in the *HS-DSCH Preconfiguration Setup* IE or in the *Secondary Cells* IE in the *HS-DSCH Preconfiguration Setup* IE the Pilot Configuration and MIMO N/M Ratio in *MIMO Information Response* IE]
 - [FDD if *Ordinal number of frequency* IE is included in the *Secondary Cells* IE in the *HS-DSCH Preconfiguration Setup* IE]
 - [FDD if *HS-DSCH MAC-d PDU Size Format* IE is included in the *HS-DSCH Preconfiguration Setup* IE and set to "Flexible MAC-d PDU Size" and if Sixtyfour QAM will not be used in the preconfiguration, the *HS-DSCH TB Size Table Indicator* IE for each preconfigured cell]
 - [FDD if Sixtyfour QAM Usage Allowed Indicator IE is included in the Secondary Cells IE in the HS-DSCH Preconfiguration Setup IE or in the HS-DSCH Preconfiguration Setup IE the SixtyfourQAM DL Usage Indicator IE for each preconfigured cell]
 - [FDD if Continuous Packet Connectivity HS-SCCH less Information IE is included in the HS-DSCH Preconfiguration Setup IE the Continuous Packet Connectivity HS-SCCH less Information Response IE]
 - [FDD if the *UE with enhanced HS-SCCH support indicator* IE is included in the *HS-DSCH Preconfiguration Setup* IE, then the DRNS shall store this information in the preconfigured configuration.]
 - [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH Preconfiguration Setup* IE with the bit *UE DTXDRX related HS-SCCH orders uniform behavior indicator* set to 0, then the DRNS shall, if supported, include the *Support of dynamic DTXDRX related HS-SCCH order* IE in the *HS-DSCH Preconfiguration Info* IE in the RADIO LINK SETUP RESPONSE message.]
 - [FDD the *SixtyfourQAM DL Support Indicator* IE shall be included]
 - [FDD if the *UE Support Indicator Extension* IE is included in the *HS-DSCH Preconfiguration Setup* IE, then the DRNS may store this information in the preconfigured configuration.]
 - [FDD the DRNS shall, if supported, include in the Sets of HS-SCCH Codes IE the Measurement Power Offset IE for each preconfigured cell.]
- [FDD The DRNS shall include in the *HS-DSCH Preconfiguration Info* IE in the *RL Information Response* IE in the RADIO LINK SETUP RESPONSE message or in the *Successful RL Information Response* IE of the RADIO LINK SETUP FAILURE message the *E-DCH FDD DL Control Channel Information* containing the preconfigured configuration of the E-DCH serving cell according to the rules defined for Serving E-DCH Radio Link Change as follows:]
 - [FDD The DRNS shall allocate for the preconfigured configuration a primary E-RNTI identifier or a secondary E-RNTI identifier or both for the new Serving E-DCH Radio Link and include these E-RNTI identifiers along with the channelisation code of the corresponding E-AGCH in the E-DCH FDD DL Control Channel Information IE.]
 - [FDD The DRNS may preconfigure the *Serving Grant Value* IE and *Primary/Secondary Grant Selector* IE for the initial grant for the serving E-DCH RL and include these values in the *E-DCH FDD DL Control Channel Information* IE.]
- [FDD –If the *HS-DSCH Preconfiguration Setup* IE includes the *E-DCH Indicator* IE for a secondary cell, the DRNS shall include in the *Additional E-DCH Preconfiguration Information* IE in the *HS-DSCH*

Preconfiguration Info IE in the RL Information Response IE in the RADIO LINK SETUP RESPONSE message or in the Successful RL Information Response IE of the RADIO LINK SETUP FAILURE message the E-DCH FDD DL Control Channel Information containing the preconfigured configuration of the Additional E-DCH serving cell, corresponding to the cell indicated with the E-DCH Indicator IE, according to the rules defined for Serving Additional E-DCH Radio Link Change as follows:]

- [FDD The DRNS shall allocate for the preconfigured configuration a primary E-RNTI identifier or a
 secondary E-RNTI identifier or both for the new Serving Additional E-DCH Radio Link and include
 these E-RNTI identifiers along with the channelisation code of the corresponding E-AGCH in the EDCH FDD DL Control Channel Information IE.]
- [FDD The DRNS may preconfigure the *Serving Grant Value* IE and *Primary/Secondary Grant Selector* IE for the initial grant for the serving Additional E-DCH RL and include these values in the *E-DCH FDD DL Control Channel Information* IE.]
- [FDD If the *Power Offset For S-CPICH for MIMO Request Indicator* IE is included in the *HS-DSCH Preconfiguration Setup* IE or in the *Secondary Cells* IE in the *HS-DSCH Preconfiguration Setup* IE, the DRNC shall, if supported and MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where HS-DSCH / secondary HS-DSCH is preconfigured, include the *Power Offset For S-CPICH for MIMO* IE in the *HS-DSCH Preconfiguration Info* IE or in the *Sets of HS-SCCH Codes* IE in the *HS-DSCH Preconfiguration Info* IE for each preconfigured cell in the RADIO LINK SETUP RESPONSE message. If zero power offset the DRNC may include the *Power Offset For S-CPICH for MIMO* IE.]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *Non-Serving RL Preconfiguration Setup* IE in the *RL Information* IE and:]

- [FDD if the choice of *new Serving RL* is "New Serving RL in the DRNS", the DRNC may include the *New non-serving RL E-DCH FDD DL Control Channel Information A* IE and/or *New non-serving RL E-DCH FDD DL Control Channel Information B* IE in the *Non-Serving RL Preconfiguration Info* IE for the RL in the RADIO LINK SETUP RESPONSE message.]
- [FDD if the choice of *new Serving RL* is "New Serving RL Not in the DRNS", the DRNC may include the *New non-serving RL E-DCH FDD DL Control Channel Information C* IE in the *Non-Serving RL Preconfiguration Info* IE for the RL in the RADIO LINK SETUP RESPONSE message.]
- [FDD if the choice of *new Serving RL* is "New Serving RL in the DRNS or New Serving RL Not in the DRNS", the DRNC may include the *New non-serving RL E-DCH FDD DL Control Channel Information A* IE, the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information C* IE for the RL in the *Non-Serving RL Preconfiguration Info* IE in the RADIO LINK SETUP RESPONSE message.]
- [FDD if the Additional E-DCH Non-Serving RL Preconfiguration Setup IE is included, the DRNC may include the New non-serving RL E-DCH FDD DL Control Channel Information A IE, the New non-serving RL E-DCH FDD DL Control Channel Information B IE and/or the New non-serving RL E-DCH FDD DL Control Channel Information C IE according to the choice of new Serving RL in Additional E-DCH New non-serving RL E-DCH FDD DL Control Channel Information IE for the additional non serving E-DCH RL in the Non-Serving RL Preconfiguration Info IE in the RADIO LINK SETUP RESPONSE message.]

General:

If the RADIO LINK SETUP REQUEST message includes the *RL Specific DCH Information* IE, the DRNC may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for the DCH or the set of co-ordinated DCHs [FDD – for every DCH being established for which the *Transport Bearer Not Requested Indicator* IE was not included].

If no *D-RNTI* IE was included in the RADIO LINK SETUP REQUEST message, the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *D-RNTI* IE, the *CN PS Domain Identifier* IE and/or the *CN CS Domain Identifier* IE for the CN domains (using LAC and RAC of the current cell) to which the DRNC is connected.

[1.28 Mcps TDD – If no *D-RNTI* IE was included in the RADIO LINK SETUP REQUEST message, the DRNC could include in the RADIO LINK SETUP RESPONSE message the *UARFCN* IE.]

[FDD – If the *D-RNTI* IE was included in the RADIO LINK SETUP REQUEST message the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Primary Scrambling Code* IE, the *UL UARFCN* IE and the *DL UARFCN* IE.]

[TDD – If the *D-RNTI* IE was included in the RADIO LINK SETUP REQUEST message the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *UARFCN* IE, the *Cell Parameter ID* IE and the *SCTD Indicator* IE.]

[3.84Mcps TDD and 7.68 Mcps TDD – If the *D-RNTI* IE was included in the RADIO LINK SETUP REQUEST message the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Sync Case* IE and if the *Sync Case* IE is set to "Case 2", the DRNC shall also include the *SCH Time Slot* IE in the RADIO LINK SETUP RESPONSE message. If the included *Sync Case* IE is set to "Case1", the DRNC shall also include the *Time Slot For SCH* IE.]

[3.84Mcps TDD – The DRNC shall include the *Secondary CCPCH Info TDD* IE in the RADIO LINK SETUP RESPONSE message if at least one *DSCH Information Response* IE or *USCH Information Response* IE is included in the message and at least one DCH is configured for the radio link. The DRNC shall also include the *Secondary CCPCH Info TDD* IE in the RADIO LINK SETUP RESPONSE message if at least one *DSCH Information Response* IE or *USCH Information Response* IE is included in the message and the SHCCH messages for this radio link will be transmitted over a different secondary CCPCH than selected by the UE from system information.]

[1.28 Mcps TDD – The DRNC shall include the *Secondary CCPCH Info TDD LCR* IE in the RADIO LINK SETUP RESPONSE message if at least one *DSCH Information Response LCR* IE or *USCH Information Response LCR* IE is included in the message and at least one DCH is configured for the radio link. The DRNC shall also include the *Secondary CCPCH Info TDD LCR* IE in the RADIO LINK SETUP RESPONSE message if at least one *DSCH Information Response LCR* IE or *USCH Information Response LCR* IE is included in the message and the SHCCH messages for this radio link will be transmitted over a different secondary CCPCH than selected by the UE from system information.]

[7.68 Mcps TDD – The DRNC shall include the *Secondary CCPCH Info 7.68Mcps TDD* IE in the RADIO LINK SETUP RESPONSE message if at least one *DSCH Information Response 7.68 Mcps* IE or *USCH Information Response 7.68 Mcps* IE is included in the message and at least one DCH is configured for the radio link. The DRNC shall also include the *Secondary CCPCH Info 7.68Mcps TDD* IE in the RADIO LINK SETUP RESPONSE message if at least one *DSCH Information Response 7.68 Mcps* IE or *USCH Information Response 7.68 Mcps* IE is included in the message and the SHCCH messages for this radio link will be transmitted over a different secondary CCPCH than selected by the UE from system information.]

For each Radio Link established in a cell in which at least one URA Identity is being broadcast, the DRNC shall include in the *URA Information* IE within the RADIO LINK SETUP RESPONSE message URA Innformation for this cell including the *URA ID* IE, the *Multiple URAs Indicator* IE indicating whether or not multiple URA Identities are being broadcast in the cell, and the *RNC-ID* Iesof all other RNCs that have at least one cell within the URA identified by the *URA ID* IE.

Depending on local configuration in the DRNS, the DRNC may include in the RADIO LINK SETUP RESPONSE message the *UTRAN Access Point Position* IE and the geographical co-ordinates of the cell, represented either by the *Cell GAI* IE or by the *Cell GA Additional Shapes* IE. If the DRNC includes the *Cell GA Additional Shapes* IE in the RADIO LINK SETUP RESPONSE message, it shall also include the *Cell GAI* IE.

If the DRNS need to limit the user rate in the uplink of a DCH due to congestion caused by the UL UTRAN Dynamic Resources (see subclause 9.2.1.79) when starting to utilise a new Radio Link, the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Allowed UL Rate* IE in the *DCH Information Response* IE for this Radio Link.

If the DRNS need to limit the user rate in the downlink of a DCH due to congestion caused by the DL UTRAN Dynamic Resources (see subclause 9.2.1.79) when starting to utilise a new Radio Link, the DRNC shall include in the RADIO LINK SETUP RESPONSE message the *Allowed DL Rate* IE in the *DCH Information Response* IE for this Radio Link.

If the *Permanent NAS UE Identity* IE is included in the RADIO LINK SETUP REQUEST message, the DRNS shall store the information for the considered UE Context for the life-time of the UE Context.

If the RADIO LINK SETUP REQUEST message includes the *Permanent NAS UE Identity* IE and a *C-ID* IE corresponding to a cell reserved for operator use, the DRNS shall use this information to determine whether it can set up a Radio Link on this cell or not for the considered UE Context.

If the HCS priority information is available in the DRNS, it shall include the *HCS Prio* IE for each of the established RLs in the RADIO LINK SETUP RESPONSE message.

The DRNS shall start receiving on the new RL(s) after the RLs are successfully established.

[FDD – If the RADIO LINK SETUP REQUEST message includes the *Cell Portion ID* IE, the DRNS shall use this information when it decides to use beamforming for the new RL.]

[1.28 Mcps TDD – If the RADIO LINK SETUP REQUEST message includes the *Cell Portion LCR ID* IE, the DRNS shall use this information when it decides to allocate physical resource for the new RL.]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *Initial DL DPCH Timing Adjustment Allowed* IE, then the DRNS may perform an initial DL DPCH Timing Adjustment (i.e. perform a timing advance or a timing delay with respect to the SFN timing) on a Radio Link. In this case, the DRNS shall include, for the concerned Radio Link(s), the *Initial DL DPCH Timing Adjustment* IE in the *Radio Link Information Response* IE in the RADIO LINK SETUP RESPONSE message.]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *D-RNTI* IE which already has a RL and *Synchonisation Indicator* IE, the DRNC shall ignore the value in the *Frame Offset* IE and *Chip Offset* IE in the RADIO LINK SETUP REQUEST message and shall include in the *Frame Offset* IE and *Chip Offset* IE the values used for already established RL in the RADIO LINK SETUP RESPONSE message.]

[FDD – Radio Link Set Handling:]

[FDD – The *First RLS Indicator* IE indicates if the concerned RL shall be considered part of the first RLS established towards this UE. The DRNS shall use the *First RLS Indicator* IE to determine the initial TPC pattern in the DL of the concerned RL and all RLs which are part of the same RLS, as described in TS 25.214 [10], section 5.1.2.2.1.2.]

[FDD – For each RL not having a common generation of the TPC commands in the DL with another RL, the DRNS shall assign to the RL a unique value for the *RL Set ID* IE which uniquely identifies the RL as an RL Set within the UE Context. In case of E-DCH, the generation of E-HICH related information for RLs in different RL Set(s) shall not be common.]

[FDD – For all RLs having a common generation of the TPC commands in the DL with another RL, the DRNS shall assign to each RL the same value for the *RL Set ID* IE which uniquely identifies these RLs as members of the same RL Set within the UE Context. In case of E-DCH, the generation of E-HICH information for all RLs in a RL Set shall be common.]

[FDD – The UL oout-of-sync algorithm defined in TS 25.214 [10] shall, for each of the established RL Set(s), use the maximum value of the parameters $N_{OUTSYNC_{IND}}$ and $T_{RLFAILURE}$ that are configured in the cells supporting the radio links of the RL Set. The UL in-sync algorithm defined in TS 25.214 [10] shall, for each of the established RL Set(s), use the minimum value of the parameters $N_{INSYNC_{IND}}$ that are configured in the cells supporting the radio links of the RL Set.]

[FDD – For each E-DCH RL which has or can have a common generation of E-RGCH information with another RL (current or future) when the DRNS would contain the E-DCH serving RL, the DRNS shall include the *E-DCH RL Set ID* IE in the RADIO LINK SETUP RESPONSE message. The value of the *E-DCH RL Set ID* IE shall allow the SRNC to identify the E-DCH RLs that have or can have a common generation of E-RGCH information.]

[TDD- E-DCH:]

[TDD – If the [3.84Mcps – *E-DCH Information* IE][1.28Mcps – *E-DCH Information* 1.28Mcps IE][7.68Mcps TDD – *E-DCH Information* 7.68Mcps IE] is present in the RADIO LINK SETUP REQUEST message:]

- [TDD The DRNS shall setup the requested E-DCH resources on the Radio Link indicated by the *E-DCH Serving RL* IE.]
- [TDD If the *TNL QoS* IE is included in the *E-DCH MAC-d Flows Information TDD* IE for an E-DCH MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink for the related MAC-d flow.]

- [TDD If the RADIO LINK SETUP REQUEST message includes the *Transport Layer Address* IE and *Binding ID* IE in the *E-DCH MAC-d Flows Information TDD* IE for an E-DCH MAC-d flow, then the DRNC may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for the concerned E-DCH MAC-d flow.]
- [TDD If the RADIO LINK SETUP REQUEST message includes the *E-DCH MAC-d Flow Multiplexing List* IE for an E-DCH MAC-d flow in the *E-DCH MAC-d Flows Information TDD* IE, the DRNS shall use this information for the related resource allocation operation.]
- [TDD If in the RADIO LINK SETUP REQUEST message the *E-DCH Grant Type* IE in the *E-DCH MAC-d Flows Information TDD* IE is set to "Non-scheduled" for an E-DCH MAC-d flow the DRNS shall assume non-scheduled grants are configured for that E-DCH MAC-d flow.]
- [TDD If in the RADIO LINK SETUP REQUEST message the *E-DCH Grant Type* IE in the *E-DCH MAC-d Flows Information TDD* IE is set to "Scheduled" the DRNS shall assume that it may issue scheduled grants for the concerned E-DCH MAC-d flow.]
- [TDD If the RADIO LINK SETUP REQUEST message includes the *MAC-es Guaranteed Bit Rate* IE in the *E-DCH Logical Channel Information* IE in the *E-DCH MAC-d Flows Information TDD* IE, then the DRNS shall use this information to optimise MAC-e scheduling decisions for the related queue.]
- [1.28Mcps TDD If the RADIO LINK SETUP REQUEST message includes the *MAC-es Maximum Bit Rate LCR* IE in the *E-DCH Logical Channel Information* IE in the *E-DCH MAC-d Flows Information TDD* IE, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
- [TDD If the RADIO LINK SETUP REQUEST message includes the *Maximum MAC-d PDU Size Extended* IE for a E-DCH Logical Channel in the *E-DCH MAC-d Flows Information TDD* IE in the *E-DCH Information* IE, then the DRNS shall ignore the *MAC-d PDU Size* IE in the *MAC-d PDU Size List* IE and use *Maximum MAC-d PDU Size Extended* IE to optimise capacity allocation for the related E-DCH Logical Channel and use the indicated format in user plane frame structure for E-DCH channels (TS 25.425 [32]) and MAC (TS 25.321 [41]).]
- [3.84Mcps TDD If the RADIO LINK SETUP REQUEST message includes the *E-DCH TDD Maximum Bitrate* IE in the *E-DCH TDD Information* IE for an E-DCH, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
- [1.28Mcps TDD If the RADIO LINK SETUP REQUEST message includes the *E-DCH Physical Layer Category LCR* IE or *Extended E-DCH Physical Layer Category LCR* IE in the *E-DCH TDD Information LCR* IE for an E-DCH, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
- [7.68Mcps TDD If the RADIO LINK SETUP REQUEST message includes the *E-DCH TDD Maximum Bitrate 7.68Mcps* IE in the *E-DCH TDD Information 7.68Mcps* IE for an E-DCH, the Node B shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
- [3.84Mcps TDD If the RADIO LINK SETUP REQUEST message includes the *E-DCH Processing Overload Level* IE in the *E-DCH TDD Information* IE, then if the DRNS could not decode the E-PUCH for the last consecutive number of TTIs, indicated in the *E-DCH Processing Overload Level* IE, because of a processing issue, the DRNS shall notify the SRNC by initiating the Radio Link Failure procedure.]
- [7.68Mcps TDD If the RADIO LINK SETUP REQUEST message includes the *E-DCH Processing Overload Level* IE in the *E-DCH TDD Information 7.68Mcps* IE, then if the DRNS could not decode the E-PUCH for the last consecutive number of TTIs, indicated in the *E-DCH Processing Overload Level* IE, because of a processing issue, the DRNS shall notify the SRNC by initiating the Radio Link Failure procedure.]
- [1.28Mcps TDD If the RADIO LINK SETUP REQUEST message includes the *E-DCH Processing Overload Level* IE in the *E-DCH TDD Information LCR* IE, then if the DRNS could not decode the E-PUCH for the last consecutive number of TTIs, indicated in the *E-DCH Processing Overload Level* IE, because of a processing issue, the DRNS shall notify the SRNC by initiating the Radio Link Failure procedure.]
- [TDD The DRNS may use the *Traffic Class* IE for a specific E-DCH MAC-d flow to determine the transport bearer characteristics to apply between DRNC and Node B.]

- [TDD If the RADIO LINK SETUP REQUEST message includes the [3.84Mcps TDD *E-DCH TDD Information* IE][1.28Mcps TDD *E-DCH TDD Information LCR* IE] in the *E-DCH MAC-d Flows Information TDD* IE, then the DRNS shall use this value as a power offset for the transmission of scheduling information without any MAC-d PDUs.]
- [1.28Mcps TDD If the RADIO LINK SETUP REQUEST message includes the *Maximum Number of Retransmission for Scheduling Info LCR* IE and the *E-DCH Retransmission timer for Scheduling Info LCR* IE in the *E-DCH TDD Information LCR* IE, then the DRNS shall use these parameters for the transmission of scheduling information without any MAC-d PDUs.]
- [3.84Mcps TDD The DRNS shall determine any non-scheduled resource to be granted for the radio link, and return this in the *E-DCH Non-scheduled Grant Information TDD* IE in the *E-DCH Information Response* IE in the RADIO LINK SETUP RESPONSE message.]
- [3.84Mcps TDD The DRNS shall allocate an E-RNTI identifier and include the E-RNTI identifier and the E-AGCH(s) assigned in the *E-DCH Information Response* IE in the RADIO LINK SETUP RESPONSE message.]
- [1.28Mcps TDD The DRNS shall determine any non-scheduled resource to be granted for the radio link, and return this in the *E-DCH Non-scheduled Grant Information LCR TDD* IE in the *E-DCH Information Response* 1.28Mcps IE in the RADIO LINK ADDITION RESPONSE message.]
- [1.28Mcps TDD The DRNS shall allocate an E-RNTI identifier and include the E-RNTI identifier, the E-AGCH(s) and E-HICH(s) assigned in the *E-DCH Information Response 1.28Mcps* IE in the RADIO LINK SETUP RESPONSE message.]
- [7.68Mcps TDD The DRNS shall determine any non-scheduled resource to be granted for the radio link, and return this in the *E-DCH Non-scheduled Grant Information* 7.68Mcps TDD IE in the *E-DCH Information Response* 7.68Mcps IE in the RADIO LINK SETUP RESPONSE message.]
- [7.68Mcps TDD The DRNS shall allocate an E-RNTI identifier and include the E-RNTI identifier and the E-AGCH(s) assigned in the E-DCH Information Response 7.68Mcps IE in the RADIO LINK SETUP RESPONSE message.]
- [1.28Mcps TDD If the RADIO LINK SETUP REQUEST message includes the *Multi-Carrier E-DCH Physical Layer Category LCR* IE in the *E-DCH TDD Information LCR* IE, the DRNS shall use this information for the related resource allocation operation, and when applicable, for multi-carrier E-DCH scheduling.]
- [1.28Mcps TDD If the *UE TSO Capability LCR* IE in the *UE Capabilities Information* IE in the *HS-DSCH Information* IE is not present and if the RADIO LINK SETUP REQUEST message includes the *UE TSO Capability LCR* IE in the *E-DCH TDD Information LCR* IE, the DRNS can use this information to allocate the downlink resources for the UE according to TS 25.306 [42].]

Response Message:

Upon receipt of the RADIO LINK SETUP REQUEST message, the DRNS allocates the requested type of channelisation codes and other physical channel resources for each RL and assigns a binding identifier and a transport layer address for each DCH, for each set of co-ordinated DCHs [TDD – and for each DSCH and USCH]. This information shall be sent to the SRNC in the RADIO LINK SETUP RESPONSE message when all the RLs have been successfully established.

[1.28 Mcps TDD – if the DRNS assigns one or more PLCCH sequence numbers to the radio link, then the PLCCH assignment(s) shall be sent to the SRNC in the RADIO LINK SETUP RESPONSE message.]

After sending the RADIO LINK SETUP RESPONSE message the DRNS shall continuously attempt to obtain UL synchronisation on the Uu interface and start reception on the new RL.

For each RL for which the *Delayed Activation* IE is not included in the RADIO LINK SETUP REQUEST message the DRNS shall:

- [FDD start transmission on the DL DPDCH(s) of the new RL as specified in TS 25.427 [4].]
- [TDD start transmission on the new RL immediately as specified in TS 25.427 [4].]

For each RL for which the *Delayed Activation* IE is included in the RADIO LINK SETUP REQUEST message, the DRNS shall:

- if the *Delayed Activation* IE indicates "Separate Indication":
 - not start any DL transmission for the concerned RL on the Uu interface;
- if the *Delayed Activation* IE indicates "CFN":
 - [FDD start transmission on the DL DPDCH(s) of the new RL as specified in TS 25.427 [4], however never before the CFN indicated in the *Activation CFN* IE.]
 - [TDD start transmission on the new RL at the CFN indicated in the *Activation CFN* IE as specified in TS 25.427 [4].]

8.3.1.3 Unsuccessful Operation




Figure 6: Radio Link Setup procedure: Unsuccessful Operation

If the establishment of at least one radio link is unsuccessful, the DRNC shall respond with a RADIO LINK SETUP FAILURE message. The DRNC shall include in the RADIO LINK SETUP FAILURE message a general *Cause* IE or a *Cause* IE for each failed radio link. The *Cause* IE indicates the reason for failure.

[FDD – If some radio links were established successfully, the DRNC shall indicate this in the RADIO LINK SETUP FAILURE message in the same way as in the RADIO LINK SETUP RESPONSE message.]

If the RADIO LINK SETUP REQUEST message includes a *C-ID* IE corresponding to a cell reserved for operator use and the *Permanent NAS UE Identity* IE is not present, the DRNC shall reject the procedure and send the RADIO LINK SETUP FAILURE message.

[FDD – If the RL identified by the *HS-PDSCH RL ID* IE is a radio link in the DRNS and this RL is successfully established, then the DRNC shall allocate a HS-DSCH-RNTI to the UE Context and include the *HS-DSCH-RNTI* IE, the *HS-DSCH FDD Information Response* IE and the *SixtyfourQAM DL Support Indicator* IE in the RADIO LINK SETUP FAILURE message. This *SixtyfourQAM DL Support Indicator* IE is related to the HS-DSCH Radio Link.]

[FDD – If the RL identified by the *HS-PDSCH RL ID* IE in the *Additional HS Cell Information RL Setup* IE is a radio link in the DRNS and this RL is successfully established, then the DRNC shall allocate a HS-DSCH-RNTI to the UE Context and include the *HS-DSCH-RNTI* IE, the *HS-DSCH FDD Secondary Serving Information Response* IE and the *SixtyfourQAM DL Support Indicator* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK SETUP FAILURE message. If the establishment of the RL identified by the *HS-PDSCH RL ID* IE in the *Additional HS Cell Information RL Setup* IE, i.e secondary serving HS-DSCH Radio Link is unsuccessful but the establishment of the RL identified by the *HS-PDSCH RL ID* IE for the serving HS-DSCH Radio Link is successful, then the DRNC shall indicate the unsuccessful secondary serving HS-DSCH Radio Link in the *Unsuccessful RL Information Response* IE in the RADIO LINK SETUP FAILURE message by setting the *RL ID* IE to the same value as the unsuccessful *HS-PDSCH RL ID* IE in the *Additional HS Cell Information RL Setup* IE.]

[1.28 Mcps TDD – If the RL identified by the *HS-PDSCH RL ID* IE is a radio link in the DRNS and this RL is successfully established, then the DRNC shall allocate a HS-DSCH-RNTI to the UE Context and include the *HS-DSCH-RNTI* IE, the *HS-DSCH TDD Information Response* IE and the *SixtyfourQAM DL Support Indicator* IE in the RADIO LINK SETUP FAILURE message.]

[FDD – If the MIMO Activation Indicator IE is included and the Power Offset For S-CPICH for MIMO Request Indicator IE is not included in the HS-DSCH FDD Information IE in the RADIO LINK SETUP REQUEST message but MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where the Serving HS-DSCH Radio Link is established, the setup of the serving HS-DSCH Radio Link shall be reported as failed and the DRNC shall include in the RADIO LINK SETUP FAILURE message the Cause IE.]

[FDD – If the RL identified by the *E-DCH Additional RL ID* IE in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE is a radio link in the DRNS and this RL is successfully established, then the DRNS shall include the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response* IE in the RADIO LINK SETUP FAILURE message in the same way as in the RADIO LINK SETUP RESPONSE message. If the establishment of the RL identified by the *E-DCH Additional RL ID* IE is unsuccessful, then the DRNS shall indicate the unsuccessful setup of the Additional E-DCH Radio Link in the *Unsuccessful RL Information Response* IE in the RADIO LINK SETUP FAILURE message by setting the *RL ID* IE to the same value as the unsuccessful *E-DCH Additional RL ID* IE in the *Additional E-DCH Cell Information Setup* IE.]

Typical cause values are:

Radio Network Layer Causes:

[FDD – UL Scrambling Code Already in Use;]

DL Radio Resources not Available;

UL Radio Resources not Available;

[FDD – Combining Resources not available;]

Combining not Supported

Requested Configuration not Supported;

Cell not Available;

[FDD – Requested Tx Diversity Mode not Supported;]

Power Level not Supported;

Number of DL codes not supported;

Number of UL codes not supported;

Dedicated Transport Channel Type not Supported;

DL Shared Channel Type not Supported;

[TDD – UL Shared Channel Type not Supported;]

[FDD – UL Spreading Factor not Supported;]

[FDD – DL Spreading Factor not Supported;]

CM not Supported;

[FDD – DPC mode change not Supported;]

Cell reserved for operator use;

Delayed Activation not supported;

E-DCH not supported;

[FDD – F-DPCH not supported;]

[FDD - Continuous Packet Connectivity DTX-DRX operation not Supported;]

[FDD – Continuous Packet Connectivity HS-SCCH less operation not Supported;]

[FDD – MIMO not supported;]

[FDD – E-DCH TTI2ms not supported;]

[FDD – Continuous Packet Connectivity DTX-DRX operation not available;]

[FDD – Continuous Packet Connectivity UE DTX Cycle not available;]

[FDD – MIMO not available;]

[FDD – SixteenQAM UL not Supported;]

HS-DSCH MAC-d PDU Size Format not supported;

[FDD – F-DPCH Slot Format operation not supported;]

E-DCH MAC-d PDU Size Format not available:

[FDD – E-DPCCH Power Boosting not supported;]

[FDD – SixtyfourOAM DL and MIMO Combined not available;]

[FDD – Multi Cell operation not available;]

[FDD – Multi Cell operation not supported;]

[FDD – Multi Cell operation with MIMO not available;]

[FDD – Multi Cell operation with MIMO not supported;]

[FDD – Single Stream MIMO not supported;]

[FDD – Single Stream MIMO not available;]

[FDD – TX diversity for MIMO UE on DL Control Channels not available;]

[FDD – Multi Cell E-DCH Operation not supported;]

[FDD – Multi Cell E-DCH Operation not available;]

[FDD – Multi Cell operation with Single Stream MIMO not available;]

[FDD – Multi Cell operation with Single Stream MIMO not supported;]

[FDD – Cell Specific Tx Diversity Handling For Multi Cell Operation Not Available;]

[FDD – Cell Specific Tx Diversity Handling For Multi Cell Operation Not Supported;]

[FDD – Frequency Specific Compressed Mode Not Available]

Transport Layer Causes:

Transport Resource Unavailable.

Miscellaneous Causes:

Control Processing Overload; HW Failure; Not enough User Plane Processing Resources.

8.3.1.4 Abnormal Conditions

If the DRNC receives either an S-RNTI or a D-RNTI which already has RL(s) established [FDD – and the *Synchronisation Indicator* IE is not included in the RADIO LINK SETUP message,] the DRNC shall send the RADIO LINK SETUP FAILURE message to the SRNC, indicating the reason for failure.

[FDD – If the RADIO LINK SETUP REQUEST message includes the *Active Pattern Sequence Information* IE, but the *Transmission Gap Pattern Sequence Information* IE is not present, then the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD – If the RADIO LINK SETUP REQUEST message includes both the *Initial DL TX Power* IE and the *Primary CPICH Ec/No* IE or does not include either of these IEs, then the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

If more than one DCH of a set of co-ordinated DCHs has the *QE-Selector* IE set to "selected" [TDD – or no DCH of a set of co-ordinated DCHs has the *QE-Selector* IE set to "selected"] the DRNS shall reject the Radio Link Setup procedure and shall respond with a RADIO LINK SETUP FAILURE message.

[FDD – If only the *Initial DL TX Power* IE or the *Uplink SIR Target* IE is included in the RADIO LINK SETUP REQUEST message, then DRNC shall reject the Radio Link Setup procedure and shall respond with the RADIO LINK SETUP FAILURE message.]

If the RADIO LINK SETUP REQUEST message includes a *DCH Information* IE with multiple *DCH Specific Info* IEs, and if the DCHs in the *DCH Information* IE do not have the same *Transmission Time Interval* IE in the *Semi-static Transport Format Information* IE, then the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.

[FDD – If the RADIO LINK SETUP REQUEST message includes the *Enhanced Primary CPICH Ec/No* IE, but not the *Primary CPICH Ec/No* IE, then the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

If the RADIO LINK SETUP REQUEST message includes the *Transport Layer Address* IE and the *Binding ID* IE in the *RL Specific DCH Information* IE [FDD – or in the *RL Specific E-DCH Information* IE] included in the *RL Information* IE for a specific RL and the *Diversity Control Field* IE is set to "Must" [FDD- or the RL is combined with an E-DCH RL previously listed in the RADIO LINK SETUP RESPONSE message in the DRNS], the DRNC shall reject the Radio Link Setup procedure and the DRNC shall respond with the RADIO LINK SETUP FAILURE message.

If ALCAP is not used, if the RADIO LINK SETUP REQUEST message does not include the *Transport Layer Address* IE and the *Binding ID* IE in the *RL Specific DCH Information* IE nor *RL Specific E-DCH Information* IE in the *RL Information* IE for a specific RL and the *Diversity Control Field* IE is set to "May", the DRNC shall reject the Radio Link Setup procedure and respond with the RADIO LINK SETUP FAILURE message.

If ALCAP is not used, if the RADIO LINK SETUP REQUEST message does not include the *Transport Layer Address* IE and the *Binding ID* IE in the *RL Specific DCH Information* IE in the *RL Information* IE for a specific RL and the *Diversity Control Field* IE is set to "Must Not", the DRNC shall reject the Radio Link Setup procedure and respond with the RADIO LINK SETUP FAILURE message.

If ALCAP is not used, if the RADIO LINK SETUP REQUEST message does not include the *Transport Layer Address* IE and the *Binding ID* IE in the *RL Specific DCH Information* IE in the *RL Information* IE for the first RL and/or [FDD – in the *RL Specific E-DCH Information* IE in the *RL Information* IE for the first E-DCH RL][TDD – in the *E-DCH MAC-d Flows Information TDD* IE], the DRNC shall reject the Radio Link Setup procedure and respond with the RADIO LINK SETUP FAILURE message.

If ALCAP is not used, if the RADIO LINK SETUP REQUEST message does not include the *Transport Layer Address* IE and the *Binding ID* IE for an HS-DSCH MAC-d Flow in the *HS-DSCH MAC-d Flows Information* IE, the DRNC shall reject the Radio Link Setup procedure and respond with the RADIO LINK SETUP FAILURE message.

[TDD – If ALCAP is not used, if the RADIO LINK SETUP REQUEST message does not include the *Transport Layer Address* IE and the *Binding ID* IE for a DSCH in the *DSCH TDD Information* IE and/or for an USCH in the *USCH Information* IE, the DRNC shall reject the Radio Link Setup procedure and respond with the RADIO LINK SETUP FAILURE message.]

If the RADIO LINK SETUP REQUEST message includes the *Transport Layer Address* IE or the *Binding ID* IE, and not both are present for a transport bearer intended to be established, the DRNC shall reject the Radio Link Setup procedure and the DRNC shall respond with the RADIO LINK SETUP FAILURE message.

If the RADIO LINK SETUP REQUEST message includes an *HS-PDSCH RL-ID* IE not referring to one of the radio links to be established, the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.

If the RADIO LINK SETUP REQUEST message contains the *HS-DSCH Information* IE and if the Priority Queues associated with the same *HS-DSCH MAC-d Flow ID* IE have the same *Scheduling Priority Indicator* IE value, the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.

If the RADIO LINK SETUP REQUEST message includes the *Maximum MAC-d PDU Size Extended* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, and the *HS-DSCH MAC-d PDU Size Format* IE in the *HS-DSCH Information* IE has the value "Indexed MAC-d PDU Size", the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.

If the RADIO LINK SETUP REQUEST message does not include the *Maximum MAC-d PDU Size Extended* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, and the *HS-DSCH MAC-d PDU Size Format* IE in the *HS-DSCH Information* IE has the value "Flexible MAC-d PDU Size", the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.

[FDD – If the RADIO LINK SETUP REQUEST message contains, for at least one logical channel, the *Maximum MAC-d PDU Size Extended* IE in the *E-DCH MAC-d Flows Information* IE in the *E-DCH FDD Information* IE and there exist a logical channel for which the *Maximum MAC-d PDU Size Extended* IE in the *E-DCH MAC-d Flows Information* IE in the *E-DCH FDD Information* IE is not present, the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[TDD – If the RADIO LINK SETUP REQUEST message contains, for at least one logical channel, the *Maximum MAC-d PDU Size Extended* IE in the *E-DCH MAC-d Flows Information TDD* IE in the *E-DCH Information* IE, and there exist a logical channel for which the *Maximum MAC-d PDU Size Extended* IE in the *E-DCH MAC-d Flows Information TDD* IE in the *E-DCH Information* IE is not present, the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *F-DPCH Information* IE and the *DL DPCH Information* IE, then the DRNS shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD – If the RADIO LINK SETUP REQUEST message contains the *E-DCH RL Indication* IE set to "E-DCH", but does not contain the *E-DCH FDD Information* IE, or if the message contains the *E-DCH FDD Information* IE, but does not contain the *E-DCH RL Indication* IE set to "E-DCH", then the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

If the RADIO LINK SETUP REQUEST message contains the *HS-PDSCH RL ID* IE and the *Serving E-DCH RL* IE but the Serving HS-DSCH Radio Link and the Serving E-DCH Radio Link are not configured to be in the same cell then the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.

[FDD – If the RADIO LINK SETUP REQUEST message contains the *HS-PDSCH RL ID* IE and the *E-DPCH Information* IE which includes the *HS-DSCH Configured Indicator* IE set as "HS-DSCH not configured" then the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD – If the RADIO LINK SETUP REQUEST message contains the *E-DPCH Information* IE but does not contain the *UL DPDCH Indicator for E-DCH operation* IE, then the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD – If the RADIO LINK SETUP REQUEST message contains the *Serving Cell Change CFN* IE, but neither the *Serving E-DCH RL* IE nor *HS-DSCH Information* IE is included, then the DRNS shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD – If the RADIO LINK SETUP REQUEST message contains the *Transport Bearer Not Requested Indicator* IE for a DCH, but does not contain the *Unidirectional DCH indicator* IE set to "Uplink DCH only" in the *DCH Specific Info* IE for the DCH, the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD – If the RADIO LINK SETUP REQUEST message contains the *Synchronisation Indicator* IE for a RL, but does not contain the *D-RNTI* IE which already has the RL, the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD – If the *UL DPCH Information* IE in the RADIO LINK SETUP REQUEST message contains the *UL DPCCH Slot Format* set to "4" but does not contain the *F-DPCH Information* IE, then the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD – If the *UL DPCH Information* IE in the RADIO LINK SETUP REQUEST message contains the *UL DPCCH Slot Format* set to "0" or "2" and the *Continuous Packet Connectivity DTX-DRX Information* IE, then the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD – If the *UL DPCH Information* IE in the RADIO LINK SETUP REQUEST message contains *Diversity Mode* IE set to "Closed loop mode 1" and *UL DPCCH Slot Format* not set to "2" or "3", then the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD – If the RADIO LINK SETUP REQUEST message contains the MIMO Activation Indicator IE, Sixtyfour QAM Usage Allowed Indicator IE set to "Allowed", the Additional HS Cell Information RL Setup IE and/or the Single Stream MIMO Activation Indicator IE, but does not contain the HS-DSCH MAC-d PDU Size Format IE set to "Flexible MAC-d PDU Size", then the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD – If the RADIO LINK SETUP REQUEST message contains the *Continuous Packet Connectivity DTX-DRX Information* IE but does not contain the *F-DPCH Information* IE, then the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message]

[FDD – If the RADIO LINK SETUP REQUEST message contains the *Serving E-DCH RL ID* IE but contains the *Transport Bearer Not Requested Indicator* IE in the RL Specific E-DCH Information for the new Serving E-DCH RL, the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD – If the RADIO LINK SETUP REQUEST message includes the *Transport Bearer Not Requested Indicator* IE for a DCH or an E-DCH MAC-d Flow for a specific RL and the specific RL is combined with RL which the transport bearer is configured to be established for the DCH or the E-DCH MAC-d Flow, previously listed in the RADIO LINK SETUP RESPONSE message in the DRNS, the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD – If the RADIO LINK SETUP REQUEST message contains the *Additional HS Cell Information RL Setup* IE indicating a secondary serving cell that is not in the same Node B as the new serving HS-DSCH cell, then the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message]

[FDD – If the RADIO LINK SETUP REQUEST message contains the *Additional HS Cell Information RL Setup* IE and if the *HS-DSCH Information* IE is not present, then the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

If the RADIO LINK SETUP REQUEST message includes the *DL RLC PDU Size Format* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE set to "Flexible RLC PDU Size", and the *HS-DSCH MAC-d PDU Size Format* IE in the *HS-DSCH Information* IE has the value "Indexed MAC-d PDU Size", the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.

If the RADIO LINK SETUP REQUEST message does not include the *Maximum MAC-d PDU Size Extended* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, and the *DL RLC PDU Size Format* IE in the *HS-DSCH Information* IE has the value "Flexible RLC PDU Size", the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.

[FDD – If the RADIO LINK SETUP REQUEST message contains a MIMO Activation Indicator IE and a Single Stream MIMO Activation Indicator IE in the HS-DSCH FDD Information IE or in the HS-DSCH FDD Secondary Serving Information IE in the Additional HS Cell Information RL Setup IE, then the DRNC shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD – If the RADIO LINK SETUP REQUEST message contains the *Additional E-DCH Cell Information RL Setup Req* IE and if the *E-DPCH Information* IE is not present, then the DRNS shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD – If the RADIO LINK SETUP REQUEST message contains the *Additional E-DCH Cell Information RL Setup Req* IE and there exist a logical channel for which the *Maximum MAC-d PDU Size Extended* IE in the *E-DCH MAC-d Flows Information* IE in the *E-DCH FDD Information* IE is not present, the DRNS shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD – If the RADIO LINK SETUP REQUEST message contains the *Additional E-DCH Cell Information RL Setup Req* IE and the *C-ID* IE is not included in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE in the *Additional E-DCH Cell Information Setup* IE, the DRNS shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD – If the RADIO LINK SETUP REQUEST message contains in the *HS-DSCH FDD Secondary Serving Information* IE in the *Additional HS Cell Information RL Setup* IE the *Diversity Mode* IE not set to "None" but not the *Transmit Diversity Indicator* or contains the *Transmit Diversity Indicator* but not the *Diversity Mode* IE not set to "None", then the DRNS shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD - If the RADIO LINK SETUP REQUEST message contains the *Additional HS Cell Information RL Setup* IE containing more than one secondary serving HS-DSCH RL, and all secondary serving HS-DSCH RLs in the new configuration will not be assigned consecutive ordinal numbers starting with the value "1", which are received in the *Ordinal Number Of Frequency* IE in the in the *HS-DSCH FDD Secondary Serving Information* IE, the DRNS shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD - If the RADIO LINK SETUP REQUEST message contains the *Additional HS Cell Information RL Setup* IE containing more than one secondary serving HS-DSCH RL, the new configuration also contains an Additional E-DCH Serving Radio Link and the secondary serving HS-DSCH Radio link, which is configured in the same cell as the Additional E-DCH Serving Radio Link does not have Ordinal Number Of Frequency value "1", the DRNS shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD - If the RADIO LINK SETUP REQUEST message contains the *Affected HS-DSCH serving cell List* IE in the *Active Pattern Sequence Information* IE, and the Transmission Gap Pattern Sequence for affected HS-DSCH Serving Cells is activated on the HS-DSCH Primary Serving Cell but not for all the other serving cells, the DRNS shall reject the procedure using the RADIO LINK SETUP FAILURE message with the cause value "Invalid CM settings".]

8.3.2 Radio Link Addition

8.3.2.1 General

This procedure is used for establishing the necessary resources in the DRNS for one [FDD – or more] additional RLs towards a UE when there is already at least one RL established to the concerned UE via this DRNS.

This procedure shall use the signalling bearer connection for the relevant UE Context.

The Radio Link Addition procedure shall not be initiated if a Prepared Reconfiguration exists, as defined in subclause 3.1.

[TDD – The Radio Link Addition procedure serves to establish a new Radio Link with the DSCH and USCH included, if they existed before.]

8.3.2.2 Successful Operation




Figure 7: Radio Link Addition procedure: Successful Operation

The procedure is initiated with a RADIO LINK ADDITION REQUEST message sent from the SRNC to the DRNC.

Upon receipt, the DRNS shall reserve the necessary resources and configure the new RL(s) according to the parameters given in the message. Unless specified below, the meaning of parameters is specified in other specifications.

The DRNS shall prioritise resource allocation for the RL(s) to be established according to Annex A.

If the *UE Aggregate Maximum Bit Rate* IE is contained in the RADIO LINK ADDITION REQUEST message, the DRNS shall, if supported, store the received UE Aggregate Maximum Bit Rate parameters to control the aggregate data rate of non GBR traffic for this UE.

Transport Channel Handling:

[3.84 Mcps TDD – The DRNC shall include the *UL/DL DPCH Information* IE within the *UL/DL CCTrCH Information* IE for each CCTrCH that requires DPCHs.]

[1.28 Mcps TDD – The DRNC shall include the *UL/DL DPCH Information LCR* IE within the *UL/DL CCTrCH Information LCR* IE for each CCTrCH that requires DPCHs.]

[7.68 Mcps TDD – The DRNC shall include the *UL/DL DPCH Information 7.68 Mcps* IE within the *UL/DL CCTrCH Information 7.68 Mcps* IE for each CCTrCH that requires DPCHs.]

[TDD - DSCH:]

[3.84 Mcps TDD – If the radio link to be added includes a DSCH, the DRNC shall include in the RADIO LINK ADDITION RESPONSE message a *DSCH Information Response* IE for each DSCH.]

[1.28 Mcps TDD – If the radio link to be added includes a DSCH, the DRNC shall include in the RADIO LINK ADDITION RESPONSE message a *DSCH Information Response LCR* IE for each DSCH.]

[7.68 Mcps TDD – If the radio link to be added includes a DSCH, the DRNC shall include in the RADIO LINK ADDITION RESPONSE message a *DSCH Information Response* 7.68 Mcps IE for each DSCH.]

[TDD - USCH:]

[3.84 Mcps TDD – If the radio link to be added includes any USCHs, the DRNC shall include in the RADIO LINK ADDITION RESPONSE message a *USCH Information Response* IE for each USCH.]

[1.28 Mcps TDD – If the radio link to be added includes any USCHs, the DRNC shall include in the RADIO LINK ADDITION RESPONSE message a *USCH Information Response LCR* IE for each USCH.]

[7.68 Mcps TDD – If the radio link to be added includes any USCHs, the DRNC shall include in the RADIO LINK ADDITION RESPONSE message a *USCH Information Response* 7.68 Mcps IE for each USCH.]

Physical Channels Handling:

[FDD -Compressed Mode:]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Active Pattern Sequence Information* IE, the DRNS shall use the information to activate the indicated (all ongoing) Transmission Gap Pattern Sequence(s) in the new RL. The received *CM Configuration Change CFN* IE refers to the latest passed CFN with that value. The DRNS shall treat the received *TGCFN* IEs as follows:]

- [FDD If any received *TGCFN* IE has the same value as the received *CM Configuration Change CFN* IE, the DRNS shall consider the concerned Transmission Gap Pattern Sequence as activated at that CFN.]
- [FDD If any received *TGCFN* IE does not have the same value as the received *CM Configuration Change CFN* IE but the first CFN after the CM Configuration Change CFN with a value equal to the *TGCFN* IE has already passed, the DRNS shall consider the concerned Transmission Gap Pattern Sequence as activated at that CFN.]
- [FDD For all other Transmission Gap Pattern Sequences included in the *Active Pattern Sequence Information* IE, the DRNS shall activate each Transmission Gap Pattern Sequence at the first CFN after the CM Configuration Change CFN with a value equal to the *TGCFN* IE for the Transmission Gap Pattern Sequence.]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Active Pattern Sequence Information* IE and the concerned UE Context is configured to use F-DPCH in the downlink, the DRNS shall

ignore, when activating the Transmission Gap Pattern Sequence(s), the downlink compressed mode method information, if existing, for the concerned Transmission Gap Pattern Sequence(s) in the Compressed Mode Configuration.]

[FDD – If the *Active Pattern Sequence Information* IE is not included, the DRNS shall not activate the ongoing compressed mode pattern in the new RLs, but the ongoing pattern in the existing RL shall be maintained.]

[FDD – If some Transmission Gap Pattern sequences using SF/2 method are initialised in the DRNS and the UE Context is configured to use DPCH in the downlink, the DRNC shall include the *Transmission Gap Pattern Sequence Scrambling Code Information* IE in the *DL Code Information* IE in the RADIO LINK ADDITION RESPONSE message to indicate the Scrambling code change method that it selects for each channelisation code.]

[FDD - If the RADIO LINK ADDITION REQUEST message includes the *Affected HS-DSCH serving cell List* IE in the *Active Pattern Sequence Information* IE, the concerned Transmission Gap Pattern Sequence shall be applied to HS-DSCH serving cells associated with *C-ID* IE included in *Affected HS-DSCH serving cell List* IE. Otherwise the concerned Transmission Gap Pattern Sequence shall be applied to all the configured serving cells.]

[FDD – DL Code Information:]

[FDD – When more than one DL DPDCH are assigned per RL, the segmented physical channel shall be mapped on to DL DPDCHs according to TS 25.211 [8]. When *p* number of DL DPDCHs are assigned to each RL, the first pair of DL Scrambling Code and FDD DL Channelisation Code Number corresponds to "*PhCH number 1*", the second to "*PhCH number 2*", and so on until the *p*th to "*PhCH number p*".]

[TDD - CCTrCH Handling:]

[TDD – If the *UL CCTrCH Information* IE is present, the DRNS shall configure the new UL CCTrCH(s) according to the parameters given in the message.]

[1.28Mcps TDD – If the *UL CCTrCH Information* IE includes the *TDD TPC Uplink Step Size* IE, the DRNS shall configure the uplink TPC step size according to the parameters given in the message, otherwise it shall use the step size configured in other radio link.]

[TDD – If the *DL CCTrCH Information* IE is present, the DRNS shall configure the new DL CCTrCH(s) according to the parameters given in the message.]

[TDD – If the *DL CCTrCH Information* IE includes the *TDD TPC Downlink Step Size* IE, the DRNS shall configure the downlink TPC step size according to the parameters given in the message, otherwise it shall use the step size configured in other radio link.]

General:

[FDD – The DRNS shall use the provided Uplink SIR Target value as the current target for the inner-loop power control.]

Radio Link Handling:

Diversity Combination Control:

The *Diversity Control Field* IE indicates for each RL whether the DRNS shall combine the new RL with existing RL(s) or not on the Iur.

- If the *Diversity Control Field* IE is set to "May" (be combined with another RL), the DRNS shall decide for any of the alternatives.
- If the *Diversity Control Field* IE is set to "Must", the DRNS shall combine the RL with one of the other RL. When a new RL is to be combined the DRNS shall choose which RL(s) to combine it with.
- If the *Diversity Control Field* IE is set to "Must not", the DRNS shall not combine the RL with any other existing RL.

[FDD – The *Diversity Control Field* IE is only applicable for DCHs, in case of E-DCH it shall always be assumed to be set to "May".]

In the case of not combining a RL with a RL established with a previous Radio Link Setup or Radio Link Addition Procedure or a RL previously listed in the RADIO LINK ADDITION RESPONSE message, the DRNC shall indicate with the Diversity Indication in the *RL Information Response* IE in the RADIO LINK ADDITION RESPONSE message that no combining is done. In this case the DRNC shall:

- include in the DCH Information Response IE both the Transport Layer Address IE and the Binding ID IE for the transport bearer to be established for each DCH of the RL in the RADIO LINK ADDITION RESPONSE message [FDD for which the Transport Bearer Not Requested Indicator IE was not included].
- [FDD include in the RADIO LINK ADDITION RESPONSE the *Transport Bearer Not Setup Indicator* IE for every DCH or set of co-ordinated DCHs for which establishment of a transport bearer has not taken
 place as a result of information in the *Transport Bearer Not Requested Indicator* IE in the RADIO LINK
 ADDITION REQUEST message.]

[FDD – In case of not combining E-DCH, the *E-DCH FDD Information Response* IE shall be included in the RADIO LINK ADDITION RESPONSE message containing the *Binding ID* IE and the *Transport Layer Address* IE for the establishment of transport bearers for every E-DCH MAC-d flow being established for which the *Transport Bearer Not Requested Indicator* IE was not included.]

[FDD – In case of not combining E-DCH, the DRNC shall include in the RADIO LINK ADDITION RESPONSE the *Transport Bearer Not Setup Indicator* IE for every E-DCH MAC-d flow for which establishment of a transport bearer has not taken place as a result of information in the *Transport Bearer Not Requested Indicator* IE in the RADIO LINK ADDITION REQUEST message.]

In the case of combining with a RL established with a previous Radio Link Setup or Radio Link Addition Procedure or with a RL previously listed in this RADIO LINK ADDITION RESPONSE message, the DRNC shall indicate with the Diversity Indication in the *RL Information Response* IE in the RADIO LINK ADDITION RESPONSE message that the RL is combined. In this case, the *RL ID* IE indicates (one of) the previously established RL(s) or a RL previously listed in this RADIO LINK ADDITION RESPONSE message with which the new RL is combined and if the ALCAP is not used [FDD – and the transport bearer for this DCH is already established], the *Transport Layer Address* IE and the *Binding ID* IE in the *RL Specific DCH Information* IE included in the *RL Information* IE for a specific RL in the RADIO LINK ADDITION REQUEST message, shall not be used.

[FDD – In the case of combining with an E-DCH RL established with a previous Radio Link Setup or Radio Link Addition Procedure or with a RL previously listed in this RADIO LINK ADDITION RESPONSE message, one of the previously established RLs or a RL previously listed in this RADIO LINK ADDITION RESPONSE message including the *E-DCH FDD Information Response* IE and part of the same Radio Link Set shall be regarded as the RL with which the concerned E-DCH RL is combined and if the ALCAP is not used, the *Transport Layer Address* IE and the *Binding ID* IE in the *RL Specific E-DCH Information* IE included in the *RL Information* IE for a specific RL in the RADIO LINK ADDITION REQUEST message, shall not be used. In case E-DCH RL is established for the first time, the DRNC shall include *E-DCH FDD Information Response* IE instead of using the Diversity Indication of DCH RL in the *RL Information Response* IE in the RADIO LINK ADDITION RESPONSE message. It shall include in the *E-DCH FDD Information Response* IE the *Binding ID* IE and *Transport Layer Address* IE for the transport bearers to be established for each E-DCH MAC-d flow of this E-DCH RL for which the *Transport Bearer Not Requested Indicator* IE was not included.]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Additional E-DCH Cell Information RL Add Req* IE, then:]

- [FDD if the *Multicell E-DCH Transport Bearer Mode* IE for an Additional E-DCH to be Setup is set to "Separate Iur Transport Bearer Mode" the DRNS shall use this mode in the new configuration and apply separate transport bearers for the MAC-d flows.]
- [FDD if the *Multicell E-DCH Transport Bearer Mode* IE for an Additional E-DCH to be Setup is set to "UL Flow Multiplexing Mode" the DRNS shall use this mode in the new configuration and multiplex MAC-d flows on the transport bearers.]
- [FDD if Separate Iur Transport Bearer Mode is used in the new configuration, then:]
 - [FDD the DRNS shall follow the rules defined in this procedure for single carrier mode of operation for establishment of the transport bearer for a MAC-d flow and use the *Transport Bearer Not*

Requested Indicator IE in the RL Specific E-DCH Information IE in the RL Information IE received for the corresponding Radio Link(s) of the Primary Uplink Frequency to determine the transport bearer configuration in the new configuration for the radio links of the Secondary Uplink Frequency.]

- [FDD – If the *Transport Layer Address* IE and *Binding ID* IE is included for an E-DCH MAC-d flow in the *Additional E-DCH MAC-d Flows Specific Information* IE in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE in the *Additional E-DCH Cell Information Setup* IE or in the *Additional E-DCH RL Specific Information To Add* IE in the *Additional E-DCH Cell Information Addition* IE, then the DRNS may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for the concerned E-DCH MAC-d flow. If the DRNS establishes a transport bearer for the concerned E-DCH MAC-d flow the DRNS shall, for establishment of the transport bearer, include in the RADIO LINK ADDITION RESPONSE message the *Binding ID* IE and *Transport Layer Address* IE in the *Additional E-DCH MAC-d Flow Specific Information Response* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RL Add* IE for establishment of the transport bearer.]

[TDD – The DRNC shall always include in the RADIO LINK ADDITION RESPONSE message both the *Transport Layer Address* IE and the *Binding ID* IE for the transport bearer to be established for each DSCH and USCH of the RL.]

In the case of a set of co-ordinated DCHs, the DRNC shall include in the RADIO LINK ADDITION RESPONSE message the *Binding ID* IE and the *Transport Layer Address* IE for only one of the DCHs in the set of co-ordinated DCHs [FDD – for which the *Transport Bearer Not Requested Indicator* IE was not included].

If the DRNS needs to limit the user rate in the uplink of a DCH due to congestion caused by the UL UTRAN Dynamic Resources (see subclause 9.2.1.79) when starting to utilise a new Radio Link, the DRNC shall include in the RADIO LINK ADDITION RESPONSE message the *Allowed UL Rate* IE in the *DCH Information Response* IE for this Radio Link.

If the DRNS needs to limit the user rate in the downlink of a DCH due to congestion caused by the DL UTRAN Dynamic Resources (see subclause 9.2.1.79) when starting to utilise a new Radio Link, the DRNC shall include in the RADIO LINK ADDITION RESPONSE message the *Allowed DL Rate* IE in the *DCH Information Response* IE for this Radio Link.

[FDD – Transmit Diversity:]

[FDD – The DRNS shall activate any feedback mode diversity according to the received settings.]

[FDD – If the cell in which the RL is being added is capable to provide Close loop Tx diversity, the DRNC shall indicate the Closed loop timing adjustment mode of the cell by including the *Closed Loop Timing Adjustment Mode* IE in the RADIO LINK ADDITION RESPONSE message.]

[FDD – When the *Transmit Diversity Indicator* IE and/or *Transmit Diversity Indicator* IE in the *HS-DSCH FDD Secondary Serving Information* IE in the *Additional HS Cell Information RL Addition* IE is present the DRNS shall activate/deactivate the Transmit Diversity for each new Radio Link and/or secondary serving HS-DSCH Radio Link in accordance with the *Transmit Diversity Indicator* IE and/or *Transmit Diversity Indicator* IE in the *HS-DSCH FDD Secondary Serving Information* IE using the diversity mode of the existing Radio Link(s) and/or existing secondary serving HS-DSCH Radio Link.]

DL Power Control:

[FDD – If the *Primary CPICH Ec/No* IE or the *Primary CPICH Ec/No* IE and the *Enhanced Primary CPICH Ec/No* IE measured by the UE are included for an RL in the RADIO LINK ADDITION REQUEST message, the DRNS shall use this in the calculation of the Initial DL TX Power for this RL. If the *Primary CPICH Ec/No* IE is not present, the DRNS shall set the Initial DL TX Power based on the power relative to the Primary CPICH power used by the existing RLs.]

[TDD – If [3.84Mcps TDD and 7.68 Mcps TDD – the *DL Time Slot ISCP Info* IE] [1.28Mcps TDD – the *DL Time Slot ISCP Info LCR* IE] is included in the RADIO LINK ADDITION REQUEST message, the DRNS shall use it in the calculation of the Initial DL TX Power.]

[TDD – If the *Primary CCPCH RSCP Delta* IE is included, the DRNS shall assume that the reported value for Primary CCPCH RSCP is in the negative range as per TS 25.123 [24], and the value is equal to the *Primary CCPCH RSCP Delta* IE. If the *Primary CCPCH RSCP Delta* IE is not included and the *Primary CCPCH RSCP* IE is included, the DRNS shall assume that the reported value is in the non-negative range as per TS 25.123 [24], and the value is equal to the *Primary CCPCH RSCP* IE. The DRNS shall use it in the calculation of the Initial DL TX Power.]

[TDD – If the *Primary CCPCH RSCP* IE, *Primary CCPCH RSCP Delta* IE, [3.84Mcps TDD and 7.68 Mcps TDD – and the *DL Time Slot ISCP Info* IE] [1.28Mcps TDD – and the *DL Time Slot ISCP Info LCR* IE] are not present, the DRNS shall set the Initial DL TX Power based on the power relative to the Primary CCPCH power used by the existing RL.]

[FDD – The Initial DL TX Power shall be applied until UL synchronisation is achieved on the Uu interface for that RLS or Power Balancing is activated. No inner loop power control or power balancing shall be performed during this period. The DL power shall then vary according to the inner loop power control (see TS 25.214 [10] subclause 5.2.1.2) and the power control procedure (see 8.3.7).]

[TDD – The Initial DL TX Power shall be applied until UL synchronisation is achieved on the Uu interface for that RL. No inner loop power control shall be performed during this period. The DL power shall then vary according to the inner loop power control (see TS 25.224 [22] subclause 4.2.3.3).]

[3.84 Mcps TDD and 7.68 Mcps TDD – The DL TX power upper and lower limit is configured in the following way: The DRNC shall include the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the RADIO LINK ADDITION RESPONSE message. If the maximum or minimum power needs to be different for particular DCH type CCTrCHs, the DRNC shall include the value(s) for that CCTrCH in the *CCTrCH Maximum DL TX Power* IE and *CCTrCH Minimum DL TX Power*. The DRNS shall not transmit with a higher power than indicated by the appropriate *Maximum DL TX Power* IE/CCTrCH Maximum DL TX Power IE or lower than indicated by the appropriate Minimum DL TX Power IE/CCTrCH Minimum DL TX Power IE on any DL DPCH within each CCTrCH of the RL.]

[1.28 Mcps TDD – The DL TX power upper and lower limit is configured in the following way: The DRNC shall include the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the RADIO LINK ADDITION RESPONSE message. If the maximum or minimum power needs to be different for particular timeslots within a DCH type CCTrCH, the DRNC shall include the value(s) for that timeslot in the *Maximum DL TX Power* IE and *Minimum DL TX Power* within the *DL Timeslot Information LCR* IE. The DRNS shall not transmit with a higher power than indicated by the appropriate *Maximum DL TX Power* IE or lower than indicated by the appropriate *Minimum DL TX Power* IE on any DL DPCH within each timeslot of the RL.]

[FDD – If the *DPC Mode* IE is present in the RADIO LINK ADDITION REQUEST message, the DRNC shall apply the DPC mode indicated in the message, and be prepared that the DPC mode may be changed during the lifetime of the RL. If the *DPC Mode* IE is not present in the RADIO LINK ADDITION REQUEST message, DPC mode 0 shall be applied (see TS 25.214 [10]).]

The DRNC shall provide the configured *Maximum DL TX Power* IE and *Minimum DL TX Power* IE for every new RL to the SRNC in the RADIO LINK ADDITION RESPONSE message. The DRNS shall not transmit with a power higher than indicated by the *Maximum DL TX Power* IE or lower than indicated by the *Minimum DL TX Power* IE on any DL DPCH [FDD – or on the F-DPCH] of the RL [FDD – except, if the UE Context is configured to use DPCH in the downlink, during compressed mode, when the δP_{curr} , as described in TS 25.214 [10] subclause 5.2.1.3, shall be added to the maximum DL power for the associated compressed frame.]

[FDD – If the power balancing is active with the Power Balancing Adjustment Type of the UE Context set to "Individual" in the existing RL(s) and the RADIO LINK ADDITION REQUEST message includes the *DL Reference Power* IE, the DRNS shall activate the power balancing and use the *DL Reference Power* IE for the power balancing procedure in the new RL(s), if activation of power balancing by the RADIO LINK ADDITION REQUEST message is supported by the DRNS, according to subclause 8.3.15. In this case, the DRNC shall include the *DL Power Balancing Activation Indicator* IE in the *RL Information Response* IE in the RADIO LINK ADDITION RESPONSE message. If the DRNS starts the DL transmission and the activation of the power balancing at the same CFN, the initial power of the power balancing, i.e. P_{init} shall be set to the power level which is calculated based on the *Primary CPICH Ec/No* IE or the *Enhanced Primary CPICH Ec/No* IE (if received), or to the power level which is calculated based on the power relative to the Primary CPICH power used by the existing RLs.]

UL Power Control:

The DRNC shall also provide the configured UL Maximum SIR and UL Minimum SIR for every new RL to the SRNC in the RADIO LINK ADDITION RESPONSE message. These values are taken into consideration by DRNS admission control and shall be used by the SRNC as limits for the UL inner-loop power control target.

Neighbouring Cell Handling:

If there are UMTS neighbouring cell(s) to the cell in which a Radio Link was established then:

- The DRNC shall include in the RADIO LINK ADDITION RESPONSE message the Neighbouring FDD Cell Information IE and/or Neighbouring TDD Cell Information IE in the Neighbouring UMTS Cell Information IE for each neighbouring FDD cell and/or TDD cell respectively. In addition, if the information is available, the DRNC shall include in the RADIO LINK ADDITION RESPONSE message the Frame Offset IE, Primary CPICH Power IE, Cell Individual Offset IE, STTD Support Indicator IE, Closed Loop Model Support Indicator IE, Coverage Indicator IE, Antenna Co-location Indicator IE and HCS Prio IE in the Neighbouring FDD Cell Information IE, and the Frame Offset IE, Cell Individual Offset IE, DPCH Constant Value IE and the PCCPCH Power IE, Coverage Indicator IE, Antenna Co-location Indicator IE and HCS Prio IE in the Neighbouring TDD Cell Information IE or the Neighbouring TDD Cell Information IE includes the Sync Case IE set to "Case1", the DRNC shall include the Time SlotFor SCH IE in the Neighbouring TDD Cell Information IE. If the Neighbouring TDD Cell Information IE includes the Sync Case IE set to "Case2", the DRNC shall include the SCH Time Slot IE in the Neighbouring TDD Cell Information IE.
- If a UMTS neighbouring cell is not controlled by the same DRNC, the DRNC shall also include in the RADIO LINK ADDITION RESPONSE message the CN PS Domain Identifier IE and/or CN CS Domain Identifier IE which are the identifiers of the CN nodes connected to the RNC controlling the UMTS neighbouring cell.
- [FDD The DRNC shall include in the RADIO LINK ADDITION RESPONSE message the *DPC Mode Change Support Indicator* IE for each neighbour cell in the *Neighbouring FDD Cell Information* IE if this information is available.]
- The DRNC shall include the *Cell Capability Container FDD* IE, the *Cell Capability Container TDD* IE, *Cell Capability Container 7.68Mcps TDD* IE, the *Cell Capability Container TDD LCR* IE and/or the *Cell Capability Container Extension FDD* IE if the DRNC is aware that the neighbouring cell supports any functionality listed in 9.2.2.D, 9.2.3.1a, 9.2.3.1b and 9.2.2.123.
- [FDD The DRNC shall, if supported, include the *Cell List Validity Indicator* IE if the neighbouring cell is multi cell capable and/or dual band capable but the cell can not be the serving HS-DSCH in a multicell and/or dual band configuration. Hence the cell can only serve as the secondary serving HS-DSCH cell. When *Cell List Validity Indicator* IE is included the SRNC should ignore the indicated cell list(s).]
- [FDD For each cell in the *Secondary Serving Cell List* IE that is Multi Cell E-DCH capable, indicated in the *Cell Capability Container Extension FDD* IE by the "Multi Cell E-DCH Support Indicator" bit = "1", and is restricted for use as an Additional E-DCH on the secondary uplink frequency with the cell identified by the *C-ID* IE as the corresponding cell of the Primary uplink frequency, the DRNS shall, if supported, include the *Multicell E-DCH Restriction* IE set to "TRUE".]
- For the UMTS neighbouring cells which are controlled by the DRNC, the DRNC shall report in the RADIO LINK ADDITION RESPONSE message the restriction state of those cells, otherwise *Restriction State Indicator* IE may be absent. The DRNC shall include the *Restriction State Indicator* IE for the neighbouring cells which are controlled by the DRNC in the *Neighbouring FDD Cell Information* IE, the *Neighbouring TDD Cell Information* IE and the *Neighbouring TDD Cell Information LCR* IE.
- If available, the DRNC shall include the *SNA Information* IE for the concerned neighbouring cells in the *Neighbouring FDD Cell Information* IE, the *Neighbouring TDD Cell Information* IE and the *Neighbouring TDD Cell Information LCR* IE.
- If MOCN or GWCN network sharing configuration is used then the DRNC shall include the broadcasted PLMN identities of concerned neighbouring cells in the *Multiple PLMN List* IE in the *Neighbouring FDD Cell Information* IE, the *Neighbouring TDD Cell Information* IE and the *Neighbouring TDD Cell Information LCR* IE.

- If available, the DRNC shall include the *Frequency Band Indicator* IE for the concerned neighbouring cells in the *Neighbouring FDD Cell Information* IE.
- If the number of neighbouring UMTS RNCs is beyond the predefined maximum number, the DRNC shall, if supported, include the remaining neighbouring information in the *Neighbouring UMTS Cell Information Extension* IE. The IE filling rules in the Neighbouring UMTS Cell Information shall also apply to the *Neighbouring UMTS Cell Information Extension* IE.

If there are GSM neighbouring cells to the cell(s) in which a radio link is established, the DRNC shall include the *Neighbouring GSM Cell Information* IE in the RADIO LINK ADDITION RESPONSE message for each of the GSM neighbouring cells. If available the DRNC shall include the *Cell Individual Offset* IE, and if the *Cell Individual Offset* IE alone cannot represent the value of the offset, the DRNC shall also include the *Extended GSM Cell Individual Offset* IE in the *Neighbouring GSM Cell Information IE*. If available the DRNC shall also include the *Coverage Indicator* IE, *Antenna Co-location Indicator* IE and *HCS Prio* IE in the *Neighbouring GSM Cell Information* IE. If available, the DRNC shall also include the *SNA Information* IE for the concerned neighbouring cells in the *Neighbouring GSM Cell Information* IE.

When receiving the *SNA Information* IE in the RADIO LINK ADDITION RESPONSE message, the SRNC should use it to restrict cell access based on SNA information. See also TS 25.401 [40] for a broader description of the SNA access control.

If there are GERAN neighbouring cells to the cell(s) where a radio link is established, the DRNC shall include the *GERAN Cell Capability* IE in the *Neighbouring GSM Cell Information* IE that is included in the RADIO LINK ADDITION RESPONSE message for each of the GERAN cells.

If there are GERAN Iu-mode neighbouring cells to the cell(s) where a radio link is established, the DRNC shall include, if available, the *GERAN Classmark* IE in the *Neighbouring GSM Cell Information* IE that is included in the RADIO LINK ADDITION RESPONSE message for each of the GERAN Iu-mode neighbouring cells. TS 43.051 [39] defines when the transmission of the *GERAN Classmark* IE will be required at the initiation of the Relocation Preparation procedure.

If there are E-UTRA neighbouring cells to the cell(s) in which a radio link is established, the DRNC shall include the *Neighbouring E-UTRA Cell Information* IE in the RADIO LINK ADDITION RESPONSE message for each of the E-UTRA neighbouring cells, and may also include the *PCI* IE, *TAC* IE and *PLMN List* IE in the Neighbouring *E-UTRA Cell Information* IE in the RADIO LINK ADDITION RESPONSE message.

[1.28Mcps TDD – Uplink Synchronisation Parameters LCR:]

[1.28Mcps TDD – If the *Uplink Synchronisation Parameters LCR* IE is present, the DRNC shall use the indicated values of *Uplink synchronisation stepsize* IE and *Uplink synchronisation frequency* IE when evaluating the timing of the UL synchronisation.]

[1.28Mcps TDD – Shared physical channels Synchronisation Detection:]

[1.28Mcps TDD – If HS-PDSCH and E-PUCH are configured but no DPCH is configured for the UE, then the DRNS shall include the *Out-of-sync Detection Window* IE in the *HS-DSCH TDD Information Response* IE in the RADIO LINK ADDITON RESPONSE message.]

[1.28Mcps TDD – Uplink Timing Advance Control LCR:]

[1.28Mcps TDD – The DRNC shall include the *Uplink Timing Advance Control LCR* IE in the RADIO LINK ADDITION RESPONSE message.]

[1.28Mcps TDD – PowerControl GAP:]

[1.28Mcps TDD – If applied in the DRNS, the DRNC may include the *PowerControl GAP* IE in the RADIO LINK ADDITION RESPONSE message.]

[1.28Mcps TDD – E-UTRAN Inter-RAT measurement:]

[1.28Mcps TDD – If the RADIO LINK ADDITION REQUEST message includes the *Idle Interval Configuration Indicator* IE, if supported, the DRNC shall include the *Idle Interval Information* IE in the RADIO LINK ADDITION RESPONSE message.]

[1.28Mcps TDD – Inter-frequency/ Inter-RAT measurement:]

[1.28Mcps TDD – If the RADIO LINK ADDTION REQUEST message includes the *DCH Measurement Type indicator* IE, if supported, the DRNS shall include the *Measurement purpose* IE and the *Measurement occasion pattern sequence parameters* IE in the *DCH Measurement Occasion Information* IE in the RADIO LINK ADDTION RESPONSE message to configure the measurement occasion pattern(s) indicated by the *DCH Measurement Type indicator* IE.]

MBMS Handling:

If the UE Link is currently stored in the UE Context and an MBMS session for some MBMS bearer services contained in the UE Link is ongoing in some of the cells identified by the *C-ID* IEs in the RADIO LINK ADDITION REQUEST message, the DRNC shall include for each of these active MBMS bearer services in the *Active MBMS Bearer Service List* IE the *Transmission Mode* IE in the concerned *RL Information Response* IEs in the RADIO LINK ADDITION RESPONSE message.

If the UE Link is currently stored in the UE Context and an MBMS preferred frequency layer for some active MBMS bearer services contained in the UE Link is set in some of the cells identified by the *C-ID* IEs in the RADIO LINK ADDITION REQUEST message, the DRNC shall include for each of these active MBMS bearer services in the *Active MBMS Bearer Service List* IE the *Preferred Frequency Layer* IE in the concerned *RL Information Response* IEs in the RADIO LINK ADDITION RESPONSE message.

[FDD – HS-DSCH Preconfiguration for Enhanced HS Serving Cell Change]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *HS-DSCH Preconfiguration Setup* IE in the *RL Information* IE for a Radio Link not indicated by the *HS-PDSCH RL ID* IE in the *HS-DSCH Serving Cell Change Information* IE the DRNS shall, if supported, preconfigure the indicated cells for Enhanced HS Serving Cell Change according to TS 25.308 [63]:]

- [FDD The DRNS shall preconfigure sets of HS-SCCH codes on the cells preconfigured for HS-DSCH, primary serving HS-DSCH cell, as well as on the secondary serving HS-DSCH cells. The primary serving HS-DSCH cell is designated through the *C-ID* IE part of the *RL Information* IE in the RADIO LINK ADDITION REQUEST message. The list of secondary serving HS-DSCH cells is designated by the list of *Secondary C-ID* Iesin the *HS-DSCH Preconfiguration Setup* IE part of the *RL Information* IE in the RADIO LINK ADDITION REQUEST message.]
- [FDD The number of HS-SCCH codes to preconfigure for each cell may be optionally specified:]
 - [FDD by the *Num Primary HS-SCCH Codes* IE in the *HS-DSCH Preconfiguration Setup* IE, for the primary serving HS-DSCH cell]
 - [FDD by the *Num Secondary HS-SCCH Codes* IE in *the Secondary Cells* IE in the *HS-DSCH Preconfiguration Setup* IE for each of the secondary serving HS-DSCH cells]
- [FDD If *Num Primary HS-SCCH Codes* IE or *Num Secondary HS-SCCH Codes* IE is not included in the message the number and distribution of codes on primary and any secondary cells shall be preconfigured to satisfy any limitations in TS 25.214 [10].
- [FDD The DRNS shall return these codes in the *Sets of HS-SCCH Codes* IE along with the corresponding per- cell *HS-DSCH-RNTI* IE in the *HS-DSCH Preconfiguration Info* IE in the *RL Information Response* IE of the RADIO LINK ADDITION RESPONSE message or in the *Successful RL Information Response* IE of the RADIO LINK ADDITION FAILURE message.]
- [FDD The DRNS shall use the first in the numbered list the primary serving HS-DSCH cell's of HS-SCCH codes in the HS-SCCH Preconfigured Codes IE sent to the SRNC to signal the Target Cell HS-SCCH Order defined in TS 25.331 [16]].
- [FDD The DRNS shall include, in the *HS-DSCH Preconfiguration Info* IE in the *RL Information Response* IE in the RADIO LINK ADDITION RESPONSE message or in the *Successful RL Information Response* IE of the RADIO LINK ADDITION FAILURE message, IEs according to the rules defined for HS-DSCH Setup at Serving HS-DSCH Radio Link Change and:]
 - [FDD if *HARQ Preamble Mode* IE is included in the *HS-DSCH Preconfiguration Setup* IE the *HARQ Preamble Mode Activation Indicator* IE]

- [FDD if *MIMO Activation Indicator* IE is included in the *HS-DSCH Preconfiguration Setup* IE or in the *Secondary Cells* IE in the *HS-DSCH Preconfiguration Setup* IE the Pilot Configuration and MIMO N/M Ratio in *MIMO Information Response* IE]
- [FDD if *Ordinal number of frequency* IE is included in the *Secondary Cells* IE in the *HS-DSCH Preconfiguration Setup* IE]
- [FDD if *HS-DSCH MAC-d PDU Size Format* IE is included in the *HS-DSCH Preconfiguration Setup* IE and set to "Flexible MAC-d PDU Size" and if Sixtyfour QAM will not be used for the cell in the preconfiguration the *HS-DSCH TB Size Table Indicator* IE for each preconfigured cell.]
- [FDD if Sixtyfour QAM Usage Allowed Indicator IE is included in the Secondary Cells IE in the HS-DSCH Preconfiguration Setup IE or in the HS-DSCH Preconfiguration Setup IE the SixtyfourQAM DL Usage Indicator IE for each preconfigured cell]
- [FDD if Continuous Packet Connectivity HS-SCCH less Information IE is included in the HS-DSCH Preconfiguration Setup IE the Continuous Packet Connectivity HS-SCCH less Information Response IE]
- [FDD if the UE with enhanced HS-SCCH support indicator IE is included in the HS-DSCH Preconfiguration Setup IE, then the DRNS shall store this information in the preconfigured configuration.]
- [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH Preconfiguration Setup* IE with the bit *UE DTXDRX related HS-SCCH orders uniform behavior indicator* set to 0, then the DRNS shall, if supported, include the *Support of dynamic DTXDRX related HS-SCCH order* IE in the *HS-DSCH Preconfiguration Info* IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD the SixtyfourQAM DL Support Indicator IE may be included]
- [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH Preconfiguration Setup* IE, then the DRNS may store this information in the preconfigured configuration.]
- [FDD the DRNS shall, if supported, include in the *Sets of HS-SCCH Codes* IE the *Measurement Power Offset* IE for each preconfigured cell.]
- [FDD If the *Power Offset For S-CPICH for MIMO Request Indicator* IE is included in the *HS-DSCH Preconfiguration Setup* IE or in the *Secondary Cells* IE in the *HS-DSCH Preconfiguration Setup* IE, the DRNC shall, if supported and MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where HS-DSCH / secondary HS-DSCH is preconfigured, include the *Power Offset For S-CPICH for MIMO* IE in the *HS-DSCH Preconfiguration Info* IE or in the *Sets of HS-SCCH Codes* IE in the *HS-DSCH Preconfiguration Info* IE for each preconfigured cell in the RADIO LINK ADDITION RESPONSE message. If zero power offset the DRNC may include the *Power Offset For S-CPICH for MIMO* IE.]

[FDD – The DRNS shall include in the *HS-DSCH Preconfiguration Info* IE in the *RL Information Response* IE in the RADIO LINK ADDITION RESPONSE message or in the *Successful RL Information Response* IE of the RADIO LINK ADDITION FAILURE message the *E-DCH FDD DL Control Channel Information* containing the preconfigured configuration of the E-DCH serving cell according to the rules defined for Serving E-DCH Radio Link Change as follows:]

- [FDD The DRNS shall allocate for the preconfigured configuration a primary E-RNTI identifier or a
 secondary E-RNTI identifier or both for the new Serving E-DCH Radio Link and include these E-RNTI
 identifiers along with the channelisation code of the corresponding E-AGCH in the E-DCH FDD DL
 Control Channel Information IE.]
- [FDD The DRNS may preconfigure the Serving Grant Value IE and Primary/Secondary Grant Selector
 IE for the initial grant for the serving E-DCH RL and include these values in the E-DCH FDD DL
 Control Channel Information IE.]

[FDD – If the *HS-DSCH Preconfiguration Setup* IE includes the *E-DCH Indicator* IE for a secondary cell, the DRNS shall include in the *Additional E-DCH Preconfiguration Information* IE in the *HS-DSCH Preconfiguration Info* IE in the *RL Information Response* IE in the RADIO LINK ADDITION RESPONSE message or in the *Successful RL Information Response* IE of the RADIO LINK ADDITION FAILURE message the *E-DCH FDD DL Control Channel Information* IE containing the preconfigured configuration of

the Additional E-DCH serving cell, corresponding to the cell indicated with the *E-DCH Indicator* IE, according to the rules defined for Serving Additional E-DCH Radio Link Change as follows:]

- [FDD The DRNS shall allocate for the preconfigured configuration a primary E-RNTI identifier or a secondary E-RNTI identifier or both for the new Serving Additional E-DCH Radio Link and include these E-RNTI identifiers along with the channelisation code of the corresponding *E-AGCH in the E-DCH FDD DL Control Channel Information* IE.]
- [FDD The DRNS may preconfigure the *Serving Grant Value* IE and *Primary/Secondary Grant Selector* IE for the initial grant for the serving Additional E-DCH RL and include these values in the *E-DCH FDD DL Control Channel Information* IE.]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Non-Serving RL Preconfiguration Setup* IE in the *RL Information* IE and:]

- [FDD if the choice of *new Serving RL* is "New Serving RL in the DRNS", the DRNC may include the *New non-serving RL E-DCH FDD DL Control Channel Information A* IE and/or *New non-serving RL E-DCH FDD DL Control Channel Information B* IE in the *Non-Serving RL Preconfiguration Info* IE for the RL in the RADIO LINK ADDITION RESPONSE message.]
- [FDD if the choice of *new Serving RL* is "New Serving RL Not in the DRNS", the DRNC may include the *New non-serving RL E-DCH FDD DL Control Channel Information C* IE in the *Non-Serving RL Preconfiguration Info* IE for the RL in the RADIO LINK ADDITION RESPONSE message.]
- [FDD if the choice of *new Serving RL* is "New Serving RL in the DRNS or New Serving RL Not in the DRNS", the DRNC may include the *New non-serving RL E-DCH FDD DL Control Channel Information A* IE, the *New non-serving E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving E-DCH FDD DL Control Channel Information C* for the RL in the *Non-Serving RL Preconfiguration Info* IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD if the *Additional E-DCH Non-Serving RL Preconfiguration Setup* IE is included, the DRNC may include the *New non-serving RL E-DCH FDD DL Control Channel Information A* IE, the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information C* IE according to the choice of new Serving RL in *Additional E-DCH New non-serving RL E-DCH FDD DL Control Channel Information* IE for the additional non serving E-DCH RL in the *Non-Serving RL Preconfiguration Info* IE in the RADIO LINK ADDITION RESPONSE message.]

General:

If the RADIO LINK ADDITION REQUEST message includes the *RL Specific DCH Information* IE, the DRNC may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for the DCH or the set of co-ordinated DCHs [FDD – for which the *Transport Bearer Not Requested Indicator* IE was not included].

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Transport Bearer Not Requested Indicator* IE set to "Transport Bearer shall not be Established" for a DCH, then the DRNC shall not establish a transport bearer for the concerned DCH and shall include the *Transport Bearer Not Setup Indicator* IE for the corresponding DCH in the RADIO LINK ADDITION RESPONSE message.]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Transport Bearer Not Requested Indicator* IE set to "Transport Bearer may not be Established" for a DCH and:]

- [FDD if the DRNC establishes a transport bearer for the concerned DCH, the DRNC shall include in the RADIO LINK ADDITION RESPONSE message the *Binding ID* IE and *Transport Layer Address* IE for establishment of a transport bearer for the DCH being established.]
- [FDD if the DRNC does not establish a transport bearer for the concerned DCH, the DRNC shall include the *Transport Bearer Not Setup Indicator* IE for the corresponding DCH in the RADIO LINK ADDITION RESPONSE message.]

Depending on local configuration in the DRNS, the DRNC may include in the RADIO LINK ADDITION RESPONSE message the *UTRAN Access Point Position* IE and the geographical co-ordinates of the cell, represented either by the *Cell GAI* IE or by the *Cell GA Additional Shapes* IE. If the DRNC includes the *Cell*

GA Additional Shapes IE in the RADIO LINK ADDITION RESPONSE message, it shall also include the Cell GAI IE.

For each Radio Link established in a cell in which at least one URA Identity is being broadcast, the DRNC shall include in the RADIO LINK ADDITION RESPONSE message a URA Information for this cell including the *URA ID* IE, the *Multiple URAs Indicator* IE indicating whether or not multiple URA Identities are being broadcast in the cell, and the *RNC-ID* IEs of all other RNCs that have at least one cell within the URA identified by the *URA ID* IE.

[3.84Mcps TDD – The DRNC shall include the *Secondary CCPCH Info TDD* IE in the RADIO LINK ADDITION RESPONSE message if at least one *DSCH Information Response* IE or *USCH Information Response* IE is included in the message and at least one DCH is configured for the radio link. The DRNC shall also include the *Secondary CCPCH Info TDD* IE in the RADIO LINK ADDITION RESPONSE message if at least one *DSCH Information Response* IE or *USCH Information Response* IE is included in the message and the SHCCH messages for this radio link will be transmitted over a different secondary CCPCH than selected by the UE from system information.]

[1.28 Mcps TDD – The DRNC shall include the *Secondary CCPCH Info TDD LCR* IE in the RADIO LINK ADDITION RESPONSE message if at least one *DSCH Information Response LCR* IE or *USCH Information Response LCR* IE is included in the message and at least one DCH is configured for the radio link. The DRNC shall also include the *Secondary CCPCH Info TDD LCR* IE in the RADIO LINK ADDITION RESPONSE message if at least one *DSCH Information Response LCR* IE or *USCH Information Response LCR* IE is included in the message and the SHCCH messages for this radio link will be transmitted over a different secondary CCPCH than selected by the UE from system information.]

[7.68 Mcps TDD – The DRNC shall include the Secondary CCPCH Info 7.68 Mcps TDD IE in the RADIO LINK ADDITION RESPONSE message if at least one DSCH Information Response 7.68 Mcps IE or USCH Information Response 7.68 Mcps IE is included in the message and at least one DCH is configured for the radio link. The DRNC shall also include the Secondary CCPCH Info 7.68 Mcps TDD IE in the RADIO LINK ADDITION RESPONSE message if at least one DSCH Information Response 7.68 Mcps IE or USCH Information Response 7.68 Mcps IE is included in the message and the SHCCH messages for this radio link will be transmitted over a different secondary CCPCH than selected by the UE from system information.]

If the *Permanent NAS UE Identity* IE is present in the RADIO LINK ADDITION REQUEST message, the DRNS shall store the information for the considered UE Context for the lifetime of the UE Context.

If the RADIO LINK ADDITION REQUEST message includes a *C-ID* IE corresponding to a cell reserved for operator use and the Permanent NAS UE Identity is available in the DRNC for the considered UE Context, the DRNC shall use this information to determine whether it can add the Radio Link on this cell or not.

If the HCS priority information is available in the DRNS, it shall include the *HCS Prio* IE for each of the established RLs in the RADIO LINK ADDITION RESPONSE message.

The DRNS shall start receiving on the new RL(s) after the RLs are successfully established.

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Initial DL DPCH Timing Adjustment Allowed* IE, then the DRNS may perform an initial DL DPCH Timing Adjustment (i.e. perform a timing advance or a timing delay with respect to the SFN timing) on a Radio Link. In this case, the DRNS shall include, for the concerned Radio Link(s), the *Initial DL DPCH Timing Adjustment* IE in the *Radio Link Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Synchronisation Indicator* IE, set to "Timing Maintained Synchronisation", the DRNS shall use synchronisation procedure B according to subclause 4.3.2.4 in TS 25.214 [10]. The DRNS shall select the TPC pattern as if "first RLS indicator" is set to "first RLS" according to subclause 5.1.2.2.1.2 in TS 25.214 [10].]

[FDD – If the UE Context is configured for F-DPCH Slot Format operation, then the DRNS shall include the *F-DPCH Slot Format* IE in the RADIO LINK ADDITION RESPONSE message.]

[FDD - Radio Link Set Handling:]

[FDD – For each RL not having a common generation of the TPC commands in the DL with another RL, the DRNS shall assign to the RL a unique value for the *RL Set ID* IE which uniquely identifies the RL as an RL

Set within the UE Context. In case of E-DCH, the generation of E-HICH information for RLs in different RL Sets shall not be common.]

[FDD – For all RLs having a common generation of the TPC commands in the DL with another new or existing RL, the DRNS shall assign to each RL the same value for the *RL Set ID* IE which uniquely identifies these RLs as members of the same RL Set within the UE Context. In case of E-DCH, the generation of E-HICH related information for all RLs in a RL Set shall be common.]

[FDD – After addition of the new RL(s), the UL out-of-sync algorithm defined in TS 25.214 [10] shall, for each of the previously existing and newly established RL Set(s), use the maximum value of the parameters N_OUTSYNC_IND and T_RLFAILURE that are configured in the cells supporting the radio links of the RL Set. The UL in-sync algorithm defined in TS 25.214 [10] shall, for each of the established RL Set(s), use the minimum value of the parameters N_INSYNC_IND that are configured in the cells supporting the radio links of the RL Set.]

[FDD – For each E-DCH RL which has or can have a common generation of E-RGCH information with another RL (current or future) when the DRNS would contain the E-DCH serving RL, the DRNS shall include the *E-DCH RL Set ID* IE in the RADIO LINK ADDITION RESPONSE message. The value of the *E-DCH RL Set ID* IE shall allow the SRNC to identify the E-DCH RLs that have or can have a common generation of E-RGCH information.]

[FDD – Serving HS-DSCH Radio Link Change:]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *HS-DSCH Serving Cell Change Information* IE, then the *HS-PDSCH RL ID* IE indicates the new Serving HS-DSCH Radio Link:]

- [FDD In the new configuration the DRNS shall allocate the HS-PDSCH resources for the new Serving HS-PDSCH Radio Link.]
- [FDD The DRNS may include the *HARQ Memory Partitioning* IE in the *HS-DSCH FDD Information* Response IE in the RADIO LINK ADDITION RESPONSE message. The *HARQ Memory Partitioning* IE may contain the *HARQ Memory Partitioning Information Extension For MIMO* IE.]
- [FDD If fields are to be included in the User Plane by the SRNC to handle TNL Congestion Control for HSDPA in the DRNS, then the DRNC shall include the *User Plane Congestion Fields Inclusion* IE in the *HS-DSCH Information Response* IE.]
- [FDD The DRNC shall allocate a new HS-DSCH-RNTI to the UE Context and include the *HS-DSCH-RNTI* IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD If a reset of the MAC-hs is not required the DRNS shall include the *MAC-hs Reset Indicator* IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD The DRNC shall include the *Measurement Power Offset* IE in the *HS-DSCH Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD The DRNS shall allocate HS-SCCH codes corresponding to the HS-DSCH and include the *HS-SCCH Specific Information Response* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD The DRNC shall include the *HS-PDSCH And HS-SCCH Scrambling Code* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
- If the *TNL QoS* IE is included for a MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink between the DRNS and the SRNC for the related MAC-d flow.
- [FDD If the *HS-DSCH Serving Cell Change Information* IE includes the *Continuous Packet Connectivity HS-SCCH less Information* IE, then:]
 - [FDD The DRNS shall configure the Serving HS-DSCH Radio Link indicated by the *HS-PDSCH RL ID* IE for Continuous Packet Connectivity HS-SCCH less operation according to TS 25.214 [10].]

- [FDD The DRNS shall allocate the HS-PDSCH codes needed for HS-SCCH less operation and include the *Continuous Packet Connectivity HS-SCCH less Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD If at least one of *HS-PDSCH Second Code Support* IE is set to "True", then the DRNC shall include *HS-PDSCH Second Code Index* IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD If the HS-DSCH Serving Cell Change Information IE includes the Continuous Packet Connectivity DTX-DRX Information IE, then:]
 - [FDD The DRNS shall configure the concerned UE Context for Continuous Packet Connectivity DTX operation according to TS 25.214 [10].]
 - [FDD If *DRX Information* IE is included in the *Continuous Packet Connectivity DTX-DRX Information* IE, then the DRNS shall configure the concerned UE Context for Continuous Packet Connectivity DRX operation according to TS 25.214 [10].]
- [FDD If the UE Context is configured with Sixtyfour QAM allowed for the serving HS-DSCH Radio Link and not used in the current configuration and then if the DRNS decides to use 64 QAM in the new configuration, then it shall include the *SixtyfourQAM DL Usage Indicator* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD If MAC-ehs is applied in the new configuration, and if Sixtyfour QAM will not be used, the DRNS shall include the *HS-DSCH TB Size Table Indicator* IE in the *HS-DSCH FDD Information Response* IE in the *HS-DSCH Serving Cell Change Information Response* IE in the RADIO LINK ADDITION RESPONSE message if it decides to use the octet aligned table defined in TS 25.321 [41] for HS-DSCH Transport Block Size signalling.]

[FDD – HS-DSCH Setup on a New Radio Link at Serving HS-DSCH Radio Link Change:]

[FDD – If the *HS-DSCH Information* IE is present in the *HS-DSCH Serving Cell Change Information* IE, then:]

- [FDD The DRNS shall setup the requested HS-PDSCH resources on the Serving HS-DSCH Radio Link indicated by the HS-PDSCH RL ID IE.]
- [FDD the *HS-DSCH Information* IE defines the new HS-DSCH configuration in the DRNS to be used on the new HS-DSCH Radio Link.]
- [FDD The DRNC shall include the *HARQ Memory Partitioning* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message. The *HARQ Memory Partitioning* IE shall either contain the *HARQ Memory Partitioning Information Extension For MIMO* IE or the *Number of Processes* IE set to a value higher than "8", if the *MIMO Activation Indicator* IE is included in the *HS-DSCH Information* IE.]
- [FDD The DRNS may use the *Traffic Class* IE for a specific HS-DSCH MAC-d flow to determine the transport bearer characteristics to apply between DRNC and Node B. If *TrCH Source Statistics Descriptor* IE is present with the value "RRC" in the *HS-DSCH MAC-d Flows Information* IE, then the DRNC should ignore the *Traffic Class* IE. If the *TNL QoS* IE is included for a MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink between the DRNS and the SRNC for the related MAC-d flow.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *MAC-hs Guaranteed Bit Rate* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, then the DRNS shall use this information to optimise MAC-hs scheduling decisions for the related HSDPA Priority Queue.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *Discard Timer* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, then the DRNS shall use this information to discard out-of-date MAC-hs SDUs from the related HSDPA Priority Queue.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *Maximum MAC-d PDU Size Extended* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, then the DRNS shall ignore the *SID* IE and *MAC-d PDU Size* IE in the *MAC-d PDU Size*

Index IE and use *Maximum MAC-d PDU Size Extended* IE to optimise capacity allocation for the related HSDPA Priority Queue.]

- [FDD The DRNC shall include the *HS-DSCH Initial Capacity Allocation* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message for every HS-DSCH MAC-d flow being established, if the DRNS allows the SRNC to start transmission of MAC-d PDUs before the DRNS has allocated capacity on user plane as described in TS 25.425 [32]. If RADIO LINK ADDITION REQUEST message includes *HS-DSCH MAC-d PDU Size Format* IE in the *HS-DSCH Information* IE set to "Flexible MAC-d PDU Size", then DRNC shall only set in the *HS-DSCH Initial Capacity Allocation* IE the values for the peer of *Scheduling Priority Indicator* IE and *Maximum MAC-d PDU Size Extended* IE to the values of the corresponding peer I in RADIO LINK ADDITION REQUEST in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE for a Priority Queue including *Scheduling Priority Indicator* IE and *Maximum MAC-d PDU Size Extended* IE.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *HS-SCCH Power Offset* IE in the *HS-DSCH Information* IE, then the DRNS may use this value to determine the HS-SCCH power. The HS-SCCH Power Offset should be applied for any HS-SCCH transmission to this UE.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *HARQ Preamble Mode* IE in the *HS-DSCH Information* IE, then the DRNS shall use the indicated HARQ Preamble Mode as described in TS 25.214 [10], if HS-DPCCH ACK/NACK preamble and postamble is supported. Then, in this case, if the mode 1 is applied, the DRNC shall include the *HARQ Preamble Mode Activation Indicator* IE in the *HS-DSCH Information Response* IE in the RADIO LINK ADDITION RESPONSE message. If the *HARQ Preamble Mode* IE is not included or if the mode 0 is applied, then the DRNC shall not include the *HARQ Preamble Mode Activation Indicator* IE in the *HS-DSCH Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *HS-DSCH MAC-d PDU Size Format* IE in the *HS-DSCH Information* IE, then the DRNS shall use the indicated format in user plane frame structure for HS-DSCH channels (TS 25.425 [32]) and MAC-hs (TS 25.321 [41]).]
- [FDD If the MIMO Activation Indicator IE is included in the HS-DSCH FDD Information IE, then]
 - [FDD The DRNS shall activate the MIMO mode for the HS-DSCH Radio Link.]
 - [FDD The DRNS shall decide the pilot configuration and the UE reporting configuration (N/M ratio) according to TS 25.214 [10] for MIMO and include the *MIMO Information Response* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
 - [FDD If the *Power Offset For S-CPICH for MIMO Request Indicator* IE is included, the DRNC shall, if supported and MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where the Serving HS-DSCH Radio Link is established, include the *Power Offset For S-CPICH for MIMO* IE in the *HS-DSCH FDD Information Response* IE. If zero power offset the DRNC may include the *Power Offset For S-CPICH for MIMO* IE.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Information IE, then the DRNS may if the value is set to "allowed" use 64 QAM for the HS-DSCH Radio Link, and the DRNS shall include the SixtyfourQAM DL Usage Indicator IE in the HS-DSCH FDD Information Response IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD If the *Sixtyfour QAM Usage Allowed Indicator* IE is included in the *HS-DSCH FDD Information* IE with value set to "not allowed", then the DRNS shall not use 64 QAM for the HS-DSCH Radio Link.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *HS-DSCH MAC-d PDU Size Format* IE set to "Flexible MAC-d PDU Size" and if Sixtyfour QAM will not be used, the DRNS shall include the *HS-DSCH TB Size Table Indicator* IE in the *HS-DSCH FDD Information Response* IE in the *HS-DSCH Serving Cell Change Information Response* IE in the RADIO LINK ADDITION RESPONSE message if it decides to use the octet aligned table defined in TS 25.321 [41] for HS-DSCH Transport Block Size signalling.]
- [FDD If the *UE with enhanced HS-SCCH support indicator* IE is included in the *HS-DSCH FDD Information* IE, then the DRNS may use:]
 - [FDD a different HS-SCCH in consecutive TTIs for this UE]

- [FDD HS-SCCH orders for the case of HS-SCCH-less operation to this UE]
- [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH FDD Information* IE the DRNS may use the supported HSDPA functions for this UE.]
 - [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH FDD Information* IE with the bit *UE DTXDRX related HS-SCCH orders uniform behavior indicator* set to 0, then the D shall, if supported, include the *Support of dynamic DTXDRX related HS-SCCH order* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes *DL RLC PDU Size Format* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, the *DL RLC PDU Size Format* IE may be used by the DRNS to determine the allocated capacity on user plane as described in TS 25.425 [32].]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *UE Aggregate Maximum Bit Rate Enforcement Indicator* IE in the *Priority Queue Information* IE in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, then the DRNS shall, if supported, consider the data of the HSDPA Priority Queue for UE Aggregate Maximum Bit Rate Enforcement.]
- [FDD If the *Single Stream MIMO Activation Indicator* IE is included in the *HS-DSCH FDD Information* IE in the *HS-DSCH Serving Cell Change Information* IE, then the DRNS shall activate the Single Stream MIMO for the HS-DSCH Radio Link.]
- [FDD The DRNC may include the *Transport Layer Address* IE and the *Binding ID* IE for HS-DSCH MAC-d flow in the *HS-DSCH FDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD If the *Serving Cell Change CFN* IE is included in the RADIO LINK ADDITION REQUEST message, then the DRNS shall activate the resources that are allocated for the new serving HS-DSCH Radio Link at the next coming CFN with a value equal to the value requested by the SRNC, or earlier. In this case, in the new configuration the DRNS shall, if applicable, de-allocate the HS-PDSCH resources of the old Serving HS-PDSCH Radio Link. The DRNS shall deactivate those resources at the next coming CFN with a value equal to the value requested by the SRNC.]
- [FDD If the *Serving Cell Change CFN* IE is not included then the DRNS shall activate immediately the resources that are allocated for the new serving HS-PDSCH Radio Link, and shall keep active the resources that are allocated for the previous serving HS-PDSCH Radio Link.]
- [FDD If the requested Serving HS-DSCH Radio Link Change was successful or unsucessful, the DRNS shall indicate this in the *HS-DSCH Serving Cell Change Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]

[FDD – Secondary Serving HS-DSCH Radio Link Change:]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Additional HS Cell Information RL Addition* IE, then the *HS-PDSCH RL ID* IE indicates the new Serving HS-DSCH Radio Link:]

- [FDD In the new configuration the DRNS shall allocate the HS-PDSCH resources for the new secondary serving HS-PDSCH Radio Link. Non cell specific secondary serving Radio Link and non cell specific secondary serving HS-DSCH parameters take the same values as for the serving HS-DSCH cell.]
- [FDD If the *Ordinal Number Of Frequency* IE is included in the *HS-DSCH FDD Secondary Serving Information* IE, and the new configuration contains more than one secondary serving HS-DSCH Radio Link, then the DRNS shall use this value in the physical layer.]
- [FDD The DRNC shall allocate a new HS-DSCH-RNTI to the UE Context and include the *HS-DSCH-RNTI* IE in the *HS-DSCH Secondary Serving Cell Change Information Response* IE in the *Additional HS Cell Change Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD The DRNC shall include the *Measurement Power Offset* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Change Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD The DRNS shall allocate HS-SCCH codes corresponding to the secondary serving HS-DSCH and include the *HS-SCCH Specific Secondary Serving Information Response* IE in the *HS-DSCH FDD Secondary*

Serving Information Response IE in the HS-DSCH Secondary Serving Cell Change Information Response IE in the Additional HS Cell Change Information Response IE in the RADIO LINK ADDITION RESPONSE message.]

- [FDD The DRNC shall include the *HS-PDSCH And HS-SCCH Scrambling Code* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *HS-DSCH Secondary Serving Cell Change Information Response* IE in the *Additional HS Cell Change Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD If the UE Context is configured with Sixtyfour QAM allowed for the secondary serving HS-DSCH Radio Link and not used in the current configuration and then if the DRNS decides to use 64 QAM in the new secondary serving HS-DSCH Radio Link, then it shall include the SixtyfourQAM DL Usage Indicator IE in the HS-DSCH FDD Secondary Serving Information Response IE in the Additional HS Cell Information Response IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD If, in the new configuration, the UE context is configured not to use Sixtyfour QAM for the secondary serving HS-DSCH, the DRNS shall include the *HS-DSCH TB Size Table Indicator* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the Additional HS Cell Change Information Response IE in the RADIO LINK ADDITION RESPONSE message if it decides to use the octet aligned table defined in TS 25.321 [41] for the secondary serving HS-DSCH Transport Block Size signalling.]

[FDD – Secondary Serving HS-DSCH Setup on a New Radio Link at Serving HS-DSCH Radio Link Change:]

- [FDD The DRNS shall setup the requested HS-PDSCH resources on the Secondary Serving HS-DSCH Radio Link indicated by the *HS-PDSCH RL ID* IE.]
- [FDD The *HS-DSCH FDD Secondary Serving Information* IE defines the new secondary serving HS-DSCH configuration in the DRNS to be used on the new secondary serving HS-DSCH Radio Link. Non cell specific secondary serving Radio Link and non cell specific secondary serving HS-DSCH parameters take the same values as for the serving HS-DSCH cell.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the HS-SCCH Power Offset IE in
 the HS-DSCH FDD Secondary Serving Information IE in the Additional HS Cell Information RL Addition
 IE, then the DRNS may use this value to determine the HS-SCCH power. The HS-SCCH Power Offset
 should be applied for any secondary serving HS-SCCH transmission to this UE.]
- [FDD If the MIMO Activation Indicator IE is included in the HS-DSCH FDD Secondary Serving Information IE, then the DRNS shall activate the MIMO mode for the secondary serving HS-DSCH Radio Link and the Node B shall decide the pilot configuration and the UE reporting configuration (N/M ratio) according to TS 25.214 [10] for MIMO and include the MIMO Information Response IE in the HS-DSCH FDD Secondary Serving Information Response IE in the HS-DSCH Secondary Serving Cell Change Information Response IE in the Additional HS Cell Change Information Response IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD If the *Power Offset For S-CPICH for MIMO Request Indicator* IE is included, the DRNC shall, if supported and MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where the Secondary Serving HS-DSCH Radio Link is established, include the *Power Offset For S-CPICH for MIMO* IE in the *HS-DSCH FDD Information Response* IE. If zero power offset the DRNC may include the *Power Offset For S-CPICH for MIMO* IE.]
- [FDD If the *Single Stream MIMO Activation Indicator* IE is included in the *HS-DSCH FDD Secondary Serving Information* IE, then the DRNS shall activate the Single Stream MIMO mode for the secondary serving HS-DSCH Radio Link.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Secondary Serving Information IE, then the DRNS may if the value is set to "allowed" use 64 QAM for the secondary serving HS-DSCH Radio Link, and the DRNS shall include the SixtyfourQAM DL Usage Indicator IE in the HS-DSCH FDD Secondary Serving Information Response IE in the HS-DSCH Secondary Serving Cell Change Information Response IE in the Additional HS Cell Change Information Response IE in the RADIO LINK ADDITION RESPONSE message.]

- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Secondary Serving Information IE with value set to "not allowed", then the DRNS shall not use 64 QAM for the secondary serving HS-DSCH Radio Link.]
- [FDD If Sixtyfour QAM will not be used for the secondary serving cell, the DRNS shall include the HS-DSCH TB Size Table Indicator IE in the HS-DSCH FDD Secondary Serving Information Response IE in the HS-DSCH Secondary Serving Cell Change Information Response IE in the Additional HS Cell Change Information Response IE in the RADIO LINK ADDITION RESPONSE message if it decides to use the octet aligned table defined in TS 25.321 [41] for secondary serving HS-DSCH Transport Block Size signalling.]
- [FDD If the *Diversity Mode* IE is included in the *HS-DSCH FDD Secondary Serving Information* IE in the *Additional HS Cell Information RL Addition* IE in the RADIO LINK ADDITION REQUEST message the DRNS shall apply cell specific transmit diversity configuration and if the *Diversity Mode* IE is not set to "None" the DRNS shall activate/deactivate the Transmit Diversity for the secondary serving HS-DSCH Radio Link in accordance with the *Transmit Diversity Indicator* IE in the *HS-DSCH FDD Secondary Serving Information* IE.]
- [FDD If the Serving Cell Change CFN IE is included in the RADIO LINK ADDITION REQUEST message, then the DRNS shall activate the resources that are allocated for the new secondary serving HS-DSCH Radio Link at the next coming CFN with a value equal to the value requested by the SRNC, or earlier. In this case, in the new configuration the DRNS shall, if applicable, de-allocate the HS-PDSCH resources of the old secondary serving HS-PDSCH Radio Link. The DRNS shall deactivate those resources at the next coming CFN with a value equal to the value requested by the SRNC.]
- [FDD If the Serving Cell Change CFN IE is not included then the DRNS shall activate immediately the resources that are allocated for the new secondary serving HS-PDSCH Radio Link, and shall keep active the resources that are allocated for the previous secondary serving HS-PDSCH Radio Link.]
- [FDD If the requested secondary serving HS-DSCH Radio Link Change was successful or unsuccessful, the DRNS shall indicate this in the *HS-DSCH Secondary Serving Cell Change Information Response* IE in the *Additional HS Cell Change Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]

[FDD – Additional Serving E-DCH Radio Link Change:]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Additional E-DCH Cell Information Addition* IE in the *Additional E-DCH Cell Information RL Add Req* IE and the *HS-PDSCH RL ID* IE in the *Additional HS Cell Information RL Addition* IE, the *HS-PDSCH RL ID* IE indicates the new Additional Serving E-DCH Radio Link:]

- [FDD In the new configuration the DRNS shall allocate the E-DCH resources for the new additional serving E-DCH Radio Link on the secondary UL frequency. Non cell specific E-DCH parameters shall take the same values as for the corresponding cell of the Primary uplink frequency.]
- [FDD If the old Additional Serving E-DCH RL is within this DRNS, the DRNS shall de-allocate the E-AGCH resources of the old Additional Serving E-DCH Radio Link at the activation of the new configuration.]
- [FDD The DRNS shall allocate a primary E-RNTI identifier or a secondary E-RNTI identifier or both for the new Additional Serving E-DCH Radio Link and include these E-RNTI identifiers along with the channelisation code of the corresponding E-AGCH in the E-DCH FDD DL Control Channel Information IE in the Additional E-DCH Serving Cell Change Information Response IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD The DRNS may include in the *E-DCH FDD DL Control Channel Information* IE in the *Additional E-DCH Serving Cell Change Information Response* IE in the RADIO LINK ADDITION RESPONSE message the *Serving Grant Value* IE and *Primary/Secondary Grant Selector* IE for the initial grant for the additional serving E-DCH RL and may include the *Default Serving Grant in DTX Cycle 2* IE]
- [FDD If the E-DCH HARQ process allocation for 2ms TTI for scheduled transmission shall be changed, the DRNS shall allocate resources according to the new/changed configuration and include the new/changed configuration in the *HARQ Process Allocation For 2ms Scheduled Transmission Grant* IE in the *Additional E-DCH FDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD The DRNS may include the *E-RGCH/E-HICH Channelisation Code* IE and/or the *E-HICH Signature Sequence* IE and/or the *E-RGCH Signature Sequence* IE or may alternatively include the *E-RGCH Release*

Indicator IE in the E-DCH FDD DL Control Channel Information IE in the Additional E-DCH Serving Cell Change Information Response IE in the RADIO LINK ADDITION RESPONSE message for any of the other E-DCH Radio Links in the DRNS Communication Context that have not been included in the E-DCH FDD DL Control Channel Information IE in the Additional E-DCH FDD Information Response IE.]

- [FDD If the Serving Cell Change CFN IE is included in the RADIO LINK ADDITION REQUEST message, then the DRNS shall activate the resources that are allocated for the new additional serving E-DCH Radio Link at the next coming CFN with a value equal to the value requested by the SRNC, or earlier. In this case, in the new configuration the DRNS shall, if applicable, de-allocate the E-AGCH resources of the old Additional Serving E-DCH Radio Link. The DRNS shall deactivate those resources at the next coming CFN with a value equal to the value requested by the SRNC.]
- [FDD- If the *Serving Cell Change CFN* IE is not included then the DRNS shall activate immediately the resources that are allocated for the new additional serving E-DCH Radio Link, and shall keep active the resources that are allocated for the previous additional serving E-DCH Radio Link.]
- [FDD If the addition of the requested Additional Serving E-DCH Radio Link was successful but the Additional Serving E-DCH Radio Link change was unsuccessful, the DRNS shall indicate this in the *Additional E-DCH Serving Cell Change Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]

[FDD - E-DCH:]

[FDD – If the RADIO LINK ADDITION REQUEST message contains the *E-DCH RL Indication* IE, set to "E-DCH", in the *RL Information* IE, then for every such RL.]

- [FDD The DRNS shall setup the E-DCH resources as configured in the UE context.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *Transport Layer Address* IE and *Binding ID* IE in the *RL specific E-DCH Information* IE for an E-DCH MAC-d flow, then if the *Transport Bearer Not Requested Indicator* IE is not included for this E-DCH MAC-d flow, the DRNC may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for the concerned E-DCH MAC-d flow.]
- [FDD The DRNC shall include in the RADIO LINK ADDITION RESPONSE message the *Binding ID* IE and *Transport Layer Address* IE for establishment of a transport bearer for every E-DCH MAC-d flow being established for which the *Transport Bearer Not Requested Indicator* IE was not included.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *Transport Bearer Not Requested Indicator* IE set to "Transport Bearer Shall not be Established" for an E-DCH MAC-d flow, then the DRNC shall not establish a transport bearer for the concerned E-DCH MAC-d flow and shall include the *Transport Bearer Not Setup Indicator* IE for the corresponding E-DCH MAC-d flow in the RADIO LINK ADDITION RESPONSE message.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *Transport Bearer Not Requested Indicator* IE set to "Transport Bearer may not be Established" for an E-DCH MAC-d flow and:]
 - [FDD if the DRNC establishes a transport bearer for the concerned E-DCH MAC-d flow, the DRNC shall include in the RADIO LINK ADDITION RESPONSE message the *Binding ID* IE and *Transport Layer Address* IE for establishment of a transport bearer for the E-DCH MAC-d flow being established.]
 - [FDD if the DRNC does not establish a transport bearer for the concerned E-DCH MAC-d flow, the DRNC shall include the *Transport Bearer Not Setup Indicator* IE for the corresponding E-DCH MAC-d flow in the RADIO LINK ADDITION RESPONSE message.]
- [FDD The DRNC may include the *E-AGCH And E-RGCH/E-HICH FDD Scrambling Code* IE and shall include the *E-RGCH/E-HICH Channelisation Code* IE and the corresponding *E-HICH Signature Sequence* IE and the DRNC may include the corresponding *E-RGCH Signature Sequence* IE in the *E-DCH FDD DL Control Channel Information* IE in the RADIO LINK ADDITION RESPONSE message, for every RL indicated by the *E-DCH RL Indication* IE, set to "E-DCH", in the *RL Information* IE.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *E-RGCH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-RGCH power for the RL. The E-RGCH Power Offset should be applied for any E-RGCH transmission to this UE.]

- [FDD If the RADIO LINK ADDITION REQUEST message includes the *E-HICH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-HICH power for the RL. The E-HICH Power Offset should be applied for any E-HICH transmission to this UE.]
- [FDD If the DRNS has no valid data for the *E-RGCH/E-HICH Channelisation Code* IE in the *E-DCH FDD DL Control Channel Information* IE in the RADIO LINK ADDITION RESPONSE message, then it shall insert the *E-RGCH and E-HICH Channelisation Code Validity Indicator* IE in the *E-DCH FDD DL Control Channel Information* IE, to indicate that the *E-RGCH/E-HICH Channelisation Code* IE contains invalid data.]

[FDD – Serving E-DCH Radio Link Change:]

[FDD – If the RADIO LINK ADDITION REQUEST message contains the *Serving E-DCH RL* IE, this indicates the new Serving E-DCH Radio Link:]

- [FDD If the new Serving E-DCH RL is in this DRNS:]
 - [FDD The DRNS shall allocate a primary E-RNTI identifier or a secondary E-RNTI identifier or both and include these E-RNTI identifiers and the Channelisation Code of the corresponding E-AGCH in the *E-DCH FDD DL Control Channel Information* IE in the *E-DCH Serving Cell Change Information Response* IE for the indicated RL in the RADIO LINK ADDITION RESPONSE message.]
 - [FDD The DRNS may include the *Serving Grant Value* IE and *Primary/Secondary Grant Selector* IE in the *E-DCH Serving Cell Change Information Response* IE in the RADIO LINK ADDITION RESPONSE message for the initial grant for the new serving E-DCH RL.]
 - [FDD If the E-DCH HARQ process allocation for 2ms TTI for scheduled and/or non-scheduled transmission shall be changed, the DRNS shall allocate resources according to the new/changed configuration and include the new/changed configuration in the *E-DCH FDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
 - [FDD If a serving cell change is performed the RADIO LINK ADDITION RESPONSE message may contain invalid data (see 9.2.2.4C).]
 - [FDD The DRNS may include the *Default Serving Grant in DTX Cycle 2* IE in the RADIO LINK ADDITION RESPONSE message for the new serving E-DCH RL.]
- [FDD The DRNS may include the *E-RGCH/E-HICH Channelisation Code* IE and/or the *E-HICH Signature Sequence* IE and/or the *E-RGCH Signature Sequence* IE or may alternatively include the *E-RGCH Release Indicator* IE in the *E-DCH FDD DL Control Channel Information* IE in the *E-DCH Serving Cell Change Information Response* IE in the RADIO LINK ADDITION RESPONSE message for any of the other E-DCH Radio Link in the DRNS Communication Context that have not been included in the *E-DCH FDD DL Control Channel Information* IE in *RL Information Response* IE.]
- [FDD If the Serving Cell Change CFN IE is included in the RADIO LINK ADDITION REQUEST message, then the DRNS shall activate the resources that are allocated for the new serving E-DCH Radio Link at the next coming CFN with a value equal to the value requested by the SRNC, or earlier. In this case, in the new configuration the DRNS shall, if applicable, de-allocate the E-AGCH resources of the old Serving E-DCH Radio Link. The DRNS shall deactivate those resources at the next coming CFN with a value equal to the value requested by the SRNC.]
- [FDD- If the *Serving Cell Change CFN* IE is not included then the DRNS shall activate immediately the resources that are allocated for the new serving E-DCH Radio Link, and shall keep active the resources that are allocated for the previous serving E-DCH Radio Link.]
- [FDD If the addition of the requested Serving E-DCH Radio Link was successful but the Serving E-DCH Radio Link change was unsuccessful, the DRNS shall indicate this in the *E-DCH Serving Cell Change Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]

[FDD - E-DPCH Handling:]

[FDD – If the RADIO LINK ADDITION REQUEST message includes an *E-DPCH Information* IE it defines the new E-DPCH configuration in the DRNS to be used on the new E-DCH Radio Link and the DRNS shall use the new parameters for the related resource allocation operations.]

[FDD – If the *E-TFCS Information* IE in the *E-DPCH Information* IE contains the *E-TFCI Boost Information* IE, the DRNS shall use the information according to TS 25.214 [10]. If the *E-TFCI Boost Information* IE is not present, the DRNS shall use the value "127" in the algorithm defined in TS 25.214 [10].]

[FDD – If the *E-DPCH Information* IE includes the *E-TFCS Information* IE, the DRNS shall use the *E-TFCS Information* IE for the E-DCH when reserving resources for the uplink of the new configuration. The DRNS shall apply the new TFCS in the uplink of the new configuration. If the *E-TFCS Information* IE contains the *E-DCH Minimum Set E-TFCI Validity Indicator* IE the DRNS shall ignore the value in *E-DCH Minimum Set E-TFCI* IE. If the *E-DCH Minimum Set E-TFCI validity indicator* IE is absent DRNS shall use the value for the related resource allocation operation.]

[FDD – If the *E-TFCS Information* IE in the *E-DPCH Information* IE contains the *E-DPDCH Power Interpolation* IE, the DRNS shall use the value to determine the applicable E-DPDCH power formula defined in TS 25.214 [10]. If the *E-DPDCH Power Interpolation* IE is not present, the DRNS shall use the E-DPDCH power extrapolation formula defined in TS 25.214 [10].]

[FDD – If the RADIO LINK ADDITION REQUEST message includes an *E-DPCH Information* IE, which contains the *Minimum Reduced E-DPDCH Gain Factor* IE, then the DRNS shall use the value to determine the applicable minimum gain factor ($\beta_{ed,k,reduced,min}$) defined in TS 25.214 [10]. For the case the *Minimum Reduced E-DPDCH Gain Factor* IE is not available for the UE Context, the DRNS may use the default value defined in TS 25.331 [16].

[FDD – E-DCH Setup on a new Radio Link:]

[FDD – If the E-DCH FDD Information IE is present in the RADIO LINK ADDITION REQUEST message then:]

- [FDD the *E-DCH FDD Information* IE defines the new E-DCH FDD configuration in the DRNS to be used on the new E-DCH Radio Link.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *MAC-es Guaranteed Bit Rate* IE in the *E-DCH Logical Channel Information* IE in the *E-DCH FDD Information* IE, then the DRNS shall use this information to optimise MAC-e scheduling decisions.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes *UE Aggregate Maximum Bit Rate Enforcement Indicator* IE in the *E-DCH Logical Channel Information* IE in the *E-DCH MAC-d Flow Specific Information* IE in the *E-DCH FDD Information* IE, then the DRNS shall, if supported, consider the data of the related E-DCH Logical Channel for UE Aggregate Maximum Bit Rate Enforcement.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *Maximum MAC-d PDU Size Extended* IE for a E-DCH Logical Channel in the *E-DCH MAC-d Flows Information* IE in the *E-DCH FDD Information* IE, then the DRNS shall ignore the *MAC-d PDU Size* IE in the *MAC-d PDU Size List* IE and use *Maximum MAC-d PDU Size Extended* IE to optimise capacity allocation for the related E-DCH Logical Channel and use the indicated format in user plane frame structure for E-DCH channels (TS 25.425 [32]) and MAC (TS 25.321 [41]).]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *E-DCH MAC-d Flow Multiplexing List* IE for an E-DCH MAC-d flow the DRNS shall use this information for the related resource allocation operation.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *HARQ Process Allocation For 2ms Scheduled Transmission Grant* IE, the DRNS shall use this information for the related resource allocation operation.]
- [FDD If in the RADIO LINK ADDITION REQUEST message the E-DCH Grant Type is indicated as being "E-DCH Non-Scheduled Transmission Grant" for an E-DCH MAC-d flow the DRNS shall assume non-scheduled grants being configured for that E-DCH MAC-d flow and shall use the information within the HARQ Process Allocation For 2ms Non-Scheduled Transmission Grant IE, if included, for the related resource allocation operation.]
- [FDD If in the RADIO LINK ADDITION REQUEST message the E-DCH Grant Type is indicated as being "E-DCH Scheduled Transmission Grant" for an E-DCH MAC-d flow the DRNS shall assume scheduled grants being configured for that E-DCH MAC-d flow.]
- [FDD The DRNS may use the *Traffic Class* IE for a specific E-DCH MAC-d flow to determine the transport bearer characteristics to apply between DRNC and Node B. If *TrCH Source Statistics Descriptor* IE is present

with the value "RRC" in the *E-DCH MAC-d Flows Information* IE, then the DRNC should ignore the *Traffic Class* IE.]

- [FDD If the *TNL QoS* IE is included for an E-DCH MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink for the related MAC-d flow.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *Bundling Mode Indicator* IE for a E-DCH MAC-d flow in the *E-DCH MAC-d Flow Specific Information* IE in the *E-DCH FDD Information* IE and the *Bundling Mode Indicator* IE is set to "Bundling" and the *E-TTI* IE is set to "2ms", then the DRNS shall use the bundling mode for the E-DCH UL data frames for the related MAC-d flow, otherwise the DRNS shall use the non-bundling mode for the E-DCH UL data frames for the related MAC-d flow.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *E-DCH Maximum Bitrate* IE for an E-DCH, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *E-DCH Processing Overload Level* IE, then if the DRNS could not decode the E-DPCCH/E-DPDCH for the last consecutive number of TTIs, indicated in the *E-DCH Processing Overload Level* IE, because of processing issue, the DRNS shall notify the SRNC by initiating the Radio Link Failure procedure.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *E-DCH Reference Power Offset* IE, then the DRNS may use this value as a default HARQ power offset if it is not able to decode the MAC-e PDU and to determine the value of the actual HARQ power offset.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *E-AGCH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-AGCH power. The E-AGCH Power Offset should be applied for any E-AGCH transmission to this UE.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *E-RGCH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-RGCH power for the RL. The E-RGCH Power Offset should be applied for any E-RGCH transmission to this UE.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *E-HICH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-HICH power for the RL. The E-HICH Power Offset should be applied for any E-HICH transmission to this UE.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the *E-DCH Power Offset for Scheduling Info* IE, then the DRNS shall use this value as a power offset for the transmission of scheduling information without any MAC-d PDUs.]
- [FDD If the RADIO LINK ADDITION REQUEST message includes the SixteenQAM UL Operation Indicator
 IE, the DRNS shall activate/deactivate SixteenQAM UL Operation for the RL in accordance with the
 SixteenQAM UL Operation Indicator IE.]
 - [FDD If SixteenQAM UL Operation is activated, then the DRNS shall base the handling of the Relative Grant signalling on Scheduling Grant Table 2 according to TS 25.321 [41]. If SixteenQAM UL Operation is deactivated, then the DRNS shall base the handling of the Relative Grant signalling on Scheduling Grant Table 1 according to TS 25.321 [41].]

[FDD – Additional E-DCH Setup:]

[FDD – If the Additional E-DCH Cell Information RL Add Req IE is present in the RADIO LINK ADDITION REQUEST message and the choice of Setup Or Addition Of E-DCH On Secondary UL Frequency is "Setup", then the Additional E-DCH Cell Information Setup IE defines the new configuration and then:]

- [FDD If the *C-ID* IE is included in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE the *C-ID* IE indicates the cell in which the additional E-DCH shall be setup]
 - [FDD The DRNS shall setup the Additional E-DCH on the secondary uplink frequency and setup the requested Additional E-DCH resources on the Radio Links and in the cells indicated by the *E-DCH Additional RL ID* IE and the *C-ID* IE in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE.]

- [FDD If the *C-ID* IE is not included in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE the *E-DCH Additional RL ID* IE indicates the existing RL on which the Additional E-DCH shall be setup.]
 - [FDD The DRNS shall setup the Additional E-DCH on the Radio Links indicated by the *E-DCH Additional RL ID* IE in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE]
- [FDD The DRNS shall use for the non cell specific Radio Link related parameters and non cell specific E-DPCH, UL DPCH, E-DCH and F-DPCH parameters the same values as for the corresponding cell of the Primary uplink frequency.]
- [FDD If the *UL SIR Target* IE in the *UL DPCH Information* IE in the *Additional E-DCH FDD Setup Information* IE in the *Additional E-DCH Cell Information Setup* IE and/or the *DL Power Balancing Information* IE and/or the *Minimum Reduced E-DPDCH Gain Factor* IE in the *Multicell E-DCH Information* IE in the *Additional E-DCH FDD Setup Information* IE are present, the DRNS shall use the information in the same way as for the information used on Primary uplink frequency.]
- [FDD If the *Secondary UL Frequency Activation State* IE is present in the *Multicell E-DCH Information* IE in the *Additional E-DCH FDD Setup Information* IE, the DRNS shall use the information as initial activation state of the Radio Links on the secondary uplink frequency.]
- [FDD If the *Initial DL Tx Power* IE, the *Primary CPICH Ec/No* IE, the *E-AGCH Power Offset* IE, the *E-RGCH Power Offset* IE and/or the *E-HICH Power Offset* IE, is included in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE in the *Additional E-DCH Cell Information Setup* IE, the DRNS shall use the information in the same way as for the information used on Primary uplink frequency.]
- [FDD If the Enhanced Primary CPICH Ec/No IE is included in the Multicell E-DCH RL Specific Information IE in the Additional E-DCH Secondary RL Specific Information To Setup IE in the Additional E-DCH FDD Setup Information IE in the Additional E-DCH Cell Information Setup IE, the DRNS shall use the information in the same way as for the information used on Primary uplink frequency.]
- If the F-DPCH Slot Format Support Request IE in the F-DPCH Information IE in the Additional E-DCH FDD Setup Information IE in the Additional E-DCH Cell Information Setup IE is included, the DRNS shall configure the concerned UE Context for F-DPCH Slot Format operation according to TS 25.211 [8] and include the F-DPCH Slot Format IE in the Additional E-DCH FDD Information Response IE in the Additional E-DCH Cell Information Response RL Add IE in the RADIO LINK ADDITION RESPONSE message. If the Multicell E-DCH Information IE in the Additional E-DCH FDD Setup Information IE includes the F-DPCH Slot Format IE, the DRNS may use the F-DPCH Slot Format IE to determine the F-DPCH slot format.]
- [FDD If the HARQ Process Allocation For 2ms Scheduled Transmission Grant IE, the E-DCH Maximum Bitrate IE, the E-DCH Minimum Set E-TFCI IE and/or the E-DCH Processing Overload Level IE are present in the Additional E-DCH FDD Information IE in the Additional E-DCH FDD Setup Information IE in the Additional E-DCH Cell Information Setup IE, the DRNS shall use the information in the same way as for the information used on Primary uplink frequency.]
- [FDD If activation of power balancing for the Additional E-DCH RL by the RADIO LINK ADDITION REQUEST message is supported by the DRNS, the DRNS shall include the *DL Power Balancing Activation Indicator* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response* RL Add IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD For each Additional E-DCH RL not having a common generation of the TPC commands in the DL with another Additional E-DCH RL, the DRNS shall set the *RL Set ID* IE included in the *Additional E-DCH FDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message to a value that uniquely identifies the RL as a RL Set within the UE Context. The generation of E-HICH related information for Additional E-DCH RLs in different RL Sets shall not be common.]
- [FDD For all Additional E-DCH RLs having a common generation of the TPC commands in the DL with another Additional E-DCH RL, the DRNS shall assign to each Additional E-DCH RL the same value for the *RL Set ID* IE included in the *Additional E-DCH FDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message. This value shall uniquely identify these Additional E-DCH RLs as members of the same RL Set within the UE Context. The generation of E-HICH information for all Additional E-DCH RLs in a RL Set shall be common.]

- [FDD For each Additional E-DCH RL which has or can have a common generation of E-RGCH information with another Additional E-DCH RL (current or future) when the DRNS would contain the Additional E-DCH serving RL, the DRNS shall set a same value to the *E-DCH RL Set ID* IE for the Additional E-DCH RL in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response* RL Add IE in the RADIO LINK ADDITION RESPONSE message.]
- [FDD For every additional E-DCH RL indicated in the Additional E-DCH RL Specific Information To Setup IE in the Additional E-DCH FDD Setup Information IE the DRNS may include the E-AGCH And E-RGCH/E-HICH FDD Scrambling Code IE and shall include the E-RGCH/E-HICH Channelisation Code IE and the corresponding E-HICH Signature Sequence IE and the DRNS may include the corresponding E-RGCH Signature Sequence IE in the E-DCH FDD DL Control Channel Information IE in the Additional E-DCH FDD Information Response IE in the Additional E-DCH Cell Information Response RL Add IE in the RADIO LINK ADDITION RESPONSE message and if DRNS has no valid data for the E-RGCH/E-HICH Channelisation Code IE, then it shall insert the E-RGCH and E-HICH Channelisation Code Validity Indicator IE to indicate that the E-RGCH/E-HICH Channelisation Code IE contains invalid data.]
- [FDD If the Additional Serving E-DCH Radio Link is configured in the DRNS, then:]
 - [FDD The DRNS shall allocate a primary E-RNTI identifier or a secondary E-RNTI identifier or both for
 the corresponding RL and include these E-RNTI identifiers and the channelisation code of the corresponding
 E-AGCH in the E-DCH FDD DL Control Channel Information IE in the Additional E-DCH FDD
 Information Response IE in the Additional E-DCH Cell Information Response RL Add IE in the RADIO
 LINK ADDITION RESPONSE message.]
 - [FDD The DRNS may include in the *E-DCH FDD DL Control Channel Information* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RL Add* IE in the RADIO LINK ADDITION RESPONSE message the the *Serving Grant Value* IE and *Primary/Secondary Grant Selector* IE for the initial grant for the Additional serving E-DCH RL and may include the *Default Serving Grant in DTX Cycle 2* IE.]
 - [FDD If the E-DCH HARQ process allocation for 2ms TTI for scheduled transmission shall be changed, the DRNS shall allocate resources according to the new/changed configuration and include the new/changed configuration in the *HARQ Process Allocation For 2ms Scheduled Transmission Grant E-DCH FDD Information Response* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
 - [FDD If the Serving Cell Change CFN IE is included in the RADIO LINK ADDITION REQUEST message, then the DRNS shall activate the resources that are allocated for the new additional serving E-DCH Radio Link at the next coming CFN with a value equal to the value requested by the SRNC. If the Serving Cell Change CFN IE is not included then the DRNS shall activate immediately the resources that are allocated for the new additional serving E-DCH Radio Link]
- [FDD If Primary CPICH is not to be used as a Phase Reference for this Radio Link on the secondary UL frequency, the DRNS shall include the *Primary CPICH Usage For Channel Estimation* IE set to the value "Primary CPICH shall not be used" in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response* RL Add IE RADIO LINK ADDITION RESPONSE message.]
- [FDD If Secondary CPICH may be used as a Phase Reference for this Radio Link on the secondary UL frequency, the DRNS shall include the *Secondary CPICH Information* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RL Add* IE in the RADIO LINK ADDITION RESPONSE message. If the DRNS doesn't include the *Secondary CPICH Information* IE, it shall not include the *Primary CPICH Usage For Channel Estimation* IE set to the value "Primary CPICH shall not be used".]

[FDD – Additional E-DCH RL Addition:]

[FDD – If the *Additional E-DCH Cell Information RL Add Req* IE is present in the RADIO LINK ADDITION REQUEST message and the choice of *Setup Or Addition Of E-DCH On Secondary UL Frequency* is "Addition", then the *Additional E-DCH Cell Information Addition* IE defines the new configuration and then:]

- [FDD – The DRNS shall setup the requested E-DCH resources as requested, or as configured in the UE context, on the Radio Links indicated by the *E-DCH Additional RL ID* IE in the *Additional E-DCH RL Specific Information To Add* IE. Non cell specific Radio Link related parameters and non cell specific E-DPCH, UL

- DPCH, E-DCH and F-DPCH parameters shall take the same values as for the corresponding cell of the Primary uplink frequency.]
- [FDD if the *Multicell E-DCH Information* IE is included and contains the *Minimum Reduced E-DPDCH Gain Factor* IE, the DRNS shall use the information in the same way as for the information used on the Primary uplink frequency.]
- [FDD if the Additional E-DCH FDD Information IE is included and contains the HARQ Process Allocation For 2ms Scheduled Transmission Grant IE, the E-DCH Maximum Bitrate IE, the E-DCH Minimum Set E-TFCI IE and/or the E-DCH Processing Overload Level IE, the DRNS shall use the information in the same way as for the information used on the Primary uplink frequency.]
- [FDD If the *E-AGCH Power Offset* IE, the *E-RGCH Power Offset* IE and/or the *E-HICH Power Offset* IE is included in the *Additional E-DCH RL Specific Information To Add* IE, the DRNS shall use the information in the same way as for the information used on Primary uplink frequency.]
- [FDD If the power balancing is active with the Power Balancing Adjustment Type of the UE Context set to "Individual" in the existing Additional E-DCH RL(s) and the RADIO LINK ADDITION REQUEST message includes the *DL Reference Power* IE in the *Multicell E-DCH RL Specific Information* IE in the *Additional E-DCH RL Specific Information To Add* IE, the DRNS shall activate the power balancing and use the *DL Reference Power* IE for the power balancing procedure in the new Additional RL(s), if activation of power balancing by the RADIO LINK ADDITION REQUEST message is supported, according to subclause 8.3.15. In this case, the DRNS shall include the *DL Power Balancing Activation Indicator* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RL Add* IE in the RADIO LINK ADDITION RESPONSE message. If the DRNS starts the DL transmission and the activation of the power balancing at the same CFN, the initial power of the power balancing, i.e. *P*_{init} shall be set to the power level which is calculated based on the following IEs in the *Additional E-DCH RL Specific Information To Add* IE (if received): *Primary CPICH Ec/No* IE or the *Enhanced Primary CPICH Ec/No* IE in the *Multicell E-DCH RL Specific Information* IE or to the power level which is calculated based on the power relative to the Primary CPICH power used by the existing Additional RLs.]
- [FDD For each Additional E-DCH RL not having a common generation of the TPC commands in the DL with another Additional E-DCH RL, the DRNS shall set the *RL Set ID* IE included in the *Additional E-DCH FDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message to a value that uniquely identifies the RL as a RL Set within the UE Context. The generation of E-HICH related information for Additional E-DCH RLs in different RL Sets shall not be common.]
- [FDD For all Additional E-DCH RLs having a common generation of the TPC commands in the DL with another Additional E-DCH RL, the DRNS shall assign to each Additional E-DCH RL the same value for the *RL Set ID* IE included in the *Additional E-DCH FDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message. This value shall uniquely identify these Additional E-DCH RLs as members of the same RL Set within the UE Context. The generation of E-HICH information for all Additional E-DCH RLs in a RL Set shall be common.]
- [FDD For each Additional E-DCH RL which has or can have a common generation of E-RGCH information with another Additional E-DCH RL (current or future) when the DRNS would contain the Additional E-DCH serving RL, the DRNS shall set the same value for the *E-DCH RL Set ID* IE for the Additional E-DCH RL in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response* RL Add IE in the RADIO LINK ADDITION RESPONSE message.]
 - [FDD For every additional E-DCH RL indicated in the Additional E-DCH RL Specific Information To Add IE the DRNS may include the E-AGCH And E-RGCH/E-HICH FDD Scrambling Code IE and shall include the E-RGCH/E-HICH Channelisation Code IE and the corresponding E-HICH Signature Sequence IE and the DRNS may include the corresponding E-RGCH Signature Sequence IE in the E-DCH FDD DL Control Channel Information IE in the Additional E-DCH FDD Information Response IE in the Additional E-DCH Cell Information Response RL Add IE in the RADIO LINK ADDITION RESPONSE message and if DRNS has no valid data for the E-RGCH/E-HICH Channelisation Code IE, then it shall insert the E-RGCH and E-HICH Channelisation Code Validity Indicator IE to indicate that the E-RGCH/E-HICH Channelisation Code IE contains invalid data.]
- [FDD If in the Additional E-DCH RL Specific Information To Add IE the Primary CPICH Ec/No IE or the Primary CPICH Ec/No IE and the Enhanced Primary CPICH Ec/No IE in the Multicell E-DCH RL Specific Information IE measured by the UE are included for an RL in the RADIO LINK ADDITION REQUEST message, the DRNS shall use this in the calculation of the Initial DL TX Power for this additional RL. If the

Primary CPICH Ec/No IE is not present, the DRNS shall set the Initial DL TX Power based on the power relative to the Primary CPICH power used by the existing RLs.]

[TDD – HS-DSCH Setup:]

[TDD – If the HS-DSCH Information IE is present in the RADIO LINK ADDITION REQUEST message, then:]

- [TDD The DRNS shall setup the requested HS-PDSCH resources on the Serving HS-DSCH Radio Link indicated by the *HS-PDSCH RL ID* IE.]
- [TDD The DRNC shall include the *HARQ Memory Partitioning* IE in the *HS-DSCH TDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
- [TDD If the RADIO LINK ADDITION REQUEST message includes the *HS-DSCH MAC-d PDU Size Format* IE in the *HS-DSCH Information* IE, then the DRNS shall use the indicated format in user plane frame structure for HS-DSCH channels (TS 25.425 [32]) and MAC-hs (TS 25.321 [41]).
- [TDD The DRNS may use the *Traffic Class* IE for a specific HS-DSCH MAC-d flow to determine the transport bearer characteristics to apply between DRNC and Node B. If *TrCH Source Statistics Descriptor* IE is present with the value "RRC" in the *HS-DSCH MAC-d Flows Information* IE, then the DRNC should ignore the *Traffic Class* IE.]
- [TDD The DRNC shall allocate an HS-DSCH-RNTI to the UE Context and include the *HS-DSCH-RNTI* IE in the RADIO LINK ADDITION RESPONSE message.]
- [TDD The DRNC shall include in the RADIO LINK ADDITION RESPONSE message the *Binding ID* IE and *Transport Layer Address* IE for establishment of transport bearer for every HS-DSCH MAC-d flow being established.]
- [TDD If the RADIO LINK ADDITION REQUEST message includes the *Transport Layer Address* IE and *Binding ID* IE in the *HS-DSCH Information* IE for an HS-DSCH MAC-d flow, then the DRNC may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for the concerned HS-DSCH MAC-d flow. If the *TNL QoS* IE is included for a MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink between the DRNS and the SRNC for the related MAC-d flow.]
- [TDD If the RADIO LINK ADDITION REQUEST message includes the *MAC-hs Guaranteed Bit Rate* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, then the DRNS shall use this information to optimise MAC-hs scheduling decisions for the related HSDPA Priority Queue.]
- [TDD If the RADIO LINK ADDITION REQUEST message includes the *Discard Timer* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, then the DRNS shall use this information to discard out-of-date MAC-hs SDUs from the related HSDPA Priority Queue.]
- [TDD If the RADIO LINK ADDITION REQUEST message includes the *Maximum MAC-d PDU Size Extended* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, then the DRNC shall ignore the *SID* IE and *MAC-d PDU Size* IE in the *MAC-d PDU Size Index* IE and use *Maximum MAC-d PDU Size Extended* IE to optimise capacity allocation for the related HSDPA Priority Queue.]
- [TDD If the RADIO LINK ADDITION REQUEST message includes *DL RLC PDU Size Format* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, the *DL RLC PDU Size Format* IE may be used by the DRNS to determine the allocated capacity on user plane as described in TS 25.425 [32].]
- ITDD The DRNC shall include the *HS-DSCH Initial Capacity Allocation* IE in the *HS-DSCH TDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message for every HS-DSCH MAC-d flow being established, if the DRNS allows the SRNC to start transmission of MAC-d PDUs before the DRNS has allocated capacity on user plane as described in TS 25.425 [32]. If RADIO LINK ADDITION REQUEST message includes *HS-DSCH MAC-d PDU Size Format* IE in the *HS-DSCH Information* IE set to "Flexible MAC-d PDU Size", then DRNC shall only set in the *HS-DSCH Initial Capacity Allocation* IE the values for the peer of *Scheduling Priority Indicator* IE and *Maximum MAC-d PDU Size Extended* IE to the values of the corresponding peer I in RADIO LINK ADDITION REQUEST in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE for a Priority Queue including *Scheduling Priority Indicator* IE and *Maximum MAC-d PDU Size Extended* IE.]

- [TDD The DRNS shall allocate HS-SCCH parameters corresponding to the HS-DSCH and the DRNC shall include the [3.84Mcps TDD HS-SCCH Specific Information Response IE] [1.28Mcps TDD HS-SCCH Specific Information Response IE in the RADIO LINK ADDITION RESPONSE message.]
 - [1.28 Mcps TDD *If the MIMO Activation Indicator* IE is included in the *HS-DSCH TDD Information* IE, then, The DRNS shall activate the MIMO mode for the HS-DSCH Radio Link. The DRNS shall decide the SF mode for HS-PDSCH dual stream and include the *MIMO SF Mode for HS-PDSCH dual stream* IE in the *HS-DSCH TDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
- [1.28 Mcps TDD If the *UE TSO Capability LCR* IE is included in the *HS-DSCH TDD Information* IE, then the DRNC may include the *TSO HS-PDSCH Indication LCR* IE in the RADIO LINK ADDITION RESPONSE message if HS-PDSCH resources could be allocated on TS0 for the UE.]

[TDD – Intra-Node B Serving HS-DSCH Radio Link Change:]

[TDD – If the RADIO LINK ADDITION REQUEST message includes the *HS-PDSCH RL ID* IE, this indicates the new Serving HS-DSCH Radio Link:]

- [TDD The DRNC shall include the *HARQ Memory Partitioning* IE in the *HS-DSCH TDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
- [TDD The DRNS shall allocate HS-SCCH parameters corresponding to the HS-DSCH and the DRNC shall include the [3.84Mcps TDD *HS-SCCH Specific Information Response* IE] [1.28Mcps TDD *HS-SCCH Specific Information Response 7.68Mcps* IE] in the *HS-DSCH TDD Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]

[TDD - E-DCH:]

[3.84Mcps TDD, 1.28Mcps TDD and 7.68Mcps TDD – If the [3.84Mcps TDD – *E-DCH Information* IE][1.28Mcps TDD – *E-DCH Information* 1.28Mcps IE] [7.68Mcps TDD – *E-DCH Information* 7.68Mcps IE] is present in the RADIO LINK ADDITION REQUEST message:]

- [TDD The DRNS shall setup the requested E-DCH resources on the Radio Link indicated by the *E-DCH Serving RL* IE.]
- [TDD If the *TNL QoS* IE is included in the *E-DCH MAC-d Flows Information TDD* IE for an E-DCH MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink for the related MAC-d flow.]
- [TDD If the RADIO LINK ADDITION REQUEST message includes the *Transport Layer Address* IE and *Binding ID* IE in the *E-DCH MAC-d Flows Information TDD* IE for an E-DCH MAC-d flow, then the DRNC may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for the concerned E-DCH MAC-d flow.]
- [TDD If the RADIO LINK ADDITION REQUEST message includes the *E-DCH MAC-d Flow Multiplexing List* IE for an E-DCH MAC-d flow in the *E-DCH MAC-d Flows Information TDD* IE, the DRNS shall use this information for the related resource allocation operation.]
- [TDD If in the RADIO LINK ADDITION REQUEST message the *E-DCH Grant Type* IE in the *E-DCH MAC-d Flows Information TDD* IE is set to "Non-scheduled" for an E-DCH MAC-d flow the DRNS shall assume non-scheduled grants are configured for that E-DCH MAC-d flow.]
- [TDD If in the RADIO LINK ADDITION REQUEST message the *E-DCH Grant Type* IE in the *E-DCH MAC-d Flows Information TDD* IE is set to "Scheduled" the DRNS shall assume that it may issue scheduled grants for the concerned E-DCH MAC-d flow.]
- [TDD If the RADIO LINK ADDITION REQUEST message includes the *MAC-es Guaranteed Bit Rate* IE in the *E-DCH Logical Channel Information* IE in the *E-DCH MAC-d Flows Information TDD* IE, then the DRNS shall use this information to optimise MAC-e scheduling decisions for the related queue.]
- [1.28Mcps TDD If the RADIO LINK ADDITION REQUEST message includes the *MAC-es Maximum Bit Rate LCR* IE in the *E-DCH Logical Channel Information* IE in the *E-DCH MAC-d Flows Information TDD* IE, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]

- [TDD If the RADIO LINK ADDITION REQUEST message includes the *Maximum MAC-d PDU Size Extended* IE for a E-DCH Logical Channel in the *E-DCH MAC-d Flows Information TDD* IE in the *E-DCH Information* IE, then the DRNS shall ignore the *MAC-d PDU Size* IE in the *MAC-d PDU Size List* IE and use *Maximum MAC-d PDU Size Extended* IE to optimise capacity allocation for the related E-DCH Logical Channel and use the indicated format in user plane frame structure for E-DCH channels (TS 25.425 [32]) and MAC (TS 25.321 [41]).]
- [3.84Mcps TDD If the RADIO LINK ADDITION REQUEST message includes the *E-DCH TDD Maximum Bitrate* IE in the *E-DCH TDD Information* IE for an E-DCH, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
- [1.28Mcps TDD If the RADIO LINK ADDITION REQUEST message includes the *E-DCH Physical Layer Category LCR* IE or *Extended E-DCH Physical Layer Category LCR* IE in the *E-DCH TDD Information LCR* IE for an E-DCH, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
- [7.68Mcps TDD If the RADIO LINK ADDITION REQUEST message includes the *E-DCH TDD Maximum Bitrate 7.68Mcps* IE in the *E-DCH TDD Information 7.68Mcps* IE for an E-DCH, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
- [3.84Mcps TDD If the RADIO LINK ADDITION REQUEST message includes the *E-DCH Processing Overload Level* IE in the *E-DCH TDD Information* IE, then if the DRNS could not decode the E-PUCH for the last consecutive number of TTIs, indicated in the *E-DCH Processing Overload Level* IE, because of a processing issue, the DRNS shall notify the SRNC by initiating the Radio Link Failure procedure.]
- [7.68Mcps TDD If the RADIO LINK ADDITION REQUEST message includes the *E-DCH Processing Overload Level* IE in the *E-DCH TDD Information 7.68Mcps* IE, then if the DRNS could not decode the E-PUCH for the last consecutive number of TTIs, indicated in the *E-DCH Processing Overload Level* IE, because of a processing issue, the DRNS shall notify the SRNC by initiating the Radio Link Failure procedure.]
- [1.28Mcps TDD If the RADIO LINK ADDITION REQUEST message includes the *E-DCH Processing Overload Level* IE in the *E-DCH TDD Information LCR* IE, then if the DRNS could not decode the E-PUCH for the last consecutive number of TTIs, indicated in the *E-DCH Processing Overload Level* IE, because of a processing issue, the DRNS shall notify the SRNC by initiating the Radio Link Failure procedure.]
- [TDD The DRNS may use the *Traffic Class* IE for a specific E-DCH MAC-d flow to determine the transport bearer characteristics to apply between DRNC and Node B.]
- [TDD If the RADIO LINK ADDITION REQUEST message includes the [3.84Mcps TDD *E-DCH TDD Information* IE][1.28Mcps TDD *E-DCH TDD Information LCR* IE] in the *E-DCH MAC-d Flows Information TDD* IE, then the DRNS shall use this value as a power offset for the transmission of scheduling information without any MAC-d PDUs.]
- [1.28Mcps TDD If the RADIO LINK ADDITION REQUEST message includes the *Maximum Number of Retransmission for Scheduling Info LCR* IE and the *E-DCH Retransmission timer for Scheduling Info LCR* IE in the *E-DCH TDD Information LCR* IE, then the DRNS shall use these parameters for the transmission of scheduling information without any MAC-d PDUs.]
- [3.84Mcps TDD The DRNS shall determine any non-scheduled resource to be granted for the radio link, and return this in the *E-DCH Non-scheduled Grant Information TDD* IE in the *E-DCH Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]
- [3.84Mcps TDD The DRNS shall allocate an E-RNTI identifier and include the E-RNTI identifier and the E-AGCH(s) assigned in the E-DCH Information Response IE in the RADIO LINK ADDITION RESPONSE message.]
- [1.28Mcps TDD The DRNS shall determine any non-scheduled resource to be granted for the radio link, and return this in the *E-DCH Non-scheduled Grant Information LCR TDD* IE in the *E-DCH Information Response* 1.28Mcps IE in the RADIO LINK ADDITION RESPONSE message.]
- [1.28Mcps TDD The DRNS shall allocate an E-RNTI identifier and include the E-RNTI identifier, the E-AGCH(s) and E-HICH(s) assigned in the *E-DCH Information Response 1.28Mcps* IE in the RADIO LINK ADDITION RESPONSE message.]

- [7.684Mcps TDD The DRNS shall determine any non-scheduled resource to be granted for the radio link, and return this in the *E-DCH Non-scheduled Grant Information* 7.68Mcps *TDD* IE in the *E-DCH Information Response* 7.68Mcps IE in the RADIO LINK ADDITION RESPONSE message.]
- [7.68Mcps TDD The DRNS shall allocate an E-RNTI identifier and include the E-RNTI identifier and the E-AGCH(s) assigned in the E-DCH Information Response 7.68Mcps IE in the RADIO LINK ADDITION RESPONSE message.]
- [1.28Mcps TDD If the RADIO LINK ADDITION REQUEST message includes the *Multi-Carrier E-DCH Physical Layer Category LCR* IE in the *E-DCH TDD Information LCR* IE, the DRNS shall use this information for the related resource allocation operation, and when applicable, for multi-carrier E-DCH scheduling.]
- [1.28Mcps TDD If the *UE TSO Capability LCR* IE in the *UE Capabilities Information* IE in the *HS-DSCH Information* IE is not present and if the RADIO LINK ADDITION REQUEST message includes the *UE TSO Capability LCR* IE in the *E-DCH TDD Information LCR* IE, the DRNS can use this information to allocate the downlink resources for the UE according to TS 25.306 [42].]

[3.84Mcps TDD – Intra-Node B Serving E-DCH Radio Link Change:]

[3.84Mcps TDD – If the RADIO LINK ADDITION REQUEST message includes the *E-DCH Serving RL* IE, this indicates the new Serving E-DCH Radio Link:]

- [3.84Mcps TDD – The DRNS shall allocate E-AGCH parameters corresponding to the E-DCH and include the *E-AGCH Specific Information Response* IE in the *E-DCH Information Response* IE in the RADIO LINK ADDITION RESPONSE message.]

[1.28Mcps TDD – Intra-Node B Serving E-DCH Radio Link Change:]

[1.28Mcps TDD – If the RADIO LINK ADDITION REQUEST message includes the *E-DCH Serving RL* IE, this indicates the new Serving E-DCH Radio Link:]

- [1.28Mcps TDD – The DRNS shall allocate E-AGCH parameters and E-HICH parameters corresponding to the E-DCH and include the *E-AGCH Specific Information Response* IE and the *E-HICH Specific Information Response* IE in the *E-DCH Information Response* 1.28Mcps IE in the RADIO LINK ADDITION RESPONSE message.]

[7.68Mcps TDD – Intra-Node B Serving E-DCH Radio Link Change:]

 $[7.68 Mcps\ TDD-If\ the\ RADIO\ LINK\ ADDITION\ REQUEST\ message\ includes\ the\ \emph{E-DCH}\ Serving\ RL\ IE,\ this\ indicates\ the\ new\ Serving\ E-DCH\ Radio\ Link:]$

- [7.68Mcps TDD – The DRNS shall allocate E-AGCH parameters corresponding to the E-DCH and include the *E-AGCH Specific Information Response* 7.68Mcps TDD IE in the *E-DCH Information Response* 7.68Mcps IE in the RADIO LINK ADDITION RESPONSE message.]

[1.28 Mcps TDD – Continuous Packet Connectivity Handling:]

[1.28 Mcps TDD – If the RADIO LINK ADDITION REQUEST message includes the Continuous Packet *Connectivity DRX Information LCR* IE, then the DRNS shall take account into these parameters to decide the DRX operation related parameters and configure the concerned UE Context for DRX operation according to TS 25.224 [22] and include the parameter(s) in the *Continuous Packet Connectivity DRX Information Response LCR* IE in the RADIO LINK ADDITION RESPONSE message.]

[1.28 Mcps TDD - If the *Inactivity Threshold for UE DRX Cycle Ext* IE is included in the *Continuous Packet Connectivity DRX Information LCR* IE, then the DRNS may use this value to determine the Inactivity Threshold for UE DRX Cycle according to TS 25.224 [22].]

[1.28 Mcps TDD – If the RADIO LINK ADDITION REQUEST message includes the *HS-DSCH Semi-Persistent scheduling Information LCR* IE, then:]

- [1.28 Mcps TDD The DRNS shall configure the Serving HS-DSCH Radio Link indicated by the *HS-PDSCH RL ID* IE for HS-DSCH Semi-Persistent scheduling operation according to TS 25.224 [22].]
- [1.28 Mcps TDD The DRNS shall allocate the HS-SICH information needed for HS-DSCH Semi-Persistent scheduling operation and include the *HS-DSCH Semi-Persistent scheduling Information Response LCR* IE in the RADIO LINK ADDITION RESPONSE message.]

- [1.28 Mcps TDD If the HS-DSCH Semi-Persistent Resource Reservation Indicator IE is included in the HS-DSCH Semi-Persistent scheduling Information LCR IE, then the DRNS shall include Allcoated HS-PDSCH Semi-persistent resource IE in the RADIO LINK ADDITON RESPONSE message.]
- [1.28 Mcps TDD The DRNS shall include the *Buffer Size for HS-DSCH Semi-Persistent scheduling* IE in the RADIO LINK ADDITION RESPONSE message.]
- [1.28 Mcps TDD The DRNS shall include the *Number of Processes for HS-DSCH Semi-Persistent scheduling* IE in the RADIO LINK ADDITION RESPONSE message.]
- [1.28 Mcps TDD If the *HS-DSCH Semi-Persistent scheduling operation Indicator* IE is included in the *HS-DSCH Semi-Persistent scheduling Information LCR* IE, then the DRNS shall apply this information for HS-DSCH Semi-Persistent scheduling operation.]

[1.28 Mcps TDD – If the RADIO LINK ADDITION REQUEST message includes the *E-DCH Semi-Persistent scheduling Information LCR* IE, then:]

- [1.28 Mcps TDD The DRNS shall configure the Serving E-DCH Radio Link indicated by the *E-DCH Serving RL* IE for E-DCH Semi-Persistent scheduling operation according to TS 25.224 [22].]
- [1.28 Mcps TDD If the *E-DCH Semi-Persistent Resource Reservation Indicator* IE is included in the *E-DCH Semi-Persistent scheduling Information LCR* IE, then the DRNS shall include *Allcoated E-DCH Semi-persistent resource* IE in the RADIO LINK ADDITON RESPONSE message.]
- [1.28 Mcps TDD If the *E-DCH Semi-Persistent scheduling Indicator* IE is included in the *E-DCH Semi-Persistent scheduling Information LCR* IE, then the DRNS shall apply this information for E-DCH Semi-Persistent scheduling operation.]

[1.28 Mcps TDD –Multi-Carrier E-DCH:]

[1.28Mcps TDD - If the *Multi-Carrier E-DCH Information* IE is present in the RADIO LINK ADDITION REQUEST message, then the *Multi-Carrier E-DCH Information* IE defines the new configuration and then:]

- [1.28Mcps TDD The DRNS shall setup the requested E-DCH resource on the uplink frequecies indicated by the the *Multi-Carrier E-DCH Information LCR* IE.]
- [1.28Mcps TDD The DRNS shall use the corresponding *PRXdes_base* IE for power control on each uplink frequency according to TS 25.331 [16].]
- [1.28Mcps TDD If the *SNPL Carrier Group Indicator* IE is present in the *Multi-Carrier E-DCH Information LCR* IE, the DRNS shall use the information to determine which SNPL Carrier Group each frequency indicated by the *UARFCN* IE belongs to.]
- [1.28Mcps TDD If the *Multi-Carrier E-DCH Transport Bearer Mode LCR* IE is set to "Separate Iur transport bearer mode", the DRNS shall use this mode in the new configuration and apply separate transport bearers for the MAC-d flows.]
- [1.28Mcps TDD If the *Multi-Carrier E-DCH Transport Bearer Mode LCR* IE is set to "E-DCH UL flow multiplexing mode", the DRNS shall use this mode in the new configuration and multiplex MAC-d flow received on the different carriers on one Iur transport bearer.]
- [1.28Mcps TDD If the Separate Iur transport bearer mode is used in the new configuration, then the DRNS shall include the *Binding ID* IE and *Transport Layer Address* IE in the *Multi-Carrier E-DCH Information Response LCR* IE in the RADIO LINK ADDITION RESPONSE message for establishment of a transport bearer for every E-DCH MAC-d flow being established.]
- [1.28Mcps TDD If the E-DCH UL flow multiplexing mode is used in the new configuration, then the DRNS shall include the *Binding ID* IE and *Transport Layer Address* IE in the *E-DCH TDD Information Response* 1.28Mcps IE in the RADIO LINK ADDITION RESPONSE message for establishment of a transport bearer for every E-DCH MAC-d flow being established.]

[1.28 Mcps TDD - MU-MIMO Handling:]

[1.28Mcps TDD - If the RADIO LINK ADDITION REQUEST message includes the MU-MIMO Indicator IE, then:]

- [1.28 Mcps TDD –the DRNS may use the MU-MIMO for the radio link according to the *MU-MIMO Usage Indicator* IE and shall include the *MU-MIMO Information* IE in the RADIO LINK SETUP RESPONSE message.]
- [1.28 Mcps TDD If the Standalone Midamble Channel Indicator IE is set to "Used", then the DRNS shall include Standalone Midamble Channel information in the RADIO LINK ADDITION RESPONSE message.
 Else, the DRNS shall not include Standalone Midamble Channel information in the RADIO LINK ADDITION RESPONSE message.

Response message:

If all requested RLs are successfully added, the DRNC shall respond with a RADIO LINK ADDITION RESPONSE message.

After sending the RADIO LINK ADDITION RESPONSE message the DRNS shall continuously attempt to obtain UL synchronisation on the Uu interface.

For each RL for which the *Delayed Activation* IE is not included in the RADIO LINK ADDITION REQUEST message the DRNS shall:

- [FDD –start transmission on the DL DPDCH(s) of the new RL as specified in TS 25.427 [4].]
- [TDD start transmission on the new RL immediately as specified in TS 25.427 [4].]

For each RL for which the *Delayed Activation* IE is included in the RADIO LINK ADDITION REQUEST message, the DRNS shall:

- if the *Delayed Activation* IE indicates "Separate Indication":
 - not start any DL transmission for the concerning RL on the Uu interface;
- if the Delayed Activation IE indicates "CFN":
 - [FDD start transmission on the DL DPDCH(s) of the new RL as specified in TS 25.427 [4], however never before the CFN indicated in the *Activation CFN* IE.]
- [TDD start transmission on the new RL at the CFN indicated in the *Activation CFN* IE as specified in TS 25.427 [4].]

[1.28 Mcps TDD – if the DRNS assigns one or more PLCCH sequence numbers to the radio link, then the PLCCH assignment(s) shall be sent to the SRNC in the RADIO LINK ADDITION RESPONSE message.]

8.3.2.3 Unsuccessful Operation




Figure 8: Radio Link Addition procedure: Unsuccessful Operation

If the establishment of at least one RL is unsuccessful, the DRNC shall respond with a RADIO LINK ADDITION FAILURE message. DRNC shall include in the RADIO LINK ADDITION FAILURE message a general *Cause* IE or a *Cause* IE for each failed radio link. The *Cause* IE indicates the reason for failure.

[FDD – If some RL(s) were established successfully, the DRNC shall indicate this in the RADIO LINK ADDITION FAILURE message in the same way as in the RADIO LINK ADDITION RESPONSE message.]

[FDD – If the requested Serving HS-DSCH Radio Link Change was successful, or if the addition of the requested serving HS-DSCH Radio Link was successful or existed already but the Serving HS-DSCH Radio Link change was

unsuccessful, the DRNS shall indicate this in the *HS-DSCH Serving Cell Change Information Response* IE in the RADIO LINK ADDITION FAILURE message]

[FDD – If the requested secondary serving HS-DSCH Radio Link Change was successful, or if the addition of the requested secondary serving HS-DSCH Radio Link was successful or existed already but the secondary serving HS-DSCH Radio Link change was unsuccessful, the DRNS shall indicate this in the *HS-DSCH Secondary Serving Cell Change Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK ADDITION FAILURE message.]

[FDD – If the requested Serving E-DCH Radio Link Change was successful, or if the addition of the requested serving E-DCH Radio Link was successful or existed already but the Serving E-DCH Radio Link change was unsuccessful, the DRNS shall indicate this in the *E-DCH Serving Cell Change Information Response* IE in the RADIO LINK ADDITION FAILURE message.]

[FDD – If the MIMO Activation Indicator IE is included and the Power Offset For S-CPICH for MIMO Request Indicator IE is not included in the HS-DSCH FDD Information IE in the HS-DSCH Serving Cell Change Information IE in the RADIO LINK ADDITION REQUEST message or the power offset for S-CPICH for MIMO Request indicator has not been configured in the UE Context but MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where the Serving HS-DSCH Radio Link is established, the setup of the serving HS-DSCH Radio Link shall be reported as failed and the DRNC shall include in the RADIO LINK ADDITION FAILURE message the Cause IE.]

[FDD – If the requested additional serving E-DCH Radio Link Change was successful, or if the addition of the requested additional serving E-DCH Radio Link was successful or existed already but the additional serving E-DCH Radio Link change was unsuccessful, the DRNS shall indicate this in the *Additional E-DCH Secondary Serving Cell Change Information Response* IE in the RADIO LINK ADDITION FAILURE message.]

Typical cause values are:

Radio Network Layer Causes:

DL Radio Resources not Available:

UL Radio Resources not Available;

Combining Resources not Available;

Combining not Supported

Cell not Available;

[FDD – Requested Tx Diversity Mode not Supported;]

Power Level not Supported;

CM not Supported;

Reconfiguration CFN not Elapsed;

Number of DL Codes not Supported;

Number of UL codes not Supported;

[FDD – DPC mode change not Supported;]

Cell reserved for operator use;

Delayed Activation not supported;

[FDD – F-DPCH not supported;]

E-DCH not supported;

[FDD – MIMO not supported;]

[FDD – E-DCH TTI2ms not supported;]

[FDD - Continuous Packet Connectivity DTX-DRX operation not available;]

[FDD - Continuous Packet Connectivity UE DTX Cycle not available;]

[FDD – MIMO not available;]

[FDD – F-DPCH Slot Format operation not supported;]

[FDD – E-DPCCH Power Boosting not supported;]

[FDD – SixtyfourQAM DL and MIMO Combined not available;]

[FDD – Multi Cell operation not available;]

[FDD – Multi Cell operation not supported;]

[1.28Mcps TDD – MIMO not supported;]

[1.28Mcps TDD – MIMO not available;]

[1.28Mcps TDD – SixtyfourQAM DL and MIMO Combined not available;]

[FDD – TX diversity for MIMO UE on DL Control Channels not available;]

[FDD – Single Stream MIMO not available;]

[FDD – Multi Cell operation with MIMO not available;]

[FDD – Multi Cell operation with MIMO not supported;]

[FDD – Multi Cell E-DCH Operation not supported;]

[FDD – Multi Cell E-DCH Operation not available;]

[FDD – Multi Cell operation with Single Stream MIMO not available;]

[FDD – Multi Cell operation with Single Stream MIMO not supported;]

[FDD – Cell Specific Tx Diversity Handling For Multi Cell Operation Not Available;]

[FDD – Cell Specific Tx Diversity Handling For Multi Cell Operation Not Supported;]

[FDD – Frequency Specific Compressed Mode Not Available]

Transport Layer Causes:

Transport Resource Unavailable.

Miscellaneous Causes:

Control Processing Overload;

HW Failure;

Not enough User Plane Processing Resources.

8.3.2.4 Abnormal Conditions

If the RADIO LINK ADDITION REQUEST message includes a *C-ID* IE corresponding to a cell reserved for operator use and the Permanent NAS UE Identity is not available in the DRNC for the considered UE Context, the DRNC shall reject the procedure for this particular Radio Link and send the RADIO LINK ADDITION FAILURE message.

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Transmission Gap Pattern Sequence Status* IEs in the *Active Pattern Sequence Information* IE and it does not address exactly all ongoing compressed mode patterns and frequency specific compressed mode is not supported, the DRNS shall reject the Radio Link Addition procedure and shall respond with a RADIO LINK ADDITION FAILURE message with the *Cause* IE value "Invalid CM settings".]

[FDD – If the RADIO LINK ADDITION REQUEST message is used to establish a new RL without compressed mode when compressed mode is active for the existing RL(s) (as specified in subclause 8.3.2.2), and if at least one of the new RLs is to be established in a cell that has the same UARFCN (both UL and DL) as at least one cell with an already existing RL and frequency specific compressed mode is not supported,, the DRNS shall reject the Radio Link Addition procedure and shall respond with a RADIO LINK ADDITION FAILURE message with the cause value "Invalid CM settings".]

[FDD – If the power balancing is active with the Power Balancing Adjustment Type of the UE Context set to "Individual" in the existing RL(s) and if the *DL Reference Power* IEs are included in the *RL Information* IE but the *DL Reference Power* IE is not present for each RL in the *RL Information* IE, the DRNC shall reject the Radio Link Addition procedure and shall respond with a RADIO LINK ADDITION FAILURE message.]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *DL Reference Power* IEs in the *RL Information* IE but the power balancing is not active in the existing RL(s) or the power balancing is active with the Power Balancing Adjustment Type of the UE Context set to "Common" in the existing RL(s), the DRNC shall reject the Radio Link Addition procedure and shall respond with a RADIO LINK ADDITION FAILURE message with the cause value "Power Balancing status not compatible".]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Enhanced Primary CPICH Ec/No* IE, but not the *Primary CPICH Ec/No* IE, then the DRNC shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

If the RADIO LINK ADDITION REQUEST message includes the *Transport Layer Address* IE and the *Binding ID* IE in the *RL Specific DCH Information* IE [FDD – or for an E-DCH MAC-d flow in *RL Specific E-DCH Information* IE] included in the *RL Information* IE for a specific RL and the *Diversity Control Field* IE is set to "Must" [FDD – or the RL is combined with existing E-DCH RL which transport bearer is not established in the DRNS], the DRNC shall reject the Radio Link Addition procedure and respond with the RADIO LINK ADDITION FAILURE message.

If ALCAP is not used, if the RADIO LINK ADDITION REQUEST message does not include the *Transport Layer Address* IE and the *Binding ID* IE in the *RL Specific DCH Information* IE nor *RL Specific E-DCH Information* IE in the *RL Information* IE for a specific RL and the *Diversity Control Field* IE is set to "May", the DRNC shall reject the Radio Link Addition procedure and respond with the RADIO LINK ADDITION FAILURE message.

If ALCAP is not used, if the RADIO LINK ADDITION REQUEST message does not include the *Transport Layer Address* IE and the *Binding ID* IE in the *RL Specific DCH Information* IE in the *RL Information* IE for a specific RL and the *Diversity Control Field* IE is set to "Must Not", the DRNC shall reject the Radio Link Addition procedure and respond with the RADIO LINK ADDITION FAILURE message.

If ALCAP is not used, if the RADIO LINK ADDITION REQUEST message does not include the *Transport Layer Address* IE and the *Binding ID* IE in [FDD – the *RL Specific E-DCH Information* IE in the *RL Information* IE for the first E-DCH RL][TDD – the *E-DCH MAC-d Flows Information TDD* IE], the DRNC shall reject the Radio Link Addition procedure and respond with the RADIO LINK ADDITION FAILURE message.

If ALCAP is not used, if the RADIO LINK ADDITION REQUEST message does not include the *Transport Layer Address* IE and the *Binding ID* IE for an HS-DSCH MAC-d Flow in the *HS-DSCH MAC-d Flows Information* IE, the DRNC shall reject the Radio Link Addition procedure and respond with the RADIO LINK ADDITION FAILURE message.

If the RADIO LINK ADDITION REQUEST message includes the *Transport Layer Address* IE or the *Binding ID* IE, and not both are present for a transport bearer intended to be established, the DRNC shall reject the Radio Link Addition procedure and respond with the RADIO LINK ADDITION FAILURE message.

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *HS-DSCH Serving Cell Change Information* IE but not the *HS-DSCH FDD Information* IE and the UE Context is not configured for HS-DSCH, then the DRNS shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Serving Cell Change CFN* IE but neither the *Serving E-DCH RL* IE nor the *HS-DSCH Serving Cell Change Information* IE, then the DRNS shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Serving E-DCH RL* IE but the UE Context is not configured for E-DCH, then the DRNS shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[FDD – If the *E-DCH FDD Information* IE is present in the RADIO LINK ADDITION REQUEST message, but the *E-DPCH Information* IE is not present, then the DRNS shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *E-DCH RL Indication* IE set to "E-DCH", but no *E-DCH FDD Information* IE, and the UE Context is not configured for E-DCH, then the DRNC shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *E-DCH FDD Information* IE but no *E-DCH RL Indication* IE set to "E-DCH", then the DRNC shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[TDD – If the RADIO LINK ADDITION REQUEST message includes the *HS-PDSCH RL-ID* IE not equal to the *RL ID* IE, the DRNC shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[TDD – If the RADIO LINK ADDITION REQUEST message includes the *E-DCH Serving RL* IE not equal to the *RL ID* IE, the DRNS shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

If the RADIO LINK ADDITION REQUEST message contains the *HS-PDSCH RL ID* IE [FDD – in the *HS-DSCH Serving Cell Change Information* IE] and/or *Serving E-DCH RL* IE and if both HS-DSCH and E-DCH are configured in the DRNS but the Serving HS-DSCH Radio Link and the Serving E-DCH Radio Link are not in the same cell then the DRNC shall reject the procedure using the RADIO LINK ADDITION FAILURE message.

[FDD – If the RADIO LINK ADDITION REQUEST message contains the *HS-DSCH Serving Cell Change Information* IE and the *E-DPCH Information* IE which includes the *HS-DSCH Configured Indicator* IE set as "HS-DSCH not configured" then the DRNC shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

If the RADIO LINK ADDITION REQUEST message includes the *Maximum MAC-d PDU Size Extended* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE [FDD – in the *HS-DSCH Serving Cell Change Information*] and the *HS-DSCH MAC-d PDU Size Format* IE in the *HS-DSCH Information* IE [FDD – in the *HS-DSCH Serving Cell Change Information*] has the value "Indexed MAC-d PDU Size", the DRNC shall reject the procedure using the RADIO LINK ADDITION FAILURE message.

If the RADIO LINK ADDITION REQUEST message does not include the *Maximum MAC-d PDU Size Extended* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE [FDD – in the *HS-DSCH Information* IE in the *HS-DSCH Information* IE [FDD – in the *HS-DSCH Serving Cell Change Information*] has the value "Flexible MAC-d PDU Size", the DRNC shall reject the procedure using the RADIO LINK ADDITION FAILURE message.

[FDD – If the RADIO LINK ADDITION REQUEST message contains, for at least one logical channel, the *Maximum MAC-d PDU Size Extended* IE in the *E-DCH MAC-d Flows Information* IE in the *E-DCH FDD Information* IE and there exist a logical channel for which the *Maximum MAC-d PDU Size Extended* IE in the *E-DCH MAC-d Flows Information* IE in the *E-DCH FDD Information* IE is not present, the DRNC shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[TDD – If the RADIO LINK ADDITION REQUEST message contains, for at least one logical channel, the *Maximum MAC-d PDU Size Extended* IE in the *E-DCH MAC-d Flows Information TDD* IE in the *E-DCH Information* IE, and there exist a logical channel for which the *Maximum MAC-d PDU Size Extended* IE in the *E-DCH MAC-d Flows Information TDD* IE in the *E-DCH Information* IE is not present, the DRNC shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[FDD – If the RADIO LINK ADDITION REQUEST message contains the *Transport Bearer Not Requested Indicator* IE for a DCH but the DCH is configured to be included as a part of the downlink CCTrCH, the DRNC shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[FDD – If the RADIO LINK ADDITION REQUEST message contains the MIMO Activation Indicator IE, Sixtyfour QAM Usage Allowed Indicator IE set to "Allowed", the Additional HS Cell Information RL Addition IE and/or the Single Stream MIMO Activation Indicator IE, but does not contain the HS-DSCH MAC-d PDU Size Format IE set to "Flexible MAC-d PDU Size", then the DRNC shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[FDD – If the RADIO LINK ADDITION REQUEST message contains the *Serving E-DCH RL ID* IE but contains the *Transport Bearer Not Requested Indicator* IE in the RL Specific E-DCH Information for the new Serving E-DCH RL or there is at least one E-DCH MAC-d flow which transport bearer was not configured in the existing E-DCH RL to be combined with the Serving E-DCH RL, the DRNC shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[FDD – If the RADIO LINK ADDITION REQUEST message includes the *Transport Bearer Not Requested Indicator* IE for a DCH or an E-DCH MAC-d Flow for a specific RL and the specific RL is combined with the existing RL which the transport bearer is established for the DCH or the E-DCH MAC-d Flow in DRNS, the DRNC shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[FDD – If the RADIO LINK ADDITION REQUEST message contains the *Additional HS Cell Information RL Addition* IE indicating a seconadry serving cell that is not in the same Node B as the new serving HS-DSCH cell, then the DRNC shall reject the procedure using the RADIO LINK ADDITION FAILURE message]

[FDD – If the RADIO LINK ADDITION REQUEST message contains the *Additional HS Cell Information RL Addition* IE and if the HS-DSCH is not configured in the DRNS Communication Context and the *HS-DSCH Information* IE is not present, then the DRNS shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

If the RADIO LINK ADDITION REQUEST message includes *DL RLC PDU Size Format* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE [FDD – in the *HS-DSCH Serving Cell Change Information* IE] set to "Flexible RLC PDU Size", *HS-DSCH MAC-d PDU Size Format* IE in the *HS-DSCH Information* IE [FDD – in the *HS-DSCH Serving Cell Change Information* IE] has the value "Indexed MAC-d PDU Size", the DRNC shall reject the procedure using the RADIO LINK ADDITION FAILURE message.

If the RADIO LINK ADDITION REQUEST message does not include the *Maximum MAC-d PDU Size Extended* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE [FDD – in the *HS-DSCH Information* IE] and the *DL RLC PDU Size Format* IE in the *HS-DSCH Information* IE [FDD – in the *HS-DSCH Serving Cell Change Information* IE] has the value "Flexible RLC PDU Size", the DRNC shall reject the procedure using the RADIO LINK ADDITION FAILURE message.

[FDD – If the RADIO LINK ADDITION REQUEST message contains a MIMO Activation Indicator IE and a Single Stream MIMO Activation Indicator IE in the HS-DSCH FDD Information IE in the HS-DSCH Serving Cell Change Information IE or in the HS-DSCH FDD Secondary Serving Information IE in the Additional HS Cell Information RL Addition IE, then the DRNC shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[FDD – If the RADIO LINK ADDITION REQUEST message contains the *Additional E-DCH Cell Information RL Setup Req* IE and if the *E-DPCH Information* IE is not present or the E-DPCH Information was not configured in the UE Context, then the DRNS shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[FDD – If the RADIO LINK ADDITION REQUEST message contains the *Additional E-DCH Cell Information RL Add Req* IE and there exist a logical channel for which the *Maximum MAC-d PDU Size Extended* IE in the *E-DCH MAC-d Flows Information* IE in the *E-DCH FDD Information* IE is not present, the DRNS shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[FDD – If the RADIO LINK ADDITION REQUEST message contains the *Additional E-DCH Cell Information RL Add Req* IE and the *C-ID* IE is not included in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE in the *Additional E-DCH Cell Information Setup* IE, but the Radio Link indicated by *the E-DCH Additional RL ID* IE is not configured in the current UE context as a Secondary Serving HS-DSCH radio link without any configured Additional E-DCH, the DRNS shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[FDD – If the RADIO LINK ADDITION REQUEST message contains the *Diversity Mode* IE in the *HS-DSCH FDD Secondary Serving Information* IE in the *Additional HS Cell Information RL Addition* IE and the secondary serving HS-DSCH is already configured in the UE Context, then the DRNS shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[FDD – If the secondary serving HS-DSCH is not configured in the UE Context and if the RADIO LINK ADDITION REQUEST message contains in the *HS-DSCH FDD Secondary Serving Information* IE in the *Additional HS Cell Information RL Addition* IE the *Diversity Mode* IE not set to "None" but not the *Transmit Diversity Indicator* or contains the *Transmit Diversity Indicator* but not the *Diversity Mode* IE not set to "None", then the DRNS shall reject the procedure using the RADIO LINK SETUP FAILURE message.]

[FDD - If the RADIO LINK ADDITION REQUEST message contains the *Additional HS Cell Information RL Addition* IE and the new configuration contains more than one secondary serving HS-DSCH RL and all secondary serving HS-DSCH RLs in the new configuration will not be assigned consecutive ordinal numbers starting with the value "1", which are previously assigned to the RL or received in the *Ordinal Number Of Frequency* IE in the *HS-DSCH FDD Secondary Serving Information* IE, the DRNS shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[FDD - If the RADIO LINK ADDITION REQUEST message contains the *Additional HS Cell Information RL Addition* IE and the new configuration contains more than one secondary serving HS-DSCH RL, the new configuration also contains an Additional E-DCH Serving Radio Link and the secondary serving HS-DSCH Radio link, which is configured in the same cell as the Additional E-DCH Serving Radio Link does not have Ordinal Number Of Frequency value "1", the DRNS shall reject the procedure using the RADIO LINK ADDITION FAILURE message.]

[FDD - If the RADIO LINK ADDITION REQUEST message contains the *Affected HS-DSCH serving cell List* IE in the *Active Pattern Sequence Information* IE, and the Transmission Gap Pattern Sequence for affected HS-DSCH Serving Cells is activated on the HS-DSCH Primary Serving Cell but not for all the other serving cells, the DRNS shall reject the procedure using the RADIO LINK ADDITION FAILURE message with the cause value "Invalid CM settings".]

8.3.3 Radio Link Deletion

8.3.3.1 General

The Radio Link Deletion procedure is used to release the resources in a DRNS for one or more established radio links towards a UE.

This procedure shall use the signalling bearer connection for the relevant UE Context.

The Radio Link Deletion procedure may be initiated by the SRNC at any time after establishing a Radio Link.

8.3.3.2 Successful Operation




Figure 9: Radio Link Deletion procedure, Successful Operation

The procedure is initiated with a RADIO LINK DELETION REQUEST message sent from the SRNC to the DRNC.

Upon receipt of this message, the DRNS shall delete the radio link(s) identified by the *RL ID* IE(s) in the message, shall release all associated resources and shall respond to the SRNC with a RADIO LINK DELETION RESPONSE message.

If the radio link(s) to be deleted represent the last radio link(s) for the UE in the DRNS and if the UE is not using any common resources in the DRNS, then the DRNC shall release the UE Context.

[FDD – After deletion of the RL(s), the UL out-of-sync algorithm defined in TS 25.214 [10] shall for each of the remaining RL Set(s) use the maximum value of the parameters N_OUTSYNC_IND and T_RLFAILURE that are configured in the cells supporting the radio links of the RL Set. The UL in-sync algorithm defined in TS 25.214 [10] shall for each of the remaining RL Set(s) use the minimum value of the parameters N_INSYNC_IND that are configured in the cells supporting the radio links of the RL Set.]

[FDD – If the RL indicated by the *RL ID* IE in the RADIO LINK DELETION REQUEST message is the serving HS-DSCH Radio link and a related secondary serving HS-DSCH Radio Link exists in the DRNS, the DRNC shall delete the secondary serving HS-DSCH Radio Link.]

[FDD – If the RL indicated by the *RL ID* IE in the RADIO LINK DELETION REQUEST message is the secondary serving HS-DSCH Radio link, the DRNC shall delete the secondary serving HS-DSCH Radio Link.]

8.3.3.3 Unsuccessful Operation

-

8.3.3.4 Abnormal Conditions

If the RL indicated by the *RL ID* IE does not exist, the DRNC shall respond with the RADIO LINK DELETION RESPONSE message.

8.3.4 Synchronised Radio Link Reconfiguration Preparation

8.3.4.1 General

The Synchronised Radio Link Reconfiguration Preparation procedure is used to prepare a new configuration of Radio Link(s) related to one UE-UTRAN connection within a DRNS.

This procedure shall use the signalling bearer connection for the relevant UE Context.

The Synchronised Radio Link Reconfiguration Preparation procedure shall not be initiated if a Prepared Reconfiguration exists, as defined in subclause 3.1.

8.3.4.2 Successful Operation




Figure 10: Synchronised Radio Link Reconfiguration Preparation procedure, Successful Operation

The Synchronised Radio Link Reconfiguration Preparation procedure is initiated by the SRNC by sending the RADIO LINK RECONFIGURATION PREPARE message to the DRNC.

Upon receipt, the DRNS shall reserve necessary resources for the new configuration of the Radio Link(s) according to the parameters given in the message. Unless specified below, the meaning of parameters is specified in other specifications.

If the RADIO LINK RECONFIGURATION PREPARE message includes the *Allowed Queuing Time* IE the DRNS may queue the request the time corresponding to the value of the *Allowed Queuing Time* IE before starting to execute the request.

The DRNS shall prioritise resource allocation for the RL(s) to be modified according to Annex A.

If the *UE Aggregate Maximum Bit Rate* IE is contained in the RADIO LINK RECONFIGURATION PREPARE message, the DRNS shall, if supported, store the received UE Aggregate Maximum Bit Rate parameters to control the aggregate data rate of non GBR traffic for this UE.

DCH Modification:

If the RADIO LINK RECONFIGURATION PREPARE message includes any *DCHs To Modify* IEs, the DRNS shall treat them each as follows:

- If the *DCHs To Modify* IE includes multiple *DCH Specific Info* IEs then the DRNS shall treat the DCHs in the *DCHs To Modify* IE as a set of co-ordinated DCHs. The DRNS shall include these DCHs in the new configuration only if it can include all of them in the new configuration.
- If the *DCHs To Modify* IE includes the *UL FP Mode* IE for a DCH or a set of co-ordinated DCHs to be modified, the DRNS shall apply the new FP Mode in the Uplink of the user plane for the DCH or the set of co-ordinated DCHs in the new configuration.
- If the *DCHs To Modify* IE includes the *ToAWS* IE for a DCH or a set of co-ordinated DCHs to be modified, the DRNS shall apply the new ToAWS in the user plane for the DCH or the set of co-ordinated DCHs in the new configuration.
- If the *DCHs To Modify* IE includes the *ToAWE* IE for a DCH or a set of co-ordinated DCHs to be modified, the DRNS shall apply the new ToAWE in the user plane for the DCH or the set of co-ordinated DCHs in the new configuration.
- If the *DCHs To Modify* IE contains a *DCH Specific Info* IE which includes the *Frame Handling Priority* IE for a DCH to be modified, the DRNS should store this information for this DCH in the new configuration. The received Frame Handling Priority should be used when prioritising between different frames in the downlink on the radio interface in congestion situations within the DRNS once the new configuration has been activated.
- If the *DCHs To Modify* IE contains a *DCH Specific Info* IE which includes the *Traffic Class* IE for a DCH to be modified, the DRNS should store this information for this DCH in the new configuration. The *Traffic Class* IE may be used to determine the transport bearer characteristics to apply between DRNC and Node B for the related DCH or set of co-ordinated DCHs. The DRNC should ignore the *Traffic Class* IE if the *TrCH Source Statistics Descriptor* IE for this DCH indicates the value "RRC".
- [FDD If the *DCHs to Modify* IE contains a *DCH Specific Info* IE which includes the *Unidirectional DCH indicator* IE set to "Uplink DCH only", the DRNS shall ignore the *Transport Format Set* IE for the downlink for this DCH. As a consequence this DCH is not included as a part of the downlink CCTrCH.]

- [FDD If the *DCHs to Modify* IE contains a *DCH Specific Info* IE which includes the *Unidirectional DCH indicator* IE set to "Downlink DCH only", the DRNS shall ignore the *Transport Format Set* IE for the uplink for this DCH. As a consequence this DCH is not included as a part of the uplink CCTrCH.]
- If the *DCHs To Modify* IE contains a *DCH Specific Info* IE which includes the *Transport Format Set* IE for the UL of a DCH to be modified, the DRNS shall apply the new Transport Format Set in the Uplink of this DCH in the new configuration.
- If the *DCHs to Modify* IE includes the *TNL QoS* IE for a DCH or a set of co-ordinated DCHs to be modified and if ALCAP is not used, the DRNS may store this information for this DCH in the new configuration. The *TNL QoS* IE may be used to determine the transport bearer characteristics to apply in the uplink for the related DCH or set of co-ordinated DCHs.
- If the *DCHs To Modify* IE contains a *DCH Specific Info* IE which includes the *Transport Format Set* IE for the DL of a DCH to be modified, the DRNS shall apply the new Transport Format Set in the Downlink of this DCH in the new configuration.
- If the *DCHs To Modify* IE contains a *DCH Specific Info* IE which includes the *Allocation/Retention Priority* IE, the DRNS shall apply the new Allocation/Retention Priority to this DCH in the new configuration according to Annex A.
- [TDD If the *DCHs To Modify* IE includes the *CCTrCH ID* IE for the UL, the DRNS shall map the DCH onto the referenced UL CCTrCH in the new configuration.]
- [TDD If the *DCHs To Modify* IE includes the *CCTrCH ID* IE for the DL, the DRNS shall map the DCH onto the referenced DL CCTrCH in the new configuration.]
- If the *DCHs To Modify* IE contains a *DCH Specific Info* IE which includes the *Guaranteed Rate Information* IE, the DRNS shall treat the included IEs according to the following:
 - If the *Guaranteed Rate Information* IE includes the *Guaranteed UL Rate* IE, the DRNS shall apply the new Guaranteed Rate in the uplink of this DCH in the new configuration. The DRNS may decide to request the SRNC to limit the user rate in the uplink of the DCH at any point in time after activating the new configuration. The DRNS may request the SRNC to reduce the user rate of the uplink of the DCH below the guaranteed bit rate, however, whenever possible the DRNS should request the SRNC to reduce the user rate between the maximum bit rate and the guaranteed bit rate.
 - If the *Guaranteed Rate Information* IE includes the *Guaranteed DL Rate* IE, the DRNS shall apply the new Guaranteed Rate in the downlink of this DCH in the new configuration. The DRNS may decide to request the SRNC to limit the user rate in the downlink of the DCH at any point in time after activating the new configuration. The DRNS may request the SRNC to reduce the user rate of the downlink of the DCH below the guaranteed bit rate, however, whenever possible the DRNS should request the SRNC to reduce the user rate between the maximum bit rate and the guaranteed bit rate.

DCH Addition:

If the RADIO LINK RECONFIGURATION PREPARE message includes any *DCHs To Add* IEs, the DRNS shall treat them each as follows:

- The DRNS shall reserve necessary resources for the new configuration of the Radio Link(s) according to the parameters given in the message and include these DCH in the new configuration.
- If the *DCH Information* IE includes a *DCHs To Add* IE with multiple *DCH Specific Info* IEs, the DRNS shall treat the DCHs in the *DCHs To Add* IE as a set of co-ordinated DCHs. The DRNS shall include these DCHs in the new configuration only if it can include all of them in the new configuration.
- If the *DCH Specific Info* IE includes the *Unidirectional DCH Indicator* IE set to "Uplink DCH only", the DRNS shall ignore the *Transport Format Set* IE for the downlink for this DCH. As a consequence this DCH is not included as a part of the downlink CCTrCH.
- If the *DCH Specific Info* IE includes the *Unidirectional DCH Indicator* IE set to "Downlink DCH only", the DRNS shall ignore the *Transport Format Set* IE for the uplink for this DCH. As a consequence this DCH is not included as a part of the uplink CCTrCH.

- [FDD For each DCH which do not belong to a set of co-ordinated DCHs and which includes a *QE-Selector* IE set to "selected", the DRNS shall use the Transport channel BER from that DCH for the QE in the UL data frames. If no Transport channel BER is available for the selected DCH, the DRNS shall use the Physical channel BER for the QE, TS 25.427 [4]. If the *QE-Selector* IE is set to "non-selected", the DRNS shall use the Physical channel BER for the QE in the UL data frames, TS 25.427 [4].]
- For a set of co-ordinated DCHs, the DRNS shall use the Transport channel BER from the DCH with the *QE-Selector* IE set to "selected" for the QE in the UL data frames, TS 25.427 [4]. [FDD If no Transport channel BER is available for the selected DCH, the DRNS shall use the Physical channel BER for the QE, TS 25.427 [4]. If all DCHs have the *QE-Selector* IE set to "non-selected", the DRNS shall use the Physical channel BER for the QE, TS 25.427 [4].] [TDD If no Transport channel BER is available for the selected DCH, the DRNS shall use 0 for the QE, TS 25.427 [4].]
- The DRNS should store the *Frame Handling Priority* IE received for a DCH to be added in the new configuration. The received Frame Handling Priority should be used when prioritising between different frames in the downlink on the Uu interface in congestion situations within the DRNS once the new configuration has been activated.
- If the *TNL QoS* IE is included for a DCH or a set of co-ordinated DCHs and if ALCAP is not used, the DRNS may use this information to determine the transport bearer characteristics to apply for the uplink for the related DCH or set of co-ordinated DCHs.
- The DRNS should store the *Traffic Class* IE received for a DCH to be added in the new configuration. The *Traffic Class* IE may be used to determine the transport bearer characteristics to apply between DRNC and Node B for the related DCH or set of co-ordinated DCHs. The DRNC should ignore the *Traffic Class* IE if the *TrCH Source Statistics Descriptor* IE indicates the value "RRC".
- The DRNS shall use the included *UL FP Mode* IE for a DCH or a set of co-ordinated DCHs to be added as the new FP Mode in the Uplink of the user plane for the DCH or the set of co-ordinated DCHs in the new configuration.
- The DRNS shall use the included *ToAWS* IE for a DCH or a set of co-ordinated DCHs to be added as the new Time of Arrival Window Startpoint in the user plane for the DCH or the set of co-ordinated DCHs in the new configuration.
- The DRNS shall use the included *ToAWE* IE for a DCH or a set of co-ordinated DCHs to be added as the new Time of Arrival Window Endpoint in the user plane for the DCH or the set of co-ordinated DCHs in the new configuration.
- [3.84Mcps TDD The DRNC shall include the *Secondary CCPCH Info TDD* IE in the RADIO LINK RECONFIGURATION READY message if at least one DSCH or USCH exists in the new configuration.]
- [1.28Mcps TDD The DRNC shall include the *Secondary CCPCH Info TDD LCR* IE in the RADIO LINK RECONFIGURATION READY message if at least one DSCH or USCH exists in the new configuration.]
- [7.68Mcps TDD The DRNC shall include the *Secondary CCPCH Info TDD* 7.68Mcps IE in the RADIO LINK RECONFIGURATION READY message if at least one DSCH or USCH exists in the new configuration.]
- If the *DCHs To Add* IE contains a *DCH Specific Info* IE which includes the *Guaranteed Rate Information* IE, the DRNS shall treat the included IEs according to the following:
 - If the *Guaranteed Rate Information* IE includes the *Guaranteed UL Rate* IE, the DRNS shall apply the new Guaranteed Rate in the uplink of this DCH in the new configuration. The DRNS may decide to request the SRNC to limit the user rate of the uplink of the DCH at any point in time after activating the new configuration. The DRNS may request the SRNC to reduce the user rate of the uplink of the DCH below the guaranteed bit rate, however, whenever possible the DRNS should request the SRNC to reduce the user rate between the maximum bit rate and the guaranteed bit rate. If the *DCH Specific Info* IE in the *DCHs To Add* IE does not include the *Guaranteed UL Rate* IE, the DRNS shall not limit the user rate of the uplink of the DCH.
 - If the *Guaranteed Rate Information* IE includes the *Guaranteed DL Rate* IE, the DRNS shall apply the new Guaranteed Rate in the downlink of this DCH in the new configuration. The DRNS may decide to request the SRNC to limit the user rate of the downlink of the DCH at any point in time after activating the new configuration. The DRNS may request the SRNC to reduce the user rate of the downlink of the DCH below

the guaranteed bit rate, however, whenever possible the DRNS should request the SRNC to reduce the user rate between the maximum bit rate and the guaranteed bit rate. If the *DCH Specific Info* IE in the *DCHs To Add* IE does not include the *Guaranteed DL Rate* IE, the DRNS shall not limit the user rate of the downlink of the DCH.

- [TDD The DRNS shall apply the *CCTrCH ID* IE (for the DL) in the Downlink of this DCH in the new configuration.]
- [TDD The DRNS shall apply the *CCTrCH ID* IE (for the UL) in the Uplink of this DCH in the new configuration.]

DCH Deletion:

If the RADIO LINK RECONFIGURATION PREPARE message includes any *DCH To Delete*, the DRNS shall not include the referenced DCHs in the new configuration.

If all of the DCHs belonging to a set of co-ordinated DCHs are requested to be deleted, the DRNS shall not include this set of co-ordinated DCHs in the new configuration.

Physical Channel Modification:

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes an *UL DPCH Information* IE, the DRNS shall apply the parameters to the new configuration as follows:]

- [FDD If the *UL DPCH Information* IE includes the *Uplink Scrambling Code* IE, the DRNS shall apply this Uplink Scrambling Code to the new configuration.]
- [FDD If the *UL DPCH Information* IE includes the *Min UL Channelisation Code Length* IE, the DRNS shall apply the new Min UL Channelisation Code Length in the new configuration. The DRNS shall apply the contents of the *Max Number of UL DPDCHs* IE (if it is included) in the new configuration.]
- [FDD If the *UL DPCH Information* IE includes the *TFCS* IE, the DRNS shall use the *TFCS* IE for the UL when reserving resources for the uplink of the new configuration. The DRNS shall apply the new TFCS in the uplink of the new configuration.]
- [FDD If the *UL DPCH Information* IE includes the *UL DPCCH Slot Format* IE, the DRNS shall apply the new Uplink DPCCH *Slot Format* to the new configuration.]
- [FDD If the *UL DPCH Information* IE includes the *UL SIR Target* IE, the DRNS shall use the value for the UL inner loop power control when the new configuration is being used.]
- [FDD If the *UL DPCH Information* IE includes the *Puncture Limit* IE, the DRNS shall apply the value in the uplink of the new configuration.]
- [FDD If the *UL DPCH Information* IE includes the *Diversity Mode* IE, the DRNS shall apply diversity according to the given value.]
- [FDD If the *UL DPCH Information* IE includes the *UL DPDCH Indicator For E-DCH Operation* IE and it is set to "UL DPDCH not present", the UL DPDCH resources shall be removed from the configuration.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes a *DL DPCH Information* IE and the concerned UE Context is configured to use F-DPCH in the downlink in the old configuration, the DRNS shall configure the concerned UE Context to use DPCH in the downlink in the new configuration. In this case, if at least one Transmission Gap Pattern Sequence is configured with an SF/2 downlink compressed mode method in the new configuration, the DRNC shall include the *Transmission Gap Pattern Sequence Scrambling Code Information* IE in the RADIO LINK RECONFIGURATION READY message indicating for each Channelisation Code whether the alternative scrambling code shall be used or not.]

- [FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *DL DPCH Power Information* IE, the DRNS shall use the information contained in it for the power settings of the DL DPCH. In particular, if the received *Inner Loop DL PC Status* IE is set to "Active", the DRNS shall activate the inner loop DL power control for all RLs. If *Inner Loop DL PC Status* IE is set to "Inactive", the DRNS shall deactivate the inner loop DL power control for all RLs according to TS 25.214 [10]. Furthermore, the DRNC shall include the *DL Code Information* IE in the RADIO LINK RECONFIGURATION READY.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes a *DL DPCH Information* IE, the DRNS shall apply the parameters to the new configuration as follows:]

- [FDD If the *DL DPCH Information* IE includes the *Number of DL Channelisation Codes* IE, the DRNS shall allocate given number of Downlink Channelisation Codes per Radio Link and apply the new Downlink Channelisation Code(s) to the new configuration. Each Downlink Channelisation Code allocated for the new configuration shall be included in the RADIO LINK RECONFIGURATION READY message within the *DL Code Information* IE as a *FDD DL Channelisation Code Number* IE when sent to the SRNC. If some Transmission Gap Pattern sequences using "SF/2" method are already initialised in the DRNS, DRNC shall include the *Transmission Gap Pattern Sequence Scrambling Code Information* IE in the RADIO LINK RECONFIGURATION READY message in case the DRNS selects to change the Scrambling code change method for one or more DL Channelisation Code.]
- [FDD When more than one DL DPDCH are assigned per RL, the segmented physical channel shall be mapped on to DL DPDCHs according to TS 25.211 [8]. When *p* number of DL DPDCHs are assigned to each RL, the first pair of DL Scrambling Code and FDD DL Channelisation Code Number corresponds to "*PhCH number 1*", the second to "*PhCH number 2*", and so on until the *p*th to "*PhCH number p*".]
- [FDD If the *DL DPCH Information* IE includes the *TFCS* IE, the DRNS shall use the *TFCS* IE for the DL when reserving resources for the downlink of the new configuration. The DRNS shall apply the new TFCS in the Downlink of the new configuration.]
- [FDD If the *DL DPCH Information* IE includes the *DL DPCH Slot Format* IE, the DRNS shall apply the new slot format used in DPCH in DL.]
- [FDD If the *DL DPCH Information* IE includes the *TFCI Signalling Mode* IE, the DRNS shall apply the new signalling mode of the TFCI.]
- [FDD If the *DL DPCH Information* IE includes the *Multiplexing Position* IE, the DRNS shall apply the new parameter to define whether fixed or flexible positions of transport channels shall be used in the physical channel.]
- [FDD If the *DL DPCH Information* IE includes the *Limited Power Increase* IE set to "Used", the DRNS shall, if supported, use Limited Power Increase according to TS 25.214 [10] subclause 5.2.1 for the inner loop DL power control in the new configuration.]
- [FDD If the *DL DPCH Information* IE includes the *Limited Power Increase* IE set to "Not Used", the DRNS shall not use Limited Power Increase for the inner loop DL power control in the new configuration.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the F-DPCH Information IE, then:]

- [FDD The DRNS shall configure the concerned UE Context to use F-DPCH in the downlink in the new configuration.]
- [FDD If the *F-DPCH Information* IE includes the *F-DPCH Slot Format Support Request* IE, then the DRNS shall configure the concerned UE Context for F-DPCH Slot Format operation according to TS 25.211 [8] and include the *F-DPCH Slot Format* IE in the RADIO LINK RECONFIGURATION READY message. If the *F-DPCH Information* IE includes the *F-DPCH Slot Format* IE, the DRNC may use the *F-DPCH Slot Format* IE to determine the F-DPCH slot format.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Transmission Gap Pattern Sequence Information* IE, the DRNS shall store the new information about the Transmission Gap Pattern Sequences to be used in the new Compressed Mode Configuration. Any Transmission Gap Pattern Sequences already existing in the previous Compressed Mode Configuration are replaced by the new sequences once the new Compressed Mode Configuration has been activated or once the previous Compressed Mode Configuration has been deactivated. This new Compressed Mode Configuration shall be valid in the DRNS until the next Compressed Mode Configuration is configured in the DRNS or until the last Radio Link is deleted.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Transmission Gap Pattern Sequence Information* IE and the *Downlink Compressed Mode Method* IE in one or more Transmission Gap Pattern Sequence within the *Transmission Gap Pattern Sequence Information* IE is set to "SF/2" and the UE Context is configured to use DPCH in the downlink in the new configuration, the DRNC shall include the *Transmission Gap Pattern Sequence Scrambling Code Information* IE in the RADIO LINK RECONFIGURATION READY message indicating for each Channelisation Code whether the alternative scrambling code shall be used or not.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes an *E-DPCH Information* IE, the DRNS shall apply the parameters to the new configuration as follows:]

- [FDD If the *E-DPCH Information* IE includes the *Maximum Set of E-DPDCHs* IE, the DRNS shall apply the contents of the Maximum Set in the new configuration.]
- [FDD If the *E-DPCH Information* IE includes the *Puncture Limit* IE, the DRNS shall apply the value in the uplink of the new configuration]
- [FDD If the *E-DPCH Information* IE includes the *E-TFCS Information* IE, the DRNS shall use the *E-TFCS Information* IE for the E-DCH when reserving resources for the uplink of the new configuration. The DRNS shall apply the new TFCS in the uplink of the new configuration. If the *E-TFCS Information* IE contains the *E-DCH Minimum Set E-TFCI Validity Indicator* IE the DRNS shall ignore the value in *E-DCH Minimum Set E-TFCI* IE. If the *E-DCH Minimum Set E-TFCI validity indicator* IE is absent DRNS shall use the value for the related resource allocation operation.]
- [FDD If the *E-TFCS Information* IE in the *E-DPCH Information* IE contains the *E-DPDCH Power Interpolation* IE, the DRNS shall use the value to determine the applicable E-DPDCH power formula defined in TS 25.214 [10]. If the *E-DPDCH Power Interpolation* IE is not present, the DRNS shall use the E-DPDCH power extrapolation formula defined in TS 25.214 [10] if the *E-DCH FDD Information* IE is included in the RADIO LINK RECONFIGURATION PREPARE message.]
- [FDD If the *E-TFCS Information* IE in the *E-DPCH Information* IE contains the *E-TFCI Boost Information* IE, the DRNS shall use the information according to TS 25.214 [10]. If the *E-TFCI Boost Information* IE is not present, the DRNS shall use the value "127" in the algorithm defined in TS 25.214 [10] if the *E-DCH FDD Information* IE is included in the RADIO LINK RECONFIGURATION PREPARE message.]
- [FDD If the *E-DPCH Information* IE includes the *E-TTI* IE, the DRNS shall use the value when the new configuration is being used.]
- [FDD If the *E-DPCH Information* IE includes the *E-DPCCH Power Offset* IE, the DRNS shall use the value when the new configuration is being used.]
- [FDD If the *E-DPCH Information* IE includes the *E-RGCH 2-Index-Step* IE, the DRNS shall use the value when the new configuration is being used.]
- [FDD If the *E-DPCH Information* IE includes the *E-RGCH 3-Index-Step* IE, the DRNS shall use the value when the new configuration is being used.]
- [FDD If the *E-DPCH Information* IE includes the *E-DCH HARQ Info* IE, the DRNS shall use the value when the new configuration is being used.]
- [FDD If the *E-DPCH Information* IE includes the *HS-DSCH Configured Indicator* IE, the DRNS shall use the value when the new configuration is being used.]
- [FDD If the *E-DPCH Information* IE includes the *Minimum Reduced E-DPDCH Gain Factor* IE , then the DRNS shall use the value to determine the applicable minimum gain factor ($\beta_{ed,k,reduced,min}$) defined in TS 25.214 [10]. For the case the *Minimum Reduced E-DPDCH Gain Factor* IE is not available for the UE Context, the DRNS may use the default value defined in TS 25.331 [16].]

[FDD – If the RADIO LINK RECONFIGURATION PREPAR message includes the *Continuous Packet Connectivity DTX-DRX Information* IE, then:]

- [FDD The DRNS shall configure the concerned UE Context for Continuous Packet Connectivity DTX operation according to TS 25.214 [10].]
- [FDD If *DRX Information* IE is included in the *Continuous Packet Connectivity DTX-DRX Information* IE, then the DRNS shall configure the concerned UE Context for Continuous Packet Connectivity DRX operation according to TS 25.214 [10].]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Continuous Packet Connectivity DTX-DRX Information To Modify* IE, then:]

- [FDD If the *UE DTX DRX Offset* IE is included in the *Continuous Packet Connectivity DTX-DRX Information To Modify* IE, then the DRNS shall apply the indicated Offset in *UE DTX DRX Cycle* IE in the new configuration.]
- [FDD If the *Enabling Delay* IE is included in the *Continuous Packet Connectivity DTX-DRX Information To Modify* IE, then the DRNS shall use this value to determine the beginning of uplink transmission in the new configuration according to TS 25.214 [10].]
- [FDD If the *DTX Information To Modify* IE is included in the *Continuous Packet Connectivity DTX-DRX Information To Modify* IE, then the DRNS shall use this information to modify the indicated DTX Information parameter in the new configuration. If the choice of *DTX Information To Modify* IE is "Deactivate", then DRX should be deactived together with DTX.]
- [FDD If the *DRX Information To Modify* IE is included in the *Continuous Packet Connectivity DTX-DRX Information To Modify* IE, then the DRNS shall use this information to modify the indicated DRX Information in the new configuration.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Continuous Packet Connectivity HS-SCCH less Information* IE, then:]

- [FDD The DRNS shall configure the Serving HS-DSCH Radio Link indicated by the *HS-PDSCH RL ID* IE for Continuous Packet Connectivity HS-SCCH less operation according to TS 25.214 [10].]
- [FDD The DRNS shall allocate the HS-PDSCH codes needed for HS-SCCH less operation and include the
 Continuous Packet Connectivity HS-SCCH less Information Response IE in the RADIO LINK
 RECONFIGURATION READY message.]
- [FDD If at least one of *HS-PDSCH Second Code Support* IE is set to "True", then the DRNC shall include *HS-PDSCH Second Code Index* IE in the RADIO LINK RECONFIGURATION READY message.]

[FDD- If the RADIO LINK RECONFIGURATION PREPARE message includes the *Continuous Packet Connectivity HS-SCCH less Deactivate Indicator* IE, then the DRNS shall deactive the Continuous Packet Connectivity HS-SCCH less operation for the HS-DSCH Radio Link.]

[1.28 Mcps TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Continuous Packet Connectivity DRX Information LCR* IE, then the DRNS shall take account into these parameters to decide the DRX operation related parameters and configure the concerned UE Context for DRX operation according to TS 25.224 [22] and include the parameter(s) in the *Continuous Packet Connectivity DRX Information Response LCR* IE in the RADIO LINK RECONFIGURATION READY message.]

[1.28 Mcps TDD – If the *Inactivity Threshold for UE DRX Cycle Ext* IE is included in the *Continuous Packet Connectivity DRX Information LCR* IE, then the DRNS may use this value to determine the Inactivity Threshold for UE DRX Cycle according to TS 25.224 [22].]

[1.28 Mcps TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Continuous Packet Connectivity DRX Information To Modify LCR* IE, then:]

- [1.28 Mcps TDD If the *UE DTX DRX Offset* IE is included in the *Continuous Packet Connectivity DRX Information To Modify LCR* IE, then the DRNS shall apply the indicated Offset in *UE DTX DRX Cycle* IE in the new configuration.]
- [1.28 Mcps TDD If the *Enabling Delay* IE is included in the *Continuous Packet Connectivity DRX Information To Modify LCR* IE, then the DRNS shall use this value to determine the beginning of uplink transmission in the new configuration according to TS 25.224 [22].]
- [1.28 Mcps TDD If the *DRX Information To Modify* IE is included in the *Continuous Packet Connectivity DRX Information To Modify LCR* IE, then the DRNS shall use this information to modify the indicated DRX Information in the new configuration.]

[1.28 Mcps TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *HS-DSCH Semi-Persistent scheduling Information LCR* IE, then:]

- [1.28 Mcps TDD – The DRNS shall configure the Serving HS-DSCH Radio Link indicated by the *HS-PDSCH RL ID* IE for HS-DSCH Semi-Persistent scheduling operation according to TS 25.224 [22].]

- [1.28 Mcps TDD The DRNS shall allocate the HS-SICH information needed for HS-DSCH Semi-Persistent scheduling operation and include the *HS-DSCH Semi-Persistent scheduling Information Response LCR* IE in the RADIO LINK RECONFIGURATION READY message.]
- [1.28 Mcps TDD If the HS-DSCH Semi-Persistent Resource Reservation Indicator IE is included in the HS-DSCH Semi-Persistent scheduling Information LCR IE, then the DRNS shall include Allcoated HS-PDSCH Semi-persistent resource IE in the RADIO LINK RECONFIGURATION READY message.]

[1.28 Mcps TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH Semi-Persistent scheduling Information LCR* IE, then:]

- [1.28 Mcps TDD The DRNS shall configure the Serving E-DCH Radio Link indicated by the *E-DCH Serving RL* IE for E-DCH Semi-Persistent scheduling operation according to TS 25.224 [22].]
- [1.28 Mcps TDD If the *E-DCH Semi-Persistent Resource Reservation Indicator* IE is included in the *E-DCH Semi-Persistent scheduling Information LCR* IE, then the DRNS shall include *Allocated E-DCH Semi-persistent resource* IE in the RADIO LINK RECONFIGURATION READY message.]

[1.28 Mcps TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *HS-DSCH Semi- Persistent scheduling Information to modify LCR* IE, then:]

- [1.28 Mcps TDD If the Transport Block Size List IE or/and Repetition Period list IE is/are included in the HS-DSCH Semi-Persistent scheduling Information to modify LCR IE, the DRNS shall modify the configuration of Serving HS-DSCH Radio Link indicated by the HS-PDSCH RL ID IE for HS-DSCH Semi-Persistent scheduling operation according to TS 25.224 [22].
- [1.28 Mcps TDD The DRNS shall allocate the HS-SICH information needed for HS-DSCH Semi-Persistent scheduling operation and include the *HS-DSCH Semi-Persistent scheduling Information Response LCR* IE in the RADIO LINK RECONFIGURATION READY message.]
- [1.28 Mcps TDD If the HS-DSCH Semi-Persistent Resource Reservation Indicator IE is included in the HS-DSCH Semi-Persistent scheduling Information to modify LCR IE, then the DRNS shall include Allcoated HS-PDSCH Semi-persistent resource IE in the RADIO LINK RECONFIGURATION READY message.]
- [1.28 Mcps TDD If the *HS-DSCH Semi-Persistent scheduling operation Indicator* IE is included in the *HS-DSCH Semi-Persistent scheduling Information to modify LCR* IE, then the DRNS shall apply this information for HS-DSCH Semi-Persistent scheduling operation.]
- [1.28 Mcps TDD If the buffer size for HS-DSCH Semi-Persistent scheduling needs to be modified, then the DRNS shall include the *Buffer Size for HS-DSCH Semi-Persistent scheduling* IE in the RADIO LINK RECONFIGURATION READY message.]
- [1.28 Mcps TDD If the number of processes for HS-DSCH Semi-Persistent scheduling needs to be modified, then the DRNS shall include the *Number of Processes for HS-DSCH Semi-Persistent scheduling* IE in the RADIO LINK RECONFIGURATION READY message.]

[1.28 Mcps TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH Semi-Persistent scheduling Information to modify LCR* IE, then:]

- [1.28 Mcps TDD If the *Repetition Period list* IE is included in the *E-DCH Semi-Persistent scheduling Information to modify LCR* IE, the DRNS shall modify the configuration of Serving E-DCH Radio Link indicated by the *E-DCH Serving RL* IE for E-DCH Semi-Persistent scheduling operation according to TS 25.224 [22].
- [1.28 Mcps TDD If the *E-DCH Semi-Persistent scheduling Indicator* IE is included in the *E-DCH Semi-Persistent scheduling Information to modify LCR* IE, then the DRNS shall apply this information for E-DCH Semi-Persistent scheduling operation.]
- [1.28 Mcps TDD If the *E-DCH Semi-Persistent Resource Reservation Indicator* IE is included in the *E-DCH Semi-Persistent scheduling Information to modify LCR* IE, then the DRNS shall include *Allocated E-DCH Semi-persistent resource* IE in the RADIO LINK RECONFIGURATION READY message.]

[1.28 Mcps TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *HS-DSCH Semi-Persistent scheduling Deactivate Indicator LCR* IE, then the DRNS shall deactivate the HS-DSCH Semi-Persistent scheduling operation for the HS-DSCH Radio Link.]

[1.28 Mcps TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH Semi-Persistent scheduling Deactivate Indicator LCR* IE, then the DRNS shall deactivate the E-DCH Semi-Persistent scheduling operation for the E-DCH Radio Link.]

[1.28Mcps TDD - If the RADIO LINK RECONFIGURATION PREPARE message includes the *MU-MIMO Indicator* IE, then:]

- [1.28 Mcps TDD The DRNS may use the MU-MIMO for the radio link according to the *MU-MIMO Usage Indicator* IE and shall include the *MU-MIMO Information* IE in the RADIO LINK RECONFIGURATION READY message.]
- [1.28 Mcps TDD If the Standalone Midamble Channel Indicator IE is set to "Used", then the DRNS shall include Standalone Midamble Channel information in the RADIO LINK RECONFIGURATION READY message. Else, the DRNS shall not include Standalone Midamble Channel information in the RADIO LINK RECONFIGURATION READY message.]

[TDD – UL/DL CCTrCH Modification]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes any *UL CCTrCH To Modify* IEs or *DL CCTrCH To Modify* IEs, then the DRNS shall treat them each as follows:]

- [TDD If any of the *UL CCTrCH To Modify* IEs or *DL CCTrCH To Modify* IEs includes any of the *TFCS* IE, *TFCI coding* IE, *Puncture limit* IE, or *TPC CCTrCH ID* IEs the DRNS shall apply these as the new values, otherwise the previous values specified for this CCTrCH are still applicable.]
- [TDD If any of the following listed DPCH information IEs are modified in the new prepared configuration, the DRNC shall include in the RADIO LINK RECONFIGURATION READY message the IEs indicating the new values: Repetition Period IE, Repetition Length IE, TDD DPCH Offset IE, [3.84Mcps TDD UL Timeslot Information IE,] [1.28Mcps TDD UL Timeslot Information LCR IE,] [7.68 Mcps TDD UL Timeslot Information T.68 Mcps IE,] [3.84Mcps TDD DL Timeslot Information IE,] [1.28Mcps TDD DL Timeslot Information LCR IE,] [7.68 Mcps TDD Midamble Shift And Burst Type IE,] [1.28Mcps TDD Midamble Shift LCR IE,] [7.68 Mcps TDD Midamble Shift And Burst Type 7.68 Mcps IE,] TFCI Presence IE, [3.84Mcps TDD TDD Channelisation Code IE,] [1.28Mcps TDD and/or TDD Channelisation Code LCR IE,] [7.68 Mcps TDD TDD Channelisation Code 7.68 Mcps IE,] [1.28Mcps TDD TDD UL DPCH Time Slot Format LCR IE].]
- [1.28Mcps TDD If the *UL CCTrCH To Modify* IE includes the *UL SIR Target* IE, the DRNS shall use the value for the UL inner loop power control according to TS 25.221 [12] and TS 25.224 [22] in the new configuration.]
- [TDD If any of the *DL CCTrCH To Modify* IEs includes any *TPC CCTrCH ID* IEs, the DRNS shall apply these as the new values, otherwise the previous values specified for this CCTrCH are still applicable.]
- [1.28Mcps TDD If the *UL CCTrCH to Modify* IE includes the *TDD TPC Uplink Step Size* IE, the DRNS shall apply this value to the uplink TPC step size in the new configuration.]
- [TDD If the *DL CCTrCH to Modify* IE includes the *TDD TPC Downlink Step Size* IE, the DRNS shall apply this value to the downlink TPC step size in the new configuration.]
- [1.28 Mcps TDD if the DRNS modifies, deletes or grants a new PLCCH assignment(s) to the UL CCTrCH, then the resulting PLCCH assignment(s) shall be sent to the SRNC in the RADIO LINK RECONFIGURATION READY message.]

[TDD - UL/DL CCTrCH Addition]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes any *UL CCTrCH To Add* IEs or *DL CCTrCH To Add* IEs, the DRNS shall include this CCTrCH in the new configuration.]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes any *DCHs to Add* IEs, the DRNC shall include in the RADIO LINK RECONFIGURATION READY message the DPCH information in [3.84Mcps TDD – *UL DPCH to be Added* IE/*DL DPCH to be Added* IEs] [1.28Mcps TDD – *UL DPCH to be Added LCR* IE/*DL DPCH to be Added LCR* IEs] [7.68 Mcps TDD – *UL DPCH to be Added 7.68 Mcps* IE/*DL DPCH to be Added 7.68 Mcps* IEs]. [3.84Mcps TDD – If no UL DPCH is active before a reconfiguration which adds an UL DPCH, and if a valid Rx Timing Deviation measurement is known in DRNC, then the DRNC shall include the *Rx Timing Deviation* IE (or the *Rx*

Timing Deviation 3.84 Mcps Extended IE if the cell containing the radio link is configured for extended timing advance) in the RADIO LINK RECONFIGURATION READY message]. [7.68 Mcps TDD – If no UL DPCH is active before a reconfiguration which adds an UL DPCH, and if a valid Rx Timing Deviation measurement is known in DRNC, then the DRNC shall include the Rx Timing Deviation 7.68 Mcps IE in the RADIO LINK RECONFIGURATION READY message].]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *TDD TPC Downlink Step Size* IE within a *DL CCTrCH To Add* IE, the DRNS shall set the TPC step size of that CCTrCH to that value, otherwise the DRNS shall use the same value as the lowest numbered DL CCTrCH in the current configuration.]

[1.28Mcps TDD – The DRNS shall use the *UL SIR Target* IE in the *UL CCTrCH To Add* IE as the UL SIR value for the inner loop power control for this CCTrCH according to TS 25.221 [12] and TS 25.224 [22] in the new configuration.]

[TDD – If any of the *DL CCTrCH To Add* IEs includes any *TPC CCTrCH ID* IEs, the DRNS shall configure the identified UL CCTrCHs with TPC according to the parameters given in the message.]

[1.28Mcps TDD – If the *UL CCTrCH To Add* IE includes *TDD TPC Uplink Step Size* IE, the DRNS shall apply the uplink TPC step size in the new configuration.]

[1.28 Mcps TDD – if the DRNS grants a PLCCH assignment(s) to the UL CCTrCH, then the resulting PLCCH assignment(s) shall be sent to the SRNC in the RADIO LINK RECONFIGURATION READY message.]

[TDD – UL/DL CCTrCH Deletion]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes any *UL CCTrCH To Delete* IEs *or DL CCTrCH To Delete* IEs, the DRNS shall remove this CCTrCH in the new configuration, and the DRNC shall include in the RADIO LINK RECONFIGURATION READY message corresponding *UL DPCH to be Deleted* IEs and *DL DPCH to be Deleted* IEs.]

DL Power Control:

[FDD – If the *RL Information* IE includes the *DL Reference Power* IEs and power balancing is active, DRNS shall update the reference power of the power balancing in the indicated RL(s), if updating of power balancing parameters by the RADIO LINK RECONFIGURATION PREPARE message is supported, when the new configuration has been activated, according to subclause 8.3.15, using the *DL Reference Power* IE. If the CFN modulo the value of the *Adjustment Period* IE is not equal to 0, the power balancing continues with the old reference power until the end of the current adjustment period, and the updated reference power shall be used from the next adjustment period.]

[FDD – If updating of power balancing parameters by the RADIO LINK RECONFIGURATION PREPARE message is supported by the DRNS, the DRNC shall include the *DL Power Balancing Updated Indicator* IE in the *RL Information Response* IE for each affected RL in the RADIO LINK RECONFIGURATION READY message.]

[TDD – DSCH Addition/Modification/Deletion:]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes any *DSCH To Add*, *DSCH To Modify* or *DSCH To Delete* IEs, then the DRNS shall use this information to add/modify/delete the indicated DSCH channels to/from the radio link, in the same way as the DCH info is used to add/modify/release DCHs.]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes any *DSCH To Add* IE, then the DRNS shall use the *Allocation/Retention Priority* IE, *Scheduling Priority Indicator* IE and *TrCH Source Statistics Descriptor* IE to define a set of DSCH Priority classes each of which is associated with a set of supported MAC-c/sh SDU lengths.]

[TDD – The DRNC shall include in the RADIO LINK RECONFIGURATION READY message both the *Transport Layer Address* IE and the *Binding ID* IE for the transport bearer to be established for each added DSCH.]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes any *DSCH To Add* IE, then the DRNS may use the *Traffic Class* IE to determine the transport bearer characteristics to apply between DRNC and Node B for the related DSCHs.]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *TNL QoS* IE in the *DSCH TDD Information* IE and if ALCAP is not used, the DRNS may use the *TNL QoS* IE to determine the transport bearer characteristics to apply in the uplink for the related DSCH.]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes any *DSCH To Modify* IE, then the DRNS shall treat them each as follows:]

- [TDD The DRNC shall include in the RADIO LINK RECONFIGURATION READY message both the
 Transport Layer Address IE and the *Binding ID* IE for any new transport bearer to be established for each
 modified DSCH.]
- [TDD If the *DSCHs To Modify* IE includes the *CCTrCH ID* IE, then the DRNS shall map the DSCH onto the referenced DL CCTrCH.]
- [TDD If the *DSCHs To Modify* IE includes any of the *Allocation/Retention Priority* IE, *Scheduling Priority Indicator* IE or *TrCH Source Statistics Descriptor* IE, the DNRS shall use them to update the set of DSCH Priority classes each of which is associated with a set of supported MAC-c/sh SDU lengths.]
- [TDD If the *DSCHs To Modify* IE includes any of the *Transport Format Set* IE or *BLER* IE, the DRNS shall apply the parameters to the new configuration.]
- [TDD If the *DSCHs To Modify* IE includes the *Traffic Class* IE, the DRNS may use this information to determine the transport bearer characteristics to apply between DRNC and Node B for the related DSCHs.]
- [TDD If the *DSCHs To Modify* IE includes the *TNL QoS* IE and if ALCAP is not used, the DRNS may use the *TNL QoS* IE to determine the transport bearer characteristics to apply in the uplink for the related DSCH.]

[3.84 Mcps TDD – The DRNC shall include the *Secondary CCPCH Info TDD* IE in the RADIO LINK RECONFIGURATION READY message if a DSCH is added and at least one DCH exists in the new configuration. The DRNC shall also include the *Secondary CCPCH Info TDD* IE in the RADIO LINK RECONFIGURATION READY message if the SHCCH messages for this radio link will be transmitted over a different secondary CCPCH than selected by the UE from system information.]

[1.28 Mcps TDD – The DRNC shall include the *Secondary CCPCH Info TDD LCR* IE in the RADIO LINK RECONFIGURATION READY message if a DSCH is added and at least one DCH exists in the new configuration. The DRNC shall also include the *Secondary CCPCH Info TDD LCR* IE in the RADIO LINK RECONFIGURATION READY message if the SHCCH messages for this radio link will be transmitted over a different secondary CCPCH than selected by the UE from system information.]

[7.68 Mcps TDD – The DRNC shall include the *Secondary CCPCH Info 7.68 Mcps TDD* IE in the RADIO LINK RECONFIGURATION READY message if a DSCH is added and at least one DCH exists in the new configuration. The DRNC shall also include the *Secondary CCPCH Info 7.68 Mcps TDD* IE in the RADIO LINK RECONFIGURATION READY message if the SHCCH messages for this radio link will be transmitted over a different secondary CCPCH than selected by the UE from system information.]

[TDD – The DRNC shall include the *DSCH Initial Window Size* IE in the RADIO LINK RECONFIGURATION READY message for each DSCH, if the DRNS allows the SRNC to start transmission of MAC-c/sh SDUs before the DRNS has allocated capacity on user plane as described in TS 25.425 [32].]

[TDD USCH Addition/Modification/Deletion]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes any *USCH To Modify*, *USCH To Add* or *USCH To Delete* IEs, then the DRNS shall use this information to add/modify/delete the indicated USCH channels to/from the radio link, in the same way as the DCH info is used to add/modify/release DCHs.]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes any *USCH To Add* IE, then, the DRNS shall use the *Allocation/Retention Priority* IE, *Scheduling Priority Indicator* IE and *TrCH Source Statistics Descriptor* IE to define a set of USCH Priority classes each of which is associated with a set of supported MAC-c/sh SDU lengths.]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes any *USCH To Add* IE, then the DRNS may use the *Traffic Class* IE to determine the transport bearer characteristics to apply between DRNC and Node B for the related USCHs.]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes any *USCH To Add* IE, if the *TNL QoS* IE is included and if ALCAP is not used, the DRNS may use the *TNL QoS* IE to determine the transport bearer characteristics to apply for the related USCHs.]

[TDD – The DRNC shall include in the RADIO LINK RECONFIGURATION READY message both the *Transport Layer Address* IE and the *Binding ID* IE for the transport bearer to be established for each added USCH.]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes any *USCH To Modify* IE, then the DRNS shall treat them each as follows:]

- [TDD If the *USCH To Modify* IE includes any of the *Allocation/Retention Priority* IE, *Scheduling Priority Indicator* IE or *TrCH Source Statistics Descriptor* IE, the DNRS shall use them to update the set of USCH Priority classes.]
- [TDD If the *USCH To Modify* IE includes any of the *CCTrCH ID* IE, *Transport Format Set* IE, *BLER* IE or *RB Info* IE, the DRNS shall apply the parameters to the new configuration.]
- [TDD If the *USCHs To Modify* IE includes the *Traffic Class* IE, the DRNS may use this information to determine the transport bearer characteristics to apply between DRNC and Node B for the related USCHs.]
- [3.84Mcps TDD The DRNC shall include the Secondary CCPCH Info TDD IE in the RADIO LINK RECONFIGURATION READY message if a USCH is added and at least one DCH exists in the new configuration. The DRNC shall also include the Secondary CCPCH Info TDD IE in the RADIO LINK RECONFIGURATION READY message if the SHCCH messages for this radio link will be transmitted over a different secondary CCPCH than selected by the UE from system information.]
- [1.28Mcps TDD The DRNC shall include the *Secondary CCPCH Info TDD LCR* IE in the RADIO LINK RECONFIGURATION READY message if a USCH is added and at least one DCH exists in the new configuration. The DRNC shall also include the *Secondary CCPCH Info TDD LCR* IE in the RADIO LINK RECONFIGURATION READY message if the SHCCH messages for this radio link will be transmitted over a different secondary CCPCH than selected by the UE from system information.]
- [7.68Mcps TDD The DRNC shall include the *Secondary CCPCH Info 7.68Mcps TDD* IE in the RADIO LINK RECONFIGURATION READY message if a USCH is added and at least one DCH exists in the new configuration. The DRNC shall also include the *Secondary CCPCH Info 7.68Mcps TDD* IE in the RADIO LINK RECONFIGURATION READY message if the SHCCH messages for this radio link will be transmitted over a different secondary CCPCH than selected by the UE from system information.]
- [TDD if the *TNL QoS* IE is included and if ALCAP is not used, the DRNS may use the *TNL QoS* IE to determine the transport bearer characteristics to apply for the related USCHs.]
- [TDD The DRNC shall include in the RADIO LINK RECONFIGURATION READY message both the *Transport Layer Address* IE and the *Binding ID* IE for any new transport bearer to be established for each modified USCH.]

RL Information:

[FDD – If the *RL Information* IE includes the *DL DPCH Timing Adjustment* IE, the DRNS shall adjust the timing of the radio link accordingly in the new configuration. If the UE Context is configured to use F-DPCH in the downlink in the new configuration, the DRNC may include the *DL Code Information* IE in the RADIO LINK RECONFIGURATION READY message.]

HS-DSCH Setup:

If the HS-DSCH Information IE is present in the RADIO LINK RECONFIGURATION PREPARE message, then:

- The DRNS shall setup the requested HS-PDSCH resources on the Serving HS-DSCH Radio Link indicated by the *HS-PDSCH RL ID* IE.
- The DRNC shall include the *HARQ Memory Partitioning* IE in the [FDD *HS-DSCH FDD Information Response* IE] [TDD *HS-DSCH TDD Information Response* IE] in the RADIO LINK RECONFIGURATION READY message. [FDD The *HARQ Memory Partitioning* IE shall either contain the *HARQ Memory Partitioning Information Extension For MIMO* IE or the *Number of Processes* IE set to a value higher than "8", if the *MIMO Activation Indicator* IE is included in the *HS-DSCH Information* IE.] [1.28Mcps TDD– The *HARQ Memory Partitioning* IE shall either contain the *HARQ Memory Partitioning Information Extension For MIMO* IE or the *Number of Processes* IE set to a value higher than "8", if the *MIMO Activation Indicator* IE is included in the *HS-DSCH Information* IE.]

- The DRNC shall allocate an HS-DSCH-RNTI to the UE Context and include the *HS-DSCH-RNTI* IE in the RADIO LINK RECONFIGURATION READY message.
- The DRNS may use the *Traffic Class* IE for a specific HS-DSCH MAC-d flow to determine the transport bearer characteristics to apply between DRNC and Node B. If *TrCH Source Statistics Descriptor* IE is present with the value "RRC" in the *HS-DSCH MAC-d Flows Information* IE, then the DRNC should ignore the *Traffic Class* IE.
- If the *TNL QoS* IE is included for a MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink between the DRNS and the SRNC for the related MAC-d flow.
- If fields are to be included in the User Plane by the SRNC to handle TNL Congestion Control for HSDPA in the DRNS, then the DRNC shall include the *User Plane Congestion Fields Inclusion* IE in the *HS-DSCH Information Response* IE.
- If the RADIO LINK RECONFIGURATION PREPARE message includes the *MAC-hs Guaranteed Bit Rate* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, then the DRNS shall use this information to optimise MAC-hs scheduling decisions for the related HSDPA Priority Queue.
- If the RADIO LINK RECONFIGURATION PREPARE message includes the *Discard Timer* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, then the DRNS shall use this information to discard out-of-date MAC-hs SDUs from the related HSDPA Priority Queue.
- If the RADIO LINK RECONFIGURATION PREPARE message includes the *Maximum MAC-d PDU Size Extended* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, then the DRNS shall ignore the *SID* IE and *MAC-d PDU Size* IE in the *MAC-d PDU Size Index* IE and use *Maximum MAC-d PDU Size Extended* IE to optimise capacity allocation for the related HSDPA Priority Queue.
- The DRNC shall include the *HS-DSCH Initial Capacity Allocation* IE in the [FDD *HS-DSCH FDD Information Response* IE] [TDD *HS-DSCH TDD Information Response* IE] in the RADIO LINK RECONFIGURATION READY message for every HS-DSCH MAC-d flow being established, if the DRNS allows the SRNC to start transmission of MAC-d PDUs before the DRNS has allocated capacity on user plane as described in TS 25.425 [32] If RADIO LINK RECONFIGURATION PREPARE message includes *HS-DSCH MAC-d PDU Size Format* IE in the *HS-DSCH Information* IE set to "Flexible MAC-d PDU Size", then DRNC shall only set in the *HS-DSCH Initial Capacity Allocation* IE the values for the peer of *Scheduling Priority Indicator* IE and *Maximum MAC-d PDU Size Extended* IE to the values of the corresponding peer I in RADIO LINK RECONFIGURATION PREPARE in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE for a Priority Queue including *Scheduling Priority Indicator* IE and *Maximum MAC-d PDU Size Extended* IE.
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *HS-SCCH Power Offset* IE in the *HS-DSCH Information* IE, then the DRNS may use this value to determine the HS-SCCH power. The HS-SCCH Power Offset should be applied for any HS-SCCH transmission to this UE.]
- [FDD The DRNC shall include the *Measurement Power Offset* IE in the *HS-DSCH Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
- FDD The DRNS shall allocate HS-SCCH codes corresponding to the HS-DSCH and the DRNC shall include the *HS-SCCH Specific Information Response* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
- [TDD The DRNS shall allocate HS-SCCH parameters corresponding to the HS-DSCH and the DRNC shall include the [3.84Mcps TDD HS-SCCH Specific Information Response IE] [1.28Mcps TDD HS-SCCH Specific Information Response 1.68 Mcps TDD HS-SCCH Specific Information Response 7.68 Mcps IE] in the HS-DSCH TDD Information Response IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD The DRNC shall include the *HS-PDSCH And HS-SCCH Scrambling Code* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *HARQ Preamble Mode* IE in the *HS-DSCH Information* IE, then the DRNS shall use the indicated HARQ Preamble Mode as described

in TS 25.214 [10], if HS-DPCCH ACK/NACK preamble and postamble is supported. Then, in this case, if the mode 1 is applied, the DRNC shall include the *HARQ Preamble Mode Activation Indicator* IE in the *HS-DSCH Information Response* IE in the RADIO LINK RECONFIGURATION READY message. If the *HARQ Preamble Mode* IE is not included or if the mode 0 is applied, then the DRNC shall not include the *HARQ Preamble Mode Activation Indicator* IE in the *HS-DSCH Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]

- If the RADIO LINK RECONFIGURATION PREPARE message includes the *HS-DSCH MAC-d PDU Size* Format IE in the *HS-DSCH Information* IE, then the DRNS shall use the indicated format in user plane frame structure for HS-DSCH channels (TS 25.425 [32]) and MAC-hs (TS 25.321 [41]).
- [FDD If the MIMO Activation Indicator IE is included in the HS-DSCH FDD Information IE, then:]
 - [FDD The DRNS shall activate the MIMO mode for the HS-DSCH Radio Link.]
 - [FDD The DRNS shall decide the pilot configuration and the UE reporting configuration (N/M ratio) according to TS 25.214 [10] for MIMO and include the *MIMO Information Response* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
 - [FDD If the Power Offset For S-CPICH for MIMO Request Indicator IE is included, the DRNC shall, if supported and MIMO pilot configuration with Primary and Secondary CPICH is set up on the cell with a non-zero power offset where the Serving HS-DSCH Radio Link is established, include the Power Offset For S-CPICH for MIMO IE in the HS-DSCH FDD Information Response IE in the RADIO LINK RECONFIGURATION READY message. If zero power offset the DRNC may include the Power Offset For S-CPICH for MIMO IE.]
- [1.28 Mcps TDD If the MIMO Activation Indicator IE is included in the HS-DSCH TDD Information IE, then:]
 - [1.28 Mcps TDD The DRNS shall activate the MIMO mode for the HS-DSCH Radio Link.]
 - [1.28 Mcps TDD The DRNS shall decide the SF mode for HS-PDSCH dual stream and include the *MIMO SF Mode for HS-PDSCH dual stream* IE in the *HS-DSCH TDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Information IE, then the DRNS may if the value is set to "allowed" use 64 QAM for the HS-DSCH Radio Link, and the DRNS shall include the SixtyfourQAM DL Usage Indicator IE in the HS-DSCH FDD Information Response IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If the *Sixtyfour QAM Usage Allowed Indicator* IE is included in the *HS-DSCH FDD Information* IE with value set to "not allowed", then the DRNS shall not use 64 QAM for the HS-DSCH Radio Link.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *HS-DSCH MAC-d PDU Size Format* IE set to "Flexible MAC-d PDU Size" and if Sixtyfour QAM will not be used, the DRNS shall include the *HS-DSCH TB Size Table Indicator* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message if it decides to use the octet aligned table defined in TS 25.321 [41] for HS-DSCH Transport Block Size signalling.]
- [FDD If the *UE with enhanced HS-SCCH support indicator* IE is included in the *HS-DSCH FDD Information* IE, then the DRNS may use:]
 - [FDD a different HS-SCCH in consecutive TTIs for this UE]
 - [FDD HS-SCCH orders for the case of HS-SCCH-less operation to this UE]
- [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH FDD Information* IE the DRNS may use the supported HSDPA functions for this UE.]
- [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH FDD Information* IE with the bit *UE DTXDRX related HS-SCCH orders uniform behavior indicator* set to 0, then the DRNS shall, if supported, include the *Support of dynamic DTXDRX related HS-SCCH order* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]

- [FDD If secondary serving HS-DSCH is applied also in the new configuration, then any changes related to parameters that are common for both the serving and the secondary serving HS-DSCH should be applied also for the secondary serving HS-DSCH.]
- If the RADIO LINK RECONFIGURATION PREPARE message includes *DL RLC PDU Size Format* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, the *DL RLC PDU Size Format* IE may be used by the DRNS to determine the allocated capacity on user plane as described in TS 25.425 [32].
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *UE Aggregate Maximum Bit Rate Enforcement Indicator* IE in the *Priority Queue Information* IE in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, the DRNS shall, if supported, consider the data of the related HSDPA Priority Queue for UE Aggregate Maximum Bit Rate Enforcement.]
- [FDD If the *Single Stream MIMO Activation Indicator* IE is included in the *HS-DSCH FDD Information* IE, then the DRNS shall activate the Single Stream MIMO for the HS-DSCH Radio Link.]
- [1.28 Mcps TDD If the *UE TSO Capability LCR* IE is included in the *HS-DSCH TDD Information* IE, then the DRNC may include the *TSO HS-PDSCH Indication LCR* IE in the RADIO LINK RECONFIGURATION READY message if HS-PDSCH resources could be allocated on TSO for the UE]

[FDD – Secondary Serving HS-DSCH Setup:]

[FDD – If the *C-ID* IE is present in the *Additional HS Cell Information RL Reconf Prep* IE in the RADIO LINK RECONFIGURATION PREPARE message, and no secondary serving HS-DSCH Radio Link(s) has been configured in the DRNS or if the new configuration contains more than one secondary serving HS-DSCH Radio Link, then if the *Ordinal Number Of Frequency* IEs, in the *HS-DSCH FDD Secondary Serving Information* IE or in the *HS-DSCH FDD Secondary Serving Information To Modify* IE for each instance of the *Additional HS Cell Information RL Reconf Prep* IE, indicate that new secondary serving HS-DSCH Radio Link(s) shall be setup, then:]

- [FDD The DRNS shall setup the requested HS-PDSCH resources on the secondary serving HS-DSCH Radio Link indicated by the *HS-PDSCH RL ID* IE. Non cell specific secondary serving Radio Link and non cell specific secondary serving HS-DSCH parameters take the same values as for the serving HS-DSCH cell.]
- [FDD The DRNC shall allocate an HS-DSCH-RNTI to the UE Context and include the HS-DSCH-RNTI IE in the Additional HS Cell Information Response IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *HS-SCCH Power Offset* IE in the *HS-DSCH FDD Secondary Serving Information* IE, then the DRNS may use this value to determine the HS-SCCH power. The HS-SCCH Power Offset should be applied for any secondary serving HS-SCCH transmission to this UE.]
- [FDD The DRNC shall include the *Measurement Power Offset* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD The DRNS shall allocate HS-SCCH codes corresponding to the secondary serving HS-DSCH and the DRNC shall include the HS-SCCH Specific Secondary Serving Information Response IE in the HS-DSCH FDD Secondary Serving Information Response IE in the Additional HS Cell Information Response IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If the MIMO Activation Indicator IE is included in the HS-DSCH FDD Secondary Serving Information IE, then the DRNS shall activate the MIMO mode for the secondary serving HS-DSCH Radio Link and the DRNS shall decide the pilot configuration and the UE reporting configuration (N/M ratio) according to TS 25.214 [10] for MIMO and include the MIMO Information Response IE in the HS-DSCH FDD Secondary Serving Information Response IE in the Additional HS Cell Information Response IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If the *Power Offset For S-CPICH for MIMO Request Indicator* IE is included, the DRNC shall, if supported and MIMO pilot configuration with Primary and Secondary CPICH is set up on the cell with a non-zero power offset where the Secondary Serving HS-DSCH Radio Link is established, include the *Power Offset For S-CPICH for MIMO* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the RADIO

LINK RECONFIGURATION READY message. If zero power offset the DRNC may include the *Power Offset For S-CPICH for MIMO* IE.]

- [FDD If the *Single Stream MIMO Activation Indicator* IE is included in the *HS-DSCH FDD Secondary Serving Information* IE, then the DRNS shall activate the Single Stream MIMO mode for the secondary serving HS-DSCH Radio Link.]
- [FDD The DRNC shall include the *HS-PDSCH And HS-SCCH Scrambling Code* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Secondary Serving Information IE, then the DRNS may if the value is set to "allowed" use 64 QAM for the secondary serving HS-DSCH Radio Link, and the DRNS shall include the SixtyfourQAM DL Usage Indicator IE in the HS-DSCH FDD Secondary Serving Information Response IE in the Additional HS Cell Information Response IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Secondary Serving Information IE with value set to "not allowed", then the DRNS shall not use 64 QAM for the secondary serving HS-DSCH Radio Link.]
- [FDD If, in the new configuration, the UE context is configured not to use Sixtyfour QAM for the secondaery serving HS-DSCH, then the DRNC shall include the *HS-DSCH TB Size Table Indicator* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION READY message if it decides to use the octet aligned table defined in TS 25.321 [41] for secondary serving HS-DSCH Transport Block Size signalling.]
- [FDD If the *Diversity Mode* IE is included in the *HS-DSCH FDD Secondary Serving Information* IE, the DRNS shall apply cell specific transmit diversity configuration and if the *Diversity Mode* IE is not set to "None" the DRNS shall activate/deactivate the Transmit Diversity for the secondary serving HS-DSCH Radio Link in accordance with the *Transmit Diversity Indicator* IE in the *HS-DSCH FDD Secondary Serving Information* IE.]
- [FDD If the *Ordinal Number Of Frequency* IE is included in the *HS-DSCH FDD Secondary Serving Information* IE, and the new configuration contains more than one secondary serving HS-DSCH Radio Link, then the DRNS shall use this value in the physical layer.]

Intra-DRNS Serving HS-DSCH Radio Link Change:

If the RADIO LINK RECONFIGURATION PREPARE message includes the *HS-PDSCH RL ID* IE, this indicates the new Serving HS-DSCH Radio Link:

The DRNS shall release the HS-PDSCH resources on the old Serving HS-DSCH Radio Link and setup the HS-PDSCH resources on the new Serving HS-DSCH Radio Link.

The DRNC may include the *HARQ Memory Partitioning* IE in the [FDD – *HS-DSCH FDD Information Response* IE] [TDD – *HS-DSCH TDD Information Response* IE] in the RADIO LINK RECONFIGURATION READY message. [FDD – The *HARQ Memory Partitioning* IE may contain the *HARQ Memory Partitioning Information Extension For MIMO* IE.] [1.28Mcps TDD – The *HARQ Memory Partitioning* IE may contain the *HARQ Memory Partitioning Information Extension For MIMO* IE.]

- If fields are to be included in the User Plane by the SRNC to handle TNL Congestion Control for HSDPA in the DRNS, then the DRNC shall include the *User Plane Congestion Fields Inclusion* IE in the *HS-DSCH Information Response* IE.

The DRNC shall allocate a new HS-DSCH-RNTI to the UE Context and include the *HS-DSCH-RNTI* IE in the RADIO LINK RECONFIGURATION READY message.

If a reset of the MAC-hs is not required the DRNS shall include the *MAC-hs Reset Indicator* IE in the RADIO LINK RECONFIGURATION READY message.

[FDD – The DRNC shall include the *Measurement Power Offset* IE in the *HS-DSCH Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]

[FDD – The DRNS shall allocate HS-SCCH codes corresponding to the HS-DSCH and the DRNC shall include the *HS-SCCH Specific Information Response* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]

[TDD – The DRNS shall allocate HS-SCCH parameters corresponding to the HS-DSCH and the DRNC shall include the [3.84Mcps TDD – *HS-SCCH Specific Information Response* IE] [1.28Mcps TDD – *HS-SCCH Specific Information Response TDD – HS-SCCH Specific Information Response 7.68 Mcps* IE] in the *HS-DSCH TDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]

[TDD – The DRNC shall include the [3.84 Mcps TDD – *HS-PDSCH Timeslot Specific Information* IE] [1.28 Mcps TDD – *HS-PDSCH Timeslot Specific Information LCR* IE] [7.68 Mcps TDD – *HS-PDSCH Timeslot Specific Information 7.68 Mcps* IE] in the *HS-DSCH Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]

[FDD – The DRNC shall include the *HS-PDSCH And HS-SCCH Scrambling Code* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]

- The DRNC may include the *Transport Layer Address* IE and the *Binding ID* IE for HS-DSCH MAC-d flow in the [FDD *HS-DSCH FDD Information Response* IE] [TDD *HS-DSCH TDD Information Response* IE] in the RADIO LINK RECONFIGURATION READY message.
- If the *TNL QoS* IE is included for a MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink between the DRNS and the SRNC for the related MAC-d flow.
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH Information To Modify IE and the value is set to "allowed" or if HS-DSCH Information To Modify IE is not included and the UE Context is configured with Sixtyfour QAM allowed for the serving HS-DSCH Radio Link and not used in the current configuration and then if the DRNS decides to use 64 QAM in the new configuration, then it shall include the SixtyfourQAM DL Usage Indicator IE in the HS-DSCH FDD Information Response IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If MAC-ehs is applied in the new configuration, and if Sixtyfour QAM will not be used, the DRNS shall include the *HS-DSCH TB Size Table Indicator* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message if it decides to use the octet aligned table defined in TS 25.321 [41] for HS-DSCH Transport Block Size signalling.]
- [FDD If the power offset for S-CPICH for MIMO Request indicator and MIMO activation indicator have been configured in the new configuration and MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where the Serving HS-DSCH Radio Link is established, the DRNC shall include the *Power Offset For S-CPICH for MIMO* IE in the HS-DSCH FDD Information Response IE in the RADIO LINK RECONFIGURATION READY message. If zero power offset the DRNC may include the *Power Offset For S-CPICH for MIMO* IE.]

[FDD – Intra-DRNS Secondary Serving HS-DSCH Radio Link Change:]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *C-ID* IE in the *Additional HS Cell Information RL Reconf Prep* IE, one or more secondary serving HS-DSCH Radio Link(s) has been configured in the DRNS and if the new configuration contains more than one secondary serving HS-DSCH Radio Link, then if the *Ordinal Number Of Frequency* IEs, in the *HS-DSCH FDD Secondary Serving Information* IE for each instance of the *Additional HS Cell Information RL Reconf Prep* IE, indicate that existing secondary serving HS-DSCH Radio Links shall be subject to intra-DRNS secondary serving HS-DSCH Radio Link change, then the *HS-PDSCH RL ID* IE indicates the new Serving HS-DSCH Radio Link:]

- [FDD The DRNS shall release the HS-PDSCH resources on the old secondary serving HS-DSCH Radio Link and setup the HS-PDSCH resources on the new secondary serving HS-DSCH Radio Link. The DRNS shall remove the old secondary serving HS-PDSCH Radio Link if no E-DCH resources are allocated to the RL. Non cell specific secondary serving Radio Link and non cell specific secondary serving HS-DSCH parameters take the same values as for the serving HS-DSCH cell.]
- [FDD The DRNC shall allocate an HS-DSCH-RNTI to the UE Context and include the *HS-DSCH-RNTI* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]

- [FDD The DRNC shall include the *Measurement Power Offset* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If the *Ordinal Number Of Frequency* IE is included in the *HS-DSCH FDD Secondary Serving Information* IE, and the new configuration contains more than one secondary serving HS-DSCH Radio Link, then the DRNS shall use this value in the physical layer.]
- [FDD The DRNS shall allocate HS-SCCH codes corresponding to the secondary serving HS-DSCH and the DRNC shall include the HS-SCCH Specific Secondary Serving Information Response IE in the HS-DSCH FDD Secondary Serving Information Response IE in the Additional HS Cell Information Response IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD The DRNC shall include the *HS-PDSCH And HS-SCCH Scrambling Code* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Secondary Serving Information To Modify IE and the value is set to "allowed" or if HS-DSCH FDD Secondary Serving Information To Modify IE is not included and the UE Context is configured with Sixtyfour QAM allowed for the secondary serving HS-DSCH Radio Link and not used in the current configuration and then if the DRNS decides to use 64 QAM for the new secondary serving HS-DSCH Radio Link, then it shall include the SixtyfourQAM DL Usage Indicator IE in the Additional HS Cell Information Response IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If, in the new configuration, the UE context is configured not to use Sixtyfour QAM for the secondary serving HS-DSCH, the DRNS shall include the *HS-DSCH TB Size Table Indicator* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION READY message if it decides to use the octet aligned table defined in TS 25.321 [41] for secondary serving HS-DSCH Transport Block Size signalling.]
- [FDD If the old and/or new configuration contains more than one Secondary Serving HS-DSCH Radio Link the HS-DSCH FDD Secondary Serving Information IE defines the new secondary serving HS-DSCH configuration in the DRNS to be used on the new secondary serving HS-DSCH Radio Link, and then:]
 - [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the HS-SCCH Power
 Offset IE in the HS-DSCH FDD Secondary Serving Information IE, then the DRNS may use this value to
 determine the HS-SCCH power. The HS-SCCH Power Offset should be applied for any secondary serving
 HS-SCCH transmission to this UE.]
 - [FDD If the MIMO Activation Indicator IE is included in the HS-DSCH FDD Secondary Serving Information IE, then the DRNS shall activate the MIMO mode for the secondary serving HS-DSCH Radio Link and the DRNS shall decide the pilot configuration and the UE reporting configuration (N/M ratio) according to TS 25.214 [10] for MIMO and include the MIMO Information Response IE in the HS-DSCH FDD Secondary Serving Information Response IE in the HS-DSCH Secondary Serving Cell Change Information Response IE in the Additional HS Cell Change Information Response IE in the RADIO LINK RECONFIGURATION READY message.]
 - [FDD If the Single Stream MIMO Activation Indicator IE is included in the HS-DSCH FDD Secondary Serving Information IE, then the DRNS shall activate the Single Stream MIMO mode for the secondary serving HS-DSCH Radio Link.]
 - [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Secondary Serving Information IE, then the DRNS may if the value is set to "allowed" use 64 QAM for the secondary serving HS-DSCH Radio Link, and the DRNS shall include the SixtyfourQAM DL Usage Indicator IE in the HS-DSCH FDD Secondary Serving Information Response IE in the Additional HS Cell Information Response IE in the RADIO LINK RECONFIGURATION READY message.]
 - [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Secondary Serving Information IE with value set to "not allowed", then the DRNS shall not use 64 QAM for the secondary serving HS-DSCH Radio Link.]
 - [FDD If the *Diversity Mode* IE is included in the *HS-DSCH FDD Secondary Serving Information* IE, the DRNS shall apply cell specific transmit diversity configuration and if the *Diversity Mode* IE is not set to

"None" the DRNS shall activate/deactivate the Transmit Diversity for the secondary serving HS-DSCH Radio Link in accordance with the *Transmit Diversity Indicator* IE in the *HS-DSCH FDD Secondary Serving Information* IE.]

- [FDD - If the power offset for S-CPICH for MIMO Request indicator and MIMO activation indicator have been configured for the secondary serving HS-DSCH radio link in the new configuration and MIMO pilot configuration with Primary and Secondary CPICH is set up with a non zero power offset on the cell where the Secondary Serving HS-DSCH Radio Link is established, the DRNC shall include the *Power Offset For S-CPICH for MIMO* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION READY message. If zero power offset the DRNC may include the *Power Offset For S-CPICH for MIMO* IE.]

[FDD – Additional Serving E-DCH Radio Link Change to an existing additional non serving E-DCH RL:]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *C-ID* IE in the *Additional HS Cell Information RL Reconf Prep* IE and an additional non serving E-DCH RL exists in the cell indicated by the *C-ID* IE, the *HS-PDSCH RL ID* IE in the *Additional HS Cell Information RL Reconf Prep* IE indicates the new Additional Serving E-DCH Radio Link.]

- [FDD If the old Additional Serving E-DCH RL is within this DRNS, the DRNS shall de-allocate the E-AGCH resources of the old Serving Additional E-DCH Radio Link at the activation of the new configuration.]
- [FDD The DRNS shall allocate a primary E-RNTI identifier or a secondary E-RNTI identifier or both for the new Additional Serving E-DCH Radio Link and include these E-RNTI identifiers along with the channelisation code of the corresponding E-AGCH in the *E-DCH FDD DL Control Channel Information* IE in the *Additional Modified E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response* RLReconf IE in the RADIO LINK RECONFIGURATION READY message]
- [FDD The DRNS may include the Serving Grant Value IE and Primary/Secondary Grant Selector IE in the E-DCH FDD DL Control Channel Information IE in the Additional Modified E-DCH FDD Information Response IE in the Additional E-DCH Cell Information Response RLReconf IE in the RADIO LINK RECONFIGURATION READY message for the initial grant for the Additional serving E-DCH RL and may include the Default Serving Grant in DTX Cycle 2 IE.]
- [FDD If the E-DCH HARQ process allocation for 2ms TTI for scheduled transmission shall be changed, the DRNS shall allocate resources according to the new/changed configuration and include the new/changed configuration in the *HARQ Process Allocation For 2ms Scheduled Transmission Grant* IE in the *Additional Modified E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response* RLReconf IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD The DRNS may include the *E-RGCH/E-HICH Channelisation Code* IE and/or the *E-HICH Signature Sequence* IE and/or the *E-RGCH Signature Sequence* IE or may alternatively include the *E-RGCH Release Indicator* IE in the *E-DCH FDD DL Control Channel Information* IE in the *Additional Modified E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION READY message for every E-DCH Radio Link on secondary UL frequency in the DRNS. If the DRNS has no valid data for the *E-RGCH/E-HICH Channelisation Code* IE in the *E-DCH FDD DL Control Channel Information* IE then it shall insert the *E-RGCH and E-HICH Channelisation Code Validity Indicator* IE in the *E-DCH FDD DL Control Channel Information* IE, to indicate that the *E-RGCH/E-HICH Channelisation Code* IE contains invalid data.]

[FDD – Additional Serving E-DCH Radio Link Change to a new RL:]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Additional E-DCH RL Specific Information To Add* IE in the *Additional E-DCH Configuration Change Information* IE in the *Additional E-DCH Cell Information RL Reconf Prep* IE and the *C-ID* IE in the *Additional HS Cell Information RL Reconf Prep* IE and there is no radio links in the cell indicated by the *C-ID* IE for the UE context, the *HS-PDSCH RL ID* IE indicates the new Additional Serving E-DCH Radio Link on secondary UL frequency.]

- [FDD – If the old Additional Serving E-DCH RL is within this DRNS, the DRNS shall de-allocate the E-AGCH resources of the old Additional Serving E-DCH Radio Link at the activation of the new configuration.]

- [FDD In the new configuration the DRNS shall allocate the E-DCH resources for the new additional serving E-DCH Radio Link on the secondary UL frequency. Non cell specific E-DCH parameters shall take the same values as for the corresponding cell of the Primary uplink frequency.]
- [FDD The DRNS shall allocate a primary E-RNTI identifier or a secondary E-RNTI identifier or both for the new Additional Serving E-DCH Radio Link and include these E-RNTI identifiers along with the channelisation code of the corresponding E-AGCH in the *E-DCH FDD DL Control Channel Information* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD The DRNS may include in the *E-DCH FDD DL Control Channel Information* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION READY message the *Serving Grant Value* IE and *Primary/Secondary Grant Selector* IE for the initial grant for the additional serving E-DCH RL and may include the *Default Serving Grant in DTX Cycle 2* IE]
- [FDD If the E-DCH HARQ process allocation for 2ms TTI for scheduled transmission shall be changed, the DRNS shall allocate resources according to the new/changed configuration and include the new/changed configuration in the *HARQ Process Allocation For 2ms Scheduled Transmission Grant* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION READY message.]

HS-DSCH Modification:

If the RADIO LINK RECONFIGURATION PREPARE message includes the *HS-DSCH Information To Modify* IE, then:

- The DRNC shall include the *HS-DSCH Initial Capacity Allocation* IE for each HS-DSCH MAC-d flow being modified for which the establishment of one or several new Priority Queues was requested, if the DRNS allows the SRNC to start the transmission of MAC-d PDUs for the Priority Queue(s) being established before the DRNS has allocated capacity on user plane as described in TS 25.425 [32]. If RADIO LINK RECONFIGURATION PREPARE message includes *HS-DSCH MAC-d PDU Size Format* IE in the *HS-DSCH Information To Modify* IE set to "Flexible MAC-d PDU Size", then DRNC shall only set in the *HS-DSCH Initial Capacity Allocation* IE the values for the peer of *Scheduling Priority Indicator* IE and *Maximum MAC-d PDU Size Extended* IE to the values of the corresponding peer I in RADIO LINK RECONFIGURATION PREPARE in the *HS-DSCH Information To Modify* IE for a Priority Queue including *Scheduling Priority Indicator* IE and *Maximum MAC-d PDU Size Extended* IE.
- If the RADIO LINK RECONFIGURATION PREPARE message includes the *Traffic Class* IE in the *HS-DSCH Information To Modify* IE for a specific HS-DSCH MAC-d flow, the DRNS may use this information to determine the transport bearer characteristics to apply between DRNC and Node B. The DRNC should ignore the *Traffic Class* IE if the *TrCH Source Statistics Descriptor* IE for this specific HS-DSCH MAC-d flow indicates the value "RRC".
- If the *TNL QoS* IE is included for a MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink between the DRNS and the SRNC for the related MAC-d flow.
- If the RADIO LINK RECONFIGURATION PREPARE message includes the *MAC-hs Guaranteed Bit Rate* IE in the *HS-DSCH Information To Modify* IE, the DRNS shall use this information to optimise MAC-hs scheduling decisions for the related HSDPA Priority Queue.
- If the RADIO LINK RECONFIGURATION PREPARE message includes the *Discard Timer* IE for a Priority Queue in the *HS-DSCH Information To Modify* IE, then the DRNS shall use this information to discard out-of-date MAC-hs SDUs from the related HSDPA Priority Queue.
- If the RADIO LINK RECONFIGURATION PREPARE message includes the *Maximum MAC-d PDU Size Extended* IE in the *HS-DSCH Information To Modify* IE, then the DRNS shall ignore the *SID* IE and *MAC-d PDU Size* IE in the *MAC-d PDU Size Index* IE and use *Maximum MAC-d PDU Size Extended* IE to optimise capacity allocation for the related HSDPA Priority Queue.
- If the RADIO LINK RECONFIGURATION PREPARE message includes the *MAC-hs Window Size* IE or *T1* IE in the *HS-DSCH Information To Modify* IE, then the DRNS shall use the indicated values in the new configuration for the related HSDPA Priority Queue.

- If the RADIO LINK RECONFIGURATION PREPARE message includes the *MAC-d PDU Size Index* IE in the *Modify Priority Queue* choice, the DRNS shall delete the previous list of MAC-d PDU Size Index values for the related HSDPA Priority Queue and use the MAC-d PDU Size Index values indicated in the *MAC-d PDU Size Index* IE in the new configuration.
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *CQI Feedback Cycle k* IE, the *CQI Repetition Factor* IE, the *ACK-NACK Repetition Factor* IE, the *ACK Power Offset* IE, the *NACK Power Offset* IE or the *CQI Power Offset* IE in the *HS-DSCH Information To Modify* IE, then the DRNS shall use the indicated CQI Feedback Cycle k value, the CQI Repetition Factor or the ACK-NACK Repetition Factor, ACK Power Offset, the NACK Power Offset or the CQI Power Offset in the new configuration.]
- [FDD If the *HS-SCCH Power Offset* IE is included in the *HS-DSCH Information To Modify* IE, the DRNS may use this value to determine the HS-SCCH power. The HS-SCCH Power Offset should be applied for any HS-SCCH transmission to this UE.]
- [TDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *TDD ACK NACK Power Offset* IE in the *HS-DSCH Information To Modify* IE, the DRNS shall use the indicated power offset in the new configuration.]
- [FDD If the *HS-DSCH Information To Modify* IE includes the *HS-SCCH Code Change Grant* IE, then the DRNS may modify the HS-SCCH codes corresponding to the HS-DSCH. The DRNC shall then report the codes which are used in the new configuration specified in the *HS-SCCH Specific Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If the HS-DSCH Information To Modify IE includes the HS-PDSCH Code Change Grant IE, then the DRNS may modify the HS-PDSCH codes corresponding to the HS-DSCH. The DRNC shall then report the codes which are used in the new configuration specified in the Continuous Packet Connectivity HS-SCCH less Information Response IE in the RADIO LINK RECONFIGURATION READY message. If the concerned DRNS is not in Continuous Packet Connectivity HS-SCCH less mode, the SRNC shall not include the HS-PDSCH Code Change Grant IE in the HS-DSCH Information To Modify IE.]
- [TDD If the *HS-DSCH Information To Modify* IE includes the *HS-SCCH Code Change Grant* IE, then the DRNS may modify the HS-SCCH parameters corresponding to the HS-DSCH. The DRNC shall then report the values for the parameters which are used in the new configuration specified in the [3.84Mcps TDD *HS-SCCH Specific Information Response LCR* IE] [7.68 Mcps TDD *HS-SCCH Specific Information Response 7.68 Mcps* IE] in the RADIO LINK RECONFIGURATION READY message.]
- FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *HARQ Preamble Mode* IE in the *HS-DSCH Information To Modify* IE, then the DRNS shall use the indicated HARQ Preamble Mode in the new configuration as described in TS 25.214 [10], if HS-DPCCH ACK/NACK preamble and postamble is supported. Then, in this case, if the mode 1 is applied, the DRNC shall include the *HARQ Preamble Mode Activation Indicator* IE in the *HS-DSCH Information Response* IE in the RADIO LINK RECONFIGURATION READY message. If the *HARQ Preamble Mode* IE is not included or if the mode 0 is applied, then the DRNC shall not include the *HARQ Preamble Mode Activation Indicator* IE in the *HS-DSCH Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
- If the RADIO LINK RECONFIGURATION PREPARE message includes the *HS-DSCH MAC-d PDU Size Format* IE in the *HS-DSCH Information To Modify* IE, then the DRNS shall use, in the new configuration, the indicated format in user plane frame structure for HS-DSCH channels (TS 25.425 [32]) and MAC-hs (TS 25.321 [41]).
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *HS-DSCH Physical Layer Category* IE in the *HS-DSCH Information To Modify* IE, the DRNS shall use this information in the new configuration.]
- [FDD If the MIMO Mode Indicator IE is included in the HS-DSCH Information To Modify IE, then:]
 - [FDD The DRNS shall activate/deactivate the MIMO mode for the HS-DSCH Radio Link in the new configuration in accordance with the *MIMO Mode Indicator* IE.]
 - [FDD If the *MIMO Mode Indicator* IE is set to "Activate", then the DRNS shall decide the pilot configuration and the UE reporting configuration (N/M ratio) according to TS 25.214 [10] for MIMO and

- include the *MIMO Information Response* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If the MIMO Mode Indicator IE is set to "Activate" and Power Offset For S-CPICH for MIMO Request Indicator IE is included, the DRNC shall, if supported and MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where the Serving HS-DSCH Radio Link is established, include the Power Offset For S-CPICH for MIMO IE in the HS-DSCH FDD Information Response IE. If zero power offset the DRNC may include the Power Offset For S-CPICH for MIMO IE.]
- [FDD The DRNC may include the *HARQ Memory Partitioning* IE in the RADIO LINK RECONFIGURATION READY message. The *HARQ Memory Partitioning* IE may contain the *HARQ Memory Partitioning Information Extension For MIMO* IE.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH Information To Modify IE, then the DRNS may if the value is set to "allowed" use 64 QAM for the HS-DSCH Radio Link, and the DRNS shall include the SixtyfourQAM DL Usage Indicator IE in the HS-DSCH FDD Information Response IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If the *Sixtyfour QAM Usage Allowed Indicator* IE is included in the *HS-DSCH Information To Modify* IE with value set to "not allowed", then the DRNS shall not use 64 QAM for the HS-DSCH Radio Link.]
- [FDD If MAC-ehs is applied in the new configuration, and if Sixtyfour QAM will not be used, the DRNS shall include the *HS-DSCH TB Size Table Indicator* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message if it decides to use the octet aligned table defined in TS 25.321 [41] for HS-DSCH Transport Block Size signalling.]
- [1.28Mcps TDD If the *MIMO Mode Indicator* IE is included in the *HS-DSCH Information To Modify* IE, then:]
 - [1.28Mcps TDD The DRNS shall activate/deactivate the MIMO mode for the HS-DSCH Radio Link in the new configuration in accordance with the *MIMO Mode Indicator* IE.]
 - [1.28 Mcps TDD If the MIMO Mode Indicator IE is set to "Activate", then the DRNS shall decide the SF mode for HS-PDSCH dual stream and include the MIMO SF Mode for HS-PDSCH dual stream IE in the HS-DSCH TDD Information Response IE in the RADIO LINK RECONFIGURATION READY message.]
- [1.28Mcps TDD The DRNC may include the *HARQ Memory Partitioning* IE in the RADIO LINK RECONFIGURATION READY message. The *HARQ Memory Partitioning* IE may contain the *HARQ Memory Partitioning Information Extension For MIMO* IE.]
- [FDD Any secondary serving HS-DSCH that was applied in the old configuration shall remain in the new configuration unless it is explicitly removed.]
- [FDD If secondary serving HS-DSCH is applied also in the new configuration, then any changes related to parameters that are common for both the serving and the secondary serving HS-DSCH should be applied also for the secondary serving HS-DSCH.]
- If the RADIO LINK RECONFIGURATION PREPARE message includes *DL RLC PDU Size Format* IE for a Priority Queue in the *HS-DSCH Information To Modify* IE, the *DL RLC PDU Size Format* IE may be used by the DRNS to determine the allocated capacity on user plane as described in TS 25.425 [32].
- [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH Information To Modify* IE the DRNS may use the supported HSDPA functions for this UE.]
- [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH Information To Modify* IE with the bit *UE DTXDRX related HS-SCCH orders uniform behavior indicator* set to 0, then the DRNS shall, if supported, include the *Support of dynamic DTXDRX related HS-SCCH order* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If the *Single Stream MIMO Mode Indicator* IE is included in the *HS-DSCH Information To Modify* IE, then the DRNS shall activate/deactivate the Single Stream MIMO for the HS-DSCH Radio Link in accordance with the *Single Stream MIMO Mode Indicator* IE.]

[FDD – Secondary Serving HS-DSCH Modification:]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *HS-DSCH FDD Secondary Serving Information To Modify* IE, then:]

- [FDD If the *HS-SCCH Power Offset* IE is included in the *HS-DSCH FDD Secondary Serving Information To Modify* IE, the DRNS may use this value to determine the HS-SCCH power. The HS-SCCH Power Offset should be applied for any secondary serving HS-SCCH transmission to this UE.]
- [FDD If the *HS-DSCH FDD Secondary Serving Information To Modify* IE includes the *HS-SCCH Code Change Grant* IE, then the DRNS may modify the HS-SCCH codes corresponding to the secondary serving HS-DSCH. The DRNC shall then report the codes which are used in the new configuration specified in the *HS-SCCH Specific Secondary Serving Information Response* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If the MIMO Mode Indicator IE is included in the HS-DSCH FDD Secondary Serving Information To Modify IE, then the DRNS shall activate/deactivate the MIMO mode for the secondary serving HS-DSCH Radio Link in accordance with the MIMO Mode Indicator IE.]
- [FDD If the *MIMO Mode Indicator* IE is set to "Activate", then the DRNS shall decide the pilot configuration and the UE reporting configuration (N/M ratio) according to TS 25.214 [10] for MIMO and include the *MIMO Information Response* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If the MIMO Mode Indicator IE is set to "Activate" and Power Offset For S-CPICH for MIMO Request Indicator IE is included, the DRNC shall, if supported and MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where the Secondary Serving HS-DSCH Radio Link is established, include the Power Offset For S-CPICH for MIMO IE in the HS-DSCH FDD Secondary Serving Information Response IE in the Additional HS Cell Information Response IE in the RADIO LINK RECONFIGURATION READY message. If zero power offset the DRNC may include the Power Offset For S-CPICH for MIMO IE.]
- [FDD If the *Single Stream MIMO Mode Indicator* IE is included in the *HS-DSCH FDD Secondary Serving Information To Modify* IE, then the DRNS shall activate/deactivate the Single Stream MIMO mode for the secondary serving HS-DSCH Radio Link in accordance with the *Single Stream MIMO Mode Indicator* IE.]
- [FDD If the *Ordinal Number Of Frequency* IE is included in the *HS-DSCH FDD Secondary Serving Information To Modify* IE, and the new configuration contains more than one secondary serving HS-DSCH Radio Link, then the DRNS shall use this value in the physical layer.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Secondary Serving Information To Modify IE, then the DRNS may if the value is set to "allowed" use 64 QAM for the secondary serving HS-DSCH Radio Link, and the DRNS shall include the SixtyfourQAM DL Usage Indicator IE in the HS-DSCH FDD Secondary Serving Information Response IE in the Additional HS Cell Information Response IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If the *Sixtyfour QAM Usage Allowed Indicator* IE is included in the *HS-DSCH FDD Secondary Serving Information To Modify* IE with value set to "not allowed", then the DRNS shall not use 64 QAM for the secondary serving HS-DSCH Radio Link.]
- [FDD If, in the new configuration, the UE context is configured not to use Sixtyfour QAM for the secondaery serving HS-DSCH, then the DRNC shall include the *HS-DSCH TB Size Table Indicator* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the Additional HS Cell Information Response IE in the RADIO LINK RECONFIGURATION READY message if it decides to use the octet aligned table defined in TS 25.321 [41] for secondary serving HS-DSCH Transport Block Size signalling.]
- [FDD If the *Diversity Mode* IE is included, then:]
 - [FDD- the DRNS shall apply cell specific transmit diversity configuration for the secondary serving HS-DSCH radio link according to *Diversity Mode* IE and *Transmit Diversity Indicator* IE in the *HS-DSCH FDD Secondary Serving Information To Modify* IE,]

- [FDD If the *Diversity Mode* IE is not set to "None", the DRNS shall apply diversity for the secondary serving HS-DSCH radio link according to the value given in the *Transmit Diversity Indicator* IE in the *HS-DSCH FDD Secondary Serving Information To Modify* IE.]
- [FDD If the *Non Cell Specific Tx Diversity* IE equals "Tx Diversity" is included, the DRNS shall apply non cell specific transmit diversity configuration and reconfigure the transmit diversity setting for the secondary serving HS-DSCH radio link to the same value as defined for the serving HS-DSCH radio link in the new configuration.]

[FDD – Secondary Serving HS-DSCH Removal:]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *HS-DSCH Secondary Serving Remove* IE in the *Additional HS Cell Information RL Reconf Prep* IE, then the indicated secondary serving HS-DSCH Radio Link shall be removed.]

HS-DSCH MAC-d Flow Addition/Deletion:

If the RADIO LINK RECONFIGURATION PREPARE message includes any *HS-DSCH MAC-d Flows To Add* or *HS-DSCH MAC-d Flows To Delete* IEs, then the DRNS shall use this information to add/delete the indicated HS-DSCH MAC-d flows on the Serving HS-DSCH Radio Link. When an HS-DSCH MAC-d flow is deleted, all its associated Priority Queues shall also be removed.

If the RADIO LINK RECONFIGURATION PREPARE message includes an *HS-DSCH MAC-d Flows To Delete* IE requesting the deletion of all remaining HS-DSCH MAC-d flows for the UE Context, then the DRNC shall delete the HS-DSCH configuration from the UE Context and release the HS-PDSCH resources.

If the RADIO LINK RECONFIGURATION PREPARE message includes the *HS-DSCH MAC-d Flows To Add* IE, then:

- The DRNS may use the Traffic Class IE for a specific HS-DSCH MAC-d flow to determine the transport bearer characteristics to apply between DRNC and Node B. If TrCH Source Statistics Descriptor IE is present with the value "RRC" in the HS-DSCH MAC-d Flows Information IE, then the DRNC should ignore the Traffic Class IE.
- If the TNL QoS IE is included for a MAC-d flow and if ALCAP is not used, the TNL QoS IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink between the DRNS and the SRNC for the related MAC-d flow.
- The DRNC shall include the HS-DSH Initial Capacity Allocation IE in the RADIO LINK RECONFIGURATION READY message for every HS-DSCH MAC-d flow being added, if the DRNS allows the SRNC to start transmission of MAC-d PDUs before the DRNS has allocated capacity on user plane as described in TS 25.425 [32]. If the UE context is configured to use the "Flexible MAC-d PDU Size" format for the HS-DSCH, then DRNC shall only set in the HS-DSCH Initial Capacity Allocation IE the values for the peer of Scheduling Priority Indicator IE and Maximum MAC-d PDU Size Extended IE to the values of the corresponding peer I in RADIO LINK RECONFIGURATION PREPARE message in the HS-DSCH MAC-d Flows To Add IE for a Priority Queue including Scheduling Priority Indicator IE and Maximum MAC-d PDU Size Extended IE.
- If the RADIO LINK RECONFIGURATION PREPARE message includes the MAC-hs Guaranteed Bit Rate IE in the HS-DSCH MAC-d Flows To Add IE, the DRNS shall use this information to optimise MAC-hs scheduling decisions for the related HSDPA Priority Queue.
- If the RADIO LINK RECONFIGURATION PREPARE message includes the Discard Timer IE for a Priority Queue in the HS-DSCH MAC-d Flows To Add IE, then the DRNS shall use this information to discard out-of-date MAC-hs SDUs from the related HSDPA Priority Queue.
- If the RADIO LINK RECONFIGURATION PREPARE message includes the Maximum MAC-d PDU Size Extended IE for a Priority Queue in the HS-DSCH MAC-d Flows To Add IE, then the DRNC shall ignore the SID IE and MAC-d PDU Size IE in the MAC-d PDU Size Index IE and use Maximum MAC-d PDU Size Extended IE to optimise capacity allocation for the related HSDPA Priority Queue.
- The DRNC may include the HARQ Memory Partitioning IE in the RADIO LINK RECONFIGURATION READY message. [FDD The HARQ Memory Partitioning IE may contain the HARQ Memory Partitioning Information Extension For MIMO IE.]

- If the RADIO LINK RECONFIGURATION PREPARE message includes DL RLC PDU Size Format IE for a Priority Queue in the HS-DSCH MAC-d Flows To Add IE, the DL RLC PDU Size Format IE may be used by the DRNS to determine the allocated capacity on user plane as described in TS 25.425 [32].
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *UE Aggregate Maximum Bit Rate Enforcement Indicator* IE for a Priority Queue in the *HS-DSCH MAC-d Flows To Add* IE, the DRNS shall, if supported, consider the data of the related HSDPA Priority Queue for UE Aggregate Maximum Bit Rate Enforcement.]

[FDD – HS-DSCH Preconfiguration for Enhanced HS Serving Cell Change]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *HS-DSCH Preconfiguration Setup* IE in the *RL Information* IE the DRNS shall, if supported, preconfigure the indicated cells for Enhanced HS Serving Cell Change according to TS 25.308 [63]:]

- [FDD The DRNS shall preconfigure sets of HS-SCCH codes on the cells preconfigured for HS-DSCH, primary serving HS-DSCH cell, as well as on the secondary serving HS-DSCH cells. The primary serving HS-DSCH cell is designated through the *C-ID* IE part of the *RL Information* IE in the RADIO LINK RECONFIGURATION PREPARE message. The list of secondary serving HS-DSCH cells is designated by the list of *Secondary C-ID* IEsin the *HS-DSCH Preconfiguration Setup* IE part of the *RL Information* IE in the RADIO LINK RECONFIGURATION PREPARE message.]
- [FDD The number of HS-SCCH codes to preconfigure for each cell may be optionally specified:]
 - [FDD by the *Num Primary HS-SCCH Codes* IE in the *HS-DSCH Preconfiguration Setup* IE, for the primary serving HS-DSCH cell.]
 - [FDD by the *Num Secondary HS-SCCH Codes* IE in *the Secondary Cells* IE in the *HS-DSCH Preconfiguration Setup* IE for each of the secondary serving HS-DSCH cells.]
- [FDD If *Num Primary HS-SCCH Codes* IE or *Num Secondary HS-SCCH Codes* IE is not included in the message the number and distribution of codes on primary and any secondary cells shall be preconfigured to satisfy any limitations in TS 25.214 [10].
- [FDD The DRNS shall return these codes in the *Sets of HS-SCCH Codes* IE along with the corresponding percell *HS-DSCH-RNTI* IE in the *HS-DSCH Preconfiguration Info* IE in the *RL Information Response* IE of the RADIO LINK RECONFIGURATION READY.]
- [FDD The DRNS shall use the first in the numbered list the primary serving HS-DSCH cell's of HS-SCCH codes in the *HS-SCCH Preconfigured Codes* IE sent to the SRNC to signal the Target Cell HS-SCCH Order defined in TS 25.331 [16].]
- [FDD The DRNS shall include, in the *HS-DSCH Preconfiguration Info* IE in the *RL Information Response* IE in the RADIO LINK RECONFIGURATION READY message, IEs according to the rules defined for HS-DSCH Setup at Serving HS-DSCH Radio Link Change and:]
 - [FDD if *HARQ Preamble Mode* IE is included in the *HS-DSCH Preconfiguration Setup* IE the HARQ Preamble Mode Activation Indicator IE.]
 - [FDD if *MIMO Activation Indicator* IE is included in the *HS-DSCH Preconfiguration Setup* IE the *MIMO N/M Ratio* IE.]
 - [FDD if *Ordinal number of frequency* IE is included in the *Secondary Cells* IE in the *HS-DSCH Preconfiguration Setup* IE.]
 - [FDD if *HS-DSCH MAC-d PDU Size Format* IE is included in the *HS-DSCH Preconfiguration Setup* IE and set to "Flexible MAC-d PDU Size" and if Sixtyfour QAM will not be used for the cell in the preconfiguration the *HS-DSCH TB Size Table Indicator* IE for each preconfigured cell.]
 - [FDD if Sixtyfour QAM Usage Allowed Indicator IE is included in the Secondary Cells IE in the HS-DSCH Preconfiguration Setup IE or in the HS-DSCH Preconfiguration Setup IE the SixtyfourQAM DL Usage Indicator IE for each preconfigured cell.]
 - [FDD if Continuous Packet Connectivity HS-SCCH less Information IE is included in the HS-DSCH Preconfiguration Setup IE the Continuous Packet Connectivity HS-SCCH less Information Response IE.]

- [FDD if the *UE with enhanced HS-SCCH support indicator* IE is included in the *HS-DSCH Preconfiguration Setup* IE, then the DRNS shall store this information in the preconfigured configuration.]
- [FDD the *SixtyfourQAM DL Support Indicator* IE may be included.]
- [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH Preconfiguration Setup* IE, then the DRNS may store this information in the preconfigured configuration.]
- [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH Preconfiguration Setup* IE with the bit *UE DTXDRX related HS-SCCH orders uniform behavior indicator* set to 0, then the DRNS shall, if supported, include the *Support of dynamic DTXDRX related HS-SCCH order* IE in the *HS-DSCH Preconfiguration Info* IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD the DRNS shall, if supported, include in the *Sets of HS-SCCH Codes* IE the *Measurement Power Offset* IE for each preconfigured cell.]
- [FDD The DRNS shall include in the *HS-DSCH Preconfiguration Info* IE in the *RL Information Response* IE in the RADIO LINK RECONFIGURATION READY message the *E-DCH FDD DL Control Channel Information* containing the preconfigured configuration of the E-DCH serving cell according to the rules defined for Serving E-DCH Radio Link Change as follows:]
 - [FDD The DRNS shall allocate for the preconfigured configuration a primary E-RNTI identifier or a secondary E-RNTI identifier or both for the new Serving E-DCH Radio Link and include these E-RNTI identifiers along with the channelisation code of the corresponding E-AGCH in the *E-DCH FDD DL Control Channel Information* IE.]
 - [FDD The DRNS may preconfigure the *Serving Grant Value* IE and *Primary/Secondary Grant Selector* IE for the initial grant for the serving E-DCH RL and include these values in the *E-DCH FDD DL Control Channel Information* IE.]
- [FDD If the *Power Offset For S-CPICH for MIMO Request Indicator* IE is included in the *HS-DSCH Preconfiguration Setup* IE or in the *Secondary Cells IE* in the *HS-DSCH Preconfiguration Setup* IE, the DRNC shall, if supported and MIMO pilot configuration with Primary and Secondary CPICH is set up on the cell with a non-zero power offset where HS-DSCH / secondary HS-DSCH is preconfigured, include the *Power Offset For S-CPICH for MIMO* IE in the *HS-DSCH Preconfiguration Info* IE or in the *Sets of HS-SCCH Codes* IE in the *HS-DSCH Preconfiguration Info* IE for each preconfigured cell in the RADIO LINK RECONFIGURATION READY message. If zero power offset the DRNC may include the *Power Offset For S-CPICH for MIMO* IE.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Non-Serving RL Preconfiguration Setup* IE in the *RL Information* IE and:]

- [FDD if the choice of *new Serving RL* is "New Serving RL in the DRNS", the DRNC may include the *New non-serving RL E-DCH FDD DL Control Channel Information A* IE and/or *New non-serving RL E-DCH FDD DL Control Channel Information B* IE in the *Non-Serving RL Preconfiguration Info* IE for the RL in the RADIO LINK RECONFIGURATION READY message.]
- [FDD if the choice of *new Serving RL* is "New Serving RL Not in the DRNS", the DRNC may include the *New non-serving RL E-DCH FDD DL Control Channel Information C* IE in the *Non-Serving RL Preconfiguration Info* IE for the RL in the RADIO LINK RECONFIGURATION READY message.]
- [FDD if the choice of *new Serving RL* is "New Serving RL in the DRNS or New Serving RL Not in the DRNS", the DRNC may include the *New non-serving RL E-DCH FDD DL Control Channel Information A* IE, the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information C* for the RL in the *Non-Serving RL Preconfiguration Info* IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD if the Additional E-DCH Non-Serving RL Preconfiguration Setup IE is included, the DRNC may include the New non-serving RL E-DCH FDD DL Control Channel Information A IE, the New non-serving RL E-DCH FDD DL Control Channel Information B IE and/or the New non-serving RL E-DCH FDD DL Control Channel Information C IE according to the choice of new Serving RL in Additional E-DCH New non-serving RL E-DCH FDD DL Control Channel Information IE for the additional non serving E-DCH RL in the Non-Serving RL Preconfiguration Info IE in the RADIO LINK RECONFIGURATION READY message.]

[FDD – Enhanced HS Serving Cell Change:]

[FDD — Upon receipt of the RADIO LINK RECONFIGURATION PREPARE message, if the Enhanced HS Serving Cell Change is preconfigured in the DRNS for the UE context, the DRNS may execute the Enhanced HS Serving Cell Change procedure according to [63.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Enhanced HS Serving CC Abort* IE in the *HS-DSCH Information To Modify* IE or the *HS-DSCH FDD Information* IE then the DRNS shall not execute the synchronized Enhanced HS Serving Cell Change procedure when performing the Serving HS-DSCH Radio Link Change or the HS-DSCH Setup.]

[FDD - If the RADIO LINK RECONFIGURATION PREPARE message includes the *Non-Serving RL Preconfiguration Removal* IE, the DRNS shall remove the corresponding preconfigured E-DCH DL Control Channel Information according to the information.]

[FDD – E-DCH Setup:]

[FDD – If the *E-DCH FDD Information* IE is present in the RADIO LINK RECONFIGURATION PREPARE message then:]

- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *MAC-es Guaranteed Bit Rate* IE in the *E-DCH Logical Channel Information* IE in the *E-DCH FDD Information* IE, then the DRNS shall use this information to optimise MAC-e scheduling decisions.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes *UE Aggregate Maximum Bit Rate Enforcement Indicator* IE in the *E-DCH Logical Channel Information* IE in the *E-DCH FDD Information* IE, then the DRNS shall, if supported, consider the data of the related E-DCH Logical Channel for UE Aggregate Maximum Bit Rate Enforcement.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *Maximum MAC-d PDU Size Extended* IE for a E-DCH Logical Channel in the *E-DCH MAC-d Flows Information* IE in the *E-DCH FDD Information* IE, then the DRNS shall ignore the *MAC-d PDU Size* IE in the *MAC-d PDU Size List* IE and use *Maximum MAC-d PDU Size Extended* IE to optimise capacity allocation for the related E-DCH Logical Channel and use the indicated format in user plane frame structure for E-DCH channels (TS 25.425 [32]) and MAC (TS 25.321 [41]).]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH MAC-d Flow Multiplexing List* IE for an E-DCH MAC-d flow the DRNS shall use this information for the related resource allocation operation.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *HARQ Process Allocation For 2ms Scheduled Transmission Grant* IE, the DRNS shall use this information for the related resource allocation operation.]
- [FDD If in the RADIO LINK RECONFIGURATION PREPARE message the E-DCH Grant Type is indicated as being "E-DCH Non-Scheduled Transmission Grant" for an E-DCH MAC-d flow the DRNS shall assume non-scheduled grants being configured for that E-DCH MAC-d flow and shall use the information within the HARQ Process Allocation For 2ms Non-Scheduled Transmission Grant IE, if included, for the related resource allocation operation.]
- [FDD If in the RADIO LINK RECONFIGURATION PREPARE message the E-DCH Grant Type is indicated as being "E-DCH Scheduled Transmission Grant" for an E-DCH MAC-d flow the DRNS shall assume scheduled grants being configured for that E-DCH MAC-d flow.]
- [FDD The DRNS may use the *Traffic Class* IE for a specific E-DCH MAC-d flow to determine the transport bearer characteristics to apply between DRNC and Node B. If *TrCH Source Statistics Descriptor* IE is present with the value "RRC" in the *E-DCH MAC-d Flows Information* IE, then the DRNC should ignore the *Traffic Class* IE.]
- [FDD If the *TNL QoS* IE is included for an E-DCH MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink for the related MAC-d flow.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *Bundling Mode Indicator* IE for a E-DCH MAC-d flow in the *E-DCH MAC-d Flow Specific Information* IE in the *E-DCH FDD Information* IE and the *Bundling Mode Indicator* IE is set to "Bundling" and the *E-TTI* IE is set to "2ms", then

- the DRNS shall use the bundling mode for the E-DCH UL data frames for the related MAC-d flow, otherwise the DRNS shall use the non-bundling mode for the E-DCH UL data frames for the related MAC-d flow.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH Maximum Bitrate* IE for an E-DCH, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the E-DCH Processing
 Overload Level IE, then if the DRNS could not decode the E-DPCCH/E-DPDCH for the last consecutive number
 of TTIs, indicated in the E-DCH Processing Overload Level IE, because of processing issue, the DRNS shall
 notify the SRNC by initiating the Radio Link Failure procedure.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH ReferencePower Offset* IE, then the DRNS may use this value as a default HARQ power offset if it is not able to decode the MAC-e PDU and to determine the value of the actual HARQ power offset.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH Power Offset for Scheduling Info* IE, then the DRNS shall use this value as a power offset for the transmission of scheduling information without any MAC-d PDUs.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-AGCH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-AGCH power. The E-AGCH Power Offset should be applied for any E-AGCH transmission to this UE.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-RGCH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-RGCH power for the RL. The E-RGCH Power Offset should be applied for any E-RGCH transmission to this UE.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-HICH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-HICH power for the RL. The E-HICH Power Offset should be applied for any E-HICH transmission to this UE.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *SixteenQAM UL Operation Indicator* IE, the DRNS shall activate/deactivate SixteenQAM UL Operation for the RL in accordance with the *SixteenQAM UL Operation Indicator* IE.]
 - [FDD If SixteenQAM UL Operation is activated, then the DRNS shall base the handling of the Relative Grant signalling on Scheduling Grant Table 2 according to TS 25.321 [41]. If SixteenQAM UL Operation is deactivated, then the DRNS shall base the handling of the Relative Grant signalling on Scheduling Grant Table 1 according to TS 25.321 [41].]

[FDD – E-DCH Radio Link Handling:]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH RL Indication* IE in the *RL Information* IE:]

- [FDD The DRNC shall setup the E-DCH resources, as requested or as configured in the UE context, on the Radio Links indicated by the *E-DCH RL Indication* IE, set to "E-DCH", in the *RL Information* IE.]
- [FDD The DRNC may include the *E-AGCH And E-RGCH/E-HICH FDD Scrambling Code* IE and shall include the *E-RGCH/E-HICH Channelisation Code* IE and the corresponding *E-HICH Signature Sequence* IE and the DRNC may include the corresponding *E-RGCH Signature Sequence* IE in the *E-DCH FDD DL Control Channel Information* IE in the RADIO LINK RECONFIGURATION READY message for every RL indicated by the *E-DCH RL Indication* IE, set to "E-DCH", in the *RL Information* IE.]
- [FDD The DRNC shall remove the E-DCH resources, if any, on the Radio Links, that are indicated by the *E-DCH RL Indication* IE set to "Non E-DCH", in the *RL Information* IE.]
- [FDD For each RL for which the *E-DCH RL Indication* IE is set to "E-DCH", and which has or can have a common generation of E-RGCH information with another RL (current or future) when the DRNS would contain the E-DCH serving RL, the DRNS shall include the *E-DCH RL Set ID* IE in the RADIO LINK RECONFIGURATION READY message. The value of the *E-DCH RL Set ID* IE shall allow the SRNC to identify the E-DCH RLs that have or can have a common generation of E-RGCH information.]

[FDD - Serving E-DCH Radio Link Change:]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the Serving E-DCH RL ID IE, this indicates the new Serving E-DCH Radio Link:]

- [FDD If the old Serving E-DCH RL is within this DRNS, the DRNS shall de-allocate the E-AGCH resources of the old Serving E-DCH Radio Link at the activation of the new configuration.]
- [FDD If the new Serving E-DCH RL is within this DRNS:]
 - [FDD the DRNS shall allocate a primary E-RNTI identifier or a secondary E-RNTI identifier or both for the new Serving E-DCH Radio Link and include these E-RNTI identifiers along with the channelisation code of the corresponding E-AGCH in the *E-DCH FDD DL Control Channel Information* IE in the *RL Information Response* IE for the indicated RL in the RADIO LINK RECONFIGURATION READY message.]
 - [FDD The DRNS may include the *Serving Grant Value* IE and *Primary/Secondary Grant Selector* IE in the RADIO LINK RECONFIGURATION READY message for the initial grant for the new serving E-DCH RL.]
 - [FDD If the E-DCH HARQ process allocation for 2ms TTI for scheduled and/or non-scheduled transmission shall be changed, the DRNS shall allocate resources according to the new/changed configuration and include the new/changed configuration in the *E-DCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
 - [FDD If a serving cell change is performed the RADIO LINK RECONFIGURATION READY message may contain invalid data (see 9.2.2.4C).]
 - [FDD The DRNS may include the *Default Serving Grant in DTX Cycle 2* IE in the RADIO LINK RECONFIGURATION READY message for the new serving E-DCH RL.]
- [FDD The DRNS may include the *E-RGCH/E-HICH Channelisation Code* IE and/or the *E-HICH Signature Sequence* IE and/or the *E-RGCH Signature Sequence* IE or may alternatively include the *E-RGCH Release Indicator* IE in the *E-DCH FDD DL Control Channel Information* IE in the RADIO LINK RECONFIGURATION READY message for every E-DCH Radio Links in the DRNS.]
- [FDD If the DRNS has no valid data for the *E-RGCH/E-HICH Channelisation Code* IE in the *E-DCH FDD DL Control Channel Information* IE in the RADIO LINK RECONFIGURATION READY message, then it shall insert the *E-RGCH and E-HICH Channelisation Code Validity Indicator* IE in the *E-DCH FDD DL Control Channel Information* IE, to indicate that the *E-RGCH/E-HICH Channelisation Code* IE contains invalid data.]

[FDD – E-DCH Modification:]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH FDD Information To Modify* IE, then:]

- [FDD If the *E-DCH FDD Information To Modify* IE contains a *E-DCH MAC-d Flow Specific Information* IE which includes the *Allocation/Retention Priority* IE, the DRNS shall apply the new Allocation/Retention Priority to this E-DCH in the new configuration according to Annex A.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH MAC-d PDU Size Format* IE in the *E-DCH FDD Information To Modify* IE, then the DRNS shall use the indicated format in user plane frame structure for E-DCH channels (TS 25.425 [32]) and MAC (TS 25.321 [41]).]
- [FDD If the *TNL QoS* IE is included for an E-DCH MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink for the related MAC-d flow.]
- [FDD –If the *Traffic Class* IE is included for an E-DCH MAC-d flow then the DRNS may use the *Traffic Class* IE for a specific E-DCH MAC-d flow to determine the transport bearer characteristics to apply between DRNC and Node B. The DRNC should ignore the *Traffic Class* IE if the *TrCH Source Statistics Descriptor* IE for this specific E-DCH MAC-d flow indicates the value "RRC".]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *Data Description Indicator* IE, the DRNC shall use the DDI values indicated in the *Data Description Indicator* IE in the new configuration.]

- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *MAC-es Guaranteed Bit Rate* IE in the *E-DCH FDD Information To Modify* IE, the DRNS shall use this information to optimise MAC-e scheduling decisions.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *Maximum MAC-d PDU Size Extended* IE for a E-DCH Logical Channel in the *E-DCH MAC-d Flows Information* IE in the *E-DCH FDD Information To Modify* IE, then the DRNS shall ignore the *MAC-d PDU Size* IE in the *MAC-d PDU Size List* IE and use *Maximum MAC-d PDU Size Extended* IE to optimise capacity allocation for the related E-DCH Logical Channel.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *Maximum Number of Retransmissions for E-DCH* IE for an E-DCH MAC-d flow in the *E-DCH FDD Information To Modify* IE, then the DRNS shall use this information to report if the maximum number of retransmissions has been exceeded.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH HARQ Power* Offset FDD IE in the *E-DCH FDD Information To Modify* IE for an E-DCH MAC-d flow the DRNS shall use this information for calculating the unquantised gain factor for an E-TFC ($\beta_{ed,i,uo}$) as defined in TS 25.214 [10].]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH MAC-d Flow Multiplexing List* IE for an E-DCH MAC-d flow the DRNS shall use this information for the related resource allocation operation.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the E-DCH Grant Type and it is indicated as being "E-DCH Non-Scheduled Transmission Grant" for an E-DCH MAC-d flow the DRNS shall assume non-scheduled grants being configured for that E-DCH MAC-d flow and shall use the information within the HARQ Process Allocation For 2ms Non-Scheduled Transmission Grant IE, if included, for the related resource allocation operation.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the E-DCH Grant Type and it is indicated as being "E-DCH Scheduled Transmission Grant" for an E-DCH MAC-d flow the DRNS shall assume scheduled grants being configured for that E-DCH MAC-d flow.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH Logical Channel To Add* or *E-DCH Logical Channel To Delete* IEs, the DRNS shall use this information to add/delete the indicated logical channels. When an logical channel is deleted, all its associated configuration data shall also removed.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH Logical Channel To Modify* IE, the DRNS shall use this information to modify the indicated logical channels:]
 - [FDD If the *E-DCH Logical Channel To Modify* IE includes *Scheduling Priority Indicator* IE, the DRNS shall apply the values in the new configuration.]
 - [FDD If the *E-DCH Logical Channel To Modify* IE includes *Scheduling Information* IE, the DRNS shall apply the values in the new configuration.]
 - [FDD If the *E-DCH Logical Channel To Modify* IE includes the *Maximum MAC-d PDU Size Extended* IE, the DRNS shall apply the value in the new configuration.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *Bundling Mode Indicator* IE for an E-DCH MAC-d flow in the *E-DCH MAC-d Flow Specific Information* IE in the *E-DCH FDD Information To Modify* IE and the *Bundling Mode Indicator* IE is set to "Bundling" and the *E-TTI* IE is set to "2ms", then the DRNS shall use the bundling mode for the E-DCH UL data frames for the related MAC-d flow, otherwise the DRNS shall use the non-bundling mode for the E-DCH UL data frames for the related MAC-d flow.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *HARQ Process Allocation For 2ms Scheduled Transmission Grant* IE, the DRNS shall use this information for the related resource allocation operation.]
- [FDD If the E-DCH serving RL is in this DRNS, the DRNS may choose to change the E-DCH HARQ process allocation for 2ms TTI for scheduled and/or non-scheduled transmission. In this case the DRNS shall allocate resources according to the new/changed configuration and include the new/changed configuration in the *E-DCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]

- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH Maximum Bitrate* IE for an E-DCH, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the E-DCH Processing
 Overload Level IE, then if the DRNS could not decode the E-DPCCH/E-DPDCH for the last consecutive number
 of TTIs, indicated in the E-DCH Processing Overload Level IE, because of processing issue, the DRNS shall
 notify the SRNC by initiating the Radio Link Failure procedure.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH ReferencePower Offset* IE, then the DRNS may use this value as a default HARQ power offset if it is not able to decode the MAC-e PDU and to determine the value of the actual HARQ power offset.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH Power Offset for Scheduling Info* IE, then the DRNS shall use this value as a power offset for the transmission of scheduling information without any MAC-d PDUs.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-AGCH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-AGCH power. The E-AGCH Power Offset should be applied for any E-AGCH transmission to this UE.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-RGCH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-RGCH power for the RL. The E-RGCH Power Offset should be applied for any E-RGCH transmission to this UE.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-HICH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-HICH power for the RL. The E-HICH Power Offset should be applied for any E-HICH transmission to this UE.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *MAC-e Reset Indicator* IE in the *E-DCH FDD Information To Modify* IE, then the DRNS shall use this value to determine whether MAC-e(or MAC-i) Reset is performed in the UE for sending the HARQ Failure Indication.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *SixteenQAM UL Operation Indicator* IE in the *E-DCH FDD Information To Modify* IE, the DRNS shall activate/deactivate SixteenQAM UL Operation for the RL in accordance with the *SixteenQAM UL Operation Indicator* IE]
 - [FDD If SixteenQAM UL Operation is activated, then the DRNS shall base the handling of the Relative Grant signalling on Scheduling Grant Table 2 according to TS 25.321 [41]. If SixteenQAM UL Operation is deactivated, then the DRNS shall base the handling of the Relative Grant signalling on Scheduling Grant Table 1 according to TS 25.321 [41].]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH DL Control Channel Grant Information* IE in the *E-DCH FDD Information To Modify* IE, the DRNS may modify E-AGCH Channelisation Code, E-RGCH/E-HICH Channelisation Code, E-RGCH Signature Sequence and/or E-HICH Signature Sequence for the E-DCH RL indicated by the *E-DCH RL ID* IE. The DRNC shall then report the modified configuration which is used in the new configuration specified in the *E-DCH FDD DL Control Channel Information* IE for each E-DCH RL in the RADIO LINK RECONFIGURATION READY message.]

[FDD – E-DCH MAC-d Flow Addition:]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes an *E-DCH MAC-d Flows To Add* IE, then the DRNS shall use this information to add the indicated E-DCH MAC-d flows.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Maximum MAC-d PDU Size Extended* IE for a E-DCH Logical Channel in the *E-DCH MAC-d Flows Information* IE in the *E-DCH MAC-d Flows To Add* IE, then the DRNS shall ignore the *MAC-d PDU Size* IE in the *MAC-d PDU Size List* IE and use *Maximum MAC-d PDU Size Extended* IE to optimise capacity allocation for the related E-DCH Logical Channel.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH MAC-d Flows To Add* IE, then:]

- [FDD – The DRNS may use the *Traffic Class* IE for a specific E-DCH MAC-d flow to determine the transport bearer characteristics to apply between DRNC and Node B. If *TrCH Source Statistics Descriptor* IE is present

with the value "RRC" in the *E-DCH MAC-d Flows Information* IE, then the DRNC should ignore the *Traffic Class* IE.]

- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *MAC-es Guaranteed Bit Rate* IE in the *E-DCH Logical Channel Information IE* in the *E-DCH MAC-d Flows To Add* IE, the DRNS shall use this information to optimise MAC-e scheduling decisions.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *UE Aggregate Maximum Bit Rate Enforcement Indicator* IE in the *E-DCH Logical Channel Information IE* in the *E-DCH MAC-d Flows To Add* IE, the DRNS shall, if supported, consider the data of the related E-DCH Logical Channel for UE Aggregate Maximum Bit Rate Enforcement.]

[FDD – E-DCH MAC-d Flow Deletion:]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes an E-DCH MAC-d Flows To Delete IEs, then the DRNS shall use this information to delete the indicated E-DCH MAC-d flows. When an E-DCH MAC-d flow is deleted, all its associated configuration shall also be removed.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes an *E-DCH MAC-d Flows To Delete* IE requesting the deletion of all remaining E-DCH MAC-d flows for the UE Context, then the DRNC shall delete the E-DCH configuration from the UE Context and release the E-DCH resources.]

[FDD – Additional E-DCH Setup:]

[FDD – If the *Additional E-DCH Cell Information RL Reconf Prep* IE is present in the RADIO LINK RECONFIGURATION PREPARE message and the choice of *Setup, Configuration Change or Removal of E-DCH On Secondary UL Frequency* is "Setup", then the *Additional E-DCH Cell Information Setup* IE defines the new configuration and then:]

- [FDD If the *C-ID* IE is included in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE the *C-ID* IE indicates the cell in which the additional E-DCH shall be setup]
 - [FDD The DRNS shall setup the Additional E-DCH on the secondary uplink frequency and setup the requested Additional E-DCH resources on the Radio Links and in the cells indicated by the *E-DCH Additional RL ID* IE and the *C-ID* IE in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE.]
- [FDD If the *C-ID* IE is not included in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE the *E-DCH Additional RL ID* IE indicates the existing RL on which the Additional E-DCH shall be setup.]
 - [FDD The DRNS shall setup the additional E-DCH on the Radio Links indicated by the *E-DCH Additional RL ID* IE in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE]
- [FDD The DRNS shall use for the non cell specific Radio Link related parameters and non cell specific E-DPCH, UL DPCH, E-DCH and F-DPCH parameters the same values as for the corresponding cell of the Primary uplink frequency.]
- [FDD If the *UL SIR Target* IE in the *UL DPCH Information* IE in the *Additional E-DCH FDD Setup Information* IE in the *Additional E-DCH Cell Information Setup* IE and/or the *DL Power Balancing Information* IE and/or the *Minimum Reduced E-DPDCH Gain Factor* IE in the *Multicell E-DCH Information* IE in the *Additional E-DCH FDD Setup Information* IE are present, the DRNS shall use the information in the same same way as for the information used on Primary uplink frequency.]
- [FDD If the Secondary UL Frequency Activation State IE is present in the Multicell E-DCH Information IE in the Additional E-DCH FDD Setup Information IE, the DRNS shall use the information as initial activation state of the Radio Links on the secondary uplink frequency.]
- [FDD If the *Initial DL Tx Power* IE, the *Primary CPICH Ec/No* IE, the *E-AGCH Power Offset* IE, the *E-RGCH Power Offset* IE and/or the *E-HICH Power Offset* IE is included in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE in the *Additional E-DCH Cell Information Setup* IE, the DRNS shall use the information in the same way as for the information used on Primary uplink frequency.]

- [FDD If the Enhanced Primary CPICH Ec/No IE is included in the Multicell E-DCH RL Specific Information IE in the Additional E-DCH Secondary RL Specific Information To Setup IE in the Additional E-DCH FDD Setup Information IE in the Additional E-DCH Cell Information Setup IE, the DRNS shall use the information in the same way as for the information used on Primary uplink frequency.]
- [FDD If the *F-DPCH Slot Format Support Request* IE in the *F-DPCH Information* IE in the *Additional E-DCH FDD Setup Information* IE in the *Additional E-DCH Cell Information Setup* IE is included, the DRNS shall configure the concerned UE Context for F-DPCH Slot Format operation according to TS 25.211 [8] and include the *F-DPCH Slot Format* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RL Reconf* IE in the RADIO RECONFIGURATION READY message. If the *Multicell E-DCH Information* IE in the *Additional E-DCH FDD Setup Information* IE includes the *F-DPCH Slot Format* IE, the DRNS may use the *F-DPCH Slot Format* IE to determine the F-DPCH slot format.]
- [FDD If the HARQ Process Allocation For 2ms Scheduled Transmission Grant IE, the E-DCH Maximum Bitrate IE, the E-DCH Minimum Set E-TFCI IE and/or the E-DCH Processing Overload Level IE are present in the Additional E-DCH FDD Information IE in the Additional E-DCH Cell Information Setup IE, the DRNS shall use the information in the same way as for the information used on Primary uplink frequency.]
- [FDD If activation of power balancing for the Additional E-DCH RL by the RADIO LINK RECONFIGURATION PREPARE message is supported by the DRNS, the DRNS shall include the *DL Power Balancing Activation Indicator* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD For each Additional E-DCH RL not having a common generation of the TPC commands in the DL with another Additional E-DCH RL, the DRNS shall set the *RL Set ID* IE included in the *Additional E-DCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message to a value that uniquely identifies the RL as a RL Set within the UE Context. The generation of E-HICH related information for Additional E-DCH RLs in different RL Sets shall not be common.]
- [FDD For all Additional E-DCH RLs having a common generation of the TPC commands in the DL with another Additional E-DCH RL, the DRNS shall assign to each Additional E-DCH RL the same value for the *RL Set ID* IE included in the *Additional E-DCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message. This value shall uniquely identify these Additional E-DCH RLs as members of the same RL Set within the UE Context. The generation of E-HICH information for all Additional E-DCH RLs in a RL Set shall be common.]
- [FDD For each Additional E-DCH RL which has or can have a common generation of E-RGCH information with another Additional E-DCH RL (current or future) when the DRNS would contain the Additional E-DCH serving RL, the DRNS shall set a same value to the *E-DCH RL Set ID* IE for the Additional E-DCH RL in the *Additional E-DCH FDD Information Response* IE in the *AdditionalE-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION READY message]
- [FDD For every additional E-DCH RL indicated in the Additional E-DCH RL Specific Information To Setup IE in the Additional E-DCH FDD Setup Information IE the DRNS may include the E-AGCH And E-RGCH/E-HICH FDD Scrambling Code IE and shall include the E-RGCH/E-HICH Channelisation Code IE and the corresponding E-HICH Signature Sequence IE and the DRNS may include the corresponding E-RGCH Signature Sequence IE for each Additional E-DCH RL in the E-DCH FDD DL Control Channel Information IE in the Additional E-DCH FDD Information Response IE in the AdditionalE-DCH Cell Information Response RLReconf IE in the RADIO LINK RECONFIGURATION READY message and if DRNS has no valid data for the E-RGCH/E-HICH Channelisation Code IE, then it shall insert the E-RGCH and E-HICH Channelisation Code Validity Indicator IE to indicate that the E-RGCH/E-HICH Channelisation Code IE contains invalid data.]
- [FDD If the Additional Serving E-DCH Radio Link is configured in the DRNS, then:]
 - [FDD The DRNS shall allocate a primary E-RNTI identifier or a secondary E-RNTI identifier or both for
 the corresponding RL and include these E-RNTI identifiers and the channelisation code of the corresponding
 E-AGCH in the E-DCH FDD DL Control Channel Information IE in the Additional E-DCH FDD
 Information Response IE in the Additional E-DCH Cell Information Response RLReconf IE in the RADIO
 LINK RECONFIGURATION READY message.]
 - [FDD The DRNS may include in the *E-DCH FDD DL Control Channel Information* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION READY message the *Serving Grant Value* IE and

Primary/Secondary Grant Selector IE for the initial grant for the Additional serving E-DCH RL and may include the *Default Serving Grant in DTX Cycle 2* IE.]

- [FDD If the E-DCH HARQ process allocation for 2ms TTI for scheduled transmission shall be changed, the DRNS shall allocate resources according to the new/changed configuration and include the new/changed configuration in the *HARQ Process Allocation For 2ms Scheduled Transmission Grant* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If Primary CPICH is not to be used as a Phase Reference for this Radio Link on the secondary UL frequency, the DRNS shall include the *Primary CPICH Usage For Channel Estimation* IE set to the value "Primary CPICH shall not be used" in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE RADIO LINK RECONFIGURATION READY message.]
- [FDD If Secondary CPICH may be used as a Phase Reference for this Radio Link on the secondary UL frequency, the DRNS shall include the *Secondary CPICH Information* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION READY message. If the DRNS doesn't include the *Secondary CPICH Information* IE, it shall not include the *Primary CPICH Usage For Channel Estimation* IE set to the value "Primary CPICH shall not be used".]

[FDD – Additional E-DCH Configuration Change]

[FDD – If the *Additional E-DCH Cell Information RL Reconf Prep* IE is present in the RADIO LINK RECONFIGURATION PREPARE message and the choice of *Setup, Configuration Change or Removal of E-DCH On Secondary UL Frequency* is "Configuration Change", then the *Additional E-DCH Cell Information Configuration Change* IE defines the new configuration and then:]

- [FDD If the *UL Scrambling Code* IE and/or the *UL SIR Target* IE are present in the *UL DPCH Information* IE in the *Additional E-DCH Configuration Change Information* IE and/or id the *Minimum Reduced E-DPDCH Gain Factor* IE is present in the *Multicell E-DCH Information* IE in the *Additional E-DCH Configuration Change Information* IE, the DRNS shall use the information in the same way as for the information that is used on the Primary uplink frequency.]
- [FDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *F-DPCH Information* IE in the *Additional E-DCH Configuration Change Information* IE, then:]
 - [FDD The DRNS shall configure the concerned UE Context to use F-DPCH in the downlink in the new configuration.]
 - [FDD If the *F-DPCH Information* IE includes the *F-DPCH Slot Format Support Request* IE, then the DRNS shall configure the concerned UE Context for F-DPCH Slot Format operation according to TS 25.211 [8] and include the *F-DPCH Slot Format* IE in the *Additional E-DCH FDD Information Response* IE for new RLs on the secondary UL frequency or in the *Additional Modified E-DCH FDD Information Response* IE for modified RLs in the RADIO LINK RECONFIGURATION READY message. If the *Multicell E-DCH Information* IE in the *Additional E-DCH Configuration Change Information* IE includes the *F-DPCH Slot Format* IE, the DRNS may use the *F-DPCH Slot Format* IE to determine the F-DPCH slot format.]

[FDD - Additional E-DCH RL Addition:]

[FDD – If the *Additional E-DCH RL Specific Information To Add* IE is present in the *Additional E-DCH Configuration Change Information* IE, then:]

- [FDD The DRNS shall setup the E-DCH resources, as requested or as configured in the UE context, on the Radio Links indicated by the *E-DCH Additional RL ID* IE. Non cell specific Radio Link related parameters and non cell specific E-DPCH, UL DPCH, E-DCH and F-DPCH parameters shall take the same values as for the corresponding cell of the Primary uplink frequency.]
- [FDD If the *E-AGCH Power Offset* IE, the *E-RGCH Power Offset* IE, the *E-HICH Power Offset* IE is included, the DRNS shall use the information in the same way as for information is used on the Primary uplink frequency.]
- [FDD If the power balancing is active with the Power Balancing Adjustment Type of the UE
 Context set to "Individual" in the existing Additional E-DCH RL(s) and the RADIO LINK
 RECONFIGURATION PREPARE message includes the DL Reference Power IE in the Multicell E-

DCH RL Specific Information IE, the DRNS shall activate the power balancing and use the DL Reference Power IE for the power balancing procedure in the new Additional RL(s), if activation of power balancing by the RADIO LINK RECONFIGURATION PREPARE message at RL addition on secondary UL frequency is supported, according to subclause 8.3.15. In this case, the DRNS shall include the DL Power Balancing Activation Indicator IE in the Additional E-DCH FDD Information Response IE in the Additional E-DCH Cell Information Response RLReconf IE in the RADIO LINK RECONFIGURATION READY message. If the DRNS starts the DL transmission and the activation of the power balancing at the same CFN, the initial power of the power balancing, i.e. P_{init} shall be set to the power level which is calculated based on the following IEs (if received): Primary CPICH Ec/No IE or the Enhanced Primary CPICH Ec/No IE in the Multicell E-DCH RL Specific Information IE or to the power level which is calculated based on the power relative to the Primary CPICH power used by the existing Additional RLs.]

- [FDD For each Additional E-DCH RL not having a common generation of the TPC commands in the DL with another Additional E-DCH RL, the DRNS shall set the *RL Set ID* IE included in the *Additional E-DCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message to a value that uniquely identifies the RL as a RL Set within the UE Context. The generation of E-HICH related information for Additional E-DCH RLs in different RL Sets shall not be common.]
- [FDD For all Additional E-DCH RLs having a common generation of the TPC commands in the DL with another Additional E-DCH RL, the DRNS shall assign to each Additional E-DCH RL the same value for the *RL Set ID* IE included in the *Additional E-DCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message. This value shall uniquely identify these Additional E-DCH RLs as members of the same RL Set within the UE Context. The generation of E-HICH information for all Additional E-DCH RLs in a RL Set shall be common.]
- [FDD For each Additional E-DCH RL which has or can have a common generation of E-RGCH information with another Additional E-DCH RL (current or future) when the DRNS would contain the Additional E-DCH serving RL, the DRNS shall set a same value to the *E-DCH RL Set ID* IE for the Additional E-DCH RL in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION READY message]
- [FDD For every additional E-DCH RL indicated in the Additional E-DCH RL Specific Information To Add IE, the DRNS may include the E-AGCH And E-RGCH/E-HICH FDD Scrambling Code IE and shall include the E-RGCH/E-HICH Channelisation Code IE and the corresponding E-HICH Signature Sequence IE and the DRNS may include the corresponding E-RGCH Signature Sequence IE in the E-DCH FDD DL Control Channel Information IE in the Additional E-DCH FDD Information Response IE in the Additional E-DCH Cell Information Response RLReconf IE in the RADIO LINK RECONFIGURATION READY message and if DRNS has no valid data for the E-RGCH/E-HICH Channelisation Code IE, then it shall insert the E-RGCH/E-HICH Channelisation Code Validity Indicator IE to indicate that the E-RGCH/E-HICH Channelisation Code IE contains invalid data.]
- [FDD If the *Primary CPICH Ec/No* IE or the *Primary CPICH Ec/No* IE and the *Enhanced Primary CPICH Ec/No* IE in the *Multicell E-DCH RL Specific Information* IE measured by the UE are included for a RL in the RADIO LINK RECONFIGURATION PREPARE message, the DRNS shall use this in the calculation of the Initial DL TX Power for this additional RL. If the *Primary CPICH Ec/No* IE is not present, the DRNS shall set the Initial DL TX Power based on the power relative to the Primary CPICH power used by the existing RLs.]

[FDD – Additional E-DCH RL Modification:]

[FDD – If the *Additional E-DCH RL Specific Information To Modify* IE is present in the *Additional E-DCH Configuration Change Information* IE, then the RL indicated by the *E-DCH Additional RL ID* IE indicates the RL on which E-DCH resources shall be modified:]

- [FDD – If the *E-AGCH Power Offset* IE, the *E-RGCH Power Offset* IE, the *E-HICH Power Offset* IE, and/or the *E-DCH DL Control Channel Grant* IE in the *Multicell E-DCH RL Specific Information* IE is included, the DRNS shall use the information in the same way as for the information used on the Primary uplink frequency.]

- [FDD If the *DL Reference Power* IEs is included in the *Multicell E-DCH RL Specific Information* IE and power balancing is active, DRNS shall apply DL power Control in the same way as defined for the Primary uplink frequency.]
- [FDD If updating of power balancing parameters by the RADIO LINK RECONFIGURATION PREPARE message is supported by the DRNS, the DRNS shall include the *DL Power Balancing Updated Indicator* IE in the *Additional Modified E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE for each affected RL in the RADIO LINK RECONFIGURATION READY message.]
- [FDD If the Phase Reference Update Indicator IE is included in the Multicell E-DCH RL Specific Information IE, DRNS shall modify the channel estimation information according to TS 25.214 [10] subclause 4.3.2.1 and set the value(s) in Primary CPICH Usage For Channel Estimation IE and/or Secondary CPICH Information Change IE in the Additional Modified E-DCH FDD Information Response IE in the Additional E-DCH Cell Information Response RLReconf IE in the RADIO LINK RECONFIGURATION READY message accordingly.]
- [FDD If the RADIO LINK RECONFIGURATION READY message includes the *Primary CPICH Usage For Channel Estimation* IE and/or the *Secondary CPICH Information Change* IE in the *Additional Modified E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE, the DRNS shall avoid the new configuration in which neither the Primary CPICH nor the Secondary CPICH is used as a Phase Reference for this Radio Link.]

[FDD – Additional E-DCH Modification:]

[FDD – If the *Additional E-DCH FDD Information To Modify* IE is present in the *Additional E-DCH Configuration Change Information* IE, then:]

- [FDD If the *HARQ Process Allocation For 2ms Scheduled Transmission Grant* IE, the *E-DCH Minimum Set E-TFC*I IE and/or the *E-DCH Maximum Bitrate* IE is included, the DRNS shall use this information for the related resource allocation operation.]
- [FDD If the *E-DCH Processing Overload Level* IE is included, then if the DRNS could not decode the E-DPCCH/E-DPDCH for the last consecutive number of TTIs, indicated in the *E-DCH Processing Overload Level* IE, because of processing issue, the DRNS shall notify the RNC by initiating the Radio Link Failure procedure.]
- [FDD If the DL TX power upper or lower limit has been re-configured for the secondary UL frequency, the DRNS shall include the new value(s) in the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the *Additional Modified E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION READY message.]
- [FDD The DRNS decides the maximum and minimum SIR for the uplink of the Radio Link(s), and the DRNS shall include in the RADIO LINK RECONFIGURATION READY message the *Maximum Uplink SIR* IE and *Minimum Uplink SIR* IE in the *Additional Modified E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE for each Radio Link when these values are changed.]
- [FDD If the Additional E-DCH serving RL is in this DRNS, the DRNS may choose to change the E-DCH HARQ process allocation for 2ms TTI for scheduled transmission. In this case the DRNS shall allocate resources according to the new/changed configuration and include the new/changed configuration in the HARQ Process Allocation For 2ms Scheduled Transmission Grant IE in the Additional Modified E-DCH FDD Information Response IE in the RADIO LINK RECONFIGURATION READY message.]

[FDD – Additional E-DCH Removal]

[FDD – If the *Additional E-DCH Cell Information RL Reconf Prep* IE is present in the RADIO LINK RECONFIGURATION PREPARE message and the choice of *Setup, Configuration Change or Removal of E-DCH On Secondary UL Frequency* is "Removal", then the additional E-DCH on the secondary uplink frequency shall be removed.]

[1.28Mcps TDD – Uplink Synchronisation Parameters LCR:]

[1.28Mcps TDD –If the *Uplink Synchronisation Parameters LCR* IE is present, the DRNC shall use the indicated values of *Uplink synchronisation stepsize* IE and *Uplink synchronisation frequency* IE when evaluating the timing of the UL synchronisation.]

[1.28Mcps TDD – Shared physical channels Synchronisation Detection:]

[1.28Mcps TDD – If HS-PDSCH and E-PUCH are configured but no DPCH is configured for the UE, then the DRNS shall include the *Out-of-sync Detection Window* IE in the *HS-DSCH TDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]

[1.28Mcps TDD – Uplink Timing Advance Control LCR:]

[1.28Mcps TDD – The DRNC shall include the *Uplink Timing Advance Control LCR* IE in the RADIO LINK RECONFIGURATION READY message, if the Uplink Timing Advance Control parameters have been changed.]

[1.28Mcps TDD – PowerControl GAP:]

[1.28Mcps TDD – If applied in the DRNS, the DRNC may include the *PowerControl GAP* IE in the RADIO LINK RECONFIGURATION READY message.]

[1.28Mcps TDD – E-UTRAN Inter-RAT measurement:]

[1.28Mcps TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Need for Idle Interval* IE set to "TRUE", if supported, the DRNC shall include the *Idle Interval Information* IE in the RADIO LINK RECONFIGURATION READY message. If the *Need for Idle Interval* IE is set to "FALSE", the DRNC shall delete the configuration related to E-UTRAN Inter-RAT measurement]

[1.28Mcps TDD – RNTI Allocation Indicator:]

[1.28Mcps TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *RNTI Allocation Indicator* IE, if supported, the DRNS may allocate an E-RNTI and/or an H-RNTI for UE to use in CELL_FACH state.]

[1.28Mcps TDD – Inter-frequency/ Inter-RAT measurement:]

[1.28Mcps TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *DCH Measurement Type indicator* IE, if supported, the DRNS shall include the *Measurement purpose* IE and the *Measurement occasion pattern sequence parameters* IE in the *DCH Measurement Occasion Information* IE in the RADIO LINK RECONFIGURATION READY message to configure the measurement occasion pattern(s) indicated by the *DCH Measurement Type indicator* IE.]

[TDD - DSCH RNTI Addition/Deletion:]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *PDSCH RL ID* IE, then the DRNS shall use it as the new RL identifier for PDSCH and PUSCH.]

- [TDD If the indicated PDSCH RL ID is in the DRNS and there was no DSCH-RNTI allocated to the UE Context, the DRNC shall allocate a DSCH-RNTI to the UE Context and include the *DSCH-RNTI* IE in the RADIO LINK RECONFIGURATION READY message.]
- [TDD If the indicated PDSCH RL ID is in the DRNS and there was a DSCH-RNTI allocated to the UE Context, the DRNC shall allocate a new DSCH-RNTI to the UE Context, release the old DSCH-RNTI and include the *DSCH-RNTI* IE in the RADIO LINK RECONFIGURATION READY message.]
- [TDD If the indicated PDSCH RL ID is not in the DRNS and there was a DSCH-RNTI allocated to the UE Context, the DRNC shall release this DSCH-RNTI.]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes a *DSCHs To Delete* IE and/or a *USCHs To Delete* IE which results in the deletion of all DSCH and USCH resources for the UE Context, then the DRNC shall release the DSCH-RNTI allocated to the UE Context, if there was one.]

[FDD - Phase Reference Handling:]

[FDD – If Primary CPICH usage for channel estimation information has been reconfigured, the DRNC shall include the *Primary CPICH Usage For Channel Estimation* IE in the RADIO LINK RECONFIGURATION READY message.]

[FDD – If Secondary CPICH information for channel estimation has been reconfigured, the DRNC shall include the *Secondary CPICH Information Change* IE in the RADIO LINK RECONFIGURATION READY message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes *Phase Reference Update Indicator* IE, DRNC shall modify the channel estimation information according to TS 25.214 [10] subclause 4.3.2.1 and set the value(s) in *Primary CPICH Usage For Channel Estimation* IE and/or *Secondary CPICH Information Change* IE in the RADIO LINK RECONFIGURATION READY message accordingly.]

[FDD – If the RADIO LINK RECONFIGURATION READY message includes the *Primary CPICH Usage For Channel Estimation* IE and/or the *Secondary CPICH Information Change* IE, the DRNC shall avoid the new configuration in which neither the Primary CPICH nor the Secondary CPICH is used as a Phase Reference for this Radio Link.]

[FDD – Fast Reconfiguration:]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Fast Reconfiguration Mode* IE, the DRNS shall, if supported, and if it is possible to base the synchronization of the reconfiguration on the detection of the change in the uplink scrambling code for this reconfiguration, include the *Fast ReconfigurationPermission* IE in the RADIO LINK RECONFIGURATION READY message.]

[TDD – Intra- DRNS Serving E-DCH Radio Link Change:]

TDD- If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH Serving RL* IE, this indicates the new Serving E-DCH Radio Link:]

- [TDD In the new configuration the DRNS shall de-allocate the E-DCH resources of the old Serving E-DCH Radio Link and allocate the E-DCH resources for the new Serving E-DCH Radio Link.]
- [3.84Mcps TDD The DRNS shall allocate E-AGCH parameters corresponding to the E-DCH and include the *E-AGCH Specific Information Response* IE in the *E-DCH TDD Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
- [1.28Mcps TDD The DRNS shall allocate E-AGCH parameters and E-HICH parameters corresponding to the E-DCH and include the *E-AGCH Specific Information Response* IE and the *E-HICH Specific Information Response* IE in the *E-DCH Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]
- [7.68Mcps TDD The DRNS shall allocate E-AGCH parameters corresponding to the E-DCH and include the *E-AGCH Specific Information Response* 7.68Mcps IE in the *E-DCH TDD Information Response* 7.68Mcps IE in the RADIO LINK RECONFIGURATION READY message.]
- [TDD If the *TNL QoS* IE is included for a MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink for the related MAC-d flow.]

[TDD - E-PUCH Handling:]

[3.84Mcps TDD and 7.68Mcps TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes an *E-PUCH Information* IE, the DRNS shall apply the parameters to the new configuration.]

[1.28Mcps TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes an *E-PUCH Information LCR* IE, the DRNS shall apply the parameters to the new configuration]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes an *E-TFCS Information* IE, the DRNS shall apply the beta parameters to the new configuration.]

[3.84Mcps TDD – E-DCH Setup:]

[3.84Mcps TDD – the radio link may be reconfigured to support E-DCH by including the appropriate E-DCH information elements: *E-DCH Serving RL* IE, *E-PUCH Information* IE, *E-TFCS Information TDD* IE, *E-DCH MAC-d Flows to Add* IE and *E-DCH TDD Information* IE.]

[1.28Mcps TDD – E-DCH Setup:]

[1.28cps TDD – the radio link may be reconfigured to support E-DCH by including the appropriate E-DCH informationelements: *E-DCH Serving RL* IE, *E-PUCH Information LCR* IE, *E-TFCS Information TDD* IE, *E-DCH MAC-d Flows to Add* IE and *E-DCH TDD Information LCR* IE.]

[1.28Mcps TDD - If the *UE TSO Capability LCR* IE in the *UE Capabilities Information* IE in the *HS-DSCH Information To Modify* IE is not present, or if the *UE TSO Capability LCR* IE in the *UE Capabilities Information* IE in the *HS-DSCH Information* IE is not present, and if the RADIO LINK RECONFIGURATION PREPARE message includes the *UE TSO Capability LCR* IE in the *E-DCH TDD Information LCR* IE, the DRNS can use this information to allocate the downlink resources for the UE according to TS 25.306 [42].]

[7.68Mcps TDD – E-DCH Setup:]

[7.68Mcps TDD – the radio link may be reconfigured to support E-DCH by including the appropriate E-DCH information elements: *E-DCH Serving RL* IE, *E-PUCH Information* IE, *E-TFCS Information TDD* IE, *E-DCH MAC-d Flows to Add* IE and *E-DCH TDD Information* 7.68Mcps IE.]

[TDD- E-DCH MAC-d Flow Addition/Deletion:]

[TDD- If the RADIO LINK RECONFIGURATION PREPARE message includes any *E-DCH MAC-d Flows To Add* or E-DCH *MAC-d Flows To Delete* IEs, then the DRNS shall use this information to add/delete the indicated E-DCH MAC-d flows. When an E-DCH MAC-d flow is deleted, all its associated configuration data shall also be removed.]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Maximum MAC-d PDU Size Extended* IE for a E-DCH Logical Channel in the *E-DCH MAC-d Flows Information TDD* IE in the *E-DCH MAC-d Flows To Add* IE, then the DRNS shall ignore the *MAC-d PDU Size* IE in the *MAC-d PDU Size List* IE and use *Maximum MAC-d PDU Size Extended* IE to optimise capacity allocation for the related E-DCH Logical Channel.]

[TDD- If the RADIO LINK RECONFIGURATION PREPARE message includes an *E-DCH MAC-d Flows To Delete* IE requesting the deletion of all remaining E-DCH MAC-d flows for the UE Context, then the DRNS shall delete the E-DCH configuration from the UE Context and release the E-DCH resources.]

[TDD- If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH MAC-d Flows To Add* IE, then:]

- [TDD- If the RADIO LINK RECONFIGURATION PREPARE message includes the *MAC-es Guaranteed Bit Rate* IE in the *E-DCH MAC-d Flows To Add* IE, the DRNS shall use this information to optimise MAC-e scheduling decisions.]
- [1.28Mcps TDD If the RADIO LINK RECONFIGURATION PREPARE message includes the *MAC-es Maximum Bit Rate LCR* IE in the *E-DCH Logical Channel Information* IE in the *E-DCH MAC-d Flows To Add* IE, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]

[3.84Mcps TDD – E-DCH Non-scheduled allocations:]

[3.84Mcps TDD – The DRNS shall determine any non-scheduled resource to be granted for the radio link, and return this in the *E-DCH Non-scheduled Grant Information TDD* IE in the *E-DCH Information Response* IE in the RADIO LINK RECONFIGURATION READY message.]

[1.28Mcps TDD – E-DCH Non-scheduled allocations:]

[1.28Mcps – The DRNS shall determine any non-scheduled resource to be granted for the radio link, and return this in the *E-DCH Non-scheduled Grant Information LCR TDD* IE in the *E-DCH Information Response 1.28Mcps* IE in the RADIO LINK RECONFIGURATION READY message.]

[7.68Mcps TDD – E-DCH Non-scheduled allocations:]

[7.68Mcps TDD – The DRNS shall determine any non-scheduled resource to be granted for the radio link, and return this in the *E-DCH Non-scheduled Grant Information* 7.68Mcps *TDD* IE in the *E-DCH Information Response* 7.68Mcps IE in the RADIO LINK RECONFIGURATION READY message.]

[TDD – E-DCH Modification:]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Maximum MAC-d PDU Size Extended* IE for a E-DCH Logical Channel in the *E-DCH MAC-d Flows Information* IE in the *E-DCH TDD*

Information To Modify IE, then the DRNS shall ignore the *MAC-d PDU Size* IE in the *MAC-d PDU Size List* IE and use *Maximum MAC-d PDU Size Extended* IE to optimise capacity allocation for the related E-DCH Logical Channel.]

[TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH MAC-d PDU Size Format* IE in the *E-DCH TDD Information To Modify* IE, then the DRNS shall use the indicated format in user plane frame structure for E-DCH channels (TS 25.425 [32]) and MAC (TS 25.321 [41]).]

[3.84Mcps TDD – E-DCH Modification:]

[3.84Mcps TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH TDD Information* IE, then:]

- [3.84Mcps TDD If the *E-DCH TDD Information* IE includes the *E-DCH TDD Maximum Bitrate* IE for an E-DCH, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
- [3.84Mcps TDD If the *E-DCH TDD Information* IE includes the *E-DCH Processing Overload Level* IE, then if the DRNS could not decode the E-PUCH for the last consecutive number of TTIs, indicated in the *E-DCH Processing Overload Level* IE, because of a processing issue, the DRNS shall notify the SRNC by initiating the Radio Link Failure procedure.]
- [3.84Mcps TDD If the *E-DCH TDD Information* IE includes the *E-DCH Power Offset for Scheduling Info* IE, then the DRNS shall use this value as a power offset for the transmission of scheduling information without any MAC-d PDUs.]

[1.28Mcps TDD – E-DCH Modification:]

[1.28Mcps TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH TDD Information LCR* IE, then:]

- [1.28Mcps TDD If the *E-DCH TDD Information LCR* IE includes the *E-DCH Physical Layer Category LCR* IE or *Extended E-DCH Physical Layer Category LCR* IE for an E-DCH, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
- [1.28Mcps TDD If the *E-DCH TDD Information LCR* IE includes the *E-DCH Processing Overload Level* IE for an E-DCH, then if the DRNS could not decode the E-PUCH for the last consecutive number of TTIs, indicated in the *E-DCH Processing Overload Level* IE, because of a processing issue, the DRNS shall notify the SRNC by initiating the Radio Link Failure procedure.]
- [1.28Mcps TDD If the *E-DCH TDD Information LCR* IE includes the *E-DCH Power Offset for Scheduling Info* IE, then the DRNS shall use this value as a power offset for the transmission of scheduling information without any MAC-d PDUs.]
- [1.28Mcps TDD If the *E-DCH TDD Information LCR* IE includes the *Maximum Number of Retransmission for Scheduling Info LCR* IE and the *E-DCH Retransmission timer for Scheduling Info LCR* IE, then the DRNS shall use these parameters for the transmission of scheduling information without any MAC-d PDUs.]
- [1.28Mcps TDD If the *E-DCH TDD Information LCR* IE includes the *Multi-Carrier E-DCH Physical Layer Category LCR* IE, the DRNS shall use this information for the related resource allocation operation, and when applicable, for multi-carrier E-DCH scheduling.]
- [1.28Mcps TDD If the *UE TSO Capability LCR* IE in the *UE Capabilities Information* IE in the *HS-DSCH Information To Modify* IE is not present, or if the *UE TSO Capability LCR* IE in the *UE Capabilities Information* IE in the *HS-DSCH Information* IE is not present, and if the RADIO LINK RECONFIGURATION PREPARE message includes the *UE TSO Capability LCR* IE in the *E-DCH TDD Information LCR* IE, the DRNS can use this information to allocate the downlink resources for the UE according to TS 25.306 [42].]

[7.68Mcps TDD – E-DCH Modification:]

[7.68Mcps TDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH TDD Information 7.68Mcps* IE, then:]

- [7.68Mcps TDD – If the *E-DCH TDD Information 7.68Mcps* IE includes the *E-DCH TDD Maximum Bitrate 7.68Mcps* IE for an E-DCH, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]

- [7.68Mcps TDD If the *E-DCH TDD Information 7.68Mcps* IE includes the *E-DCH Processing Overload Level* IE, then if the DRNS could not decode the E-PUCH for the last consecutive number of TTIs, indicated in the *E-DCH Processing Overload Level* IE, because of a processing issue, the DRNS shall notify the SRNC by initiating the Radio Link Failure procedure.]
- [7.68Mcps TDD If the *E-DCH TDD Information 7.68Mcps* IE includes the *E-DCH Power Offset for Scheduling Info* IE, then the DRNS shall use this value as a power offset for the transmission of scheduling information without any MAC-d PDUs.]

[TDD- If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH TDD Information To Modify* IE, then:]

- [TDD- If the *E-DCH TDD Information To Modify* IE contains a *E-DCH MAC-d Flow Specific Information* IE which includes the *Allocation/Retention Priority* IE, the DRNS shall apply the new Allocation/Retention Priority to this E-DCH in the new configuration according to Annex A.]
 - [TDD- If the *E-DCH TDD Information To Modify* IE contains a *TNL QoS* IE for an E-DCH MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink for the related MAC-d flow.]
- [TDD- If the *E-DCH TDD Information To Modify* IE includes the *Maximum Number of Retransmissions for E-DCH* IE for an E-DCH MAC-d flow then the DRNS shall use this information to report if the maximum number of retransmissions has been exceeded.]
- [1.28Mcps TDD If the *E-DCH TDD Information To Modify* IE includes the *E-DCH MAC-d Flow Retransmission Timer* IE for an E-DCH MAC-d flow then the DRNS shall use this information to set the retransmission timer.]
- [TDD– If the *TNL QoS* IE is included in the *E-DCH TDD Information to Modify* IE for an E-DCH MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink for the related MAC-d flow.]
- [TDD- If the *E-DCH TDD Information To Modify* IE includes the *E-DCH HARQ Power Offset TDD* IE for an E-DCH MAC-d flow the DRNS shall use this new power offset value.]
- [TDD- If the *E-DCH TDD Information To Modify* IE includes the *E-DCH MAC-d Flow Multiplexing List* IE for an E-DCH MAC-d flow the DRNS shall use this information for the related resource allocation operation.]
- [TDD- If the *E-DCH TDD Information To Modify* IE contains the *E-DCH Grant Type* IE, the DRNS shall treat the E-DCH MAC-d flow as Scheduled or Non-scheduled accordingly.]
- [TDD- If the *E-DCH TDD Information To Modify* IE includes the *E-DCH Logical Channel To Add* or *E-DCH Logical Channel To Delete* IEs, the DRNS shall use this information to add/delete the indicated logical channels. When a logical channel is deleted, all its associated configuration data shall also removed.]
- [TDD- If the *E-DCH TDD Information To Modify* IE includes the *E-DCH Logical Channel To Modify* IE, the DRNS shall use this information to modify the indicated logical channels:]
 - [TDD If the *E-DCH Logical Channel To Modify* IE includes *Scheduling Priority Indicator* IE, the DRNS shall apply the values in the new configuration.]
 - [TDD If the *E-DCH Logical Channel To Modify* IE includes *Scheduling Information* IE, the DRNS shall apply the values in the new configuration.]
 - [TDD If the *E-DCH Logical Channel To Modify* IE includes *MAC-es Guaranteed Bit Rate* IE, the DRNS shall apply the values in the new configuration.]
 - [TDD If the *E-DCH Logical Channel To Modify* IE includes E-*DCH DDI Value* IE, the DRNS shall apply the values in the new configuration.]
 - [1.28Mcps TDD If the *E-DCH Logical Channel To Modify* IE includes *MAC-es Maximum Bit Rate LC*R IE, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
 - [TDD If the *E-DCH Logical Channel To Modify* IE includes the *Maximum MAC-d PDU Size Extended* IE, the DRNS shall apply the value in the new configuration.]

- [TDD– If the *E-DCH TDD Information To Modify* IE includes the *MAC-e Reset Indicator* IE, then the DRNS shall use this value to determine whether MAC-e (or MAC-i) Reset is performed in the UE for sending the HARQ Failure Indication.]

[1.28Mcps TDD –Multi-Carrier E-DCH Continue:]

[1.28Mcps TDD - If the *Multi-Carrier E-DCH Information Reconf* IE is present in the RADIO LINK RECONFIGURATION PREPARE message and the choice of *Continue*, *Setup or Change* is "Continue", then the current Multi-Carrier E-DCH configuration shall not be changed.]

[1.28Mcps TDD – Multi-Carrier E-DCH Setup:]

[1.28Mcps TDD - If the *Multi-Carrier E-DCH Information Reconf* IE is present in the RADIO LINK RECONFIGURATION PREPARE message and the choice of *Continue, Setup or Change* is "Setup", then the *Multi-Carrier E-DCH Information LCR* IE defines the new configuration and then:]

- [1.28Mcps TDD The DRNS shall use the *Multi-Carrier E-DCH Transport Bearer Mode LCR* IE to decide the transport bearer mode in the new configuration.]
- [1.28Mcps TDD The DRNS shall setup the requested E-DCH resource on the uplink frequecies indicated by the *UARFCN* IE in the *Multi-Carrier E-DCH Information LCR* IE.]

[1.28Mcps TDD – Multi-Carrier E-DCH Change:]

[1.28Mcps TDD - If the *Multi-Carrier E-DCH Information Reconf* IE is present in the RADIO LINK RECONFIGURATION PREPARE message and the choice of *Continue, Setup or Change* is "Change", then: the *Multi-Carrier E-DCH Information LCR* IE defines the new configuration and then:]

- [1.28Mcps TDD If the *UARFCN* IE in the *Multi-Carrier E-DCH Information LCR* IE is different from current configured frequencies, then the DRNS shall setup the E-DCH resources, as requested in the DRNS Communication Context, on the uplink frequecies indicated by the *UARFCN* IE in the *Multi-Carrier E-DCH Information LCR* IE.]
- [1.28Mcps TDD If the *UARFCN* IE in the *Multi-Carrier E-DCH Information LCR* IE is the same as any current configured frequency, then the DRNS shall reconfigure the E-DCH resources, as requested or as configured in the DRNS Communication Context, on the uplink frequecies indicated by the *UARFCN* IE in the *Multi-Carrier E-DCH Information LCR* IE.]

[1.28Mcps TDD - If the *Multi-Carrier E-DCH Information Reconf* IE is present in the RADIO LINK RECONFIGURATION PREPARE message and the choice of *Continue, Setup or Change* is "Change" and the *Removal UL Multi-Carrier info* IE is included, then the DRNS shall remove the corresponding E-DCH configuration on the uplink frequencies indicated by the *UARFCN* IE in the *Removal UL Multi-Carrier info* IE.]

General

If the requested modifications are allowed by the DRNC and the DRNC has successfully reserved the required resources for the new configuration of the Radio Link(s), it shall respond to the SRNC with the RADIO LINK RECONFIGURATION READY message. When this procedure has been completed successfully there exists a Prepared Reconfiguration, as defined in subclause 3.1.

If the RADIO LINK RECONFIGURATION PREPARE message includes the *Transport Layer Address* IE and *Binding ID* IE in the [TDD – *DSCHs To Modify* IE, *DSCHs To Add* IE, *USCHs To Modify* IE, *USCHs To Add* IE], *HS-DSCH Information* IE, *HS-DSCH Information To Modify* IE, *HS-DSCH MAC-d Flows To Add* IE, [FDD – *RL Specific E-DCH Information* IE,] [TDD – *E-DCH MAC-d Flows to Add* IE,] [TDD – *E-DCH TDD Information to Modify* IE,] or in the *RL Specific DCH Information* IEs, the DRNC may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for any Transport Channel [FDD – for which the *Transport Bearer Not Requested Indicator* IE is not included], HS-DSCH MAC-d flow being added or E-DCH MAC-d flow [FDD – for which the *Transport Bearer Not Requested Indicator* IE is not included] being added, or any Transport Channel, HS-DSCH MAC-d flow or E-DCH MAC-d flow being modified for which a new transport bearer was requested with the *Transport Bearer Request Indicator* IE.

The DRNC shall include in the RADIO LINK RECONFIGURATION READY message the *Transport Layer Address* IE and the *Binding ID* IE for any Transport Channel [FDD – for which the *Transport Bearer Not Requested Indicator* IE is not included], HS-DSCH MAC-d flow being added or E-DCH MAC-d flow [FDD – for which the *Transport Bearer Not Requested Indicator* IE is not included] being added, or any Transport Channel [FDD – for which the

Transport Bearer Not Requested Indicator IE was not included], HS-DSCH MAC-d flow or E-DCH MAC-d flow [FDD – for which the Transport Bearer Not Requested Indicator IE was not included] being modified for which a new transport bearer was requested with the Transport Bearer Request Indicator IE. In the case of a set of co-ordinated DCHs requiring a new transport bearer on the Iur interface, the Transport Layer Address IE and the Binding ID IE in the DCH Information Response IE shall be included [FDD – if the Transport Bearer Not Requested Indicator IE is not included for the corresponding DCH,] for only one of the DCHs in the set of co-ordinated DCHs.

[FDD – If the RADIO LINK RECONDIGURATION PREPARE message includes the *Transport Bearer Not Requested Indicator* IE set to "Transport Bearer Shall not be Established" for a DCH or an E-DCH MAC-d flow, then the DRNC shall not establish a transport bearer for the concerned DCH or E-DCH MAC-d flow and shall include the *Transport Bearer Not Setup Indicator* IE for the corresponding DCH or E-DCH MAC-d flow in the RADIO LINK RECONFIGURATION READY message.]

[FDD – If the RADIO LINK RECONDIGURATION PREPARE message includes the *Transport Bearer Not Requested Indicator* IE set to "Transport Bearer may not be Established" for a DCH or an E-DCH MAC-d flow and:]

- [FDD if the DRNC establishes a transport bearer for the concerned DCH or E-DCH MAC-d flow, the DRNC shall include in the RADIO LINK RECONFIGURATION READY message the *Binding ID* IE and *Transport Layer Address* IE for establishment of a transport bearer for the DCH or E-DCH MAC-d flow being established.]
- [FDD if the DRNC does not establish a transport bearer for the concerned DCH or E-DCH MAC-d flow, the DRNC shall include the *Transport Bearer Not Setup Indicator* IE for the corresponding DCH or E-DCH MAC-d flow in the RADIO LINK RECONFIGURATION READY message.]

In the case of a Radio Link being combined with another Radio Link within the DRNS, the *Transport Layer Address* IE and the *Binding ID* IE in the *DCH Information Response* IE shall be included for only one of the combined Radio Links [FDD – if the *Transport Bearer Not Requested Indicator* IE is not included for this DCH of the Radio Link].

[FDD – In the case of an E-DCH RL being combined with another E-DCH RL within the DRNS, the *E-DCH FDD Information Response* IE shall be included only for one of the combined E-DCH RLs.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Additional E-DCH Cell Information RL Reconf Prep* IE, then:]

- [FDD if the *Multicell E-DCH Transport Bearer Mode* IE for an Additional E-DCH to be Setup is set to "Separate Iur Transport Bearer Mode" the DRNS shall use this mode in the new configuration and apply separate transport bearers for the MAC-d flows.]
- [FDD if the *Multicell E-DCH Transport Bearer Mode* IE for an Additional E-DCH to be Setup is set to "UL Flow Multiplexing Mode" the DRNS shall use this mode in the new configuration and multiplex MAC-d flows on the transport bearers.]
- [FDD if Separate Iur Transport Bearer Mode is used in the new configuration, then:]
 - [FDD the DRNS shall follow the rules defined in this procedure for single carrier mode of operation for establishment of the transport bearer for a MAC-d flow, use the *Transport Bearer Not Requested Indicator* IE in the *RL Specific E-DCH Information* IE in the *RL Information* IE and/or the *Transport Bearer Request Indicator* IE in the *E-DCH FDD Information To Modify* IE received for the corresponding Radio Link(s) of the Primary Uplink Frequency to determine the transport bearer configuration in the new configuration for the radio links of the Secondary Uplink Frequency.]
 - [FDD If the Transport Layer Address IE and Binding ID IE is included for an E-DCH MAC-d flow in the Additional E-DCH MAC-d Flows Specific Information IE in the Additional E-DCH RL Specific Information To Setup IE in the Additional E-DCH FDD Setup Information IE in the Additional E-DCH Cell Information Setup IE or in the Additional E-DCH RL Specific Information To Add IE and/or the Additional E-DCH RL Specific Information To Modify IE in the Additional E-DCH Configuration Change Information IE in the Additional E-DCH Cell Information Configuration Change IE, then the DRNS may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for the concerned E-DCH MAC-d flow. If the DRNS establishes a transport bearer for the concerned E-DCH MAC-d flow the DRNS shall, for establishment of the transport bearer, include in the RADIO LINK RECONFIGURATION READY message in the Additional E-DCH Cell Information Response RLReconf IE the Binding ID IE and Transport Layer Address IE in the Additional E-DCH MAC-d Flow Specific Information Response IE in the Additional E-DCH FDD Information Response IE for new E-DCH radio links on the Secondary UL frequency and/or include the Binding ID IE and Transport Layer Address IE in

the *Additional E-DCH MAC-d Flow Specific Information Response* IE in the *Additional Modified E-DCH FDD Information Response* IE for radio links on the Secondary UL frequency that has been modified.]

[1.28Mcps TDD - If the RADIO LINK RECONFIGURATION PREPARE message includes the *Multi-Carrier E-DCH Information Reconf* IE, then:]

- [1.28Mcps TDD If the *Multi-carrier E-DCH Transport Bearer Mode LCR* IE is set to "Separate Iur Transport Bearer Mode" the DRNS shall use this mode in the new configuration and apply separate transport bearers for the MAC-d flows.]
- [1.28Mcps TDD If the *Multi-Carrier E-DCH Transport Bearer Mode LCR* IE is set to "UL Flow Multiplexing Mode" the DRNS shall use this mode in the new configuration and multiplex each MAC-d flow on one transport bearer.]
- [1.28Mcps TDD If the choice of *Continue, Setup or Change* in the the *Multi-Carrier E-DCH Information Reconf* IE is "Setup" and the Separate Iur transport bearer mode is used in the new configuration, or if the choice of *Continue, Setup or Change* in the the *Multi-Carrier E-DCH Information Reconf* IE is "Change" and the Transport Bearer Mode is changed to "Separate Iur Transport Bearer Mode" indicated by *Multi-carrier E-DCH Transport Bearer Mode LCR* IE, then the DRNS shall include the *Binding ID* IE and *Transport Layer Address* IE in the *Multi-Carrier E-DCH Information Response LCR* IE in the RADIO LINK RECONFIGURATION READY message for establishment of a transport bearer for every E-DCH MAC-d flow being established.]
- [1.28Mcps TDD The DRNS shall follow the rules defined in this procedure for single carrier mode of operation for establishment of the transport bearer for a MAC-d flow, use the *Transport Bearer Request Indicator* IE in the *E-DCH TDD Information to Modify* IE received for the corresponding Radio Link to determine the transport bearer configuration in the new configuration for the all Uplink Frequencies.]
- [1.28Mcps TDD If the E-DCH UL flow multiplexing mode is used in the new configuration and if the *Transport Bearer Request Indicator* IE is set to "Bearer Requested", then the DRNS shall include the *Binding ID* IE and *Transport Layer Address* IE in the *E-DCH TDD Information Response 1.28Mcps* IE in the RADIO LINK RECONFIGURATION READY message for establishment of a transport bearer for every E-DCH MAC-d flow being established.]

Any allowed rate for the uplink of a modified DCH provided for the old configuration will not be valid for the new configuration. If the DRNS needs to limit the user rate in the uplink of a DCH due to congestion caused by the UL UTRAN Dynamic Resources (see subclause 9.2.1.79) in the new configuration for a Radio Link, the DRNC shall include in the RADIO LINK RECONFIGURATION READY message the *Allowed UL Rate* IE in the *DCH Information Response* IE for this Radio Link.

Any allowed rate for the downlink of a modified DCH provided for the old configuration will not be valid for the new configuration. If the DRNS needs to limit the user rate in the downlink of a DCH due to congestion caused by the DL UTRAN Dynamic Resources (see subclause 9.2.1.79) in the new configuration for a Radio Link, the DRNC shall include in the RADIO LINK RECONFIGURATION READY message the *Allowed DL Rate* IE in the *DCH Information Response* IE for this Radio Link.

The DRNS decides the maximum and minimum SIR for the uplink of the Radio Link(s) and the DRNC shall include in the RADIO LINK RECONFIGURATION READY message the *Maximum Uplink SIR* IE and *Minimum Uplink SIR* IE for each Radio Link when these values are changed.

[FDD – If the DL TX power upper or lower limit has been re-configured, the DRNC shall include in the RADIO LINK RECONFIGURATION READY message the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE respectively. The DRNS shall not transmit with a higher power than indicated by the *Maximum DL TX Power* IE or lower than indicated by the *Minimum DL TX Power* IE on any DL DPCH or on the F-DPCH of the RL –except, if the UE Context is configured to use DPCH in the downlink, during compressed mode, when the δP_{curr} , as described in TS 25.214 [10] subclause 5.2.1.3, shall be added to the maximum DL power for the associated compressed frame.]

[3.84 Mcps TDD and 7.68 Mcps TDD – If the DL TX power upper or lower limit has been re-configured, the DRNC shall include the new value(s) in the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the RADIO LINK RECONFIGURATION READY message. If the maximum or minimum power needs to be different for particular DCH type CCTrCHs, the DRNC shall include the new value(s) for that CCTrCH in the *CCTrCH Maximum DL TX Power* IE and *CCTrCH Minimum DL TX Power*. The DRNS shall not transmit with a higher power than indicated by the appropriate *Maximum DL TX Power* IE/CCTrCH Maximum DL TX Power IE or lower than indicated by the Aliminum DL TX Power IE/CCTrCH Minimum DL TX Power IE on any DL DPCH within each CCTrCH of the RL.]

[1.28 Mcps TDD – If the DL TX power upper or lower limit has been re-configured, the DRNC shall include the new value(s) in the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the RADIO LINK RECONFIGURATION READY message. If the maximum or minimum power needs to be different for particular timeslots within a DCH type CCTrCH, the DRNC shall include the new value(s) for that timeslot in the *Maximum DL TX Power* IE and *Minimum DL TX Power* within the *DL Timeslot Information LCR* IE. The DRNS shall not transmit with a higher power than indicated by the appropriate *Maximum DL TX Power* IE or lower than indicated by the appropriate *Minimum DL TX Power* IE on any DL DPCH within each timeslot of the RL.]

[TDD – If the [3.84Mcps TDD and 7.68 Mcps TDD – *DL Time Slot ISCP Info* IE][1.28Mcps TDD – *DL Time Slot ISCP Info LCR* IE] is present, the DRNS should use the indicated values when deciding the Initial DL TX Power.]

[TDD – If the *Primary CCPCH RSCP Delta* IE is included, the DRNS shall assume that the reported value for Primary CCPCH RSCP is in the negative range as per TS 25.123 [24], and the value is equal to the *Primary CCPCH RSCP Delta* IE. If the *Primary CCPCH RSCP Delta* IE is not included and the *Primary CCPCH RSCP* IE is included, the DRNS shall assume that the reported value is in the non-negative range as per TS 25.123 [24], and the value is equal to the *Primary CCPCH RSCP* IE. The DRNS shall use the indicated values when deciding the Initial DL TX Power.]

8.3.4.3 Unsuccessful Operation




Figure 11: Synchronised Radio Link Reconfiguration Preparation procedure, Unsuccessful Operation

If the DRNS cannot reserve the necessary resources for all the new DCHs of a set of co-ordinated DCHs requested to be added, it shall reject the Synchronised Radio Link Reconfiguration Preparation procedure as having failed.

If the requested Synchronised Radio Link Reconfiguration Preparation procedure fails for one or more RLs, the DRNC shall send the RADIO LINK RECONFIGURATION FAILURE message to the SRNC, indicating the reason for failure for each failed radio link in a *Cause* IE.

[FDD – If the MIMO Activation Indicator IE is included and the Power Offset For S-CPICH for MIMO Request Indicator IE is not included in the HS-DSCH FDD Information IE in the HS-DSCH FDD Information IE in the RADIO LINK RECONFIGURATION PREPARE message or MIMO is activated and the power offset for S-CPICH for MIMO Request indicator has not been configured in the new configuration but MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where the Serving HS-DSCH Radio Link is established, the setup of the serving HS-DSCH Radio Link, and/or activation of MIMO, shall be reported as failed and the DRNC shall include in the RADIO LINK RECONFIGURATION FAILURE message the Cause IE.]

Typical cause values are:

Radio Network Layer Causes:

UL Scrambling Code Already in Use;

DL Radio Resources not Available;

UL Radio Resources not Available;

Requested Configuration not Supported;

Number of DL Codes not Supported;

Number of UL Codes not Supported;

Dedicated Transport Channel Type not Supported;

DL Shared Channel Type not Supported;

[TDD – UL Shared Channel Type not Supported;]

[FDD – UL Spreading Factor not Supported;]

[FDD – DL Spreading Factor not Supported;]

CM not Supported;

RL Timing Adjustment not Supported;

E-DCH not supported;

 $[FDD-F\text{-}DPCH\ not\ supported;]$

[FDD – Continuous Packet Connectivity DTX-DRX operation not Supported;]

[FDD – Continuous Packet Connectivity HS-SCCH less operation not Supported;]

[FDD – MIMO not supported;]

[FDD – E-DCH TTI2ms not supported;]

[FDD – Continuous Packet Connectivity DTX-DRX operation not available;]

[FDD – Continuous Packet Connectivity UE DTX Cycle not available;]

[FDD – MIMO not available;]

[FDD – SixteenQAM UL not Supported;]

HS-DSCH MAC-d PDU Size Format not supported;

[FDD – F-DPCH Slot Format operation not supported;]

E-DCH MAC-d PDU Size Format not available;

[FDD – E-DPCCH Power Boosting not supported;]

[FDD - SixtyfourQAM DL and MIMO Combined not available;]

[FDD – Multi Cell operation not available;]

[FDD – Multi Cell operation not supported;]

[FDD – SixtyfourQAM DL and MIMO Combined not supported;]

[1.28Mcps TDD- MIMO not supported;]

[1.28Mcps TDD – MIMO not available;]

[1.28Mcps TDD – SixtyfourQAM DL and MIMO Combined not available;]

[FDD – TX diversity for MIMO UE on DL Control Channels not available;]

[FDD – Single Stream MIMO not supported;]

[FDD – Single Stream MIMO not available;]

[FDD – Multi Cell operation with MIMO not available;]

[FDD – Multi Cell operation with MIMO not supported;]

[FDD – Multi Cell E-DCH Operation not supported;]

[FDD – Multi Cell E-DCH Operation not available;]

[FDD – Multi Cell operation with Single Stream MIMO not available;]

[FDD – Multi Cell operation with Single Stream MIMO not supported;]

[FDD – Cell Specific Tx Diversity Handling For Multi Cell Operation Not Available;]

[FDD – Cell Specific Tx Diversity Handling For Multi Cell Operation Not Supported.]

Miscellaneous Causes:

Control Processing Overload;

Not enough User Plane Processing Resources.

8.3.4.4 Abnormal Conditions

If only a subset of all the DCHs belonging to a set of co-ordinated DCHs is requested to be deleted, the DRNS shall reject the Synchronised Radio Link Reconfiguration Preparation procedure as having failed and shall send the RADIO LINK RECONFIGURATION FAILURE message to the SRNC.

If more than one DCH of a set of co-ordinated DCHs has the *QE-Selector* IE set to "selected" [TDD – or no DCH of a set of co-ordinated DCHs has the *QE-Selector* IE set to "selected"] the DRNS shall reject the Synchronised Radio Link Reconfiguration Preparation procedure and the DRNC shall respond with a RADIO LINK RECONFIGURATION FAILURE message.

If the RADIO LINK RECONFIGURATION PREPARE message includes a *DCHs To Modify* IE or *DCHs To Add* IE with multiple *DCH Specific Info* IEs, and if the DCHs in the *DCHs To Modify* IE or *DCHs To Add* IE do not have the same *Transmission Time Interval* IE in the *Semi-static Transport Format Information* IE, then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

[FDD – If the *RL Information* IE includes the *DL Reference Power* IE, but the power balancing is not active in the indicated RL(s), the DRNS shall reject the Synchronised Radio Link Reconfiguration Preparation procedure as having failed and the DRNC shall respond with the RADIO LINK RECONFIGURATION FAILURE message with the cause value "Power Balancing status not compatible".]

[FDD – If the power balancing is active with the Power Balancing Adjustment Type of the UE Context set to "Common" in the existing RL(s) but the RADIO LINK RECONFIGURATION PREPARE message includes more than one *DL Reference Power* IE, the DRNS shall reject the Synchronised Radio Link Reconfiguration Preparation procedure as having failed and the DRNC shall respond with the RADIO LINK RECONFIGURATION FAILURE message with the cause value "Power Balancing status not compatible".]

If the RADIO LINK RECONFIGURATION PREPARE message contains the *Transport Layer Address* IE or the *Binding ID* IE when establishing a transport bearer for any Transport Channel or HS-DSCH MAC-d flow being added, or any Transport Channel or HS-DSCH MAC-d flow being modified for which a new transport bearer was requested with the *Transport Bearer Request Indicator* IE., and not both are present for a transport bearer intended to be established, the DRNC shall reject the Synchronised Radio Link Reconfiguration Preparation procedure and the DRNC shall respond with a RADIO LINK RECONFIGURATION FAILURE message.

If the RADIO LINK RECONFIGURATION PREPARE message contains any of the *HS-DSCH Information To Modify* IE, *HS-DSCH MAC-d Flows To Add* IE or *HS-DSCH MAC-d Flows To Delete* IE in addition to the *HS-DSCH Information* IE, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If the RADIO LINK RECONFIGURATION PREPARE message contains any of the *HS-DSCH Information To Modify* IE, *HS-DSCH MAC-d Flows To Add* IE, *HS-DSCH MAC-d Flows To Delete* IE or *HS-PDSCH RL ID* IE and the Serving HS-DSCH Radio Link is not in the DRNS, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If the RADIO LINK RECONFIGURATION PREPARE message includes the *HS-DSCH Information* IE and does not include the *HS-PDSCH RL-ID* IE, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If the RADIO LINK RECONFIGURATION PREPARE message includes the *HS-DSCH Information To Modify* IE deleting the last remaining Priority Queue of an HS-DSCH MAC-d Flow, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If the RADIO LINK RECONFIGURATION PREPARE message includes the *HS-PDSCH RL-ID* IE indicating a Radio Link not existing in the UE Context, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If the RADIO LINK RECONFIGURATION PREPARE message contains any of the *HS-DSCH Information* IE, *HS-DSCH Information To Modify* IE, or *HS-DSCH MAC-d Flows To Add* IE and if in the new configuration the Priority Queues associated with the same *HS-DSCH MAC-d Flow ID* IE have the same *Scheduling Priority Indicator* IE value, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If, in the new configuration, the concerned UE Context is configured to use "Indexed MAC-d PDU Size" for an HS-DSCH but there exist a priority queue of the MAC-d flows of the HS-DSCH that is configured to use Maximum MAC-d PDU Size Extended, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If, in the new configuration, the concerned UE Context is configured to use "Flexible MAC-d PDU Size" for an HS-DSCH but there exist a priority queue of the MAC-d flows of the HS-DSCH that is configured to use MAC-d PDU Size Index, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If, in the new configuration, the concerned UE Context is configured to use "Fixed MAC-d PDU Size" for an E-DCH and there exist a Logical Channel of the MAC-d flows of the E-DCH that is configured to use Maximum MAC-d PDU Size Extended, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If, in the new configuration, the concerned UE Context is configured to use "Flexible MAC-d PDU Size" for an E-DCH and there exist a Logical Channel of the MAC-d flows of the E-DCH that is configured to use *MAC-d PDU Size List*, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *F-DPCH Information* IE and the *DL DPCH Information* IE, then the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

If the RADIO LINK RECONFIGURATION PREPARE message includes *HS-DSCH Information* IE and the HS-DSCH is already configured in the UE Context, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

[FDD – If the concerned UE Context is configured to use DPCH in the downlink in the old configuration and if the RADIO LINK RECONFIGURATION PREPARE message includes the *DL DPCH Power Information* IE, then the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the concerned UE Context is configured to use F-DPCH in the downlink in the old configuration and the RADIO LINK RECONFIGURATION PREPARE message includes at least one but not all of the *TFCS* IE, *DL DPCH Slot Format* IE, *TFCI Signalling Mode* IE, *Multiplexing Position* IE, *Limited Power Increase* IE and *DL DPCH Power Information* IE in the *DL DPCH Information* IE, then the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the *E-DCH FDD Information* IE is present in the RADIO LINK RECONFIGURATION PREPARE message, but the *E-DPCH Information* IE is not present or if any of the *Maximum Set of E-DPDCHs* IE, *Puncture Limit* IE, *E-TFCS Information* IE, *E-TTI* IE, *E-DPCCH Power Offset* IE, *E-RGCH 2-Index-Step Threshold* IE, *E-RGCH 3-Index-Step Threshold* IE, *HARQ Info for E-DCH* IE or *HS-DSCH Configured Indicator* IE are not present in the *E-DPCH Information* IE, then the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH RL Indication* IE set to "E-DCH", but no *E-DCH FDD Information* IE, and the UE Context is not configured for E-DCH, then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH FDD Information* IE but no *E-DCH RL Indication* IE set to "E-DCH", then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

If the RADIO LINK RECONFIGURATION PREPARE message contains the *HS-PDSCH RL ID* IE and/or the *Serving E-DCH RL* IE and if both HS-DSCH and E-DCH are configured in the new configuration but the Serving HS-DSCH Radio Link and the Serving E-DCH Radio Link are not in the same cell then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message contains the *HS-PDSCH RL ID* IE and the *E-DPCH Information* IE which includes the *HS-DSCH Configured Indicator* IE set as "HS-DSCH not configured" then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message contains any of the *E-DCH FDD Information To Modify* IE, *E-DCH MAC-d Flows To Add* IE or *E-DCH MAC-d Flows To Delete* IE in addition to the *E-DCH FDD Information* IE, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message contains any of the *E-DCH FDD Information To Modify* IE, *E-DCH MAC-d Flows To Add* IE, *E-DCH MAC-d Flows To Delete* IE and the UE Context is not configured for E-DCH, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *E-DCH FDD Information To Modify* IE deleting the last remaining E-DCH Logical Channel of an E-DCH MAC-d Flow, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes *E-DCH FDD Information* IE and the E-DCH is already configured in the UE Context, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the Fast Reconfiguration IE is included in the RADIO LINK RECONFIGURATION PREPARE message and the UL Scrambling Code IE does not indicate an uplink scrambling code different from the currently used uplink scrambling code the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Continuous Packet Connectivity DTX-DRX Information To Modify* IE in addition to the *Continuous Packet Connectivity DTX-DRX Information* IE, then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Continuous Packet Connectivity HS-SCCH less Deactivate Indicator* IE in addition to the *Continuous Packet Connectivity HS-SCCH less Information* IE, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Continuous Packet Connectivity HS-SCCH less Deactivate Indicator* IE while the Continuous Packet Connectivity HS-SCCH less configuration isn't

configured in the DRNC, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Continuous Packet Connectivity DTX-DRX Information To Modify* IE while the Continuous Packet Connectivity *DTX-DRX* configuration isn't configured in the DRNC, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *DRX Information To Modify* IE in *Continuous Packet Connectivity DTX-DRX Information To Modify* IE while the Continuous Packet Connectivity DRX configuration is not configured in the DRNC, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

If the *DCHs to Modify* IE contains a *DCH Specific Info* IE which includes the *Unidirectional DCH Indicator* IE set to "Uplink DCH only" but no *Transport Format Set* IE for the uplink for this DCH and the DRNC had ignored the configuration of Transport Format Set for uplink, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If the *DCHs to Modify* IE contains a *DCH Specific Info* IE which includes the *Unidirectional DCH Indicator* IE set to "Downlink DCH only" but no *Transport Format Set* IE for the downlink for this DCH and the DRNC had ignored the configuration of Transport Format Set for downlink, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message contains the *Transport Bearer Not Requested Indicator* IE for a DCH or an E-DCH MAC-d flow but does not contain the corresponding *DCH ID* IE and the *Unidirectional DCH indicator* IE set to "Uplink DCH only" for the DCH in *DCH Information To Add* IE or does not contain the corresponding *E-DCH MAC-d Flow ID* IE in *E-DCH MAC-d Flows Information* IE, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the concerned UE Context is configured to apply UL DPCCH Slot Format 4 but is not configured to use F-DPCH, then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the concerned UE Context is configured to apply UL DPCCH Slot Format 0 or 2 and execute Continuous Packet Connectivity DTX-DRX operation, then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the concerned UE Context is configured to apply the "Closed loop mode 1" and if the concerned UE Context is not configured to apply UL DPCCH Slot Format 2 or 3, then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the concerned UE Context is configured to apply MIMO, allowed to apply 64QAM, establish the secondary serving HS-DSCH Radio Link or apply Single Stream MIMO in the new configuration but is not configured to use flexible MAC-d PDU Size, then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Transport Bearer Not Requested Indicator* IE for a DCH in the *RL Specific DCH Information* IE but does not include the *DCH ID* IE for the DCH in the *DCHs to Add* IE, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Transport Bearer Not Requested Indicator* IE for an E-DCH MAC-d flow in the *RL Specific E-DCH Information* IE but does not include the *E-DCH MAC-d flow ID* IE for the E-DCH MAC-d flow in the *E-DCH MAC-d flows Information* IE, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message contains the *Continuous Packet Connectivity DTX-DRX Information* IE but does not contain the *F-DPCH Information* IE and the concerned UE Context is not previously configured to use F-DPCH, then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message]

[FDD – If the concerned UE Context is configured to have the Serving E-DCH Radio Link but there is at least one E-DCH MAC-d flow which the transport bearer is not configured for the Serving E-DCH Radio Link in DRNS, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message includes the *Transport Bearer Not Requested Indicator* IE for a DCH or an E-DCH MAC-d Flow for a specific RL and the specific RL is combined with existing RL which the transport bearer is established for the DCH or the E-DCH MAC-d Flow in the DRNS, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message contains the *Additional HS Cell Information RL Reconf Prep* IE indicating a new secondary serving cell that is not in the same Node B as the serving HS-DSCH cell (or new serving in case of simultaneous serving HS-DSCH cell change), then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message]

If ALCAP is not used, if the concerned UE Context is configured to establish a DCH, an E-DCH MAC-d flow and/or an HS-DSCH MAC-d flow but the RADIO LINK RECONFIGURATION PREPARE message does not include the *Transport Layer Address* IE and the *Binding ID* IE for the DCH, the E-DCH MAC-d flow and/or the HS-DSCH MAC-d flow, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

[TDD – If ALCAP is not used, if the concerned UE Context is configured to establish a DSCH and/or a USCH but the RADIO LINK RECONFIGURATION PREPARE message does not include the *Transport Layer Address* IE and the *Binding ID* IE for the DSCH and/or the USCH, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

If, in the new configuration, there exist a priority queue of the MAC-d flows of the HS-DSCH that is configured to use "Flexible RLC PDU Size" for an HS-DSCH but is not configured to use Maximum MAC-d PDU Size Extended, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If, in the new configuration, the concerned UE Context is configured to use MAC-d PDU Size Index for an HS-DSCH but there exist a priority queue of the MAC-d flows of the HS-DSCH that is configured to use "Flexible RLC PDU Size", the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message contains a MIMO Activation Indicator IE and a Single Stream MIMO Activation Indicator IE in the HS-DSCH FDD Information IE or in the HS-DSCH FDD Secondary Serving Information IE in the Additional HS Cell Information RL Reconf Prep IE, then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the concerned UE Context is configured to apply MIMO and Single Stream MIMO for the HS-DSCH Radio Link or the Secondary Serving Radio link, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message contains the *Additional E-DCH Cell Information RL Reconf Prep* IE and if the *E-DPCH Information* IE is not present or the E-DPCH Information was not configured in the UE Context, then the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message contains the *Additional E-DCH Cell Information RL Reconf Prep* IE and there exist a logical channel for which the *Maximum MAC-d PDU Size Extended* IE in the *E-DCH MAC-d Flows Information* IE in the *E-DCH FDD Information* IE is not present, the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message contains the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE in the *Additional E-DCH Cell Information Setup* IE in the *Additional E-DCH Cell Information RL Reconf Prep* IE and the *C-ID* IE is not included but the RL indicated by the *E-DCH Additional RL ID* IE is not configured in the current UE context as a Secondary Serving HS-DSCH radio link without any configured Additional E-DCH, the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message contains the *Diversity Mode* IE in the *HS-DSCH FDD Secondary Serving Information* IE in the *Additional HS Cell Information RL Reconf Prep* IE and the secondary serving HS-DSCH is already configured in the UE Context, then the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the secondary serving HS-DSCH is not configured in the UE Context and if the RADIO LINK RECONFIGURATION PREPARE message contains in the *HS-DSCH FDD Secondary Serving Information* IE in the *Additional HS Cell Information RL Reconf Prep* IE the *Diversity Mode* IE not set to "None" but not the *Transmit Diversity Indicator* or contains the *Transmit Diversity Indicator* but not the *Diversity Mode* IE not set to "None", then the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION PREPARE message contains the *Diversity Mode* IE in the *Secondary Serving Information To Modify* IE in the *Additional HS Cell Information RL Reconf Prep* IE and the *Non Cell Specific Tx Diversity* IE, the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD - If the RADIO LINK RECONFIGURATION PREPARE message contains the *Additional HS Cell Information RL Reconf Prep* IE and the new configuration contains more than one secondary serving HS-DSCH RL, and all secondary serving HS-DSCH RLs in the new configuration will not be assigned consecutive ordinal numbers starting with the value "1", which are previously assigned to the RL or received in the *Ordinal Number Of Frequency* IE in the *HS-DSCH FDD Secondary Serving Information To Modify* IE, the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD - If the RADIO LINK RECONFIGURATION PREPARE message contains the *Additional HS Cell Information RL Reconf Prep* IE and the new configuration contains more than one secondary serving HS-DSCH RL, the new configuration also contains an Additional E-DCH Serving Radio Link and the secondary serving HS-DSCH Radio link, which is configured in the same cell as the Additional E-DCH Serving Radio Link does not have Ordinal Number Of Frequency value "1", the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

8.3.5 Synchronised Radio Link Reconfiguration Commit

8.3.5.1 General

This procedure is used to order the DRNS to switch to the new configuration for the Radio Link(s) within the DRNS, previously prepared by the Synchronised Radio Link Reconfiguration Preparation procedure.

This procedure shall use the signalling bearer connection for the relevant UE Context.

8.3.5.2 Successful Operation



Figure 12: Synchronised Radio Link Reconfiguration Commit procedure, Successful Operation

The DRNS shall switch to the new configuration previously prepared by the Synchronised Radio Link Reconfiguration Preparation procedure at the "configuration switching point" occurring:

- [TDD at the next coming CFN with a value equal to the value requested by the SRNC in the *CFN* IE (see TS 25.402 [17] subclause 9.4) when receiving the RADIO LINK RECONFIGURATION COMMIT message from the SRNC.]
- [FDD if the *Fast Reconfiguration* IE is not included in the RADIO LINK RECONFIGURATION COMMIT message at the next coming CFN with a value equal to the value requested by the SRNC in the *CFN* IE (see TS 25.402 [17] subclause 9.4) when receiving the RADIO LINK RECONFIGURATION COMMIT message from the SRNC.]
- [FDD if the Fast Reconfiguration IE is included in the RADIO LINK RECONFIGURATION COMMIT message as soon as the DRNS detects that the UE uses the new configuration in the uplink (e.g. the NodeB indicates that the UE uses the new scrambling code used for the uplink by sending the RADIO LINK RESTORATION message). In order to limit the period for the detection in the DRNS the CFN in the RADIO LINK RECONFIGURATION COMMIT message indicates the earliest possible time instant at which the UE might use the new configuration.]

[FDD – If the *Active Pattern Sequence Information* IE is included in the RADIO LINK RECONFIGURATION COMMIT message, the *CM Configuration Change CFN* IE in the *Active Pattern Sequence Information* IE shall be ignored by the DRNS.]

[FDD – If the *Active Pattern Sequence Information* IE is not included in the RADIO LINK RECONFIGURATION COMMIT message and a new Compressed Mode Configuration exists in the prepared configuration, the DRNS shall behave as if an *Active Pattern Sequence Information* IE with an empty *Transmission Gap Pattern Sequence Status* IE was included.]

When this procedure has been completed the Prepared Reconfiguration does not exist any more, see subclause 3.1.

In the case of a Transport Channel or MAC-d flow modification for which a new transport bearer was requested and established, the switch to the new transport bearer shall also take place at the configuration switching point (defined above) indicated CFN.

The detailed frame protocol handling during transport bearer replacement is described in TS 25.427 [4], subclause 5.10.1, and in TS 25.425 [32], subclauses 5.3.1 and 5.3.2.

[FDD – If the RADIO LINK RECONFIGURATION COMMIT includes the *Active Pattern Sequence Information* IE, the DRNS shall deactivate all the ongoing Transmission Gap Pattern Sequences at the configuration switching point (defined above). From that moment on all Transmission Gap Pattern Sequences included in *Transmission Gap Pattern Sequence Status* IE repetitions shall be started when the indicated *TGCFN* IE elapses. The *CFN* IE and *TGCFN* IE for each sequence refer to the next coming CFN with that value. If the values of the *CFN* IE and the *TGCFN* IE are equal, the concerned Transmission Gap Pattern Sequence shall be started immediately at the CFN with a value equal to the value received in the *CFN* IE.]

[FDD – If the RADIO LINK RECONFIGURATION COMMIT message includes the *Active Pattern Sequence Information* IE and the concerned UE Context is configured to use F-DPCH in the downlink, the DRNS shall ignore, when activating the Transmission Gap Pattern Sequence(s), the downlink compressed mode method information, if existing, for the concerned Transmission Gap Pattern Sequence(s) in the Compressed Mode Configuration.]

[FDD - If the RADIO LINK RECONFIGURATION COMMIT message includes the *Affected HS-DSCH serving cell List* IE in the *Active Pattern Sequence Information* IE, the concerned Transmission Gap Pattern Sequence shall be applied to HS-DSCH serving cells associated with *C-ID* IE included in *Affected HS-DSCH serving cell List* IE. Otherwise the concerned Transmission Gap Pattern Sequence shall be applied to all the configured serving cells.]

8.3.5.3 Abnormal Conditions

If a new transport bearer is required for the new configuration and it is not available at the requested configuration switching point (defined in sub-clause 8.3.3.2), the DRNS shall initiate the Radio Link Failure procedure.

[FDD – If the Fast Reconfiguration IE is included in the RADIO LINK RECONFIGURATION COMMIT message and the DRNC did not include the Fast ReconfigurationPermission IE in the RADIO LINK RECONFIGURATION READY message, the DRNC shall initiate the Radio Link Failure procedure.]

[FDD - If the RADIO LINK RECONFIGURATION COMMIT message contains the *Affected HS-DSCH serving cell List* IE in the *Active Pattern Sequence Information* IE and the Transmission Gap Pattern Sequence for affected HS-DSCH Serving Cells is activated on the HS-DSCH Primary Serving Cell but not for all the other serving cells, the DRNS shall initiate the Radio Link Failure procedure with the cause value "Invalid CM Settings".]

8.3.6 Synchronised Radio Link Reconfiguration Cancellation

8.3.6.1 General

This procedure is used to order the DRNS to release the new configuration for the Radio Link(s) within the DRNS, previously prepared by the Synchronised Radio Link Reconfiguration Preparation procedure.

This procedure shall use the signalling bearer connection for the relevant UE Context.

8.3.6.2 Successful Operation



Figure 13: Synchronised Radio Link Reconfiguration Cancellation procedure, Successful Operation

Upon receipt of the RADIO LINK RECONFIGURATION CANCEL message from the SRNC, the DRNS shall release the new configuration ([FDD – including the new Transmission Gap Pattern Sequence parameters (if existing)]) previously prepared by the Synchronised RL Reconfiguration Preparation procedure and continue using the old configuration. When this procedure has been completed the Prepared Reconfiguration does not exist any more, see subclause 3.1.

8.3.6.3 Abnormal Conditions

-

8.3.7 Unsynchronised Radio Link Reconfiguration

8.3.7.1 General

The Unsynchronised Radio Link Reconfiguration procedure is used to reconfigure Radio Link(s) related to one UE-UTRAN connection within a DRNS.

The procedure is used when there is no need to synchronise the time of the switching from the old to the new radio link configuration in the cells used by the UE-UTRAN connection within the DRNS.

This procedure shall use the signalling bearer connection for the relevant UE Context.

The Unsynchronised Radio Link Reconfiguration procedure shall not be initiated if a Prepared Reconfiguration exists, as defined in subclause 3.1.

8.3.7.2 Successful Operation




Figure 14: Unsynchronised Radio Link Reconfiguration procedure, Successful Operation

The Unsynchronised Radio Link Reconfiguration procedure is initiated by the SRNC by sending the RADIO LINK RECONFIGURATION REQUEST message to the DRNC.

Upon receipt, the DRNS shall modify the configuration of the Radio Link(s) according to the parameters given in the message. Unless specified below, the meaning of parameters is specified in other specifications.

If the RADIO LINK RECONFIGURATION REQUEST message includes the *Allowed Queuing Time* IE the DRNS may queue the request the time corresponding to the value of the *Allowed Queuing Time* IE before starting to execute the request.

The DRNS shall prioritise resource allocation for the RL to be modified according to Annex A.

If the *UE Aggregate Maximum Bit Rate* IE is contained in the RADIO LINK RECONFIGURATION REQUEST message, the DRNS shall, if supported, store the received UE Aggregate Maximum Bit Rate parameters to control the aggregate data rate of non GBR traffic for this UE.

DCH Modification:

If the RADIO LINK RECONFIGURATION REQUEST message includes any *DCHs To Modify* IEs, then the DRNS shall treat them as follows:

- If the *DCHs To Modify* IE includes multiple *DCH Specific Info* IEs, then the DRNS shall treat the DCHs as a set of co-ordinated DCHs. The DRNS shall include these DCHs in the new configuration only if it can include all of them in the new configuration.
- If the *DCHs To Modify* IE includes the *UL FP Mode* IE for a DCH or a set of co-ordinated DCHs to be modified, the DRNS shall apply the new FP Mode in the Uplink of the user plane for the DCH or the set of co-ordinated DCHs in the new configuration.
- If the *DCHs To Modify* IE includes the *ToAWS* IE for a DCH or a set of co-ordinated DCHs to be modified, the DRNS shall apply the new ToAWS in the user plane for the DCH or the set of co-ordinated DCHs in the new configuration.
- If the *DCHs To Modify* IE includes the *ToAWE* IE for a DCH or a set of co-ordinated DCHs to be modified, the DRNS shall apply the new ToAWE in the user plane for the DCH or the set of co-ordinated DCHs in the new configuration.
- If the *DCHs To Modify* IE contains a *DCH Specific Info* IE which includes a *Transport Format Set* IE for the UL of a DCH to be modified, the DRNS shall apply the new Transport Format Set in the Uplink of this DCH in the new configuration.
- If the *DCHs To Modify* IE contains a *DCH Specific Info* IE which includes a *Transport Format Set* IE for the DL of a DCH to be modified, the DRNS shall apply the new Transport Format Set in the Downlink of this DCH in the new configuration.
- If the *DCHs To Modify* IE contains a *DCH Specific Info* IE which includes the *Frame Handling Priority* IE, the DRNS should store this information for this DCH in the new configuration. The received Frame Handling Priority should be used when prioritising between different frames in the downlink on the radio interface in congestion situations within the DRNS once the new configuration has been activated.
- If the *DCH Specific Info* IE includes the *Traffic Class* IE, the DRNC may use this information to determine the transport bearer characteristics to apply between DRNC and Node B for the related DCH or set of co-ordinated DCHs. The DRNC should ignore the *Traffic Class* IE if the *TrCH Source Statistics Descriptor* IE for this DCH indicates the value "RRC".
- [FDD If the *DCHs to Modify* IE contains a *DCH Specific Info* IE which includes the *Unidirectional DCH indicator* IE set to "Uplink DCH only", the DRNS shall ignore the *Transport Format Set* IE for the downlink for this DCH. As a consequence this DCH is not included as a part of the downlink CCTrCH.]
- [FDD If the *DCHs to Modify* IE contains a *DCH Specific Info* IE which includes the *Unidirectional DCH indicator* IE set to "Downlink DCH only", the DRNS shall ignore the *Transport Format Set* IE for the uplink for this DCH. As a consequence this DCH is not included as a part of the uplink CCTrCH.]
- If the *TNL QoS* IE is included for a DCH or a set of co-ordinated DCHs and if ALCAP is not used, the DRNS may use this information to determine the transport bearer characteristics to apply for the uplink for the related DCH or set of co-ordinated DCHs.
- If the *DCHs To Modify* IE contains a *DCH Specific Info* IE which includes the *Allocation/Retention Priority* IE, the DRNS shall apply the new Allocation/Retention Priority to this DCH in the new configuration according to Annex A.
- [TDD If the *DCHs To Modify* IE contains a *DCH Specific Info* IE which includes the *CCTrCH ID* IE for the UL, the DRNS shall map the DCH onto the referenced UL CCTrCH in the new configuration.]
- [TDD If the *DCHs To Modify* IE contains a *DCH Specific Info* IE which includes the *CCTrCH ID* IE for the DL, the DRNS shall map the DCH onto the referenced DL CCTrCH in the new configuration.]
- If the *DCHs To Modify* IE contains a *DCH Specific Info* IE which includes the *Guaranteed Rate Information* IE, the DRNS shall treat the included IEs according to the following:

- If the *Guaranteed Rate Information* IE includes the *Guaranteed UL Rate* IE, the DRNS shall apply the new Guaranteed Rate in the uplink of this DCH in the new configuration. The DRNS may decide to request the SRNC to limit the user rate in the uplink of the DCH at any point in time after activating the new configuration. The DRNS may request the SRNC to reduce the user rate of the uplink of the DCH below the guaranteed bit rate, however, whenever possible the DRNS should request the SRNC to reduce the user rate between the maximum bit rate and the guaranteed bit rate.
- If the *Guaranteed Rate Information* IE includes the *Guaranteed DL Rate* IE, the DRNS shall apply the new Guaranteed Rate in the downlink of this DCH in the new configuration. The DRNS may decide to request the SRNC to limit the user in the downlink of the DCH at any point in time after activating the new configuration. The DRNS may request the SRNC to reduce the user rate of the downlink of the DCH below the guaranteed bit rate, however, whenever possible the DRNS should request the SRNC to reduce the user rate between the maximum bit rate and the guaranteed bit rate.

DCH Addition:

If the RADIO LINK RECONFIGURATION REQUEST message includes any *DCHs To Add* IEs, then the DRNS shall treat them each as follows:

- The DRNS shall reserve necessary resources for the new configuration of the Radio Link(s) according to the parameters given in the message and include these DCH in the new configuration.
- If the *DCHs To Add* IE includes multiple *DCH Specific Info* IEs then the DRNS shall treat the DCHs in the *DCHs To Add* IE as a set of co-ordinated DCHs. The DRNS shall include these DCHs in the new configuration only if all of them can be in the new configuration.
- If the *DCH Specific Info* IE includes the *Unidirectional DCH Indicator* IE set to "Uplink DCH only", the DRNS shall ignore the *Transport Format Set* IE for the downlink for this DCH. As a consequence this DCH is not included as a part of the downlink CCTrCH.
- If the *DCH Specific Info* IE includes the *Unidirectional DCH Indicator* IE set to "Downlink DCH only", the DRNS shall ignore the *Transport Format Set* IE for the uplink for this DCH. As a consequence this DCH is not included as a part of the uplink CCTrCH.
- [FDD For each DCH which does not belong to a set of co-ordinated DCHs, and which includes a *QE-Selector* IE set to "selected", the DRNS shall use the Transport channel BER from that DCH for the QE in the UL data frames. If no Transport channel BER is available for the selected DCH, the DRNS shall use the Physical channel BER for the QE, TS 25.427 [4]. If the *QE-Selector* IE is set to "non-selected", the DRNS shall use the Physical channel BER for the QE in the UL data frames, TS 25.427 [4].]
- For a set of co-ordinated DCHs, the DRNS shall use the Transport channel BER from the DCH with the *QE-Selector* IE set to "selected" for the QE in the UL data frames, TS 25.427 [4]. [FDD If no Transport channel BER is available for the selected DCH, the DRNS shall use the Physical channel BER for the QE, TS 25.427 [4]. If all DCHs have the *QE-Selector* IE set to "non-selected", the DRNS shall use the Physical channel BER for the QE, TS 25.427 [4].] [TDD If no Transport channel BER is available for the selected DCH, the DRNS shall use 0 for the QE, TS 25.427 [4].]
- The DRNS should store the *Frame Handling Priority* IE received for a DCH to be added in the new configuration. The received Frame Handling Priority should be used when prioritising between different frames in the downlink on the Uu interface in congestion situations within the DRNS once the new configuration has been activated.
- The *Traffic Class* IE may be used to determine the transport bearer characteristics to apply between DRNC and Node B for the related DCH or set of co-ordinated DCHs. The DRNC should ignore the *Traffic Class* IE if the *TrCH Source Statistics Descriptor* IE indicates the value "RRC".
- If the *TNL QoS* IE is included for a DCH or a set of co-ordinated DCHs and if ALCAP is not used, the DRNS may use this information to determine the transport bearer characteristics to apply for the uplink for the related DCH or set of co-ordinated DCHs.
- The DRNS shall use the included *UL FP Mode* IE for a DCH or a set of co-ordinated DCHs to be added as the new FP Mode in the Uplink of the user plane for the DCH or the set of co-ordinated DCHs in the new configuration.

- The DRNS shall use the included *ToAWS* IE for a DCH or a set of co-ordinated DCHs to be added as the new Time of Arrival Window Startpoint in the user plane for the DCH or the set of co-ordinated DCHs in the new configuration.
- The DRNS shall use the included *ToAWE* IE for a DCH or a set of co-ordinated DCHs to be added as the new Time of Arrival Window Endpoint in the user plane for the DCH or the set of co-ordinated DCHs in the new configuration.
- If the *DCH Specific Info* IE includes the *Guaranteed Rate Information* IE, the DRNS shall treat the included IEs according to the following:
 - If the *Guaranteed Rate Information* IE includes the *Guaranteed UL Rate* IE, the DRNS shall apply the new Guaranteed Rate in the uplink of this DCH in the new configuration. The DRNS may decide to request the SRNC to limit the user rate of the uplink of the DCH at any point in time after activating the new configuration. The DRNS may request the SRNC to reduce the user rate of the uplink of the DCH below the guaranteed bit rate, however, whenever possible the DRNS should request the SRNC to reduce the user rate between the maximum bit rate and the guaranteed bit rate. If the *DCH Specific Info* IE in the *DCH Information* IE does not include the *Guaranteed UL Rate* IE, the DRNS shall not limit the user rate of the uplink of the DCH.
 - If the *Guaranteed Rate Information* IE includes the *Guaranteed DL Rate* IE, the DRNS shall apply the new Guaranteed Rate in the downlink of this DCH in the new configuration. The DRNS may decide to request the SRNC to limit the user rate of the downlink of the DCH at any point in time after activating the new configuration. The DRNS may request the SRNC to reduce the user rate of the downlink of the DCH below the guaranteed bit rate, however, whenever possible the DRNS should request the SRNC to reduce the user rate between the maximum bit rate and the guaranteed bit rate. If the *DCH Specific Info* IE in the *DCH Information* IE does not include the *Guaranteed DL Rate* IE, the DRNS shall not limit the user rate of the uplink of the DCH.

DCH Deletion:

If the RADIO LINK RECONFIGURATION REQUEST message includes any *DCHs To Delete* IEs, the DRNS shall not include the referenced DCHs in the new configuration.

If all of the DCHs belonging to a set of co-ordinated DCHs are requested to be deleted, the DRNS shall not include this set of co-ordinated DCHs in the new configuration.

[FDD – Physical Channel Modification:]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes an *UL DPCH Information* IE, then the DRNS shall apply the parameters to the new configuration as follows:]

- [FDD If the *UL DPCH Information* IE includes the *TFCS* IE for the UL, the DRNS shall apply the new TFCS in the Uplink of the new configuration.]
- [FDD If the *UL DPCH Information* IE includes the *UL DPDCH Indicator For E-DCH Operation* IE set to "UL DPDCH not present", the UL DPDCH resources shall be removed from the configuration.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes a *DL DPCH Information* IE, then the DRNS shall apply the parameters to the new configuration as follows:]

- [FDD If the *DL DPCH Information* IE includes the *TFCS* IE for the DL, the DRNS shall apply the new TFCS in the Downlink of the new configuration.]
- [FDD If the *DL DPCH Information* IE includes the *TFCI Signalling Mode* IE for the DL, the DRNS shall apply the new TFCI Signalling Mode in the Downlink of the new configuration.]
- [FDD If the *DL DPCH Information* IE includes the *Limited Power Increase* IE and the IE is set to "Used", the DRNS shall, if supported, use Limited Power Increase according to TS 25.214 [10] subclause 5.2.1 for the inner loop DL power control in the new configuration.]
- [FDD If the *DL DPCH Information* IE includes the *Limited Power Increase* IE and the IE is set to "Not Used", the DRNS shall not use Limited Power Increase for the inner loop DL power control in the new configuration.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Transmission Gap Pattern Sequence Information* IE, the DRNS shall store the new information about the Transmission Gap Pattern Sequences to be used in the new Compressed Mode configuration. Any Transmission Gap Pattern Sequences already existing in the previous Compressed Mode Configuration are replaced by the new sequences once the new Compressed Mode Configuration has been activated. This new Compressed Mode Configuration shall be valid in the DRNS until the next Compressed Mode Configuration is configured in the DRNS or last Radio Link is deleted.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Transmission Gap Pattern Sequence Information* IE, and if the *Downlink Compressed Mode Method* in one or more Transmission Gap Pattern Sequence within the *Transmission Gap Pattern Sequence Information* IE is set to "SF/2", the DRNC shall include the *DL Code Information* IE in the RADIO LINK RECONFIGURATION RESPONSE message, without changing any of the DL Channelisation Codes or DL Scrambling Codes, indicating for each DL Channelisation Code whether the alternative scrambling code shall be used or not.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes an *E-DPCH Information* IE which contains the *E-TFCS Information* IE, the DRNS shall use the *E-TFCS Information* IE for the E-DCH when reserving resources for the uplink of the new configuration. The DRNS shall apply the new TFCS in the uplink of the new configuration. If the *E-TFCS Information* IE contains the *E-DCH Minimum Set E-TFCI Validity Indicator* IE the DRNS shall ignore the value in *E-DCH Minimum Set E-TFCI* IE. If the *E-DCH Minimum Set E-TFCI validity indicator* IE is absent DRNS shall use the value for the related resource allocation operation.]

[FDD – If the *E-TFCS Information* IE in the *E-DPCH Information* IE contains the *E-DPDCH Power Interpolation* IE, the DRNS shall use the value to determine the applicable E-DPDCH power formula defined in TS 25.214 [10]. If the *E-DPDCH Power Interpolation* IE is not present, the DRNS shall use the E-DPDCH power extrapolation formula defined in TS 25.214 [10] if the *E-DCH FDD Information* IE is included in the RADIO LINK RECONFIGURATION REQUEST message.]

FDD – If the *E-TFCS Information* IE in the *E-DPCH Information* IE contains the *E-TFCI Boost Information* IE, the DRNS shall use the information according to TS 25.214 [10]. If the *E-TFCI Boost Information* IE is not present, the DRNS shall use the value "127" in the algorithm defined in TS 25.214 [10] if the *E-DCH FDD Information* IE is included in the RADIO LINK RECONFIGURATION REQUEST message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST includes an *E-DPCH Information* IE which contains the *E-DPCCH Power Offset* IE, the DRNS shall use the value when the new configuration is being used.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST includes an *E-DPCH Information* IE which contains the *E-RGCH 2-Index-Step* IE, the DRNS shall use the value when the new configuration is being used.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST includes an *E-DPCH Information* IE which contains the *E-RGCH 3-Index-Step* IE, the DRNS shall use the value when the new configuration is being used.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST includes an *E-DPCH Information* IE which contains the *HARQ Info for E-DCH* IE, the DRNS shall use the value when the new configuration is being used.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST includes an *E-DPCH Information* IE which contains the *Minimum Reduced E-DPDCH Gain Factor* IE, then the DRNS shall use the value to determine the applicable minimum gain factor ($\beta_{ed,k,reduced,min}$) defined in TS 25.214 [10]. For the case the *Minimum Reduced E-DPDCH Gain Factor* IE is not available for the UE Context, the DRNS may use the default value defined in TS 25.331 [16].

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Continuous Packet Connectivity DTX-DRX Information* IE, then:]

- [FDD The DRNS shall configure the concerned UE Context for Continuous Packet Connectivity DTX operation according to TS 25.214 [10].]
- [FDD If *DRX Information* IE is included in the *Continuous Packet Connectivity DTX-DRX Information* IE, then the DRNS shall configure the concerned UE Context for Continuous Packet Connectivity DRX operation according to TS 25.214 [10].]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Continuous Packet Connectivity DTX-DRX Information To Modify* IE, then:]

- [FDD – If the *UE DTX DRX Offset* IE is included in the *Continuous Packet Connectivity DTX-DRX Information To Modify* IE, then the DRNS shall apply the indicated Offset in *UE DTX DRX Cycle* IE in the new configuration.]

- [FDD If the *Enabling Delay* IE is included in the *Continuous Packet Connectivity DTX-DRX Information To Modify* IE, then the DRNS shall use this value to determine the beginning of uplink transmission in the new configuration according to TS 25.214 [10].]
- [FDD If the *DTX Information To Modify* IE is included in the *Continuous Packet Connectivity DTX-DRX Information To Modify* IE, then the DRNS shall use this information to modify the indicated DTX Information parameter in the new configuration. If the choice of *DTX Information To Modify* IE is "Deactivate", then DRX should be deactived together with DTX.]
- FDD If the *DRX Information To Modify* IE is included in the *Continuous Packet Connectivity DTX-DRX Information To Modify* IE, then the DRNS shall use this information to modify the indicated DRX Information in the new configuration.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Continuous Packet Connectivity HS-SCCH less Information* IE, then:]

- [FDD The DRNS shall configure the Serving HS-DSCH Radio Link indicated by the *HS-PDSCH RL ID* IE for Continuous Packet Connectivity HS-SCCH less operation according to TS 25.214 [10].]
- [FDD The DRNS shall allocate the HS-PDSCH codes needed for HS-SCCH less operation and include the Continuous Packet Connectivity HS-SCCH less Information Response IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If at least one of *HS-PDSCH Second Code Support* IE is set to "True", then the DRNC shall include *HS-PDSCH Second Code Index* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]

[FDD- If the RADIO LINK RECONFIGURATION REQUEST message includes the *Continuous Packet Connectivity HS-SCCH less Deactivate Indicator* IE, then the DRNS shall deactive the Continuous Packet Connectivity HS-SCCH less operation for the HS-DSCH Radio Link.]

[1.28 Mcps TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Continuous Packet Connectivity DRX Information LCR* IE, then the DRNS shall take account into these parameters to decide the DRX operation related parameters and configure the concerned UE Context for DRX operation according to TS 25.224 [22] and include the parameter(s) in the *Continuous Packet Connectivity DRX Information Response LCR* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]

[1.28 Mcps TDD - If the *Inactivity Threshold for UE DRX Cycle Ext* IE is included in the *Continuous Packet Connectivity DRX Information LCR* IE, then the DRNS may use this value to determine the Inactivity Threshold for UE DRX Cycle according to TS 25.224 [22].]

[1.28 Mcps TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Continuous Packet Connectivity DRX Information To Modify LCR* IE, then:]

- [1.28 Mcps TDD If the *UE DTX DRX Offset* IE is included in the *Continuous Packet Connectivity DRX Information To Modify LCR* IE, then the DRNS shall apply the indicated Offset in *UE DTX DRX Cycle* IE in the new configuration.]
- [1.28 Mcps TDD If the *Enabling Delay* IE is included in the *Continuous Packet Connectivity DRX Information To Modify LCR* IE, then the DRNS shall use this value to determine the beginning of uplink transmission in the new configuration according to TS 25.224 [22].]
- [1.28 Mcps TDD If the *DRX Information To Modify* IE is included in the *Continuous Packet Connectivity DRX Information To Modify LCR* IE, then the DRNS shall use this information to modify the indicated DRX Information in the new configuration.]

[1.28 Mcps TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *HS-DSCH Semi-Persistent scheduling Information LCR* IE, then:]

- [1.28 Mcps TDD The DRNS shall configure the Serving HS-DSCH Radio Link indicated by the *HS-PDSCH RL ID* IE for HS-DSCH Semi-Persistent scheduling operation according to TS 25.224 [22].]
- [1.28 Mcps TDD The DRNS shall allocate the HS-SICH information needed for HS-DSCH Semi-Persistent scheduling operation and include the *HS-DSCH Semi-Persistent scheduling Information Response LCR* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]

- [1.28 Mcps TDD – If the HS-DSCH Semi-Persistent Resource Reservation Indicator IE is included in the HS-DSCH Semi-Persistent scheduling Information LCR IE, then the DRNS shall include Allcoated HS-PDSCH Semi-persistent resource IE in the RADIO LINK RECONFIGURATION RESPONSE message.]

[1.28 Mcps TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH Semi-*Persistent scheduling Information LCR IE, then:]

- [1.28 Mcps TDD The DRNS shall configure the Serving E-DCH Radio Link indicated by the *E-DCH Serving RL* IE for E-DCH Semi-Persistent scheduling operation according to TS 25.224 [22].]
- [1.28 Mcps TDD If the *E-DCH Semi-Persistent Resource Reservation Indicator* IE is included in the *E-DCH Semi-Persistent scheduling Information LCR* IE, then the DRNS shall include *Allocated E-DCH Semi-persistent resource* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]

[1.28 Mcps TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *HS-DSCH Semi-Persistent scheduling Information to modify LCR* IE, then:]

- [1.28 Mcps TDD If the *Transport Block Size List* IE or/and *Repetition Period list* IE is/are included in the *HS-DSCH Semi-Persistent scheduling Information to modify LCR* IE, the DRNS shall modify the configuration of Serving HS-DSCH Radio Link indicated by the *HS-PDSCH RL ID* IE for HS-DSCH Semi-Persistent scheduling operation according to TS 25.224 [22].
- [1.28 Mcps TDD The DRNS shall allocate the HS-SICH information needed for HS-DSCH Semi-Persistent scheduling operation and include the *HS-DSCH Semi-Persistent scheduling Information Response LCR* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [1.28 Mcps TDD If the HS-DSCH Semi-Persistent Resource Reservation Indicator IE is included in the HS-DSCH Semi-Persistent scheduling Information to modify LCR IE, then the DRNS shall include Allcoated HS-PDSCH Semi-persistent resource IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [1.28 Mcps TDD If the *HS-DSCH Semi-Persistent scheduling operation Indicator* IE is included in the *HS-DSCH Semi-Persistent scheduling Information to modify LCR* IE, then the DRNS shall apply this information for HS-DSCH Semi-Persistent scheduling operation.]
- [1.28 Mcps TDD If the buffer size for HS-DSCH Semi-Persistent scheduling needs to be modified, then the DRNS shall include the *Buffer Size for HS-DSCH Semi-Persistent scheduling* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [1.28 Mcps TDD If the number of processes for HS-DSCH Semi-Persistent scheduling needs to be modified, then the DRNS shall include the *Number of Processes for HS-DSCH Semi-Persistent scheduling* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]

 $[1.28~{
m Mcps}~{
m TDD}-{
m If}$ the RADIO LINK RECONFIGURATION RQUEST message includes the *E-DCH Semi-Persistent scheduling Information to modify LCR* IE, then:]

- [1.28 Mcps TDD If the *Repetition Period list* IE is included in the *E-DCH Semi-Persistent scheduling Information to modify LCR* IE, the DRNS shall modify the configuration of Serving HS-DSCH Radio Link indicated by the *E-DCH Serving RL* IE for E-DCH Semi-Persistent scheduling operation according to TS 25.224 [22].
- [1.28 Mcps TDD If the *E-DCH Semi-Persistent scheduling Indicator* IE is included in the *E-DCH Semi-Persistent scheduling Information to modify LCR* IE, then the DRNS shall apply this information for E-DCH Semi-Persistent scheduling operation.]
- [1.28 Mcps TDD If the *E-DCH Semi-Persistent Resource Reservation Indicator* IE is included in the *E-DCH Semi-Persistent scheduling Information to modify LCR* IE, then the DRNS shall include *Allocated E-DCH Semi-persistent resource* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]

[1.28 Mcps TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *HS-DSCH Semi-Persistent scheduling Deactivate Indicator LCR* IE, then the DRNS shall deactivate the HS-DSCH Semi-Persistent scheduling operation for the HS-DSCH Radio Link.]

[1.28 Mcps TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH Semi-Persistent scheduling Deactivate Indicator LCR* IE, then the DRNS shall deactivate the E-DCH Semi-Persistent scheduling operation for the E-DCH Radio Link.]

[1.28Mcps TDD - If the RADIO LINK RECONFIGURATION REQUEST message includes the *MU-MIMO Indicator* IE, then:]

- [1.28 Mcps TDD –the DRNS may use the MU-MIMO for the radio link according to the *MU-MIMO Usage Indicator* IE and shall include the *MU-MIMO Information* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [1.28 Mcps TDD If the Standalone Midamble Channel Indicator IE is set to "Used", then the DRNS shall include Standalone Midamble Channel information in the RADIO LINK RECONFIGURATION RESPONSE message. Else, the DRNS shall not include Standalone Midamble Channel information in the RADIO LINK RECONFIGURATION RESPONSE message.]

[TDD - UL/DL CCTrCH Modification]

[TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes any *UL CCTrCH To Modify* IE or *DL CCTrCH To Modify* IE, the DRNS shall reserve necessary resources for the new configuration of the Radio Link(s) according to the parameters given in the message.]

[TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes any *UL CCTrCH Information To Modify* IEs or *DL CCTrCH Information To Modify* IEs which contain a *TFCS* IE, the DRNS shall apply the included *TFCS* IE as the new value(s) to the referenced CCTrCH. Otherwise the DRNS shall continue to apply the previous value(s) specified for this CCTrCH.]

[1.28Mcps TDD – If the *UL CCTrCH To Modify* IE includes *UL SIR Target* IE, the DRNS shall apply this value as the new configuration and use it for the UL inner loop power control according to TS 25.221 [12] and TS 25.224 [22].]

[TDD – UL/DL CCTrCH Deletion]

[TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes any *UL CCTrCH Information To Delete* IEs or *DL CCTrCH Information To Delete* IEs, the DRNS shall not include the referenced CCTrCH in the new configuration.]

DL Power Control:

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *DL Reference Power Information* IE and the power balancing is active, the DRNS shall update the reference power of the power balancing in the indicated RL(s), if updating of power balancing parameters by the RADIO LINK RECONFIGURATION REQUEST message is supported, using the *DL Reference Power Information* IE in the RADIO LINK RECONFIGURATION REQUEST message. The updated reference power shall be used from the next adjustment period.]

[FDD – If updating of power balancing parameters by the RADIO LINK RECONFIGURATION REQUEST message is supported by the DRNS, the DRNC shall include the *DL Power Balancing Updated Indicator* IE in the *RL Information Response* IE for each affected RL in the RADIO LINK RECONFIGURATION RESPONSE message.]

[1.28Mcps TDD – Uplink Synchronisation Parameters LCR:]

[1.28Mcps TDD – If the *Uplink Synchronisation Parameters LCR* IE is present, the DRNC shall use the indicated values of *Uplink synchronisation stepsize* IE and *Uplink synchronisation frequency* IE when evaluating the timing of the UL synchronisation.]

[1.28Mcps TDD – Shared physical channels Synchronisation Detection:]

[1.28Mcps TDD – If HS-PDSCH and E-PUCH are configured but no DPCH is configured for the UE, then the DRNS shall include the *Out-of-sync Detection Window* IE in the *HS-DSCH TDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]

[1.28Mcps TDD – Uplink Timing Advance Control LCR:]

[1.28Mcps TDD – The DRNC shall include the *Uplink Timing Advance Control LCR* IE in the RADIO LINK RECONFIGURATION RESPONSE message, if the Uplink Timing Advance Control parameters have been changed.]

[1.28Mcps TDD – PowerControl GAP:]

[1.28Mcps TDD – If applied in the DRNS, the DRNC may include the *PowerControl GAP* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]

[1.28Mcps TDD – E-UTRAN Inter-RAT measurement:]

[1.28Mcps TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Need for Idle Interval* IE set to "TRUE", if supported, the DRNC shall include the *Idle Interval Information* IE in the RADIO LINK RECONFIGURATION RESPONSE message. If the *Need for Idle Interval* IE is set to "FALSE", the DRNC shall delete the configuration related to E-UTRAN Inter-RAT measurement]

[1.28Mcps TDD – Inter-frequency/ Inter-RAT measurement:]

[1.28Mcps TDD – If the RADIO LINK RECONFIGURATION REQUESTmessage includes the *DCH Measurement Type indicator* IE, if supported, the DRNS shall include the *Measurement purpose* IE and the *Measurement occasion pattern sequence parameters* IE in the *DCH Measurement Occasion Information* IE in the RADIO LINK RECONFIGURATION RESPONSE message to configure the measurement occasion pattern(s) indicated by the *DCH Measurement Type indicator* IE.]

[1.28Mcps TDD - RNTI Allocation Indicator:]

[1.28Mcps TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *RNTI Allocation Indicator* IE, if supported, the DRNS may allocate an E-RNTI and/or an H-RNTI for UE to use in CELL FACH state.]

RL Information:

[FDD. If the UE Context is configured for F-DPCH Slot Format operation, the DRNS shall include the *F-DPCH Slot Format* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]

HS-DSCH Setup:

If the HS-DSCH Information IE is present in the RADIO LINK RECONFIGURATION REQUEST message, then:

- The DRNS shall setup the requested HS-PDSCH resources on the Serving HS-DSCH Radio Link indicated by the *HS-PDSCH RL ID* IE.
- The DRNC shall include the *HARQ Memory Partitioning* IE in the [FDD *HS-DSCH FDD Information Response* IE] [TDD *HS-DSCH TDD Information Response* IE] in the RADIO LINK RECONFIGURATION RESPONSE message. [FDD The *HARQ Memory Partitioning* IE shall either contain the *HARQ Memory Partitioning Information Extension For MIMO* IE or the *Number of Processes* IE set to a value higher than "8", if the *MIMO Activation Indicator* IE is included in the *HS-DSCH Information* IE.] [1.28Mcps TDD– The *HARQ Memory Partitioning* IE shall either contain the *HARQ Memory Partitioning Information Extension For MIMO* IE or the *Number of Processes* IE set to a value higher than "8", if the *MIMO Activation Indicator* IE is included in the *HS-DSCH Information* IE.]
- The DRNC shall allocate an HS-DSCH-RNTI to the UE Context and include the *HS-DSCH-RNTI* IE in the RADIO LINK RECONFIGURATION RESPONSE message.
- The DRNS may use the *Traffic Class* IE for a specific HS-DSCH MAC-d flow to determine the transport bearer characteristics to apply between DRNC and Node B. If *TrCH Source Statistics Descriptor* IE is present with the value "RRC" in the *HS-DSCH MAC-d Flows Information* IE, then the DRNC should ignore the *Traffic Class* IE.
- If the *TNL QoS* IE is included for a MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink between the DRNS and the SRNC for the related MAC-d flow.
- If fields are to be included in the User Plane by the SRNC to handle TNL Congestion Control for HSDPA in the DRNS, then the DRNC shall include the *User Plane Congestion Fields Inclusion* IE in the *HS-DSCH Information Response* IE.
- If the RADIO LINK RECONFIGURATION REQUEST message includes the *MAC-hs Guaranteed Bit Rate* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, then the DRNS shall use this information to optimise MAC-hs scheduling decisions for the related HSDPA Priority Queue.
- If the RADIO LINK RECONFIGURATION REQUEST message includes the *Discard Timer* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, then the DRNS shall use this information to discard out-of-date MAC-hs SDUs from the related HSDPA Priority Queue.

- If the RADIO LINK RECONFIGURATION REQUEST message includes the *Maximum MAC-d PDU Size Extended* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, then the DRNS shall ignore the *SID* IE and *MAC-d PDU Size* IE in the *MAC-d PDU Size Index* IE and use *Maximum MAC-d PDU Size Extended* IE to optimise capacity allocation for the related HSDPA Priority Queue.
- The DRNC shall include the *HS-DSCH Initial Capacity Allocation* IE in the [FDD *HS-DSCH FDD Information Response* IE] [TDD *HS-DSCH TDD Information Response* IE] in the RADIO LINK RECONFIGURATION RESPONSE message for every HS-DSCH MAC-d flow being established, if the DRNS allows the SRNC to start transmission of MAC-d PDUs before the DRNS has allocated capacity on user plane as described in TS 25.425 [32]. If RADIO LINK RECONFIGURATION REQUESTmessage includes *HS-DSCH MAC-d PDU Size Format* IE in the *HS-DSCH Information* IE set to "Flexible MAC-d PDU Size", then DRNC shall only set in the *HS-DSCH Initial Capacity Allocation* IE the values for the peer of *Scheduling Priority Indicator* IE and *Maximum MAC-d PDU Size Extended* IE to the values of the corresponding peer I in RADIO LINK RECONFIGURATION REQUEST in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE for a Priority Queue including *Scheduling Priority Indicator* IE and *Maximum MAC-d PDU Size Extended* IE.
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *HS-SCCH Power Offset* IE in the *HS-DSCH Information* IE, then the DRNS may use this value to determine the HS-SCCH power. The HS-SCCH Power Offset should be applied for any HS-SCCH transmission to this UE.]
- [FDD The DRNS shall allocate HS-SCCH codes corresponding to the HS-DSCH and the DRNC shall include the *HS-SCCH Specific Information Response* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [TDD The DRNS shall allocate HS-SCCH parameters corresponding to the HS-DSCH and the DRNC shall include the [3.84Mcps TDD *HS-SCCH Specific Information Response* IE] [1.28Mcps TDD *HS-SCCH Specific Information Response LCR* IE] [7.68Mcps TDD *HS-SCCH Specific Information Response* 7.68Mcps IE] in the *HS-DSCH TDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD The DRNC shall include the *HS-PDSCH And HS-SCCH Scrambling Code* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the HARQ Preamble Mode IE in the HS-DSCH Information IE, then the DRNS shall use the indicated HARQ Preamble Mode as described in TS 25.214 [10], if HS-DPCCH ACK/NACK preamble and postamble is supported. Then, in this case, if the mode 1 is applied, the DRNC shall include the HARQ Preamble Mode Activation Indicator IE in the HS-DSCH Information Response IE in the RADIO LINK RECONFIGURATION RESPONSE message. If the HARQ Preamble Mode IE is not included or if the mode 0 is applied, then the DRNC shall not include the HARQ Preamble Mode Activation Indicator IE in the HS-DSCH Information Response IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- If the RADIO LINK RECONFIGURATION REQUEST message includes the *HS-DSCH MAC-d PDU Size Format* IE in the *HS-DSCH Information* IE, then the DRNS shall use the indicated format in user plane frame structure for HS-DSCH channels (TS 25.425 [32]) and MAC-hs (TS 25.321 [41]).
- [FDD The DRNC shall include the *Measurement Power Offset* IE in the *HS-DSCH Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the MIMO Activation Indicator IE is included in the HS-DSCH FDD Information IE, then]
 - [FDD The DRNS shall activate the MIMO mode for the HS-DSCH Radio Link.]
 - [FDD The DRNS shall decide the pilot configuration and the UE reporting configuration (N/M ratio) according to TS 25.214 [10] for MIMO and include the *MIMO Information Response* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
 - [FDD If the *Power Offset For S-CPICH for MIMO Request Indicator* IE is included, the DRNC shall, if supported and MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where the Serving HS-DSCH Radio Link is established, include the *Power Offset For S-CPICH for MIMO* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message. If zero power offset the DRNC may include the *Power Offset For S-CPICH for MIMO* IE.]

- [1.28 Mcps TDD If the MIMO Activation Indicator IE is included in the HS-DSCH TDD Information IE, then]
 - [1.28 Mcps TDD The DRNS shall activate the MIMO mode for the HS-DSCH Radio Link.]
 - [1.28 Mcps TDD The DRNS shall decide the SF mode for HS-PDSCH dual stream and include the *MIMO SF Mode for HS-PDSCH dual stream* IE in the *HS-DSCH TDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Information IE, then the DRNS may if the value is set to "allowed" use 64 QAM for the HS-DSCH Radio Link, and the DRNS shall include the SixtyfourQAM DL Usage Indicator IE in the HS-DSCH FDD Information Response IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the *Sixtyfour QAM Usage Allowed Indicator* IE is included in the *HS-DSCH FDD Information* IE with value set to "not allowed", then the DRNS shall not use 64 QAM for the HS-DSCH Radio Link.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *HS-DSCH MAC-d PDU Size Format* IE set to "Flexible MAC-d PDU Size" and if Sixtyfour QAM will not be used, the DRNS shall include the *HS-DSCH TB Size Table Indicator* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message if it decides to use the octet aligned table defined in TS 25.321 [41] for HS-DSCH Transport Block Size signalling.]
- [FDD If the *UE with enhanced HS-SCCH support indicator* IE is included in the *HS-DSCH FDD Information* IE, then the DRNS may use:]
 - [FDD a different HS-SCCH in consecutive TTIs for this UE]
 - [FDD HS-SCCH orders for the case of HS-SCCH-less operation to this UE]
- [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH FDD Information* IE the DRNS may use the supported HSDPA functions for this UE.]
- [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH FDD Information* IE with the bit *UE DTXDRX related HS-SCCH orders uniform behavior indicator* set to 0, then the DRNS shall, if supported, include the *Support of dynamic DTXDRX related HS-SCCH order* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If secondary serving HS-DSCH is applied also in the new configuration, then any changes related to parameters that are common for both the serving and the secondary serving HS-DSCH should be applied also for the secondary serving HS-DSCH.]
- If the RADIO LINK RECONFIGURATION REQUEST message includes *DL RLC PDU Size Format* IE for a Priority Queue in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, the *DL RLC PDU Size Format* IE may be used by the DRNS to determine the allocated capacity on user plane as described in TS 25.425 [32].
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *UE Aggregate Maximum Bit Rate Enforcement Indicator* IE in the *Priority Queue Information* IE in the *HS-DSCH MAC-d Flows Information* IE in the *HS-DSCH Information* IE, the DRNS shall, if supported, consider the data of the related HSDPA Priority Queue for UE Aggregate Maximum Bit Rate Enforcement.]
- [FDD If the *Single Stream MIMO Activation Indicator* IE is included in the *HS-DSCH FDD Information* IE, then the DRNS shall activate the Single Stream MIMO for the HS-DSCH Radio Link.]
- [1.28 Mcps TDD If the *UE TS0 Capability LCR* IE is included in the *HS-DSCH TDD Information* IE, then the DRNC may include the *TS0 HS-PDSCH Indication LCR* IE in the RADIO LINK RECONFIGURATION RESPONSE message if HS-PDSCH resources could be allocated on TS0 for the UE.]

[FDD – Secondary Serving HS-DSCH Setup:]

[FDD – If the *C-ID* IE is present in the RADIO LINK RECONFIGURATION REQUEST message, no secondary serving HS-DSCH Radio Link(s) has been configured in the DRNS or if the new configuration contains more than one secondary serving HS-DSCH Radio Link, then if the *Ordinal Number Of Frequency* IEs, in the *HS-DSCH FDD Secondary Serving Information* IE or in the *HS-DSCH FDD Secondary Serving Information To ModifyUnsynchronised*

IE for each instance of the *Additional HS Cell Information RL Reconf Req* IE, indicate that new secondary serving HS-DSCH Radio Link(s) shall be setup, then:]

- [FDD The DRNS shall setup the requested HS-PDSCH resources on the secondary serving HS-DSCH Radio Link indicated by the *HS-PDSCH RL ID* IE. Non cell specific secondary serving Radio Link and non cell specific secondary serving HS-DSCH parameters take the same values as for the serving HS-DSCH cell.]
- [FDD The DRNC shall allocate an HS-DSCH-RNTI to the UE Context and include the *HS-DSCH-RNTI* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *HS-SCCH Power Offset* IE in the *HS-DSCH FDD Secondary Serving Information* IE, then the DRNS may use this value to determine the HS-SCCH power. The HS-SCCH Power Offset should be applied for any secondary serving HS-SCCH transmission to this UE.]
- [FDD The DRNS shall allocate HS-SCCH codes corresponding to the secondary serving HS-DSCH and the DRNC shall include the *HS-SCCH Specific Secondary Serving Information Response* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the Additional HS Cell Information Response IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD The DRNC shall include the *HS-PDSCH And HS-SCCH Scrambling Code* IE in the HS-*DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD The DRNC shall include the *Measurement Power Offset* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the *MIMO Activation Indicator* IE is included in the *HS-DSCH FDD Secondary Serving Information* IE, then the DRNS shall activate the MIMO mode for the secondary serving HS-DSCH Radio Link and the DRNS shall decide the pilot configuration and the UE reporting configuration (N/M ratio) according to TS 25.214 [10] for MIMO and include the *MIMO Information Response* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the Power Offset For S-CPICH for MIMO Request Indicator IE is included, the DRNC shall, if supported and MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where the Secondary Serving HS-DSCH Radio Link is established, include the Power Offset For S-CPICH for MIMO IE in the HS-DSCH FDD Secondary Serving Information Response IE in the RADIO LINK RECONFIGURATION RESPONSE message. If zero power offset the DRNC may include the Power Offset For S-CPICH for MIMO IE.]
- [FDD If the *Single Stream MIMO Activation Indicator* IE is included in the *HS-DSCH FDD Secondary Serving Information* IE, then the DRNS shall activate the Single Stream MIMO mode for the secondary serving HS-DSCH Radio Link.]
- [FDD If the *Ordinal Number Of Frequency* IE is included in the *HS-DSCH FDD Secondary Serving Information* IE, and the new configuration contains more than one secondary serving HS-DSCH Radio Link, then the DRNS shall use this value in the physical layer.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Secondary Serving Information IE, then the DRNS may if the value is set to "allowed" use 64 QAM for the secondary serving HS-DSCH Radio Link, and the DRNS shall include the SixtyfourQAM DL Usage Indicator IE in the HS-DSCH FDD Secondary Serving Information Response IE in the Additional HS Cell Information Response IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Secondary Serving Information IE with value set to "not allowed", then the DRNS shall not use 64 QAM for the secondary serving HS-DSCH Radio Link.]
- [FDD If, in the new configuration, the UE context is configured not to use Sixtyfour QAM for the secondary serving HS-DSCH, the DRNS shall include the *HS-DSCH TB Size Table Indicator* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO

LINK RECONFIGURATION RESPONSE message if it decides to use the octet aligned table defined in TS 25.321 [41] for secondary serving HS-DSCH Transport Block Size signalling.]

Intra-DRNS Serving HS-DSCH Radio Link Change:

If the RADIO LINK RECONFIGURATION REQUEST message includes the *HS-PDSCH RL ID* IE, this indicates the new Serving HS-DSCH Radio Link:

- The DRNS shall release the HS-PDSCH resources on the old Serving HS-DSCH Radio Link and setup the HS-PDSCH resources on the new Serving HS-DSCH Radio Link.
- If fields are to be included in the User Plane by the SRNC to handle TNL Congestion Control for HSDPA in the DRNS, then the DRNC shall include the *User Plane Congestion Fields Inclusion* IE in the *HS-DSCH Information Response* IE.
- The DRNC may include the *HARQ Memory Partitioning* IE in the [FDD *HS-DSCH FDD Information Response* IE] [TDD *HS-DSCH TDD Information Response* IE] in the RADIO LINK RECONFIGURATION RESPONSE message. [FDD The *HARQ Memory Partitioning* IE may contain the *HARQ Memory Partitioning Information Extension For MIMO* IE.] [1.28Mcps TDD– The *HARQ Memory Partitioning* IE may contain the *HARQ Memory Partitioning Information Extension For MIMO* IE.]
- The DRNC shall allocate a new HS-DSCH-RNTI to the UE Context and include the *HS-DSCH-RNTI* IE in the RADIO LINK RECONFIGURATION RESPONSE message.
- If a reset of the MAC-hs is not required the DRNS shall include the *MAC-hs Reset Indicator* IE in the RADIO LINK RECONFIGURATION RESPONSE message.
- [FDD The DRNC shall include the *Measurement Power Offset* IE in the *HS-DSCH Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD The DRNS shall allocate HS-SCCH codes corresponding to the HS-DSCH and the DRNC shall include the *HS-SCCH Specific Information Response* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [TDD The DRNS shall allocate HS-SCCH parameters corresponding to the HS-DSCH and the DRNC shall include the [3.84Mcps TDD HS-SCCH Specific Information Response IE] [1.28Mcps TDD HS-SCCH Specific Information Response 7.68 Mcps IE] in the HS-DSCH TDD Information Response IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [TDD The DRNC shall include the [3.84 Mcps TDD *HS-PDSCH Timeslot Specific Information* IE] [1.28 Mcps TDD *HS-PDSCH Timeslot Specific Information LCR* IE] [7.68 Mcps TDD *HS-PDSCH Timeslot Specific Information 7.68 Mcps* IE]in the *HS-DSCH Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD The DRNC shall include the *HS-PDSCH And HS-SCCH Scrambling Code* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- The DRNC may include the *Transport Layer Address* IE and the *Binding ID* IE for HS-DSCH MAC-d flow in the [FDD *HS-DSCH FDD Information Response* IE] [TDD *HS-DSCH TDD Information Response* IE] in the RADIO LINK RECONFIGURATION RESPONSE message.
- If the *TNL QoS* IE is included for a MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink between the DRNS and the SRNC for the related MAC-d flow.
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH Information To Modify Unsynchronised IE and the value is set to "allowed" or if HS-DSCH Information To Modify Unsynchronized IE is not included and the UE Context is configured with Sixtyfour QAM allowed for the serving HS-DSCH Radio Link and not used in the current configuration and then if the DRNS decides to use 64 QAM in the new configuration, then it shall include the SixtyfourQAM DL Usage Indicator IE in the HS-DSCH FDD Information Response IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If MAC-ehs is applied in the new configuration, and if Sixtyfour QAM will not be used, the DRNS shall include the *HS-DSCH TB Size Table Indicator* IE in the *HS-DSCH FDD Information Response* IE in the RADIO

LINK RECONFIGURATION RESPONSE message if it decides to use the octet aligned table defined in TS 25.321 [41] for HS-DSCH Transport Block Size signalling.]

- [FDD – If the power offset for S-CPICH for MIMO Request indicator and MIMO activation indicator have been configured in the new configuration and MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where the Serving HS-DSCH Radio Link is established, the DRNC shall include the *Power Offset For S-CPICH for MIMO* IE in the HS-DSCH FDD Information Response IE in the RADIO LINK RECONFIGURATION RESPONSE message. If zero power offset the DRNC may include the *Power Offset For S-CPICH for MIMO* IE.]

[FDD – Intra-DRNS Secondary Serving HS-DSCH Radio Link Change:]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *C-ID* IE in the *Additional HS Cell Information RL Reconf Req* IE, one or more secondary serving HS-DSCH Radio Link(s) has been configured in the DRNS and if the new configuration contains more than one secondary serving HS-DSCH Radio Link, then if the *Ordinal Number Of Frequency* IEs, in the *HS-DSCH FDD Secondary Serving Information* IE for each instance of the *Additional HS Cell Information RL Reconf Req* IE, indicate that existing secondary serving HS-DSCH Radio Links shall be subject to intra-DRNS secondary serving HS-DSCH Radio Link change, then the *HS-PDSCH RL ID* IE indicates the new Serving HS-DSCH Radio Link:]

- [FDD The DRNS shall release the HS-PDSCH resources on the old secondary serving HS-DSCH Radio Link and setup the HS-PDSCH resources on the new secondary serving HS-DSCH Radio Link. The DRNS shall remove the old secondary serving HS-PDSCH Radio Link if no E-DCH resources are allocated to the RL. Non cell specific secondary serving Radio Link and non cell specific secondary serving HS-DSCH parameters take the same values as for the serving HS-DSCH cell.]
- [FDD The DRNC shall allocate a new HS-DSCH-RNTI to the UE Context and include the *HS-DSCH-RNTI* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD The DRNC shall include the *Measurement Power Offset* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the *Ordinal Number Of Frequency* IE is included in the *HS-DSCH FDD Secondary Serving Information* IE, and the new configuration contains more than one secondary serving HS-DSCH Radio Link, then the DRNS shall use this value in the physical layer.]
- [FDD The DRNS shall allocate HS-SCCH codes corresponding to the secondary serving HS-DSCH and the DRNC shall include the *HS-SCCH Specific Secondary Serving Information Response* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD The DRNC shall include the *HS-PDSCH And HS-SCCH Scrambling Code* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Secondary Serving Information To Modify Unsynchronised IE and the value is set to "allowed" or if HS-DSCH FDD Secondary Serving Information To Modify Unsynchronised IE is not included and the UE context is configured with Sixtyfour QAM allowed for the secondary serving HS-DSCH Radio Link and not used in the current configuration and then if the DRNS decides to use 64 QAM for the new secondary serving HS-DSCH Radio Link, then it shall include the SixtyfourQAM DL Usage Indicator IE in the Additional HS Cell Information Response IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If, in the new configuration, the UE context is configured not to use Sixtyfour QAM for the secondary serving HS-DSCH, the DRNS shall include the *HS-DSCH TB Size Table Indicator* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message if it decides to use the octet aligned table defined in TS 25.321 [41] for secondary serving HS-DSCH Transport Block Size signalling.]
- [FDD If the old and/or new configuration contains more than one Secondary Serving HS-DSCH Radio Link the HS-DSCH FDD Secondary Serving Information IE defines the new secondary serving HS-DSCH configuration in the DRNS to be used on the new secondary serving HS-DSCH Radio Link, and then:]

- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *HS-SCCH Power Offset* IE in the *HS-DSCH FDD Secondary Serving Information* IE, then the DRNS may use this value to determine the HS-SCCH power. The HS-SCCH Power Offset should be applied for any secondary serving HS-SCCH transmission to this UE.]
- [FDD If the MIMO Activation Indicator IE is included in the HS-DSCH FDD Secondary Serving Information IE, then the DRNS shall activate the MIMO mode for the secondary serving HS-DSCH Radio Link and the DRNS shall decide the pilot configuration and the UE reporting configuration (N/M ratio) according to TS 25.214 [10] for MIMO and include the MIMO Information Response IE in the HS-DSCH FDD Secondary Serving Information Response IE in the HS-DSCH Secondary Serving Cell Change Information Response IE in the Additional HS Cell Change Information Response IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the Single Stream MIMO Activation Indicator IE is included in the HS-DSCH FDD Secondary Serving Information IE, then the DRNS shall activate the Single Stream MIMO mode for the secondary serving HS-DSCH Radio Link.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Secondary Serving Information IE, then the DRNS may if the value is set to "allowed" use 64 QAM for the secondary serving HS-DSCH Radio Link, and the DRNS shall include the SixtyfourQAM DL Usage Indicator IE in the HS-DSCH FDD Secondary Serving Information Response IE in the Additional HS Cell Information Response IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Secondary Serving Information IE with value set to "not allowed", then the DRNS shall not use 64 QAM for the secondary serving HS-DSCH Radio Link.]
- [FDD If the power offset for S-CPICH for MIMO Request indicator and MIMO activation indicator have been configured in the new configuration and MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where the Secondary Serving HS-DSCH Radio Link is established, the DRNC shall include the *Power Offset For S-CPICH for MIMO* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message. If zero power offset the DRNC may include the *Power Offset For S-CPICH for MIMO* IE.]

[FDD - Additional Serving E-DCH Radio Link Change to an existing additional non serving E-DCH RL:]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *C-ID* IE in the *Additional HS Cell Information RL Reconf Req* IE and an additional non serving E-DCH RL exists in the cell indicated by the *C-ID* IE, the *HS-PDSCH RL ID* IE in the *HS Cell Information RL Reconf Req* IE indicates the new Additional Serving E-DCH Radio Link.]

- [FDD If the old Additional Serving E-DCH RL is within this DRNS, the DRNS shall de-allocate the E-AGCH resources of the old Additional Serving E-DCH Radio Link at the activation of the new configuration.]
- [FDD The DRNS shall allocate a primary E-RNTI identifier or a secondary E-RNTI identifier or both for
 the new Additional Serving E-DCH Radio Link and include these E-RNTI identifiers along with the
 channelisation code of the corresponding E-AGCH in the E-DCH FDD DL Control Channel Information IE
 in the Additional Modified E-DCH FDD Information Response IE in the Additional E-DCH Cell Information
 Response RLReconf IE in the RADIO LINK RECONFIGURATION RESPONSE message]
- [FDD The DRNS may include the Serving Grant Value IE and Primary/Secondary Grant Selector IE in the E-DCH FDD DL Control Channel Information IE in the Additional Modified E-DCH FDD Information Response IE in the Additional E-DCH Cell Information Response RLReconf IE in the RADIO LINK RECONFIGURATION READY message for the initial grant for the Additional serving E-DCH RL and may include the Default Serving Grant in DTX Cycle 2 IE.]
- [FDD If the E-DCH HARQ process allocation for 2ms TTI for scheduled transmission shall be changed, the DRNS shall allocate resources according to the new/changed configuration and include the new/changed configuration in the *HARQ Process Allocation For 2ms Scheduled Transmission Grant* IE in the *Additional Modified E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response* RLReconf IE in the RADIO LINK RECONFIGURATION READY message.]

FDD – The DRNS may include the *E-RGCH/E-HICH Channelisation Code* IE and/or the *E-HICH Signature Sequence* IE and/or the *E-RGCH Signature Sequence* IE or may alternatively include the *E-RGCH Release Indicator* IE in the *E-DCH FDD DL Control Channel Information* IE in the *Additional Modified E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION RESPONSE message for every E-DCH Radio Link on secondary UL frequency in the DRNS. If the DRNS has no valid data for the *E-RGCH/E-HICH Channelisation Code* IE in the *E-DCH FDD DL Control Channel Information* IE then it shall insert the *E-RGCH and E-HICH Channelisation Code Validity Indicator* IE in the *E-DCH FDD DL Control Channel Information* IE, to indicate that the *E-RGCH/E-HICH Channelisation Code* IE contains invalid data.]

[FDD - Additional Serving E-DCH Radio Link Change to a new RL:]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Additional E-DCH RL Specific Information To Add* IE in the *Additional E-DCH Configuration Change Information* IE in the *Additional E-DCH Cell Information RL Reconf Req* IE and the *C-ID* IE in the *Additional HS Cell Information RL Reconf Req* IE and there is no radio links in the cell indicated by the *C-ID* IE for the UE context, the *HS-PDSCH RL ID* IE indicates the new Additional Serving E-DCH Radio Link on secondary UL frequency.]

- [FDD If the old Additional Serving E-DCH RL is within this DRNS, the DRNS shall de-allocate the E-AGCH resources of the old Additional Serving E-DCH Radio Link at the activation of the new configuration.]
- [FDD In the new configuration the DRNS shall allocate the E-DCH resources for the new additional serving E-DCH Radio Link on the secondary UL frequency. Non cell specific E-DCH parameters shall take the same values as for the corresponding cell of the Primary uplink frequency.]
- [FDD The DRNS shall allocate a primary E-RNTI identifier or a secondary E-RNTI identifier or both for the new Additional Serving E-DCH Radio Link and include these E-RNTI identifiers along with the channelisation code of the corresponding E-AGCH in the *E-DCH FDD DL Control Channel Information* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD The DRNS may include in the *E-DCH FDD DL Control Channel Information* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION RESPONSE message the *Serving Grant Value* IE and *Primary/Secondary Grant Selector* IE for the initial grant for the additional serving E-DCH RL and may include the *Default Serving Grant in DTX Cycle 2* IE]
- [FDD If the E-DCH HARQ process allocation for 2ms TTI for scheduled transmission shall be changed, the DRNS shall allocate resources according to the new/changed configuration and include the new/changed configuration in the *HARQ Process Allocation For 2ms Scheduled Transmission Grant* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]

HS-DSCH Modification:

If the RADIO LINK RECONFIGURATION REQUEST message includes the *HS-DSCH Information To Modify Unsynchronised* IE, then:

- The DRNC shall include the HS-DSCH Initial Capacity Allocation IE for each HS-DSCH MAC-d flow being modified for which the establishment of one or several new Priority Queues was requested, if the DRNS allows the SRNC to start the transmission of MAC-d PDUs for the Priority Queue(s) being established before the DRNS has allocated capacity on user plane as described in TS 25.425 [32]. If UE context is configured to use "Flexible MAC-d PDU Size", then DRNC shall only set in the HS-DSCH Initial Capacity Allocation IE the values for the peer of Scheduling Priority Indicator IE and Maximum MAC-d PDU Size Extended IE to the values of the corresponding peer for the Priority Queue of UE context.
- If the RADIO LINK RECONFIGURATION REQUEST message includes the *Traffic Class* IE in the *HS-DSCH Information To Modify Unsynchronised* IE for a specific HS-DSCH MAC-d flow, the DRNS may use this information to determine the transport bearer characteristics to apply between DRNC and Node B. The DRNC should ignore the *Traffic Class* IE if the *TrCH Source Statistics Descriptor* IE for this specific HS-DSCH MAC-d flow indicates the value "RRC".

- If the *TNL QoS* IE is included for a MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink between the DRNS and the SRNC for the related MAC-d flow.
- If the RADIO LINK RECONFIGURATION REQUEST message includes the *MAC-hs Guaranteed Bit Rate* IE in the *HS-DSCH Information To Modify Unsynchronised* IE, the DRNS shall use this information to optimise MAC-hs scheduling decisions for the related HSDPA Priority Queue.
- If the RADIO LINK RECONFIGURATION REQUEST message includes the *Discard Timer* IE for a Priority Queue in the *HS-DSCH Information To Modify Unsynchronised* IE, then the DRNS shall use this information to discard out-of-date MAC-hs SDUs from the related HSDPA Priority Queue.
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *ACK Power Offset* IE, the *NACK Power Offset* IE or the *CQI Power Offset* IE in the *HS-DSCH Information To Modify Unsynchronised* IE, then the DRNS shall use the indicated ACK Power Offset, the NACK Power Offset or the CQI Power Offset in the new configuration.]
- [FDD If the *HS-SCCH Power Offset* IE is included in the *HS-DSCH Information To Modify Unsynchronised* IE, the DRNS may use this value to determine the HS-SCCH power. The HS-SCCH Power Offset should be applied for any HS-SCCH transmission to this UE.]
- [TDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *TDD ACK NACK Power Offset* IE in the *HS-DSCH Information To Modify Unsynchronised* IE, the DRNS shall use the indicated power offset in the new configuration.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *HARQ Preamble Mode* IE in the *HS-DSCH Information To ModifyUnsynchronised* IE, then the DRNS shall use the indicated HARQ Preamble Mode in the new configuration as described in TS 25.214 [10], if HS-DPCCH ACK/NACK preamble and postamble is supported. Then, in this case, if the mode 1 is applied, the DRNC shall include the *HARQ Preamble Mode Activation Indicator* IE in the *HS-DSCH Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message. If the *HARQ Preamble Mode Activation Indicator* IE in the *HS-DSCH Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the MIMO Mode Indicator To Modify IE is included in the HS-DSCH Information To Modify Unsynchronised IE, then]
 - [FDD The DRNS shall activate/deactivate the MIMO mode for the HS-DSCH Radio Link in the new configuration in accordance with the *MIMO Mode Indicator* IE.]
 - [FDD If the *MIMO Mode Indicator* IE is set to "Activate", then the DRNS shall decide the pilot configuration and the UE reporting configuration (N/M ratio) according to TS 25.214 [10] for MIMO and include the *MIMO Information Response* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
 - FDD If the MIMO Mode Indicator IE is set to "Activate" and Power Offset For S-CPICH for MIMO Request Indicator IE is included, the DRNC shall, if supported and MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where the Serving HS-DSCH Radio Link is established, include the Power Offset For S-CPICH for MIMO IE in the HS-DSCH FDD Information Response IE. If zero power offset the DRNC may include the Power Offset For S-CPICH for MIMO IE.]
- [FDD The DRNC may include the *HARQ Memory Partitioning* IE in the RADIO LINK RECONFIGURATION RESPONSE message. The *HARQ Memory Partitioning* IE may contain the *HARQ Memory Partitioning Information Extension For MIMO* IE.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH Information To Modify Unsynchronised IE, then the DRNS may if the value is set to "allowed" use 64 QAM for the HS-DSCH Radio Link, and the DRNS shall include the SixtyfourQAM DL Usage Indicator IE in the HS-DSCH FDD Information Response IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH Information To Modify Unsynchronised IE with value set to "not allowed", then the DRNS shall not use 64 QAM for the HS-DSCH Radio Link.]

- [FDD If MAC-ehs is applied in the new configuration, and if Sixtyfour QAM will not be used, the DRNS shall include the *HS-DSCH TB Size Table Indicator* IE in the *HS-DSCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message if it decides to use the octet aligned table defined in TS 25.321 [41] for HS-DSCH Transport Block Size signalling.]
- [1.28Mcps TDD- If the MIMO Mode Indicator To Modify IE is included in the HS-DSCH Information To Modify Unsynchronised IE, then]
 - [1.28Mcps TDD- The DRNS shall activate/deactivate the MIMO mode for the HS-DSCH Radio Link in the new configuration in accordance with the *MIMO Mode Indicator* IE.]
 - [1.28 Mcps TDD If the *MIMO Mode Indicator* IE is set to "Activate", then the DRNS shall decide the SF mode for HS-PDSCH dual stream and include the *MIMO SF Mode for HS-PDSCH dual stream* IE in the *HS-DSCH TDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD Any secondary serving HS-DSCH that was applied in the old configuration shall remain in the new configuration unless it is explicitly removed.]
- [FDD If secondary serving HS-DSCH is applied also in the new configuration, then any changes related to parameters that are common for both the serving and the secondary serving HS-DSCH should be applied also for the secondary serving HS-DSCH.]
- [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH Information To Modify Unsynchronised* IE the DRNS may use the supported HSDPA functions for this UE.]
- [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH Information To Modify* IE with the bit *UE DTXDRX related HS-SCCH orders uniform behavior indicator* set to 0, then the DRNS shall, if supported, include the *Support of dynamic DTXDRX related HS-SCCH order* IE in the *HS-DSCH FDD Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the Single Stream MIMO Mode Indicator IE is included in the HS-DSCH Information To Modify Unsynchronised IE, then the DRNS shall activate/deactivate the Single Stream MIMO for the HS-DSCH Radio Link in accordance with the Single Stream MIMO Mode Indicator IE.]

[FDD – Secondary Serving HS-DSCH Modification:]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *HS-DSCH FDD Secondary Serving Information To Modify Unsynchronised* IE in the *Additional HS Cell Information RL Reconf Reg* IE, then:]

- [FDD If the *HS-SCCH Power Offset* IE is included in the *HS-DSCH FDD Secondary Serving Information To Modify Unsynchronised* IE, the DRNS may use this value to determine the HS-SCCH power. The HS-SCCH Power Offset should be applied for any secondary serving HS-SCCH transmission to this UE.]
- [FDD If the *MIMO Mode Indicator* IE is included in the *HS-DSCH FDD Secondary Serving Information To Modify Unsynchronised* IE, then the DRNS shall activate/deactivate the MIMO mode for the secondary serving HS-DSCH Radio Link in accordance with the *MIMO Mode Indicator* IE.]
- [FDD If the *MIMO Mode Indicator* IE is set to "Activate", then the DRNS shall decide the pilot configuration and the UE reporting configuration (N/M ratio) according to TS 25.214 [10] for MIMO and include the *MIMO Information Response* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the *Additional HS Cell Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the *MIMO Mode Indicator* IE is set to "Activate" and *Power Offset For S-CPICH for MIMO Request Indicator* IE is included, the DRNC shall, if supported and MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where the Secondary Serving HS-DSCH Radio Link is established, include the *Power Offset For S-CPICH for MIMO* IE in the *HS-DSCH FDD Secondary Serving Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message. If zero power offset the DRNC may include the *Power Offset For S-CPICH for MIMO* IE.]
- [FDD If the Single Stream MIMO Mode Indicator IE is included in the HS-DSCH FDD Secondary Serving Information To Modify Unsynchronised IE, then the Node B shall activate/deactivate the Single Stream MIMO mode for the secondary serving HS-DSCH Radio Link in accordance with the Single Stream MIMO Mode Indicator IE.]

- [FDD If the *Ordinal Number Of Frequency* IE is included in the *HS-DSCH FDD Secondary Serving Information To Modify Unsynchronised* IE, and the new configuration contains more than one secondary serving HS-DSCH Radio Link, then the DRNS shall use this value in the physical layer.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Secondary Serving Information To Modify Unsynchronised IE, then the DRNS may if the value is set to "allowed" use 64 QAM for the secondary serving HS-DSCH Radio Link, and the DRNS shall include the SixtyfourQAM DL Usage Indicator IE in the HS-DSCH FDD Secondary Serving Information Response IE in the Additional HS Cell Information Response IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the Sixtyfour QAM Usage Allowed Indicator IE is included in the HS-DSCH FDD Secondary Serving Information To Modify Unsynchronised IE with value set to "not allowed", then the DRNS shall not use 64 QAM for the secondary serving HS-DSCH Radio Link.]
- [FDD If, in the new configuration, the UE context is configured to use the "Flexible MAC-d PDU Size" format and if Sixtyfour QAM will not be used for the secondaery serving HS-DSCH, then the DRNS shall include the HS-DSCH TB Size Table Indicator IE in the HS-DSCH FDD Secondary Serving Information Response IE in the Additional HS Cell Information Response IE in the RADIO LINK RECONFIGURATION RESPONSE message if it decides to use the octet aligned table defined in TS 25.321 [41] for secondary serving HS-DSCH Transport Block Size signalling.]

[FDD – Secondary Serving HS-DSCH Removal:]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *HS-DSCH Secondary Serving Remove* IE in the *Additional HS Cell Information RL Reconf Req* IE, then the indicated secondary serving HS-DSCH Radio Link shall be removed.]

HS-DSCH MAC-d Flow Addition/Deletion:

If the RADIO LINK RECONFIGURATION REQUEST message includes any *HS-DSCH MAC-d Flows To Add* or *HS-DSCH MAC-d Flows To Delete* IEs, then the DRNS shall use this information to add/delete the indicated HS-DSCH MAC-d flows on the Serving HS-DSCH Radio Link. When an HS-DSCH MAC-d flow is deleted, all its associated Priority Queues shall also be removed.

If the RADIO LINK RECONFIGURATION REQUEST message includes an *HS-DSCH MAC-d Flows To Delete* IE requesting the deletion of all remaining HS-DSCH MAC-d flows for the UE Context, then the DRNC shall delete the HS-DSCH configuration from the UE Context and release the HS-PDSCH resources.

If the RADIO LINK RECONFIGURATION REQUEST message includes the *HS-DSCH MAC-d Flows To Add* IE, then:

- The DRNS may use the Traffic Class IE for a specific HS-DSCH MAC-d flow to determine the transport bearer characteristics to apply between DRNC and Node B. If TrCH Source Statistics Descriptor IE is present with the value "RRC" in the HS-DSCH MAC-d Flows Information IE, then the DRNC should ignore the Traffic Class IE.
- If the TNL QoS IE is included for a MAC-d flow and if ALCAP is not used, the TNL QoS IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink between the DRNS and the SRNC for the related MAC-d flow.
- The DRNC shall include the HS-DSCH Initial Capacity Allocation IE in the RADIO LINK RECONFIGURATION RESPONSE message for every HS-DSCH MAC-d flow being added, if the DRNS allows the SRNC to start transmission of MAC-d PDUs before the DRNS has allocated capacity on user plane as described in TS 25.425 [32]. If the UE context is configured to use the "Flexible MAC-d PDU Size" format for the HS-DSCH, then DRNC shall only set in the HS-DSCH Initial Capacity Allocation IE the values for the peer of Scheduling Priority Indicator IE and Maximum MAC-d PDU Size Extended IE to the values of the corresponding peer I in RADIO LINK RECONFIGURATION REQUEST message in the HS-DSCH MAC-d Flows To Add IE for a Priority Queue including Scheduling Priority Indicator IE and Maximum MAC-d PDU Size Extended IE
- If the RADIO LINK RECONFIGURATION REQUEST message includes the MAC-hs Guaranteed Bit Rate IE in the HS-DSCH MAC-d Flows To Add IE, the DRNS shall use this information to optimise MAC-hs scheduling decisions for the related HSDPA Priority Queue.

- If the RADIO LINK RECONFIGURATION REQUEST message includes the Maximum MAC-d PDU Size Extended IE for a Priority Queue in the HS-DSCH MAC-d Flows To Add IE, then the DRNC shall ignore the SID IE and MAC-d PDU Size IE in the MAC-d PDU Size Index IE and use Maximum MAC-d PDU Size Extended IE to optimise capacity allocation for the related HSDPA Priority Queue.
- If the RADIO LINK RECONFIGURATION REQUEST message includes DL RLC PDU Size Format IE for a Priority Queue in the HS-DSCH MAC-d Flows To Add IE, the DL RLC PDU Size Format IE may be used by the DRNS to determine the allocated capacity on user plane as described in TS 25.425 [32].
- [FDD FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *UE Aggregate Maximum Bit Rate Enforcement Indicator* IE for a Priority Queue in the *HS-DSCH MAC-d Flows To Add* IE, the DRNS shall, if supported, consider the data of the related HSDPA Priority Queue for UE Aggregate Maximum Bit Rate Enforcement.]

If the RADIO LINK RECONFIGURATION REQUEST message includes the *Discard Timer* IE for a Priority Queue in the *HS-DSCH MAC-d Flows To Add* IE, then the DRNS shall use this information to discard out-of-date MAC-hs SDUs from the related HSDPA Priority Queue.

[FDD - HS-DSCH Preconfiguration for Enhanced HS Serving Cell Change]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *HS-DSCH Preconfiguration Setup* IE in the *RL Information* IE the DRNS shall, if supported, preconfigure the indicated cells for Enhanced HS Serving Cell Change according to TS 25.308 [63]:]

- [FDD The DRNS shall preconfigure sets of HS-SCCH codes on the cells preconfigured for HS-DSCH, primary serving HS-DSCH cell, as well as on the secondary serving HS-DSCH cells. The primary serving HS-DSCH cell is designated through the *C-ID* IE part of the *RL Information* IE in the RADIO LINK RECONFIGURATION REQUEST message. The list of secondary serving HS-DSCH cells is designated by the list of *Secondary C-ID* IEsin the *HS-DSCH Preconfiguration Setup* IE part of the *RL Information* IE in the RADIO LINK RECONFIGURATION REQUEST message.]
- [FDD The number of HS-SCCH codes to preconfigure for each cell may be optionally specified:]
 - [FDD by the *Num Primary HS-SCCH Codes* IE in the *HS-DSCH Preconfiguration Setup* IE, for the primary serving HS-DSCH cell.]
 - [FDD by the *Num Secondary HS-SCCH Codes* IE in *the Secondary Cells* IE in the *HS-DSCH Preconfiguration Setup* IE for each of the secondary serving HS-DSCH cells.]
- [FDD If *Num Primary HS-SCCH Codes* IE or *Num Secondary HS-SCCH Codes* IE is not included in the message the number and distribution of codes on primary and any secondary cells shall be preconfigured to satisfy any limitations in TS 25.214 [10].]
- [FDD The DRNS shall return these codes in the *Sets of HS-SCCH Codes* IE along with the corresponding percell *HS-DSCH-RNTI* IE in the *HS-DSCH Preconfiguration Info* IE in the *RL Information Response* IE of the RADIO LINK RECONFIGURATION RESPONSE.]
- [FDD The DRNS shall use the first in the numbered list the primary serving HS-DSCH cell's of HS-SCCH codes in the HS-SCCH Preconfigured Codes IE sent to the SRNC to signal the Target Cell HS-SCCH Order defined in TS 25.331 [16].]
- [FDD The DRNS shall include, in the *HS-DSCH Preconfiguration Info* IE in the *RL Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message, IEs according to the rules defined for HS-DSCH Setup at Serving HS-DSCH Radio Link Change and:]
 - [FDD if *HARQ Preamble Mode* IE is included in the *HS-DSCH Preconfiguration Setup* IE the HARQ Preamble Mode Activation Indicator IE.]
 - [FDD if MIMO Activation Indicator IE is included in the HS-DSCH Preconfiguration Setup IE the MIMO N/M Ratio IE.]
 - [FDD if *Ordinal number of frequency* IE is included in the *Secondary Cells* IE in the *HS-DSCH Preconfiguration Setup* IE.]

- [FDD if *HS-DSCH MAC-d PDU Size Format* IE is included in the *HS-DSCH Preconfiguration Setup* IE and set to "Flexible MAC-d PDU Size" and if Sixtyfour QAM will not be used for the cell in the preconfiguration the *HS-DSCH TB Size Table Indicator* IE for each preconfigured cell.]
- [FDD if Sixtyfour QAM Usage Allowed Indicator IE is included in the Secondary Cells IE in the HS-DSCH Preconfiguration Setup IE or in the HS-DSCH Preconfiguration Setup IE the SixtyfourQAM DL Usage Indicator IE for each preconfigured cell.]
- [FDD if Continuous Packet Connectivity HS-SCCH less Information IE is included in the HS-DSCH Preconfiguration Setup IE the Continuous Packet Connectivity HS-SCCH less Information Response IE.]
- [FDD if the *UE with enhanced HS-SCCH support indicator* IE is included in the *HS-DSCH Preconfiguration Setup* IE, then the DRNS shall store this information in the preconfigured configuration.]
- [FDD the SixtyfourQAM DL Support Indicator IE may be included.]
- [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH Preconfiguration Setup* IE, then the DRNS may store this information in the preconfigured configuration.]
- [FDD If the *UE Support Indicator Extension* IE is included in the *HS-DSCH Preconfiguration Setup* IE with the bit *UE DTXDRX related HS-SCCH orders uniform behavior indicator* set to 0, then the DRNS shall, if supported, include the *Support of dynamic DTXDRX related HS-SCCH order* IE in the *Preconfiguration Info* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD the DRNS shall, if supported, include in the *Sets of HS-SCCH Codes* IE the *Measurement Power Offset* IE for each preconfigured cell.]
- [FDD The DRNS shall include in the *HS-DSCH Preconfiguration Info* IE in the *RL Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message the *E-DCH FDD DL Control Channel Information* containing the preconfigured configuration of the E-DCH serving cell according to the rules defined for Serving E-DCH Radio Link Change as follows:]
 - [FDD The DRNS shall allocate for the preconfigured configuration a primary E-RNTI identifier or a secondary E-RNTI identifier or both for the new Serving E-DCH Radio Link and include these E-RNTI identifiers along with the channelisation code of the corresponding E-AGCH in the *E-DCH FDD DL Control Channel Information* IE.]
 - [FDD The DRNS may preconfigure the *Serving Grant Value* IE and *Primary/Secondary Grant Selector* IE for the initial grant for the serving E-DCH RL and include these values in the *E-DCH FDD DL Control Channel Information* IE.]
- [FDD If the *Power Offset For S-CPICH for MIMO Request Indicator* IE is included in the *HS-DSCH Preconfiguration Setup* IE or in the *Secondary Cells* IE in the *HS-DSCH Preconfiguration Setup* IE, the DRNC shall, if supported and MIMO pilot configuration with Primary and Secondary CPICH is set up on the cell with a non-zero power offset where HS-DSCH / secondary HS-DSCH is preconfigured, include the *Power Offset For S-CPICH for MIMO* IE in the *HS-DSCH Preconfiguration Info* IE or in the *Sets of HS-SCCH Codes* IE in the *HS-DSCH Preconfiguration Info* IE for each preconfigured cell in the RADIO LINK RECONFIGURATION RESPONSE message. If zero power offset the DRNC may include the *Power Offset For S-CPICH for MIMO* IE.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Non-Serving RL Preconfiguration Setup* IE in the *RL Information* IE and:]

- [FDD if the choice of *new Serving RL* is "New Serving RL in the DRNS", the DRNC may include the *New non-serving RL E-DCH FDD DL Control Channel Information A* IE and/or *New non-serving RL E-DCH FDD DL Control Channel Information B* IE in the *Non-Serving RL Preconfiguration Info* IE for the RL in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD if the choice of *new Serving RL* is "New Serving RL Not in the DRNS", the DRNC may include the *New non-serving RL E-DCH FDD DL Control Channel Information C* IE in the *Non-Serving RL Preconfiguration Info* IE for the RL in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD if the choice of *new Serving RL* is "New Serving RL in the DRNS or New Serving RL Not in the DRNS", the DRNC may include the *New non-serving RL E-DCH FDD DL Control Channel Information A* IE, the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and/or the *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and *New non-serving RL E-DCH FDD DL Control Channel Information B* IE and *New non-serving RL E-DCH FDD DL Control Channel Informatio*

DCH FDD DL Control Channel Information C for the RL in the *Non-Serving RL Preconfiguration Info* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]

- [FDD – if the Additional E-DCH Non-Serving RL Preconfiguration Setup IE is included, the DRNC may include the New non-serving RL E-DCH FDD DL Control Channel Information A IE, the New non-serving RL E-DCH FDD DL Control Channel Information B IE and/or the New non-serving RL E-DCH FDD DL Control Channel Information C IE according to the choice of new Serving RL in Additional E-DCH New non-serving RL E-DCH FDD DL Control Channel Information IE for the additional non serving E-DCH RL in the Non-Serving RL Preconfiguration Info IE in the RADIO LINK RECONFIGURATION RESPONSE message.]

[FDD – Enhanced HS Serving Cell Change:]

[FDD —Upon receipt of the RADIO LINK RECONFIGURATION REQUEST message, if the Enhanced HS Serving Cell Change is preconfigured in the DRNS for the UE context, the DRNS may execute the Enhanced HS Serving Cell Change procedure according to TS 25.308 [63]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Enhanced HS Serving CC Abort* IE in the *HS-DSCH Information To Modify Unsynchronised* IE or the *HS-DSCH FDD Information* IE then the DRNS shall not execute the unsynchronized Enhanced HS Serving Cell Change procedure when performing the Serving HS-DSCH Radio Link Change or the HS-DSCH Setup.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *No of Target Cell HS-SCCH Order* IE then the DRNS shall repeat the Target Cell HS-SCCH Order on the HS-SCCH the number of times defined in the IE.]

[FDD - If the RADIO LINK RECONFIGURATION REQUEST message includes the *Non-Serving RL Preconfiguration Removal* IE, the DRNC shall remove the corresponding preconfigured E-DCH DL Control Channel Information according to the information.]

[FDD – E-DCH Setup:]

[FDD – If the *E-DCH FDD Information* IE is present in the RADIO LINK RECONFIGURATION REQUEST message then:]

- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *MAC-es Guaranteed Bit Rate* IE in the *E-DCH Logical Channel information* IE in the *E-DCH FDD Information* IE, then the DRNS shall use this information to optimise MAC-e scheduling decisions.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes *UE Aggregate Maximum Bit Rate Enforcement Indicator* IE in the *E-DCH Logical Channel Information* IE in the *E-DCH FDD Information* IE, the DRNS shall, if supported, consider the data of the related E-DCH Logical Channel for UE Aggregate Maximum Bit Rate Enforcement.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *Maximum MAC-d PDU Size Extended* IE for a E-DCH Logical Channel in the *E-DCH MAC-d Flows Information* IE in the *E-DCH Information* IE, then the DRNS shall ignore the *MAC-d PDU Size* IE in the *MAC-d PDU Size List* IE and use *Maximum MAC-d PDU Size Extended* IE to optimise capacity allocation for the related E-DCH Logical Channel and use the indicated format in user plane frame structure for E-DCH channels (TS 25.425 [32]) and MAC (TS 25.321 [41]).]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH MAC-d Flow Multiplexing List* IE for an E-DCH MAC-d flow the DRNS shall use this information for the related resource allocation operation.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *HARQ Process Allocation For 2ms Scheduled Transmission Grant* IE, the DRNS shall use this information for the related resource allocation operation.]
- [FDD If in the RADIO LINK RECONFIGURATION REQUEST message the E-DCH Grant Type is indicated as being "E-DCH Non-Scheduled Transmission Grant" for an E-DCH MAC-d flow the DRNS shall assume non-scheduled grants being configured for that E-DCH MAC-d flow and shall use the information within the HARQ Process Allocation For 2ms Non-Scheduled Transmission Grant IE, if included, for the related resource allocation operation.]

- [FDD If in the RADIO LINK RECONFIGURATION REQUEST message the E-DCH Grant Type is indicated as being "E-DCH Scheduled Transmission Grant" for an E-DCH MAC-d flow the DRNS shall assume scheduled grants being configured for that E-DCH MAC-d flow.]
- [FDD The DRNS may use the *Traffic Class* IE for a specific E-DCH MAC-d flow to determine the transport bearer characteristics to apply between DRNC and Node B. If *TrCH Source Statistics Descriptor* IE is present with the value "RRC" in the *E-DCH MAC-d Flows Information* IE, then the DRNC should ignore the *Traffic Class* IE.]
- [FDD If the *TNL QoS* IE is included for an E-DCH MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink for the related MAC-d flow.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *Bundling Mode Indicator* IE for a E-DCH MAC-d flow in the *E-DCH MAC-d Flow Specific Information* IE in the *E-DCH FDD Information* IE and the *Bundling Mode Indicator* IE is set to "Bundling" and the *E-TTI* IE is set to "2ms", then the DRNS shall use the bundling mode for the E-DCH UL data frames for the related Mac-d flow, otherwise the DRNS shall use the non-bundling mode for the E-DCH UL data frames for the related Mac-d flow.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH Maximum Bitrate* IE for an E-DCH, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the E-DCH Processing
 Overload Level IE, then if the DRNS could not decode the E-DPCCH/E-DPDCH for the last consecutive number
 of TTIs, indicated in the E-DCH Processing Overload Level IE, because of processing issue, the DRNS shall
 notify the SRNC by initiating the Radio Link Failure procedure.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH ReferencePower Offset* IE, then the DRNS may use this value as a default HARQ power offset if it is not able to decode the MAC-e PDU and to determine the value of the actual HARQ power offset.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH Power Offset for Scheduling Info* IE, then the DRNS shall use this value as a power offset for the transmission of scheduling information without any MAC-d PDUs.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-AGCH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-AGCH power. The E-AGCH Power Offset should be applied for any E-AGCH transmission to this UE.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-RGCH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-RGCH power for the RL. The E-RGCH Power Offset should be applied for any E-RGCH transmission to this UE.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-HICH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-HICH power for the RL. The E-HICH Power Offset should be applied for any E-HICH transmission to this UE.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes an *E-DPCH Information* IE which contains the *HS-DSCH Configured Indicator* IE and/or the *Maximum Set of E-DPDCHs* IE, and/or the *Puncture Limit* IE and/or the *E-TTI* IE, the DRNS shall use and apply the value(s) in the new configuration.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *SixteenQAM UL Operation Indicator* IE, the DRNS shall activate/deactivate SixteenQAM UL Operation for the RL in accordance with the *SixteenQAM UL Operation Indicator* IE.]
 - [FDD If SixteenQAM UL Operation is activated, then the DRNS shall base the handling of the Relative Grant signalling on Scheduling Grant Table 2 according to TS 25.321 [41]. If SixteenQAM UL Operation is deactivated, then the DRNS shall base the handling of the Relative Grant signalling on Scheduling Grant Table 1 according to TS 25.321 [41].]

[FDD – E-DCH Radio Link Handling:]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH RL Indication* IE in the *RL Information* IE:]

- [FDD The DRNC shall setup the E-DCH resources, as requested or as configured in the UE context, on the Radio Links indicated by the *E-DCH RL Indication* IE, set to "E-DCH", in the *RL Information* IE.]
- [FDD The DRNC may include the *E-AGCH And E-RGCH/E-HICH FDD Scrambling Code* IE and shall include the *E-RGCH/E-HICH Channelisation Code* IE and the corresponding *E-HICH Signature Sequence* IE and the DRNC may include the corresponding *E-RGCH Signature Sequence* IE in the *E-DCH FDD DL Control Channel Information* IE in the RADIO LINK RECONFIGURATION RESPONSE message for every RL indicated by the *E-DCH RL Indication* IE, set to "E-DCH", in the *RL Information* IE.]
- [FDD The DRNC shall remove the E-DCH resources, if any, on the Radio Links, that are indicated by the *E-DCH RL Indication* set to "Non E-DCH".]
- [FDD For each RL for which the *E-DCH RL Indication* IE is set to "E-DCH", and which has or can have a common generation of E-RGCH information with another RL (current or future) when the DRNS would contain the E-DCH serving RL, the DRNS shall include the *E-DCH RL Set ID* IE in the RADIO LINK RECONFIGURATION RESPONSE message. The value of the *E-DCH RL Set ID* IE shall allow the SRNC to identify the E-DCH RLs that have or can have a common generation of E-RGCH information.]

[FDD – Serving E-DCH Radio Link Change:]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Serving E-DCH RL* IE, this indicates the new Serving E-DCH Radio Link:]

- [FDD If the old Serving E-DCH RL is within this DRNS, the DRNS shall de-allocate the E-AGCH resources of the old Serving E-DCH Radio Link.]
- [FDD If the new Serving E-DCH RL is within this DRNS:]
 - [FDD The DRNS shall allocate a primary E-RNTI identifier or a secondary E-RNTI identifier or both for
 the new Serving E-DCH Radio Link and include these E-RNTI identifiers along with the channelisation code
 of the corresponding E-AGCH in the *E-DCH FDD DL Control Channel Information* IE in the *RL Information Response* IE for the indicated RL in the RADIO LINK RECONFIGURATION RESPONSE
 message.]
 - [FDD The DRNS may include the *Serving Grant Value* IE and *Primary/Secondary Grant Selector* IE in the RADIO LINK RECONFIGURATION RESPONSE message for the initial grant for the new serving E-DCH RL.]
 - [FDD If the E-DCH HARQ process allocation for 2ms TTI for scheduled and/or non-scheduled transmission shall be changed, the DRNS shall allocate resources according to the new/changed configuration and include the new/changed configuration in the *E-DCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
 - [FDD If a serving cell change is performed the RADIO LINK RECONFIGURATION RESPONSE message may contain invalid data (see 9.2.2.4C).]
 - [FDD The DRNS may include the *Default Serving Grant in DTX Cycle 2* IE in the RADIO LINK RECONFIGURATION RESPONSE message for the new serving E-DCH RL.]
- [FDD The DRNS may include the *E-RGCH/E-HICH Channelisation Code* IE and/or the *E-HICH Signature Sequence* IE and/or the *E-RGCH Signature Sequence* IE or may alternatively include the *E-RGCH Release Indicator* IE in the *E-DCH FDD DL Control Channel Information* IE in the RADIO LINK RECONFIGURATION RESPONSE message for every E-DCH Radio Links in the DRNS.]
- [FDD If the DRNS has no valid data for the *E-RGCH/E-HICH Channelisation Code* IE in the *E-DCH FDD DL Control Channel Information* IE in the RADIO LINK RECONFIGURATION RESPONSE message, then it shall insert the *E-RGCH and E-HICH Channelisation Code Validity Indicator* IE in the *E-DCH FDD DL Control Channel Information* IE, to indicate that the *E-RGCH/E-HICH Channelisation Code* IE contains invalid data.]

[FDD – E-DCH Modification:]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH FDD Information To Modify* IE, then:]

- [FDD If the *E-DCH FDD Information To Modify* IE contains a *E-DCH MAC-d Flow Specific Information* IE which includes the *Allocation/Retention Priority* IE, the DRNS shall apply the new Allocation/Retention Priority to this E-DCH in the new configuration according to Annex A.]
- [FDD If the *TNL QoS* IE is included for an E-DCH MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink for the related MAC-d flow.]
- [FDD If *Traffic Class* IE is included for an E-DCH MAC-d flow the DRNS may use the *Traffic Class* IE for a specific E-DCH MAC-d flow to determine the transport bearer characteristics to apply between DRNC and Node B. The DRNC should ignore the *Traffic Class* IE if the *TrCH Source Statistics Descriptor* IE for this specific E-DCH MAC-d flow indicates the value "RRC".]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *Data Description Indicator* IE, the DRNC shall use the DDI values indicated in the *Data Description Indicator* IE in the new configuration.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *MAC-es Guaranteed Bit Rate* IE in the *E-DCH FDD Information To Modify* IE, the DRNS shall use this information to optimise MAC-e scheduling decisions.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *Maximum Number of Retransmissions for E-DCH* IE for an E-DCH MAC-d flow in the *E-DCH FDD Information To Modify* IE, then the DRNS shall use this information to report if the maximum number of retransmissions has been exceeded.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH HARQ Power Offset FDD* IE in the *E-DCH FDD Information To Modify* IE for an E-DCH MAC-d flow the DRNS shall use this information for calculating the unquantised gain factor for an E-TFC ($\beta_{ed,i,uq}$) as defined in TS 25.214 [10].]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH MAC-d Flow Multiplexing List* IE for an E-DCH MAC-d flow the DRNS shall use this information for the related resource allocation operation.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the E-DCH Grant Type and it
 is indicated as being "E-DCH Non-Scheduled Transmission Grant" for an E-DCH MAC-d flow the DRNS shall
 assume non-scheduled grants being configured for that E-DCH MAC-d flow and shall use the information within
 the HARQ Process Allocation For 2ms Non-Scheduled Transmission Grant IE, if included, for the related
 resource allocation operation.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the E-DCH Grant Type and it
 is indicated as being "E-DCH Scheduled Transmission Grant" for an E-DCH MAC-d flow the DRNS shall
 assume scheduled grants being configured for that E-DCH MAC-d flow.]
- [FDD If the RADIO LINK RECONFIGURATION RE QUEST message includes the *E-DCH Logical Channel To Add* or *E-DCH Logical Channel To Delete* IEs, the DRNS shall use this information to add/delete the indicated logical channels. When an logical channel is deleted, all its associated configuration data shall also removed.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH Logical Channel To Modify* IE, the DRNS shall use this information to modify the indicated logical channels.]
 - [FDD If the *E-DCH Logical Channel To Modify* IE includes *Scheduling Priority Indicator* IE, the DRNS shall apply the values in the new configuration.]
 - [FDD If the *E-DCH Logical Channel To Modify* IE includes *Scheduling Information* IE, the DRNS shall apply the values in the new configuration.]
 - [FDD If the *E-DCH Logical Channel To Modify* IE includes the *Maximum MAC-d PDU Size Extended* IE, the DRNC shall apply the value in the new configuration.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *Bundling Mode Indicator* IE for an E-DCH MAC-d flow in the *E-DCH MAC-d Flow Specific Information* IE in the *E-DCH FDD Information To Modify* IE and the *Bundling Mode Indicator* IE is set to "Bundling" and the *E-TTI* IE is set to "2ms", then the DRNS shall use the bundling mode for the E-DCH UL data frames for the related MAC-d flow,

otherwise the DRNS shall use the non-bundling mode for the E-DCH UL data frames for the related MAC-d flow.]

- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *HARQ Process Allocation For 2ms Scheduled Transmission Grant* IE, the DRNS shall use this information for the related resource allocation operation.]
- [FDD If the E-DCH serving RL is in this DRNS, the DRNS may choose to change the E-DCH HARQ process allocation for 2ms TTI for scheduled and/or non-scheduled transmission. In this case the DRNS shall allocate resources according to the new/changed configuration and include the new/changed configuration in the *E-DCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH Maximum Bitrate* IE for an E-DCH, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the E-DCH Processing
 Overload Level IE, then if the DRNS could not decode the E-DPCCH/E-DPDCH for the last consecutive number
 of TTIs, indicated in the E-DCH Processing Overload Level IE, because of processing issue, the DRNS shall
 notify the SRNC by initiating the Radio Link Failure procedure.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH ReferencePower Offset* IE, then the DRNS may use this value as a default HARQ power offset if it is not able to decode the MAC-e PDU and to determine the value of the actual HARQ power offset.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-AGCH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-AGCH power. The E-AGCH Power Offset should be applied for any E-AGCH transmission to this UE.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-RGCH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-RGCH power for the RL. The E-RGCH Power Offset should be applied for any E-RGCH transmission to this UE.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-HICH Power Offset* IE in the *RL Specific E-DCH Information* IE, then the DRNS may use this value to determine the E-HICH power for the RL. The E-HICH Power Offset should be applied for any E-HICH transmission to this UE.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH Power Offset for Scheduling Info* IE, then the DRNS shall use this value as a power offset for the transmission of scheduling information without any MAC-d PDUs.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *SixteenQAM UL Operation Indicator* IE in the *E-DCH FDD Information To Modify* IE, the DRNS shall activate/deactivate SixteenQAM UL Operation for the RL in accordance with the *SixteenQAM UL Operation Indicator* IE.]
 - [FDD If SixteenQAM UL Operation is activated, then the DRNS shall base the handling of the Relative Grant signalling on Scheduling Grant Table 2 according to TS 25.321 [41]. If SixteenQAM UL Operation is deactivated, then the DRNS shall base the handling of the Relative Grant signalling on Scheduling Grant Table 1 according to TS 25.321 [41].]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH DL Control Channel Grant Information* IE in the *E-DCH FDD Information To Modify* IE, the DRNS may modify E-AGCH Channelisation Code, E-RGCH/E-HICH Channelisation Code, E-RGCH Signature Sequence and/or E-HICH Signature Sequence for the E-DCH RL indicated by the *E-DCH RL ID* IE. The DRNC shall then report the modified configuration which is used in the new configuration specified in the *E-DCH FDD DL Control Channel Information* IE for each E-DCH RL in the RADIO LINK RECONFIGURATION RESPONSE message.]

[FDD – E-DCH MAC-d Flow Addition:]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes an *E-DCH MAC-d Flows To Add* IE, then the DRNS shall use this information to add the indicated E-DCH MAC-d flows.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Maximum MAC-d PDU Size Extended* IE for a E-DCH Logical Channel in the *E-DCH MAC-d Flows Information* IE in the *E-DCH MAC-d Flows To*

Add IE, then the DRNS shall ignore the MAC-d PDU Size IE in the MAC-d PDU Size List IE and use Maximum MAC-d PDU Size Extended IE to optimise capacity allocation for the related E-DCH Logical Channel.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH MAC-d Flows To Add* IE, then:]

- [FDD The DRNS may use the *Traffic Class* IE for a specific E-DCH MAC-d flow to determine the transport bearer characteristics to apply between DRNC and Node B. If *TrCH Source Statistics Descriptor* IE is present with the value "RRC" in the *E-DCH MAC-d Flows Information* IE, then the DRNC should ignore the *Traffic Class* IE.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *MAC-es Guaranteed Bit Rate* IE in the *E-DCH Logical Channel Information IE* in the *E-DCH MAC-d Flows To Add* IE, the DRNS shall use this information to optimise MAC-e scheduling decisions.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *UE Aggregate Maximum Bit Rate Enforcement Indicator* IE in the *E-DCH Logical Channel Information IE* in the *E-DCH MAC-d Flows To Add* IE, the DRNS shall, if supported, consider the data of the related E-DCH Logical Channel for UE Aggregate Maximum Bit Rate Enforcement.]

[FDD – E-DCH MAC-d Flow Deletion:]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes an *E-DCH MAC-d Flows To Delete* IEs, then the DRNS shall use this information to delete the indicated E-DCH MAC-d flows. When an E-DCH MAC-d flow is deleted, all its associated configuration shall also be removed.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes an *E-DCH MAC-d Flows To Delete* IE requesting the deletion of all remaining E-DCH MAC-d flows for the UE Context, then the DRNC shall delete the E-DCH configuration from the UE Context and release the E-DCH resources.]

[FDD – Additional E-DCH Setup:]

[FDD – If the *Additional E-DCH Cell Information RL Reconf Req* IE is present in the RADIO LINK RECONFIGURATION REQUEST message and the choice of *Setup, Configuration Change or Removal of E-DCH On Secondary UL Frequency* is "Setup", then the *Additional E-DCH Cell Information Setup* IE defines the new configuration and then:]

- [FDD If the *C-ID* IE is included in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE the *C-ID* IE indicates the cell in which the additional E-DCH shall be setup]
 - [FDD The DRNS shall setup the E-DCH on the secondary uplink frequency and setup the requested E-DCH resources on the Radio Links and in the cells indicated by the *E-DCH Additional RL ID* IE and the *C-ID* IE in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE.]
- [FDD If the *C-ID* IE is not included in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE the *E-DCH Additional RL ID* IE indicates the existing RL on which the additional E-DCH shall be setup.]
 - [FDD The DRNS shall setup the additional E-DCH on the Radio Links indicated by the *E-DCH Additional RL ID* IE in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE]
- [FDD The DRNS shall use for the non cell specific Radio Link related parameters and non cell specific E-DPCH, UL DPCH, E-DCH and F-DPCH parameters the same values as for the corresponding cell of the Primary uplink frequency.]
- [FDD If the *UL SIR Target* IE in the *UL DPCH Information* IE in the *Additional E-DCH FDD Setup Information* IE in the *Additional E-DCH Cell Information Setup* IE and/or the *DL Power Balancing Information* IE and/or the *Minimum Reduced E-DPDCH Gain Factor* IE in the *Multicell E-DCH Information* IE in the *Additional E-DCH FDD Setup Information* IE are present, the DRNS shall use the information in the same same way as for the information used on Primary uplink frequency.]

- [FDD If the *Secondary UL Frequency Activation State* IE is present in the *Multicell E-DCH Information* IE in the *Additional E-DCH FDD Setup Information* IE, the DRNS shall use the information as initial activation state of the Radio Links on the secondary uplink frequency.]
- [FDD If the *Initial DL Tx Power* IE, the *Primary CPICH Ec/No* IE, the *E-AGCH Power Offset* IE, the *E-RGCH Power Offset* IE and/or the *E-HICH Power Offset* IE is included in the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE in the *Additional E-DCH Cell Information Setup* IE, the DRNS shall use the information in the same way as for the information used on Primary uplink frequency.]
- [FDD If the Enhanced Primary CPICH Ec/No IE is included in the Multicell E-DCH RL Specific Information IE in the Additional E-DCH Secondary RL Specific Information To Setup IE in the Additional E-DCH FDD Setup Information IE in the Additional E-DCH Cell Information Setup IE, the DRNS shall use the information in the same way as for the information used on Primary uplink frequency.]
- [FDD If the F-DPCH Slot Format Support Request IE in the F-DPCH Information IE in the Additional E-DCH FDD Setup Information IE in the Additional E-DCH Cell Information Setup IE is included, the DRNS shall configure the concerned UE Context for F-DPCH Slot Format operation according to TS 25.211 [8] and include the F-DPCH Slot Format IE in the Additional E-DCH FDD Information Response IE in the Additional E-DCH Cell Information Response RLReconfIE in the RADIO LINK RECONFIGURATION RESPONSE message. If the Multicell E-DCH Information IE in the Additional E-DCH FDD Setup Information IE includes the F-DPCH Slot Format IE, the DRNS may use the F-DPCH Slot Format IE to determine the F-DPCH slot format.]
- [FDD If the HARQ Process Allocation For 2ms Scheduled Transmission Grant IE, the E-DCH Maximum Bitrate IE, the E-DCH Minimum Set E-TFCI IE and/or the E-DCH Processing Overload Level IE are present in the Additional E-DCH FDD Information IE in the Additional E-DCH Cell Information Setup IE, the DRNS shall use the information in the same way as for the information used on Primary uplink frequency.]
- [FDD If activation of power balancing for the Additional E-DCH RL by the RADIO LINK RECONFIGURATION REQUEST message is supported by the DRNS, the DRNS shall include the *DL Power Balancing Activation Indicator* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD For each Additional E-DCH RL not having a common generation of the TPC commands in the DL with another Additional E-DCH RL, the DRNS shall set the *RL Set ID* IE included in the *Additional E-DCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message to a value that uniquely identifies the RL as a RL Set within the UE Context. The generation of E-HICH related information for Additional E-DCH RLs in different RL Sets shall not be common.]
- [FDD For all Additional E-DCH RLs having a common generation of the TPC commands in the DL with another Additional E-DCH RL, the DRNS shall assign to each Additional E-DCH RL the same value for the *RL Set ID* IE included in the *Additional E-DCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message. This value shall uniquely identify these Additional E-DCH RLs as members of the same RL Set within the UE Context. The generation of E-HICH information for all Additional E-DCH RLs in a RL Set shall be common.]
- [FDD For each Additional E-DCH RL which has or can have a common generation of E-RGCH information with another Additional E-DCH RL (current or future) when the DRNS would contain the Additional E-DCH serving RL, the DRNS shall set a same value to the *E-DCH RL Set ID* IE for the Additional E-DCH RL in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response* RLReconf IE in the RADIO LINK RECONFIGURATION RESPONSE message]
- [FDD For every additional E-DCH RL indicated in the Additional E-DCH RL Specific Information To Setup IE in the Additional E-DCH FDD Setup Information IE the DRNS may include the E-AGCH And E-RGCH/E-HICH FDD Scrambling Code IE and shall include the E-RGCH/E-HICH Channelisation Code IE and the corresponding E-HICH Signature Sequence IE and the DRNS may include the corresponding E-RGCH Signature Sequence IE for each Additional E-DCH RL in the E-DCH FDD DL Control Channel Information IE in the Additional E-DCH FDD Information Response IE in the Additional E-DCH Cell Information Response RLReconf IE in the RADIO LINK RECONFIGURATION RESPONSE message and if DRNS has no valid data for the E-RGCH/E-HICH Channelisation Code IE, then it shall insert the E-RGCH and E-HICH Channelisation Code Validity Indicator IE to indicate that the E-RGCH/E-HICH Channelisation Code IE contains invalid data.]

- [FDD If the Additional Serving E-DCH Radio Link is configured in the DRNS, then:]
 - [FDD The DRNS shall allocate a primary E-RNTI identifier or a secondary E-RNTI identifier or both for
 the corresponding RL and include these E-RNTI identifiers and the channelisation code of the corresponding
 E-AGCH in the E-DCH FDD DL Control Channel Information IE in the Additional E-DCH FDD
 Information Response IE in the Additional E-DCH Cell Information Response RLReconf IE in the RADIO
 LINK RECONFIGURATION RESPONSE message.]
 - [FDD The DRNS may include in the *E-DCH FDD DL Control Channel Information* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION RESPONSE message the *Serving Grant Value* IE and *Primary/Secondary Grant Selector* IE for the initial grant for the Additional serving E-DCH RL and may include the *Default Serving Grant in DTX Cycle 2* IE.]
 - [FDD If the E-DCH HARQ process allocation for 2ms TTI for scheduled transmission shall be changed, the DRNS shall allocate resources according to the new/changed configuration and include the new/changed configuration in the *HARQ Process Allocation For 2ms Scheduled Transmission Grant* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If Primary CPICH is not to be used as a Phase Reference for this Radio Link on the secondary UL frequency, the DRNS shall include the *Primary CPICH Usage For Channel Estimation* IE set to the value "Primary CPICH shall not be used" in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If Secondary CPICH may be used as a Phase Reference for this Radio Link on the secondary UL frequency, the DRNS shall include the *Secondary CPICH Information* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION RESPONSE message. If the DRNS doesn't include the *Secondary CPICH Information* IE, it shall not include the *Primary CPICH Usage For Channel Estimation* IE set to the value "Primary CPICH shall not be used".]

[FDD – Additional E-DCH Configuration Change]

[FDD – If the *Additional E-DCH Cell Information RL Reconf Req* IE is present in the RADIO LINK RECONFIGURATION REQUEST message and the choice of *Setup, Configuration Change or Removal of E-DCH On Secondary UL Frequency* is "Configuration Change", then the *Additional E-DCH Cell Information Configuration Change* IE defines the new configuration and then:]

- [FDD If the *Minimum Reduced E-DPDCH Gain Factor* IE and/or the *Common DL Reference Power* IE is present in the *Multicell E-DCH Information* IE in the *Additional E-DCH Configuration Change Information* IE IE the DRNS shall use the information in the same way as for the information that is used on the Primary uplink frequency.]
- [FDD. If the UE Context is configured for F-DPCH Slot Format operation, the DRNS shall include the *F-DPCH Slot Format* IE in the *Additional E-DCH FDD Information Response* IE for new RLs on the secondary UL frequency or in the *Additional Modified E-DCH FDD Information Response* IE for modified RLs in the RADIO LINK RECONFIGURATION RESPONSE message.]

[FDD – Additional E-DCH RL Addition:]

[FDD – If the Additional E-DCH RL Specific Information To Add IE is present in the Additional E-DCH Configuration Change Information IE in the Additional E-DCH Configuration Change Information IE, then:]

- [FDD The DRNS shall setup the E-DCH resources, as requested or as configured in the UE context, on the Radio Links indicated by the *E-DCH Additional RL ID* IE. Non cell specific Radio Link related parameters and non cell specific E-DPCH, UL DPCH, E-DCH and F-DPCH parameters shall take the same values as for the corresponding cell of the Primary uplink frequency.]
- [FDD If the *E-AGCH Power Offset* IE, the *E-RGCH Power Offset* IE, the *E-HICH Power Offset* IE is included, the DRNS shall use the information in the same way as for the information used on the Primary uplink frequency.]

- [FDD If the power balancing is active with the Power Balancing Adjustment Type of the UE Context set to "Individual" in the existing Additional E-DCH RL(s) and the RADIO LINK RECONFIGURATION REQUEST message includes the *DL Reference Power* IE in the *Multicell E-DCH RL Specific Information* IE, the DRNS shall activate the power balancing and use the *DL Reference Power* IE for the power balancing procedure in the new Additional RL(s), if activation of power balancing by the RADIO LINK RECONFIGURATION REQUEST message at RL addition on secondary UL frequency is supported, according to subclause 8.3.15. In this case, the DRNS shall include the *DL Power Balancing Activation Indicator* IE in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION RESPONSE message. If the DRNS starts the DL transmission and the activation of the power balancing at the same CFN, the initial power of the power balancing, i.e. *P_{init}* shall be set to the power level which is calculated based on the following IEs (if received): *Primary CPICH Ec/No* IE or the *Enhanced Primary CPICH Ec/No* IE in the *Multicell E-DCH RL Specific Information* IE or to the power level which is calculated based on the power relative to the Primary CPICH power used by the existing Additional RLs.]
- [FDD For each Additional E-DCH RL not having a common generation of the TPC commands in
 the DL with another Additional E-DCH RL, the DRNS shall set the *RL Set ID* IE included in the *Additional E-DCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION
 RESPONSE message to a value that uniquely identifies the RL as a RL Set within the UE Context.
 The generation of E-HICH related information for Additional E-DCH RLs in different RL Sets shall
 not be common.]
- [FDD For all Additional E-DCH RLs having a common generation of the TPC commands in the DL with another Additional E-DCH RL, the DRNS shall assign to each Additional E-DCH RL the same value for the *RL Set ID* IE included in the *Additional E-DCH FDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message. This value shall uniquely identify these Additional E-DCH RLs as members of the same RL Set within the UE Context. The generation of E-HICH information for all Additional E-DCH RLs in a RL Set shall be common.]
- [FDD For each Additional E-DCH RL which has or can have a common generation of E-RGCH information with another Additional E-DCH RL (current or future) when the DRNS would contain the Additional E-DCH serving RL, the DRNS shall set a same value to the *E-DCH RL Set ID* IE for the Additional E-DCH RL in the *Additional E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION RESPONSE message]
- [FDD For every additional E-DCH RL indicated in the Additional E-DCH RL Specific Information To Add IE, the DRNS may include the E-AGCH And E-RGCH/E-HICH FDD Scrambling Code IE and shall include the E-RGCH/E-HICH Channelisation Code IE and the corresponding E-HICH Signature Sequence IE and the DRNS may include the corresponding E-RGCH Signature Sequence IE in the E-DCH FDD DL Control Channel Information IE in the Additional E-DCH FDD Information Response IE in the Additional E-DCH Cell Information Response RLReconf IE in the RADIO LINK RECONFIGURATION RESPONSE message and if DRNS has no valid data for the E-RGCH/E-HICH Channelisation Code Validity Indicator IE to indicate that the E-RGCH/E-HICH Channelisation Code IE contains invalid data
- [FDD If the *Primary CPICH Ec/No* IE or the *Primary CPICH Ec/No* IE and the *Enhanced Primary CPICH Ec/No* IE in the *Multicell E-DCH RL Specific Information* IE measured by the UE are included for a RL in the RADIO LINK RECONFIGURATION REQUEST message, the DRNS shall use this in the calculation of the Initial DL TX Power for this additional RL. If the *Primary CPICH Ec/No* IE is not present, the DRNS shall set the Initial DL TX Power based on the power relative to the Primary CPICH power used by the existing RLs.]

[FDD - Additional E-DCH RL Modification:]

[FDD – If the *Additional E-DCH RL Specific Information To Modify* IE is present in the *Additional E-DCH Configuration Change Information* IE, then the additional E-DCH RL indicated by the *E-DCH Additional RL ID* IE indicates the RL on which E-DCH resources shall be modified:]

- [FDD – If the E-AGCH Power Offset IE, the E-RGCH Power Offset IE, the E-HICH Power Offset IE, and/or the E-DCH DL Control Channel Grant IE in the Multicell E-DCH RL Specific Information IE

is included, the DRNS shall use the information in the same way as for the information used on the Primary uplink frequency.]

- [FDD If the *DL Reference Power* IEs is included in the *Multicell E-DCH RL Specific Information* IE and power balancing is active, DRNS shall apply DL power Control in the same way as defined for the Primary uplink frequency.]
- [FDD If updating of power balancing parameters by the RADIO LINK RECONFIGURATION REQUEST message is supported by the DRNS, the DRNS shall include the *DL Power Balancing Updated Indicator* IE in the *Additional Modified E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE for each affected RL in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the RADIO LINK RECONFIGURATION RESPONSE message includes the *Primary CPICH Usage For Channel Estimation* IE and/or the *Secondary CPICH Information Change* IE in the *Additional Modified E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE, the DRNS shall avoid the new configuration in which neither the Primary CPICH nor the Secondary CPICH is used as a Phase Reference for this Radio Link.]

[FDD - Additional E-DCH Modification:]

[FDD – If the *Additional E-DCH FDD Information To Modify* IE is present in the *Additional E-DCH Configuration Change Information* IE, then:]

- [FDD If the *HARQ Process Allocation For 2ms Scheduled Transmission Grant* IE, the *E-DCH Minimum Set E-TFC*I IE and/or the *E-DCH Maximum Bitrate* IE is included, the DRNS shall use this information for the related resource allocation operation.]
- [FDD If the *E-DCH Processing Overload Level* IE is included, then if the DRNS could not decode the E-DPCCH/E-DPDCH for the last consecutive number of TTIs, indicated in the *E-DCH Processing Overload Level* IE, because of processing issue, the DRNS shall notify the RNC by initiating the Radio Link Failure procedure.]
- [FDD If the DL TX power upper or lower limit has been re-configured for the secondary UL frequency, the DRNS shall include the new value(s) in the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the *Additional Modified E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE in the RADIO LINK RECONFIGURATION RESPONSE message.
- [FDD The DRNS decides the maximum and minimum SIR for the uplink of the Radio Link(s), and the DRNS shall include in the RADIO LINK RECONFIGURATION RESPONSE message the *Maximum Uplink SIR* IE and *Minimum Uplink SIR* IE in the *Additional Modified E-DCH FDD Information Response* IE in the *Additional E-DCH Cell Information Response RLReconf* IE for each Radio Link when these values are changed.]
- [FDD If the Additional E-DCH serving RL is in this DRNS, the DRNS may choose to change the E-DCH HARQ process allocation for 2ms TTI for scheduled transmission. In this case the DRNS shall allocate resources according to the new/changed configuration and include the new/changed configuration in the HARQ Process Allocation For 2ms Scheduled Transmission Grant IE in the Additional Modified E-DCH FDD Information Response IE in the RADIO LINK RECONFIGURATION RESPONSE message.]

[FDD – Additional E-DCH Removal]

[FDD – If the *Additional E-DCH Cell Information RL Reconf Req* IE is present in the RADIO LINK RECONFIGURATION REQUEST message and the choice of *Setup, Configuration Change or Removal of E-DCH On Secondary UL Frequency* is "Removal", then the additional E-DCH on the secondary uplink frequency shall be removed.]

[TDD – Intra- DRNS Serving E-DCH Radio Link Change:]

[TDD- If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH Serving RL* IE, this indicates the new Serving E-DCH Radio Link:]

- [TDD In the new configuration the DRNS shall de-allocate the E-DCH resources of the old Serving E-DCH Radio Link and allocate the E-DCH resources for the new Serving E-DCH Radio Link.]
- [3.84Mcps TDD The DRNS shall allocate E-AGCH parameters corresponding to the E-DCH and include the *E-AGCH Specific Information Response* IE in the *E-DCH TDD Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [1.28Mcps TDD The DRNS shall allocate E-AGCH parameters and E-HICH parameters corresponding to the E-DCH and include the *E-AGCH Specific Information Response* IE and the *E-HICH Specific Information Response* IE in the *E-DCH Information Response* 1.28Mcps IE in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [7.68Mcps TDD The DRNS shall allocate E-AGCH parameters corresponding to the E-DCH and include the *E-AGCH Specific Information Response* 7.68Mcps IE in the *E-DCH TDD Information Response* 7.68Mcps IE in the RADIO LINK RECONFIGURATION READY message.]
- [TDD If the *TNL QoS* IE is included for a MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink for the related MAC-d flow.]

[TDD – E-PUCH Handling:]

[3.84Mcps TDD and 7.68Mcps TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes an *E-PUCH Information* IE, the DRNS shall apply the parameters to the new configuration.]

[1.28Mcps TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes an *E-PUCH Information LCR* IE, the DRNS shall apply the parameters to the new configuration]

[TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes an *E-TFCS Information* IE, the DRNS shall apply the beta parameters to the new configuration.]

[3.84Mcps TDD – E-DCH Setup:]

[3.84Mcps TDD – the radio link may be reconfigured to support E-DCH by including the appropriate E-DCH information elements: *E-DCH Serving RL* IE, *E-PUCH Information* IE, *E-TFCS Information TDD* IE, *E-DCH MAC-d Flows to Add* IE and *E-DCH TDD Information* IE.]

[1.28Mcps TDD – E-DCH Setup:]

[1.28cps TDD – the radio link may be reconfigured to support E-DCH by including the appropriate E-DCH information elements: *E-DCH Serving RL* IE, *E-PUCH Information LCR* IE, *E-TFCS Information TDD* IE, *E-DCH MAC-d Flows to Add* IE and *E-DCH TDD Information LCR* IE.]

[1.28Mcps TDD - If the *UE TSO Capability LCR* IE in the *UE Capabilities Information* IE in the *HS-DSCH Information To Modify* IE is not present, or if the *UE TSO Capability LCR* IE in the *UE Capabilities Information* IE in the *HS-DSCH Information* IE is not present, and if the RADIO LINK RECONFIGURATION REQUEST message includes the *UE TSO Capability LCR* IE in the *E-DCH TDD Information LCR* IE, the DRNS can use this information to allocate the downlink resources for the UE according to TS 25.306 [42].]

[7.68Mcps TDD – E-DCH Setup:]

[7.68Mcps TDD – the radio link may be reconfigured to support E-DCH by including the appropriate E-DCH information elements: *E-DCH Serving RL* IE, *E-PUCH Information* IE, *E-TFCS Information TDD* IE, *E-DCH MAC-d Flows to Add* IE and *E-DCH TDD Information* 7.68Mcps IE.]

[TDD- E-DCH MAC-d Flow Addition/Deletion:]

[TDD- If the RADIO LINK RECONFIGURATION REQUEST message includes any *E-DCH MAC-d Flows To Add* or E-DCH *MAC-d Flows To Delete* IEs, then the DRNS shall use this information to add/delete the indicated E-DCH MAC-d flows. When an E-DCH MAC-d flow is deleted, all its associated configuration data shall also be removed.]

[TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Maximum MAC-d PDU Size Extended* IE for a E-DCH Logical Channel in the *E-DCH MAC-d Flows Information* IE in the *E-DCH TDD Information To Add* IE, then the DRNS shall ignore the *MAC-d PDU Size* IE in the *MAC-d PDU Size List* IE and use *Maximum MAC-d PDU Size Extended* IE to optimise capacity allocation for the related E-DCH Logical Channel.]

[TDD- If the RADIO LINK RECONFIGURATION REQUEST message includes an *E-DCH MAC-d Flows To Delete* IE requesting the deletion of all remaining E-DCH MAC-d flows for the UE Context, then the DRNS shall delete the E-DCH configuration from the UE Context and release the E-DCH resources.]

[TDD- If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH MAC-d Flows To Add* IE, then:]

- [TDD- If the RADIO LINK RECONFIGURATION REQUEST message includes the *MAC-es Guaranteed Bit Rate* IE in the *E-DCH MAC-d Flows To Add* IE, the DRNS shall use this information to optimise MAC-e scheduling decisions.]
- [1.28Mcps TDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *MAC-es Maximum Bit Rate LC*R IE in the *E-DCH Logical Channel Information* IE in the *E-DCH MAC-d Flows To Add* IE, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]

[3.84Mcps TDD – E-DCH Non-scheduled allocations:]

[3.84Mcps TDD – The DRNS shall determine any non-scheduled resource to be granted for the radio link, and return this in the *E-DCH Non-scheduled Grant Information TDD* IE in the *E-DCH Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]

[1.28Mcps TDD – E-DCH Non-scheduled allocations:]

[1.28Mcps – The DRNS shall determine any non-scheduled resource to be granted for the radio link, and return this in the *E-DCH Non-scheduled Grant Information LCR TDD* IE in the *E-DCH Information Response 1.28Mcps* IE in the RADIO LINK RECONFIGURATION RESPONSE message.]

[7.68Mcps TDD – E-DCH Non-scheduled allocations:]

[7.68Mcps TDD – The DRNS shall determine any non-scheduled resource to be granted for the radio link, and return this in the *E-DCH Non-scheduled Grant Information* 7.68Mcps *TDD* IE in the *E-DCH Information Response* 7.68Mcps IE in the RADIO LINK RECONFIGURATION RESPONSE message.]

[3.84Mcps TDD – E-DCH Modification:]

[3.84Mcps TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH TDD Information* IE, then:]

- [3.84Mcps TDD If the *E-DCH TDD Information* IE includes the *E-DCH TDD Maximum Bitrate* IE for an E-DCH, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
- [3.84Mcps TDD If the *E-DCH TDD Information* IE includes the *E-DCH Processing Overload Level* IE, then if the DRNS could not decode the E-PUCH for the last consecutive number of TTIs, indicated in the *E-DCH Processing Overload Level* IE, because of a processing issue, the DRNS shall notify the SRNC by initiating the Radio Link Failure procedure.]
- [3.84Mcps TDD If the *E-DCH TDD Information* IE includes the *E-DCH Power Offset for Scheduling Info* IE, then the DRNS shall use this value as a power offset for the transmission of scheduling information without any MAC-d PDUs.]

[1.28Mcps TDD – E-DCH Modification:]

[1.28Mcps TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH TDD Information LCR* IE, then:]

- [1.28Mcps TDD If the *E-DCH TDD Information LCR* IE includes the *E-DCH Physical Layer Category LCR* IE or *Extended E-DCH Physical Layer Category LCR* IE for an E-DCH, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
- [1.28Mcps TDD If the *E-DCH TDD Information LCR* IE includes the *E-DCH Processing Overload Level* IE, then if the DRNS could not decode the E-PUCH for the last consecutive number of TTIs, indicated in the *E-DCH Processing Overload Level* IE, because of a processing issue, the DRNS shall notify the SRNC by initiating the Radio Link Failure procedure.]

- [1.28Mcps TDD If the *E-DCH TDD Information LCR* IE includes the *E-DCH Power Offset for Scheduling Info* IE, then the DRNS shall use this value as a power offset for the transmission of scheduling information without any MAC-d PDUs.]
- [1.28Mcps TDD If the *E-DCH TDD Information LCR* IE includes the *Maximum Number of Retransmission for Scheduling Info LCR* IE and the *E-DCH Retransmission timer for Scheduling Info LCR* IE, then the DRNS shall use these parameters for the transmission of scheduling information without any MAC-d PDUs.]
- [1.28Mcps TDD If the *E-DCH TDD Information LCR* IE includes the *Multi-Carrier E-DCH Physical Layer Category LCR* IE, the DRNS shall use this information for the related resource allocation operation, and when applicable, for multi-carrier E-DCH scheduling.]
- [1.28Mcps TDD If the *UE TS0 Capability LCR* IE in the *UE Capabilities Information* IE in the *HS-DSCH Information To Modify* IE is not present, or if the *UE TS0 Capability LCR* IE in the *UE Capabilities Information* IE in the *HS-DSCH Information* IE is not present, and if the RADIO LINK RECONFIGURATION REQUEST message includes the *UE TS0 Capability LCR* IE in the *E-DCH TDD Information LCR* IE, the DRNS can use this information to allocate the downlink resources for the UE according to TS 25.306 [42].]

[7.68Mcps TDD – E-DCH Modification:]

[7.68Mcps TDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH TDD Information 7.68Mcps* IE, then:]

- [7.68Mcps TDD If the *E-DCH TDD Information 7.68Mcps* IE includes the *E-DCH TDD Maximum Bitrate 7.68Mcps* IE for an E-DCH, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
- [7.68Mcps TDD If the *E-DCH TDD Information 7.68Mcps* IE includes the *E-DCH Processing Overload Level* IE, then if the DRNS could not decode the E-PUCH for the last consecutive number of TTIs, indicated in the *E-DCH Processing Overload Level* IE, because of a processing issue, the DRNS shall notify the SRNC by initiating the Radio Link Failure procedure.]
- [7.68Mcps TDD If the *E-DCH TDD Information 7.68Mcps* IE includes the *E-DCH Power Offset for Scheduling Info* IE, then the DRNS shall use this value as a power offset for the transmission of scheduling information without any MAC-d PDUs.]

[TDD- If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH TDD Information To Modify* IE, then:]

- [TDD- If the *E-DCH TDD Information To Modify* IE contains a *E-DCH MAC-d Flow Specific Information* IE which includes the *Allocation/Retention Priority* IE, the DRNS shall apply the new Allocation/Retention Priority to this E-DCH in the new configuration according to Annex A.]
- [TDD- If the *E-DCH TDD Information To Modify* IE contains a *TNL QoS* IE for an E-DCH MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink for the related MAC-d flow.]
- [TDD- If the *E-DCH TDD Information To Modify* IE includes the *Maximum Number of Retransmissions for E-DCH* IE for an E-DCH MAC-d flow then the DRNS shall use this information to report if the maximum number of retransmissions has been exceeded.]
- [1.28Mcps TDD If the *E-DCH TDD Information To Modify* IE includes the *E-DCH MAC-d Flow Retransmission Timer* IE for an E-DCH MAC-d flow then the DRNS shall use this information to set the retransmission timer.]
- [TDD– If the *TNL QoS* IE is included in the *E-DCH TDD Information to Modify* IE for an E-DCH MAC-d flow and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNS to determine the transport bearer characteristics to apply in the uplink for the related MAC-d flow.]
- [TDD- If the *E-DCH TDD Information To Modify* IE includes the *E-DCH HARQ Power Offset TDD* IE for an E-DCH MAC-d flow the DRNS shall use this new power offset value.]
- [TDD- If the *E-DCH TDD Information To Modify* IE includes the *E-DCH MAC-d Flow Multiplexing List* IE for an E-DCH MAC-d flow the DRNS shall use this information for the related resource allocation operation.]

- [TDD- If the *E-DCH TDD Information To Modify* IE contains the *E-DCH Grant Type* IE, the DRNS shall treat the E-DCH MAC-d flow as Scheduled or Non-scheduled accordingly.]
- [TDD- If the *E-DCH TDD Information To Modify* IE includes the *E-DCH Logical Channel To Add* or *E-DCH Logical Channel To Delete* IEs, the DRNS shall use this information to add/delete the indicated logical channels. When a logical channel is deleted, all its associated configuration data shall also removed.]
- [TDD- If the *E-DCH TDD Information To Modify* IE includes the *E-DCH Logical Channel To Modify* IE, the DRNS shall use this information to modify the indicated logical channels:]
 - [TDD If the *E-DCH Logical Channel To Modify* IE includes *Scheduling Priority Indicator* IE, the DRNS shall apply the values in the new configuration.]
 - [TDD If the *E-DCH Logical Channel To Modify* IE includes *Scheduling Information* IE, the DRNS shall apply the values in the new configuration.]
 - [TDD If the *E-DCH Logical Channel To Modify* IE includes *MAC-es Guaranteed Bit Rate* IE, the DRNS shall apply the values in the new configuration.]
 - [TDD If the *E-DCH Logical Channel To Modify* IE includes E-*DCH DDI Value* IE, the DRNS shall apply the values in the new configuration.]
 - [1.28Mcps TDD If the *E-DCH Logical Channel To Modify* IE includes *MAC-es Maximum Bit Rate LC*R IE, the DRNS shall use this information for the related resource allocation operation, and when applicable, for E-DCH scheduling.]
 - [TDD If the *E-DCH Logical Channel To Modify* IE includes the *Maximum MAC-d PDU Size Extended* IE, the DRNC shall apply the value in the new configuration.]
- [TDD– If the *E-DCH TDD Information To Modify* IE includes the *MAC-e Reset Indicator* IE, then the DRNS shall use this value to determine whether MAC-e (or MAC-i) Reset is performed in the UE for sending the HARQ Failure Indication.]

[1.28Mcps TDD -Multi-Carrier E-DCH Continue:]

[1.28Mcps TDD - If the *Multi-Carrier E-DCH Information Reconf* IE is present in the RADIO LINK RECONFIGURATION REQUEST message and the choice of *Continue*, *Setup or Change* is "Continue", then the current Multi-Carrier E-DCH configuration shall not be changed.]

[1.28Mcps TDD – Multi-Carrier E-DCH Setup:]

[1.28Mcps TDD - If the *Multi-Carrier E-DCH Information Reconf* IE is present in the RADIO LINK RECONFIGURATION REQUEST message and the choice of *Continue, Setup or Change* is "Setup", then the *Multi-Carrier E-DCH Information LCR* IE defines the new configuration and then:]

- [1.28Mcps TDD The DRNS shall use the *Multi-Carrier E-DCH Transport Bearer Mode LCR* IE to decide the transport bearer mode in the new configuration.]
- [1.28Mcps TDD The DRNS shall setup the requested E-DCH resource on the uplink frequecies indicated by the *UARFCN* IE in the *Multi-Carrier E-DCH Information LCR* IE.]

[1.28Mcps TDD – Multi-Carrier E-DCH Change:]

- [1.28Mcps TDD If the *Multi-Carrier E-DCH Information Reconf* IE is present in the RADIO LINK RECONFIGURATION REQUEST message and the choice of *Continue*, *Setup or Change* is "Change", then the *Multi-Carrier E-DCH Information LCR* IE defines the new configuration and then:]
 - [1.28Mcps TDD If the *UARFCN* IE in the *Multi-Carrier E-DCH Information LCR* IE is different from current configured frequencies, then the DRNS shall setup the E-DCH resources, as requested in the DRNS Communication Context, on the uplink frequecies indicated by the *UARFCN* IE in the *Multi-Carrier E-DCH Information LCR* IE.]
 - [1.28Mcps TDD If the *UARFCN* IE in the *Multi-Carrier E-DCH Information LCR* IE is the same as any current configured frequency, then the DRNS shall reconfigure the E-DCH resources, as requested or as configured in the DRNS Communication Context, on the uplink frequecies indicated by the *UARFCN* IE in the *Multi-Carrier E-DCH Information LCR* IE.]

[1.28Mcps TDD - If the *Multi-Carrier E-DCH Information Reconf* IE is present in the RADIO LINK RECONFIGURATION REQUEST message and the choice of *Continue, Setup or Change* is "Change" and the *Removal UL Multi-Carrier info* IE is included, then the DRNS shall remove the corresponding E-DCH configuration on the uplink frequencies indicated by the *UARFCN* IE in the *Removal UL Multi-Carrier info* IE.]

General:

If the requested modifications are allowed by the DRNS, and if the DRNS has successfully allocated the required resources and changed to the new configuration, the DRNC shall respond to the SRNC with the RADIO LINK RECONFIGURATION RESPONSE message.

If the RADIO LINK RECONFIGURATION REQUEST message includes the *RL Specific DCH Information* IE, *HS-DSCH Information* IE, *HS-DSCH Information To Modify Unsynchronised* IE, *HS-DSCH MAC-d Flows To Add* IE, [FDD – *RL Specific E-DCH Information* IE] [TDD – *E-DCH MAC-d Flows to Add* IE], the DRNC may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for any Transport Channel [FDD – for which the *Transport Bearer Not Requested Indicator* IE is not included], HS-DSCH MAC-d flow being added or E-DCH MAC-d flow [FDD – for which the *Transport Bearer Not Requested Indicator* IE is not included] being added, or any Transport Channel [FDD – for which the *Transport Bearer Not Requested Indicator* IE was not included] or HS-DSCH MAC-d flow being modified for which a new transport bearer was requested with the *Transport Bearer Request Indicator* IE.

The DRNC shall include the *Transport Layer Address* IE and the *Binding ID* IE in the RADIO LINK RECONFIGURATION RESPONSE message for any Transport Channel [FDD – for which the *Transport Bearer Not Requested Indicator* IE is not included], HS-DSCH MAC-d flow being added or E-DCH MAC-d flow [FDD – for which the *Transport Bearer Not Requested Indicator* IE is not included] being added, or any Transport Channel [FDD – for which the *Transport Bearer Not Requested Indicator* IE was not included], HS-DSCH MAC-d flow or E-DCH MAC-d flow [FDD – for which the *Transport Bearer Not Requested Indicator* IE was not included] being modified for which a new transport bearer was requested with the *Transport Bearer Request Indicator* IE. The detailed frame protocol handling during transport bearer replacement is described in TS 25.427 [4], subclause 5.10.1, and in TS 25.425 [32], subclause 5.3.2.

- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *Transport Bearer Not Requested Indicator* IE set to "Transport Bearer Shall not be Established" for a DCH or an E-DCH MAC-d flow being added, then the DRNC shall not establish a transport bearer for the concerned DCH or E-DCH MAC-d flow and shall include the *Transport Bearer Not Setup Indicator* IE for the corresponding DCH or E-DCH MAC-d flow in the RADIO LINK RECONFIGURATION RESPONSE message.]
- [FDD If the RADIO LINK RECONFIGURATION REQUEST message includes the *Transport Bearer Not Requested Indicator* IE set to "Transport Bearer may not be Established" for a DCH or an E-DCH MAC-d flow being added and:]
 - [FDD if the DRNC establishes a transport bearer for the concerned DCH or E-DCH MAC-d flow, the DRNC shall include in the RADIO LINK RECONFIGURATION RESPONSE message the *Binding ID* IE and *Transport Layer Address* IE for establishment of a transport bearer for the DCH or E-DCH MAC-d flow being established.]
 - [FDD if the DRNC does not establish a transport bearer for the concerned DCH or E-DCH MAC-d flow, the DRNC shall include the *Transport Bearer Not Setup Indicator* IE for the corresponding DCH or E-DCH MAC-d flow in the RADIO LINK RECONFIGURATION RESPONSE message.]

In the case of a set of co-ordinated DCHs requiring a new transport bearer on the Iur interface, the DRNC shall include the *Transport Layer Address* IE and the *Binding ID* IE in the *DCH Information Response* IE only for one of the DCHs [FDD – for which the *Transport Bearer Not Requested Indicator* IE is not included] in the set of co-ordinated DCHs.

In the case of a Radio Link being combined with another Radio Link within the DRNS, the DRNC shall include the *Transport Layer Address* IE and the *Binding ID* IE [FDD for the concerned DCH for which the *Transport Bearer Not Requested Indicator* IE is not included]in the *DCH Information Response* IE in the RADIO LINK RECONFIGURATION RESPONSE message for only one of the combined Radio Links.

[FDD – In the case of an E-DCH RL being combined with another E-DCH RL within the DRNS, the *E-DCH FDD Information Response* IE shall be included only for one of the combined E-DCH RLs.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Additional E-DCH Cell Information RL Reconf Req* IE, then:]

- [FDD if the *Multicell E-DCH Transport Bearer Mode* IE for an Additional E-DCH to be Setup is set to "Separate Iur Transport Bearer Mode" the DRNS shall use this mode in the new configuration and apply separate transport bearers for the MAC-d flows.]
- [FDD if the *Multicell E-DCH Transport Bearer Mode* IE for an Additional E-DCH to be Setup is set to "UL Flow Multiplexing Mode" the DRNS shall use this mode in the new configuration and multiplex MAC-d flows on the transport bearers.]
- [FDD if Separate Iur Transport Bearer Mode is used in the new configuration, then:]
 - [FDD the DRNS shall follow the rules defined in this procedure for single carrier mode of operation for establishment of the transport bearer for a MAC-d flow, use the *Transport Bearer Not Requested Indicator* IE in the *RL Specific E-DCH Information* IE in the *RL Information* IE and/or the *Transport Bearer Request Indicator* IE in the *E-DCH FDD Information To Modify* IE received for the corresponding Radio Link(s) of the Primary Uplink Frequency to determine the transport bearer configuration in the new configuration for the radio links of the Secondary Uplink Frequency.]
 - [FDD If the Transport Layer Address IE and Binding ID IE is included for an E-DCH MAC-d flow in the Additional E-DCH MAC-d Flows Specific Information IE in the Additional E-DCH RL Specific Information To Setup IE in the Additional E-DCH FDD Setup Information IE in the Additional E-DCH Cell Information Setup IE or in the Additional E-DCH RL Specific Information To Add IE and/or the Additional E-DCH RL Specific Information To Modify IE in the Additional E-DCH Configuration Change Information IE in the Additional E-DCH Cell Information Configuration Change IE, then the DRNS may use the transport layer address and the binding identifier received from the SRNC when establishing a transport bearer for the concerned E-DCH MAC-d flow. If the DRNS establishes a transport bearer for the concerned E-DCH MAC-d flow the DRNS shall, for establishment of the transport bearer, include in the RADIO LINK RECONFIGURATION RESPONSE message in the Additional E-DCH Cell Information Response RLReconf IE the Binding ID IE and Transport Layer Address IE in the Additional E-DCH MAC-d Flow Specific Information Response IE for new E-DCH radio links on the Secondary UL frequency and/or include the Binding ID IE and Transport Layer Address IE in the Additional Modified E-DCH FDD Information Response IE for radio links on the Secondary UL frequency that has been modified.]

[1.28Mcps TDD - If the RADIO LINK RECONFIGURATION REQUEST message includes the *Multi-Carrier E-DCH Information Reconf* IE, then:]

- [1.28Mcps TDD If the *Multi-carrier E-DCH Transport Bearer Mode LCR* IE is set to "Separate Iur Transport Bearer Mode" the DRNS shall use this mode in the new configuration and apply separate transport bearers for the MAC-d flows.]
- [1.28Mcps TDD If the *Multi-Carrier E-DCH Transport Bearer Mode LCR* IE is set to "UL Flow Multiplexing Mode" the DRNS shall use this mode in the new configuration and multiplex each MAC-d flow on one transport bearer.]
- [1.28Mcps TDD If the choice of *Continue, Setup or Change* in the the *Multi-Carrier E-DCH Information Reconf* IE is "Setup" and the Separate Iur transport bearer mode is used in the new configuration, or if the choice of *Continue, Setup or Change* in the the *Multi-Carrier E-DCH Information Reconf* IE is "Change" and the Transport Bearer Mode is changed to "Separate Iur Transport Bearer Mode" indicated by *Multi-carrier E-DCH Transport Bearer Mode LCR* IE, then the DRNS shall include the *Binding ID* IE and *Transport Layer Address* IE in the *Multi-Carrier E-DCH Information Response LCR* IE in the RADIO LINK RECONFIGURATION RESPONSE message for establishment of a transport bearer for every E-DCH MAC-d flow being established.]
- [1.28Mcps TDD The DRNS shall follow the rules defined in this procedure for single carrier mode of operation for establishment of the transport bearer for a MAC-d flow, use the *Transport Bearer Request Indicator* IE in the *E-DCH TDD Information to Modify* IE received for the corresponding Radio Link to determine the transport bearer configuration in the new configuration for the all Uplink Frequencies.]
- [1.28Mcps TDD If the E-DCH UL flow multiplexing mode is used in the new configuration and if the *Transport Bearer Request Indicator* IE is set to "Bearer Requested", then the DRNS shall include the *Binding ID* IE and *Transport Layer Address* IE in the *E-DCH TDD Information Response 1.28Mcps* IE in the RADIO LINK RECONFIGURATION RESPONSE message for establishment of a transport bearer for every E-DCH MAC-d flow being established.]

Any allowed rate for the uplink of a modified DCH provided for the old configuration will not be valid for the new configuration. If the DRNS needs to limit the user rate in the uplink of a DCH due to congestion caused by the UL UTRAN Dynamic Resources (see subclause 9.2.1.79) in the new configuration for a Radio Link, the DRNC shall include in the RADIO LINK RECONFIGURATION RESPONSE message the *Allowed UL Rate* IE in the *DCH Information Response* IE for this Radio Link.

Any allowed rate for the downlink of a modified DCH provided for the old configuration will not be valid for the new configuration. If the DRNS needs to limit the user rate in the downlink of a DCH due to congestion caused by the DL UTRAN Dynamic Resources (see subclause 9.2.1.79) in the new configuration for a Radio Link, the DRNC shall include in the RADIO LINK RECONFIGURATION RESPONSE message the *Allowed DL Rate* IE in the *DCH Information Response* IE for this Radio Link.

The DRNS decides the maximum and minimum SIR for the uplink of the Radio Link(s), and the DRNC shall include in the RADIO LINK RECONFIGURATION RESPONSE message the *Maximum Uplink SIR* IE and *Minimum Uplink SIR* IE for each Radio Link when these values are changed.

[FDD – If the DL TX power upper or lower limit has been re-configured, the DRNC shall include the new value(s) in the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the RADIO LINK RECONFIGURATION RESPONSE message. The DRNS shall not transmit with a higher power than indicated by the *Maximum DL TX Power* IE or lower than indicated by the *Minimum DL TX Power* IE on any DL DPCH or on the F-DPCH of the RL except, if the UE Context is configured to use DPCH in the downlink, during compressed mode, when the δP_{curr} , as described in TS 25.214 [10] subclause 5.2.1.3, shall be added to the maximum DL power for the associated compressed frame.]

[3.84 Mcps TDD and 7.68 Mcps TDD – If the DL TX power upper or lower limit has been re-configured, the DRNC shall include the new value(s) in the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the RADIO LINK RECONFIGURATION RESPONSE message. If the maximum or minimum power needs to be different for particular DCH type CCTrCHs, the DRNC shall include the new value(s) for that CCTrCH in the *CCTrCH Maximum DL TX Power* IE and *CCTrCH Minimum DL TX Power*. The DRNS shall not transmit with a higher power than indicated by the appropriate *Maximum DL TX Power* IE/CCTrCH Maximum DL TX Power IE or lower than indicated by the appropriate *Minimum DL TX Power* IE/CCTrCH Minimum DL TX Power IE on any DL DPCH within each CCTrCH of the RL.]

[1.28 Mcps TDD – If the DL TX power upper or lower limit has been re-configured, the DRNC shall include the new value(s) in the *Maximum DL TX Power* IE and *Minimum DL TX Power* IE in the RADIO LINK RECONFIGURATION RESPONSE message. If the maximum or minimum power needs to be different for particular timeslots within a DCH type CCTrCH, the DRNC shall include the new value(s) for that timeslot in the *Maximum DL TX Power* IE and *Minimum DL TX Power* within the *DL Timeslot Information LCR* IE. The DRNS shall not transmit with a higher power than indicated by the appropriate *Maximum DL TX Power* IE or lower than indicated by the appropriate *Minimum DL TX Power* IE on any DL DPCH within each timeslot of the RL.]

8.3.7.3 Unsuccessful Operation




Figure 15: Unsynchronised Radio Link Reconfiguration procedure, Unsuccessful Operation

If the DRNS cannot allocate the necessary resources for all the new DCHs in a set of co-ordinated DCHs requested to be added, it shall reject the Unsynchronised Radio Link Reconfiguration procedure as having failed.

If the requested Unsynchronised Radio Link Reconfiguration procedure fails for one or more Radio Link(s), the DRNC shall send the RADIO LINK RECONFIGURATION FAILURE message to the SRNC, indicating the reason for failure.

[FDD – If the MIMO Activation Indicator IE is included and the Power Offset For S-CPICH for MIMO Request Indicator IE is not included in the HS-DSCH FDD Information IE in the HS-DSCH Serving Cell Change Information IE in the RADIO LINK RECONFIGURATION REQUEST message or MIMO is activated and the power offset for S-CPICH for MIMO Request indicator has not been configured in the UE Context but MIMO pilot configuration with Primary and Secondary CPICH is set up with a non-zero power offset on the cell where the Serving HS-DSCH Radio

Link is established, the setup of the serving HS-DSCH Radio Link, and/or activation of MIMO, shall be reported as failed and the DRNC shall include in the RADIO LINK RECONFIGURATION FAILURE message the *Cause* IE.]

Typical cause values are:

Radio Network Layer Causes:

UL Scrambling Code Already in Use;

DL Radio Resources not Available;

UL Radio Resources not Available;

Requested Configuration not Supported;

CM not Supported;

E-DCH not supported;

[FDD – Continuous Packet Connectivity DTX-DRX operation not Supported;]

[FDD – Continuous Packet Connectivity HS-SCCH less operation not Supported;]

[FDD – MIMO not supported;]

[FDD – E-DCH TTI2ms not supported;]

[FDD – Continuous Packet Connectivity DTX-DRX operation not available;]

[FDD - Continuous Packet Connectivity UE DTX Cycle not available;]

[FDD – MIMO not available;]

[FDD – SixteenQAM UL not Supported;]

HS-DSCH MAC-d PDU Size Format not supported;

E-DCH MAC-d PDU Size Format not available;

[FDD – E-DPCCH Power Boosting not supported;]

[FDD – SixtyfourQAM DL and MIMO Combined not available;]

[FDD – Multi Cell operation not available;]

[FDD – Multi Cell operation not supported;]

[FDD – SixtyfourQAM DL and MIMO Combined not supported;]

[1.28Mcps TDD – MIMO not available;]

[1.28Mcps TDD- SixteenQAM UL not Supported;]

[1.28Mcps TDD – SixtyfourQAM DL and MIMO Combined not available;]

[FDD – Single Stream MIMO not supported;]

[FDD – Single Stream MIMO not available;]

[FDD – Multi Cell operation with MIMO not available;]

[FDD – Multi Cell operation with MIMO not supported;]

[FDD – Multi Cell E-DCH Operation not supported;]

[FDD – Multi Cell E-DCH Operation not available;]

[FDD – Multi Cell operation with Single Stream MIMO not available;]

[FDD – Multi Cell operation with Single Stream MIMO not supported.]

Miscellaneous Causes:

Control Processing Overload;

Not enough User Plane Processing Resources.

8.3.7.4 Abnormal Conditions

If only a subset of all the DCHs belonging to a set of co-ordinated DCHs is requested to be deleted, the DRNS shall reject the Unsynchronised Radio Link Reconfiguration procedure as having failed, and the DRNC shall send the RADIO LINK RECONFIGURATION FAILURE message to the SRNC.

If more than one DCH of a set of co-ordinated DCHs has the *QE-Selector* IE set to "selected" [TDD – or no DCH of a set of co-ordinated DCHs has the *QE-Selector* IE set to "selected"], the DRNS shall reject the Unsynchronised Radio Link Reconfiguration procedure, and the DRNC shall respond with a RADIO LINK RECONFIGURATION FAILURE message.

If the RADIO LINK RECONFIGURATION REQUEST message includes a *DCHs To Modify* IE or *DCHs To Add* IE with multiple *DCH Specific Info* IEs, and if the DCHs in the *DCHs To Modify* IE or *DCHs To Add* IE do not have the same *Transmission Time Interval* IE in the *Semi-static Transport Format Information* IE, then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *DL Reference Power Information* IE, but the power balancing is not active in the indicated RL(s), the DRNS shall reject the Unsynchronised Radio Link Reconfiguration procedure as having failed and the DRNC shall respond the RADIO LINK RECONFIGURATION FAILURE message with the cause value "Power Balancing status not compatible".]

[FDD – If the power balancing is active with the Power Balancing Adjustment Type of the UE Context set to "Common" in the existing RL(s) but the *DL Reference Power Information* IE includes the *Individual DL Reference Power Information* IE, the DRNS shall reject the Unsynchronised Radio Link Reconfiguration procedure as having failed and the DRNC shall respond with the RADIO LINK RECONFIGURATION FAILURE message with the cause value "Power Balancing status not compatible".]

[FDD – If the power balancing is active with the Power Balancing Adjustment Type of the UE Context set to "Individual" in the existing RL(s) but the *DL Reference Power Information* IE includes the *Common DL Reference Power* IE, the DRNS shall reject the Unsynchronised Radio Link Reconfiguration procedure as having failed and the DRNC shall respond with the RADIO LINK RECONFIGURATION FAILURE message with the cause value "Power Balancing status not compatible".]

If the RADIO LINK RECONFIGURATION REQUEST message contains the *Transport Layer Address* IE or the *Binding ID* IE when establishing a transport bearer for any Transport Channel or HS-DSCH MAC-d flow being added, or any Transport Channel or HS-DSCH MAC-d flow being modified for which a new transport bearer was requested with the *Transport Bearer Request Indicator* IE., and not both are present for a transport bearer intended to be established, the DRNC shall reject the Unsynchronised Radio Link Reconfiguration procedure, and the DRNC shall respond with a RADIO LINK RECONFIGURATION FAILURE message.

If the RADIO LINK RECONFIGURATION REQUEST message contains any of the *HS-DSCH Information To Modify* IE, *HS-DSCH MAC-d Flows To Add* IE or *HS-DSCH MAC-d Flows To Delete* IE in addition to the *HS-DSCH Information* IE, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If the RADIO LINK RECONFIGURATION REQUEST message contains any of the *HS-DSCH Information To Modify* IE, *HS-DSCH MAC-d Flows To Add* IE, *HS-DSCH MAC-d Flows To Delete* IE or *HS-PDSCH RL ID* IE and the Serving HS-DSCH Radio Link is not in the DRNS, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If the RADIO LINK RECONFIGURATION REQUEST message includes the *HS-DSCH Information* IE and does not include the *HS-PDSCH RL-ID* IE, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If the RADIO LINK RECONFIGURATION REQUEST message includes the *HS-PDSCH RL-ID* IE indicating a Radio Link not existing in the UE Context, the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If the RADIO LINK RECONFIGURATION REQUEST message contains any of the *HS-DSCH Information* IE, *HS-DSCH Information To Modify* IE, or *HS-DSCH MAC-d Flows To Add* IE and if in the new configuration the Priority Queues associated with the same *HS-DSCH MAC-d Flow ID* IE have the same *Scheduling Priority Indicator* IE value, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If, in the new configuration, the concerned UE Context is configured to use "Indexed MAC-d PDU Size" for an HS-DSCH but there exist a priority queue of the MAC-d flows of the HS-DSCH that is configured to use Maximum MAC-d PDU Size Extended, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If, in the new configuration, the concerned UE Context is configured to use "Flexible MAC-d PDU Size" for an HS-DSCH but there exist a priority queue of the MAC-d flows of the HS-DSCH that is configured to use MAC-d PDU Size Index, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If, in the new configuration, the UE Context is configured to use "Fixed MAC-d PDU Size" for an E-DCH and there exist a Logical Channel of the MAC-d flows of the E-DCH that is configured to use Maximum MAC-d PDU Size Extended, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If, in the new configuration, the concerned UE Context is configured to use "Flexible MAC-d PDU Size" for an E-DCH and there exist a Logical Channel of the MAC-d flows of the E-DCH that is configured to use MAC-d PDU Size List, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If the RADIO LINK RECONFIGURATION REQUEST message includes *HS-DSCH Information* IE and the HS-DSCH is already configured in the UE Context, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

[FDD – If the *E-DCH FDD Information* IE is present in the RADIO LINK RECONFIGURATION REQUEST message, but the *E-DPCH Information* IE is not present or if any of the *Maximum Set of E-DPDCHs* IE, *Puncture Limit* IE, *E-TFCS Information* IE, *E-TTI* IE, *E-DPCCH Power Offset* IE, *E-RGCH 2-Index-Step Threshold* IE, *E-RGCH 3-Index-Step Threshold* IE, *HARQ Info for E-DCH* IE or *HS-DSCH Configured Indicator* IE are not present in the *E-DPCH Information* IE, then the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If any of the *HS-DSCH Configured Indicator* IE, *Maximum Set of E-DPDCHs* IE, *Puncture Limit* IE or *E-TTI* IE are present in the *E-DPCH Information* IE and the *E-DCH FDD Information* IE is not present in the RADIO LINK RECONFIGURATION REQUEST message, then the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH RL Indication* IE set to "E-DCH", but no *E-DCH FDD Information* IE, and the UE Context is not configured for E-DCH, then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH FDD Information* IE but no *E-DCH RL Indication* IE set to "E-DCH", then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

If the RADIO LINK RECONFIGURATION REQUEST message contains the *HS-PDSCH RL ID* IE and/or the *Serving E-DCH RL* IE and if both HS-DSCH and E-DCH are configured in the new configuration but the Serving HS-DSCH Radio Link and the Serving E-DCH Radio Link are not in the same cell then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message contains the *HS-PDSCH RL ID* IE and the *E-DPCH Information* IE which includes the *HS-DSCH Configured Indicator* IE set as "HS-DSCH not configured" then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message contains any of the *E-DCH FDD Information To Modify* IE, *E-DCH MAC-d Flows To Add* IE or *E-DCH MAC-d Flows To Delete* IE in addition to the *E-DCH FDD Information* IE, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message contains any of the *E-DCH FDD Information To Modify* IE, *E-DCH MAC-d Flows To Add* IE, *E-DCH MAC-d Flows To Delete* IE and the UE Context is not configured for E-DCH, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *E-DCH FDD Information To Modify* IE deleting the last remaining E-DCH Logical Channel of an E-DCH MAC-d Flow, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes *E-DCH FDD Information* IE and the E-DCH is already configured in the UE Context, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Continuous Packet Connectivity DTX-DRX Information To Modify* IE in addition to the *Continuous Packet Connectivity DTX-DRX Information* IE, then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Continuous Packet Connectivity HS-SCCH less Deactivate Indicator* IE in addition to the *Continuous Packet Connectivity HS-SCCH less Information* IE, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Continuous Packet Connectivity HS-SCCH less Deactivate Indicator* IE while the Continuous Packet Connectivity HS-SCCH less configuration isn't configured in the DRNC, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Continuous Packet Connectivity DTX-DRX Information To Modify* IE while the Continuous Packet Connectivity *DTX-DRX* configuration isn't configured in the DRNC, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *DRX Information To Modify* IE in *Continuous Packet Connectivity DTX-DRX Information To Modify* IE while the Continuous Packet Connectivity DRX configuration is not configured in the DRNC, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

If the *DCHs to Modify* IE contains a *DCH Specific Info* IE which includes the *Unidirectional DCH Indicator* IE set to "Uplink DCH only" but no *Transport Format Set* IE for the uplink for this DCH and the DRNC had ignored the configuration of Transport Format Set for uplink, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If the *DCHs to Modify* IE contains a *DCH Specific Info* IE which includes the *Unidirectional DCH Indicator* IE set to "Downlink DCH only" but no *Transport Format Set* IE for the downlink for this DCH and the DRNC had ignored the configuration of Transport Format Set for downlink, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message contains the *Transport Bearer Not Requested Indicator* IE for a DCH or an E-DCH MAC-d flow but does not contain the corresponding *DCH ID* IE and the *Unidirectional DCH indicator* IE set to "Uplink DCH only" for the DCH in *DCH Information To Add* IE or does not contain the corresponding *E-DCH MAC-d Flow ID* IE in *E-DCH MAC-d Flows Information* IE, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the concerned UE Context is configured to apply UL DPCCH Slot Format 0 or 2 and execute Continuous Packet Connectivity DTX-DRX operation, then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the concerned UE Context is configured to apply MIMO, allowed to apply 64QAM, establish the secondary serving HS-DSCH Radio Link or apply Single Stream MIMO in the new configuration but is not configured to use flexible MAC-d PDU Size, then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message contains the *Additional HS Cell Information RL Reconf Req* IE indicating a new seconadry serving cell that is not in the same Node B as the serving HS-DSCH cell (or new serving in case of simultaneous serving HS-DSCH cell change), then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Transport Bearer Not Requested Indicator* IE for a DCH in the *RL Specific DCH Information* IE but does not include the *DCH ID* IE for the DCH in the *DCHs to Add* IE, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Transport Bearer Not Requested Indicator* IE for an E-DCH MAC-d flow in the *RL Specific E-DCH Information* IE but does not include the *E-DCH MAC-d flow ID* IE for the E-DCH MAC-d flow in the *E-DCH MAC-d flows Information* IE, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message contains the *Continuous Packet Connectivity DTX-DRX Information* IE but the concerned UE Context is not previously configured to use F-DPCH, then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message]

[FDD – If the concerned UE Context is configured to have the Serving E-DCH Radio Link but there is at least one E-DCH MAC-d flow which the transport bearer is not configured for the Serving E-DCH Radio Link in DRNS, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message includes the *Transport Bearer Not Requested Indicator* IE for a DCH or an E-DCH MAC-d Flow for a specific RL and the specific RL is combined with existing RL which the transport bearer is established for the DCH or the E-DCH MAC-d Flow in the DRNS, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

If ALCAP is not used, if the concerned UE Context is configured to establish a DCH, an E-DCH MAC-d flow and/or an HS-DSCH MAC-d flow but the RADIO LINK RECONFIGURATION REQUEST message does not include the *Transport Layer Address* IE and the *Binding ID* IE for the DCH, the E-DCH MAC-d flow and/or HS-DSCH MAC-d flow, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If, in the new configuration, there exist a priority queue of the MAC-d flows of the HS-DSCH that is configured to use "Flexible RLC PDU Size" for an HS-DSCH but is not configured to use Maximum MAC-d PDU Size Extended, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

If, in the new configuration, the concerned UE Context is configured to use MAC-d PDU Size Index for an HS-DSCH but there exist a priority queue of the MAC-d flows of the HS-DSCH that is configured to use "Flexible RLC PDU Size", the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message contains a *MIMO Activation Indicator* IE and a *Single Stream MIMO Activation Indicator* IE in the *HS-DSCH FDD Information* IE or in the *HS-DSCH FDD Secondary Serving Information* IE in the *Additional HS Cell Information RL Reconf Req* IE, then the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the concerned UE Context is configured to apply MIMO and Single Stream MIMO for the HS-DSCH Radio Link or the Secondary Serving Radio link, the DRNC shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message contains the *Additional E-DCH Cell Information RL Reconf Req* IE and if the *E-DPCH Information* IE is not present or the E-DPCH Information was not configured in the UE Context, then the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message contains the *Additional E-DCH Cell Information RL Reconf Req* IE and there exist a logical channel for which the *Maximum MAC-d PDU Size Extended* IE in the *E-DCH MAC-d Flows Information* IE in the *E-DCH FDD Information* IE is not present, the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD – If the RADIO LINK RECONFIGURATION REQUEST message contains the *Additional E-DCH RL Specific Information To Setup* IE in the *Additional E-DCH FDD Setup Information* IE in the *Additional E-DCH Cell Information Setup* IE in the *Additional E-DCH Cell Information RL Reconf Req* IE and the *C-ID* IE is not included but the RL indicated by the *E-DCH Additional RL ID* IE is not configured in the current UE context as a Secondary Serving HS-DSCH radio link without any configured Additional E-DCH, the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD - If the RADIO LINK RECONFIGURATION REQUEST message contains the *Additional HS Cell Information RL Reconf Req* IE and the new configuration contains more than one secondary serving HS-DSCH RL, and all secondary serving HS-DSCH RLs in the new configuration will not be assigned consecutive ordinal numbers starting with the value "1"which are previously assigned to the RL or received in the *Ordinal Number Of Frequency* IE in the *HS-DSCH FDD Secondary Serving Information* IE or the *HS-DSCH FDD Secondary Serving Information To Modify Unsynchronised* IE, the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

[FDD - If the RADIO LINK RECONFIGURATION REQUEST message contains the *Additional HS Cell Information RL Reconf Req* IE and the new configuration contains more than one secondary serving HS-DSCH RL, the new configuration also contains an Additional E-DCH Serving Radio Link and the secondary serving HS-DSCH Radio link, which is configured in the same cell as the Additional E-DCH Serving Radio Link does not have Ordinal Number Of Frequency value "1", the DRNS shall reject the procedure using the RADIO LINK RECONFIGURATION FAILURE message.]

8.3.8 Physical Channel Reconfiguration

8.3.8.1 General

The Physical Channel Reconfiguration procedure is used by the DRNS to request the SRNC to reconfigure one of the configured physical channels.

This procedure shall use the signalling bearer connection for the relevant UE Context.

The DRNS shall not initiate the Physical Channel Reconfiguration procedure if a Prepared Reconfiguration exists as defined in subclause 3.1, or if a Synchronised Radio Link Reconfiguration Preparation procedure, Unsynchronised Radio Link Reconfiguration procedure or Radio Link Deletion procedure is ongoing for the relevant UE context.

8.3.8.2 Successful Operation




Figure 16: Physical Channel Reconfiguration procedure, Successful Operation

When the DRNC detects the need to modify one of its physical channels, it shall send a PHYSICAL CHANNEL RECONFIGURATION REQUEST to the SRNC.

The PHYSICAL CHANNEL RECONFIGURATION REQUEST message contains the new value(s) of the physical channel parameter(s) of the radio link for which the DRNC is requesting the reconfiguration.

[FDD – If compressed mode is prepared or active and at least one of the downlink compressed mode methods is "SF/2", the DRNC shall include the *Transmission Gap Pattern Sequence Scrambling Code Information* IE in the *DL Code Information* IE in the PHYSICAL CHANNEL RECONFIGURATION REQUEST message indicating for each DL Channelisation Code whether the alternative scrambling code will be used or not if the downlink compressed mode methods "SF/2" is activated.]

[TDD – The SRNC shall apply the new values for any of [3.84Mcps TDD – *UL Code Information* IE, *Midamble Shift And Burst Type* IE,] [1.28Mcps TDD – *UL Code Information LCR* IE, *Midamble Shift LCR* IE,] [7.68 Mcps TDD – *UL Code Information 7.68 Mcps* IE, *Midamble Shift And Burst Type 7.68 Mcps* IE,] *TDD DPCH Offset* IE, *Repetition Period* IE, *Repetition Length* IE, or *TFCI presence* IE included in the *UL DPCH Information* IE within the PHYSICAL CHANNEL RECONFIGURATION REQUEST message, otherwise the previous values specified for this DPCH shall still apply.]

[TDD – The SRNC shall apply the new values for any of [3.84Mcps TDD – *DL Code Information* IE, *Midamble Shift And Burst Type* IE,] [1.28Mcps TDD – *DL Code Information LCR* IE, *Midamble Shift LCR* IE,] [7.68 Mcps TDD – *DL Code Information 7.68 Mcps* IE, *Midamble Shift And Burst Type 7.68 Mcps* IE,] *TDD DPCH Offset* IE *Repetition Period* IE, *Repetition Length* IE, or *TFCI presence* IE included in the *DL DPCH Information* IE within the PHYSICAL CHANNEL RECONFIGURATION REQUEST message, otherwise the previous values specified for this DPCH shall still apply.]

[3.84 Mcps TDD – If the PHYSICAL CHANNEL RECONFIGURATION REQUEST includes *HS-PDSCH Timeslot Specific Information* IE the SRNC shall apply the values of the *Midamble Shift And Burst Type* IE for each HS-PDSCH timeslot.]

[1.28 Mcps TDD – If the PHYSICAL CHANNEL RECONFIGURATION REQUEST includes HS-PDSCH Timeslot Specific Information LCR IE the SRNC shall apply the values of the Midamble Shift LCR IE for each HS-PDSCH timeslot.]

[1.28 Mcps TDD – if the PHYSICAL CHANNEL RECONFIGURATION REQUEST includes the *PLCCH Information* IE the SRNC shall modify, delete or grant a new PLCCH assignment to the indicated timeslot of the indicated UL DCH-type CCTrCH according to its content.]

[7.68 Mcps TDD – If the PHYSICAL CHANNEL RECONFIGURATION REQUEST includes *HS-PDSCH Timeslot Specific Information 7.68 Mcps* IE the SRNC shall apply the values of the *Midamble Shift And Burst Type 7.68 Mcps* IE for each HS-PDSCH timeslot.]

[FDD – If the PHYSICAL CHANNEL RECONFIGURATION REQUEST includes F-DPCH Slot F-ormat E in the SRNC shall apply the values of the F-DPCH E-DPCH E-DPCH

Upon receipt of the PHYSICAL CHANNEL RECONFIGURATION REQUEST, the SRNC shall decide an appropriate execution time for the change. The SRNC shall respond with a PHYSICAL CHANNEL RECONFIGURATION COMMAND message to the DRNC that includes the *CFN* IE indicating the execution time.

At the CFN, the DRNS shall switch to the new configuration that has been requested, and release the resources related to the old physical channel configuration.

8.3.8.3 Unsuccessful Operation




Figure 17: Physical Channel Reconfiguration procedure, Unsuccessful Operation

If the SRNC cannot accept the reconfiguration request it shall send the PHYSICAL CHANNEL RECONFIGURATION FAILURE message to the DRNC, including the reason for the failure in the *Cause* IE.

Typical cause values are:

Radio Network Layer Causes:

Reconfiguration not Allowed.

8.3.8.4 Abnormal Conditions

While waiting for the PHYSICAL CHANNEL RECONFIGURATION COMMAND message, if the DRNC receives any of the RADIO LINK RECONFIGURATION PREPARE, RADIO LINK RECONFIGURATION REQUEST, or RADIO LINK DELETION REQUEST messages, the DRNC shall abort the Physical Channel Reconfiguration procedure. These messages thus override the DRNC request for physical channel reconfiguration.

When the SRNC receives a PHYSICAL CHANNEL RECONFIGURATION REQUEST message while a Synchronised Radio Link Reconfiguration procedure, Unsynchronised Radio Link Reconfiguration procedure or Radio Link Deletion procedure is ongoing, the SRNC shall ignore the request message and assume that receipt of any of the messages RADIO LINK RECONFIGURATION PREPARE, RADIO LINK RECONFIGURATION REQUEST or RADIO LINK DELETION REQUEST by the DRNC has terminated the Physical Channel Reconfiguration procedure. In this case the SRNC shall not send a PHYSICAL CHANNEL RECONFIGURATION FAILURE message to the DRNC.

8.3.9 Radio Link Failure

8.3.9.1 General

This procedure is started by the DRNS when one or more Radio Links [FDD – or Radio Link Sets][TDD – or CCTrCHs within a Radio Link] are no longer available.

This procedure shall use the signalling bearer connection for the relevant UE Context.

The DRNS may initiate the Radio Link Failure procedure at any time after establishing a Radio Link.

8.3.9.2 Successful Operation




Figure 18: Radio Link Failure procedure, Successful Operation

When the DRNC detects that one or more Radio Link(s) [FDD – or Radio Link Set(s)] [TDD – or CCTrCHs within a Radio Link] are no longer available, it shall send the RADIO LINK FAILURE INDICATION message to the SRNC. The message indicates the failed Radio Link(s) [FDD – or Radio Link Set(s)] [TDD – or CCTrCHs] with the most appropriate cause values defined in the *Cause* IE. If the failure concerns one or more individual Radio Links the DRNC shall include the affected Radio Link(s) using the *RL Information* IE. [FDD – If the failure concerns one or more Radio Link Set(s) the DRNC shall include the affected Radio Link Set(s) using the *RL Set Information* IE.] [TDD – If the failure concerns only the failure of one or more CCTrCHs within in a radio link the DRNC shall include the affected CCTrCHs using the *CCTrCH ID* IE.]

When the RL Failure procedure is used to notify loss of UL synchronisation of a [FDD – Radio Link Set] [TDD – Radio Link or CCTrCHs within a Radio Link] on the Uu interface, the RADIO LINK FAILURE INDICATION message shall be sent with the *Cause* IE set to "Synchronisation Failure" when indicated by the UL synchronisation detection algorithm defined in TS 25.214 [10] subclause 4.3 and TS 25.224 [22] subclause 4.4.2.

[FDD – When the Radio Link Failure procedure is used to indicate permanent failure in one or more Radio Link(s)/Radio Link Set(s) due to the occurrence of an UL or DL frame with more than one transmission gap caused by one or more compressed mode pattern sequences, the DL transmission shall be stopped and the RADIO LINK FAILURE INDICATION message shall be sent with the *Cause Value* IE set to "Invalid CM Settings". After sending the RADIO LINK FAILURE INDICATION message to notify the permanent failure, the DRNS shall not remove the Radio Link(s)/Radio Link Set(s) from the UE Context, or remove the UE Context itself.]

[FDD – When the Radio Link Failure Procedure is used to indicate E-DCH non serving cell processing issue, the RADIO LINK FAILURE INDICATION shall be sent, with the *Cause* IE set to "Not enough user plane processing resources".]

In the other cases the Radio Link Failure procedure is used to indicate that one or more Radio Link(s) [FDD – or Radio Link Set(s)] are permanently unavailable and cannot be restored. After sending the RADIO LINK FAILURE INDICATION message to notify the permanent failure, the DRNS shall not remove the Radio Link from the UE Context, or remove the UE Context itself. When applicable, the allocation retention priorities associated with the transport channels shall be used by the DRNS to prioritise which Radio Links to indicate as unavailable to the SRNC.

Typical cause values are:

Radio Network Layer Causes:

Synchronisation Failure; Invalid CM Settings.

Transport Layer Causes:

Transport Resources Unavailable.

Miscellaneous Causes:

Control Processing Overload; HW Failure; O&M Intervention; Not enough user plane processing resources.

8.3.9.3 Abnormal Conditions

-

8.3.10 Radio Link Restoration

8.3.10.1 General

This procedure is used to notify establishment and re-establishment of UL synchronisation of one or more [FDD – RL Set(s)] [TDD – Radio Links or CCTrCH(s) in a Radio Link] on the Uu interface.

This procedure shall use the signalling bearer connection for the relevant UE Context.

The DRNC may initiate the Radio Link Restoration procedure at any time after establishing a Radio Link.

8.3.10.2 Successful Operation



Figure 19: Radio Link Restoration procedure, Successful Operation

The DRNC shall send the RADIO LINK RESTORE INDICATION message to the SRNC when and as specified by the UL Uu synchronisation detection algorithm defined in TS 25.214 [10] subclause 4.3 and TS 25.224 [22] subclause 4.4.2 [FDD -, or when the *Fast Reconfiguration Mode* IE has been included in the RADIO LINK RECONFIGURATION COMMIT message and the DRNS has detected that the UE has changed to the new configuration. The algorithm in TS 25.214 [10] shall use the minimum value of the parameters N_INSYNC_IND that are configured in the cells supporting the radio links of the RL Set.]

[TDD – If the re-established UL Uu synchronisation concerns one or more individual Radio Links the DRNC shall include in the RADIO LINK RESTORE INDICATION message the *RL Information* IE to indicate the affected Radio Link(s). If the re-established synchronisation concerns one or more individual CCTrCHs within a radio link the DRNS shall include in the RADIO LINK RESTORE INDICATION message the *RL Information* IE to indicate the affected CCTrCHs.] [FDD – If the re-established UL Uu synchronisation concerns one or more Radio Link Sets the DRNC shall include in the RADIO LINK RESTORE INDICATION message the *RL Set Information* IE to indicate the affected Radio Link Set(s).]

[FDD – The DRNC shall send the RADIO LINK RESTORE INDICATION message when the E-DCH processing issue condition has ceased.]

8.3.10.3 Abnormal Conditions

_

8.3.11 Dedicated Measurement Initiation

8.3.11.1 General

This procedure is used by an SRNS to request the initiation of dedicated measurements in a DRNS.

This procedure shall use the signalling bearer connection for the relevant UE Context.

The Dedicated Measurement Initiation procedure shall not be initiated if a Prepared Reconfiguration exists, as defined in subclause 3.1.

8.3.11.2 Successful Operation




Figure 20: Dedicated Measurement Initiation procedure, Successful Operation

The procedure is initiated with a DEDICATED MEASUREMENT INITIATION REQUEST message sent from the SRNC to the DRNC.

Upon receipt, the DRNC shall initiate the requested dedicated measurement according to the parameters given in the DEDICATED MEASUREMENT INITIATION REQUEST message.

If the Dedicated Measurement Object Type is indicated as being "RL" in the DEDICATED MEASUREMENT INITIATION REQUEST message, measurement results shall be reported for all the indicated Radio Links.

[FDD – If the Dedicated Measurement Object Type is indicated as being "RLS" in the DEDICATED MEASUREMENT INITIATION REQUEST message, measurement results shall be reported for all the indicated Radio Link Sets.]

[FDD – If the Dedicated Measurement Object Type is indicated as being "ALL RL" in the DEDICATED MEASUREMENT INITIATION REQUEST message, measurement results shall be reported for all current and future Radio Links within the UE Context.]

[TDD – If the Dedicated Measurement Object Type is indicated as being "ALL RL" in the DEDICATED MEASUREMENT INITIATION REQUEST message, measurement results shall be reported for one existing DPCH per CCTrCH in each used time slot of current and future Radio Links within the UE Context, provided the measurement type is applicable to the respective DPCH.]

[FDD – If the Dedicated Measurement Object Type is indicated as being "ALL RLS" in the DEDICATED MEASUREMENT INITIATION REQUEST message, measurement results shall be reported for all the existing and future Radio Link Sets within the UE Context.]

[TDD – If the *DPCH ID* IE or *DPCH ID 7.68Mcps* IE is provided within the RL Information, the measurement request shall apply for the requested physical channel individually. If no *DPCH ID* IE, *DPCH ID 7.68Mcps* IE or *HS-SICH ID* IE is provided within the RL Information the measurement request shall apply for one existing DPCH per CCTrCH in each used time slot of the Radio Link, provided the measurement type is applicable to this DPCH.]

[TDD – If the *HS-SICH Information* IE is provided within the RL Information, the measurement request shall apply for the requested physical channel individually.]

[TDD – If the *Dedicated Measurement Type* IE is set to "HS-SICH reception quality", the DRNS shall initiate measurements of the failed, missed and total HS-SICH transmissions on all of the HS-SICH assigned to this UE Context. If either the failed or missed HS-SICH transmission satisfies the requested report characteristics, the DRNS shall report the result of both failed and missed transmission measurements along with the total number of transmissions.]

Report characteristics

The *Report Characteristics* IE indicates how the reporting of the dedicated measurement shall be performed. See also Annex B.

If the *Report Characteristics* IE is set to "On Demand" and if the *CFN* IE is not provided, the DRNS shall report the measurement result immediately in the DEDICATED MEASUREMENT INITIATION RESPONSE message. If the *CFN* IE is provided, it indicates the frame for which the measurement value shall be provided. The provided measurement value shall be the one reported by the layer 3 filter, referred to as point C in the measurement model (TS 25.302 [26]).

If the *Report Characteristics* IE is set to "Periodic" and if the *CFN* IE is not provided, the DRNS shall immediately and periodically initiate the Dedicated Measurement Reporting procedure for this measurement, with a frequency as specified by the *Report Periodicity* IE. If the *CFN* IE is provided, the DRNS shall initiate a Dedicated Measurement Reporting procedure for this measurement at the CFN indicated in the *CFN* IE, and shall repeat this initiation periodically thereafter with a frequency as specified by the *Report Periodicity* IE. The provided measurement value shall be the one reported by the layer 3 filter, referred to as point C in the measurement model (TS 25.302 [26]).

If the *Report Characteristics* IE is set to "Event A", the DRNS shall initiate the Dedicated Measurement Reporting procedure when the measured entity rises above the requested threshold, as specified by the *Measurement Threshold* IE, and then stays above the threshold for the requested hysteresis time, as specified by the *Measurement Hysteresis Time* IE. If the *Measurement Hysteresis Time* IE is not included, the DRNC shall use the value zero for the hysteresis time.

If the *Report Characteristics* IE is set to "Event B", the DRNS shall initiate the Dedicated Measurement Reporting procedure when the measured entity falls below the requested threshold, as specified by the *Measurement Threshold* IE, and then stays below the threshold for the requested hysteresis time, as specified by the *Measurement Hysteresis Time* IE. If the *Measurement Hysteresis Time* IE is not included, the DRNC shall use the value zero for the hysteresis time.

If the *Report Characteristics* IE is set to "Event C", the DRNS shall initiate the Dedicated Measurement Reporting procedure when the measured entity rises more than the requested threshold specified by the *Measurement Increase/Decrease Threshold* IE, and only when this rise occurs within the requested rising time specified by the *Measurement Change Time* IE. After reporting this type of event, DRNS shall not initiate the next C event reporting for the same measurement during the subsequent time specified by the *Measurement Change Time* IE.

If the *Report Characteristics* IE is set to "Event D", the DRNS shall initiate the Dedicated Measurement Reporting procedure when the measured entity falls more than the requested threshold specified by the *Measurement Increase/Decrease Threshold* IE, and only when this falls occurs within the requested falling time specified by the *Measurement Change Time* IE. After reporting this type of event, the DRNS shall not initiate the next D event reporting for the same measurement during the subsequent time specified by the *Measurement Change Time* IE.

If the *Report Characteristics* IE is set to "Event E", the DRNS shall initiate the Dedicated Measurement Reporting procedure when the measured entity rises above the *Measurement Threshold 1* IE and stays above the threshold for the *Measurement Hysteresis Time* IE (Report A). When the conditions for Report A are met and if the *Report Periodicity* IE is provided, the DRNS shall initiate the Dedicated Measurement Reporting procedure periodically with the requested report frequency specified by the *Report Periodicity* IE. If the conditions for Report A have been met and the measured entity falls below the *Measurement Threshold 2* IE and stays below the threshold for the *Measurement Hysteresis Time* IE, the DRNS shall initiate the Dedicated Measurement Reporting procedure (Report B) and shall terminate any corresponding periodic reporting. If the *Measurement Threshold 2* IE is not present, the DRNS shall use the value of the *Measurement Threshold 1* IE instead. If the *Measurement Hysteresis Time* IE is not included, the DRNC shall use the value zero as hysteresis times for both Report A and Report B.

If the *Report Characteristics* IE is set to "Event F", the DRNS shall initiate the Dedicated Measurement Reporting procedure when the measured entity falls below the *Measurement Threshold 1* IE and stays below the threshold for the *Measurement Hysteresis Time* IE (Report A). When the conditions for Report A are met and if the *Report Periodicity* IE is provided, the DRNS shall initiate the Dedicated Measurement Reporting procedure periodically with the requested report frequency specified by the *Report Periodicity* IE. If the conditions for Report A have been met and the measured entity rises above the *Measurement Threshold 2* IE and stays above the threshold for the *Measurement Hysteresis Time* IE, the DRNS shall initiate the Dedicated Measurement Reporting procedure (Report B) and shall terminate any corresponding periodic reporting. If the *Measurement Threshold 2* IE is not present, the DRNS shall use the value of the *Measurement Threshold 1* IE instead. If the *Measurement Hysteresis Time* IE is not included, the DRNC shall use the value zero as hysteresis times for both Report A and Report B.

If the *Report Characteristics* IE is not set to "On –Demand", the DRNS is required to perform reporting for a dedicated measurement object, in accordance with the conditions provided in the DEDICATED MEASUREMENT INITIATION REQUEST message, as long as the object exists. If no dedicated measurement object(s) for which a measurement is defined exists any more, the DRNS shall terminate the measurement locally without reporting this to the SRNC.

If at the start of the measurement, the reporting criteria are fulfilled for any of Event A, Event B, Event E or Event F, the DRNS shall initiate the Dedicated Measurement Reporting procedure immediately, and then continue with the measurements as specified in the DEDICATED MEASUREMENT INITIATION REQUEST message.

Higher layer filtering

The *Measurement Filter Coefficient* IE indicates how filtering of the dedicated measurement values shall be performed before measurement event evaluation and reporting.

The averaging shall be performed according to the following formula.

$$F_n = (1-a) \cdot F_{n-1} + a \cdot M_n$$

The variables in the formula are defined as follows:

 F_n is the updated filtered measurement result

 F_{n-1} is the old filtered measurement result

 M_n is the latest received measurement result from physical layer measurements, the unit used for M_n is the same unit as the reported unit in the DEDICATED MEASUREMENT INITIATION RESPONSE, DEDICATED MEASUREMENT REPORT messages or the unit used in the event evaluation (i.e. same unit as for Fn).

 $A = \frac{1}{2}(k^{2})$, where k is the parameter received in the *Measurement Filter Coefficient IE*. If the *Measurement Filter Coefficient IE* is not present, a shall be set to 1 (no filtering)

In order to initialise the averaging filter, F_0 is set to M_I when the first measurement result from the physical layer measurement is received.

Measurement Recovery Behavior:

If the *Measurement Recovery Behavior* IE is included in the DEDICATED MEASUREMENT INITIATION REQUEST message, the DRNS shall, if Measurement Recovery Behavior is supported, include the *Measurement Recovery Support Indicator* IE in the DEDICATED MEASUREMENT INITIATION RESPONSE message and perform the Measurement Recovery Behavior as described in subclause 8.3.12.2.

Response message

If the DRNS was able to initiate the measurement requested by the SRNS it shall respond with the DEDICATED MEASUREMENT INITIATION RESPONSE message. The message shall include the same Measurement ID that was used in the DEDICATED MEASUREMENT INITIATION REQUEST message.

In the case in which the Report Characteristics IE is set to "On Demand":

- The DRNC shall include the measurement result in the *Dedicated Measurement Value* IE within the DEDICATED MEASUREMENT INITIATION RESPONSE message.
- If the *CFN Reporting Indicator* IE is set to "FN Reporting Required", the *CFN* IE shall be included in the DEDICATED MEASUREMENT INITIATION RESPONSE message. The reported CFN shall be the CFN at the time when the dedicated measurement value was reported by the layer 3 filter, referred to as point C in the measurement model (TS 25.302 [26]).
- [TDD If the measurement was made on a particular DPCH, the DEDICATED MEASUREMENT INITIATION RESPONSE message shall include the DPCH ID of that DPCH in the [1.28Mcps TDD and 3.84Mcps TDD DPCH ID IE] [7.68Mcps TDD DPCH ID 7.68Mcps IE].]
- [TDD If the measurement was made on a particular HS-SICH, the DEDICATED MEASUREMENT INITIATION RESPONSE message shall include the ID of that HS-SICH in the *HS-SICH ID* IE.]

[FDD – If the *Alternative Format Reporting Indicator* IE is set to "Alternative format is allowed" in the DEDICATED MEASUREMENT INITIATION REQUEST message, the DRNC may include the *Extended Round Trip Time* IE in the DEDICATED MEASUREMENT INITIATION RESPONSE message.]

8.3.11.3 Unsuccessful Operation




Figure 21: Dedicated Measurement Initiation procedure, Unsuccessful Operation

If the requested measurement cannot be initiated for one of the RL/RLS, the DRNC shall send a DEDICATED MEASUREMENT INITIATION FAILURE message. The message shall include the same *Measurement ID* IE that was used in the DEDICATED MEASUREMENT INITIATION REQUEST message and shall include the *Cause* IE set to an appropriate value.

If the DEDICATED MEASUREMENT INITIATION REQUEST message includes the *Partial Reporting Indicator* IE, the DRNS shall, if partial reporting is supported, separate the unsuccessful measurement initiations from the successful measurement initiations. For the successful measurement initiations on a RL or an RLS, the DRNS shall include the *Successful RL Information* IE or the *Successful RL Set Information* IE for the concerned RL or RLS if the Report *Characteristics* IE in the DEDICATED MEASUREMENT INITIATION REQUEST message was set to "On Demand". For the unsuccessful measurement initiations, the DRNS shall include the *Individual Cause* IE set to an appropriate value if it differs from the value of the *Cause* IE.

Typical cause values are:

Radio Network Layer Causes:

Measurement not Supported For The Object Measurement Temporarily not Available

Miscellaneous Causes:

Control Processing Overload HW Failure

8.3.11.4 Abnormal Conditions

The allowed combinations of the Dedicated Measurement Type and Report Characteristics Type are shown in the table below marked with "X". For not allowed combinations, the DRNS shall reject the Dedicated Measurement Initiation procedure using the DEDICATED MEASUREMENT INITIATION FAILURE message.

Dedicated	Report Characteristics Type								
Measurement Type	On Demand	Periodic	Event A	Event B	Event C	Event D	Event E	Event F	On Modification
SIR	X	X	Χ	Х	Х	Χ	Χ	Χ	
SIR Error	X	X	Χ	Х	Х	Χ	Χ	Χ	
Transmitted Code	Х	Х	Х	Х	Х	Х	Х	Х	
Power									
RSCP	X	X	X	X	X	Χ	X	Χ	
Rx Timing Deviation	X	X	Χ	Х			Χ	Χ	
Round Trip Time	X	Х	Χ	Х	Х	Χ	Χ	Χ	
Rx Timing Deviation LCR	Х	Х	Х	Х			Х	Х	
HS-SICH Reception Quality	Х	Х	Х	Х			Х	Х	
Angle Of Arrival LCR	X	X							
Rx Timing Deviation 7.68Mcps	Х	Х	Х	Х			Х	Х	
Rx Timing Deviation 3.84Mcps Extended	Х	Х	Х	Х			Х	Х	

Table 4: Allowed Dedicated Measurement Type and Report Characteristics Type combinations

If the Dedicated Measurement Type received in the *Dedicated Measurement Type* IE is not defined in TS 25.215 [11] or TS 25.225 [14] to be measured on the Dedicated Measurement Object Type received in the DEDICATED MEASUREMENT INITIATION REQUEST message, the DRNS shall reject the Dedicated Measurement Initiation procedure.

If the *CFN* IE is included in the DEDICATED MEASUREMENT INITIATION REQUEST message and the *Report Characteristics* IE is other than "Periodic" or "On Demand", the DRNS shall reject the Dedicated Measurement Initiation procedure, and the DRNC shall send a DEDICATED MEASUREMENT INITIATION FAILURE message.

8.3.12 Dedicated Measurement Reporting

8.3.12.1 General

This procedure is used by the DRNS to report the results of the successfully initiated measurements requested by the SRNS with the Dedicated Measurement Initiation procedure.

This procedure shall use the signalling bearer connection for the relevant UE Context.

The DRNC may initiate the Dedicated Measurement Reporting procedure at any time after establishing a Radio Link.

8.3.12.2 Successful Operation



Figure 22: Dedicated Measurement Reporting procedure, Successful Operation

If the requested measurement reporting criteria are met, the DRNS shall initiate the Dedicated Measurement Reporting procedure. If the measurement was initiated (by the Dedicated Measurement Initiation procedure) for multiple dedicated measurement objects, the DRNC may include dedicated measurement values in the *Dedicated Measurement Value Information* IE for multiple objects in the DEDICATED MEASUREMENT REPORT message.

The *Measurement ID* IE shall be set to the Measurement ID provided by the SRNC when initiating the measurement with the Dedicated Measurement Initiation procedure.

If the achieved measurement accuracy does not fulfil the given accuracy requirement specified in TS 25.133 [23] and TS 25.123 [24] or the measurement is temporarily not available in case Measurement Recovery Behavior is supported, the Measurement not available shall be reported in the *Dedicated Measurement Value Information* IE in the DEDICATED MEASUREMENT REPORT message, otherwise the DRNC shall include the *Dedicated Measurement Value* IE within the *Dedicated Measurement Value Information* IE. If the DRNC was configured to perform the Measurement Recovery Behavior, the DRNC shall indicate Measurement Available to the SRNC when the achieved measurement accuracy again fullfils the given accuracy requirement (see TS 25.133 [23] and TS 25.123 [24]) and include the *Measurement Recovery Report Indicator* IE in the DEDICATED MEASUREMENT REPORT message if the requested measurement reporting criteria are not met.

If the CFN Reporting Indicator when initiating the measurement with the Dedicated Measurement Initiation procedure was set to "FN Reporting Required", the DRNC shall include the *CFN* IE in the DEDICATED MEASUREMENT REPORT message. The reported CFN shall be the CFN at the time when the dedicated measurement value was reported by the layer 3 filter, referred to as point C in the measurement model (TS 25.302 [26]).

[TDD – If the measurement was made on a particular DPCH, the DEDICATED MEASUREMENT REPORT message shall include the DPCH ID of that DPCH in the [1.28Mcps TDD and 3.84Mcps TDD – DPCH ID IE] [7.68Mcps TDD – DPCH ID 7.68Mcps IE].]

[TDD – If the measurement was made on a particular HS-SICH, the DEDICATED MEASUREMENT INITIATION RESPONSE message shall include the ID of that HS-SICH in the *HS-SICH ID* IE.]

[FDD – If the *Alternative Format Reporting Indicator* IE was set to "Alternative format is allowed" in the DEDICATED MEASUREMENT INITIATION REQUEST message setting up the measurement to be reported, the DRNC may include the *Extended Round Trip Time* IE in the DEDICATED MEASUREMENT REPORT message.]

8.3.12.3 Abnormal Conditions

-

8.3.13 Dedicated Measurement Termination

8.3.13.1 General

This procedure is used by the SRNS to terminate a measurement previously requested by the Dedicated Measurement Initiation procedure.

This procedure shall use the signalling bearer connection for the relevant UE Context.

The Dedicated Measurement Termination procedure shall not be initiated if a Prepared Reconfiguration exists, as defined in subclause 3.1.

8.3.13.2 Successful Operation



Figure 23: Dedicated Measurement Termination procedure, Successful Operation

This procedure is initiated with a DEDICATED MEASUREMENT TERMINATION REQUEST message, sent from the SRNC to the DRNC.

Upon receipt, the DRNS shall terminate reporting of dedicated measurements corresponding to the received *Measurement ID* IE.

8.3.13.3 Abnormal Conditions

_

8.3.14 Dedicated Measurement Failure

8.3.14.1 General

This procedure is used by the DRNS to notify the SRNS that a measurement previously requested by the Dedicated Measurement Initiation procedure can no longer be reported. When partial reporting is allowed and supported, this procedure shall be used to report that measurement for one or more RL/RLS can no longer be reported.

This procedure shall use the signalling bearer connection for the relevant UE Context.

The DRNC may initiate the Dedicated Measurement Failure procedure at any time after establishing a Radio Link.

8.3.14.2 Successful Operation



Figure 24: Dedicated Measurement Failure procedure, Successful Operation

This procedure is initiated with a DEDICATED MEASUREMENT FAILURE INDICATION message, sent from the DRNC to the SRNC, to inform the SRNC that a previously requested dedicated measurement can no longer be reported. The DRNC has locally terminated the indicated measurement. The DRNC shall include in the DEDICATED MEASUREMENT FAILURE INDICATION message the reason for the failure in the *Cause* IE.

The DRNS shall include *Unsuccessful RL Information* IE or the *Unsuccessful RL Set Information* IE for the concerned RL or RLS if partial reporting is allowed and it is supported. The DRNS shall include the *Individual Cause* IE set to an appropriate value if it differs from the value of the *Cause* IE.

Typical cause values are:

Miscellaneous Causes:

- Control Processing Overload
- HW Failure
- O&M Intervention

8.3.14.3 Abnormal Conditions

_

8.3.15 Downlink Power Control [FDD]

8.3.15.1 General

The purpose of this procedure is to balance the DL transmission powers of one or more radio links for one UE.

This procedure shall use the signalling bearer connection for the relevant UE Context.

The Downlink Power Control procedure may be initiated by the SRNC at any time after establishing a Radio Link. If the SRNC has initiated in this DRNS the deletion of the last Radio Link for this UE context, the Downlink Power Control procedure shall not be initiated.

8.3.15.2 Successful Operation



Figure 25: Downlink Power Control procedure, Successful Operation

The Downlink Power Control procedure is initiated by the SRNC sending a DL POWER CONTROL REQUEST message to the DRNC.

The Power Adjustment Type IE defines the characteristic of the power adjustment.

If the value of the *Power Adjustment Type* IE is "Common", the DRNS shall set the Power Balancing Adjustment Type of the UE Context set to "Common". As long as the Power Balancing Adjustment Type of the UE Context is set to "Common", the DRNS shall perform the power adjustment (see below) for all existing and future radio links for the UE Context and use a common DL reference power level.

If the value of the *Power Adjustment Type* IE is "Individual", the DRNS shall set the Power Balancing Adjustment Type of the UE Context set to "Individual". The DRNS shall perform the power adjustment (see below) for all radio links addressed in the message using the given DL Reference Power per RL. If the Power Balancing Adjustment Type of the UE Context was set to "Common" before this message was received, power balancing on all radio links not addressed by the DL POWER CONTROL REQUEST message shall remain to be executed in accordance with the existing power balancing parameters which are now considered RL individual parameters. Power balancing will not be started on future radio links without a specific request.

If the value of the *Power Adjustment Type* IE is "None", the DRNS shall set the Power Balancing Adjustment Type of the UE Context set to "None" and the DRNS shall suspend on going power adjustments for all radio links for the UE Context.

If the *Inner Loop DL PC Status* IE is present and set to "Active", the DRNS shall activate inner loop DL power control for all radio links for the UE Context. If the *Inner Loop DL PC Status* IE is present and set to "Inactive", the DRNS shall deactivate inner loop DL power control for all radio links for the UE Context according to TS 25.214 [10].

Power Adjustment

The power balancing adjustment shall be superimposed on the inner loop power control adjustment (see TS 25.214 [10]) if activated. The power balancing adjustment shall be such that:

$$\sum P_{bal} = (1 - r)(P_{ref} + P_{P-CPICH} - P_{init})$$
 with an accuracy of ±0.5 dB

where the sum is performed over an adjustment period corresponding to a number of frames equal to the value of the *Adjustment Period* IE, P_{ref} is the value of the *DL Reference Power* IE, $P_{P-CPICH}$ is the power used on the primary CPICH, P_{init} is the code power of the last slot of the previous adjustment period and r is given by the *Adjustment Ratio* IE. If the last slot of the previous adjustment period is within a transmission gap due to compressed mode, P_{init} shall be set to the same value as the code power of the slot just before the transmission gap.

The adjustment within one adjustment period shall in any case be performed with the constraints given by the *Max Adjustment Step* IE and the DL TX power range set by the DRNC.

The power adjustments shall be started at the first slot of a frame with CFN modulo the value of *Adjustment Period* IE equal to 0 and shall be repeated for every adjustment period and shall be restarted at the first slot of a frame with CFN=0, until a new DL POWER CONTROL REQUEST message is received or the RL is deleted.

8.3.15.3 Abnormal Conditions

_

8.3.16 Compressed Mode Command [FDD]

8.3.16.1 General

The Compressed Mode Command procedure is used to activate or deactivate the compressed mode in the DRNS for one UE-UTRAN connection. This procedure shall use the signalling bearer connection for the relevant UE Context.

The Compressed Mode Command procedure shall not be initiated if a Prepared Reconfiguration exists, as defined in subclause 3.1.

8.3.16.2 Successful Operation



Figure 26: Compressed Mode Command procedure, Successful Operation

The procedure is initiated by the SRNC sending a COMPRESSED MODE COMMAND message to the DRNC.

Upon receipt of the COMPRESSED MODE COMMAND message from the SRNC and at the CFN indicated in the *CM Configuration Change CFN* IE, the DRNS shall deactivate all the ongoing Transmission Gap Pattern Sequences. From that moment on all Transmission Gap Pattern Sequences included in *Transmission Gap Pattern Sequence Status* IE repetitions (if present) shall be started when the indicated *TGCFN* IE elapses. The *CM Configuration Change CFN* IE in the *Active Pattern Sequence Information* IE and *TGCFN* IE for each sequence refer to the next coming CFN with that value

If the values of the *CM Configuration Change CFN* IE and the *TGCFN* IE are equal, the concerned Transmission Gap Pattern Sequence shall be started immediately at the CFN with a value equal to the value received in the *CM Configuration Change CFN* IE.

If the *Affected HS-DSCH serving cell List* IE is included, the concerned Transmission Gap Pattern Sequence shall be applied to HS-DSCH serving cells associated with *C-ID* IE included in *Affected HS-DSCH serving cell List* IE. Otherwise the concerned Transmission Gap Pattern Sequence shall be applied to all the configured serving cells.

If the concerned UE Context is configured to use F-DPCH in the downlink, the DRNS shall ignore, when activating the Transmission Gap Pattern Sequence(s), the downlink compressed mode method information, if existing, for the concerned Transmission Gap Pattern Sequence(s) in the Compressed Mode Configuration.

8.3.16.3 Abnormal Conditions

[FDD - If the Affected HS-DSCH serving cell List IE is included in the Active Pattern Sequence Information IE, and the Transmission Gap Pattern Sequence for affected HS-DSCH Serving Cells is activated on the HS-DSCH Primary Serving Cell but not for all the other serving cells, the DRNS shall initiate the Radio Link Failure procedure with the cause value "Invalid CM Settings".]

8.3.17 Downlink Power Timeslot Control [TDD]

8.3.17.1 General

The purpose of this procedure is to provide the DRNS with updated DL Timeslot ISCP values to use when deciding the DL TX Power for each timeslot.

This procedure shall use the signalling bearer connection for the relevant UE Context.

The Downlink Power Timeslot Control procedure can be initiated by the SRNC at any time after establishing a Radio Link. If the SRNC has initiated deletion of the last Radio Link in this DRNS, the Downlink Power Timeslot Control procedure shall not be initiated.

8.3.17.2 Successful Operation



Figure 26A: Downlink Power Timeslot Control procedure, Successful Operation

The Downlink Power Timeslot Control procedure is initiated by the SRNC sending a DL POWER TIMESLOT CONTROL REQUEST message to the DRNC.

Upon receipt of the DL POWER TIMESLOT CONTROL REQUEST message, the DRNS shall use the included [3.84Mcps TDD and 7.68 Mcps TDD – *DL Timeslot ISCP Info* IE] [1.28Mcps TDD – *DL Timeslot ISCP Info LCR* IE] value when deciding the DL TX Power for each timeslot as specified in TS 25.224 [22], i.e. it shall reduce the DL TX power in those downlink timeslots of the radio link in which the interference is low, and increase the DL TX power in those timeslots in which the interference is high, while keeping the total downlink power in the radio link unchanged.

If the *Primary CCPCH RSCP Delta* IE is included, the DRNS shall assume that the reported value for Primary CCPCH RSCP is in the negative range as per TS 25.123 [24], and the value is equal to the *Primary CCPCH RSCP Delta* IE. If the *Primary CCPCH RSCP Delta* IE is not included and the *Primary CCPCH RSCP* IE is included, the DRNS shall assume that the reported value is in the non-negative range as per TS 25.123 [24], and the value is equal to the *Primary CCPCH RSCP* IE. The DRNS should use the indicated value for HS-DSCH scheduling and transmit power adjustment.

8.3.17.3 Abnormal Conditions

-

8.3.18 Radio Link Pre-emption

8.3.18.1 General

This procedure is started by the DRNS when resources need to be freed.

This procedure shall use the signalling bearer connection for the UE Context associated with the RL to be pre-empted.

The DRNS may initiate the Radio Link Pre-emption procedure at any time after establishing a Radio Link.

8.3.18.2 Successful Operation



Figure 26B: Radio Link Pre-emption procedure, Successful Operation

When DRNC detects that one or more Radio Link(s) should be pre-empted (see Annex A), it shall send the RADIO LINK PREEMPTION REQUIRED INDICATION message to the SRNC. If all Radio Links for a UE Context should be pre-empted, the *RL Information* IE shall not be included in the message. If one or several but not all Radio Link(s) should be pre-empted for an UE Context, the Radio Link(s) that should be pre-empted shall be indicated in the *RL Information* IE. The Radio Link(s) that should be pre-empted, should be deleted by the SRNC.

[FDD – If only the E-DCH traffic on a Radio Link should be pre-empted, the DRNC shall indicate the EDCH MAC-d flows that should be pre-empted by including the *E-DCH MAC-d Flow Specific Information* IE in the RADIO LINK PREEMPTION REQUIRED INDICATION message.]

When only the HS-DSCH traffic on a Radio Link should be pre-empted, the DRNC shall indicate the HS-DSCH MAC-d flow(s) that should be pre-empted by including the *HS-DSCH MAC-d Flow Specific Information* IE in the RADIO LINK PREEMPTION REQUIRED INDICATION message.

8.3.18.3 Abnormal Conditions

-

8.3.19 Radio Link Congestion

8.3.19.1 General

This procedure is started by the DRNS when resource congestion is detected and the rate of one or more DCHs, corresponding to one or more radio links, is preferred to be limited in the UL and/or DL. This procedure is also used by the DRNC to indicate to the SRNC any change of the UL/DL resource congestion situation, affecting these radio links. This procedure shall use the signalling bearer connection for the relevant UE Context.

The Radio Link Congestion procedure shall not be initiated if a Prepared Reconfiguration exists, as defined in subclause 3.1.

8.3.19.2 Successful Operation



Figure 26C: Radio Link Congestion procedure, Successful Operation

Start of an UL/DL Resource Congestion Situation

When the DRNC detects the start of a UL/DL resource congestion situation and prefers the rate of one or more DCHs for one or more Radio Link(s) to be limited below the maximum rate currently configured in the UL/DL TFS, it shall send the RADIO LINK CONGESTION INDICATION message to the SRNC. The DRNC shall indicate the cause of the congestion in the *Congestion Cause* IE and shall indicate all the Radio Links for which the rate of a DCH needs to be reduced. For each DCH within the RL with UL congestion, the DRNC shall indicate the desired maximum UL data rate with the *Allowed UL Rate* IE in the *Allowed Rate Information* IE. For each DCH within the RL with DL congestion, the DRNC shall indicate the desired maximum DL data rate with the *Allowed DL Rate* IE in the *Allowed Rate Information* IE.

[FDD – For each E-DCH MAC-d flow within the RL with UL congestion, the DRNC shall indicate all the MAC-d flows for which the rate cannot be fullfilled.]

When receiving the RADIO LINK CONGESTION INDICATION message the SRNC should reduce the rate in accordance with the *Congestion Cause* IE and the indicated *Allowed DL Rate* IE and/or *Allowed UL Rate* IE for a DCH.

[FDD – If the RADIO LINK CONGESTION INDICATION message includes the *DCH Indicator For E-DCH-HSDPA Operation* IE, then the SRNS shall ignore the *DCH Rate Information* IE in the RADIO LINK CONGESTION INDICATION message.]

Change of UL/DL Resource Congestion Situation

The DRNC shall indicate any change of the UL/DL resource congestion situation by sending the RADIO LINK CONGESTION INDICATION message in which the new allowed rate(s) of the DCHs are indicated by the *Allowed Rate Information* IE. In the case that for at least one DCH the new allowed rate is lower than the previously indicated allowed rate for that DCH, the *Congestion Cause* IE, indicating the cause of the congestion, shall also be included.

When receiving a RADIO LINK CONGESTION INDICATION message indicating a further rate decrease on any DCH(s) on any RL, the SRNC should reduce the rate in accordance with the indicated congestion cause and the indicated allowed rate(s) for the DCH(s).

End of UL/DL Resource Congestion Situation

The end of an UL resource congestion situation, affecting a specific RL, shall be indicated by including the TF corresponding to the highest data rate in the *Allowed UL Rate* IE in the *Allowed Rate Information* IE for the concerned RL. The end of a DL resource congestion situation, affecting a specific RL, shall be indicated by including the TF with the highest data rate in the *Allowed DL Rate* IE in the *Allowed Rate Information* IE for the concerned RL.

8.3.19.3 Abnormal Conditions

_

8.3.20 Radio Link Activation

8.3.20.1 General

This procedure is used to activate or de-activate the DL transmission on the Uu interface regarding selected RLs.

8.3.20.2 Successful Operation



Figure 26D: Radio Link Activation procedure

This procedure is initiated by sending the RADIO LINK ACTIVATION COMMAND message from the SRNC to the DRNC. This procedure shall use the signalling bearer connection for the relevant UE Context.

Upon receipt, the DRNS shall for each concerned RL:

- if the *Delayed Activation Update* IE indicates "Activate":
 - if the *Activation Type* IE equals "Unsynchronised":
 - [FDD start transmission on the new RL after synchronisation is achieved in the DL user plane as specified in TS 25.427 [4].]
 - [TDD start transmission on the new RL immediately as specified in TS 25.427 [4].]
 - if the *Activation Type* IE equals "Synchronised":
 - [FDD start transmission on the new RL after synchronisation is achieved in the DL user plane as specified in TS 25.427 [4], however never before the CFN indicated in the *Activation CFN* IE.]
 - [TDD start transmission on the new RL at the CFN indicated in the *Activation CFN* IE as specified in TS 25.427 [4].]
 - [FDD the DRNS shall apply the power level indicated in the *Initial DL Tx Power* IE to the transmission on each DL DPCH or on the F-DPCH of the RL when starting transmission until either UL synchronisation on the Uu interface is achieved for the RLS or power balancing is activated. During this period no inner loop power control shall be performed and, unless activated by the DL POWER CONTROL REQUEST message, no power balancing shall be performed. The DL power shall then vary according to the inner loop power control (see TS 25.214 [10], subclause 5.2.1.2) and downlink power balancing adjustments (see 8.3.7).]

- [TDD the DRNS shall apply the power level indicated in the *Initial DL Tx Power* IE to the transmission on each DL DPCH and on each Time Slot of the RL when starting transmission until the UL synchronisation on the Uu interface is achieved for the RL. No inner loop power control shall be performed during this period. The DL power shall then vary according to the inner loop power control (see TS 25.224 [22], subclause 4.2.3.3).]
- [FDD if the *Propagation Delay* IE and optionally the *Extended Propagation Delay* IE are included, the DRNS may use this information to speed up the detection of UL synchronisation on the Uu interface.]
- [FDD if the *First RLS Indicator* IE is included, it indicates if the concerned RL shall be considered part of the first RLS established towards this UE. The *First RLS Indicator* IE shall be used by the DRNS to determine the initial TPC pattern in the DL of the concerned RL and all RLs which are part of the same RLS, as described in TS 25.214 [10], section 5.1.2.2.1.2.]
- if the Delayed Activation Update IE indicates "Deactivate":
 - stop DL transmission immediately if the *Deactivation Type* IE equals "Unsynchronised", or at the CFN indicated by the *Deactivation CFN* IE if the *Deactivation Type* IE equals "Synchronised".

8.3.20.3 Abnormal Conditions

[FDD – If the *Delayed Activation Update* IE is included in the RADIO LINK ACTIVATION COMMAND message, it indicates "Activate" and the *First RLS Indicator* IE is not included, the DRNC shall initiate the ERROR INDICATION procedure.]

8.3.21 Radio Link Parameter Update

8.3.21.1 General

The Radio Link Parameter Update procedure is executed by the DRNS to update parameters related to HS-DSCH on a radio link for a UE-UTRAN connection or to update phase reference on a list of the radio links.

This procedure shall use the signalling bearer connection for the relevant UE context.

The Radio Link Parameter Update procedure shall not be initiated if a Prepared Reconfiguration exists, as defined in subclause 3.1.

8.3.21.2 Successful Operation



Figure 26E: Radio Link Parameter Update Indication, Successful Operation

The Radio Link Parameter Update procedure is initiated by the DRNS by sending the RADIO LINK PARAMETER UPDATE INDICATION message to the SRNC.

HS-DSCH related Parameter(s) Updating:

If RADIO LINK PARAMETER UPDATE INDICATION message is used to update the parameters related to HS-DSCH, it contains suggested value(s) of the HS-DSCH related parameter(s) that should be reconfigured on the radio link

If the DRNS needs to update HS-DSCH related parameters, the DRNS shall initiate RADIO LINK PARAMETER UPDATE INDICATION message including [FDD – HS-DSCH FDD Update Information IE] [TDD – HS-DSCH TDD Update Information IE].

If the DRNS needs to allocate new HS-SCCH Codes, the DRNS shall initiate RADIO LINK PARAMETER UPDATE INDICATION message including *HS-SCCH Code Change Indicator* IE.

[FDD – If the DRNS needs to allocate new HS-PDSCH Codes, the DRNS shall initiate RADIO LINK PARAMETER UPDATE INDICATION message including *HS-PDSCH Code Change Indicator* IE.]

[FDD – If the DRNS needs to update the CQI Feedback Cycle k, CQI Repetition Factor, ACK-NACK Repetition Factor, CQI Power Offset, ACK Power Offset and/or NACK Power Offset, the DRNS shall initiate RADIO LINK PARAMETER UPDATE INDICATION message including *CQI Feedback Cycle k* IE, *CQI Repetition Factor* IE, *ACK-NACK Repetition Factor* IE, *CQI Power Offset* IE, *ACK Power Offset* IE and/or *NACK Power Offset* IE.]

[TDD – If the DRNS needs to update the TDD ACK-NACK Power Offset the DRNS shall initiate RADIO LINK PARAMETER UPDATE INDICATION message including *TDD ACK-NACK Power Offset* IE.]

[FDD – Secondary Serving HS-DSCH related Parameter(s) Updating:]

[FDD – If RADIO LINK PARAMETER UPDATE INDICATION message is used to update the parameters related to secondary serving HS-DSCH, it contains suggested value(s) of the secondary serving HS-DSCH related parameter(s) that should be reconfigured on the radio link.]

[FDD – If the DRNS needs to update secondary serving HS-DSCH related parameters, the DRNS shall initiate RADIO LINK PARAMETER UPDATE INDICATION message and include the *Additional HS Cell Information RL Param Upd* IE.]

- [FDD – If the DRNS needs to allocate new secondary serving HS-SCCH Codes, the DRNS shall include the HS-SCCH Code Change Indicator IE in the HS-DSCH FDD Secondary Serving Update Information IE.]

[FDD – Phase Reference Handling:]

[FDD – If DRNS needs to update phase reference for the channel estimation for one or several Radio Links, the DRNC shall initiate RADIO LINK PARAMETER UPDATE INDICATION message including *Phase Reference Update Information* IE for the concerned RL(s).]

[FDD - E-DCH:]

[FDD – If DRNS needs to update E-DCH related parameters, the DRNC shall initiate RADIO LINK PARAMETER UPDATE INDICATION message including *E-DCH FDD Update Information* IE.]

[FDD – If the DRNS needs to update the HARQ process allocation for non-scheduled transmission and/or HARQ process allocation for scheduled Transmission, the DRNS shall initiate RADIO LINK PARAMETER UPDATE INDICATION message including the *HARQ Process Allocation For 2ms Non-Scheduled Transmission Grant* IE for the concerned MAC-d Flows and/or *HARQ Process Allocation For 2ms Scheduled Transmission Grant* IE.]

[FDD – If the DRNS needs to allocate new E-AGCH Channelisation Code, new E-RGCH/E-HICH Channelisation Code, new E-RGCH Signature Sequence and/or new E-HICH Signature Sequence, the DRNC shall initiate RADIO LINK PARAMETER UPDATE INDICATION message including *E-DCH DL Control Channel Change Information* IE.]

[FDD – If the DRNS needs to update Additional E-DCH related parameters, the DRNS shall initiate RADIO LINK PARAMETER UPDATE INDICATION message including *Additional E-DCH Cell Information RL Param Upd* IE.]

- [FDD If the DRNS needs to update the HARQ process allocation for scheduled Transmission, the DRNS shall initiate RADIO LINK PARAMETER UPDATE INDICATION message including the *HARQ Process Allocation For 2ms Scheduled Transmission Grant* .]
- [FDD If the DRNS needs to allocate new E-AGCH Channelisation Code, new E-RGCH/E-HICH Channelisation Code, new E-RGCH Signature Sequence and/or new E-HICH Signature Sequence, the DRNS shall initiate RADIO LINK PARAMETER UPDATE INDICATION message including *Additional E-DCH DL Control Channel Change Information* IE.]

[FDD – CPC Recovery:]

[FDD – If the DRNS needs to indicate that the CPC Recovery has been initiated, the DRNC shall initiate RADIO LINK PARAMETER UPDATE INDICATION message including *CPC Recovery Report* IE.]

8.3.21.3 Abnormal Conditions

_

8.3.22 UE Measurement Initiation [TDD]

8.3.22.1 General

This procedure is used by a DRNC to request the initiation of UE measurements by the SRNC.

This procedure shall use the signalling bearer connection for the relevant UE Context.

The UE Measurement Initiation procedure shall not be initiated if a Prepared Reconfiguration exists, as defined in subclause 3.1.

8.3.22.2 Successful Operation




Figure 26F: UE Measurement Initiation procedure, Successful Operation

The procedure is initiated with a UE MEASUREMENT INITIATION REQUEST message sent from the DRNC to the SRNC.

Upon receipt the SRNC shall, provided that it determines that the measurement can be performed by the UE, initiate and forward the requested UE measurement according to the parameters given in the UE MEASUREMENT INITIATION REQUEST message. If the UE MEASUREMENT INITIATION REQUEST message includes the *UE Measurement Parameter Modification Allowed* IE with a value of "Parameter Modification Allowed" the *UE Measurement Report Characteristics* IE and the *Measurement Filter Coefficient* IE, if it is included, are suggested values, otherwise the values of these parameters must be fulfilled.

[3.84 Mcps TDD – If the *UE Measurement Timeslot Information HCR* IE is provided, the measurement request shall apply for the requested timeslot(s) individually. If the *UE Measurement Timeslot Information HCR* IE are not provided the SRNC may choose the timeslots for measurements that apply to individual timeslots.]

[1.28 Mcps TDD – If the *UE Measurement Timeslot Information LCR* IE is provided, the measurement request shall apply for the requested timeslot(s) individually. If the *UE Measurement Timeslot Information LCR* IE are not provided the SRNC may choose the timeslots for measurements that apply to individual timeslots.]

[7.68 Mcps TDD – If the *UE Measurement Timeslot Information 7.68 Mcps* IE is provided, the measurement request shall apply for the requested timeslot(s) individually. If the *UE Measurement Timeslot Information 7.68 Mcps* IE are not provided the SRNC may choose the timeslots for measurements that apply to individual timeslots.]

If the UE MEASUREMENT INITIATION REQUEST message includes the *Allowed Queuing Time* IE the SRNC may queue the request for a time period not to exceed the value of the *Allowed Queuing Time* IE before starting to execute the request.

The SRNC is required to perform reporting for a UE measurement object, in accordance with the conditions provided in the UE MEASUREMENT INITIATION REQUEST message, as long as the object exists. If no UE measurement object(s) for which a measurement is defined exists any more, the SRNC shall terminate the measurement locally without reporting this to the DRNC.

If at the start of the measurement, the reporting criteria are fulfilled for any of Event 1h, Event 1i,Event 6a, Event 6b, Event 6c, or Event 6d, the SRNC shall initiate the UE Measurement Reporting procedure immediately, and then continue with the measurements as specified in the UE MEASUREMENT INITIATION REQUEST message

At the start of a periodic measurement, the SRNC shall not initiate UE Measurement Reporting procedure until the next measurement is received from the UE, even if measurement data is available.

Report characteristics

The *UE Measurement Report Characteristics* IE indicates how the reporting of the dedicated measurement shall be performed. See TS 25.331 [16].

Higher layer filtering

The *Measurement Filter Coefficient* IE indicates how filtering of the dedicated measurement values shall be performed before measurement event evaluation and reporting. If the *Measurement Filter Coefficient* IE is not present, *a* shall be set to 1 (no filtering). The use of the *Measurement Filter Coefficient* IE is shown in TS 25.331 [16].

Response message

If the SRNC was able to initiate the measurement requested by the DRNC it shall respond with the UE MEASUREMENT INITIATION RESPONSE message. The message shall include the same Measurement ID that was used in the UE MEASUREMENT INITIATION REQUEST message.

If the DRNC allowed parameter modification and the SRNC modified the *Measurement Filter Coefficient* IE the SRNC shall include the modified value in the UE MEASUREMENT INTIATION RESPONSE message.

If the DRNC allowed parameter modification and the SRNC modified the *UE Measurement Report Characteristics* IE the SRNC shall include the modified value in the UE MEASUREMENT INTIATION RESPONSE message.

8.3.22.3 Unsuccessful Operation




Figure 26G: UE Measurement Initiation procedure, Unsuccessful Operation

If the requested measurement cannot be initiated, the SRNC shall send a UE MEASUREMENT INITIATION FAILURE message. The message shall include the same *Measurement ID* IE that was used in the UE MEASUREMENT INITIATION REQUEST message and shall include the *Cause* IE set to an appropriate value.

Typical cause values are:

Radio Network Layer Causes:

Measurement not Supported For The Object Measurement Temporarily not Available Measurement Repetition Rate not Compatible with Current Measurements UE not Capable to Implement Measurement

Miscellaneous Causes:

Control Processing Overload HW Failure

8.3.22.4 Abnormal Conditions

-

8.3.23 UE Measurement Reporting [TDD]

8.3.23.1 General

This procedure is used by the SRNC to report the results of the successfully initiated measurements requested by the DRNC with the UE Measurement Initiation procedure.

This procedure shall use the signalling bearer connection for the relevant UE Context.

The SRNC may initiate the UE Measurement Reporting procedure at any time after establishing a Radio Link.

8.3.23.2 Successful Operation



Figure 26H: UE Measurement Reporting procedure, Successful Operation

If the requested measurement reporting criteria was met in the UE and reported to the SRNC, the SRNC shall initiate the UE Measurement Reporting procedure. The *Measurement ID* IE shall be set to the Measurement ID provided by the DRNC when initiating the measurement with the UE Measurement Initiation procedure.

If Primary CCPCH RSCP is being reported:

- If the *Primary CCPCH RSCP Delta* IE is included, the DRNC shall assume that the reported value for Primary CCPCH RSCP is in the negative range as per TS 25.123 [24], and the value is equal to the *Primary CCPCH RSCP Delta* IE.
- If the *Primary CCPCH RSCP Delta* IE is not included the DRNC shall assume that the reported value is in the non negative range as per TS 25.123 [24], and the value is equal to the *Primary CCPCH RSCP* IE

If the achieved measurement accuracy does not fulfil the given accuracy requirement specified in TS 25.123 [24], the Measurement not available shall be reported in the *UE Measurement Value Information* IE in the UE MEASUREMENT REPORT message, otherwise the SRNC shall include the *UE Measurement Value* IE within the *UE Measurement Value Information* IE.

8.3.23.3 Abnormal Conditions

8.3.24 UE Measurement Termination [TDD]

8.3.24.1 General

This procedure is used by the DRNC to terminate a measurement previously requested by the UE Measurement Initiation procedure.

This procedure shall use the signalling bearer connection for the relevant UE Context.

The UE Measurement Termination procedure shall not be initiated if a Prepared Reconfiguration exists, as defined in subclause 3.1.

8.3.24.2 Successful Operation



Figure 26I: UE Measurement Termination procedure, Successful Operation

This procedure is initiated with a UE MEASUREMENT TERMINATION REQUEST message, sent from the DRNC to the SRNC.

Upon receipt, the SRNC shall terminate forwarding of UE measurements corresponding to the received *Measurement ID* IE.

8.3.24.3 Abnormal Conditions

-

8.3.25 UE Measurement Failure [TDD]

8.3.25.1 General

This procedure is used by the SRNC to notify the DRNC that a measurement previously requested by the UE Measurement Initiation procedure can no longer be reported.

This procedure shall use the signalling bearer connection for the relevant UE Context.

The SRNC may initiate the UE Measurement Failure procedure at any time after establishing a Radio Link.

8.3.25.2 Successful Operation



Figure 26J: UE Measurement Failure procedure, Successful Operation

This procedure is initiated with a UE MEASUREMENT FAILURE INDICATION message, sent from the SRNC to the DRNC, to inform the DRNC that a previously requested UE measurement can no longer be reported. The SRNC has locally terminated the forwarding of the indicated measurement. The SRNC shall include in the UE MEASUREMENT FAILURE INDICATION message the reason for the failure in the *Cause* IE.

Typical cause values are:

Miscellaneous Causes:

- Control Processing Overload
- HW Failure
- O&M Intervention

8.3.25.3 Abnormal Conditions

-

8.3.26 Iur Invoke Trace

8.3.26.1 General

The purpose of the Iur Invoke Trace procedure is to inform the DRNC that it should begin a Trace Session for a given UE Context according to the Trace Parameters indicated by the SRNC. This procedure is used for Trace Parameter Propagation in the Signalling Based Activation mechanism as defined in TS 32.421 [48] and TS 32.422 [49].

This procedure shall use the signalling bearer mode specified below.

8.3.26.2 Successful Operation



Figure 26K: lur Invoke Trace procedure, Successful Operation

The Iur Invoke Trace procedure is invoked by the SRNC by sending an IUR INVOKE TRACE message to the DRNC.

When the concerned UE is utilising one or more radio links in the DRNC the message shall be sent using the connection oriented service of the signalling bearer and no further identification of the UE Context in the DRNC is required. If on the other hand, the UE is not utilising any radio link the message shall be sent using the connectionless service of the signalling bearer and the *D-RNTI* IE shall be included in the message to identify the UE Context in the DRNC.

Upon receiving the IUR INVOKE TRACE message, the DRNC should begin a Trace Recording Session according to the parameters indicated in the IUR INVOKE TRACE message.

If the *List Of Interfaces To Trace* IE is included in the IUR INVOKE TRACE message, the DRNC shall trace, for the concerned UE Context, the interfaces indicated by the *List Of Interfaces To Trace* IE. Otherwise, the DRNC shall trace, for the concerned UE Context, the Iur and Iub interfaces.

The values of the *UE Identity* IE, *Trace Reference* IE and *Trace Recording Session Reference* IE are used to tag the Trace Record to allow simpler construction of the total record by the entity which combines Trace Records.

If the DRNC does not support the requested value "Minimum" or "Medium" of the *Trace Depth* IE, the DRNC should begin a Trace Recording Session with maximum Trace Depth.

The DRNC may not start a Trace Recording Session if there are insufficient resources available within the DRNC.

If the *MDT Configuration* IE is included and the *MDT Activation* IE is set to "MDT and Trace" then the DRNC shall, if supported, initiate the requested trace function and MDT function (M3 Report, if indicated) as described in TS 32.422 [49].

If the *MDT Configuration* IE is included and the *MDT Activation* IE is set to "MDT Only" then the DRNC shall, if supported, initiate the requested MDT function (M3 Report, if indicated) as described in TS 32.422 [49] and shall ignore the List of *Interfaces to Trace* IE and the *Trace Depth* IE.

If *Trace Collection Entity IP Address* IE is included then the DRNC shall, if supported, store the Trace Collection Entity IP address and may use the Trace Collection Entity IP address when transferring trace records.

8.3.26.3 Abnormal Conditions

If the MDT Configuration IE is included in the IUR INVOKE TRACE message and the Trace Collection Entity IP Address IE is not included, the DRNC shall ignore the MDT Configuration.

8.3.27 Iur Deactivate Trace

8.3.27.1 General

The purpose of the Iur Deactivate Trace procedure is to inform the DRNC that it should stop a Trace Session for the concerned UE Context and the indicated Trace Reference. This procedure is used for the Signalling Based Deactivation mechanism as defined in TS 32.421 [48] and TS 32.422 [49].

This procedure shall use the signalling bearer mode specified below.

8.3.27.2 Successful Operation



Figure 26L: Iur Invoke Trace procedure, Successful Operation

The Iur Deactivate Trace procedure is invoked by the SRNC by sending an IUR DEACTIVATE TRACE message to the DRNC.

When the concerned UE is utilising one or more radio links in the DRNC the message shall be sent using the connection oriented service of the signalling bearer and no further identification of the UE Context in the DRNC is required. If on the other hand, the UE is not utilising any radio link the message shall be sent using the connectionless service of the signalling bearer and the *D-RNTI* IE shall be included in the message to identify the UE Context in the DRNC.

Upon receiving the IUR DEACTIVATE TRACE message, the DRNC shall stop for the concerned UE Context any ongoing Trace Recording Session for the Trace Session identified by the *Trace Reference* IE.

8.3.27.3 Abnormal Conditions

_

8.3.28 Enhanced Relocation

8.3.28.1 General

This procedure is used for relocation of SRNS in case the SRNC and DRNC connect to same CN node.

The connection-oriented service of the signalling bearer shall be established in conjunction with this procedure in case the relevant UE Context does not exist for the UE.

This procedure shall use the signalling bearer connection for the relevant UE Context in the UE Context exists. The Enhanced Relocation procedure shall not be initiated if a Prepared Reconfiguration exists, as defined in subclause 3.1.

8.3.28.2 Successful Operation




Figure 26M: Enhanced Relocation procedure: Successful Operation

The SRNC initiates the procedure by sending an ENHANCED RELOCATION REQUEST message. When the SRNC sends the ENHANCED RELOCATION REQUEST message, it shall start the timer $T_{RELOCprep}$. The ENHANCED RELOCATION REQUEST message shall contain the *Cause* IE with an appropriate value e.g.: "Time critical Relocation", "Resource optimisation relocation", "Relocation desirable for radio reasons", "Directed Retry", "Reduce Load in Serving Cell", "No Iu CS UP relocation".

If the ENHANCED RELOCATION REQUEST message includes SRNC-ID, the DRNC shall create a UE Context for this UE, allocate a D-RNTI for the UE Context.

8.3.28.3 Unsuccessful Operation




Figure 26N: Enhanced Relocation procedure: Unsuccessful Operation

If the DRNC is not able to accept any of the RABs or a failure occurs during the procedure, the DRNC shall send the ENHANCED RELOCATION FAILURE message to the SRNC. The message shall contain the *Cause* IE with an appropriate value.

Interactions with Enhanced Relocation Cancel procedure:

If there is no response from the DRNC to the ENHANCED RELOCATION REQUEST message before timer $T_{\text{RELOC}prep}$ expires in the DRNC, the SRNC should cancel the Enhanced Relocation procedure towards the DRNC by initiating the Enhanced Relocation Cancel procedure with the appropriate value for the *Cause* IE, e.g. " $T_{\text{RELOC}prep}$ expiry". The SRNC shall ignore any ENHANCED RELOCATION RESPONSE or ENHANCED RELOCATION FAILURE message received after the initiation of the Enhanced Relocation Cancel procedure and remove any reference and release any resources related to the concerned UE Context.

8.3.28.4 Abnormal Conditions

_

8.3.29 Enhanced Relocation Cancel

8.3.29.1 General

This procedure is used to cancel an ongoing enhanced relocation or an already prepared relocation.

This procedure shall use the signalling bearer connection for the relevant UE Context.

8.3.29.2 Successful Operation



Figure 260: Enhanced Relocation Cancel procedure: Successful Operation

The SRNC initiates the procedure by sending the ENHANCED RELOCATION CANCEL message to the DRNC. The SRNC shall indicate the reason for cancelling the relocation by means of an appropriate cause value. Typical cause values are " $T_{RELOCprep}$ Expiry", "Relocation Cancelled", "Traffic Load In The Target Cell Higher Than In The Source Cell".

At the reception of the ENHANCED RELOCATION CANCEL message, the DRNC shall remove any reference to, and release any resources previously reserved to the concerned UE context.

8.3.29.3 Unsuccessful Operation

Not applicable.

8.3.29.4 Abnormal Conditions

-

8.3.30 Enhanced Relocation Signalling Transfer

8.3.30.1 General

The procedure is used by the SRNC to transfer DL L3 information to DRNC during enhanced relocation.

This procedure shall use the signalling bearer connection for the relevant UE Context.

8.3.30.2 Successful Operation



Figure 26P: Enhanced Relocation Signalling Transfer procedure, Successful Operation

The procedure consists of the ENHANCED RELOCATION SIGNALLING TRANSFER message sent by the SRNC to the DRNC.

The ENHANCED RELOCATION SIGNALLING TRANSFER message contains the L3 Information and after the receipt of the message, the DRNC shall send the L3 Information on the DCCH.

8.3.30.3 Abnormal Conditions

-

8.3.31 Enhanced Relocation Release

8.3.31.1 General

The procedure is used by the DRNC to signal to the SRNC that resource for CN domain is released due to failure of the enhanced relocation.

This procedure shall use the signalling bearer connection for the relevant UE Context.

8.3.31.2 Successful Operation




Figure 26Q: Enhanced Relocation Signalling Transfer procedure, Successful Operation

The procedure consists of the ENHANCED RELOCATION RELEASE message sent by the DRNC to the SRNC.

Upon reception of the ENHANCED RELOCATION RELEASE message, the SRNC shall release related resources associated to indicated CN domain(s) by the *Released CN Domain* IE in the message for the UE context.

8.3.31.3 Abnormal Conditions

-

8.3.32 Secondary UL Frequency Reporting [FDD]

8.3.32.1 General

The purpose of this procedure is to inform the DRNS about the activation state of the secondary UL frequency of the UE in Dual Cell E-DCH operation.

This procedure shall use the signalling bearer connection for the relevant UE Context.

8.3.32.2 Successful Operation




Figure 26R: Secondary UL Frequency Reporting procedure

The Secondary UL Frequency Reporting procedure is initiated by sending the SECONDARY UL FREQUENCY REPORT message from the SRNC to the DRNC.

The *Activation Information* IE defines the local activation state of the Secondary uplink frequency of the UE in Dual Cell E-DCH operation.

- If the value of *Uu Activation State* IE is "Activated": the DRNS shall if supported use this information for resource allocation operation of the secondary E-DCH radio link(s), F-DPCH transmission and DPCCH detection.
- If the value of *Uu Activation State* IE is "De-Activated": the DRNS shall if supported use this information for release of the related resources for the secondary E-DCH radio link(s), cease of F-DPCH transmission and DPCCH detection.

8.3.32.3 Abnormal Conditions

_

8.3.33 Secondary UL Frequency Update [FDD]

8.3.33.1 General

The purpose of this procedure is to inform the SRNC about updates to activation state of the secondary UL frequency of the UE in Dual Cell E-DCH operation .

This procedure shall use the signalling bearer connection for the relevant UE context.

8.3.33.2 Successful Operation




Figure 26S: Secondary UL Frequency Update procedure

The Secondary UL Frequency Update procedure is initiated by the DRNS by sending the SECONDARY UL FREQUENCY UPDATE INDICATION message to the SRNC.

If the DRNS needs to update the local activation state of the Secondary uplink frequency of the UE in Dual Cell E-DCH operation, the DRNS shall send SECONDARY UL FREQUENCY UPDATE INDICATION message and include the *Activation Information* IE.

8.3.33.3 Abnormal Conditions

_

8.4 Common Transport Channel Procedures

8.4.1 Common Transport Channel Resources Initialisation

8.4.1.1 General

The Common Transport Channel Resources Initialisation procedure is used by the SRNC for the initialisation of the Common Transport Channel user plane towards the DRNC and/or for the initialisation of the Common Transport Channel resources in the DRNC to be used by a UE.

This procedure shall use the connectionless mode of the signalling bearer.

8.4.1.2 Successful Operation




Figure 27: Common Transport Channel Resources Initialisation procedure, Successful Operation

The SRNC initiates the procedure by sending the message COMMON TRANSPORT CHANNEL RESOURCES REQUEST message to the DRNC.

If the value of the *Transport Bearer Request Indicator* IE is set to "Bearer Requested", the DRNC shall store the received *Transport Bearer ID* IE. The DRNC may use the *Transport Layer Address* and *Binding ID* IEs included in the COMMON TRANSPORT CHANNEL RESOURCES REQUEST message received from the SRNC when establishing a transport bearer for the common transport channel. In addition, the DRNC shall include its own *Binding ID* IE and *Transport Layer Address* IE in the COMMON TRANSPORT CHANNEL RESOURCES RESPONSE message.

If the *TNL QoS* IE is included and if ALCAP is not used, the *TNL QoS* IE may be used by the DRNC to determine the transport bearer characteristics to apply in the uplink between the DRNS and the SRNC for the related common transport channels.

If the value of the *Transport Bearer Request Indicator* IE is set to" Bearer not Requested", the DRNC shall use the transport bearer indicated by the *Transport Bearer ID* IE.

If the *C-ID* IE is included in the COMMON TRANSPORT CHANNEL RESOURCES REQUEST message, the DRNC shall allocate a C-RNTI for the indicated cell and include the *C-RNTI* IE in the COMMON TRANSPORT CHANNEL RESOURCES RESPONSE message.

If the *C-ID* IE is included in the COMMON TRANSPORT CHANNEL RESOURCES REQUEST message, the DRNC shall include the *FACH Info for UE Selected S-CCPCH* IE valid for the cell indicated by the *C-ID* IE and the corresponding *C-ID* IE in the COMMON TRANSPORT CHANNEL RESOURCES RESPONSE message. If the *C-ID* IE is not included in the COMMON TRANSPORT CHANNEL RESOURCES REQUEST message, the DRNC shall include the *FACH Info for UE Selected S-CCPCH* IE valid for the cell where the UE is located and the corresponding *C-ID* IE. The DRNC shall include the *FACH Scheduling Priority* IE and *FACH Initial Window Size* IE in the *FACH Flow Control Information* IE of the *FACH Info for UE Selected S-CCPCH* IE for each priority class that the DRNC has determined shall be used. The DRNC may include several *MAC-c/sh SDU Length* IEs for each priority class.

If the DRNS has any RACH and/or FACH [FDD – and/or HS-DSCH] [1.28Mcps TDD – and/or HS-DSCH] resources previously allocated for the UE in another cell than the cell in which resources are currently being allocated, the DRNS shall release the previously allocated RACH and/or FACH resources [FDD – and/or HS-DSCH] [1.28Mcps TDD – and/or HS-DSCH].

If the DRNS has successfully reserved the required resources, the DRNC shall respond to the SRNC with the COMMON TRANSPORT CHANNEL RESOURCES RESPONSE message.

If the *Permanent NAS UE Identity* IE is present in the COMMON TRANSPORT CHANNEL RESOURCES REQUEST message, the DRNS shall store the information for the considered UE Context for the lifetime of the UE Context.

If the COMMON TRANSPORT CHANNEL RESOURCES REQUEST message includes a *C-ID* IE corresponding to a cell reserved for operator use and the Permanent NAS UE Identity is available in the DRNC for the considered UE Context, the DRNC shall use this information to determine whether it can reserve resources on a common transport channel in this cell or not.

If the *MBMS Bearer Service List* IE is included in the COMMON TRANSPORT CHANNEL RESOURCES REQUEST message, the DRNC shall, if supported, perform the UE Linking as specified in TS 25.346 [50], section 5.1.6. If an MBMS session for some MBMS bearer services contained in the UE Link is ongoing in the cell identified by the *C-ID* IE, the DRNC shall include in the *Active MBMS Bearer Service List* IE the *Transmission Mode* IE for each of these active MBMS bearer services in the COMMON TRANPORT CHANNEL RESOURCES RESPONSE message.

[FDD – If the COMMON TRANSPORT CHANNEL RESOURCES REQUEST message includes an *Enhanced FACH Support Indicator* IE, the DRNC may include the *Enhanced FACH Information Response* IE in the COMMON TRANSPORT CHANNEL RESOURCES RESPONSE message. If a HS-DSCH RNTI was not previously allocated to the UE or a new HS-DSCH RNTI is allocated to the UE, the DRNC shall include the *HS-DSCH-RNTI* IE in the *Enhanced FACH Information Response* IE. And if Enhanced PCH operation is activated in the cell indicated by the *C-ID* IE, the DRNC shall include the *Priority Queue Information for Enhanced PCH* IE in the *Enhanced FACH Information Response* IE.]

[1.28Mcps TDD – If the COMMON TRANSPORT CHANNEL RESOURCES REQUEST message includes an *Enhanced FACH Support Indicator* IE, the DRNC may include the *Enhanced FACH Information Response* IE in the COMMON TRANSPORT CHANNEL RESOURCES RESPONSE message. If a HS-DSCH RNTI was not previously allocated to the UE or a new HS-DSCH RNTI is allocated to the UE, the DRNC shall include the *HS-DSCH-RNTI* IE in the *Enhanced FACH Information Response* IE. And if Enhanced PCH operation is activated in the cell indicated by the

C-ID IE, the DRNC shall include the *Priority Queue Information for Enhanced PCH* IE in the *Enhanced FACH Information Response* IE.]

[FDD – If the COMMON TRANSPORT CHANNEL RESOURCES REQUEST message includes an *Common E-DCH Support Indicator* IE, the DRNC may include the *Common E-DCH MAC-d Flow Specific Information* IE in the COMMON TRANSPORT CHANNEL RESOURCES RESPONSE message. If the E-DCH MAC-d Flow Multiplexing List for a Common E-DCH MAC-d Flow is configured in DRNC, the DRNC shall include the *E-DCH MAC-d Flow Multiplexing List* IE in the COMMON TRANSPORT CHANNEL RESOURCES RESPONSE message. If the COMMON TRANSPORT CHANNEL RESOURCES REQUEST message includes the *C-ID* IE and the *Common E-DCH Support Indicator* IE, the DRNC may include the *E-RNTI* IE in the COMMON TRANSPORT CHANNEL RESOURCES RESPONSE message.]

[1.28Mcps TDD – If the COMMON TRANSPORT CHANNEL RESOURCES REQUEST message includes a *Enhanced FACH Support Indicator* IE, the DRNC may include the *Common E-DCH MAC-d Flow Specific Information LCR* IE in the COMMON TRANSPORT CHANNEL RESOURCES RESPONSE message.]

If the COMMON TRANSPORT CHANNEL RESOURCES REQUEST message includes an *HS-DSCH physical layer category* IE, the DRNC may store the information for the considered UE Context for the lifetime of the UE Context.

[FDD – If the COMMON TRANSPORT CHANNEL RESOURES REQUEST message includes an *UE with enhanced HS-SCCH support indicator* IE, the DRNC may store the information for the considered UE Context for the lifetime of the UE context.]

8.4.1.3 Unsuccessful Operation




Figure 28: Common Transport Channel Resources Initialisation procedure, Unsuccessful Operation

If the *Transport Bearer Request Indicator* IE is set to "Bearer Requested" and the DRNC is not able to provide a Transport Bearer, the DRNC shall reject the procedure and respond to the SRNC with the COMMON TRANSPORT CHANNEL RESOURCES FAILURE message, including the reason for the failure in the *Cause* IE.

If the COMMON TRANSPORT CHANNEL RESOURCES REQUEST message contains a *C-ID* IE corresponding to a cell reserved for operator use and the Permanent NAS UE Identity is not available for the considered UE Context, the DRNC shall reject the procedure and send the COMMON TRANSPORT CHANNEL RESOURCES FAILURE message, including the reason for the failure in the *Cause* IE.

Typical cause values are:

Radio Network Layer Causes:

- Common Transport Channel Type not Supported;
- Cell reserved for operator use.

Transport Layer Causes:

- Transport Resource Unavailable.

8.4.1.4 Abnormal Conditions

If the COMMON TRANSPORT CHANNEL RESOURCES REQUEST message contains the *Transport Layer Address* IE or the *Binding ID* IE, and not both are present for a transport channel intended to be established, the DRNC shall reject the procedure using the COMMON TRANSPORT CHANNEL RESOURCES FAILURE message.

If ALCAP is not used, if the COMMON TRANSPORT CHANNEL RESOURCES REQUEST message contains the *Transport Bearer Request Indicator* IE set to "Bearer Requested" but does not contain the *Transport Layer Address* IE and the *Binding ID* IE, the DRNC shall reject the procedure using the COMMON TRANSPORT CHANNEL RESOURCES FAILURE message.

8.4.2 Common Transport Channel Resources Release

8.4.2.1 General

This procedure is used by the SRNC to request release of Common Transport Channel Resources for a given UE in the DRNS. The SRNC uses this procedure either to release the UE Context from the DRNC (and thus both the D-RNTI and the C-RNTI) or to release only the C-RNTI.

This procedure shall use the connectionless mode of the signalling bearer.

8.4.2.2 Successful Operation



Figure 29: Common Transport Channel Resources Release procedure, Successful Operation

The SRNC initiates the Common Transport Channel Resources Release procedure by sending the COMMON TRANSPORT CHANNEL RESOURCES RELEASE REQUEST message to the DRNC. Upon receipt of the message the DRNC shall release the UE Context identified by the D-RNTI and all its related RACH and/or FACH resources, unless the UE is using dedicated resources (DCH, [TDD – USCH and/or DSCH]) in the DRNS in which case the DRNC shall release only the C-RNTI and all its related RACH and/or FACH [FDD – and/or HS-DSCH] [1.28Mcps TDD – and/or HS-DSCH] resources allocated for the UE.

8.4.2.3 Abnormal Conditions

_

8.5 Global Procedures

8.5.1 Error Indication

8.5.1.1 General

The Error Indication procedure is initiated by a node to report detected errors in a received message, provided they cannot be reported by an appropriate response message.

This procedure shall use the signalling bearer mode specified below.

8.5.1.2 Successful Operation



Figure 30: Error Indication procedure, Successful Operation

When the conditions defined in clause 10 are fulfilled, the Error Indication procedure is initiated by an ERROR INDICATION message sent from the receiving node. This message shall use the same mode of the signalling bearer and the same signalling bearer connection (if connection oriented) as the message that triggers the procedure.

When the ERROR INDICATION message is sent from a DRNC to an SRNC using connectionless mode of the signalling bearer, the *S-RNTI* IE shall be included in the message if the UE Context addressed by the *D-RNTI* IE which was received in the message triggering the Error Indication procedure exists. When the ERROR INDICATION message is sent from an SRNC to a DRNC using connectionless mode of the signalling bearer, the *D-RNTI* IE shall be included in the message if available.

When a message using connectionless mode of the signalling bearer is received in the DRNC and there is no UE Context in the DRNC as indicated by the *D-RNTI* IE, the DRNC shall include the D-RNTI from the received message in the *D-RNTI* IE and set the *Cause* IE to "Unknown RNTI" in the ERROR INDICATION message, unless another handling is specified in the procedure text for the affected procedure.

When a message using connectionless mode of the signalling bearer is received in the SRNC and there is no UE in the SRNC as indicated by the *S-RNTI* IE, the SRNC shall include the S-RNTI from the received message in the *S-RNTI* IE and set the *Cause* IE to "Unknown RNTI" in the ERROR INDICATION message, unless another handling is specified in the procedure text for the affected procedure.

The ERROR INDICATION message shall include either the *Cause* IE, or the *Criticality Diagnostics* IE, or both the *Cause* IE and the *Criticality Diagnostics* IE to indicate the reason for the error indication.

Typical cause values for the ERROR INDICATION message are:

Protocol Causes:

- Transfer Syntax Error
- Abstract Syntax Error (Reject)
- Abstract Syntax Error (Ignore and Notify)
- Message not Compatible with Receiver State
- Unspecified

8.5.1.2.1 Successful Operation for lur-g

The RNC₁/BSS₁ and RNC₂/BSS₂ shall use the error indication procedure as specified in section 8.5.1.2.

8.5.1.3 Abnormal Conditions

-

8.5.2 Common Measurement Initiation

8.5.2.1 General

This procedure is used by an RNC to request the initiation of measurements of common resources to another RNC. The requesting RNC is referred to as RNC₁ and the RNC to which the request is sent is referred to as RNC₂.

This procedure uses the signalling bearer connection for the relevant Distant RNC Context.

8.5.2.2 Successful Operation




Figure 30A: Common Measurement Initiation procedure, Successful Operation

The procedure is initiated with a COMMON MEASUREMENT INITIATION REQUEST message sent from the RNC₁ to the RNC₂.

Upon receipt, the RNC₂ shall initiate the requested measurement according to the parameters given in the request.

Unless specified below, the meaning of the parameters are given in other specifications.

[TDD – If the [3.84 Mcps TDD and 7.68 Mcps TDD – *Time Slot* IE] [1.28 Mcps – *Time Slot LCR* IE] is present in the COMMON MEASUREMENT INITIATION REQUEST message, the measurement request shall apply to the requested time slot individually.]

Common measurement type

If the *Common Measurement Type* IE is set to "SFN-SFN Observed Time Difference", then:

- The RNC₂ shall initiate the SFN-SFN Observed Time Difference measurements between the reference cell identified by the *Reference Cell Identifier* IE and the neighbouring cells identified by the *UTRAN Cell Identifier* IE (*UC-ID*) in the *Neighbouring Cell Measurement Information* IE.
- [3.84 Mcps TDD The RNC₂ shall perform the measurement using the time slot specified in the *Time Slot* IE in the *Neighbouring TDD Cell Measurement Information* IE and using the midamble shift and burst type specified in the *Midamble Shift And Burst Type* IE in the *Neighbouring TDD Cell Measurement Information* IE. If *Time Slot* IE and *Midamble Shift And Burst Type* IE are not available in the *Neighbouring TDD Cell Measurement Information* IE, the RNC₂ may use any appropriate time slots, midamble shifts and burst types to make the measurement.]
- [7.68 Mcps TDD The RNC₂ shall perform the measurement using the time slot specified in the *Time Slot* IE in the *Neighbouring TDD Cell Measurement Information 7.68 Mcps* IE and using the midamble shift and burst type specified in the *Midamble Shift And Burst Type 7.68 Mcps* IE in the *Neighbouring TDD Cell Measurement Information 7.68 Mcps* IE. If *Time Slot* IE and *Midamble Shift And Burst Type 7.68 Mcps* IE are not available in the *Neighbouring TDD Cell Measurement Information 7.68 Mcps* IE, the RNC₂ may use any appropriate time slots, midamble shifts and burst types to make the measurement.]

If the *Common Measurement Type* IE is set to "load", the RNC₂ shall initiate measurements of uplink and downlink load on the measured object identified by the *Reference Cell Identifier* IE. If either uplink or downlink load satisfies the requested report characteristics, the RNC₂ shall report the result of both uplink and downlink measurements.

If the *Common Measurement Type* IE is set to "UTRAN GPS Timing of Cell Frames for UE Positioning", "UTRAN GANSS Timing of Cell Frames for UE Positioning", "transmitted carrier power", "received total wide band power", or

"UL timeslot ISCP" the RNC₂ shall initiate measurements on the measured object identified by the *Reference Cell Identifier* IE.

If the *Common Measurement Type* IE is set to "UTRAN GANSS Timing of Cell Frames for UE Positioning", then the RNC₂ shall initiate the UTRAN GANSS Timing of Cell Frames measurements using the GNSS system time identified by *GANSS Time ID* IE included in the COMMON MEASUREMENT INITIATION REQUEST message.

- If the *Common Measurement Type* IE is set to "UTRAN GANSS Timing of Cell Frames for UE Positioning" and the *GANSS Time ID* IE is not included in the COMMON MEASUREMENT INITIATION REQUEST message, the RNC₂ shall assume that the corresponding GANSS time is "Galileo" system time.

If the Common Measurement Type IE is set to "RT load", the RNC $_2$ shall initiate measurements of uplink and downlink estimated share of RT (Real Time) traffic of the load of the measured object. If either uplink or downlink RT load satisfies the requested report characteristics, the RNC $_2$ shall report the result of both uplink and downlink measurements.

If the Common Measurement Type IE is set to "NRT load Information", the RNC $_2$ shall initiate measurements of uplink and downlink NRT (Non Real Time) load situation on the measured object. If either uplink or downlink NRT load satisfies the requested report characteristics, the RNC $_2$ shall report the result of both uplink and downlink measurements.

Report characteristics

The Report Characteristics IE indicates how the reporting of the measurement shall be performed. See also Annex B.

If the *Report Characteristics* IE is set to "On Demand" and if the *SFN* IE is not provided, the RNC₂ shall report the result of the requested measurement immediately in the COMMON MEASUREMENT INITIATION RESPONSE message. If the *SFN* IE is provided, it indicates the frame for which the measurement value shall be provided. The provided measurement value shall be the one reported by the layer 3 filter, referred to as point C in the measurement model (TS 25.302 [26]). Furthermore, if the *SFN* IE is present and if the *Common Measurement Type* IE is set to "SFN-SFN Observed Time Difference", then the *SFN* IE relates to the Radio Frames of the Reference Cell identified by the *Reference Cell Identifier* IE.

If the *Report Characteristics* IE is set to "Periodic" and if the *SFN* IE is not provided, the RNC₂ shall immediately and periodically initiate a Common Measurement Reporting procedure for this measurement, with a frequency as specified by the *Report Periodicity* IE. If the *SFN* IE is provided, the RNC₂ shall initiate a Common Measurement Reporting procedure for this measurement at the SFN indicated in the *SFN* IE, and shall repeat this initiation periodically thereafter with a frequency as specified by the *Report Periodicity* IE. The provided measurement value shall be the one reported by the layer 3 filter, referred to as point C in the measurement model (TS 25.302 [26]). Furthermore, if the *SFN* IE is present and if the *Common Measurement Type* IE is set to "SFN-SFN Observed Time Difference", then the *SFN* IE relates to the Radio Frames of the Reference Cell identified by the *Reference Cell Identifier* IE.

If the *Report Characteristics* IE is set to "Event A", the RNC₂ shall initiate the Common Measurement Reporting procedure when the measured entity rises above the requested threshold, as specified by the *Measurement Threshold* IE, and then stays above the threshold for the requested hysteresis time, as specified by the *Measurement Hysteresis Time* IE. If the *Measurement Hysteresis Time* IE is not included, the RNC₂ shall use the value zero for the hysteresis time.

If the *Report Characteristics* IE is set to "Event B", the RNC₂ shall initiate the Common Measurement Reporting procedure when the measured entity falls below the requested threshold, as specified by the *Measurement Threshold* IE, and then stays below the threshold for the requested hysteresis time, as specified by the *Measurement Hysteresis Time* IE. If the *Measurement Hysteresis Time* IE is not included, the RNC₂ shall use the value zero for the hysteresis time.

If the *Report Characteristics* IE is set to "Event C", the RNC₂ shall initiate the Common Measurement Reporting procedure when the measured entity rises more than the requested threshold specified by the *Measurement Increase/Decrease Threshold* IE, and only when this rise occurs within the requested rising time specified by the *Measurement Change Time* IE. After reporting this type of event, the RNC₂ shall not initiate the next C event reporting for the same measurement during the subsequent time specified by the *Measurement Change Time* IE.

If the *Report Characteristics* IE is set to "Event D", the RNC₂ shall initiate the Common Measurement Reporting procedure when the measured entity falls more than the requested threshold specified by the *Measurement Increase/Decrease Threshold* IE, and only when this fall occurs within the requested falling time specified by the *Measurement Change Time* IE. After reporting this type of event,, the RNC₂ shall not initiate the next D event reporting for the same measurement during the subsequent time specified by the *Measurement Change Time* IE.

If the *Report Characteristics* IE is set to "Event E", the RNC₂shall initiate the Common Measurement Reporting procedure when the measured entity rises above the *Measurement Threshold 1* IE and stays above the threshold for the *Measurement Hysteresis Time* IE (Report A). When the conditions for Report A are met and if the *Report Periodicity* IE is provided, the RNC₂ shall initiate the Common Measurement Reporting procedure periodically with the requested report frequency specified by the *Report Periodicity* IE. If the conditions for Report A have been met and the measured entity falls below the *Measurement Threshold 2* IE and stays below the threshold for the *Measurement Hysteresis Time* IE, the RNC₂ shall initiate the Common Measurement Reporting procedure (Report B) and shall terminate any corresponding periodic reporting. If the *Measurement Threshold 2* IE is not present, the RNC₂ shall use the value of the *Measurement Threshold 1* IE instead. If the *Measurement Hysteresis Time* IE is not included, the RNC₂ shall use the value zero as hysteresis times for both Report A and Report B.

If the *Report Characteristics* IE is set to "Event F", the RNC₂ shall initiate the Common Measurement Reporting procedure when the measured entity falls below the *Measurement Threshold 1* IE and stays below the threshold for the *Measurement Hysteresis Time* IE (Report A). When the conditions for Report A are met and if the *Report Periodicity* IE is provided, the RNC₂ shall initiate the Measurement Reporting procedure periodically with the requested report frequency specified by the *Report Periodicity* IE. If the conditions for Report A have been met and the measured entity rises above the *Measurement Threshold 2* IE and stays above the threshold for the *Measurement Hysteresis Time* IE, the RNC₂ shall initiate the Common Measurement Reporting procedure (Report B) and shall terminate any corresponding periodic reporting. If the *Measurement Threshold 2* IE is not present, the RNC₂ shall use the value of the *Measurement Threshold 1* IE instead. If the *Measurement Hysteresis Time* IE is not included, the RNC₂ shall use the value zero as hysteresis times for both Report A and Report B.

[1.28Mcps TDD-If the *Report Characteristics* IE is set to "Event H" (figure B.7), the Measurement Reporting procedure (Report A) is initiated when the measurement value of measured entity rises above the *Measurement Threshold 1* and stays above the threshold for the *Measurement Hysteresis Time* (T_1 in figure B.7).] The measurement value of measured entity in Report A substitutes the *Measurement Base value* for the consequent measurement reporting.

When the Report A conditions has been met and the measurement value of measured entity rises above or falls below the *Measurement Base Value* by *Measurement Fluctuation Range* (H₁ in figure B.7), and stays there for the *Measurement Hysteresis Time* (T_h in figure B.7) counting from the beginning of every *Report Periodicity*, the Measurement Reporting procedure (Report B or Report C) is initiated. The the measurement value of measured entity in (Report B or Report C) substitutes the *Measurement Base value* for the consequent measurement reporting.

When the Report A conditions have been met and the measurement value of measured entity falls below the *Measurement Threshold 2* and stays there for the *Measurement Hysteresis Time* (T_h in figure B.7), the Measurement Reporting procedure (Report D) is initiated and the reporting is terminated.]

If the *Report Characteristics* IE is set to "On Modification" and if the *SFN* IE is not provided, the RNC₂ shall report the result of the requested measurement immediately. If the *SFN* IE is provided, it indicates the frame for which the first measurement value shall be provided. The provided measurement value shall be the one reported by the layer 3 filter, referred to as point C in the measurement model (TS 25.302 [26]). Furthermore, if the *SFN* IE is present and if the *Common Measurement Type* IE is set to "SFN-SFN Observed Time Difference", then the *SFN* IE relates to the Radio Frames of the Reference Cell identified by the *Reference Cell Identifier* IE. Following the first measurement report, the RNC₂ shall initiate the Common Measurement Reporting procedure in accordance to the following conditions:

- 1. If the Common Measurement Type IE is set to "UTRAN GPS Timing of Cell Frames for UE Positioning":
 - If the *T_{UTRAN-GPS} Change Limit* IE is included in the *T_{UTRAN-GPS} Measurement Threshold Information* IE, the RNC₂ shall calculate the change of T_{UTRAN-GPS} value (F_n) each time a new measurement result is received after point C in the measurement model (TS 25.302 [26]). The RNC₂ shall initiate the Common Measurement Reporting procedure and set n equal to zero when the absolute value of F_n rises above the threshold indicated by the *T_{UTRAN-GPS} Change Limit* IE. The change of T_{UTRAN-GPS} value (F_n) is calculated according to the following:

 $F_n=0$ for n=0

$$F_n = (M_n - M_{n-1}) \bmod 37158912000000 - ((SFN_n - SFN_{n-1}) \bmod 4096) *10*3.84*10^3*16 + F_{n-1} \qquad \qquad \text{for } n > 0$$

F_n is the change of the T_{UTRAN-GPS} value expressed in unit [1/16 chip] when n measurement results have been received after the first Common Measurement Reporting at initiation or after the last event was triggered.

- M_n is the latest measurement result received after point C in the measurement model (TS 25.302 [26]), measured at SFN_n.
- M_{n-1} is the previous measurement result received after point C in the measurement model (TS 25.302 [26]), measured at SFN_{n-1} .
- M₁ is the first measurement result received after point C in the measurement model (TS 25.302 [26]), after first Common Measurement Reporting at initiation or after the last event was triggered.
- M₀ is equal to the value reported in the first Common Measurement Reporting at initiation or in the Common Measurement Reporting when the event was triggered.
- If the *Predicted T_{UTRAN-GPS} Deviation Limit* IE is included in the *T_{UTRAN-GPS} Measurement Threshold Information* IE, the RNC₂ shall update the P_n and F each time a new measurement result is received after point C in the measurement model (TS 25.302 [26]). The RNC₂ shall initiate the Common Measurement Reporting procedure and set n equal to zero when F_n rises above the threshold indicated by the *Predicted T_{UTRAN-GPS} Deviation Limit* IE. The P_n and F_n are calculated according to the following:

```
P_n=b for n=0
```

```
P_n = ((a/16)*((SFN_n - SFN_{n-1}) \bmod 4096)/100 + ((SFN_n - SFN_{n-1}) \bmod 4096)*10*3.84*10^3*16 + P_{n-1}) \bmod 37158912000000 \ for \quad n>0
```

```
F_n = min((M_n - P_n) \text{ mod } 37158912000000, (P_n - M_n) \text{ mod } 37158912000000) for n>0
```

 P_n is the predicted $T_{UTRAN\text{-}GPS}$ value when n measurement results have been received after the first Common Measurement Reporting at initiation or after the last event was triggered.

A is the last reported T_{UTRAN-GPS} Drift Rate value.

B is the last reported $T_{UTRAN-GPS}$ value.

- F_n is the deviation of the last measurement result from the predicted $T_{UTRAN\text{-}GPS}$ value (P_n) when n measurements have been received after the first Common Measurement Reporting at initiation or after the last event was triggered.
- M_n is the latest measurement result received after point C in the measurement model (TS 25.302 [26]), measured at SFN_n.
- M_1 is the first measurement result received after point C in the measurement model (TS 25.302 [26]), after first Common Measurement Reporting at initiation or after the last event was triggered.

The $T_{UTRAN-GPS}$ Drift Rate is determined by the RNS₂ in an implementation-dependent way after point B (see model of physical layer measurements in (TS 25.302 [26])).

- 2. If the Common Measurement Type IE is set to "SFN-SFN Observed Time Difference":
 - If the SFN-SFN Change Limit IE is included in the SFN-SFN Measurement Threshold Information IE, the RNC₂ shall calculate the change of SFN-SFN value (F_n) each time a new measurement result is received after point C in the measurement model (TS 25.302 [26]). The RNC₂ shall initiate the Common Measurement Reporting procedure in order to report the particular SFN-SFN measurement which has triggered the event and set n equal to zero when the absolute value of F_n rises above the threshold indicated by the SFN-SFN Change Limit IE. The change of the SFN-SFN value is calculated according to the following:

 $F_n=0$ for n=0

$$[FDD - F_n = (M_n - a) \ mod \ 614400 \quad \ for \ n{>}0]$$

$$[TDD - F_n = (M_n - a) \mod 40960$$
 for n>0]

 F_n is the change of the SFN-SFN value expressed in unit [1/16 chip] when n measurement results have been received after the first Common Measurement Reporting at initiation or after the last event was triggered.

A is the last reported SFN-SFN.

- M_n is the latest measurement result received after point C in the measurement model (TS 25.302 [26]), measured at SFN_n.
- M₁ is the first measurement result received after point C in the measurement model (TS 25.302 [26]), after the first Common Measurement Reporting at initiation or after the last event was triggered.
- If the *Predicted SFN-SFN Deviation Limit* IE is included in the *SFN-SFN Measurement Threshold Information* IE, the RNC₂ shall each time a new measurement result is received after point C in the measurement model (TS 25.302 [26]), update the P_n and F_n. The RNC₂ shall initiate the Common Measurement Reporting procedure in order to report the particular SFN-SFN measurement which has triggered the event and set n equal to zero when F_n rises above the threshold indicated by the *Predicted SFN-SFN Deviation Limit* IE. The P_n and F_n are calculated according to the following:

 $P_n=b$ for n=0

$$[FDD - P_n = ((a/16) * ((SFN_n - SFN_{n-1}) \ mod \ 4096)/100 + \ P_{n-1}) \ mod \ 614400 \qquad for \quad n>0]$$

$$[FDD - F_n = min((M_n - P_n) \text{ mod } 614400, (P_n - M_n) \text{ mod } 614400)$$
 for n>0]

$$[TDD - P_n = ((a/16)*(15*(SFN_n - SFN_{n-1})mod\ 4096 + (TS_n - TS_{n-1}))/1500 + P_{n-1}\)\ mod\ 40960\ for \\ m>0]$$

$$[TDD - F_n = min((M_n - P_n) \mod 40960, (P_n - M_n) \mod 40960)$$
 for n>0]

P_n is the predicted SFN-SFN value when n measurement results have been received after the first Common Measurement Reporting at initiation or after the last event was triggered.

A is the last reported SFN-SFN Drift Rate value.

B is the last reported SFN-SFN value.

- F_n is the deviation of the last measurement result from the predicted SFN-SFN value (P_n) when n measurements have been received after first Common Measurement Reporting at initiation or after the last event was triggered.
- M_n is the latest measurement result received after point C in the measurement model (TS 25.302 [26]), measured at the [TDD the Time Slot TS_n of] the Frame SFN_n .
- M_1 is the first measurement result received after point C in the measurement model (TS 25.302 [26]), after first Common Measurement Reporting at initiation or after the last event was triggered.

The SFN-SFN Drift Rate is determined by the RNS₂ in an implementation-dependent way after point B (see model of physical layer measurements in (TS 25.302 [26])).

- 3. If the Common Measurement Type IE is set to "UTRAN GANSS Timing of Cell Frames for UE Positioning":
 - If the T_{UTRAN-GANSS} Change Limit IE is included in the T_{UTRAN-GANSS} Measurement Threshold Information IE, the RNC₂ shall calculate the change of T_{UTRAN-GANSS} value (F_n) each time a new measurement result is received after point C in the measurement model (TS 25.302 [26]). The RNC₂ shall initiate the Common Measurement Reporting procedure and set n equal to zero when the absolute value of F_n rises above the threshold indicated by the T_{UTRAN-GANSS} Change Limit IE. The change of T_{UTRAN-GANSS} value (F_n) is calculated according to the following:

Fn=0 for n=0

$$Fn = (GAMn - GAMn - 1) \bmod 5308416000000 - ((SFNn - SFNn - 1) \bmod 4096) *10*3.84*10^3 *16 + Fn - 1 \\ for n > 0$$

Fn is the change of the TUTRAN-GANSS value expressed in unit [1/16 chip] when n measurement results have been received after the first Common Measurement Reporting at initiation or after the last event was triggered.

GAMn is the latest GANSS measurement result received after point C in the GANSS measurement model, measured at SFNn.

- GAMn-1 is the previous GANSS measurement result received after point C in the GANSS measurement model, measured at SFNn-1.
- GAM1 is the first GANSS measurement result received after point C in the GANSS measurement model, after the first Common Measurement Reporting at initiation or after the last event was triggered.
- GAM0 is equal to the value reported in the first Common Measurement Reporting at initiation or in the Common Measurement Reporting when the event was triggered.

GANSS measurement model is the timing between cell j and GANSS Time Of Day. $T_{UE\text{-}GANSSj}$ is defined as the time of occurrence of a specified UTRAN event according to GANSS time. The specified UTRAN event is the beginning of a particular frame (identified through its SFN) in the first detected path (in time) of the cell j CPICH, where cell j is a cell chosen by the UE. The reference point for $T_{UE\text{-}GANSSj}$ shall be the antenna connector of the UE.

- If the *Predicted T_{UTRAN-GANSS} Deviation Limit* IE is included in the *T_{UTRAN-GANSS} Measurement Threshold Information* IE, the RNC₂ shall update the P_n and F each time a new measurement result is received after point C in the measurement model (TS 25.302 [26]). The RNC₂ shall initiate the Common Measurement Reporting procedure and set n equal to zero when F_n rises above the threshold indicated by the *Predicted T_{UTRAN-GANSS} Deviation Limit* IE. The P_n and F_n are calculated according to the following:

 $P_n=b$ for n=0

 $P_n = ((a/16)*((SFN_n - SFN_{n-1}) \bmod 4096)/100 + ((SFN_n - SFN_{n-1}) \bmod 4096)*10*3.84*10^3*16 + P_{n-1}) \bmod 5308416000000 \qquad \qquad for \ n > 0$

 $F_n = min((GAM_n - P_n) \mod 5308416000000, (P_n - GAM_n) \mod 5308416000000)$ for n>0

 P_n is the predicted $T_{UTRAN-GANSS}$ value when n measurement results have been received after the first Common Measurement Reporting at initiation or after the last event was triggered.

A is the last reported T_{UTRAN-GANSS} Drift Rate value.

B is the last reported T_{UTRAN-GANSS} value.

- F_n is the deviation of the last measurement result from the predicted $T_{UTRAN\text{-}GANSS}$ value (P_n) when n measurements have been received after the first Common Measurement Reporting at initiation or after the last event was triggered.
- GAM_n is the latest GANSS measurement result received after point C in the GANSS measurement model, measured at SFN_n.
- GAM₁ is the first GANSS measurement result received after point C in the GANSS measurement model, after the first Common Measurement Reporting at initiation or after the last event was triggered.

The $T_{UTRAN-GANSSS}$ Drift Rate is determined by the RNS₂ in an implementation-dependent way after point B (see model of physical layer measurements in (TS 25.302 [26])).

If the *Report Characteristics* IE is not set to "On Demand", the RNC₂ is required to perform reporting for a common measurement object, in accordance with the conditions provided in the COMMON MEASUREMENT INITIATION REQUEST message, as long as the object exists. If no common measurement object(s) for which a measurement is defined exists any more, the RNC₂ shall terminate the measurement locally without reporting this to RNC₁.

If at the start of the measurement, the reporting criteria are fulfilled for any of Event A, Event B, Event E or Event F, the RNC₂ shall initiate a Measurement Reporting procedure immediately, and then continue with the measurements as specified in the COMMON MEASUREMENT INITIATION REQUEST message.

Common measurement accuracy

If the Common Measurement Type IE is set to "UTRAN GPS Timing of Cell Frames for UE Positioning", then the RNC₂ shall use the $T_{UTRAN-GPS}$ Measurement Accuracy Class IE included in the Common Measurement Accuracy IE according to the following:

- If the $T_{UTRAN-GPS}$ Measurement Accuracy Class IE indicates "Class A", then the concerned RNC₂ shall perform the measurement with the highest supported accuracy within the accuracy classes A, B or C.

- If the $T_{UTRAN-GPS}$ Measurement Accuracy Class IE indicates the "Class B", then the concerned RNC₂ shall perform the measurements with the highest supported accuracy within the accuracy classes B and C.
- If the $T_{UTRAN-GPS}$ Measurement Accuracy Class IE indicates "Class C", then the concerned RNC₂ shall perform the measurements with the highest supported accuracy according to class C.

If the *Common Measurement Type* IE is set to "SFN-SFN Observed Time Difference", then the concerned RNC₂ shall initiate the SFN-SFN observed Time Difference measurements between the reference cell identified by *UC-ID* IE and the neighbouring cells identified by their UC-ID. The *Report Characteristics* IE applies to each of these measurements.

If the *Common Measurement Type* IE is set to "UTRAN GANSS Timing of Cell Frames for UE positioning", then the RNC₂ shall use the $T_{UTRAN-GANSS}$ Measurement Accuracy Class IE included in the Common Measurement Accuracy IE according to the following:

- If the $T_{UTRAN-GANSS}$ Measurement Accuracy Class IE indicates "Class A", then the concerned RNC₂ shall perform the measurement with the highest supported accuracy within the accuracy classes A, B or C.
- If the $T_{UTRAN-GANSS}$ Measurement Accuracy Class IE indicates the "Class B", then the concerned RNC₂ shall perform the measurements with the highest supported accuracy within the accuracy classes B and C.
- If the $T_{UTRAN-GANSS}$ Measurement Accuracy Class IE indicates "Class C", then the concerned RNC₂ shall perform the measurements with the highest supported accuracy according to class C.

Higher layer filtering

The *Measurement Filter Coefficient* IE indicates how filtering of the measurement values shall be performed before measurement event evaluation and reporting.

The averaging shall be performed according to the following formula.

$$F_n = (1-a) \cdot F_{n-1} + a \cdot M_n$$

The variables in the formula are defined as follows

 F_n is the updated filtered measurement result

 F_{n-1} is the old filtered measurement result

 M_n is the latest received measurement result from physical layer measurements, the unit used for M_n is the same unit as the reported unit in the COMMON MEASUREMENT INITIATION RESPONSE, COMMON MEASUREMENT REPORT messages or the unit used in the event evaluation (i.e. same unit as for Fn).

 $A = \frac{1}{2}(k^2)$, where k is the parameter received in the *Measurement Filter Coefficient* IE. If the *Measurement Filter Coefficient* IE is not present, a shall be set to 1 (no filtering).

In order to initialise the averaging filter, F_0 is set to M_1 when the first measurement result from the physical layer measurement is received.

Measurement Recovery Behavior:

If the *Measurement Recovery Behavior* IE is included in the COMMON MEASUREMENT INITIATION REQUEST message, the RNC₂ shall, if Measurement Recovery Behavior is supported, include the *Measurement Recovery Support Indicator* IE in the COMMON MEASUREMENT INITIATION RESPONSE message and perform the Measurement Recovery Behavior as described in subclause 8.5.3.2.

Response message

If the RNC₂ was able to initiate the measurement requested by RNC, it shall respond with the COMMON MEASUREMENT INITIATION RESPONSE message. The message shall include the same Measurement ID that was used in the COMMON MEASUREMENT INITIATION REQUEST message.

In the case in which the Report Characteristics IE is set to "On Demand" or "On Modification":

The COMMON MEASUREMENT INITIATION RESPONSE message shall include the *Common Measurement Object Type* IE containing the measurement result. It shall also include the *Common Measurement Achieved Accuracy* IE if the *Common Measurement Type* IE is set to "UTRAN GPS Timing of Cell Frames for UE positioning" or "UTRAN GANSS Timing of Cell Frames for UE positioning".

- If the *Common Measurement Type* IE is not set to "SFN-SFN Observed Time Difference" and if the *SFN Reporting Indicator* IE is set to "FN Reporting Required", then the RNC₂ shall include the *SFN* IE in the COMMON MEASUREMENT INITIATION RESPONSE message,. The reported SFN shall be the SFN at the time when the measurement value was reported by the layer 3 filter, referred to as point C in the measurement model (TS 25.302 [26]). If the *Common Measurement Type* IE is set to "SFN-SFN Observed Time Difference", then the *SFN Reporting Indicator* IE is ignored.
- If the Common Measurement Type IE is set to "SFN-SFN Observed Time Difference", then the RNC₂ shall report all the available measurements in the Successful Neighbouring cell SFN-SFN Observed Time Difference Measurement Information IE, and the RNC₂ shall report the neighbouring cells with no measurement result available in the Unsuccessful Neighbouring cell SFN-SFN Observed Time Difference Measurement Information IE. For all available measurement results, the RNC₂ shall include in the Successful Neighbouring Cell SFN-SFN Observed Time Difference Measurement Information IE the SFN-SFN Quality IE and the SFN-SFN Drift Rate Quality IE, if available.

If the *Common Measurement Type* IE is set to "UTRAN GPS Timing of Cell Frames for UE Positioning" and the *Report Characteristics* IE is set to "On Demand" or "On Modification", the RNC₂ shall include in the $T_{UTRAN-GPS}$ *Measurement Value Information* IE the $T_{UTRAN-GPS}$ *Quality* IE and the $T_{UTRAN-GPS}$ *Drift Rate Quality* IE, if available.

If the Common Measurement Type IE is set to "UTRAN GANSS Timing of Cell Frames for UE Positioning" and the Report Characteristics IE is set to "On Demand" or "On Modification", the RNC₂ shall include in the $T_{UTRAN-GANSS}$ Measurement Value Information IE, the $T_{UTRAN-GANSS}$ Quality IE and the $T_{UTRAN-GANSS}$ Drift Rate Quality IE, if available.

8.5.2.2.1 Successful Operation for lur-g

The procedure is initiated with a COMMON MEASUREMENT INITIATION REQUEST message sent from the RNC₁ to the BSS₂ or from the BSS₁ to the RNC₂/BSS₂.

Upon receipt, the RNC₂/BSS₂ shall initiate the requested measurement according to the parameters given in the request.

[1.28Mcps TDD-The procedure is also initiated with a COMMON MEASUREMENT INITIATION REQUEST message sent from the TDD RNC $_1$ to the BSS $_2$ for multiple GERAN cells' measurements by allocating unique Measurement ID for each GERAN cell. Upon receipt, the BSS $_2$ shall initiate the requeted measurement according to the parameters given in the request.]

Common measurement type on Iur-g

If the *Common Measurement Type* IE is set to "load", the RNC₂/BSS₂ shall initiate measurements and report results as described in section 8.5.2.2.

If the *Common Measurement Type* IE is set to "RT load", the RNC₂/BSS₂ shall initiate measurements and report results as described in section 8.5.2.2.

If the *Common Measurement Type* IE is set to "NRT load Information", the RNC₂/BSS₂ shall initiate measurements and report results as described in section 8.5.2.2.

Report characteristics on Iur-g

The *Report Characteristics* IE indicates how the reporting of the measurement shall be performed. This IE is used as described in section 8.5.2.2.

Response message for Iur-g

If the RNC₂/BSS₂ was able to initiate the measurement requested by RNC₁/BSS₁ it shall respond with the COMMON MEASUREMENT INITIATION RESPONSE message sent. The message shall include the same Measurement ID that was used in the measurement request. Only in the case when the *Report Characteristics* IE is set to "On Demand", the COMMON MEASUREMENT INITIATION RESPONSE message shall contain the measurement result.

[1.28Mcps TDD- If the BSS_2 was able to initiate the measurement requested by RNC_1 , it shall respond with one or more COMMON MEASUREMENT INITIATION RESPONSE messages sent. The message(s) should include the same Measurement ID that was used in the mesasurement request.

8.5.2.3 Unsuccessful Operation




Figure 30B: Common Measurement Initiation procedure, Unsuccessful Operation

If the requested measurement cannot be initiated, the RNC₂ shall send a COMMON MEASUREMENT INITIATION FAILURE message. The message shall include the same *Measurement ID* IE that was used in the COMMON MEASUREMENT INITIATION REQUEST message and shall include the *Cause* IE set to an appropriate value.

Typical cause values are as follows:

Radio Network Layer Cause

- Measurement not supported for the object.
- Measurement Temporarily not Available

8.5.2.4 Abnormal Conditions

If the COMMON MEASUREMENT INITIATION REQUEST message contains the SFN-SFN Measurement Threshold Information IE (in the Measurement Threshold IE contained in the Report Characteristics IE) and it does not contain at least one IE, the RNC₂ shall reject the procedure using the COMMON MEASUREMENT INITIATION FAILURE message.

If the COMMON MEASUREMENT INITIATION REQUEST message contains the $T_{UTRAN-GPS}$ Measurement Threshold Information IE (in the Measurement Threshold IE contained in the Report Characteristics IE) and it does not contain at least one IE, the RNC₂ shall reject the procedure using the COMMON MEASUREMENT INITIATION FAILURE message.

If the COMMON MEASUREMENT INITIATION REQUEST message contains the $T_{UTRAN-GANSS}$ Measurement Threshold Information IE (in the Measurement Threshold IE contained in the Report Characteristics IE) and it does not contain at least one IE, the RNC₂ shall reject the procedure using the COMMON MEASUREMENT INITIATION FAILURE message.

If the Common Measurement Type IE is set to "UTRAN GPS Timing of Cell Frames for UE positioning", but the $T_{UTRAN-GPS}$ Measurement Accuracy Class IE in the Common Measurement Accuracy IE is not included in the COMMON MEASUREMENT INITIATION REQUEST message, the RNC₂ shall reject the Common Measurement Initiation procedure using the COMMON MEASUREMENT INITIATION FAILURE message.

If the Common Measurement Type IE is set to "UTRAN GANSS Timing of Cell Frames for UE positioning", but the $T_{UTRAN-GANSS}$ Measurement Accuracy Class IE in the Common Measurement Accuracy IE is not included in the COMMON MEASUREMENT INITIATION REQUEST message, the RNC₂ shall reject the Common Measurement Initiation procedure using the COMMON MEASUREMENT INITIATION FAILURE message.

If the Common Measurement Type received in the *Common Measurement Type* IE is not "load", "RT load" or "NRT load Information", and if the Common Measurement Type received in the *Common Measurement Type* IE is not defined in TS 25.215 [11] or TS 25.225 [14] to be measured on the Common Measurement Object Type indicated in the COMMON MEASUREMENT INITIATION REQUEST message the RNC₂ shall reject the Common Measurement Initiation procedure using the COMMON MEASUREMENT INITIATION FAILURE message.

If the *Common Measurement Type* IE is set to "SFN-SFN Observed Time Difference", but the *Neighbouring Cell Measurement Information* IE is not received in the COMMON MEASUREMENT INITIATION REQUEST message, the RNC₂ shall reject the Common Measurement Initiation procedure using the COMMON MEASUREMENT INITIATION FAILURE message.

The allowed combinations of the Common Measurement Type and Report Characteristics Type are shown in the table below marked with "X". For not allowed combinations, the RNC₂ shall reject the Common Measurement Initiation procedure using the COMMON MEASUREMENT INITIATION FAILURE message.

Table 5: Allowed Common Measurement Type and Report Characteristics Type Combinations

Common measurement type	Report characteristics type									
поисилент туро	On Demand	Periodic	Event A	Event B	Event C	Event D	Event E	Event F	Event-H	On Modification
Received total wide band power	Х	X	X	X	Х	X	Х	Х		
Transmitted Carrier Power	Χ	X	Х	X	Х	Х	Х	Х		
UL Timeslot ISCP	Х	X	Х	Х	Х	Х	Х	Х		
Load	X	X	X	Х	X	Χ	Χ	Χ	X	
UTRAN GPS Timing of Cell Frames for UE Positioning	Х	Х								X
SFN-SFN Observed Time Difference	Х	Х								Х
RT load	X	X	X	Х	X	Χ	Χ	Χ		
NRT load Information	Χ	Х	Х	Х	Х	X	X	Х		
UpPTS interference	X	Х	Х	Х	Х	Х	Х	Х		
UTRAN GANSS Timing of Cell Frames for UE Positioning	Х	Х								X

[TDD – If the Common Measurement Type requires the Time Slot Information but the [3.84Mcps TDD and 7.68 Mcps TDD – *Time Slot* IE] [1.28Mcps TDD – *Time Slot LCR* IE] is not provided in the COMMON MEASUREMENT INITIATION REQUEST message the RNS₂ shall reject the Common Measurement Initiation procedure using the COMMON MEASUREMENT INITIATION FAILURE message.]

If the *SFN* IE is included in the COMMON MEASUREMENT INITIATION REQUEST message and the *Report Characteristics* IE is other than "Periodic", "On Demand" or "On Modification", the RNS₂ shall reject the Common Measurement Initiation procedure using the COMMON MEASUREMENT INITIATION FAILURE message.

8.5.2.4.1 Abnormal Conditions for lur-g

The measurements which can be requested on the Iur and Iur-g interfaces are shown in the table below marked with "X".

Table 6: Allowed Common measurement type on lur and lur-g interfaces

Common Measurement Type	Int	erface
	lur	lur-g
Received total wide band power	X	
Transmitted Carrier Power	X	
UL Timeslot ISCP	X	
Load	X	X
UTRAN GPS Timing of Cell	Х	
Frames for LCS		
SFN-SFN Observed Time	X	
Difference		
RT load	X	X
NRT load Information	X	X
UTRAN GANSS Timing of Cell	Х	
Frames for UE Positioning		

If the RNC₂ receives from the BSS₁ a COMMON MEASUREMENT INITIATION REQUEST message in which a measurement, which is not applicable on the Iur-g interface, is requested, the RNC₂ shall reject the Common Measurement Initiation procedure.

If the BSS_2 receives from the BSS_1 / RNC₁ a COMMON MEASUREMENT INITIATION REQUEST message in which a measurement, which is not applicable on the Iur-g interface, is requested, the BSS_2 shall reject the Common Measurement Initiation procedure.

If the RNC₂ receives from the BSS₁ a COMMON MEASUREMENT INITIATION REQUEST message in which the *SFN reporting indicator* IE is set to "FN Reporting Required", the RNC₂ shall ignore that IE.

If the BSS₂ receives from the BSS₁ / RNC₁ a COMMON MEASUREMENT INITIATION REQUEST message in which the *SFN reporting indicator* IE is set to "FN Reporting Required", the BSS₂ shall ignore that IE.

The allowed combinations of the Common measurement type and Report characteristics type are shown in the table in section 8.5.2.4 marked with "X". For not allowed combinations, the RNC₂/BSS₂ shall reject the Common Measurement Initiation procedure.

8.5.3 Common Measurement Reporting

8.5.3.1 General

This procedure is used by an RNC to report the result of measurements requested by another RNC using the Common Measurement Initiation.

This procedure uses the signalling bearer connection for the relevant Distant RNC Context.

8.5.3.2 Successful Operation



Figure 30C: Common Measurement Reporting procedure, Successful Operation

If the requested measurement reporting criteria are met, the RNC₂ shall initiate the Common Measurement Reporting procedure. Unless specified below, the meaning of the parameters are given in other specifications.

The *Measurement ID* IE shall be set to the Measurement ID provided by RNC_1 when initiating the measurement with the Common Measurement Initiation procedure.

If the achieved measurement accuracy does not fulfil the given accuracy requirement (see TS 25.133 [23] and TS 25.123 [24]) or the measurement is temporarily not available in case Measurement Recovery Behavior is supported, the *Common Measurement Value Information* IE shall indicate Measurement not Available. If the RNC₂ was configured to perform the Measurement Recovery Behavior, the RNC₂ shall indicate Measurement Available to the RNC₁ when the achieved measurement accuracy again fulfils the given accuracy requirement (see TS 25.133 [23] and TS 25.123 [24]) and include the *Measurement Recovery Report Indicator* IE in the COMMON MEASUREMENT REPORT message if the requested measurement reporting criteria are not met.

For measurements included in the *Successful Neighbouring Cell SFN-SFN Observed Time Difference Measurement Information* IE, the RNC₂ shall include the *SFN-SFN Quality* IE and the *SFN-SFN Drift Rate Quality* IE if available.

If the Common Measurement Type provided by RNC₁ when initiating the measurement with the Common Measurement Initiation procedure was "UTRAN GPS Timing of Cell Frames for UE Positioning", then the RNC₂ shall include in the $T_{UTRAN-GPS}$ Measurement Value Information IE the $T_{UTRAN-GPS}$ Quality IE and the $T_{UTRAN-GPS}$ Drift Rate Quality IE, if available.

If the Common Measurement Type provided by RNC₁ when initiating the measurement with the Common Measurement Initiation procedure was "UTRAN GANSS Timing of Cell Frames for UE Positioning", then the RNC₂ shall include in the $T_{UTRAN-GANSS}$ Measurement Value Information IE the $T_{UTRAN-GANSS}$ Quality IE and the $T_{UTRAN-GANSS}$ Drift Rate Quality IE, if available.

8.5.3.2.1 Successful Operation for lur-g

If the requested measurement reporting criteria are met, the RNC₂/BSS₂ shall initiate a Measurement Reporting procedure. Unless specified below, the meaning of the parameters are given in other specifications.

The Common Measurement ID IE shall be set to the Common Measurement ID provided by RNC_1/BSS_1 when initiating the measurement with the Common Measurement Initiation procedure.

If the Common measurement type provided by RNC₁ when initiating the measurement with the Common Measurement Initiation procedure was "SFN-SFN Observed Time Difference", then RNC₂ shall include in the COMMON MEASUREMENT REPORT all the available measurements in the *Successful Neighbouring cell SFN-SFN Observed Time Difference Measurement Information* IE and shall include the neighbouring cells with no measurement result available in the *Unsuccessful Neighbouring cell SFN-SFN Observed Time Difference Measurement Information* IE.

If the Common measurement type provided by RNC₁ when initiating the measurement with the Common Measurement Initiation procedure was not set to "SFN-SFN Observed Time Difference" and the SFN Reporting Indicator when initiating the measurement was set to "FN Reporting Required", the RNC₂ shall include the SFN IE in the COMMON MEASUREMENT REPORT message. The reported SFN shall be the SFN at the time when the measurement value was reported by the layer 3 filter, referred to as point C in the measurement model (TS 25.302 [26]). If the Common Measurement Type IE is set to "SFN-SFN Observed Time Difference", then the SFN Reporting Indicator IE is ignored.

8.5.3.3 Abnormal Conditions

_

8.5.4 Common Measurement Termination

8.5.4.1 General

This procedure is used by an RNC to terminate a measurement previously requested by the Common Measurement Initiation procedure.

This procedure uses the signalling bearer connection for the relevant Distant RNC Context.

8.5.4.2 Successful Operation



Figure 30D: Common Measurement Termination procedure, Successful Operation

This procedure is initiated with a COMMON MEASUREMENT TERMINATION REQUEST message.

Upon receipt, RNC₂ shall terminate reporting of common measurements corresponding to the received *Measurement ID* IF.

8.5.4.2.1 Successful Operation for Iur-g

The RNC_1/BSS_1 and RNC_2/BSS_2 shall use the Common Measurement Termination procedure as specified in section 8.5.4.2.

8.5.4.3 Abnormal Conditions

_

8.5.5 Common Measurement Failure

8.5.5.1 General

This procedure is used by an RNC to notify another RNC that a measurement previously requested by the Common Measurement Initiation procedure can no longer be reported.

This procedure uses the signalling bearer connection for the relevant Distant RNC Context.

8.5.5.2 Successful Operation



Figure 30E: Common Measurement Failure procedure, Successful Operation

This procedure is initiated with a COMMON MEASUREMENT FAILURE INDICATION message, sent from RNC₂ to RNC₁ to inform the RNC₁ that a previously requested measurement can no longer be reported. RNC₂ has locally terminated the indicated measurement. The RNC₂ shall include in the COMMON MEASUREMENT FAILURE INDICATION message the reason for the failure in the *Cause* IE.

8.5.5.2.1 Successful Operation for lur-g

The RNC₁/BSS₁ and RNC₂/BSS₂ shall use the Common Measurement Failure procedure as specified in section 8.5.5.2.

8.5.5.3 Abnormal Conditions

-

8.5.6 Information Exchange Initiation

8.5.6.1 General

This procedure is used by an RNC to request the initiation of an information exchange with another RNC.

This procedure uses the signalling bearer connection for the relevant Distant RNC Context.

8.5.6.2 Successful Operation




Figure 30F: Information Exchange Initiation procedure, Successful Operation

The procedure is initiated with an INFORMATION EXCHANGE INITIATION REQUEST message sent from RNC₁ to RNC₂.

Upon receipt, the RNC₂ shall provide the requested information according to the parameters given in the request. Unless specified below, the meaning of the parameters are given in other specifications.

If the *Information Exchange Object Type* is set to "MBMS Bearer Service" and the *Information Type Item* IE is set to "MBMS Bearer Service Full Address", the RNC₂ shall report for each TMGI included in the received *MBMS Bearer Service Identifiers List* IE, the Access Point Name and the IP Multicast Address corresponding to this TMGI in the *MBMS Bearer Service Identifiers List* IE in the INFORMATION EXCHANGE INITIATION RESPONSE message.

[FDD – If the *Information Exchange Object Type* is set to "MBMS Bearer Service in MBMS Cell" and the *Information Type Item* IE is set to "MBMS Counting Information", the RNC₂ shall perform counting in cells as defined in TS 25.346 [50] and report in the *Counting Result* IE for each TMGI included in the received *MBMS Bearer Service Identifiers List* IE for each cell included in the received *MBMS Cell List* IE either the counting information or, if relevant counting information is not available in RNC₂ (TS 25.346 [50]), the value "0" in the INFORMATION EXCHANGE INITIATION RESPONSE message.]

[FDD – If the *Information Exchange Object Type* is set to "MBMS Bearer Service" in MBMS Cell" and the *Information Type Item* IE is set to "MBMS Transmission Mode", the RNC₂ shall report for each TMGI included in the received *MBMS Bearer Service Identifiers List* IE for each cell included in the received *MBMS Cell List* IE, the transmission mode for each TMGI in the cells of RNC₂ that have a neighbour relation to the cells received in *MBMS Cell List* IE as defined in TS 25.346 [50] in the INFORMATION EXCHANGE INITIATION RESPONSE message. If no cells of RNC₂ have a neighbour relation to a cell received in *MBMS Cell List* IE for a TMGI the value "Not Provided" shall be used]

[FDD – If the *Information Exchange Object Type* is set to "MBMS Cell" and the *Information Type Item* IE is set to "MBMS Neighbouring Cell Information", the RNC₂ shall report for each cell included in the received *MBMS Cell List* IE, the MBMS radio bearer information for each cells in the INFORMATION EXCHANGE INITIATION RESPONSE message.]

[FDD – If the *Information Exchange Object Type* is set to "MBMS Bearer Service" in MBMS Cell" and the *Information Type Item* IE is set to "MBMS RLC Sequence Number", the RNC₂ shall report for each TMGI included in the received *MBMS Bearer Service Identifiers List* IE for each cell included in the received *MBMS Cell List* IE, the RLC sequence number for each TMGI for the indicated cells in the INFORMATION EXCHANGE INITIATION RESPONSE message.]

If the *Information Exchange Object Type* is set to "ANR Cell" and the *Information Type Item* IE is set to "ANR Cell Information", the RNC₂ shall, if supported, for each cell in the *ANR Cell List* IE that is controlled by RNC₂, report the ANR Cell Information in the INFORMATION EXCHANGE INITIATION RESPONSE message.

If the Information Type IE contains a GANSS Generic Data IE, at least one of the GANSS Navigation Model And Time Recovery, GANSS Time Model GNSS-GNSS, GANSS UTC Model, GANSS Almanac, GANSS Real Time Integrity, GANSS Data Bit Assistance, GANSS Additional Navigation Models And Time Recovery, GANSS Additional UTC Models, GANSS Auxiliary Information IEs shall be present in the GANSS Generic Data IE.

- If the GANSS Generic Data IE does not contain the GANSS ID IE, the RNC₂ shall assume that the corresponding GANSS is "Galileo".

Information Report Characteristics:

The Information Report Characteristics IE indicates how the reporting of the information shall be performed.

If the *Information Report Characteristics* IE is set to "On Demand", the RNC₂ shall report the requested information immediately.

If the *Information Report Characteristics* IE is set to "Periodic", the RNC₂ shall report the requested information immediately and then shall periodically initiate the Information Reporting procedure for all the requested information, with the report frequency indicated by the *Information Report Periodicity* IE.

If the *Information Report Characteristics* IE is set to "On Modification", the RNC₂ shall report the requested information immediately if available. If the requested information is not available at the moment of receiving the INFORMATION EXCHANGE INITIATION REQUEST message, but expected to become available after some acquisition time, the RNC₂ shall initiate the Information Reporting procedure when the requested information becomes available. The RNC₂ shall then initiate the Information Reporting procedure in accordance to the following conditions:

- If the *Information Type Item* IE is set to "IPDL Parameters", the RNC₂ shall initiate the Information Reporting procedure when any change in the parameters occurs.
- If the *Information Type Item* IE is set to "DGPS Corrections", the RNC₂ shall initiate the Information Reporting procedure for this specific Information Type when either the PRC has drifted from the previously reported value more than the threshold indicated in the *PRC Deviation* IE in the *Information Threshold* IE or a change has occurred in the IODE.
- If the *Information Type Item* IE is set to "GPS Information" and the *GPS Information Item* IE includes "GPS Navigation Model & Recovery Assistance", the RNC₂ shall initiate the Information Reporting procedure for this specific GPS Information Item when a change has occurred regarding either the IODC or the list of visible satellites, identified by the *Sat ID* IEs.
- If the *Information Type Item* IE is set to "GPS Information" and the *GPS Information Item* IE includes "GPS Ionospheric Model", the RNC₂ shall initiate the Information Reporting procedure for this specific GPS Information Item when any change has occurred.
- If the *Information Type Item* IE is set to "GPS Information" and the *GPS Information Item* IE includes "GPS UTC Model", the RNC₂ shall initiate the Information Reporting procedure for this specific GPS Information Item when a change has occurred in the t_{ot} or WN_t parameter.
- If the *Information Type Item* IE is set to "GPS Information" and the *GPS Information Item* IE includes "GPS Almanac", the RNC₂ shall initiate the Information Reporting procedure for this specific GPS Information Item when a change in the t_{oa} or WN_a parameter has occurred.
- If the *Information Type Item* IE is set to "GPS Information" and the *GPS Information Item* IE includes "GPS Real-Time Integrity", the RNC₂ shall initiate the Information Reporting procedure for this specific GPS Information Item when any change has occurred.
- If the *Information Type* IE is set to "Cell Capacity Class", the RNC₂ shall initiate the Information Reporting procedure for uplink and downlink cell capacity class when any change has occurred. If either uplink or downlink cell capacity class satisfies the requested report characteristics, the RNC₂ shall report the result of both uplink and downlink cell capacity information.
- If any of the above *Information Type* IEs becomes temporarily unavailable, the RNC₂ shall initiate the Information Reporting procedure for this specific Information Item by indicating "Information Not Available" in the *Requested Data Value Information* IE. If the Information becomes available again, the RNC₂ shall initiate the Information Reporting procedure for this specific Information.
- If the *Information Type* IE is set to "NACC related data", the RNC₂ shall initiate the Information Reporting procedure for NACC related data if any change has occurred.
- If the *Information Type* IE is set to "Inter-frequency Cell Information", the RNC₂ shall initiate the Information Reporting procedure for this specific Information Item when any change has occurred to the inter-frequency cell information broadcasted in the SIB11 or SIB12.
- If the *Information Type Item* IE is set to "DGANSS Corrections", the RNC₂ shall initiate the Information Reporting procedure for this specific Information Type when either the PRC has drifted from the previously reported value more than the threshold indicated in the *PRC Deviation* IE in the *Information Threshold* IE or a change has occurred in the IODE.
- If the *Information Type Item* IE is set to "GANSS Information" and the *GANSS Information* IE includes the *GANSS Navigation Model And Time Recovery* IE, the RNC₂ shall initiate the Information Reporting procedure for this specific GANSS Information Item when a change has occurred regarding either the IOD or the list of visible satellites, identified by the *Sat ID* IEs.
- If the *Information Type Item* IE is set to "GANSS Information" and the *GANSS Information* IE includes the *GANSS Ionospheric Model* IE, the RNC₂ shall initiate the Information Reporting procedure for this specific GANSS Information Item when any change has occurred.
- If the *Information Type Item* IE is set to "GANSS Information" and the *GANSS Information* IE includes the *GANSS UTC Model* IE, the RNC₂ shall initiate the Information Reporting procedure for this specific GANSS Information Item when a change has occurred in the t_{ot} or WN_t parameter.

- If the *Information Type Item* IE is set to "GANSS Information" and the *GANSS Information* IE includes the *GANSS Almanac* IE, the RNC₂ shall initiate the Information Reporting procedure for this specific GANSS Information Item when a change in the T_{oa}, IOD_a, or Week Number parameter has occurred.
- If the *Information Type Item* IE is set to "GANSS Information" and the *GANSS Information* IE includes the *GANSS Real Time Integrity* IE, the RNC₂ shall initiate the Information Reporting procedure for this specific GANSS Information Item when any change has occurred.
- If the *Information Type Item* IE is set to "GANSS Information" and the *GANSS Information* IE includes the *GANSS Data Bit Assistance* IE, the RNC₂ shall initiate the Information Reporting procedure for this specific GANSS Information Item when any change has occurred.
- If the *Information Type Item* IE is set to "MBMS Transmission Mode", the RNC₂ shall initiate the Information Reporting procedure when any change in the parameter occurs.
- If the *Information Type Item* IE is set to "MBMS Neighbouring Cell Information", the RNC₂ shall initiate the Information Reporting procedure when any change in the parameters occurs.
- If the *Information Type Item* IE is set to "GANSS Information" and the *GANSS Information* IE includes the *GANSS Additional Navigation Models And Time Recovery* IE, the RNC₂ shall initiate the Information Reporting procedure for this specific GANSS Information item when a change has occurred regarding either the IOD or the list of visible satellites, identified by the *Sat ID* IEs.
- If the *Information Type Item* IE is set to "GANSS Information" and the *GANSS Information* IE includes the *GANSS Additional Ionospheric Model* IE, the RNC₂ shall initiate the Information Reporting procedure for this specific GANSS Information item when any change has occurred.
- If the *Information Type Item* IE is set to "GANSS Information" and the *GANSS Information* IE includes the *GANSS Additional UTC Models* IE, the RNC₂ shall initiate the Information Reporting procedure for this specific GANSS Information item when a change has occurred in the t_{ot}, WN_{ot}, WN_t, or N^A parameter.
- If the *Information Type Item* IE is set to "GANSS Information" and the *GANSS Information* IE includes the *GANSS Earth Orientation Parameters* IE, the RNC₂ shall initiate the Information Reporting procedure for this specific GANSS Information item when a change has occurred in the t_{EOP} parameter.
- If the *Information Type Item* IE is set to "GANSS Information" and the *GANSS Information* IE includes the *GANSS Auxiliary Information* IE, the RNC₂ shall initiate the Information Reporting procedure for this specific GANSS Information item when a change has occurred in the *Signals Available* or *Channel Number* IE parameter.

Response message:

If the RNC₂ is able to determine the information requested by the RNC₁, it shall respond with the INFORMATION EXCHANGE INITIATION RESPONSE message. The message shall include the *Information Exchange ID* IE set to the same value that was included in the INFORMATION EXCHANGE INITIATION REQUEST message. When the *Report Characteristics* IE is set to or "On Modification" or "Periodic", the INFORMATION EXCHANGE INITIATION RESPONSE message shall contain the *Requested Data Value* IE if the data are available. When the *Report Characteristics* IE is set to "On Demand", the INFORMATION EXCHANGE INITIATION RESPONSE message shall contain the *Requested Data Value* IE.

If the Requested DataValue IE contains the GANSS Common Data IE, at least one of the GANSS Ionospheric Model, GANSS RX Pos, GANSS Additional Ionospheric Model, or GANSS Earth Orientation Parameters IEs shall be present.

Any GANSS Generic Data IE associated with a given GANSS included in the Requested DataValue IE shall contain at least one of the DGANSS Corrections, GANSS Navigation Model And Time Recovery, GANSS Time Model, GANSS UTC Model, GANSS Almanac, GANSS Real Time Integrity, GANSS Data Bit Assistance, GANSS Additional Time Models, GANSS Additional Navigation Models And Time Recovery, GANSS Additional UTC Models, or GANSS Auxiliary Information IEs.

- If the GANSS Generic Data IE does not contain the GANSS ID IE, the corresponding GANSS is "Galileo".
- The *DGANSS Corrections* IE contains one or several *DGANSS Information* IE(s), each of them associated with a GANSS Signal. A *DGANSS Information* IE for a particular GANSS that does not contain the *GANSS Signal ID* IE is by default associated with the default signal defined in TS 25.331 [16], clause 10.3.3.45a.

- The *GANSS Real Time Integrity* IE contains one or several *Satellite Information* IEs, each of them associated with a satellite and a GANSS Signal. A *Satellite Information* IE for a particular GANSS that does not contain the *Bad GANSS Signal ID* IE is by default associated with all the signals of the corresponding satellite (see [53], IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], DTFA01-96-C-00025 [58], IS-QZSS [59], [60]).

If the *Information Type Item* IE is set to "GANSS Information" and the *GANSS Information* IE includes the *GANSS Time Model GNSS-GNSS* IE with exactly one bit set to value "1", the RNC₂ shall include the *GANSS Time Model* IE in the *Requested Data Value* IE with the requested time information.

If the *Information Type Item* IE is set to "GANSS Information" and the *GANSS Information* IE includes the *GANSS Time Model GNSS-GNSS* IE with more than one bit set to value "1", the RNC₂ shall include the *GANSS Additional Time Models* IE in *Requested Data Value* IE with the requested time information for each GANSS.

If the *Information Type Item* IE is set to "DGPS Corrections", the RNC₂ shall include the *DGPS Corrections* IE in *Requested Data Value* IE with the *DGNSS Validity Period* IE included, if available.

If the *Information Type Item* IE is set to "DGANSS Corrections", the RNC₂ shall include the *DGANSS Corrections* IE in *Requested Data Value* IE with the *DGNSS Validity Period* IE included, if available.

If the *Information Type Item* IE is set to "GPS Almanac", the RNC₂ shall include the *GPS Almanac* IE in *Requested Data Value* IE with the *Complete Almanac Provided* IE included, if available.

If the *Information Type Item* IE is set to "GANSS Almanac", the RNC₂ shall include the *GANSS Almanac* IE in *Requested Data Value* IE with the *Complete Almanac Provided* IE included, if available.

If the *Information Type Item* IE is set to "GANSS Time Model GNSS-GNSS", the RNC₂ shall include the *GANSS Time Model* IE in *Requested Data Value* IE with the *Delta T* IE included, if available.

8.5.6.2.1 Successful Operation for lur-g

The procedure is initiated with an INFORMATION EXCHANGE INITIATION REQUEST message sent from BSS₁ to BSS₂/RNC₂ or by RNC₁ to BSS₂.

Upon receipt, the BSS₂/RNC₂ shall provide the requested information according to the parameters given in the request. Unless specified below, the meaning of the parameters are given in other specifications.

Information Report Characteristics on Iur-g:

If the *Information Type Item* IE is set to "Cell Capacity Class", the RNC₂/BSS₂ shall initiate measurements and report results as described in section 8.5.6.2.

The *Information Report Characteristics* IE indicates how the reporting of the information shall be performed. This IE is used as described in section 8.5.6.2.

8.5.6.3 Unsuccessful Operation




Figure 30G: Information Exchange Initiation procedure, Unsuccessful Operation

If the requested Information Type received in the *Information Type* IE indicates a type of information that RNC₂ cannot provide, the RNC₂ shall reject the Information Exchange Initiation procedure.

If the requested information provision cannot be accessed, the RNC₂ shall reject the procedure and shall send the INFORMATION EXCHANGE INITIATION FAILURE message.

The message shall include the *Information Exchange ID* IE set to the same value that was used in the INFORMATION EXCHANGE INITIATION REQUEST message and the *Cause* IE set to an appropriate value.

Typical cause values are as follows:

Radio Network Layer Cause:

- Information temporarily not available.
- Information Provision not supported for the object.

8.5.6.4 Abnormal Conditions

If the *Information Report Characteristics* IE is set to "On Modification", and the *Information Type Item* IE is set to "DGPS Corrections", but the *Information Threshold* IE is not received in the INFORMATION EXCHANGE INITIATION REQUEST message, the RNC₂ shall reject the Information Exchange Initiation procedure and shall send the INFORMATION EXCHANGE INITIATION FAILURE message.

If the *Information Exchange Object Type* IE is set to a value other than "GSM Cell" and the *Information Type Item* IE set to "NACC related data" the RNC₂ shall reject the Information Exchange Initiation procedure and shall send the INFORMATION EXCHANGE INITIATION FAILURE message.

If the *Information Type Item* IE is set to the value "MBMS Bearer Service Full Address" and the *Information Exchange Object Type* IE is not set to "MBMS Bearer Service", the RNC₂ shall reject the Information Exchange Initiation procedure and shall send the INFORMATION EXCHANGE INITIATION FAILURE message.

If the *Information Type Item* IE is set to the value "ANR Cell Information" and the *Information Exchange Object Type* IE is not set to "ANR Cell", the RNC₂ shall reject the Information Exchange Initiation procedure and shall send the INFORMATION EXCHANGE INITIATION FAILURE message.

If the *Information Type Item* IE is set to the value "ANR Cell Information" and the *Information Exchange Object Type* IE is set to "ANR Cell", but the RNC₂ can only collect the "Requested Data Value" for the subset of the cells requested, RNC₂ shall not reject the Information Exchange Initiation procedure and shall send the INFORMATION EXCHANGE INITIATION RESPONSE message with the information it could obtain.

The allowed combinations of the Information type and Information Report Characteristics type are shown in the table below marked with "X". For not allowed combinations, the RNC₂ shall reject the Information Exchange Initiation procedure using the INFORMATION EXCHANGE INITIATION FAILURE message.

Table 6a: Allowed Information Type and Information Report Characteristics type combinations

Туре	Information Report Characteristics Type			
	On Demand	Periodic	On Modification	
UTRAN Access Point Position with	Χ			
Altitude Information				
UTRAN Access Point Position	Χ			
IPDL Parameters	Χ	Χ	X	
GPS Information	Χ	Χ	X	
DGPS Corrections	X	Χ	X	
GPS RX Pos	X			
SFN-SFN Measurement Reference Point	Х			
Position				
Cell Capacity Class	Χ		X	
NACC related data	Χ		X	
MBMS Bearer Service Full Address	Χ			
Inter-frequency Cell Information	Χ		X	
GANSS Information	Χ	X	X	
DGANSS Corrections	Χ	X	X	
GANSS RX Pos	Χ			
MBMS Counting Information [FDD only]	Χ			
MBMS Transmission Mode [FDD only]			X	
MBMS Neighbouring Cell Information	Χ		X	
[FDD only]				
MBMS RLC Sequence Number	X			
[FDD only]				
ANR Cell Information	Χ			

8.5.6.4.1 Abnormal Conditions for lur-g

The information types that can be requested on the Iur and Iur-g interfaces are shown in the table below marked with "X". For information types that are not applicable on the Iur-g interface, the BSS shall reject the Information Exchange Initiation procedure.

Table 7: Allowed Information types on lur and lur-g interfaces

Information Type	Inte	rface
	lur	lur-g
UTRAN Access Point Position with Altitude Information	Χ	
UTRAN Access Point Position	Χ	
IPDL Parameters	Χ	
DGPS Corrections	Χ	
GPS Information	Χ	
GPS RX Pos	Χ	
SFN-SFN Measurement Reference Point Position	Х	
Cell Capacity Class	Х	X
NACC related data	Х	
MBMS Bearer Service Full Address	Χ	
Inter-frequency Cell Information	Χ	
DGANSS Corrections	Χ	
GANSS Information	Х	
GANSS RX Pos	Х	
MBMS Counting Information [FDD only]	Х	
MBMS Transmission Mode [FDD only]	Χ	
MBMS Neighbouring Cell Information [FDD only]	Χ	
MBMS RLC Sequence Number [FDD only]	Χ	

8.5.7 Information Reporting

8.5.7.1 General

This procedure is used by a RNC to report the result of information requested by another RNC using the Information Exchange Initiation.

264

This procedure uses the signalling bearer connection for the relevant Distant RNC Context.

8.5.7.2 Successful Operation



Figure 30H: Information Reporting procedure, Successful Operation

If the requested information reporting criteria are met, the RNC₂ shall initiate an Information Reporting procedure. Unless specified below, the meaning of the parameters are given in other specifications.

The *Information Exchange ID* IE shall be set to the Information Exchange ID provided by the RNC₁ when initiating the information exchange with the Information Exchange Initiation procedure.

The Requested Data Value IE shall include at least one IE containing the data to be reported.

8.5.7.2.1 Successful Operation for lur-g

The RNC₁/BSS₁ and RNC₂/BSS₂ shall use the Information Reporting procedure as specified in section 8.5.7.2.

8.5.7.3 Abnormal Conditions

-

8.5.8 Information Exchange Termination

8.5.8.1 General

This procedure is used by a RNC to terminate the information exchange requested using the Information Exchange Initiation.

This procedure uses the signalling bearer connection for the relevant Distant RNC Context.

8.5.8.2 Successful Operation



Figure 30I: Information Exchange Termination procedure, Successful Operation

This procedure is initiated with a INFORMATION EXCHANGE TERMINATION REQUEST message.

Upon receipt, the RNC₂ shall terminate the information exchange corresponding to the *Information Exchange ID* IE provided by the RNC₁ when initiating the information exchange with the Information Exchange Initiation procedure.

8.5.8.2.1 Successful Operation for lur-g

The RNC_1/BSS_1 and RNC_2/BSS_2 shall use the Information Exchange Termination procedure as specified in section 8.5.8.2.

8.5.8.3 Abnormal Conditions

-

8.5.9 Information Exchange Failure

8.5.9.1 General

This procedure is used by a RNC to notify another that the information exchange it previously requested using the Information Exchange Initiation can no longer be reported.

This procedure uses the signalling bearer connection for the relevant Distant RNC Context.

8.5.9.2 Successful Operation



Figure 30J: Information Exchange Failure procedure, Successful Operation

This procedure is initiated with a INFORMATION EXCHANGE FAILURE INDICATION message, sent from the RNC₂ to the RNC₁, to inform the RNC₁ that information previously requested by the Information Exchange Initiation procedure can no longer be reported. The RNC₂ shall include in the INFORMATION EXCHANGE FAILURE INDICATION message the *Information Exchange ID* IE set to the same value provided by the RNC₁ when initiating the information exchange with the Information Exchange Initiation procedure, and the RNC₂ shall include the *Cause* IE set to an appropriate value.

Typical cause values are as follows:

Radio Network Layer Cause:

Information temporarily not available.

8.5.9.2.1 Successful Operation for lur-g

The RNC₁/BSS₁ and RNC₂/BSS₂ shall use the Information Exchange Failure procedure as specified in section 8.5.9.2.

8.5.10 Reset

8.5.10.1 General

The purpose of the reset procedure is to align the resources in RNC₁ and RNC₂ in the event of an abnormal failure.

The procedure uses connectionless signalling.

8.5.10.2 Successful Operation




Figure 30K: Reset procedure, Successful Operation

The procedure is initiated with a RESET REQUEST message sent from the RNC₁ to the RNC₂.

If the *Reset Indicator* IE is set to "Context", then:

- For all indicated UE Contexts identified by the *S-RNTI* IE, the RNC₂ in the role of DRNC, shall remove all the indicated UE Contexts and all the radio resources allocated for these UE Contexts. In addition, the RNC₂ shall take actions according to Annex D.2.
- For all indicated UE Contexts identified by the *D-RNTI* IE, the RNC₂ in the role of SRNC, shall remove the information related to the RNC₁ for all indicated UE Contexts and the radio resources allocated for these UE Contexts.

If the *Reset Indicator* IE is set to "Context Group", then:

- For all indicated UE Context Groups identified by the *S-RNTI Group* IE, the RNC₂ in the role of DRNC, shall remove all the indicated UE Contexts and all the radio resources allocated for these UE Contexts. In addition, the RNC₂ shall take actions according to Annex D.2.

If the *Reset Indicator* IE is set to "All Contexts", then the RNC₂ shall:

- In the role of DRNC, remove all the UE Contexts for which the RNC₁ is the SRNC and all the radio resources allocated for these UE Contexts. In addition, the RNC₂ shall take actions according to Annex D.2.
- In the role of SRNC, remove the information related to the RNC₁ for all the UE Contexts and all the radio resources allocated for these UE Contexts.

For all the removed UE Contexts and for all the UE Contexts for which the RNC_2 has removed information related to the RNC_1 , the RNC_2 shall also initiate release of the dedicated or common user plane resources that were involved in these UE Contexts. After clearing all related resources, the RNC_2 shall return the RESET RESPONSE message to the RNC_1 .

8.5.10.3 Abnormal Conditions

If the RESET message is received, any other ongoing procedure (except another Reset procedure) on same Iur interface related to a context indicated explicitly or implicitly in the message shall be aborted.

8.5.11 Direct Information Transfer

8.5.11.1 General

This procedure is used by an RNC to transfer information to another RNC spontaneously.

This procedure shall use the connectionless mode of signalling bearer.

8.5.11.2 Successful Operation



Figure 30L: Direct Information Transfer procedure, Successful Operation

The procedure is initiated with an DIRECT INFORMATION TRANSFER message sent from RNC₁ to RNC₂.

If the initiating RNC of this procedure is RNC₁, RNC₁ shall provide appropriate information in the *Provided Information* IE.

MBMS Channel Type Indication:

At the start time of a session for an MBMS bearer service, if the RNC₁ is in the DRNC role for some Ues whose UE Link contains the concerned MBMS bearer service and whose SRNC is RNC₂ and if the channel type is determined by the RNC₁ for certain cells in the DRNS, the procedure shall be initiated by the RNC₁ to the RNC₂. In this case, the RNC₁ shall include in the *Provided Information* IE the *Channel Type Information* IE in the DIRECT INFORMATION TRANSFER message.

During a session of an MBMS bearer service, if the RNC₁ is in the DRNC role for some Ues whose UE Link contains the concerned MBMS bearer service and whose SRNC is RNC₂, then the RNC₁ may initiate this procedure to indicate channel type change for the MBMS bearer service in certain cells. In this case, the RNC₁ shall include in the *Provided Information* IE the *Channel Type Information* IE in the DIRECT INFORMATION TRANSFER message.

The RNC₁ shall include the available information within the *PTM Cell List* IE, the *PTP Cell List* IE and/or the *Not Provided Cell List* IE in the *Channel Type Information* IE.

MBMS Preferred Frequency Layer Indication:

At the start time of a session for an MBMS bearer service, if the RNC₁ is in the DRNC role for at least one CELL_DCH UE whose UE Link contains the concerned MBMS bearer service and whose SRNC is RNC₂ and if the preferred frequency layer is determined by the RNC₁ for certain cells that host at least one of these CELL_DCH Ues whose SRNC is RNC₂, the procedure shall be initiated by the RNC₁ to the RNC₂. In this case, the RNC₁ shall include in the *Provided Information* IE the *Preferred Frequency Layer Information* IE in the DIRECT INFORMATION TRANSFER message.

If some of the cells controlled by RNC₁ that host at least one of these CELL_DCH Ues whose SRNC is RNC₂ are configured with different preferred frequencies, the *Additional Preferred Frequency* IE as well as *Default Preferred Frequency* IE shall be included in the *Preferred Frequency Layer Information* IE. In this case, for each preferred frequency different from the *Default Preferred Frequency* IE, one *Additional Preferred Frequency* IE shall be included containing at least one *Corresponding Cells* IE.

ANR Report Indication:

The message contains ANR Report Indication IE if the initiating RNC (RNC₁) has decided to forward a logged ANR report received over Uu to RNC₂. On reception of the ANR Report Indication IE, RNC2 may use the information to configure neighbour relations.

8.5.12 Information Transfer Control

8.5.12.1 General

This procedure is used by an RNC to control transfer of information (e.g. log information related to ANR) from an RNC to any other RNC. This procedure is initiated by an RNC to suspend or resume transfer of information.

This procedure shall use the connectionless mode of signalling bearer.

8.5.12.2 Successful Operation



Figure 30M: Information Transfer Control procedure, Successful Operation

The RNC₁ initiates the procedure by sending the INFORMATION TRANSFER CONTROL REQUEST message to the RNC₂.

The *Control Type* IE within the INFORMATION TRANSFER CONTROL REQUEST message shall be used to either suspend or to resume (respectively indicated by *Suspension* IE or *Resume* IE in *Control Type* IE) the transfer of information for the specified scope of objects indicated by *Controlled Object Scope* IE.

If the control of information transfer is intended for individual cells, those cells shall be indicated in the *UMTS Cell Information* IE within the *Controlled Object Scope* IE. If the *UMTS Cell Information* IE is not included, the procedure is intended for the whole entity indicated in *RNC-ID* IE or *Extended RNC-ID* IE. In shared network configurations, PLMN identities shall be indicated with *Multiple PLMN List* IE.

8.5.12.3 Abnormal Conditions

_

8.6 MBMS Procedures

8.6.1 MBMS Attach

8.6.1.1 General

The MBMS Attach procedure is used by the SRNC to either create a UE Link/URA Link in the DRNC or inform the DRNC about any addition of one or several MBMS bearer services in an already stored UE Link or URA Link.

This procedure shall use the signalling bearer mode specified below.

8.6.1.2 Successful Operation



Figure 31: MBMS Attach procedure, Successful Operation

The SRNC initiates the procedure by sending the message MBMS ATTACH COMMAND message to the DRNC.

When the UE is utilising one or more radio links in the DRNC, the message shall be sent using the connection oriented service of the signalling bearer and no further identification of the UE Context in the DRNC is required. If the UE is not utilising any radio link, the message shall be sent using the connectionless service of the signalling bearer.

If no *UE State* IE is included in the message or the *UE State* IE is set to "CELL_FACH/CELL_PCH", the DRNC shall perform the UE Linking as specified in TS 25.346 [50], section 5.1.6.

If the *UE State* IE is set to "URA_PCH", the DRNC shall perform the URA Linking as specified in TS 25.346 [50], section 5.1.10.

8.6.1.3 Abnormal Conditions

_

8.6.2 MBMS Detach

8.6.2.1 General

The MBMS Detach procedure is used by the SRNC to either delete a UE Link/URA Link in the DRNC or to inform DRNC about any removal of one or several MBMS bearer services in an already stored UE link or URA Link.

This procedure shall use the signalling bearer mode specified below.

8.6.2.2 Successful Operation



Figure 32: MBMS Detach procedure, Successful Operation

The SRNC initiates the procedure by sending the message MBMS DETACH COMMAND message to the DRNC.

When the UE is utilising one or more radio links in the DRNC, the message shall be sent using the connection oriented service of the signalling bearer and no further identification of the UE Context in the DRNC is required. If the UE is not utilising any radio link, the message shall be sent using the connectionless service of the signalling bearer.

If no *UE State* IE is included in the message or the *UE State* IE is set to "CELL_FACH/CELL_PCH", the DRNC shall perform the UE De-linking as specified in TS 25.346 [50], section 5.1.6.

If the *UE State* IE is set to "URA_PCH", the DRNC shall perform the URA De-linking as specified in TS 25.346 [50], section 5.1.10.

8.6.2.3 Abnormal Conditions

_

9 Elements for RNSAP Communication

9.1 Message Functional Definition and Content

9.1.1 General

This subclause defines the structure of the messages required for the RNSAP protocol in tabular format. The corresponding ASN.1 definition is presented in subclause 9.3. In case there is contradiction between the tabular format in subclause 9.1 and the ASN.1 definition, the ASN.1 shall take precedence, except for the definition of conditions for the presence of conditional IEs, in which the tabular format shall take precedence.

NOTE: The messages have been defined in accordance to the guidelines specified in TR 25.921 [28].

9.1.2 Message Contents

9.1.2.1 Presence

An information element can be of the following types:

M	IEs marked as Mandatory (M) shall always be included in the message.
0	IEs marked as Optional (O) may or may not be included in the message.
С	IEs marked as Conditional I shall be included in a message only if the condition is satisfied. Otherwise the IE shall not be included.

In the case of an Information Element group, the group is preceded by a name for the info group (in bold). It is also indicated how many times a group may be repeated in the message and whether the group is conditional. Each group may be also repeated within one message. The presence field of the Information Elements inside one group defines if the Information Element is mandatory, optional or conditional if the group is present.

9.1.2.2 Criticality

Each information element or Group of information elements may have criticality information applied to it. Following cases are possible:

_	No criticality information is applied explicitly.
YES	Criticality information is applied. 'YES' is usable only for non-repeatable information elements.
GLOBAL	The information element and all its repetitions together have one common criticality information.
	'GLOBAL' is usable only for repeatable information elements.
EACH	Each repetition of the information element has its own criticality information. It is not allowed to assign
	different criticality values to the repetitions. 'EACH' is usable only for repeatable information elements.

9.1.2.3 Range

The Range column indicates the allowed number of copies of repetitive IEs/IE groups.

9.1.2.4 Assigned Criticality

This column provides the actual criticality information as defined in subclause 10.3.2, if applicable.

9.1.3 RADIO LINK SETUP REQUEST

9.1.3.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	•
SRNC-ID	M		RNC-ID 9.2.1.50	If the Extended SRNC-ID IE is included in the message, the SRNC-ID IE shall be ignored.	YES	reject
S-RNTI	M		9.2.1.53		YES	reject
D-RNTI	0		9.2.1.24		YES	reject
Allowed Queuing Time	0		9.2.1.2		YES	reject
UL DPCH Information		1			YES	reject
>UL Scrambling Code	M		9.2.2.53		_	
>Min UL Channelisation Code Length	М		9.2.2.25		-	
>Max Number of UL DPDCHs	C – CodeLen		9.2.2.24		-	
>Puncture Limit	M		9.2.1.46	For the UL.	_	
>TFCS	М		9.2.1.63		_	
>UL DPCCH Slot Format	M		9.2.2.52		_	
>Uplink SIR Target	0		Uplink SIR		_	
· · · · · · · · · · · · · · · · · · ·			9.2.1.69			
>Diversity mode	М		9.2.2.8		_	
>Not Used	0		NULL		-	
>Not Used	0		NULL		_	
>DPC Mode	0		9.2.2.12A		YES	reject
>UL DPDCH Indicator for E- DCH operation	0		9.2.2.52A	This IE may be present without the presence of the <i>E-DPCH</i> <i>Information</i> IE	YES	reject
DL DPCH Information		01			YES	reject
>TFCS	M				_	
			9.2.1.63			
>DL DPCH Slot Format	M		9.2.2.9		_	
>Number of DL	M		9.2.2.26A		_	
Channelisation Codes						
>TFCI Signalling Mode	M		9.2.2.46		_	
>TFCI Presence	C- SlotFormat		9.2.1.55		-	
>Multiplexing Position	M		9.2.2.26		_	
>Power Offset Information		1			_	
>>PO1	М		Power Offset 9.2.2.30	Power offset for the TFCI bits.	_	
>>PO2	M		Power Offset 9.2.2.30	Power offset for the TPC bits.	-	
>>PO3	М		Power Offset 9.2.2.30	Power offset for the pilot bits.	-	
>FDD TPC Downlink Step Size	M		9.2.2.16		_	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>Limited Power Increase	M		9.2.2.21A		_	
>Inner Loop DL PC Status	M		9.2.2.21a		_	
DCH Information	M		DCH FDD		YES	reject
Derrinionnation	IVI		Information 9.2.2.4A		123	reject
RL Information		1 <maxno ofRLs></maxno 	3.2.2.4A		EACH	notify
>RL ID	M	OTTLS2	9.2.1.49		_	
>C-ID	M		9.2.1.6		_	
>First RLS Indicator						
	M		9.2.2.16A		_	
>Frame Offset	M		9.2.1.30		_	
>Chip Offset	M		9.2.2.1		_	
>Propagation Delay	0		9.2.2.33		_	
>Diversity Control Field	C – NotFirstRL		9.2.1.20		_	
>Initial DL TX Power	0		DL Power		_	
			9.2.1.21A			
>Primary CPICH Ec/No	0		9.2.2.32		_	
>Not Used	0		NULL		_	
>Transmit Diversity Indicator	C – Diversity mode		9.2.2.48		_	
>Enhanced Primary CPICH Ec/No	O		9.2.2.131		YES	ignore
>RL Specific DCH Information	0		9.2.1.49A		YES	ignore
>Delayed Activation	0		9.2.1.19Aa		YES	reject
>Cell Portion ID	0		9.2.2.E		YES	ignore
>RL specific E-DCH Information	0		9.2.2.35a		YES	reject
>E-DCH RL Indication	0		9.2.2.4E		YES	reject
>Extended Propagation Delay	0		9.2.2.33a		YES	ignore
>Synchronisation Indicator	0		9.2.2.45A		YES	reject
>HS-DSCH Preconfiguration Setup	Ō		9.2.2.100		YES	ignore
>Non-Serving RL Preconfiguration Setup	0		9.2.2.124		YES	ignore
Transmission Gap Pattern Sequence Information	0		9.2.2.47A		YES	reject
Active Pattern Sequence Information	0		9.2.2.A		YES	reject
Permanent NAS UE Identity	0		9.2.1.73		YES	ignore
DL Power Balancing Information	0		9.2.2.10A		YES	ignore
HS-DSCH Information	0		HS-DSCH FDD Information 9.2.2.19a		YES	reject
HS-PDSCH RL ID	C – InfoHSDS CH		RL ID 9.2.1.49		YES	reject
MBMS Bearer Service List		0 <maxno ofMBMS></maxno 			GLOBAL	notify
>TMGI	М		9.2.1.80		_	
E-DPCH Information		01			YES	reject
>Maximum Set of E- DPDCHs	М		9.2.2.24e		_	
>Puncture Limit	М		9.2.1.46		_	
>E-TFCS Information	M		9.2.2.4G		_	
>E-TTI	M		9.2.2.4J		_	
>E-DPCCH Power Offset	M		9.2.2.4K		_	
>E-RGCH 2-Index-Step	M	+	9.2.2.64		_	
Threshold			5.2.2.0 T			

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>E-RGCH 3-Index-Step	M		9.2.2.65		_	
Threshold			0.0.0.0			
>HARQ Info for E-DCH	M		9.2.2.66		_	
>HS-DSCH Configured Indicator	М		9.2.2.19C		_	
> Minimum Reduced E- DPDCH Gain Factor	0		9.2.2.102		YES	ignore
E-DCH FDD Information	C- EDCHInfo		9.2.2.4B		YES	reject
Serving E-DCH RL	0		9.2.2.38C		YES	reject
F-DPCH Information		01			YES	reject
>Power Offset Information	D.4	1	D	This IF shall	_	
>>PO2	M		Power Offset 9.2.2.30	This IE shall be ignored by DRNS.	_	
>FDD TPC Downlink Step Size	М		9.2.2.16		_	
>Limited Power Increase	М		9.2.2.21A		_	
>Inner Loop DL PC Status	M		9.2.2.21a		-	
>F-DPCH Slot Format Support Request	0		9.2.2.86		YES	reject
>F-DPCH Slot Format	0		9.2.2.85		YES	Ignore
Initial DL DPCH Timing Adjustment Allowed	0		9.2.2.21b		YES	ignore
DCH Indicator For E-DCH- HSDPA Operation	0		9.2.2.67		YES	reject
Serving Cell Change CFN	0		CFN 9.2.1.9		YES	reject
Continuous Packet Connectivity DTX-DRX Information	0		9.2.2.72		YES	reject
Continuous Packet Connectivity HS-SCCH less Information	0		9.2.2.74		YES	reject
Extended SRNC-ID	0		Extended RNC-ID 9.2.1.50a	The Extended SRNC-ID IE shall be used if the RNC identity has a value larger than 4095.	YES	reject
Additional HS Cell Information RL Setup		0 <maxno ofHSDSC H-1></maxno 		For secondary serving HS- DSCH cell. Max 3 in this 3GPP release.	EACH	reject
>HS-PDSCH RL ID	М		RL ID 9.2.1.49		_	
>C-ID	М		9.2.1.6			
>HS-DSCH Secondary Serving Information	М		9.2.2.19aa		_	
UE Aggregate Maximum Bit Rate	0		9.2.1.137		YES	ignore
Additional E-DCH Cell Information RL Setup Req		01		For E-DCH on multiple frequencies in this DRNS.	YES	reject
>Multicell E-DCH Transport Bearer Mode	М		9.2.2.113		_	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>Additional E-DCH Cell Information Setup		1 <maxno ofEDCH- 1></maxno 		E-DCH on Secondary uplink frequency – max 1 in this 3GPP release.	_	
>>Additional E-DCH FDD Setup Information	М		9.2.2.110		-	
Usefulness of Battery Optimization	0		9.2.2.127		YES	ignore

Condition	Explanation
CodeLen	The IE shall be present if Min UL Channelisation Code length IE
	equals to 4
SlotFormat	The IE shall be present if the DL DPCH Slot Format IE is equal to
	any of the values from 12 to 16.
NotFirstRL	The IE shall be present if the RL is not the first one in the RL
	Information IE.
Diversity mode	The IE shall be present if Diversity Mode IE in UL DPCH Information
	IE is not equal to "none".
InfoHSDSCH	This IE shall be present if HS-DSCH Information IE is present.
EDCHInfo	This IE shall be present if <i>E-DPCH Information</i> IE is present.

Range bound	Explanation
maxnoofRLs	Maximum number of RLs for one UE.
maxnoofMBMS	Maximum number of MBMS bearer services that a UE can join.
maxnoofHSDSCH-1	Maximum number of Secondary Serving HS-DSCH cells for one UE.
maxnoofEDCH-1	Maximum number of uplink frequencies -1 for E-DCH for one UE

9.1.3.2 TDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
SRNC-ID	М		RNC-ID 9.2.1.50	If the Extended SRNC-ID IE is included in the message, the SRNC-ID IE shall be ignored.	YES	reject
S-RNTI	M		9.2.1.53		YES	reject
D-RNTI	0		9.2.1.24		YES	reject
UL Physical Channel Information		1			YES	reject
>Maximum Number of Timeslots	M		9.2.3.3A	For the UL	-	
>Minimum Spreading Factor	М		9.2.3.4A	For the UL	_	
>Maximum Number of UL Physical Channels per Timeslot	М		9.2.3.3B		-	
>Support of 8PSK	0		9.2.3.7H	Applicable to 1.28Mcps TDD only	YES	ignore
>Minimum Spreading Factor 7.68Mcps	0		9.2.3.19	Applicable to 7.68Mcps TDD only	YES	ignore
DL Physical Channel Information		1			YES	reject
>Maximum Number of Timeslots	М		9.2.3.3A	For the DL	-	
>Minimum Spreading Factor	M		9.2.3.4A	For the DL	_	
>Maximum Number of DL Physical Channels	M		9.2.3.3C		_	
>Maximum Number of DL Physical Channels per Timeslot	0		9.2.3.3D		YES	ignore
>Support of 8PSK	0		9.2.3.7H	Applicable to 1.28Mcps TDD only	YES	ignore
>Support of PLCCH	0		9.2.3.16	Applicable to 1.28Mcps TDD only	YES	ignore

>Minimum Spreading Factor 7.68Mcps	0		9.2.3.19	Applicable to 7.68Mcps TDD only	YES	ignore
>Maximum Number of DL Physical Channels 7.68Mcps	0		9.2.3.20	Applicable to 7.68Mcps TDD only	YES	ignore
>Maximum Number of DL Physical Channels per Timeslot 7.68Mcps	0		9.2.3.21	Applicable to 7.68Mcps TDD only	YES	ignore
Allowed Queuing Time	0		9.2.1.2	j	YES	reject
UL CCTrCH Information		0 <maxn oofCCTr CHs></maxn 		For DCH and USCH	EACH	notify
>CCTrCH ID	M		9.2.3.2		_	
>TFCS	M		9.2.1.63	For the UL.	_	
>TFCI Coding	M		9.2.3.11		_	
>Puncture Limit	M		9.2.1.46			
>TDD TPC Uplink Step Size	0		9.2.3.10a	Mandatory for 1.28Mcps TDD, not applicable to 3.84Mcps TDD or 7.68Mcps TDD	YES	reject
DL CCTrCH Information		0 <maxn oofCCTr CHs></maxn 		For DCH and DSCH	EACH	notify
>CCTrCH ID	М		9.2.3.2		_	
>TFCS	М		9.2.1.63	For the DL.	_	
>TFCI Coding	M		9.2.3.11		-	
>Puncture Limit	M		9.2.1.46		_	
>TDD TPC Downlink Step	M		9.2.3.10		_	
Size						
>TPC CCTrCH List		0 <maxn oCCTrC Hs></maxn 		List of uplink CCTrCH which provide TPC	-	
>>TPC CCTrCH ID	М		CCTrCH ID 9.2.3.2		_	
DCH Information	0		DCH TDD Information 9.2.3.2A		YES	reject
DSCH Information	0		DSCH TDD Information 9.2.3.3a		YES	reject
USCH Information	0		9.2.3.15		YES	reject
RL Information	-	1	3.2.3.10		YES	reject
>RL ID	М	-	9.2.1.49		-	. 5,550
>C-ID	M		9.2.1.6		_	
>Frame Offset	M		9.2.1.30		_	
>Special Burst Scheduling	М		9.2.3.7D		1	
>Primary CCPCH RSCP	0		9.2.3.5		1	
>DL Time Slot ISCP Info	0		9.2.3.2D	Applicable to 3.84Mcps TDD and 7.68Mcps TDD only	-	
>DL Time Slot ISCP Info LCR	0		9.2.3.2F	Applicable to 1.28Mcps TDD only	YES	reject
>TSTD Support Indicator	0		9.2.3.13F	Applicable to 1.28Mcps TDD only	YES	ignore
>RL Specific DCH Information	0		9.2.1.49A		YES	ignore
>Delayed Activation	0	1	9.2.1.19Aa	1	YES	reject

>UL Synchronisation Parameters LCR		01		Mandatory for 1.28Mcps TDD. Not Applicable to 3.84Mcps TDD or 7.68Mcps TDD.	YES	reject
>>Uplink Synchronisation Step Size	M		9.2.3.13J		_	
>>Uplink Synchronisation Frequency	M		9.2.3.131		_	
>Primary CCPCH RSCP Delta	0		9.2.3.5a		YES	ignore
>Idle Interval Configuration Indicator	0		NULL	TDD only	YES	ignore
>Cell Portion LCR ID	0		9.2.3.73	Applicable to 1.28Mcps TDD only	YES	ignore
Permanent NAS UE Identity	0		9.2.1.73		YES	ignore
HS-DSCH Information	0		HS-DSCH TDD Information 9.2.3.3aa		YES	reject
HS-PDSCH RL ID	C – InfoHSDSC H		RL ID 9.2.1.49		YES	reject
PDSCH-RL-ID	0		RL ID 9.2.1.49		YES	ignore
MBMS Bearer Service List		0 <maxn oofMBM S></maxn 			GLOBAL	notify
>TMGI	М		9.2.1.80		_	
E-DCH Information		01		3.84Mcps TDD only	YES	reject
>E-PUCH Information	M		9.2.3.36		_	
>E-TFCS Information TDD	M		9.2.3.37		_	
>E-DCH MAC-d Flows Information TDD	М		9.2.3.38		_	
>E-DCH TDD Information	M		9.2.3.40		_	
E-DCH Serving RL	0		9.2.1.49	TDD only	YES	reject
E-DCH Information 7.68Mcps		01		7.68Mcps TDD only	YES	reject
>E-PUCH Information	M		9.2.3.36		_	
>E-TFCS Information TDD	M		9.2.3.37		_	
>E-DCH MAC-d Flows Information TDD	M		9.2.3.38		_	
>E-DCH TDD Information 7.68Mcps	М		9.2.3.51	1.0014	-	
E-DCH Information 1.28Mcps		01		1.28Mcps TDD only	YES	reject
>E-PUCH Information LCR	M		9.2.3.36a		_	
>E-TFCS Information TDD >E-DCH MAC-d Flows	M M		9.2.3.37 9.2.3.38		_	
Information TDD >E-DCH TDD Information	M		9.2.3.40a		_	
LCR Extended SRNC-ID	0		Extended RNC-ID 9.2.1.50a	The Extended SRNC-ID IE shall be used if the RNC identity has a value larger than 4095.	YES	reject
Continuous Packet Connectivity DRX Information LCR	0		9.2.3.61	1.28 Mcps TDD only	YES	reject

HS-DSCH Semi-Persistent	0		9.2.3.64	1.28 Mcps	YES	reject
scheduling Information LCR				TDD only		
E-DCH Semi-Persistent	0		9.2.3.66	1.28 Mcps	YES	reject
scheduling Information LCR				TDD only		
RNTI Allocation Indicator	0		ENUMERA	1.28 Mcps	YES	ignore
			TED (True)	TDD only		
DCH Measurement Type	0		9.2.3.76	1.28 Mcps	YES	reject
indicator				TDD only		
Multi-Carrier E-DCH		01		Applicable for	YES	reject
Information				Multi-Carrier		
				E-DCH		
				Operation in		
				1.28 Mcps		
				TDD only		
>Multi-Carrier E-DCH	M		9.2.3.79	1.28 Mcps	_	
Transport Bearer Mode				TDD only		
LCR						
>Multi-Carrier E-DCH	M		9.2.3.77	1.28 Mcps	_	
Information LCR				TDD only		
MU-MIMO Indicator	0		9.2.3.82	1.28 Mcps	YES	reject
				TDD only		

Condition	Explanation
InfoHSDSCH	This IE shall be present if HS-DSCH Information IE is present.

Range bound	Explanation
maxnoofCCTrCHs	Maximum number of CCTrCH for one UE.
maxnoofMBMS	Maximum number of MBMS bearer services that a UE can join.

9.1.4 RADIO LINK SETUP RESPONSE

9.1.4.1 FDD Message

Message Type	IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Transaction ID	Message Type	M		9.2.1.40		YES	reject
CN PS Domain Identifier	Transaction ID					_	
CNCS Domain Identifier	D-RNTI	0		9.2.1.24		YES	ignore
SNC SDomain Identifier O	CN PS Domain Identifier	0		9.2.1.12		YES	ignore
RL Information Response		0				YES	
New York Note	RL Information Response					EACH	
SURA Information O 9.2.1.70B -		M				_	
SAI	>RL Set ID	M		9.2.2.35		_	
SCEIL GAI O 9.2.1.5A -	>URA Information	0		9.2.1.70B		_	
SUTRAN Access Point	>SAI	M		9.2.1.52		_	
Position Position Power Power	>Cell GAI	0				_	
Power	>UTRAN Access Point Position	0				_	
SDL Code Information	Power					_	
Code Information 9.2.2.14A						_	
Indication	>DL Code Information	М		Code Information		_	
SSPALID M 9.2.1.49 Reference R ID for the combining	Indication	М				_	
RL ID for the combining						_	
SSECTION STATE	>>>RL ID	M		9.2.1.49	RL ID for the	_	
SSE-DCH FDD		0		9.2.1.16A		YES	ignore
RL	Information Response	0		9.2.2.4C		YES	ignore
Response	RL					_	
Information Response	Response					_	
>Maximum Uplink SIR M Uplink SIR 9.2.1.69 — >Minimum Uplink SIR M Uplink SIR 9.2.1.69 — >Closed Loop Timing Adjustment Mode O 9.2.2.3A — >Maximum Allowed UL Tx Power M 9.2.1.35 — >Maximum DL TX Power M DL Power 9.2.1.21A — >Minimum DL TX Power M DL Power 9.2.1.21A — >Primary Scrambling Code O 9.2.1.45 — >UL UARFCN O UARFCN 25.104 [6] — >DL UARFCN O UARFCN 25.104 [6] — >Primary CPICH Power M 9.2.1.44 —	Information Response					YES	ignore
9.2.1.69						_	
9.2.1.69	·			9.2.1.69		-	
Adjustment Mode SMaximum Allowed UL Tx M 9.2.1.35 -	·			9.2.1.69		_	
Power	Adjustment Mode					_	
9.2.1.21A	Power					_	
9.2.1.21A				9.2.1.21A		_	
>UL UARFCN O UARFCN 9.2.1.66 Corresponds to Nu in TS 25.104 [6] — >DL UARFCN O UARFCN Corresponds to Nd in TS 25.104 [6] — >Primary CPICH Power M 9.2.1.44 —				9.2.1.21A		_	
9.2.1.66 to Nu in TS 25.104 [6] >DL UARFCN						_	
>DL UARFCN O UARFCN 9.2.1.66 Corresponds to Nd in TS 25.104 [6] — >Primary CPICH Power M 9.2.1.44 —	>UL UARFCN	0			to Nu in TS	_	
>Primary CPICH Power M 9.2.1.44 –	>DL UARFCN	0			Corresponds to Nd in TS	_	
	>Primary CPICH Power	М		92144	20.10 [[0]	_	
I Not lead O NI II	>Not Used	0	+	NULL		_	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>Neighbouring UMTS Cell	0		9.2.1.41A		_	
Information >Neighbouring GSM Cell Information	0		9.2.1.41C		_	
>PC Preamble	М		9.2.2.27a		_	
>SRB Delay	M		9.2.2.39A		_	
>Cell GA Additional Shapes	0		9.2.1.5B		YES	ignore
>DL Power Balancing Activation Indicator	0		9.2.2.10B		YES	ignore
>HCS Prio	0		9.2.1.30N		YES	ignore
>Primary CPICH Usage For Channel Estimation	0		9.2.2.32A		YES	ignore
>Secondary CPICH Information	0		9.2.2.38A		YES	ignore
>Active MBMS Bearer Service List		0 <maxno ofActiveM BMS></maxno 			GLOBAL	ignore
>>TMGI	М		9.2.1.80		_	
>>Transmission Mode	0		9.2.1.81		_	
>>Preferred Frequency Layer	0		UARFCN 9.2.1.66		_	
>E-DCH RL Set ID	0		RL Set ID 9.2.2.35		YES	ignore
>E-DCH FDD DL Control Channel Information	0		9.2.2.4D		YES	ignore
>Initial DL DPCH Timing Adjustment	0		DL DPCH Timing Adjustment 9.2.2.9A		YES	ignore
>F-DPCH Slot Format	0		9.2.2.85		YES	ignore
>Frame Offset	0		9.2.1.30		YES	ignore
>Chip Offset	0		9.2.2.1		YES	ignore
>Neighbouring E-UTRA Cell Information	0		9.2.1.41De		YES	ignore
>HS-DSCH Preconfiguration Info	0		9.2.2.99		YES	ignore
>Non-Serving RL Preconfiguration Info	0		9.2.2.125		YES	ignore
>Neighbouring UMTS Cell Information Extension	0		9.2.1.141		YES	ignore
Uplink SIR Target	0		Uplink SIR 9.2.1.69		YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore
HS-DSCH-RNTI	0		9.2.1.30P		YES	ignore
HS-DSCH Information Response	0		HS-DSCH FDD Information Response 9.2.2.19b		YES	ignore
Continuous Packet Connectivity HS-SCCH less Information Response	0		9.2.2.75		YES	ignore
SixtyfourQAM DL Support Indicator	0		9.2.1.123		YES	ignore
Additional HS Cell Information Response		0 <maxno ofHSDSC H-1></maxno 		For secondary serving HS- DSCH cell. Max 3 in this 3GPP release.	EACH	ignore
>HS-PDSCH RL ID	М		RL ID 9.2.1.49		_	
>HS-DSCH-RNTI	М		9.2.1.30P		_	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>HS-DSCH FDD Secondary Serving Information Response	М		9.2.2.19ba		_	
>SixtyfourQAM DL Support Indicator	0		9.2.1.123		_	
Additional E-DCH Cell Information Response		0 <maxno ofEDCH- 1></maxno 		E-DCH on Secondary uplink frequency – max 1 in this 3GPP release.	EACH	ignore
>Additional E-DCH FDD Information Response	М		9.2.2.120		_	

Range bound	Explanation
maxnoofRLs	Maximum number of RLs for one UE.
maxnoofActiveMBMS	Maximum number of MBMS bearer services that are active in parallel.
maxnoofHSDSCH-1	Maximum number of Secondary Serving HS-DSCH cells for one UE.
maxnoofEDCH-1	Maximum number of uplink frequencies -1 for E-DCH for one UE

9.1.4.2 TDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		-	TOJOOL
D-RNTI	O		9.2.1.24		YES	ignore
CN PS Domain Identifier	0		9.2.1.12		YES	_
	0		9.2.1.12		YES	ignore
CN CS Domain Identifier RL Information Response	U	01	9.2.1.11	Mandatanifan	YES	ignore
		01		Mandatory for 3.84Mcps TDD, not applicable to 1.28Mcps TDD or 7.68Mcps TDD		ignore
>RL ID	М		9.2.1.49		_	
>URA Information	0		9.2.1.70B		_	
>SAI	M		9.2.1.52		_	
>Cell GAI	0		9.2.1.5A		_	
>UTRAN Access Point Position	0		9.2.1.70A		_	
>UL Time Slot ISCP Info	М		9.2.3.13D		_	
>Maximum Uplink SIR	М		Uplink SIR 9.2.1.69		_	
>Minimum Uplink SIR	М	†	Uplink SIR		_	
·			9.2.1.69			
>Maximum Allowed UL Tx Power	М		9.2.1.35		_	
>Maximum DL TX Power	М		DL Power 9.2.1.21A		_	
>Minimum DL TX Power	М		DL Power 9.2.1.21A		_	
>UARFCN	0		9.2.1.66	Corresponds to Nt in TS 25.105 [7]	_	
>Cell Parameter ID	0		9.2.1.8		_	
>Sync Case	0		9.2.1.54		_	
>SCH Time Slot	C-Case2		9.2.1.51		_	
>SCTD Indicator	0		9.2.1.78		_	
>PCCPCH Power	M		9.2.1.43		_	
>Timing Advance Applied	M		9.2.3.12A		_	
>Alpha Value	М		9.2.3.a		_	
>UL PhysCH SF Variation	M		9.2.3.13B		_	
>Synchronisation Configuration	M		9.2.3.7E		_	
>Secondary CCPCH Info TDD	0		9.2.3.7B		_	
>UL CCTrCH Information		0 <maxno ofCCTrCH s></maxno 		For DCH	GLOBAL	ignore
>>CCTrCH ID	М		9.2.3.2		_	
>>UL DPCH Information		01			YES	ignore
>>>Repetition Period	М		9.2.3.7			J
>>>Repetition Length	M		9.2.3.6		_	
>>>TDD DPCH Offset	M		9.2.3.8A		_	
>>>UL Timeslot Information	M		9.2.3.13C		_	
>>Uplink SIR Target CCTrCH	0		Uplink SIR 9.2.1.69		YES	ignore
>DL CCTrCH Information		0 <maxno ofCCTrCH s></maxno 	9.2.1.03	For DCH	GLOBAL	ignore
>>CCTrCH ID	М		9.2.3.2		_	

IE/Group Name	Presence	Range	IE Type	Semantics	Criticality	Assigned
·			and Reference	Description		Criticality
>>DL DPCH Information		01	Reference		YES	ignore
>>>Repetition Period	M	01	9.2.3.7		163	ignore
>>>Repetition Length	M		9.2.3.6			
>>>TDD DPCH Offset	M		9.2.3.8A			
>>>DL Timeslot	M		9.2.3.2C		_	
Information						
>>CCTrCH Maximum DL TX Power	0		DL Power 9.2.1.21A	Maximum allowed power on DPCH	YES	ignore
>>CCTrCH Minimum DL TX Power	0		DL Power 9.2.1.21A	Minimum allowed power on DPCH	YES	ignore
>DCH Information Response	0		9.2.1.16A		YES	ignore
>DSCH Information		0			GLOBAL	ignore
Response		<maxnoof DSCHs></maxnoof 			GEODILE	ignore
>>DSCH ID	М		9.2.3.3ae		_	
>>DSCH Flow Control	M		9.2.3.3ag		-	
Information	1					
>>Binding ID	0		9.2.1.3		_	
>>Transport Layer Address	0		9.2.1.62		_	
>>Transport Format Management	М		9.2.3.13		_	
>USCH Information		0			GLOBAL	ignore
Response		<maxnoof USCHs></maxnoof 			GLOBAL	ignore
>>USCH ID	M		9.2.3.14		_	
>>Binding ID	0		9.2.1.3		_	
>>Transport Layer Address	0		9.2.1.62		-	
>>Transport Format Management	М		9.2.3.13		_	
>Neighbouring UMTS Cell Information	0		9.2.1.41A		_	
>Neighbouring GSM Cell Information	0		9.2.1.41C		_	
>Cell GA Additional Shapes	0		9.2.1.5B		YES	ignore
>HCS Prio	0		9.2.1.30N		YES	ignore
>Time Slot for SCH	C-Case1		Time Slot 9.2.1.56		YES	ignore
>Neighbouring E-UTRA Cell Information	0		9.2.1.41De		YES	ignore
>Neighbouring UMTS Cell Information Extension	0		9.2.1.141		YES	ignore
Uplink SIR Target	М		Uplink SIR 9.2.1.69		YES	ignore
Criticality Diagnostics	0	†	9.2.1.13	1	YES	ignore
RL Information Response LCR		01		Mandatory for 1.28Mcps TDD, not applicable to 3.84Mcps TDD or 7.68Mcps TDD	YES	ignore
>RL ID	M		9.2.1.49		_	
>URA Information	M	1	9.2.1.70B		-	
>SAI	M		9.2.1.52		-	
>Cell GAI >UTRAN Access Point	0		9.2.1.5A 9.2.1.70A		_	
Position						
>UL Time Slot ISCP Info	M	L	9.2.3.13H	ļ	_	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
LCR			Reference			
>Maximum Uplink SIR	М		Uplink SIR 9.2.1.69		_	
>Minimum Uplink SIR	М		Uplink SIR 9.2.1.69		_	
>Maximum Allowed UL Tx Power	М		9.2.1.35		_	
>Maximum DL TX Power	М		DL Power 9.2.1.21A		_	
>Minimum DL TX Power	М		DL Power 9.2.1.21A		_	
>UARFCN	0		9.2.1.66	Corresponds to Nt in TS 25.105 [7]	_	
>Cell Parameter ID	0		9.2.1.8		_	
>SCTD Indicator	0		9.2.1.78		_	
>PCCPCH Power	М		9.2.1.43		_	
>Alpha Value	М		9.2.3.a		_	
>UL PhysCH SF Variation	M		9.2.3.13B		_	
>Synchronisation Configuration	М		9.2.3.7E		_	
>Secondary CCPCH Info TDD LCR	0		9.2.3.7F		_	-
>UL CCTrCH Information LCR		0 <maxno ofCCTrCH sLCR></maxno 		For DCH	GLOBAL	ignore
>>CCTrCH ID	М		9.2.3.2		_	
>>UL DPCH Information LCR		01			YES	ignore
>>>Repetition Period	М		9.2.3.7		_	
>>>Repetition Length	М		9.2.3.6		_	
>>>TDD DPCH Offset	M		9.2.3.8A		_	
>>>UL Timeslot Information LCR	M		9.2.3.13G		_	
>>Uplink SIR Target CCTrCH	0		Uplink SIR 9.2.1.69		YES	ignore
>DL CCTrCH Information LCR		0 <maxno ofCCTrCH sLCR></maxno 		For DCH	GLOBAL	ignore
>>CCTrCH ID	М		9.2.3.2		_	
>>DL DPCH Information LCR		01			YES	ignore
>>>Repetition Period	М		9.2.3.7		_	
>>>Repetition Length	М		9.2.3.6		-	
>>>TDD DPCH Offset	M		9.2.3.8A		_	
>>>DL Timeslot Information LCR	М		9.2.3.2E		_	
>>>TSTD Indicator	M		9.2.3.13E		_	
>DCH Information Response	0		9.2.1.16A		YES	ignore
>DSCH Information Response LCR		0 <maxnoof DSCHsLC R></maxnoof 			GLOBAL	ignore
>>DSCH ID	М		9.2.3.3ae	1	_	
>>DSCH Flow Control Information	M		9.2.3.3ag		_	
>>Binding ID	0		9.2.1.3	1	_	
>>Transport Layer Address	0		9.2.1.62		_	
>>Transport Format Management	М		9.2.3.13		_	
>USCH Information Response LCR		0 <maxnoof< td=""><td></td><td></td><td>GLOBAL</td><td>ignore</td></maxnoof<>			GLOBAL	ignore

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
		USCHsLC	Reference			
		R>				
>>USCH ID	M		9.2.3.14		_	
>>Binding ID	0		9.2.1.3 9.2.1.62		_	
>>Transport Layer Address					_	
>>Transport Format Management	M		9.2.3.13		_	
>Neighbouring UMTS Cell Information	0		9.2.1.41A		_	
>Neighbouring GSM Cell Information	0		9.2.1.41C		_	
>HCS Prio	0		9.2.1.30N		YES	ignore
>Cell GA Additional Shapes	Ö		9.2.1.5B		YES	ignore
>Uplink Timing Advance Control LCR	M		9.2.3.13K		YES	ignore
>PowerControl GAP	0		INTEGER (1255)	Unit: umber of subframes Applicable to 1.28Mcps TDD only	YES	ignore
>SixtyfourQAM DL Support Indicator	0		9.2.1.123	Applicable to 1.28Mcps TDD only	YES	ignore
>Neighbouring E-UTRA Cell Information	0		9.2.1.41De		YES	ignore
>Idle Interval Information	0		9.2.3.60	TDD only	YES	ignore
>Neighbouring UMTS Cell Information Extension	0		9.2.1.141		YES	ignore
HS-DSCH-RNTI	0		9.2.1.30P		YES	ignore
HS-DSCH Information Response	0		HS-DSCH TDD Information Response 9.2.3.3ab		YES	ignore
DSCH-RNTI	0		9.2.3.3ah		YES	ignore
Active MBMS Bearer Service List		0 <maxno ofActiveM BMS></maxno 			GLOBAL	ignore
>TMGI	M		9.2.1.80		_	
>Transmission Mode	0		9.2.1.81		_	
>Preferred Frequency Layer	0		UARFCN 9.2.1.66		_	
RL Information Response 7.68Mcps		01		Mandatory for 7.68Mcps TDD, not applicable to 1.28Mcps TDD or 3.84Mcps TDD	YES	ignore
>RL ID	M	1	9.2.1.49	-	_	
>URA Information >SAI	O M		9.2.1.70B		_	
>SAI >Cell GAI	M O	1	9.2.1.52 9.2.1.5A	+	_	
>Cell GAI >UTRAN Access Point Position	0		9.2.1.5A 9.2.1.70A			
>UL Time Slot ISCP Info	M		9.2.3.13D		_	
>Maximum Uplink SIR	M		Uplink SIR		_	
>Minimum Uplink SIR	M		9.2.1.69 Uplink SIR		_	
>Maximum Allowed UL Tx	M		9.2.1.69 9.2.1.35			
Power	IVI		3.Z.1.33		_	

IE/Group Name	Presence	Range	IE Type	Semantics	Criticality	Assigned
			and Reference	Description		Criticality
>Maximum DL TX Power	М		DL Power		-	
>Minimum DL TX Power	M		9.2.1.21A DL Power		_	
			9.2.1.21A			
>UARFCN	0		UARFCN	Corresponds	_	
			9.2.1.66	to Nt in TS 25.105 [7]		
>Cell Parameter ID	0		9.2.1.8		-	
>Sync Case	0		9.2.1.54		_	
>SCH Time Slot >SCTD Indicator	C-Case2		9.2.1.51		_	
>PCCPCH Power	M		9.2.1.78 9.2.1.43		_	
>Timing Advance Applied	M		9.2.3.12A		_	
>Alpha Value	M		9.2.3.a		_	
>UL PhysCH SF Variation	М		9.2.3.13B		_	
>Synchronisation	M		9.2.3.7E		_	
Configuration			0.0.0.00			
>Secondary CCPCH Info 7.68Mcps TDD	0		9.2.3.22		_	
>UL CCTrCH Information		0 <maxno< td=""><td></td><td>For DCH</td><td>GLOBAL</td><td>ignore</td></maxno<>		For DCH	GLOBAL	ignore
7.68 Mcps		ofCCTrCH s>				J
>>CCTrCH ID	M		9.2.3.2		-	
>>UL DPCH Information		01			YES	ignore
>>>Repetition Period	M		9.2.3.7		_	
>>>Repetition Length >>>TDD DPCH Offset	M		9.2.3.6 9.2.3.8A		_	
>>>UL Timeslot	M		9.2.3.6A 9.2.3.26		_	
Information 7.68Mcps	IVI		9.2.3.20		_	
>>Uplink SIR Target CCTrCH	0		Uplink SIR 9.2.1.69		-	
>DL CCTrCH Information 7.68 Mcps		0 <maxno ofCCTrCH s></maxno 	0.200	For DCH	GLOBAL	ignore
>>CCTrCH ID	М	32	9.2.3.2		_	
>>DL DPCH Information		01			YES	ignore
>>>Repetition Period	М		9.2.3.7		_	
>>>Repetition Length	M		9.2.3.6		_	
>>>TDD DPCH Offset	M		9.2.3.8A		_	
>>>DL Timeslot Information 7.68Mcps	M		9.2.3.28		_	
>>CCTrCH Maximum DL	0		DL Power	Maximum	-	
TX Power			9.2.1.21A	allowed power on DPCH		
>>CCTrCH Minimum DL	0		DL Power	Minimum	_	
TX Power			9.2.1.21A	allowed power on DPCH		
>DCH Information Response	0		9.2.1.16A		YES	ignore
>DSCH Information Response 7.68 Mcps		0 <maxnoof< td=""><td></td><td></td><td>GLOBAL</td><td>ignore</td></maxnoof<>			GLOBAL	ignore
-		DSCHs>				
>>DSCH ID	M		9.2.3.3ae		-	
>>DSCH Flow Control	M		9.2.3.3ag		_	
Information >>Binding ID	0		9.2.1.3		_	
>>Transport Layer	0		9.2.1.62		_	
Address >>Transport Format	M		9.2.3.13			
>>rransport Format Management	IVI		3.2.3.13		_	
>USCH Information		0			GLOBAL	ignore
Response 7.68 Mcps		<maxnoof< td=""><td></td><td></td><td></td><td>·</td></maxnoof<>				·
~116CH ID	N/	USCHs>	02244			
>>USCH ID	M		9.2.3.14		_	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>>Binding ID	0		9.2.1.3		_	
>>Transport Layer Address	0		9.2.1.62		_	
>>Transport Format Management	М		9.2.3.13		_	
>Neighbouring UMTS Cell Information	0		9.2.1.41A		_	
>Neighbouring GSM Cell Information	0		9.2.1.41C		_	
>Cell GA Additional Shapes	0		9.2.1.5B		_	
>HCS Prio	0		9.2.1.30N		_	
>Time Slot for SCH	C-Case1		Time Slot 9.2.1.56		_	
>Neighbouring E-UTRA Cell Information	0		9.2.1.41De		YES	ignore
>Neighbouring UMTS Cell Information Extension	0		9.2.1.141		YES	ignore
E-DCH Information Response	0		E-DCH TDD Information Response 9.2.3.41	3.84Mcps TDD only	YES	ignore
E-DCH Information Response 7.68Mcps	0		E-DCH TDD Information Response 7.68Mcps 9.2.3.52	7.68Mcps TDD only	YES	ignore
E-DCH Information Response 1.28Mcps	0		E-DCH TDD Information Response 1.28Mcps 9.2.3.41a	1.28Mcps TDD only	YES	ignore
Continuous Packet Connectivity DRX Information Response LCR	0		9.2.3.63	1.28 Mcps TDD only	YES	ignore
HS-DSCH Semi-Persistent scheduling Information Response LCR	0		9.2.3.68	1.28 Mcps TDD only	YES	ignore
E-DCH Semi-Persistent scheduling Information Response LCR	0		9.2.3.69	1.28 Mcps TDD only	YES	ignore
E-RNTI for FACH	0		E-RNTI 9.2.1.94	1.28 Mcps TDD only	YES	ignore
H-RNTI for FACH	0		HS-DSCH- RNTI 9.2.1.30P	1.28 Mcps TDD only	YES	ignore
DCH Measurement Occasion Information	0		9.2.3.75	1.28 Mcps TDD only	YES	reject
Multi-Carrier E-DCH Information Response LCR	0		9.2.3.78	1.28 Mcps TDD only	YES	ignore
MU-MIMO Information	0		9.2.3.81	1.28 Mcps TDD only	YES	reject

Condition	Explanation
Case2	The IE shall be present if Sync Case IE is equal to "Case2".
Case1	This IE shall be present if Sync Case IE is equal to "Case1".

Range bound	Explanation
maxnoofDSCHs	Maximum number of DSCHs for one UE for 3.84Mcps TDD or 7.68Mcps TDD.
maxnoofUSCHs	Maximum number of USCHs for one UE for 3.84Mcps TDD or 7.68Mcps TDD.
maxnoofCCTrCHs	Maximum number of CCTrCH for one UE for 3.84Mcps TDD or 7.68Mcps TDD.
maxnoofDSCHsLCR	Maximum number of DSCHs for one UE for 1.28Mcps TDD.
maxnoofUSCHsLCR	Maximum number of USCHs for one UE for 1.28Mcps TDD.
maxnoofCCTrCHsLCR	Maximum number of CCTrCH for one UE for 1.28Mcps TDD.
maxnoofActiveMBMS	Maximum number of MBMS bearer services that are active in parallel.

9.1.5 RADIO LINK SETUP FAILURE

9.1.5.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	•
D-RNTI	0		9.2.1.24		YES	ignore
CN PS Domain Identifier	0		9.2.1.12		YES	ignore
CN CS Domain Identifier	0		9.2.1.11		YES	ignore
CHOICE Cause Level	М				YES	ignore
>General					_	J
>>Cause	М		9.2.1.5		_	
>RL Specific					_	
>>Unsuccessful RL Information Response		1 <maxno ofRLs></maxno 			EACH	ignore
>>>RL ID	М		9.2.1.49		_	
>>>Cause	M		9.2.1.5		_	
>>>Max UE DTX Cycle	C-DTX- CycleNotA vailable		9.2.2.87		YES	ignore
>>Successful RL		0 <maxno< td=""><td></td><td></td><td>EACH</td><td>ignore</td></maxno<>			EACH	ignore
Information Response	<u> </u>	ofRLs-1>	<u> </u>		<u> </u>	
>>>RL ID	М		9.2.1.49		_	
>>>RL Set ID	М		9.2.2.35		_	
>>>URA Information	0		9.2.1.70B		_	
>>>SAI	M		9.2.1.52		_	
>>>Cell GAI	0		9.2.1.5A		_	
>>>UTRAN Access Point	0		9.2.1.70A		_	
Position			0.2			
>>>Received Total Wide Band Power	М		9.2.2.35A		_	
>>Not Used	0		NULL		_	
>>>DL Code Information	M		FDD DL Code Information 9.2.2.14A		_	
>>>CHOICE Diversity Indication	М				-	
>>>Combining					_	
>>>>RL ID	М		9.2.1.49	Reference RL ID for the combining	_	
>>>>DCH Information Response	0		9.2.1.16A		YES	ignore
>>>>E-DCH FDD Information Response	0		9.2.2.4C		YES	ignore
>>>Non Combining or First RL					_	
>>>>DCH Information Response	М		9.2.1.16A		_	
>>>>E-DCH FDD Information Response	0		9.2.2.4C		YES	ignore
>>>SSDT Support Indicator	М		9.2.2.43		_	
>>>Maximum Uplink SIR	М		Uplink SIR 9.2.1.69		_	
>>>Minimum Uplink SIR	М		Uplink SIR 9.2.1.69		_	
>>>Closed Loop Timing Adjustment Mode	0		9.2.2.3A		_	
>>>Maximum Allowed UL Tx Power	M		9.2.1.35		_	

290

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
M : DI TY			Reference			
>>>Maximum DL TX Power	М		DL Power 9.2.1.21A		_	
>>>Minimum DL TX Power	М		DL Power 9.2.1.21A		_	
>>>Primary CPICH Power	М		9.2.1.44		_	
>>>Primary Scrambling Code	0		9.2.1.45		_	
>>>UL UARFCN	0		UARFCN 9.2.1.66	Corresponds to Nu in TS 25.104 [6]	_	
>>>DL UARFCN	0		UARFCN 9.2.1.66	Corresponds to Nd in TS 25.104 [6]	-	
>>>Not Used	0		NULL		_	
>>>Neighbouring UMTS Cell Information	0		9.2.1.41A		_	
>>>Neighbouring GSM Cell Information	0		9.2.1.41C		_	
>>>PC Preamble	М		9.2.2.27a		_	
>>>SRB Delay	M		9.2.2.39A		_	
>>>Cell GA Additional Shapes	0		9.2.1.5B		YES	ignore
>>>DL Power Balancing Activation Indicator	0		9.2.2.10B		YES	ignore
>>>HCS Prio	0		9.2.1.30N		YES	ignore
>>>Primary CPICH Usage For Channel Estimation	0		9.2.2.32A		YES	ignore
>>>Secondary CPICH Information	0		9.2.2.38A		YES	ignore
>>>Active MBMS Bearer Service List		0 <maxno ofActiveM BMS></maxno 			GLOBAL	ignore
>>>TMGI	М	2	9.2.1.80		_	
>>>>Transmission Mode	0		9.2.1.81		_	
>>>Preferred Frequency Layer	0		UARFCN 9.2.1.66		_	
>>>E-DCH RL Set ID	0		RL Set ID 9.2.2.35		YES	ignore
>>>E-DCH FDD DL Control Channel Information	0		9.2.2.4D		YES	ignore
>>>Initial DL DPCH Timing Adjustment	0		DL DPCH Timing Adjustment 9.2.2.9A		YES	ignore
>>>Neighbouring E- UTRA Cell Information	0		9.2.1.41De		YES	ignore
>>> HS-DSCH Preconfiguration Info	0		9.2.2.99		YES	ignore
>>>F-DPCH Slot Format	0		9.2.2.85		YES	ignore
>>Non-Serving RL Preconfiguration Info	0		9.2.2.125		YES	ignore
>>Neighbouring UMTS Cell Information Extension	0		9.2.1.141		YES	ignore
>>HS-DSCH-RNTI	0		9.2.1.30P		YES	ignore
>>HS-DSCH Information Response	0		HS-DSCH FDD Information		YES	ignore

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
			Response 9.2.2.19b			
>>Continuous Packet Connectivity HS-SCCH less Information Response	0		9.2.2.75		YES	ignore
>>SixtyfourQAM DL Support Indicator	0		9.2.1.123		YES	ignore
>>Additional HS Cell Information Response	0	0 <maxno ofHSDSC H-1></maxno 		For secondary serving HS-DSCH cell. Max 3 in this 3GPP release.	EACH	ignore
>>>HS-PDSCH RL ID	М		RL ID 9.2.1.49		_	
>>>HS-DSCH-RNTI	М		9.2.1.30P		_	
>>>HS-DSCH FDD Secondary Serving Information Response	M		9.2.2.19ba		_	
>>>SixtyfourQAM DL Support Indicator	0		9.2.1.123		-	
>>Additional E-DCH Cell Information Response		0 <maxno ofEDCH- 1></maxno 		E-DCH on Secondary uplink frequency – max 1 in this 3GPP release.	EACH	ignore
>>>Additional E-DCH FDD Information Response	М		9.2.2.120		-	
Uplink SIR Target	0		Uplink SIR 9.2.1.69		YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore

Condition	Explanation
DTX-CycleNotAvailable	The IE shall be present if the Cause IE is set to Continuous Packet
	Connectivity UE DTX Cycle not Available ".

Range bound	Explanation
maxnoofRLs	Maximum number of RLs for one UE.
maxnoofActiveMBMS	Maximum number of MBMS bearer services that are active in parallel.
maxnoofHSDSCH-1	Maximum number of Secondary Serving HS-DSCH cells for one UE.
maxnoofEDCH-1	Maximum number of uplink frequencies -1 for E-DCH for one UE

9.1.5.2 TDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
CHOICE Cause Level	M				YES	ignore
>General					_	_
>>Cause	М		9.2.1.5		_	
>RL Specific					_	
>>Unsuccessful RL Information Response		1			YES	ignore
>>>RL ID	M		9.2.1.49		_	
>>>Cause	M		9.2.1.5		_	
>>SixtyfourQAM DL Support Indicator	0		9.2.1.123		YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore

9.1.6 RADIO LINK ADDITION REQUEST

9.1.6.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
Uplink SIR Target	М		Uplink SIR 9.2.1.69		YES	reject
RL Information		1 <maxn oofRLs- 1></maxn 			EACH	notify
>RL ID	М		9.2.1.49		_	
>C-ID	М		9.2.1.6		_	
>Frame Offset	М		9.2.1.30		_	
>Chip Offset	М		9.2.2.1		_	
>Diversity Control Field	М		9.2.1.20		_	
>Primary CPICH Ec/No	0		9.2.2.32		_	
>Not Used	0		NULL		-	
>Transmit Diversity Indicator	0		9.2.2.48		-	
>DL Reference Power	0		DL Power 9.2.1.21A	Power on DPCH or on F-DPCH	YES	ignore
>Enhanced Primary CPICH Ec/No	0		9.2.2.131		YES	ignore
>RL Specific DCH Information	0		9.2.1.49A		YES	ignore
>Delayed Activation	0		9.2.1.19Aa		YES	reject
>RL specific E-DCH Information	0		9.2.2.35a		YES	reject
>E-DCH RL Indication	0		9.2.2.4E		YES	reject
>Synchronisation Indicator	0		9.2.2.45A		YES	ignore
>HS-DSCH Preconfiguration Setup	0		9.2.2.100		YES	Ignore
>Non-Serving RL Preconfiguration Setup	0		9.2.2.124		YES	Ignore
Active Pattern Sequence Information	0		9.2.2A	Either all the already active Transmissio n Gap Sequence(s) are addressed (Transmissio n Gap Pattern sequence shall overlap with the existing one) or none of the transmission gap sequences is activated.	YES	reject
DPC Mode	0		9.2.2.12A		YES	reject
Permanent NAS UE Identity	0		9.2.1.73		YES	ignore
Serving E-DCH RL	0		9.2.2.38C		YES	reject
Initial DL DPCH Timing Adjustment Allowed	0		9.2.2.21b		YES	ignore
HS-DSCH Serving Cell Change Information	0		9.2.2.19f		YES	reject

	T -	T		1		
Serving Cell Change CFN	0		CFN		YES	reject
E-DPCH Information		01	9.2.1.9		YES	reject
>Maximum Set of E-	М	01	9.2.2.24e		-	10,000
DPDCHs			0.2.2.2			
>Puncture Limit	М		9.2.1.46		_	
>E-TFCS Information	М		9.2.2.4G		_	
>E-TTI	M		9.2.2.4J		_	
>E-DPCCH Power Offset	M		9.2.2.4K		_	
>E-RGCH 2-Index-Step Threshold	М		9.2.2.64		_	
>E-RGCH 3-Index-Step Threshold	М		9.2.2.65		-	
>HARQ Info for E-DCH	M		9.2.2.66		_	
>HS-DSCH Configured Indicator	M		9.2.2.19C		YES	reject
> Minimum Reduced E- DPDCH Gain Factor	0		9.2.2.102		YES	ignore
E-DCH FDD Information	C- EDCHInfo		9.2.2.4B		YES	reject
Additional HS Cell		0 <maxn< td=""><td></td><td>For</td><td>EACH</td><td>reject</td></maxn<>		For	EACH	reject
Information RL Addition		oofHSDS CH-1>		secondary serving HS- DSCH cell. Max 3 in this 3GPP release.		,
>HS-PDSCH RL ID	М		RL ID 9.2.1.49		_	
>C-ID	М		9.2.1.6		_	
>HS-DSCH FDD Secondary Serving Information	М		9.2.2.19aa		_	
UE Aggregate Maximum Bit Rate	0		9.2.1.137		YES	ignore
Additional E-DCH Cell Information RL Add Req		01		For E-DCH on multiple frequencies in this DRNS.	YES	reject
>CHOICE Setup Or Addition Of E-DCH On Secondary UL Frequency	М			Diviso.	YES	reject
>> Setup				Used when the secondary UL frequency does not exist or is not configured with E-DCH in the current UE context	_	
>>>Multicell E-DCH	M		9.2.2.113		_	
Transport Bearer Mode	-	4		E DOLL		
>>>Additional E-DCH Cell Information Setup		1 <maxn oofEDCH -1></maxn 		E-DCH on Secondary uplink frequency – max 1 in this 3GPP release.	-	
>>>> Additional E- DCH FDD Setup Information	М		9.2.2.110	10-2-2-	-	
>> Addition				Used when	_	
	•	1	i			

				there exist additional E- DCH RLs in the current UE context		
>>>Additional E-DCH Cell Information Addition		1 <maxn oofEDCH -1></maxn 		E-DCH on Secondary uplink frequency – max 1 in this 3GPP release.	-	
>>>UL DPCH Information		1			-	
>>>> Uplink SIR Target	М		Uplink SIR 9.2.1.69		_	
>>>> Additional E-DCH RL Specific Information To Add	M		9.2.2.116		-	
>>>> Additional E-DCH FDD Information	0		9.2.2.112		_	
>>>> Multicell E-DCH Information	0		9.2.2.114		YES	ignore

Condition	Explanation
EDCHInfo	This IE shall be present if <i>E-DPCH Information</i> IE is present.

Range bound	Explanation
maxnoofRLs	Maximum number of radio links for one UE.
maxnoofHSDSCH-1	Maximum number of Secondary Serving HS-DSCH cells for one UE.
maxnoofEDCH-1	Maximum number of uplink frequencies -1 for E-DCH for one UE

9.1.6.2 TDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	М		9.2.1.59		_	.,
RL Information		1			YES	reject
>RL ID	М		9.2.1.49		_	
>C-ID	M		9.2.1.6		_	
>Frame Offset	M		9.2.1.30		ı	
>Diversity Control Field	M		9.2.1.20		-	
>Primary CCPCH RSCP	0		9.2.3.5		_	
>DL Time Slot ISCP Info	0		9.2.3.2D	Applicable to 3.84Mcps TDD and 7.68Mcps TDD only	-	
>DL Time Slot ISCP Info LCR	0		9.2.3.2F	Applicable to 1.28Mcps TDD only	YES	reject
>RL Specific DCH Information	0		9.2.1.49A		YES	ignore
>Delayed Activation	0		9.2.1.19Aa		YES	reject
>UL Synchronisation Parameters LCR		01		Mandatory for 1.28Mcps TDD. Not Applicable to 3.84Mcps TDD or 7.68Mcps TDD.	YES	reject
>>Uplink Synchronisation Step Size	М		9.2.3.13J		_	
>>Uplink Synchronisation Frequency	М		9.2.3.131		-	
> Primary CCPCH RSCP Delta	0		9.2.3.5a		YES	ignore
> Idle Interval Configuration Indicator	0		NULL	TDD only	YES	ignore
Permanent NAS UE Identity	0		9.2.1.73		YES	ignore
UL CCTrCH Information		0< maxno ofCCTr CHs >			EACH	notify
>CCTrCH ID	M		9.2.3.2		_	
>TDD TPC Uplink Step Size	0		9.2.3.10a	Applicable to 1.28Mcps TDD only	I	
DL CCTrCH Information		0< maxno ofCCTr CHs >			EACH	notify
>CCTrCH ID	М		9.2.3.2		_	
>TDD TPC Downlink Step Size	0		9.2.3.10		-	
HS-DSCH Information	0		HS-DSCH TDD Information 9.2.3.3aa		YES	reject
HS-PDSCH RL ID	0		RL ID 9.2.1.49		YES	reject
E-DCH Information		01		3.84Mcps TDD only	YES	reject
>E-PUCH Information	М		9.2.3.36	<u> </u>	_	

	T = -		1	1		I
>E-TFCS Information TDD	M		9.2.3.37		_	
>E-DCH MAC-d Flows	M		9.2.3.38		_	
Information TDD						
>E-DCH TDD Information	M		9.2.3.40		_	
E-DCH Serving RL	0		9.2.1.49	3.84Mcps	YES	reject
				TDD only		
E-DCH Information		01		7.68Mcps	YES	reject
7.68Mcps				TDD only		
>E-PUCH Information	M		9.2.3.36		-	
>E-TFCS Information TDD	M		9.2.3.37		-	
>E-DCH MAC-d Flows	M		9.2.3.38		_	
Information TDD						
>E-DCH TDD Information	М		9.2.3.51		_	
7.68Mcps						
E-DCH Information		01		1.28Mcps	YES	reject
1.28Mcps				TDD only		,
>E-PUCH Information LCR	М		9.2.3.36a	1	_	
>E-TFCS Information TDD	М		9.2.3.37		_	
>E-DCH MAC-d Flows	М		9.2.3.38		_	
Information TDD						
>E-DCH TDD Information	М		9.2.3.40a		_	
LCR						
Continuous Packet	0		9.2.3.61	1.28 Mcps	YES	reject
Connectivity DRX				TDD only		,
Information LCR						
HS-DSCH Semi-Persistent	0		9.2.3.64	1.28 Mcps	YES	reject
scheduling Information LCR				TDD only		,
E-DCH Semi-Persistent	0		9.2.3.66	1.28 Mcps	YES	reject
scheduling Information LCR				TDD only		,
DCH Measurement Type	0		9.2.3.76	1.28 Mcps	YES	reject
indicator				TDD only		,
Multi-Carrier E-DCH		01		Applicable	YES	reject
Information				for Multi-		,
				Carrier E-		
				DCH		
				Operation in		
				1.28 Mcps		
				TDD only		
>Multi-Carrier E-DCH	M		9.2.3.79	1.28 Mcps		
Transport Bearer Mode				TDD only		
LCR						
>Multi-Carrier E-DCH	M		9.2.3.77	1.28 Mcps	_	
Information LCR				TDD only		
MU-MIMO Indicator	0		9.2.3.82	1.28 Mcps	YES	reject
				TDD only		

Range bound	Explanation
maxnoofCCTrCHs	Maximum number of CCTrCH for one UE.

9.1.7 RADIO LINK ADDITION RESPONSE

FDD Message 9.1.7.1

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		-	10,000
RL Information Response	i i i	1 <maxnoof RLs-1></maxnoof 	0.2.1.00		EACH	ignore
>RL ID	М	-	9.2.1.49		_	
>RL Set ID	М		9.2.2.35		_	
>URA Information	0		9.2.1.70B		_	
>SAI	М		9.2.1.52		_	
>Cell GAI	0		9.2.1.5A		_	
>UTRAN Access Point Position	0		9.2.1.70A		_	
>Received Total Wide Band Power	М		9.2.2.35A		_	
>Not Used	0		NULL		_	
>DL Code Information	M		FDD DL Code Information 9.2.2.14A		YES	ignore
>CHOICE Diversity Indication	М				_	
>>Combining					_	
>>>RL ID	M		9.2.1.49	Reference RL ID	_	
>>>DCH Information Response	0		9.2.1.16A		YES	ignore
>>>E-DCH FDD Information Response >>Non Combining	0		9.2.2.4C		YES	ignore
>>>DCH Information	M		9.2.1.16A		_	
Response >>>E-DCH FDD	O		9.2.1.16A 9.2.2.4C			:
Information Response					YES	ignore
>SSDT Support Indicator	M		9.2.2.43		_	
>Minimum Uplink SIR	M		Uplink SIR 9.2.1.69		_	
>Maximum Uplink SIR	М		Uplink SIR 9.2.1.69		_	
>Closed Loop Timing Adjustment Mode	0		9.2.2.3A		_	
>Maximum Allowed UL Tx Power	M		9.2.1.35		_	
>Maximum DL TX Power	M		DL Power 9.2.1.21A		_	
>Minimum DL TX Power	М		DL Power 9.2.1.21A		_	
>Neighbouring UMTS Cell Information	0		9.2.1.41A		-	
>Neighbouring GSM Cell Information	0		9.2.1.41C		_	
>PC Preamble	M		9.2.2.27a		_	
>SRB Delay	M		9.2.2.39A		_	
>Primary CPICH Power	M		9.2.1.44		_	
>Cell GA Additional Shapes	0		9.2.1.5B		YES	ignore
>DL Power Balancing Activation Indicator	0		9.2.2.10B		YES	ignore
>HCS Prio	0	ļ	9.2.1.30N		YES	ignore
>Active MBMS Bearer		0 <maxnoof< td=""><td></td><td></td><td>GLOBAL</td><td>ignore</td></maxnoof<>			GLOBAL	ignore

IE/Group Name	Presence	Range	IE Type	Semantics	Criticality	Assigned
			and Reference	Description		Criticality
Service List		ActiveMBM S>				
>>TMGI	М	02	9.2.1.80		_	
>>Transmission Mode	0		9.2.1.81		_	
>>Preferred Frequency	0		UARFCN		_	
Layer			9.2.1.66			
>E-DCH RL Set ID	0		RL Set ID 9.2.2.35		YES	ignore
>E-DCH FDD DL Control Channel Information	0		9.2.2.4D		YES	ignore
>Initial DL DPCH Timing Adjustment	0		DL DPCH Timing Adjustment 9.2.2.9.A		YES	ignore
>F-DPCH Slot Format	0		9.2.2.85		YES	ignore
>Neighbouring E-UTRA Cell Information	0		9.2.1.41De		YES	ignore
>HS-DSCH Preconfiguration Info	0		9.2.2.99		YES	ignore
>Non-Serving RL Preconfiguration Info	0		9.2.2.125		YES	ignore
>Neighbouring UMTS Cell Information Extension	0		9.2.1.141		YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore
HS-DSCH Serving Cell Change Information	0		9.2.2.19g		YES	ignore
Response					\/=0	
E-DCH Serving Cell Change	0		9.2.2.19h		YES	ignore
Information Response MAC-hs Reset Indicator	0		9.2.1.34B		YES	ignore
Additional HS Cell Change	0	0 <maxnoof< td=""><td>9.2.1.346</td><td>For</td><td>EACH</td><td>ignore</td></maxnoof<>	9.2.1.346	For	EACH	ignore
Information Response		HSDSCH-1>		secondary serving HS- DSCH cell. Max 3 in this 3GPP release.		g
>HS-PDSCH RL ID	M		RL ID 9.2.1.49		_	
>HS-DSCH Secondary Serving Cell Change Information Response	M		9.2.2.19ga		_	
Additional E-DCH Cell Information Response RL Add		0 <maxnoof EDCH-1></maxnoof 		E-DCH on Secondary uplink frequency – max 1 in this 3GPP release.	EACH	ignore
>Additional E-DCH FDD Information Response	0		9.2.2.120		_	
>Additional E-DCH Serving Cell Change Information response	0		E-DCH Serving Cell Change Information Response 9.2.2.19h		-	

Range bound	Explanation
maxnoofRLs	Maximum number of radio links for one UE.
maxnoofActiveMBMS	Maximum number of MBMS bearer services that are active in parallel.
maxnoofHSDSCH-1	Maximum number of Secondary Serving HS-DSCH cells for one UE.
maxnoofEDCH-1	Maximum number of uplink frequencies -1 for E-DCH for one UE

300

9.1.7.2 TDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		-	reject
RL Information Response		01		Mandatory for 3.84Mcps TDD, not applicable to 1.28Mcps TDD or 7.68Mcps TDD	YES	ignore
>RL ID	M		9.2.1.49		_	
>URA Information	0		9.2.1.70B		_	
>SAI	M		9.2.1.52		_	
>Cell GAI	0		9.2.1.5A		_	
>UTRAN Access Point Position	0		9.2.1.70A		_	
>UL Time Slot ISCP Info	M		9.2.3.13D		_	
>Minimum Uplink SIR	M		Uplink SIR		_	
	1		9.2.1.69			
>Maximum Uplink SIR	М		Uplink SIR 9.2.1.69		_	
>Maximum Allowed UL Tx Power	М		9.2.1.35		_	
>Maximum DL TX Power	М		DL Power 9.2.1.21A		_	
>Minimum DL TX Power	М		DL Power 9.2.1.21A		_	
>PCCPCH Power	М		9.2.1.43		_	
>Timing Advance Applied	M		9.2.3.12A		_	
>Alpha Value	М		9.2.3.a		_	
>UL PhysCH SF Variation	М		9.2.3.13B		_	
>Synchronisation Configuration	М		9.2.3.7E		-	
>Secondary CCPCH Info TDD	0		9.2.3.7B		_	
>UL CCTrCH Information		0 <maxnoof CCTrCHs></maxnoof 		For DCH	GLOBAL	ignore
>>CCTrCH ID	М		9.2.3.2		_	
>>UL DPCH Information		01			YES	ignore
>>>Repetition Period	М		9.2.3.7		_	
>>>Repetition Length	M		9.2.3.6		_	
>>>TDD DPCH Offset	M		9.2.3.8A		_	
>>>UL Timeslot Information	М		9.2.3.13C		_	
>DL CCTrCH Information		0 <maxnoof CCTrCHs></maxnoof 		For DCH	GLOBAL	ignore
>>CCTrCH ID	М		9.2.3.2		_	
>>DL DPCH Information		01			YES	ignore
>>>Repetition Period	М		9.2.3.7		_	
>>>Repetition Length	M		9.2.3.6		_	
>>>TDD DPCH Offset	M		9.2.3.8A		_	
>>>DL Timeslot Information	M		9.2.3.2C		-	
>>CCTrCH Maximum DL TX Power	0		DL Power 9.2.1.21A	Maximum allowed power on DPCH	YES	ignore
>>CCTrCH Minimum DL TX Power	0		DL Power 9.2.1.21A	Minimum allowed	YES	ignore

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
			Reference	power on DPCH		
>DCH Information		01		респ	_	
>>CHOICE Diversity Indication	М	01			_	
>>>Combining					_	
>>>>RL ID	М		9.2.1.49	Reference RL	_	
>>>>DCH Information Response	0		9.2.1.16A		YES	ignore
>>>Non Combining					_	
>>>>DCH Information Response	M		9.2.1.16A		_	
>DSCH Information Response		0 <maxnoof DSCHs></maxnoof 			GLOBAL	ignore
>>DSCH ID	М		9.2.3.3ae		_	
>>Transport Format Management	М		9.2.3.13		_	
>>DSCH Flow Control Information	М		9.2.3.3ag		_	
>>CHOICE Diversity Indication	0				_	
>>>Non Combining			0.040		_	
>>>>Binding ID	0		9.2.1.3		_	
>>>>Transport Layer Address >USCH Information	0		9.2.1.62		-	
Response		0 <maxnoof USCHs></maxnoof 			GLOBAL	ignore
>>USCH ID	M		9.2.3.14		_	
>>Transport Format Management	М		9.2.3.13		_	
>>CHOICE Diversity Indication	0				_	
>>>Non Combining					_	
>>>Binding ID	0		9.2.1.3		_	
>>>>Transport Layer Address	0		9.2.1.62		_	
>Neighbouring UMTS Cell Information	0		9.2.1.41A		-	
>Neighbouring GSM Cell Information	0		9.2.1.41C		_	
>Cell GA Additional Shapes	0		9.2.1.5B		YES	ignore
>HCS Prio	0		9.2.1.30N		YES	ignore
>Neighbouring E-UTRA Cell Information	0		9.2.1.41De		YES	ignore
>Neighbouring UMTS Cell Information Extension	0		9.2.1.141		YES	ignore
Criticality Diagnostics	0	1	9.2.1.13		YES	ignore
RL Information Response LCR		01		Mandatory for 1.28Mcps TDD, not applicable to 3.84Mcps TDD or 7.68Mcps TDD	YES	ignore
>RL ID	M	ļ	9.2.1.49		_	
>URA Information	M	ļ	9.2.1.70B			
>SAI	М		9.2.1.52		_	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>Cell GAI	0		9.2.1.5A		_	
>UTRAN Access Point Position	0		9.2.1.70A		_	
>UL Time Slot ISCP Info LCR	М		9.2.3.13H		_	
>Maximum Uplink SIR	М		Uplink SIR 9.2.1.69		_	
>Minimum Uplink SIR	М		Uplink SIR 9.2.1.69		_	
>PCCPCH Power	М		9.2.1.43		_	
>Maximum Allowed UL Tx Power	М		9.2.1.35		-	
>Maximum DL TX Power	М		DL Power 9.2.1.21A		_	
>Minimum DL TX Power	М		DL Power 9.2.1.21A		_	
>Alpha Value	М		9.2.3.a		_	
>UL PhysCH SF Variation	M		9.2.3.13B		_	
>Synchronisation Configuration	М		9.2.3.7E		-	
>Secondary CCPCH Info TDD LCR	0		9.2.3.7F		_	
>UL CCTrCH Information LCR		0 <maxnoof CCTrCHsLC R></maxnoof 		For DCH	GLOBAL	ignore
>>CCTrCH ID	М		9.2.3.2		_	
>>UL DPCH Information LCR		01			YES	ignore
>>>Repetition Period	M		9.2.3.7		_	
>>>Repetition Length	М		9.2.3.6		_	
>>>TDD DPCH Offset	M		9.2.3.8A		_	
>>>UL Timeslot Information LCR	М		9.2.3.13G		_	
>DL CCTrCH Information LCR		0 <maxnoof CCTrCHsLC R></maxnoof 		For DCH	GLOBAL	ignore
>>CCTrCH ID	M		9.2.3.2		_	
>>DL DPCH		01			YES	ignore
Information LCR						
>>>Repetition Period	M		9.2.3.7		_	
>>>Repetition Length	M		9.2.3.6 9.2.3.8A		_	
>>>TDD DPCH Offset >>>DL Timeslot	M		9.2.3.8A 9.2.3.2E	1	_	
Information LCR >>>TSTD Indicator	M		9.2.3.13E		_	
>>> 151D Indicator >DCH Information	M		9.2.3.13E 9.2.1.16A	1	_	
Response			5.2.1.10A			
>DSCH Information Response LCR		0 <maxnoof DSCHsLCR</maxnoof 			GLOBAL	ignore
>>DSCH ID	М		9.2.3.3ae		_	
>>DSCH Flow Control Information	M		9.2.3.3ag		_	
>>Binding ID	0		9.2.1.3		_	
>>Transport Layer Address	0		9.2.1.62		_	
>>Transport Format Management	М		9.2.3.13		_	
>USCH Information Response LCR		0 <maxnoof USCHsLCR ></maxnoof 			GLOBAL	ignore
>>USCH ID	М		9.2.3.14		_	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>>Transport Format Management	М		9.2.3.13		_	
>>CHOICE Diversity Indication	0				-	
>>>Non Combining					_	
>>>Binding ID	0		9.2.1.3		_	
>>>Transport	Ö		9.2.1.62		_	
Layer Address			0.2.1.02			
>Neighbouring UMTS Cell Information	0		9.2.1.41A		_	
>Neighbouring GSM Cell Information	0		9.2.1.41C		_	
>Cell GA Additional	0		9.2.1.5B		YES	ignore
Shapes						
>HCS Prio	0		9.2.1.30N		YES	ignore
>Uplink Timing Advance	M		9.2.3.13K		YES	ignore
Control LCR >PowerControl GAP	0		INTEGER (1255)	Unit: number of subframes Applicable to 1.28Mcps TDD only	YES	ignore
>UARFCN	0		9.2.1.66	Applicable to 1.28Mcps TDD only. Mandatory for 1.28Mcps TDD when using multiple frequencies. Corresponds to Nt □3GPP TS 25.105□.	YES	ignore
>Neighbouring E-UTRA Cell Information	0		9.2.1.41De		YES	ignore
>Idle Interval Information	0		9.2.3.60	TDD only	YES	ignore
>Neighbouring UMTS Cell Information Extension	0		9.2.1.141		YES	ignore
Active MBMS Bearer Service List		0 <maxnoof ActiveMBM S></maxnoof 			GLOBAL	ignore
>TMGI	М		9.2.1.80		_	
>Transmission Mode	0		9.2.1.81		_	
>Preferred Frequency Layer	0		UARFCN 9.2.1.66		_	
HS-DSCH Information Response	0		HS-DSCH TDD Information Response 9.2.3.3ab		YES	ignore
HS-DSCH-RNTI	0		9.2.1.30P		YES	ignore
RL Information Response 7.68Mcps		01		Mandatory for 7.68Mcps TDD, not applicable to 1.28Mcps TDD or 3.84Mcps TDD	YES	ignore
>RL ID	М		9.2.1.49		_	
>URA Information	0		9.2.1.70B			
>SAI	M		9.2.1.52		_	
>Cell GAI	0		9.2.1.5A		_	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>UTRAN Access Point	0		9.2.1.70A		_	
Position >UL Time Slot ISCP Info	M		9.2.3.13D		_	
>Minimum Uplink SIR	M		Uplink SIR		_	
>Maximum Uplink SIR	M		9.2.1.69 Uplink SIR		_	
>Maximum Allowed UL Tx	M		9.2.1.69 9.2.1.35		_	
Power >Maximum DL TX Power	M		DL Power		_	
>Minimum DL TX Power	M		9.2.1.21A DL Power		_	
>PCCPCH Power	M		9.2.1.21A 9.2.1.43		_	
>Timing Advance Applied	M		9.2.3.12A		_	
>Alpha Value	М		9.2.3.a		_	
>UL PhysCH SF Variation	М		9.2.3.13B		_	
>Synchronisation Configuration	M		9.2.3.7E		_	
>Secondary CCPCH Info 7.68Mcps TDD	0		9.2.3.22		_	
>UL CCTrCH Information 7.68 Mcps		0 <maxnoof CCTrCHs></maxnoof 		For DCH	GLOBAL	ignore
>>CCTrCH ID	М	001101101	9.2.3.2		_	
>>UL DPCH	141	01	0.2.0.2		YES	ignore
Information 7.68 Mcps		01			123	ignore
>>>Repetition Period	М		9.2.3.7		_	
>>>Repetition Length	M		9.2.3.6			
>>>TDD DPCH Offset	M		9.2.3.8A		_	
>>>UL Timeslot	M				_	
Information 7.68Mcps	IVI		9.2.3.26	F 8011	-	
>DL CCTrCH Information 7.68 Mcps		0 <maxnoof CCTrCHs></maxnoof 		For DCH	GLOBAL	ignore
>>CCTrCH ID	M		9.2.3.2		_	
>>DL DPCH		01			YES	ignore
Information 7.68 Mcps						.9
>>>Repetition Period	М		9.2.3.7		_	
>>>Repetition Length	M		9.2.3.6		_	
>>>TDD DPCH Offset	M		9.2.3.8A		_	
>>>DL Timeslot	M		9.2.3.28		_	
Information 7.68Mcps	IVI		9.2.3.20		_	
>>CCTrCH Maximum DL	0		DL Power	Maximum		
TX Power			9.2.1.21A	allowed power on	_	
OOT OUT I		1	DI D	DPCH		
>>CCTrCH Minimum DL TX Power	0		DL Power 9.2.1.21A	Minimum allowed power on DPCH	_	
>DCH Information		01			_	
>>CHOICE Diversity Indication	М	-			-	
>>>Combining	+	 		1	_	
>>>RL ID	M		9.2.1.49	Reference	_	
				Reference	VEO	: aua
>>>DCH Information Response	0		9.2.1.16A		YES	ignore
>>Non Combining	+	 		1		
>>>NON Combining	M	1	9.2.1.16A	+	_	
Information	IVI		3.∠.1.10A		_	
Response				-	01.05	
>DSCH Information		0			GLOBAL	ignore
Response 7.68 Mcps		<maxnoof< td=""><td></td><td></td><td></td><td></td></maxnoof<>				

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
		DSCHs>	Reference			
>>DSCH ID	М	2001101	9.2.3.3ae		_	
>>Transport Format	M		9.2.3.13		_	
Management						
>>DSCH Flow Control	М		9.2.3.3ag		_	
Information						
>>CHOICE Diversity	0				_	
Indication						
>>>Non Combining					_	
>>>>Binding ID	0		9.2.1.3		_	
>>>>Transport	Ō		9.2.1.62		_	
Layer Address						
>USCH Information Response 7.68 Mcps		0 <maxnoof USCHs></maxnoof 			GLOBAL	ignore
>>USCH ID	М		9.2.3.14		_	
>>Transport Format	M		9.2.3.13		_	
Management	1					
>>CHOICE Diversity	0				_	
Indication						
>>>Non Combining					_	
>>>Binding ID	0		9.2.1.3		_	
>>>>Transport Layer	0		9.2.1.62		_	
Address			0.202			
>Neighbouring UMTS Cell Information	0		9.2.1.41A		-	
>Neighbouring GSM Cell Information	0		9.2.1.41C		_	
>Cell GA Additional Shapes	0		9.2.1.5B		_	
>HCS Prio	0		9.2.1.30N		_	
>Neighbouring E-UTRA Cell Information	0		9.2.1.41De		YES	ignore
>Neighbouring UMTS Cell Information Extension	0		9.2.1.141		YES	ignore
E-DCH Information Response	0		E-DCH TDD Information Response 9.2.3.41	3.84Mcps TDD only	YES	ignore
E-DCH Information Response 7.68Mcps	0		E-DCH TDD Information Response 7.68Mcps 9.2.3.52	7.68Mcps TDD only	YES	ignore
E-DCH Information Response 1.28Mcps	0		E-DCH TDD Information Response 1.28Mcps 9.2.3.41a	1.28Mcps TDD only	YES	ignore
Continuous Packet Connectivity DRX Information Response LCR	0		9.2.3.63	1.28 Mcps TDD only	YES	ignore
HS-DSCH Semi-Persistent scheduling Information Response LCR	0		9.2.3.68	1.28 Mcps TDD only	YES	ignore
E-DCH Semi-Persistent scheduling Information Response LCR	0		9.2.3.69	1.28 Mcps TDD only	YES	ignore
DCH Measurement Occasion Information	0		9.2.3.75	1.28 Mcps TDD only	YES	reject
Multi-Carrier E-DCH	0		9.2.3.78	1.28 Mcps	YES	ignore

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Information Response LCR				TDD only		
MU-MIMO Information	0		9.2.3.81	1.28 Mcps TDD only	YES	reject

Range Bound	Explanation
maxnoofDSCHs	Maximum number of DSCHs for one UE for 3.84Mcps TDD.
maxnoofUSCHs	Maximum number of USCHs for one UE for 3.84Mcps TDD.
maxnoofCCTrCHs	Maximum number of CCTrCHs for one UE for 3.84Mcps TDD.
maxnoofDSCHsLCR	Maximum number of DSCHs for one UE for 1.28Mcps TDD.
maxnoofUSCHsLCR	Maximum number of USCHs for one UE for 1.28Mcps TDD.
maxnoofCCTrCHsLCR	Maximum number of CCTrCH for one UE for 1.28Mcps TDD.
maxnoofActiveMBMS	Maximum number of MBMS bearer services that are active in parallel.

9.1.8 RADIO LINK ADDITION FAILURE

9.1.8.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
CHOICE Cause Level	M				YES	ignore
>General					_	
>>Cause	M		9.2.1.5		_	
>RL Specific					_	
>>Unsuccessful RL		1 <maxnoof< td=""><td></td><td></td><td>EACH</td><td>ignore</td></maxnoof<>			EACH	ignore
Information Response		RLs-1>				
>>>RL ID	M		9.2.1.49		_	
>>>Cause	M		9.2.1.5		_	
>>Successful RL Information Response		0 <maxnoof RLs-2></maxnoof 			EACH	ignore
>>>RL ID	M		9.2.1.49		_	
>>>RL Set ID	M		9.2.2.35		_	
>>>URA Information	0		9.2.1.70B		_	
>>>SAI	M		9.2.1.52		_	
>>>Cell GAI	0		9.2.1.5A		_	
>>>UTRAN Access Point Position	0		9.2.1.70A		_	
>>>Received Total Wide Band Power	M		9.2.2.35A		_	
>>>Not Used	0		NULL		_	
>>>DL Code	M		FDD DL		YES	ignore
Information			Code Information 9.2.2.14A			
>>>CHOICE Diversity Indication	М				_	
>>>Combining					_	
>>>>RL ID	M		9.2.1.49	Reference RL ID	_	
>>>>DCH Information Response	0		9.2.1.16A		YES	ignore
>>>>E-DCH FDD Information Response	0		9.2.2.4C		YES	ignore
>>>Non Combining					_	
>>>>DCH Information Response	M		9.2.1.16A		_	
>>>>E-DCH FDD Information Response	0		9.2.2.4C		YES	ignore
>>>SSDT Support Indicator	М		9.2.2.43		-	
>>>Minimum Uplink SIR	М		Uplink SIR 9.2.1.69		_	
>>>Maximum Uplink SIR	М		Uplink SIR 9.2.1.69		_	
>>>Closed Loop Timing Adjustment Mode	0		9.2.2.3A		_	
>>>Maximum Allowed UL Tx Power	М		9.2.1.35		_	
>>>Maximum DL TX Power	М		DL Power 9.2.1.21A		_	
>>>Minimum DL TX Power	М		DL Power 9.2.1.21A		_	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>>>Neighbouring	0		9.2.1.41A		-	
UMTS Cell Information >>>Neighbouring GSM	0		9.2.1.41C			
Cell Information			9.2.1.410		_	
>>>Primary CPICH	M		9.2.1.44		_	
Power						
>>>PC Preamble	M		9.2.2.27a		_	
>>>SRB Delay >>>Cell GA Additional	O		9.2.2.39A 9.2.1.5B		YES	ignore
Shapes			0.2.1.00		120	ignore
>>>DL Power	0		9.2.2.10B		YES	ignore
Balancing Activation						
Indicator >>>HCS Prio	0		9.2.1.30N		YES	ignore
>>>Active MBMS	0	0 <maxnoof< td=""><td>9.2.1.30N</td><td></td><td>GLOBAL</td><td>ignore</td></maxnoof<>	9.2.1.30N		GLOBAL	ignore
Bearer Service List		ActiveMBM S>			0205/12	ignore
>>>>TMGI	M		9.2.1.80		_	
>>>>Transmission	0		9.2.1.81		_	
Mode >>>Preferred	0		UARFCN			
Frequency Layer			9.2.1.66		_	
>>>E-DCH RL Set ID	0		RL Set ID		YES	ignore
			9.2.2.35			
>>>E-DCH FDD DL	0		9.2.2.4D		YES	ignore
Control Channel Information						
>>>Initial DL DPCH	0		DL DPCH		YES	ignore
Timing Adjustment			Timing			ignore
			Adjustment 9.2.2.9.A			
>>>Neighbouring E- UTRA Cell Information	0		9.2.1.41De		YES	ignore
>>>HS-DSCH Preconfiguration Info	0		9.2.2.99		YES	ignore
>>>F-DPCH Slot	0		9.2.2.85		YES	ignore
Format						3
>>>Non-Serving RL	0		9.2.2.125		YES	ignore
Preconfiguration Info	0		9.2.1.141		YES	ignoro
>>>Neighbouring UMTS Cell Information Extension			9.2.1.141		TES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore
HS-DSCH Serving Cell	0		9.2.2.19g		YES	Ignore
Change Information						
Response E-DCH Serving Cell Change	0		9.2.2.19h		YES	Ignore
Information Response			3.2.2.1311		123	ignore
Additional HS Cell Change		0 <maxnoof< td=""><td></td><td>For</td><td>EACH</td><td>Ignore</td></maxnoof<>		For	EACH	Ignore
Information Response		HSDSCH-1>		secondary serving HS- DSCH cell. Max 3 in this 3GPP release.		
>HS-PDSCH RL ID	М		RL ID 9.2.1.49		-	
>HS-DSCH Secondary Serving Cell Change Information Response	М		9.2.2.19ga		-	
MAC-hs Reset Indicator	0		9.2.1.34B		YES	ignore
Additional E-DCH Cell		0 <maxnoof< td=""><td></td><td>E-DCH on</td><td>EACH</td><td>ignore</td></maxnoof<>		E-DCH on	EACH	ignore
Information Response RL Add		EDCH-1>		Secondary uplink		

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
				frequency – max 1 in this 3GPP release.		
>Additional E-DCH FDD Information Response	0		9.2.2.120		_	
>Additional E-DCH Serving Cell Change Information response	0		E-DCH Serving Cell Change Information Response 9.2.2.19h		-	

Range bound	Explanation
maxnoofRLs	Maximum number of radio links for one UE.
maxnoofActiveMBMS	Maximum number of MBMS bearer services that are active in parallel.
maxnoofHSDSCH-1	Maximum number of Secondary Serving HS-DSCH cells for one UE.
maxnoofEDCH-1	Maximum number of uplink frequencies -1 for E-DCH for one UE

9.1.8.2 TDD Message

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
			Reference			
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
CHOICE Cause Level	M				YES	ignore
>General					-	
>>Cause	M		9.2.1.5		-	
>RL Specific					-	
>>Unsuccessful RL		1			YES	ignore
Information Response						
>>>RL ID	M		9.2.1.49		_	
>>>Cause	M		9.2.1.5		-	
Criticality Diagnostics	0		9.2.1.13		YES	ignore

9.1.9 RADIO LINK DELETION REQUEST

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		ı	
RL Information		1 <maxno ofRLs></maxno 			EACH	notify
>RL ID	M		9.2.1.49		_	

Range bound	Explanation			
maxnoofRLs	Maximum number of radio links for one UE			

9.1.10 RADIO LINK DELETION RESPONSE

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
Criticality Diagnostics	0		9.2.1.13		YES	ignore

9.1.11 RADIO LINK RECONFIGURATION PREPARE

FDD Message 9.1.11.1

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
Managa Tuna	M		Reference 9.2.1.40		YES	raigat
Message Type Transaction ID	M				150	reject
Allowed Queuing Time	O		9.2.1.59 9.2.1.2		YES	roiget
UL DPCH Information	0	0.1	9.2.1.2		YES	reject
		01	9.2.2.53		150	reject
>UL Scrambling Code >UL SIR Target	0		Uplink SIR			
•			9.2.1.69		_	
>Min UL Channelisation Code Length	0		9.2.2.25		_	
>Max Number of UL DPDCHs	C – CodeLen		9.2.2.24		_	
>Puncture Limit	0		9.2.1.46	For the UL.	_	
>TFCS	0		9.2.1.63	TFCS for the UL.	_	
>UL DPCCH Slot Format	0		9.2.2.52	OL.	_	
>Diversity Mode	0		9.2.2.8		_	
>Not Used	0		NULL		_	
>Not Used	0		NULL		_	
>UL DPDCH Indicator For E-DCH Operation	0		9.2.2.52A		YES	reject
DL DPCH Information		01			YES	reject
>TFCS	0	01	9.2.1.63	TFCS for the	163	reject
				DL.	_	
>DL DPCH Slot Format	0		9.2.2.9		_	
>Number of DL Channelisation Codes	0		9.2.2.26A		_	
>TFCI Signalling Mode	0		9.2.2.46		_	
>TFCI Presence	C- SlotFormat		9.2.1.55		_	
>Multiplexing Position	0		9.2.2.26		_	
>Limited Power Increase	0		9.2.2.21A		_	
>DL DPCH Power Information		01			YES	reject
>>Power Offset Information		1			_	
>>>PO1	M		Power	Power offset	_	
>>>FO1	IVI		Offset	for the TFCI	_	
>>>PO2	M		9.2.2.30 Power	bits Power offset		
>>>PO2	IVI		Offset	for the TPC	_	
>>>PO3	M		9.2.2.30 Power	bits Power offset		
>>>PU3	IVI		Offset 9.2.2.30	for the pilot	_	
>>FDD TPC Downlink Step Size	M		9.2.2.16	DILO	_	
>>Inner Loop DL PC Status	М		9.2.2.21a		_	
DCHs To Modify	0		FDD DCHs		YES	reject
			To Modify 9.2.2.13C		0	10,000
DCHs To Add	0		DCH FDD Information		YES	reject
			9.2.2.4A			
DCHs To Delete		0 <maxnoof DCHs></maxnoof 			GLOBAL	reject

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>DCH ID	M		9.2.1.16		_	
RL Information		0 <maxnoof RLs></maxnoof 			EACH	reject
>RL ID	M		9.2.1.49		_	
>Not Used	0		NULL		_	
>Not Used	0		NULL		_	
>Transmit Diversity Indicator	C – Diversity mode		9.2.2.48		_	
>DL Reference Power	0		DL Power 9.2.1.21A	Power on DPCH	YES	ignore
>RL Specific DCH Information	0		9.2.1.49A		YES	ignore
>DL DPCH Timing Adjustment	0		9.2.2.9A	Required RL Timing Adjustment	YES	reject
>Phase Reference Update Indicator	0		9.2.2.27B		YES	ignore
>RL specific E-DCH Information	0		9.2.2.35a		YES	reject
>E-DCH RL Indication	0		9.2.2.4E		YES	reject
>HS-DSCH Preconfiguration Setup	0		9.2.2.100		YES	ignore
>Non-Serving RL Preconfiguration Setup	0		9.2.2.124		YES	ignore
>Non-Serving RL Preconfiguration Removal	0		Non- Serving RL Preconfigu ration Setup 9.2.2.124		YES	ignore
Transmission Gap Pattern Sequence Information	0		9.2.2.47A		YES	reject
HS-DSCH Information	0		HS-DSCH FDD Information 9.2.2.19a		YES	reject
HS-DSCH Information To Modify	0		9.2.1.30Q		YES	reject
HS-DSCH MAC-d Flows To Add	0		HS-DSCH MAC-d Flows Information 9.2.1.300A		YES	reject
HS-DSCH MAC-d Flows To Delete	0		9.2.1.30OB		YES	reject
HS-PDSCH RL ID	0		RL ID 9.2.1.49		YES	reject
E-DPCH Information		01	5.2.11.10		YES	reject
>Maximum Set of E- DPDCHs	0	J	9.2.2.24e		-	. 5,550
>Puncture Limit	0		9.2.1.46		_	
>E-TFCS Information	0		9.2.2.4G		_	
>E-TTI	0		9.2.2.4J		_	
>E-DPCCH Power Offset	0		9.2.2.4K		_	
>E-RGCH 2-Index-Step Threshold	0		9.2.2.64		-	
>E-RGCH 3-Index-Step Threshold	0		9.2.2.65		_	
>HARQ Info for E-DCH	0		9.2.2.66		_	
>HS-DSCH Configured Indicator	0		9.2.2.19C		_	
> Minimum Reduced E-	0		9.2.2.102		YES	ignore

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
DPDCH Gain Factor			11010101100			
E-DCH FDD Information	0		9.2.2.4B		YES	reject
E-DCH FDD Information to	0		9.2.2.4F		YES	reject
Modify						_
E-DCH MAC-d Flows to Add	0		E-DCH MAC-d flows Information 9.2.2.4MC		YES	reject
E-DCH MAC-d Flows to Delete	0		9.2.1.90		YES	reject
Serving E-DCH RL	0		9.2.2.38C		YES	reject
F-DPCH Information		01	0.2.2.000		YES	reject
>Power Offset		1			-	10,000
Information		,				
>>PO2	М		Power Offset 9.2.2.30	This IE shall be ignored by DRNS.	_	
>FDD TPC Downlink Step Size	М		9.2.2.16		_	
>Limited Power Increase	М		9.2.2.21A		_	
>Inner Loop DL PC Status	М		9.2.2.21a		_	
>F-DPCH Slot Format Support Request	0		9.2.2.86		YES	reject
>F-DPCH Slot Format	0		9.2.2.85		YES	Ignore
Fast Reconfiguration Mode	0		9.2.2.70		YES	ignore
CPC Information		01	0.2.2.7		YES	reject
>Continuous Packet Connectivity DTX-DRX Information	0	01	9.2.2.72		-	10,000
>Continuous Packet Connectivity DTX-DRX Information To Modify	0		9.2.2.73		-	
>Continuous Packet Connectivity HS-SCCH less Information	0		9.2.2.74		-	
>Continuous Packet Connectivity HS-SCCH less Deactivate Indicator	0		9.2.2.75A		YES	reject
Additional HS Cell Information RL Reconf Prep		0 <maxnoof HSDSCH-1></maxnoof 		For secondary serving HS-DSCH cell. Max 3 in this 3GPP release.	EACH	reject
>HS-PDSCH RL ID	M		RL ID 9.2.1.49		_	
>C-ID	0		9.2.1.6		_	
>HS-DSCH FDD	0		9.2.2.19aa		_	
Secondary Serving Information						
>HS-DSCH FDD Secondary Serving Information To Modify	0		9.2.2.19bb		-	
>HS-DSCH Secondary Serving Remove	0		NULL		_	
UE Aggregate Maximum Bit Rate	0		9.2.1.137		YES	ignore
Additional E-DCH Cell Information RL Reconf Prep		01		For E-DCH on multiple frequencies in this	YES	reject

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
			Reference	55110		
>CHOICE Setup, Configuration Change or Removal of E-DCH On Secondary UL Frequency	М			DRNS.	YES	reject
>>Setup >>>Multicell E-DCH	М		9.2.2.113	Used when RLs on the secondary UL frequency does not exist or is not configured with E-DCH in the current UE context	-	
Transport Bearer Mode	IVI		9.2.2.113		_	
>>>Additional E- DCH Cell Information Setup		1 <maxnoof EDCH-1></maxnoof 		E-DCH on Secondary uplink frequency – max 1 in this 3GPP release.	1	
>>>>Additional E- DCH FDD Setup Information	М		9.2.2.110		-	
>>Configuration Change		1 emaypoot		Used when RLs with additional E-DCH on the secondary UL frequency exist in the current UE context and the configuration is modified (adding new RLs or modification of existing RLs)	-	
>>>Additional E- DCH Cell Information Configuration Change		1 <maxnoof EDCH-1></maxnoof 		E-DCH on Secondary uplink frequency – max 1 in this 3GPP release.	_	
>>>>Additional E- DCH Configuration Change Information	М		9.2.2.111		_	
>>Removal				Used when all RLs on the indicated secondary UL	_	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
				frequency is removed.		
>>>Additional E- DCH Cell Information Removal		1 <maxnoof EDCH-1></maxnoof 		E-DCH on Secondary uplink frequency – max 1 in this 3GPP release.	-	
>>>RL on Secondary UL Frequency	M		ENUMERA TED (Remove,)	Removal of all RL on secondary UL frequency	_	

Condition	Explanation
CodeLen	The IE shall be present only if the Min UL
	Channelisation Code length IE equals to 4.
SlotFormat	The IE shall only be present if the DL DPCH Slot
	Format IE is equal to any of the values from 12 to 16.
Diversity mode	The IE shall be present if <i>Diversity Mode</i> IE is present in the <i>UL DPCH Information</i> IE and is not equal to
	"none".

Range bound	Explanation
maxnoofDCHs	Maximum number of DCHs for a UE.
maxnoofRLs	Maximum number of RLs for a UE.
maxnoofHSDSCH-1	Maximum number of Secondary Serving HS-DSCH cells for one UE.
maxnoofEDCH-1	Maximum number of uplink frequencies -1 for E-DCH for one UE

9.1.11.2 TDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	М		9.2.1.59		_	-
Allowed Queuing Time	0		9.2.1.2		YES	reject
UL CCTrCH To Add		0 <maxn oofCCTr CHs></maxn 		For DCH and USCH	EACH	notify
>CCTrCH ID	M		9.2.3.2		_	
>TFCS	M		9.2.1.63	For the UL.	_	
>TFCI Coding	M		9.2.3.11		_	
>Puncture Limit	M		9.2.1.46		_	
>UL SIR Target	0		Uplink SIR 9.2.1.69	Mandatory for 1.28Mcps TDD; not applicable to 3.84Mcps TDD or 7.68Mcps TDD	YES	reject
>TDD TPC Uplink Step Size	0		9.2.3.10a	Mandatory for 1.28Mcps TDD, not applicable to 3.84Mcps TDD or 7.68Mcps TDD	YES	reject
UL CCTrCH To Modify		0 <maxn oofCCTr CHs></maxn 			EACH	notify
>CCTrCH ID	М		9.2.3.2		_	
>TFCS	0		9.2.1.63	For the UL.	_	
>TFCI Coding	0		9.2.3.11		_	
>Puncture Limit	0		9.2.1.46		_	
>UL SIR Target	0		Uplink SIR 9.2.1.69	Applicable to 1.28Mcps TDD only	YES	reject
>TDD TPC Uplink Step Size	0		9.2.3.10a	Applicable to 1.28Mcps TDD only	YES	reject
UL CCTrCH to Delete		0 <maxn oofCCTr CHs></maxn 			EACH	notify
>CCTrCH ID	М		9.2.3.2		_	
DL CCTrCH To Add		0 <maxn oofCCTr CHs></maxn 		For DCH and DSCH	EACH	notify
>CCTrCH ID	М		9.2.3.2		_	
>TFCS	М		9.2.1.63	For the DL.	_	
>TFCI Coding	M		9.2.3.11		_	
>Puncture Limit	M		9.2.1.46		_	
>TPC CCTrCH List		0 <maxn oCCTrC Hs></maxn 		List of uplink CCTrCH which provide TPC	_	
>>TPC CCTrCH ID	М		9.2.3.2		_	
>TDD TPC Downlink Step Size	0		9.2.3.10		YES	reject
DL CCTrCH To Modify		0 <maxn oofCCTr CHs></maxn 			EACH	notify

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>CCTrCH ID	N 4		9.2.3.2			
>TFCS	M		9.2.3.2	Courth o DI	_	
	0		9.2.1.63	For the DL.	_	
>TFCI Coding >Puncture Limit	0		9.2.3.11		_	
>TPC CCTrCH List		0 <maxn oCCTrC Hs></maxn 		List of uplink CCTrCH which provide TPC	_ _	
>>TPC CCTrCH ID	M		9.2.3.2		_	
>TDD TPC Downlink Step Size	0		9.2.3.10		YES	reject
DL CCTrCH to Delete		0 <maxn oofCCTr CHs></maxn 			EACH	notify
>CCTrCH ID	M		9.2.3.2		_	
DCHs To Modify	0		TDD DCHs To Modify 9.2.3.8B		YES	reject
DCHs To Add	0		DCH TDD Information 9.2.3.2A		YES	reject
DCHs to Delete		0 <maxn oofDCHs ></maxn 			GLOBAL	reject
>DCH ID	M		9.2.1.16			
DSCHs To Modify		0 <maxn oofDSCH s></maxn 			GLOBAL	reject
>DSCH ID	M		9.2.3.3ae		_	
>CCTrCH ID	0		9.2.3.2	DL CCTrCH in which the DSCH is mapped.	_	
>TrCH Source Statistics Descriptor	0		9.2.1.65		_	
>Transport Format Set	0		9.2.1.64		_	
>Allocation/Retention Priority	0		9.2.1.1		_	
>Scheduling Priority Indicator	0		9.2.1.51A		_	
>BLER	0		9.2.1.4		_	
>Transport Bearer Request Indicator	М		9.2.1.61		_	
>Traffic Class	0		9.2.1.58A		YES	ignore
>Binding ID	0		9.2.1.3	Shall be ignored if bearer establishment with ALCAP.	YES	ignore
>Transport Layer Address	0		9.2.1.62	Shall be ignored if bearer establishment with ALCAP.	YES	ignore
>TNL QoS	0		9.2.1.56A	Shall be ignored if bearer establishment with ALCAP.	YES	ignore
DSCHs To Add	0		DSCH TDD Information 9.2.3.3a		YES	reject

IE/Group Name	Presence	Range	IE Type	Semantics	Criticality	Assigned
			and Reference	Description		Criticality
DSCHs to Delete		0 <maxn oofDSCH s></maxn 			GLOBAL	reject
>DSCH ID	M		9.2.3.3ae		_	
USCHs To Modify		0 <maxn oofUSCH s></maxn 			GLOBAL	reject
>USCH ID	M		9.2.3.14		_	
>CCTrCH ID	0		9.2.3.2	UL CCTrCH in which the USCH is mapped.	_	
>TrCH Source Statistics Descriptor	0		9.2.1.65		_	
>Transport Format Set	0		9.2.1.64		_	
>Allocation/Retention Priority	0		9.2.1.1		_	
>Scheduling Priority Indicator	0		9.2.1.51A		_	
>BLER	0		9.2.1.4		_	
>Transport Bearer Request Indicator	M		9.2.1.61		_	
>RB Info		0 <maxn oofRB></maxn 		All Radio Bearers using this USCH	_	
>>RB Identity	M		9.2.3.5B		_	
>Traffic class	0		9.2.1.58A		YES	ignore
>Binding ID	0		9.2.1.3	Shall be ignored if bearer establishment with ALCAP.	YES	ignore
>Transport Layer Address	0		9.2.1.62	Shall be ignored if bearer establishment with ALCAP.	YES	ignore
>TNL QoS	0		9.2.1.56A		YES	ignore

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
USCHs To Add	0		USCH Information 9.2.3.15		YES	reject
USCHs to Delete		0 <maxn oofUSCH s></maxn 			GLOBAL	reject
>USCH ID	М		9.2.3.14		_	
Primary CCPCH RSCP	0		9.2.3.5	A l' l- l	YES	ignore
DL Time Slot ISCP Info	0		9.2.3.2D	Applicable to 3.84Mcps TDD and 7.68Mcps TDD only	YES	ignore
DL Time Slot ISCP Info LCR	0		9.2.3.2F	Applicable to 1.28Mcps TDD only	YES	ignore
HS-DSCH Information	0		HS-DSCH TDD Information 9.2.3.3aa		YES	reject
HS-DSCH Information To Modify	0		9.2.1.30Q		YES	reject
HS-DSCH MAC-d Flows To Add	0		HS-DSCH MAC-d Flows Information 9.2.1.30OA		YES	reject
HS-DSCH MAC-d Flows To Delete	0		9.2.1.30OB		YES	reject
HS-PDSCH RL ID	0		RL ID 9.2.1.49		YES	reject
PDSCH-RL-ID	0		RL ID 9.2.1.49		YES	ignore
UL Synchronisation Parameters LCR		01		Mandatory for 1.28Mcps TDD. Not Applicable to 3.84Mcps TDD or 7.68Mcps TDD.	YES	ignore
>Uplink Synchronisation Step Size	М		9.2.3.13J		_	
>Uplink Synchronisation Frequency	М		9.2.3.131		_	
RL Information		0 <maxn oofRLs.</maxn 			YES	ignore
>RL ID	М		9.2.1.49		_	
>RL Specific DCH Information	0		9.2.1.49A			
Primary CCPCH RSCP Delta	0		9.2.3.5a		YES	ignore
E-DCH Information		01		3.84Mcps TDD only	YES	reject
>E-PUCH Information	0		9.2.3.36		_	
>E-TFCS Information TDD	0		9.2.3.37		_	
>E-DCH MAC-d Flows to Add >E-DCH MAC-d Flows to	0		9.2.3.38		_	
Delete			9.2.1.90		_	
>E-DCH TDD Information >E-DCH TDD Information to	0		9.2.3.40 9.2.3.42		_	
Modify			3.2.3.42		_	

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
			Reference			
E-DCH Serving RL	0		9.2.1.49	3.84Mcps TDD only	YES	reject
E-DCH Information 7.68Mcps		01		7.68Mcps TDD only	YES	reject
>E-PUCH Information	0		9.2.3.36	•	_	
>E-TFCS Information TDD	0		9.2.3.37		_	
>E-DCH MAC-d Flows to Add	0		9.2.3.38		_	
>E-DCH MAC-d Flows to Delete	0		9.2.1.90		_	
>E-DCH TDD Information 7.68Mcps	0		9.2.3.51		_	
>E-DCH TDD Information to Modify	0		9.2.3.42		_	
E-DCH Information 1.28Mcps		01		1.28Mcps TDD only	YES	reject
>E-PUCH Information LCR	0		9.2.3.36a	Í	_	
>E-TFCS Information TDD	0		9.2.3.37		_	
>E-DCH MAC-d Flows to Add	0		9.2.3.38		_	
>E-DCH MAC-d Flows to Delete	0		9.2.1.90		_	
>E-DCH TDD Information LCR	0		9.2.3.40a		_	
>E-DCH TDD Information to Modify	0		9.2.3.42		-	
Need for Idle Interval	0		ENUMERA TED (True, False)	TDD only	YES	ignore
CPC Information		01	,	1.28Mcps TDD only	YES	reject
>Continuous Packet Connectivity DRX Information LCR	0		9.2.3.61	,	_	
>Continuous Packet Connectivity DRX Information To Modify LCR	0		9.2.3.62		-	
>HS-DSCH Semi-Persistent scheduling Information LCR	0		9.2.3.64		_	
>HS-DSCH Semi-Persistent scheduling Information to modify LCR	0		9.2.3.65		_	
>HS-DSCH Semi-Persistent scheduling Deactivate Indicator LCR	0		9.2.3.70		-	
>E-DCH Semi-Persistent scheduling Information LCR	0		9.2.3.66		_	
>E-DCH Semi-Persistent scheduling Information to modify LCR	0		9.2.3.67		-	
>E-DCH Semi-Persistent scheduling Deactivate Indicator LCR	0		9.2.3.71		-	
RNTI Allocation Indicator	0		ENUMERA TED (True)	1.28 Mcps TDD only	YES	ignore
DCH Measurement Type indicator	0		9.2.3.76	1.28 Mcps TDD only	YES	reject
Multi-Carrier E-DCH Information Reconf		01		Applicable for Multi-Carrier E-DCH Operation in 1.28 Mcps TDD only	YES	reject

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>CHOICE continue,Setup or Change	М				_	
>>continue					_	
>>Setup					_	
>>>Multi-Carrier E-DCH Transport Bearer Mode LCR	M		9.2.3.79		_	
>>>Multi-Carrier E-DCH Information LCR	M		9.2.3.77		_	
>>change					_	
>>>MultiCarrier E-DCH Transport Bearer Mode	0		9.2.3.79		_	
>>>Multi-Carrier E-DCH Information LCR	0		9.2.3.77		_	
>>>Removal UL Multi- Carrier info		0 <maxn oofUL128 Carriers- 1></maxn 			-	
>>>UARFCN	М		9.2.1.65	Corresponds to Nt TS 25.105 [17]	_	
MU-MIMO Indicator	0		9.2.3.82	1.28 Mcps TDD only	YES	reject

Range bound	Explanation
maxnoofDCHs	Maximum number of DCHs for a UE.
maxnoofCCTrCHs	Maximum number of CCTrCHs for a UE.
maxnoofDSCHs	Maximum number of DSCHs for one UE.
maxnoofUSCHs	Maximum number of USCHs for one UE.
maxnoofRLs	Maximum number of RLs for one UE
maxnoofUL128Carriers	Maximum number of uplink frequencies in Multi-
	Carrier E-DCH Operation

9.1.12 RADIO LINK RECONFIGURATION READY

FDD Message 9.1.12.1

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	М		9.2.1.59		_	•
RL Information Response		0 <maxno ofRLs></maxno 			EACH	ignore
>RL ID	М		9.2.1.49		_	
>Maximum Uplink SIR	0		Uplink SIR 9.2.1.69		-	
>Minimum Uplink SIR	0		Uplink SIR 9.2.1.69		-	
>Maximum DL TX Power	0		DL Power 9.2.1.21A		ı	
>Minimum DL TX Power	0		DL Power 9.2.1.21A		-	
>Not Used	0		NULL		1	
>DL Code Information	0		FDD DL Code Information 9.2.2.14A		YES	ignore
>DCH Information Response	0		9.2.1.16A		YES	ignore
>Not Used	0		NULL		1	
>DL Power Balancing Updated Indicator	0		9.2.2.10D		YES	ignore
>Primary CPICH Usage For Channel Estimation	0		9.2.2.32A		YES	ignore
>Secondary CPICH Information Change	0		9.2.2.38B		YES	ignore
>E-DCH FDD Information Response	0		9.2.2.4C		YES	ignore
>E-DCH RL Set ID	0		RL Set ID 9.2.2.35		YES	ignore
>E-DCH FDD DL Control Channel Information	0		9.2.2.4D		YES	ignore
>F-DPCH Slot Format	0		9.2.2.85		YES	ignore
>HS-DSCH Preconfiguration Info	0		9.2.2.99		YES	ignore
>Non-Serving RL Preconfiguration Info	0		9.2.2.125		YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore
HS-DSCH-RNTI	0		9.2.1.30P		YES	ignore
HS-DSCH Information Response	0		HS-DSCH FDD Information Response 9.2.2.19b		YES	ignore
MAC-hs Reset Indicator	0		9.2.1.34B		YES	ignore
Fast Reconfiguration Permission	0		9.2.2.71	FDD only	YES	ignore
Continuous Packet Connectivity HS-SCCH less Information Response	0		9.2.2.75		YES	ignore
Additional HS Cell Information Response		0 <maxno ofHSDSC H-1></maxno 		For secondary serving HS- DSCH cell. Max 3 in this 3GPP release.	EACH	ignore

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>HS-PDSCH RL ID	M		RL ID 9.2.1.49		_	
>HS-DSCH-RNTI	M		9.2.1.30P		_	
>HS-DSCH FDD Secondary Serving Information Response	М		9.2.2.19ba		-	
Additional E-DCH Cell Information Response RLReconf		0 <maxno ofEDCH- 1></maxno 		E-DCH on Secondary uplink frequency – max 1 in this 3GPP release.	EACH	ignore
>Additional E-DCH FDD Information Response	0		9.2.2.120	For new E- DCH Radio Links on secondary carrier	I	
>Additional Modified E- DCH FDD Information Response	0		9.2.2.121		-	

Range bound	Explanation
maxnoofRLs	Maximum number of RLs for a UE.
maxnoofHSDSCH-1	Maximum number of Secondary Serving HS-DSCH cells for one UE.
maxnoofEDCH-1	Maximum number of uplink frequencies -1 for E-DCH for one UE

9.1.12.2 TDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
RL Information Response		0 <maxn oofRLs></maxn 		See Note 1 below	YES	ignore
>RL ID	M		9.2.1.49		_	
>Maximum Uplink SIR	0		Uplink SIR 9.2.1.69		_	
>Minimum Uplink SIR	0		Uplink SIR 9.2.1.69		_	
>Maximum DL TX Power	0		DL Power 9.2.1.21A		_	
>Minimum DL TX Power	0		DL Power 9.2.1.21A		_	
>Secondary CCPCH Info TDD	0		9.2.3.7B	Applicable to 3.84Mcps TDD only	_	
>UL CCTrCH Information		0 <maxn oofCCTr CHs></maxn 		For DCH	GLOBAL	ignore
>>CCTrCH ID	М		9.2.3.2		_	
>>UL DPCH to be Added		01		Applicable to 3.84Mcps TDD only	YES	ignore
>>>Repetition Period	М		9.2.3.7		_	
>>>Repetition Length	М		9.2.3.6		_	
>>>TDD DPCH Offset	M		9.2.3.8A		_	
>>> Rx Timing Deviation	0		9.2.3.7A		_	
>>>UL Timeslot Information	М		9.2.3.13C		_	
>>> Rx Timing Deviation 3.84 Mcps Extended	0		9.2.3.35		YES	Ignore
>>UL DPCH to be Modified		01			YES	ignore
>>>Repetition Period	0		9.2.3.7		_	
>>>Repetition Length	0		9.2.3.6		_	
>>>TDD DPCH Offset	0		9.2.3.8A		_	
>>>UL Timeslot Information		0 <maxn oOfTS></maxn 		Applicable to 3.84Mcps TDD only	-	
>>>Time Slot	М		9.2.1.56			
>>>>Midamble Shift And Burst Type	0		9.2.3.4		_	
>>>TFCI Presence	0		9.2.1.55		_	
>>>UL Code Information		0 <maxn oOfDPC Hs></maxn 			_	
>>>>DPCH ID	М		9.2.3.3		_	
>>>>TDD Channelisation Code	0		9.2.3.8		_	
>>>UL Timeslot Information LCR		0 <maxn oOfTSLC R></maxn 		Applicable to 1.28Mcps TDD only	GLOBAL	ignore
>>>>Time Slot LCR	М		9.2.3.12a		_	
>>>Midamble	0		9.2.3.4C			

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Shift LCR						
>>>TFCI Presence	0		9.2.1.55		_	
>>>UL Code Information LCR		0 <maxn oOfDPC HLCR></maxn 			GLOBAL	ignore
>>>>DPCH ID	М		9.2.3.3		-	
>>>>TDD Channelisation Code LCR	0		9.2.3.8a		_	
>>>> TDD UL DPCH Time Slot Format LCR	0		9.2.3.10C		YES	reject
>>>UL Timeslot Information 7.68Mcps		0 <maxn oOfTS></maxn 		Applicable to 7.68Mcps TDD only	GLOBAL	ignore
>>>Time Slot	М		9.2.1.56		_	
>>>>Midamble Shift And Burst Type 7.68Mcps	0		9.2.3.23		_	
>>>TFCI Presence	0		9.2.1.55		_	
>>>UL Code Information 7.68Mcps		0 <maxn oOfDPC Hs768></maxn 			GLOBAL	ignore
>>>>DPCH ID	М		9.2.3.3		_	
>>>>TDD Channelisation Code 7.68Mcps	0		9.2.3.25		_	
>>UL DPCH to be Deleted		0 <maxn oofDPCH s></maxn 			GLOBAL	ignore
>>>DPCH ID	М		9.2.3.3		_	
>>UL DPCH to be Added LCR		01		Applicable to 1.28Mcps TDD only	YES	ignore
>>>Repetition Period	М		9.2.3.7		_	
>>>Repetition Length	М		9.2.3.6		_	
>>>TDD DPCH Offset	М		9.2.3.8A		_	
>>>UL Timeslot Information LCR	М		9.2.3.13G		-	
>>UL DPCH to be Added 7.68Mcps		01		Applicable to 7.68Mcps TDD only	YES	ignore
>>>Repetition Period	М		9.2.3.7		_	
>>>Repetition Length	М		9.2.3.6		_	
>>>TDD DPCH Offset	M		9.2.3.8A		_	
>>> Rx Timing Deviation 7.68Mcps	0		9.2.3.30		_	
>>>UL Timeslot	М		9.2.3.26		_	
Information 7.68Mcps >DL CCTrCH Information		0 <maxn oofCCTr CHs></maxn 		For DCH	GLOBAL	ignore
>>CCTrCH ID	М	05	9.2.3.2		_	
>>DL DPCH to be Added		01		Applicable to 3.84Mcps TDD only	YES	ignore
>>>Repetition Period	М		9.2.3.7	-	_	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>>>Repetition Length	М		9.2.3.6		_	
>>>TDD DPCH Offset	М		9.2.3.8A		_	
>>>DL Timeslot	М		9.2.3.2C		_	
Information						
>>DL DPCH to be Modified		01			YES	ignore
>>>Repetition Period	0		9.2.3.7		_	
>>>Repetition Length	0		9.2.3.6		_	
>>>TDD DPCH Offset	0		9.2.3.8A		_	
>>>DL Timeslot Information		0 <maxn oOfTS></maxn 		Applicable to 3.84Mcps TDD only	-	
>>>>Time Slot	М		9.2.1.56	•	_	
>>>>Midamble Shift	0		9.2.3.4		_	
And Burst Type						
>>>TFCI Presence	0		9.2.1.55		_	
>>>DL Code Information		0 <maxn oOfDPC</maxn 			_	
		Hs>				
>>>>DPCH ID	M		9.2.3.3		_	
>>>>TDD Channelisation Code	0		9.2.3.8		_	
>>>DL Timeslot Information LCR		0 <maxn oOfTSLC R></maxn 		Applicable to 1.28Mcps TDD only	GLOBAL	ignore
>>>>Time Slot LCR	М		9.2.3.12a		_	
>>>Midamble Shift	0		9.2.3.4C		_	
LCR						
>>>TFCI Presence	0		9.2.1.55		_	
>>>>DL Code Information LCR		0 <maxn oOfDPC HLCR></maxn 			GLOBAL	ignore
>>>>DPCH ID	М	772077	9.2.3.3		_	
>>>>TDD Channelisation Code LCR	0		9.2.3.8a		_	
>>>> TDD DL DPCH Time Slot Format LCR	0		9.2.3.8E		YES	reject
>>>Maximum DL TX Power	0		DL Power 9.2.1.21A	Maximum allowed power on DPCH	YES	ignore
>>>>Minimum DL TX Power	0		DL Power 9.2.1.21A	Minimum allowed power on DPCH	YES	ignore
>>>DL Timeslot Information 7.68Mcps		0 <maxn oOfTS></maxn 		Applicable to 7.68Mcps TDD only	GLOBAL	ignore
>>>>Time Slot	М		9.2.1.56	1	_	
>>>>Midamble Shift And Burst Type 7.68Mcps	0		9.2.3.23		_	
>>>TFCI Presence	0		9.2.1.55		_	
>>>DL Code Information		0 <maxn oOfDPC Hs768></maxn 			_	
>>>>DPCH ID 7.68Mcps	М		9.2.3.34		_	
>>>>TDD Channelisation Code 7.68Mcps	0		9.2.3.25		_	
>>DL DPCH to be		0 <maxn< td=""><td></td><td></td><td>GLOBAL</td><td>ignore</td></maxn<>			GLOBAL	ignore

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Deleted		oofDPCH				
>>>DPCH ID	M	S>	9.2.3.3		_	
>>DL DPCH to be Deleted 7.68Mcps TDD		0 <maxn oofDPCH s768></maxn 			GLOBAL	ignore
>>>DPCH ID 7.68Mcps	М		9.2.3.34		_	
>>DL DPCH to be Added LCR		01		Applicable to 1.28Mcps TDD only	YES	ignore
>>>Repetition Period	М		9.2.3.7		_	
>>>Repetition Length	М		9.2.3.6		_	
>>>TDD DPCH Offset	М		9.2.3.8A		_	
>>>DL Timeslot Information LCR	М		9.2.3.2E		_	
>>DL DPCH to be Added 7.68Mcps		01		Applicable to 7.68Mcps TDD only	YES	ignore
>>>Repetition Period	M		9.2.3.7		_	
>>>Repetition Length	M		9.2.3.6		_	
>>>TDD DPCH Offset	M		9.2.3.8A		_	
>>>DL Timeslot Information 7.68Mcps	М		9.2.3.28		-	
>>CCTrCH Maximum DL TX Power	0		DL Power 9.2.1.21A	Maximum allowed power on DPCH Applicable to 3.84Mcps TDD and 7.68Mcps TDD only	YES	ignore
>>CCTrCH Minimum DL TX Power	0		DL Power 9.2.1.21A	Minimum allowed power on DPCH Applicable to 3.84Mcps TDD and 7.68Mcps TDD only	YES	ignore
>DCH Information Response	0		9.2.1.16A		YES	ignore
>DSCH to be Added or Modified		0 <maxnoo f DSCHs></maxnoo 			GLOBAL	ignore
>>DSCH ID	М	2001102	9.2.3.3ae		_	
>>Transport Format Management	M		9.2.3.13		_	
>>DSCH Flow Control Information	М		9.2.3.3ag		_	
>>Binding ID	0		9.2.1.3		_	
>>Transport Layer Address	0		9.2.1.62		_	
>USCH to be Added or Modified		0 <maxnoo f USCHs></maxnoo 			GLOBAL	ignore
>>USCH ID	М		9.2.3.14		_	
>>Transport Format Management	M		9.2.3.13		_	
>>Binding ID	0		9.2.1.3		_	
>>Transport Layer Address	0		9.2.1.62		_	
>Uplink Timing Advance Control LCR	0		9.2.3.13K	Applicable to 1.28Mcps TDD	YES	ignore

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
			Reference			
			<u> </u>	only		
>Secondary CCPCH Info TDD LCR	0		9.2.3.7F	Applicable to 1.28Mcps TDD only	YES	ignore
>Secondary CCPCH Info 7.68Mcps TDD	0		9.2.3.22	Applicable to 7.68Mcps TDD only	YES	ignore
>UARFCN	0		9.2.1.66	Applicable to 1.28Mcps TDD only. Mandatory for 1.28Mcps TDD when using multiple frequencies. Corresponds to Nt (3GPP TS 25.105)	YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore
HS-DSCH-RNTI	0		9.2.1.30P		YES	ignore
HS-DSCH Information Response	0		HS-DSCH TDD Information Response 9.2.3.3ab		YES	ignore
DSCH-RNTI	0		9.2.3.3ah		YES	ignore
MAC-hs Reset Indicator	0		9.2.1.34B		YES	ignore
E-DCH Information Response	0		E-DCH TDD Information Response 9.2.3.41	3.84Mcps TDD only	YES	ignore
E-DCH Information Response 7.68Mcps	0		E-DCH TDD Information Response 7.68Mcps 9.2.3.52	7.68Mcps TDD only	YES	ignore
E-DCH Information Response 1.28Mcps	0		E-DCH TDD Information Response 1.28Mcps 9.2.3.41a	1.28Mcps TDD only	YES	ignore
PowerControl GAP	0		INTEGER (1255)	1.28Mcps TDD only	YES	ignore
Idle Interval Information	0	`	9.2.3.60	TDD only	YES	ignore
Continuous Packet Connectivity DRX Information Response LCR	0		9.2.3.63	1.28 Mcps TDD only	YES	ignore
HS-DSCH Semi-Persistent scheduling Information Response LCR	0		9.2.3.68	1.28 Mcps TDD only	YES	ignore
E-DCH Semi-Persistent scheduling Information Response LCR	0		9.2.3.69	1.28 Mcps TDD only	YES	ignore
E-RNTI for FACH	0		E-RNTI 9.2.1.94	1.28 Mcps TDD only	YES	ignore
H-RNTI for FACH	0		HS-DSCH- RNTI 9.2.1.30P	1.28 Mcps TDD only	YES	ignore
DCH Measurement Occasion Information	0		9.2.3.75	1.28 Mcps TDD only	YES	reject
Multi-Carrier E-DCH Information Response LCR	0		9.2.3.78	1.28 Mcps TDD only	YES	ignore

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
MU-MIMO Information	0		9.2.3.81	1.28 Mcps TDD only	YES	reject
Note 1: This information element is a simplified representation of the ASN.1. Repetition 1 and repetition 2 through maxnoofRLs are represented by separate ASN.1 structures with different criticalities.						

Range bound	Explanation
maxnoofDSCHs	Maximum number of DSCHs for one UE.
maxnoofUSCHs	Maximum number of USCHs for one UE.
maxnoofCCTrCHs	Maximum number of CCTrCHs for a UE.
maxnoofTS	Maximum number of Timeslots for a UE for 3.84Mcps TDD or 7.68Mcps TDD.
maxnoofDPCHs	Maximum number of DPCH for a UE for 3.84Mcps TDD.
maxnoofTSLCRs	Maximum number of Timeslots for a UE for 1.28Mcps TDD.
maxnoofDPCHLCRs	Maximum number of DPCH for a UE for 1.28Mcps TDD.
maxnoofRLs	Maximum number of RLs for one UE
maxnoofDPCHs768	Maximum number of DPCH for a UE for 7.68Mcps TDD.

9.1.13 RADIO LINK RECONFIGURATION COMMIT

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
			Reference			,
Message Type	М		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	
CFN	М		9.2.1.9		YES	ignore
Active Pattern Sequence Information	0		9.2.2.A	FDD only	YES	ignore
Fast Reconfiguration Mode	0		9.2.2.70	FDD only	YES	reject

9.1.14 RADIO LINK RECONFIGURATION FAILURE

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
CHOICE Cause Level	М				YES	ignore
>General					_	
>>Cause	M		9.2.1.5		_	
>RL Specific					_	
>>RLs Causing Reconfiguration Failure		0 <maxnoof RLs></maxnoof 			EACH	ignore
>>>RL ID	М		9.2.1.49		_	
>>>Cause	М		9.2.1.5		_	
>>>Max UE DTX Cycle	C-DTX- CycleNotA vailable		9.2.2.87		YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore

Condition	Explanation
DTX-CycleNotAvailable	The IE shall be present if the Cause IE is set to "Continuous Packet
	Connectivity UE DTX Cycle not Available ".

Range bound	Explanation
maxnoofRLs	Maximum number of RLs for a UE.

9.1.15 RADIO LINK RECONFIGURATION CANCEL

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	

9.1.16 RADIO LINK RECONFIGURATION REQUEST

9.1.16.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		1	
Allowed Queuing Time	0		9.2.1.2		YES	reject
UL DPCH Information		01			YES	reject
>TFCS	0		9.2.1.63	TFCS for the UL.	ı	
>UL DPDCH Indicator For E-DCH Operation	0		9.2.2.52A		YES	reject
DL DPCH Information		01			YES	reject
>TFCS	0		9.2.1.63	TFCS for the DL.	-	
>TFCI Signalling Mode	0		9.2.2.46		_	
>Limited Power Increase	0		9.2.2.21A		_	
DCHs To Modify	0		FDD DCHs To Modify 9.2.2.13C		YES	reject
DCHs To Add	0		DCH FDD Information 9.2.2.4A		YES	reject
DCHs To Delete		0 <maxno ofDCHs></maxno 			GLOBAL	reject
>DCH ID	M		9.2.1.16		ı	
Transmission Gap Pattern Sequence Information	0		9.2.2.47A		YES	reject
RL Information		0 <maxno ofRLs></maxno 			EACH	ignore
>RL ID	M		9.2.1.49		ı	
>RL Specific DCH Information	0		9.2.1.49A		I	
>RL specific E-DCH Information	0		9.2.2.35a		YES	reject
>E-DCH RL Indication	0		9.2.2.4E		YES	reject
>HS-DSCH Preconfiguration Setup	0		9.2.2.100		YES	ignore
>Non-Serving RL Preconfiguration Setup	0		9.2.2.124		YES	ignore
>Non-Serving RL Preconfiguration Removal	0		Non- Serving RL Preconfigu ration Setup 9.2.2.124		YES	ignore
DL Reference Power Information	0		9.2.2.10C		YES	ignore
HS-DSCH Information	0		HS-DSCH FDD Information 9.2.2.19a		YES	reject
HS-DSCH Information To Modify Unsynchronised	0		9.2.1.30NA		YES	reject
HS-DSCH MAC-d Flows To Add	0		HS-DSCH MAC-d Flows Information 9.2.1.300A		YES	reject
HS-DSCH MAC-d Flows To Delete	0		9.2.1.30OB		YES	reject

LIO DDOOLLDL ID			T 51 15	1 1	\/=0	
HS-PDSCH RL ID	0		RL ID 9.2.1.49		YES	reject
E-DPCH Information		01			YES	reject
>Maximum Set of E- DPDCHs	O		9.2.2.24e		-	
>Puncture Limit	О		9.2.1.46		-	
>E-TFCS Information	0		9.2.2.4G		_	
>E-TTI	О		9.2.2.4J		_	
>E-DPCCH Power Offset	0		9.2.2.4K		-	
>E-RGCH 2-Index-Step Threshold	0		9.2.2.64		_	
>E-RGCH 3-Index-Step Threshold	0		9.2.2.65		_	
>HARQ Info for E-DCH	0		9.2.2.66		_	
> Minimum Reduced E- DPDCH Gain Factor	0		9.2.2.102		YES	ignore
>HS-DSCH Configured Indicator	0		9.2.2.19C		-	
E-DCH FDD Information	0		9.2.2.4B		YES	reject
E-DCH FDD Information to Modify	0		9.2.2.4F		YES	reject
E-DCH MAC-d Flows to Add	0		E-DCH MAC-d flows Information 9.2.2.4MC		YES	reject
E-DCH MAC-d Flows to Delete	0		9.2.1.90		YES	reject
Serving E-DCH RL	0		9.2.2.38C		YES	reject
CPC Information		01			YES	reject
>Continuous Packet Connectivity DTX-DRX Information	0		9.2.2.72		-	
>Continuous Packet Connectivity DTX-DRX Information To Modify	0		9.2.2.73		-	
>Continuous Packet Connectivity HS-SCCH less Information	0		9.2.2.74		-	
>Continuous Packet Connectivity HS-SCCH less Deactivate Indicator	0		9.2.2.75A		YES	reject
No of Target Cell HS-SCCH Order	0		INTEGER (130)		YES	ignore
Additional HS Cell Information RL Reconf Req		0 <maxno ofHSDSC H-1></maxno 		For secondary serving HS- DSCH cell. Max 3 in this 3GPP release.	EACH	reject
>HS-PDSCH RL ID	М		RL ID 9.2.1.49	.010000.	_	
>C-ID	0		9.2.1.49		_	
>HS-DSCH FDD Secondary Serving Information	0		9.2.2.19aa		-	
>HS-DSCH FDD Secondary Serving Information To Modify Unsynchronised	0		9.2.2.19bc		-	

>HS-DSCH Secondary Serving Remove	0		NULL		_	
UE Aggregate Maximum Bit Rate	0		9.2.1.137		YES	ignore
Additional E-DCH Cell Information RL Reconf Req		01		For E-DCH on multiple frequencies in this DRNS.	YES	reject
>CHOICE Setup, Configuration Change or Removal of E-DCH On Secondary UL Frequency	М				YES	reject
>>Setup				Used when RLs on the secondary UL frequency does not exist or is not configured with E-DCH in the current UE context	_	
>>>Multicell E-DCH Transport Bearer Mode	М		9.2.2.113		_	
>>>Additional E-DCH Cell Information Setup		1 <maxno ofEDCH- 1></maxno 		E-DCH on Secondary uplink frequency – max 1 in this 3GPP release.	-	
>>>>Additional E- DCH FDD Setup Information	М		9.2.2.110		-	
>>Configuration Change				Used when RLs with additional E-DCH on the secondary UL frequency exist in the current UE context and the configuration is modified (adding new RLs or modification of existing RLs)	_	
>>>Additional E-DCH Cell Information Configuration Change		1 <maxno ofEDCH- 1></maxno 		E-DCH on Secondary uplink frequency – max 1 in this 3GPP release.	_	
>>> Additional E- DCH Configuration Change Information	М		9.2.2.111	10.00	-	
>>Removal				Used when all RLs on the indicated	-	

				secondary UL frequency is removed.		
>>>Additional E-DCH Cell Information Removal		1 <maxno ofEDCH- 1></maxno 		E-DCH on Secondary uplink frequency – max 1 in this 3GPP release.	-	
>>>>RL on Secondary UL Frequency	М		ENUMERA TED (Remove,)	Removal of all RL on secondary UL frequency	-	

Range Bound	Explanation
maxnoofDCHs	Maximum number of DCHs for one UE.
maxnoofRLs	Maximum number of RLs for a UE.
maxnoofHSDSCH-1	Maximum number of Secondary Serving HS-DSCH
	cells for one UE.
maxnoofEDCH-1	Maximum number of uplink frequencies -1 for E-DCH
	for one UE

9.1.16.2 TDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40	•	YES	reject
Transaction ID	М		9.2.1.59		_	,
Allowed Queuing Time	0		9.2.1.2		YES	reject
UL CCTrCH Information To Modify		0 <maxn oofCCTr CHs></maxn 			EACH	notify
>CCTrCH ID	M		9.2.3.2		_	
>TFCS	0		9.2.1.63		_	
>UL SIR Target	0		Uplink SIR 9.2.1.69	Applicable to 1.28Mcps TDD only	YES	reject
UL CCTrCH Information to Delete		0 <maxn oofCCTr CHs></maxn 			EACH	notify
>CCTrCH ID	M		9.2.3.2		_	
DL CCTrCH Information To Modify		0 <maxn oofCCTr CHs></maxn 			EACH	notify
>CCTrCH ID	M		9.2.3.2		_	
>TFCS	0		9.2.1.63		_	
DL CCTrCH Information to Delete		0 <maxn oofCCTr CHs></maxn 			EACH	notify
>CCTrCH ID	M		9.2.3.2		_	
DCHs To Modify	0		TDD DCHs To Modify 9.2.3.8B		YES	reject
DCHs To Add	0		DCH TDD Information 9.2.3.2A		YES	reject
DCHs to Delete		0 <maxn oofDCHs ></maxn 			GLOBAL	reject
>DCH ID	М		9.2.1.16		_	
RL Information		0 <maxn oofRLs></maxn 			YES	ignore
>RL ID	M		9.2.1.49		_	
>RL Specific DCH Information	0		9.2.1.49A		_	
UL Synchronisation Parameters LCR		01		Mandatory for 1.28Mcps TDD. Not Applicable to 3.84Mcps TDD.	YES	ignore
>Uplink Synchronisation Step Size	М		9.2.3.13J		_	
>Uplink Synchronisation Frequency	М		9.2.3.131		_	
HS-DSCH Information	0		HS-DSCH TDD Information9. 2.3.3aa		YES	reject
HS-DSCH Information To Modify Unsynchronised	0		9.2.1.30NA		YES	reject
HS-DSCH MAC-d Flows To Add	0		HS-DSCH MAC-d Flows Information 9.2.1.300A		YES	reject
HS-DSCH MAC-d Flows To Delete	0		9.2.1.30OB		YES	reject
HS-PDSCH RL ID	0		RL ID		YES	reject

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
			9.2.1.49			
E-DCH Information		01		3.84Mcps TDD only	YES	reject
>E-PUCH Information	0		9.2.3.36		_	
>E-TFCS Information TDD >E-DCH MAC-d Flows to	0		9.2.3.37		_	
Add	0		9.2.3.38		_	
>E-DCH MAC-d Flows to Delete	0		9.2.1.90		_	
>E-DCH TDD Information	0		9.2.3.40		_	
>E-DCH TDD Information to Modify	0		9.2.3.42		_	
E-DCH Serving RL	0		9.2.1.49	3.84Mcps TDD only	YES	reject
E-DCH Information 7.68Mcps		01		7.68Mcps TDD only	YES	reject
>E-PUCH Information	0		9.2.3.36	100 only	_	
>E-TFCS Information TDD	0		9.2.3.37		_	
>E-DCH MAC-d Flows to	0		9.2.3.38		 	
Add >E-DCH MAC-d Flows to						
Delete	0		9.2.1.90		_	
>E-DCH TDD Information 7.68Mcps	0		9.2.3.51		_	
>E-DCH TDD Information to Modify	0		9.2.3.42		_	
E-DCH Information 1.28Mcps		01		1.28Mcps TDD only	YES	reject
>E-PUCH Information LCR	0		9.2.3.36a	,	_	
>E-TFCS Information TDD	0		9.2.3.37		_	
>E-DCH MAC-d Flows to Add	0		9.2.3.38		_	
>E-DCH MAC-d Flows to Delete	0		9.2.1.90		_	
>E-DCH TDD Information LCR	0		9.2.3.40a		_	
>E-DCH TDD Information to Modify	0		9.2.3.42		_	
Need for Idle Interval	0		ENUMERAT ED (True, False)	TDD only	YES	ignore
CPC Information		01	1 4.00)		YES	reject
>Continuous Packet Connectivity DRX Information LCR	0		9.2.3.61		_	
>Continuous Packet Connectivity DRX	0		9.2.3.62		_	
Information To Modify LCR >HS-DSCH Semi-Persistent	0		9.2.3.64		_	
scheduling Information LCR >HS-DSCH Semi-Persistent scheduling Information to modify LCR	0		9.2.3.65		_	
>HS-DSCH Semi-Persistent scheduling Deactivate Indicator LCR	0		9.2.3.70		_	
>E-DCH Semi-Persistent scheduling Information LCR	0		9.2.3.66		_	
>E-DCH Semi-Persistent scheduling Information to modify LCR	0		9.2.3.67		_	
>E-DCH Semi-Persistent scheduling Deactivate Indicator LCR	0		9.2.3.71		_	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
RNTI Allocation Indicator	0		ENUMERAT ED (True)	1.28 Mcps TDD only	YES	ignore
DCH Measurement Type indicator	0		9.2.3.76	1.28 Mcps TDD only	YES	reject
Multi-Carrier E-DCH Information Reconf		01		Applicable for Multi-Carrier E-DCH Operation in 1.28 Mcps TDD only	YES	reject
>CHOICE continue,Setup or Change	М				_	
>>continue					_	
>>Setup					_	
>>>Multi-Carrier E-DCH Transport Bearer Mode LCR	M		9.2.3.79		_	
>>>Multi-Carrier E-DCH Information LCR	М		9.2.3.77		_	
>>Change					_	
>>>Multi-Carrier E-DCH Transport Bearer Mode	0		9.2.3.79		_	
>>>Multi-Carrier E-DCH Information LCR	0		9.2.3.77		_	
>>>Removal UL Multi- Carrier info		0 <maxn oofUL128 Carriers- 1></maxn 			_	
>>>UARFCN	М		9.2.1.65	Corresponds to Nt TS 25.105 [17]	_	
MU-MIMO Indicator	0		9.2.3.82	1.28 Mcps TDD only	YES	reject

Range Bound	Explanation
maxnoofCCTrCHs	Maximum number of CCTrCHs for a UE.
maxnoofDCHs	Maximum number of DCHs for one UE.
maxnoofRLs	Maximum number of RLs for one UE
maxnoofUL1.28Carriers	Maximum number of uplink frequencis in Multi-Carrier E-DCH Operation

9.1.17 RADIO LINK RECONFIGURATION RESPONSE

9.1.17.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
RL Information Response		0 <maxno ofRLs></maxno 			EACH	ignore
>RL ID	M		9.2.1.49		_	
>Maximum Uplink SIR	0		Uplink SIR 9.2.1.69		_	
>Minimum Uplink SIR	0		Uplink SIR 9.2.1.69		_	
>Maximum DL TX Power	0		DL Power 9.2.1.21A		_	
>Minimum DL TX Power	0		DL Power 9.2.1.21A		_	
>Not Used	0		NULL		_	
>DCH Information Response	0		9.2.1.16A		YES	ignore
>DL Code Information	0		FDD DL Code Information 9.2.2.14A		YES	ignore
>DL Power Balancing Updated Indicator	0		9.2.2.10D		YES	ignore
>E-DCH FDD Information Response	0		9.2.2.4C		YES	ignore
>E-DCH RL Set ID	0		RL Set ID 9.2.2.35		YES	ignore
>E-DCH FDD DL Control Channel Information	0		9.2.2.4D		YES	ignore
>F-DPCH Slot Format	0		9.2.2.85		YES	ignore
>HS-DSCH Preconfiguration Info	0		9.2.2.99		YES	ignore
>Non-Serving RL Preconfiguration Info	0		9.2.2.125		YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore
HS-DSCH-RNTI	0		9.2.1.30P		YES	ignore
HS-DSCH Information Response	0		HS-DSCH FDD Information Response 9.2.2.19b		YES	ignore
MAC-hs Reset Indicator	0		9.2.1.34B		YES	ignore
Continuous Packet Connectivity HS-SCCH less Information Response	0		9.2.2.75		YES	Ignore
Additional HS Cell Information Response		0 <maxno ofHSDSC H-1></maxno 		For secondary serving HS-DSCH cell. Max 3 in this 3GPP release.	EACH	ignore
>HS-PDSCH RL ID	М		RL ID 9.2.1.49		_	
>HS-DSCH-RNTI	М		9.2.1.30P		_	
>HS-DSCH FDD Secondary Serving Information Response	М		9.2.2.19ba		_	
Additional E-DCH Cell		0 <maxno< td=""><td></td><td>E-DCH on</td><td>EACH</td><td>ignore</td></maxno<>		E-DCH on	EACH	ignore

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Information Response RLReconf		ofEDCH- 1>		Secondary uplink frequency – max 1 in this 3GPP release.		
>Additional E-DCH FDD Information Response	0		9.2.2.120	For new E- DCH Radio Links on secondary carrier	-	
>Additional Modified E- DCH FDD Information Response	0		9.2.2.121		-	

Range Bound	Explanation
maxnoofRLs	Maximum number of RLs for a UE.
maxnoofHSDSCH-1	Maximum number of Secondary Serving HS-DSCH cells for one UE.
maxnoofEDCH-1	Maximum number of uplink frequencies -1 for E-DCH for one UE

9.1.17.2 TDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	М		9.2.1.59		_	
RL Information Response		0 <max noofRLs ></max 		See note 1 below	YES	ignore
>RL ID	M		9.2.1.49		_	
>Maximum Uplink SIR	0		Uplink SIR 9.2.1.69		_	
>Minimum Uplink SIR	0		Uplink SIR 9.2.1.69		_	
>Maximum DL TX Power	0		DL Power 9.2.1.21A		_	
>Minimum DL TX Power	0		DL Power 9.2.1.21A		-	
>DCH Information Response	0		9.2.1.16A		YES	ignore
>DL CCTrCH Information		0 <max noofCC TrCHs></max 		For DCH	GLOBAL	ignore
>>CCTrCH ID	М		9.2.3.2		_	
>>DL DPCH To Modify LCR		01		Applicable to 1.28Mcps TDD only	YES	ignore
>>>DL Timeslot Information LCR		0 <max noOfTS LCR></max 			_	
>>>>Time Slot LCR	M		9.2.3.12a		_	
>>>>Maximum DL TX Power	0		DL Power 9.2.1.21A	Maximum allowed power on DPCH	_	
>>>>Minimum DL TX Power	0		DL Power 9.2.1.21A	Minimum allowed power on DPCH	_	
>>CCTrCH Maximum DL TX Power	0		DL Power 9.2.1.21A	Maximum allowed power on DPCH Applicable to 3.84Mcps TDD and 7.68Mcps TDD only	YES	ignore
>>CCTrCH Minimum DL TX Power	0		DL Power 9.2.1.21A	Minimum allowed power on DPCH Applicable to 3.84Mcps TDD and 7.68Mcps TDD only	YES	ignore
>Uplink Timing Advance Control LCR	0		9.2.3.13K	Applicable to 1.28Mcps TDD only	YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore
HS-DSCH-RNTI	0		9.2.1.30P		YES	ignore
HS-DSCH Information Response	0		HS-DSCH TDD Information Response 9.2.3.3ab		YES	ignore
MAC-hs Reset Indicator	0		9.2.1.34B		YES	ignore
E-DCH Information Response	0		E-DCH TDD Information	3.84Mcps TDD only	YES	ignore

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
			Response 9.2.3.41			
E-DCH Information Response 7.68Mcps	0		E-DCH TDD Information Response 7.68Mcps 9.2.3.52	7.68Mcps TDD only	YES	ignore
E-DCH Information Response 1.28Mcps	0		E-DCH TDD Information Response 1.28Mcps 9.2.3.41a	1.28Mcps TDD only	YES	ignore
PowerControl GAP	0		INTEGER (1255)	1.28Mcps TDD only	YES	ignore
Idle Interval Information	0		9.2.3.60	TDD only	YES	ignore
Continuous Packet Connectivity DRX Information Response LCR	0		9.2.3.63	1.28 Mcps TDD only	YES	ignore
HS-DSCH Semi-Persistent scheduling Information Response LCR	0		9.2.3.68	1.28 Mcps TDD only	YES	ignore
E-DCH Semi-Persistent scheduling Information Response LCR	0		9.2.3.69	1.28 Mcps TDD only	YES	ignore
E-RNTI for FACH	0		E-RNTI 9.2.1.94	1.28 Mcps TDD only	YES	ignore
H-RNTI for FACH	0		HS-DSCH- RNTI 9.2.1.30P	1.28 Mcps TDD only	YES	ignore
DCH Measurement Occasion Information	0		9.2.3.75	1.28 Mcps TDD only	YES	reject
Multi-Carrier E-DCH Information Response LCR	0		9.2.3.78	1.28 Mcps TDD only	YES	ignore
MU-MIMO Information	0		9.2.3.81	1.28 Mcps TDD only	YES	reject

Note 1: This information element is a simplified representation of the ASN.1. Repetition 1 and repetition 2 through maxnoofRLs are represented by separate ASN.1 structures with different criticalities.

Range bound	Explanation
maxnoofCCTrCHs	Maximum number of CCTrCHs for a UE.
maxnoofTSLCRs	Maximum number of Timeslots for a UE for 1.28Mcps TDD.
maxnoofRLs	Maximum number of RLs for one UE

9.1.18 RADIO LINK FAILURE INDICATION

IE/Group Name	Presence	Range	IE Type	Semantics	Criticality	Assigned
			and	Description		Criticality
			Reference			
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	
CHOICE Reporting Object	М			Object for which the Failure shall be reported.	YES	ignore
>RL					_	
>>RL Information		1 <maxnoof RLs></maxnoof 			EACH	ignore
>>>RL ID	M		9.2.1.49		_	
>>>Cause	M		9.2.1.5		_	
>RLS				FDD only	_	
>>RL Set Information		1 <maxnoof RLSets></maxnoof 			EACH	ignore
>>>RL Set ID	M		9.2.2.35		_	
>>>Cause	M		9.2.1.5		_	
>CCTrCH				TDD only		
>>RL ID	M		9.2.1.49		_	
>>CCTrCH List		1 <maxnoc CTrCHs></maxnoc 			EACH	ignore
>>>CCTrCH ID	M		9.2.3.2		_	
>>>Cause	M		9.2.1.5		_	

Range bound	Explanation
maxnoofRLs	Maximum number of RLs for one UE.
maxnoofRLSets	Maximum number of RL Sets for one UE.
maxnoofCCTrCHs	Maximum number of CCTrCHs for a UE.

9.1.19 RADIO LINK RESTORE INDICATION

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	
CHOICE Reporting Object	M			Object for which the Restoration shall be reported.	YES	ignore
>RL				TDD only	_	
>>RL Information		1 <max noofRLs ></max 			EACH	ignore
>>>RL ID	M		9.2.1.49		_	
>RLS				FDD only	_	
>>RL Set Information		1 <max noofRL Sets></max 			EACH	ignore
>>>RL Set ID	M		9.2.2.35		_	
>CCTrCH				TDD only		
>>RL ID	М		9.2.1.49		_	
>>CCTrCH List		1 <max noCCTr CHs></max 			EACH	ignore
>>>CCTrCH ID	M		9.2.3.2		_	

Range bound	Explanation
maxnoofRLs	Maximum number of RLs for one UE.
maxnoofRLSets	Maximum number of RL Sets for one UE.
maxnoofCCTrCHs	Maximum number of CCTrCHs for a UE.

9.1.20 DL POWER CONTROL REQUEST [FDD]

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	_
Power Adjustment Type	M		9.2.2.28		YES	ignore
DL Reference Power	C- Common		DL Power 9.2.1.21A		YES	ignore
Inner Loop DL PC Status	0		9.2.2.21a		YES	ignore
DL Reference Power Information	C- Individual	1 <maxnoo fRLs></maxnoo 			EACH	ignore
>RL ID	M		9.2.1.49		_	
>DL Reference Power	М		DL Power 9.2.1.21A		_	
Max Adjustment Step	C- CommonO rIndividual		9.2.2.23		YES	ignore
Adjustment Period	C- CommonO rIndividual		9.2.2.B		YES	ignore
Adjustment Ratio	C- CommonO rIndividual		9.2.2.C		YES	ignore

Condition	Explanation
Common	The IE shall be present if the <i>Power Adjustment Type</i> IE is set to "Common".
Individual	The IE shall be present if the <i>Power Adjustment Type</i> IE is set to "Individual".
CommonOrIndividual	The IE shall be present if the <i>Power Adjustment Type</i> IE is set to "Common" or "Individual".

Range Bound	Explanation
maxnoofRLs	Maximum number of RLs for one UE.

9.1.21 PHYSICAL CHANNEL RECONFIGURATION REQUEST

9.1.21.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	М		9.2.1.59		_	,
RL Information		1			YES	reject
>RL ID	М		9.2.1.49		_	
>DL Code Information	М		FDD DL Code Information 9.2.2.14A		YES	notify
>F-DPCH Slot Format	0		9.2.2.85		YES	Ignore

9.1.21.2 TDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	,
RL Information		1	0.200		YES	reject
>RL ID	М		9.2.1.49		_	,
>UL CCTrCH Information		0 <maxnoof CCTrCHs></maxnoof 			GLOBAL	reject
>>CCTrCH ID	М		9.2.3.2		_	
>>UL DPCH Information		1			YES	notify
>>>Repetition Period	0		9.2.3.7		_	,
>>>Repetition Length	Ō		9.2.3.6		_	
>>>TDD DPCH Offset	0		9.2.3.8A		_	
>>>UL Timeslot Information		0 <maxno OfTS></maxno 		Applicable to 3.84Mcps TDD only	-	
>>>>Time Slot	М		9.2.1.56	•	-	
>>>>Midamble Shift And Burst Type	0		9.2.3.4		-	
>>>TFCI Presence	0		9.2.1.55		_	
>>>>UL Code Information	0		TDD UL Code Information 9.2.3.10A		_	
>>>UL Timeslot Information LCR		0 <maxno OfTSLCR ></maxno 		Applicable to 1.28Mcps TDD only	GLOBAL	reject
>>>>Time Slot LCR	M		9.2.3.12a		-	
>>>>Midamble Shift LCR	0		9.2.3.4C		1	
>>>TFCI Presence	0		9.2.1.55		_	
>>>>UL Code Information LCR	0		TDD UL Code Information LCR 9.2.3.10B		-	
>>>>PLCCH Information	0		9.2.3.17		YES	Reject
>>>UL Timeslot Information 7.68Mcps		0 <maxno OfTS></maxno 		Applicable to 7.68Mcps TDD only	GLOBAL	reject
>>>>Time Slot	M		9.2.1.56		-	
>>>Midamble Shift And Burst Type 7.68Mcps	0		9.2.3.23		I	
>>>TFCI Presence	0		9.2.1.55		_	
>>>>UL Code Information 7.68Mcps	0		TDD UL Code Information 9.2.3.27		-	
>DL CCTrCH Information		0 <maxno ofCCTrCH s></maxno 			GLOBAL	reject
>>CCTrCH ID	М	-	9.2.3.2	1	_	
>>DL DPCH Information	† · · ·	1	0.2.0.2	1	YES	notify
>>Repetition Period	0	<i>'</i>	9.2.3.7		-	
>>>Repetition Length	0		9.2.3.6		_	
>>>TDD DPCH Offset	Ō		9.2.3.8A		_	
>>>DL Timeslot Information		0 <maxno OfTS></maxno 	3.2.3.071	Applicable to 3.84Mcps TDD only	_	
>>>Time Slot	М		9.2.1.56		_	
>>>Midamble Shift	0	1	9.2.3.4		_	

And Burst Type						
>>>TFCI Presence	0		9.2.1.55		_	
>>>DL Code Information	0		TDD DL Code Information 9.2.3.8C		_	
>>>DL Timeslot Information LCR		0 <maxno OfTSLCR ></maxno 		Applicable to 1.28Mcps TDD only	GLOBAL	reject
>>>>Time Slot LCR	M		9.2.3.12a		_	
>>>>Midamble Shift LCR	0		9.2.3.4C		_	
>>>TFCI Presence	0		9.2.1.55		_	
>>>DL Code Information LCR	0		TDD DL Code Information LCR 9.2.3.8D		-	
>>>DL Timeslot Information 7.68Mcps		0 <maxno OfTS></maxno 		Applicable to 7.68Mcps TDD only	GLOBAL	reject
>>>>Time Slot	M		9.2.1.56		_	
>>>Midamble Shift And Burst Type 7.68Mcps	0		9.2.3.23		Г	
>>>TFCI Presence	0		9.2.1.55		_	
>>>DL Code Information 7.68Mcps	0		TDD DL Code Information 7.68Mcps 9.2.3.29		-	
>HS-PDSCH Timeslot Specific Information		0 <maxno ofDLts></maxno 		Applicable to 3.84Mcps TDD only.	GLOBAL	reject
>>Time Slot	M		9.2.1.56	-	_	
>>Midamble Shift And Burst Type	M		9.2.3.4		_	
>HS-PDSCH Timeslot Specific Information LCR		0 <maxno ofDLtsLCR ></maxno 		Applicable to 1.28Mcps TDD only	GLOBAL	reject
>>Time Slot LCR	М		9.2.3.12a		_	
>>Midamble Shift LCR	M		9.2.3.4C		_	
>HS-PDSCH Timeslot Specific Information 7.68Mcps		0 <maxno ofDLts></maxno 		Applicable to 7.68Mcps TDD only.	GLOBAL	reject
>>Time Slot	M		9.2.1.56		_	
>>Midamble Shift And Burst Type 7.68Mcps	M		9.2.3.23		-	-
>UARFCN	0		9.2.1.66	Applicable to 1.28Mcps TDD only.	YES	ignore

Range bound	Explanation
maxnoofCCTrCHs	Maximum number of CCTrCHs for a UE.
maxnoofTS	Maximum number of Timeslots for a UE for 3.84Mcps TDD or
	7.68Mcps TDD.
maxnoofTSLCR	Maximum number of Timeslots for a UE for 1.28Mcps TDD.
maxnoofDLts	Maximum number of downlink time slots per Radio Link for
	3.84Mcps TDD or 7.68Mcps TDD.
maxnoofDLtsLCR	Maximum number of Downlink time slots per Radio Link for
	1.28Mcps TDD.

9.1.22 PHYSICAL CHANNEL RECONFIGURATION COMMAND

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
CFN	M		9.2.1.9		YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore

9.1.23 PHYSICAL CHANNEL RECONFIGURATION FAILURE

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	М		9.2.1.59		_	
Cause	М		9.2.1.5		YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore

9.1.24 UPLINK SIGNALLING TRANSFER INDICATION

9.1.24.1 FDD Message

IE/Group Name	Presence	Range	IE Type	Semantics	Criticality	Assigned
			and Reference	Description		Criticality
Message Type	М		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	<u> </u>
UC-ID	M		9.2.1.71		YES	ignore
SAI	M		9.2.1.52		YES	ignore
Cell GAI	0		9.2.1.5A		YES	ignore
C-RNTI	M		9.2.1.14		YES	ignore
S-RNTI	M		9.2.1.53		YES	ignore
D-RNTI	0		9.2.1.24		YES	ignore
Propagation Delay	M		9.2.2.33		YES	ignore
STTD Support Indicator	M		9.2.2.45		YES	ignore
Closed Loop Mode1 Support	M		9.2.2.2		YES	ignore
Indicator						
L3 Information	M		9.2.1.32		YES	ignore
CN PS Domain Identifier	0		9.2.1.12		YES	ignore
CN CS Domain Identifier	0		9.2.1.11		YES	ignore
URA Information	0		9.2.1.70B		YES	ignore
Cell GA Additional Shapes	0		9.2.1.5B		YES	ignore
DPC Mode Change Support	0		9.2.2.56		YES	ignore
Indicator						
Common Transport Channel	0		9.2.1.12F		YES	Ignore
Resources Initialisation Not						
Required						

Cell Capability Container FDD	0		9.2.2.D	YES	ignore
SNA Information	0		9.2.1.52Ca	YES	ignore
Cell Portion ID	0		9.2.2.E	YES	ignore
Active MBMS Bearer Service List		0 <max noofActiv eMBMS</max 		GLOBAL	ignore
>TMGI	М		9.2.1.80	_	
>Transmission Mode	М		9.2.1.81	-	
Inter-frequency Cell List		0 <max CellsMe as></max 		GLOBAL	ignore
>DL UARFCN	М		UARFCN 9.2.1.66	-	
>UL UARFCN	0		UARFCN 9.2.1.66	_	
>Primary Scrambling Code	M		9.2.1.45	_	
Extended Propagation Delay	0		9.2.2.33a	YES	ignore
HS-DSCH-RNTI	0		9.2.1.30P	YES	ignore
Multiple PLMN List	0		9.2.1.117	YES	ignore
E-RNTI	0		9.2.1.94	YES	ignore
Max UE DTX Cycle	C-DTX- DRXCapab ility		9.2.2.87	YES	ignore
Cell Capability Container FDD Extension	0		9.2.2.123	YES	ignore
Secondary Serving Cell List	0		9.2.2.101	YES	ignore
Dual Band Secondary Serving Cell List	0		Secondary Serving Cell List 9.2.2.101	YES	ignore

Condition	Explanation
DTX-DRXCapability	The IE shall be present if the Continuous Packet Connectivity DTX-DRX
	Support Indicator IE in Cell Capability Container FDD IE is set to 1.

Range bound	Explanation
maxnoofActiveMBMS	Maximum number of MBMS bearer services that are active in parallel.
maxCellsMeas	Maximum number of inter-frequency cells measured by a UE.

9.1.24.2 TDD Message

IE/Group Name	Presence	Range	IE Type	Semantics	Criticality	Assigned
			and Reference	Description		Criticality
Message Type	М		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59			.g
UC-ID	M		9.2.1.71		YES	ignore
SAI	M		9.2.1.52		YES	ignore
Cell GAI	0		9.2.1.5A		YES	Ignore
C-RNTI	M		9.2.1.14		YES	ignore
S-RNTI	М		9.2.1.53		YES	ignore
D-RNTI	0		9.2.1.24		YES	ignore
Rx Timing Deviation	M		9.2.3.7A		YES	ignore
L3 Information	М		9.2.1.32		YES	ignore
CN PS Domain Identifier	0		9.2.1.12		YES	ignore
CN CS Domain Identifier	0		9.2.1.11		YES	ignore
URA Information	0		9.2.1.70B		YES	ignore
Cell GA Additional Shapes	0		9.2.1.5B		YES	ignore
Common Transport Channel Resources Initialisation Not Required	0		9.2.1.12F		YES	ignore
Cell Capability Container TDD	0		9.2.3.1a	Applicable to 3.84Mcps TDD only	YES	ignore
Cell Capability Container TDD LCR	0		9.2.3.1b	Applicable to 1.28Mcps TDD only	YES	ignore
SNA Information	0		9.2.1.52Ca	_	YES	ignore
Active MBMS Bearer Service List		0 <max noofActiv eMBMS ></max 			GLOBAL	ignore
>TMGI	М		9.2.1.80		-	
>Transmission Mode	М		9.2.1.81		_	
Cell Capability Container 7.68Mcps TDD	0		9.2.3.31	Applicable to 7.68Mcps TDD only	YES	ignore
Rx Timing Deviation 7.68Mcps	0		9.2.3.30	Applicable to 7.68Mcps TDD only	YES	ignore
Rx Timing Deviation 3.84Mcps Extended	0		9.2.3.35	Applicable to 3.84Mcps TDD only	YES	ignore
Multiple PLMN List	0		9.2.1.117		YES	ignore
HS-DSCH-RNTI	0		9.2.1.30P		YES	ignore
E-RNTI	0		9.2.1.94		YES	ignore
Cell Portion LCR ID	0		9.2.3.73	Applicable to 1.28Mcps TDD only	YES	ignore
Cell Capability Container Extension TDD LCR	0		9.2.3.80	Applicable to 1.28Mcps TDD only	YES	ignore

Range bound	Explanation
maxnoofActiveMBMS	Maximum number of MBMS bearer services that are active in
	parallel.

9.1.24A GERAN UPLINK SIGNALLING TRANSFER INDICATION

IE/Group Name	Presence	Range	IE type and reference	Semantics description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	_
UC-ID	M		9.2.1.71	UC-ID may be a GERAN cell identifier.	YES	ignore
SAI	M		9.2.1.52		YES	ignore
S-RNTI	M		9.2.1.53		YES	ignore
D-RNTI	0		9.2.1.24		YES	ignore
L3 Information	M		9.2.1.32		YES	ignore
CN PS Domain Identifier	0		9.2.1.12		YES	ignore
CN CS Domain Identifier	0		9.2.1.11		YES	ignore
URA Information	0		9.2.1.70B	URA information may be GRA information	YES	ignore

9.1.25 DOWNLINK SIGNALLING TRANSFER REQUEST

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	М		9.2.1.59		_	
C-ID	M		9.2.1.6	May be a GERAN cell identifier	YES	ignore
D-RNTI	М		9.2.1.24		YES	ignore
L3 Information	M		9.2.1.32		YES	ignore
D-RNTI Release Indication	М		9.2.1.25		YES	ignore
URA-ID	0		9.2.1.70		YES	ignore
MBMS Bearer Service List		0 <maxno ofMBMS></maxno 			GLOBAL	ignore
>TMGI	M		9.2.1.80		_	
Old URA-ID	0		URA-ID 9.2.1.70		YES	ignore
SRNC-ID	C-URA		RNC-ID 9.2.1.50	If the Extended SRNC-ID IE is included in the message, the SRNC-ID IE shall be ignored.	YES	ignore
Extended SRNC-ID	0		Extended RNC-ID 9.2.1.50a	The Extended SRNC-ID IE shall be used if the RNC identity has a value larger than 4095.	YES	reject
Enhanced PCH Capability	0		9.2.1.132	FDD and 1.28Mcps TDD only	YES	Ignore

Condition	Explanation				
URA	The IE shall be present if the URA-ID IE or Old URA-ID IE is present.				

Range bound	Explanation					
maxnoofMBMS	Maximum number of MBMS bearer services that a UE can join.					

9.1.26 RELOCATION COMMIT

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	
D-RNTI	0		9.2.1.24		YES	ignore
RANAP Relocation Information	0		9.2.1.47		YES	ignore

9.1.27 PAGING REQUEST

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		-	
CHOICE Paging Area	M				YES	ignore
>URA					-	
>>URA-ID	М		9.2.1.70	May be a GRA-ID.	_	
>Cell				UTRAN only	-	
>>C-ID	M		9.2.1.6	_	_	
SRNC-ID	M		RNC-ID 9.2.1.50	May be a BSC-ID. If the Extended SRNC-ID IE is included in the message, the SRNC-ID IE shall be ignored.	YES	ignore
S-RNTI	М		9.2.1.53		YES	ignore
IMSI	М		9.2.1.31		YES	ignore
DRX Cycle Length Coefficient	М		9.2.1.26		YES	ignore
CN Originated Page to Connected Mode UE		01			YES	ignore
>Paging Cause	M		9.2.1.41E		_	
>CN Domain Type	M		9.2.1.11A		_	
>Paging Record Type	M		9.2.1.41F		_	
Extended SRNC-ID	0		Extended RNC-ID 9.2.1.50a	The Extended SRNC-ID IE shall be used if the RNC identity has a value larger than 4095.	YES	reject
Enhanced PCH Capability	0		9.2.1.132	FDD and 1.28Mcps TDD only	YES	Ignore

9.1.28 DEDICATED MEASUREMENT INITIATION REQUEST

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
			Reference			
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		-	
Measurement ID	M		9.2.1.37		YES	reject
CHOICE Dedicated	M				YES	reject
Measurement Object Type						
>RL					-	
>>RL Information		1 <maxn oofRLs></maxn 			EACH	reject
>>>RL-ID	M		9.2.1.49		1	
>>>DPCH ID	0		9.2.3.3	TDD only		
>>>DPCH ID 7.68Mcps	0		9.2.3.34	7.68Mcps TDD only	-	
>>>HS-SICH Information		0 <maxn oofHSSI CHs></maxn 		TDD only	GLOBAL	reject
>>>>HS-SICH ID	M		9.2.3.3ad		-	
>RLS				FDD only	_	
>>RL Set Information		1 <maxn oofRLSet s></maxn 			EACH	reject
>>>RL-Set-ID	М	_	9.2.2.35		_	
>ALL RL			NULL		_	
>ALL RLS			NULL	FDD only	_	
Dedicated Measurement Type	M		9.2.1.18	,	YES	reject
Measurement Filter Coefficient	0		9.2.1.36		YES	reject
Report Characteristics	M		9.2.1.48		YES	reject
CFN reporting indicator	М		FN reporting indicator 9.2.1.28A		YES	reject
CFN	0		9.2.1.9		YES	reject
Partial Reporting Indicator	0		9.2.1.41Fa		YES	ignore
Measurement Recovery Behavior	0		9.2.1.38A		YES	ignore
Alternative Format Reporting Indicator	0		9.2.1.2D		YES	ignore

Range bound	Explanation
maxnoofRLs	Maximum number of individual RLs a measurement can be started on.
maxnoofRLSets	Maximum number of individual RL Sets a measurement can be started
	on.

9.1.29 DEDICATED MEASUREMENT INITIATION RESPONSE

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		-	
Measurement ID	M		9.2.1.37		YES	ignore
CHOICE Dedicated Measurement Object Type	0			Dedicated Measurement Object Type the measurement was initiated with	YES	ignore
>RL or ALL RL				See Note 1	_	
>>RL Information		1 <maxno ofRLs></maxno 			EACH	ignore
>>>RL ID	M		9.2.1.49		_	
>>>DPCH ID	0		9.2.3.3	TDD only	_	
>>>DPCH ID 7.68Mcps	0		9.2.3.34	7.68Mcps TDD only	_	
>>>Dedicated Measurement Value	М		9.2.1.19		_	
>>>CFN	0		9.2.1.9	Dedicated Measuremen t Time Reference	-	
>>>HS-SICH ID	0		9.2.3.3ad	TDD only	YES	reject
>>>Multiple Dedicated Measurement Value Information		0 <maxno ofDPCHsP erRL-1></maxno 		Applicable to 3.84Mcps TDD only	GLOBAL	ignore
>>>DPCH ID	М		9.2.3.3		ı	
>>>Dedicated Measurement Value	М		9.2.1.19		-	
>>>Multiple Dedicated Measurement Value Information LCR		0 <maxno ofDPCHsL CRPerRL- 1></maxno 		Applicable to 1.28McpsTD D only	GLOBAL	ignore
>>>DPCH ID	М		9.2.3.3		-	
>>>>Dedicated Measurement Value	М		9.2.1.19		-	
>>>Multiple HS-SICH Measurement Value Information		0 <maxno ofHSSICHs -1></maxno 		TDD only	GLOBAL	ignore
>>>HS-SICH ID	М		9.2.3.3ad		_	
>>>>Dedicated	M		9.2.1.19		-	
Measurement Value						
>>>Multiple Dedicated Measurement Value Information 7.68Mcps		0 <maxno ofDPCHs7 68PerRL- 1></maxno 		Applicable to 7.68Mcps TDD only	GLOBAL	ignore
>>>>DPCH ID 7.68Mcps	М		9.2.3.34		-	
>>>Dedicated Measurement Value >RLS or ALL RLS	М		9.2.1.19	FDD only	-	
				See Note 2		-
>>RL Set Information		1 <maxno ofRLSets></maxno 			EACH	ignore
>>>RL Set ID	M		9.2.2.35			
>>>Dedicated	M		9.2.1.19		_	

Measurement Value					
>>>CFN	0	9.2.1.9	Dedicated Measuremen t Time Reference	_	
Criticality Diagnostics	0	9.2.1.13		YES	Ignore
Measurement Recovery Support Indicator	0	9.2.1.38C		YES	ignore

Note 1: This is a simplified representation of the ASN.1: there are two different choice tags "RL" and "ALL RL" in the ASN.1, each having exactly the same structure.

This is a simplified representation of the ASN.1: there are two different choice tags "RLS" and "ALL RLS" in

Note 2: the ASN.1, each having exactly the same structure.

Range bound	Explanation
maxnoofRLs	Maximum number of individual RLs the measurement can be started on.
maxnoofRLSets	Maximum number of individual RL Sets the measurement can be started on.
maxnoofDPCHsPerRL	Maximum number of DPCHs per RL a measurement can be started on for 3.84Mcps TDD
maxnoofDPCHsLCRPerRL	Maximum number of DPCHs per RL a measurement can be started on for 1.28Mcps TDD
maxnoofHSSICHs	Maximum number of HSSICHs per RL a measurement can be started on
maxnoofDPCHs768PerRL	Maximum number of DPCHs per RL a measurement can be started on for 7.68Mcps TDD

9.1.30 DEDICATED MEASUREMENT INITIATION FAILURE

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	М		9.2.1.59		-	•
Measurement ID	М		9.2.1.37		YES	ignore
Cause	М		9.2.1.5		YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore
CHOICE Dedicated Measurement Object Type	0			Dedicated Measuremen t Object Type the measuremen t was initiated with	YES	ignore
>RL or ALL RL					_	
>>Unsuccessful RL		1 <maxno< td=""><td></td><td></td><td>EACH</td><td>ignore</td></maxno<>			EACH	ignore
Information		ofRLs>				
>>>RL ID	M		9.2.1.49		ı	
>>>Individual Cause	0		Cause 9.2.1.5		1	
>>Successful RL Information		0 <maxno ofRLs-1></maxno 			EACH	ignore
>>>RL ID	М		9.2.1.49		1	
>>>DPCH ID	0		9.2.3.3	TDD only	-	
>>>Dedicated Measurement Value	М		9.2.1.19		_	
>>>CFN	0		9.2.1.9	Dedicated Measuremen t Time Reference	-	
>>>HS-SICH ID	0		9.2.3.3ad	TDD only	YES	reject
>RLS or ALL RLS				FDD only	-	
>>Unsuccessful RL Set Information		1 <maxno ofrlsets=""></maxno>			EACH	ignore
>>>RL Set ID	M		9.2.2.35		ı	
>>>Individual Cause	0		Cause 9.2.1.5		_	
>>Successful RL Set Information		0 <maxno ofRLSets- 1></maxno 			EACH	ignore
>>>RL Set ID	М		9.2.2.35		-	
>>>Dedicated Measurement Value	М		9.2.1.19		-	
>>>CFN	0		9.2.1.9	Dedicated Measuremen t Time Reference	-	

Range bound	Explanation
maxnoofRLs	Maximum number of individual RLs the measurement can be started on.
maxnoofRLSets	Maximum number of individual RL Sets the measurement can be started
	on.

9.1.31 DEDICATED MEASUREMENT REPORT

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	
Measurement ID	M		9.2.1.37		YES	ignore
CHOICE Dedicated Measurement Object Type	М			Dedicated Measuremen t Object Type the measuremen t was initiated with	YES	ignore
>RL or ALL RL				See Note 1	_	
>>RL Information		1 <maxnoo fRLs></maxnoo 			EACH	ignore
>>>RL-ID	М		9.2.1.49		_	
>>>DPCH ID	0		9.2.3.3	TDD only	_	
>>>DPCH ID 7.68Mcps	0		9.2.3.34	7.68Mcps TDD only	_	
>>>Dedicated Measurement Value Information	М		9.2.1.19A		_	
>>>HS-SICH ID	0		9.2.3.3ad	TDD only	YES	ignore
>RLS or ALL RLS				FDD only See Note 2	_	
>>RL Set Information		1 <maxnoo fRLSets></maxnoo 			EACH	ignore
>>>RL Set ID	М		9.2.2.35		_	
>>>Dedicated Measurement Value Information	M		9.2.1.19A		_	
Measurement Recovery Reporting Indicator	0		9.2.1.38B		YES	ignore

Note 1: This is a simplified representation of the ASN.1: there are two different choice tags "RL" and "ALL RL" in the ASN.1, each having exactly the same structure.

Note 2: This is a simplified representation of the ASN.1: there are two different choice tags "RLS" and "ALL RLS" in the ASN.1, each having exactly the same structure.

Range bound	Explanation
maxnoofRLs	Maximum number of individual RLs the measurement can be started
	on.
maxnoofRLSets	Maximum number of individual RL Sets the measurement can be started on.

9.1.32 DEDICATED MEASUREMENT TERMINATION REQUEST

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	
Measurement ID	M		9.2.1.37		YES	ignore

9.1.33 DEDICATED MEASUREMENT FAILURE INDICATION

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	
Measurement ID	M		9.2.1.37		YES	ignore
Cause	M		9.2.1.5		YES	ignore
CHOICE Dedicated Measurement Object Type	0			Dedicated Measuremen t Object Type the measuremen t was initiated with	YES	ignore
>RL or ALL RL					_	
>>Unsuccessful RL Information		1 <maxnoof RLs></maxnoof 			EACH	ignore
>>>RL ID	M		9.2.1.49		ı	
>>>Individual Cause	0		Cause 9.2.1.5		_	
>RLS or ALL RLS				FDD only	-	
>>Unsuccessful RL Set Information		1 <maxnoof RLSets></maxnoof 			EACH	ignore
>>>RL Set ID	M		9.2.2.35		ı	
>>>Individual Cause	0		Cause 9.2.1.5		-	

Range bound	Explanation
maxnoofRLs	Maximum number of individual RLs the measurement can be started on.
maxnoofRLSets	Maximum number of individual RL Sets the measurement can be started
	on.

9.1.34 COMMON TRANSPORT CHANNEL RESOURCES RELEASE **REQUEST**

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	
D-RNTI	M		9.2.1.24		YES	ignore

9.1.35 COMMON TRANSPORT CHANNEL RESOURCES REQUEST

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59			
D-RNTI	M		9.2.1.24		YES	reject
C-ID Transport Bearer Request Indicator	O M		9.2.1.6 9.2.1.61	Request a new transport bearer or to use an existing bearer for the user	YES YES	reject reject
Transport Bearer ID	M		9.2.1.60	plane. Indicates the lur transport bearer to be used for the user plane.	YES	reject
Permanent NAS UE Identity	0		9.2.1.73		YES	ignore
Binding ID	0		9.2.1.3	Shall be ignored if bearer establishme nt with ALCAP.	YES	ignore
Transport Layer Address	0		9.2.1.62	Shall be ignored if bearer establishme nt with ALCAP.	YES	ignore
MBMS Bearer Service List		0 <max noofMB MS></max 			GLOBAL	notify
>TMGI	М		9.2.1. 80		_	
TNL QoS	0		9.2.1.56A	Shall be ignored if bearer establishme nt with ALCAP.	YES	ignore
Enhanced FACH Support Indicator	0		9.2.1.131	FDD and 1.28Mcps TDD only	YES	Ignore
Common E-DCH Support Indicator	0		9.2.2.92	FDD only	YES	Ignore
HS-DSCH Physical Layer Category	0		9.2.1.30Oa		Yes	Ignore
UE with enhanced HS- SCCH support indicator	0		NULL	UE supports enhanced HS-SCCH functionality: - UE supports different HS- SCCH in consecutive TTIs	YES	ignore

Range bound	Explanation
maxnoofMBMS	Maximum number of MBMS bearer services that a UE can join.

9.1.36 COMMON TRANSPORT CHANNEL RESOURCES RESPONSE

9.1.36.1 FDD Message

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
			Reference	2000 ipilon		Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	М		9.2.1.59		1	Í
S-RNTI	M		9.2.1.53		YES	ignore
C-RNTI	0		9.2.1.14		YES	ignore
FACH Info for UE Selected S-CCPCH		1			YES	ignore
>FACH Flow Control Information	M		9.2.1.26C	If the Enhanced FACH Information Response IE is included in the message, the FACH Flow Control Information IE shall be ignored.	YES	ignore
Transport Layer Address	0		9.2.1.62	<u> </u>	YES	ignore
Binding Identity	0		9.2.1.3		YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore
C-ID	M		9.2.1.6		YES	ignore
Active MBMS Bearer Service List		0 <maxnoo fActiveMB MS></maxnoo 			GLOBAL	ignore
>TMGI	М		9.2.1.80		_	
>Transmission Mode	M		9.2.1.81		_	
Enhanced FACH Information Response		01			YES	ignore
>Common HS-DSCH- RNTI Priority Queue Information for Enhanced FACH	М		Priority Queue Information for Enhanced FACH/PC H 9.2.1.133		I	
>Dedicated HS-DSCH- RNTI Priority Queue Information for Enhanced FACH	M		Priority Queue Information for Enhanced FACH/PC H 9.2.1.133		T	
>Priority Queue Information for Enhanced PCH	0		Priority Queue Information for Enhanced FACH/PC H 9.2.1.133		_	
>HS-DSCH Initial Capacity Allocation	М		9.2.1.30Na		_	
>HS-DSCH-RNTI	0		9.2.1.30P		ı	
Common E-DCH MAC-d Flow Specific Information	0		9.2.2.93		_	

361

E-RNTI	0	9.2.1.94	YES	ignore

Range bound	Explanation
maxnoofActiveMBMS	Maximum number of MBMS bearer services that are active in
	parallel.

9.1.36.2 TDD Message

IE/Group Name	Presence	Range	IE Type	Semantics	Criticality	Assigned
			and Reference	Description		Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	-,
S-RNTI	M		9.2.1.53		YES	ignore
C-RNTI	0		9.2.1.14		YES	ignore
FACH Info for UE Selected S-CCPCHs		1			YES	ignore
>FACH Flow Control Information	M		9.2.1.26C	If the Enhanced FACH Information Response IE is included in the message, the FACH Flow Control Information IE shall be ignored.	YES	ignore
Transport Layer Address	0		9.2.1.62	.ge.e.	YES	ignore
Binding Identity	0		9.2.1.3		YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore
C-ID	M		9.2.1.6		YES	ignore
Active MBMS Bearer Service List		0 <maxno ofActiveMB MS></maxno 	0.2.1.0		GLOBAL	ignore
>TMGI	М		9.2.1.80		_	
>Transmission Mode	M		9.2.1.81		_	
Enhanced FACH Information Response		0 1			YES	ignore
>Common HS-DSCH- RNTI Priority Queue Information for Enhanced FACH	М		Priority Queue Information for Enhanced FACH/PC H 9.2.1.133		-	
>Dedicated HS-DSCH- RNTI Priority Queue Information for Enhanced FACH	М		Priority Queue Information for Enhanced FACH/PC H 9.2.1.133		_	
>Priority Queue Information for Enhanced PCH	0		Priority Queue Information for Enhanced FACH/PC H 9.2.1.133		-	
>HS-DSCH Initial	М		9.2.1.30Na		_	
Capacity Allocation						
>HS-DSCH-RNTI	0		9.2.1.30P			
Common E-DCH MAC-d Flow Specific Information LCR	0		9.2.3.58		YES	ignore

Range bound	Explanation
maxnoofActiveMBMS	Maximum number of MBMS bearer services that are active in
	parallel.

9.1.37 COMMON TRANSPORT CHANNEL RESOURCES FAILURE

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
			Reference			
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
S-RNTI	M		9.2.1.53		YES	ignore
Cause	M		9.2.1.5		YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore

9.1.38 COMPRESSED MODE COMMAND [FDD]

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	
Active Pattern Sequence Information	M		9.2.2.A		YES	ignore

9.1.39 ERROR INDICATION

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		1	
Cause	0		9.2.1.5		YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore
S-RNTI	0		9.2.1.53		YES	ignore
D-RNTI	0	•	9.2.1.24		YES	ignore

9.1.40 DL POWER TIMESLOT CONTROL REQUEST [TDD]

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	_
DL Time Slot ISCP Info	0		9.2.3.2D	Mandatory for 3.84Mcps TDD and 7.68Mcps TDD, not applicable to 1.28Mcps TDD	YES	ignore
DL Time Slot ISCP Info LCR	0		9.2.3.2F	Mandatory for 1.28Mcps TDD, not applicable to 3.84Mcps TDD or 7.68Mcps TDD	YES	ignore
Primary CCPCH RSCP	0		9.2.3.5		YES	ignore
Primary CCPCH RSCP Delta	0	•	9.2.3.5a		YES	ignore

9.1.41 RADIO LINK PREEMPTION REQUIRED INDICATION

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		ı	
RL Information		0 <maxno ofRLs></maxno 			EACH	ignore
>RL ID	M		9.2.1.49		_	
>E-DCH MAC-d Flow Specific Information		0 <maxno ofEDCHM ACdFlows ></maxno 			EACH	ignore
>>E-DCH MAC-d Flow ID	M		9.2.1.91		-	
HS-DSCH MAC-d Flow Specific Information		0 <maxno ofMACdFl ows></maxno 			EACH	ignore
>HS-DSCH MAC-d Flow ID	М		9.2.1.300		1	

Range bound	Explanation
maxnoofRLs	Maximum number of radio links for one UE
maxnoofMACdFlows	Maximum number of HS-DSCH MAC-d flows
maxnoofEDCHMACdFlows	Maximum number of E-DCH MAC-d flows

9.1.42 RADIO LINK CONGESTION INDICATION

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		ı	
Congestion Cause	0		9.2.1.79		YES	ignore
RL Information		1 <maxno ofRLs></maxno 			EACH	ignore
>RL ID	M		9.2.1.49		_	
>DCH Rate Information		1 <maxno ofDCHs></maxno 			EACH	ignore
>>DCH ID	M		9.2.1.16		-	
>>Allowed Rate Information	0		9.2.1.2A		-	
>E-DCH MAC-d Flow Specific Information		0 <maxno ofEDCHM ACdFlows ></maxno 			EACH	ignore
>>E-DCH MAC-d Flow ID	M		9.2.1.91		_	
>DCH Indicator For E- DCH-HSDPA Operation	0		9.2.2.67		YES	ignore

Range bound	Explanation		
maxnoofRLs	Maximum number of Radio Links for one UE		
maxnoofDCHs	Maximum number of DCHs for one UE.		
maxnoofEDCHMACdFlows	Maximum number of E-DCH MAC-d flows		

9.1.43 COMMON MEASUREMENT INITIATION REQUEST

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
			Reference			
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		-	
Measurement ID	M		9.2.1.37		YES	reject
CHOICE Common	М				YES	reject
Measurement Object Type						
>Cell					_	
>>Reference Cell	М		UTRAN Cell	May be a	_	
Identifier			Identifier	GERAN Cell Identifier		
			9.2.1.71	identiller		
>>Time Slot	0		9.2.1.71	3.84Mcps		
>>Time Siot			9.2.1.50	TDD and	_	
				7.68 Mcps		
				TDD only		
>>Time Slot LCR	0		9.2.3.12a	1.28Mcps	_	
>> Time Slot Lork			3.2.3.12a	TDD only		
>>Neighbouring Cell		0 <maxnoof< td=""><td></td><td>UTRAN only</td><td>_</td><td></td></maxnoof<>		UTRAN only	_	
Measurement		MeasNCells		O Tru ar Ormy		
Information		>				
>>>CHOICE					_	
Neighbouring Cell						
Measurement						
Information						
>>>Neighbourin				FDD only	_	
g FDD Cell						
Measurement						
Information						
>>>>Neighbo	M		9.2.1.41G		_	
uring FDD Cell						
Measurement						
Information						
>>>Neighbourin				3.84Mcps	_	
g TDD Cell				TDD only		
Measurement						
Information	M		9.2.1.41H			
>>>>Neighbo uring TDD Cell	IVI		9.2.1.41H		_	
Measurement						
Information						
>>>Additional					_	
Neighbouring Cell						
Measurement						
Information						
>>>>Neighbo			1	1.28Mcps	_	
uring TDD Cell				TDD only		
Measurement						
InformationLC						
R			<u> </u>		<u> </u>	
>>>>Neig	M		9.2.1.41Dd		YES	reject
hbouring						-
TDD Cell						
Measureme			1			
nt						
InformationL						
CR						
>>>Additional					_	
Neighbouring Cell						
Measurement						
Information						
7.68Mcps			1	7 6014		
>>>>Neighbo				7.68Mcps	_	
uring TDD Cell	j	İ	L	TDD only		

Measurement Information No. N		1	ı		1		ı
Section Sect	Information						
S>UARFCN O 9.2.1.66 Applicable to 1.28Mcps TDD only.	>>>>Neig hbouring TDD Cell Measureme nt Information	М		9.2.3.32		YES	reject
SUPCH Position Cormon Position Cormon Position Common Position Position Position Position Position Positioning" Positioning" Positioning" Positioning" Positioning P		0		9.2.1.66	1.28Mcps	YES	ignore
Measurement Object Types Signore Signo	LCR	0		9.2.3.56	Applicable to 1.28Mcps TDD only.	YES	ignore
Section	Measurement Object Types				1.28Mcps	_	
Common Measurement Type I Eis set to "UTRAN GANSS Timing of Cell Frames for UE Positioning". If the Common Measurement it I Es absent, the GANSS time is Gallleo system ime. Extension Common Measurement O	>>GSM Cell					YES	ignore
Type Measurement Filter O Section Section O O Section O O Section O O Section O O O O O O O O O		M					
Coefficient Report Characteristics M 9.2.1.48 YES reject	Туре						_
SFN reporting indicator SFN	Coefficient				UTRAN only		
reporting indicator 9.2.1.28A SFN O O 9.2.1.28A UTRAN only YES reject Accuracy Measurement Recovery Behavior GANSS Time ID O O O O O O O O O O O O O O O O O O O							
Common Measurement Accuracy Measurement Recovery Behavior GANSS Time ID O 9.2.1.119a This IE may only be present if the Common Measurement type IE is set to "UTRAN GANSS Timing of Cell Frames for UE Positioning". If the Common Measuremen type IE is set to "UTRAN GANSS Timing of Cell Frames for UE Positioning". If the Common Measuremen type IE is set to "UTRAN GANSS Timing of Cell Frames for UE Positioning". If the Common Measuremen type IE is set to "UTRAN GANSS Timing of Cell Frames for UE Positioning" and this IE is absent, the GANSS time is Galileo system time. Extension Common Measurement Object Type Extension Common O Applicable to 1.28Mcps TDD only				reporting indicator 9.2.1.28A			reject
Accuracy Measurement Recovery Behavior O 9.2.1.38A UTRAN only YES ignore	SFN			9.2.1.52A	UTRAN only	YES	reject
Behavior GANSS Time ID O 9.2.1.119a This IE may only be present if the Common Measuremen t Type IE is set to "UTRAN GANSS Timing of Cell Frames for UE Positioning". If the Common Measuremen t Type IE is set to "UTRAN GANSS Timing of Cell Frames for UE Positioning". If the Common Measuremen t Type IE is set to "UTRAN GANSS Timing of Cell Frames for UE Positioning" and this IE is absent, the GANSS time is Galileo system time. Extension Common O Measurement Object Type O Applicable to YES ignore 1.28Mcps TDD only	Accuracy				UTRAN only		reject
only be present if the Common Measuremen t Type IE is set to "UTRAN GANSS Timing of Cell Frames for UE Positioning". If the Common Measuremen t Type IE is set to "UTRAN GANSS Timing of Common Measuremen t Type IE is set to "UTRAN GANSS Timing of Cell Frames for UE Positioning" and this IE is absent, the GANSS time is Galileo system time. Extension Common O Applicable to YES ignore 1.28Mcps TDD only	Behavior						ignore
Measurement Object Type 1.28Mcps TDD only				9.2.1.119a	only be present if the Common Measuremen t Type IE is set to "UTRAN GANSS Timing of Cell Frames for UE Positioning". If the Common Measuremen t Type IE is set to "UTRAN GANSS Timing of Cell Frames for UE Positioning" and this IE is absent, the GANSS time is Galileo system time.		
		0			Applicable to 1.28Mcps	YES	ignore
	>GsmCellList	+	1 <maxnoo< td=""><td></td><td>טוווט טט ו</td><td>YES</td><td>ignore</td></maxnoo<>		טוווט טט ו	YES	ignore

		fGsmCell>			
>>Measurement ID	M		9.2.1.37	_	
>>GSM Cell				_	
>>>CGI	М		9.2.1.5D	_	

Range bound	Explanation
maxnoofMeasNCell	Maximum number of neighbouring cells on which
	measurements can be performed.
maxNoOfGsmCell	Maximum number of GSM Cells in one message

9.1.44 COMMON MEASUREMENT INITIATION RESPONSE

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
Measurement ID	M		9.2.1.37		YES	ignore
CHOICE Common Measurement Object Type	0			Common Measuremen t Object Type that the measuremen t was initiated with.	YES	ignore
>Cell					-	
>>Common Measurement value	М		9.2.1.12D		_	
SFN	0		9.2.1.52A	Common Measuremen t Time Reference, UTRAN only.	YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore
Common Measurement Achieved Accuracy	0		Common Measurem ent Accuracy 9.2.1.12A	UTRAN only	YES	ignore
Measurement Recovery Support Indicator	0		9.2.1.38C	UTRAN only	YES	ignore
Extension Common Measurement Object Type	0			Applicable to 1.28Mcps TDD only	YES	ignore
>GsmCellList		1 <maxnoo fGsmCell></maxnoo 			YES	ignore
>>Measurement ID	M		9.2.1.37		_	
>>Common Measurement value	0		9.2.1.12D		-	

Range bound	Explanation
maxNoOfGsmCell	Maximum number of GSM Cells in one message

9.1.45 COMMON MEASUREMENT INITIATION FAILURE

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		-	
Measurement ID	M		9.2.1.37		YES	ignore
Cause	M		9.2.1.5		YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore
Extension Measurement IdList		0 <maxno0 fGsmCell></maxno0 		Applicable to 1.28Mcps TDD only	YES	ignore
>Measurement ID	M		9.2.1.37		_	
>Cause	M		9.2.1.5		_	

Range bound	Explanation
maxNoOfGsmCell	Maximum number of GSM Cells in one message

9.1.46 COMMON MEASUREMENT REPORT

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		-	
Measurement ID	М		9.2.1.37		YES	ignore
CHOICE Common Measurement Object Type	М			Common Measuremen t Object Type that the measuremen t was initiated with.	YES	ignore
>Cell					-	
>>Common Measurement Value Information	M		9.2.1.12E		-	
SFN	0		9.2.1.52A	Common Measuremen t Time Reference, UTRAN only.	YES	ignore
Measurement Recovery Reporting Indicator	0		9.2.1.38B	UTRAN only	YES	ignore
Extension Common Measurement Object Type	0			Applicable to 1.28Mcps TDD only	YES	ignore
>GsmCellList		1 <maxnoo fGsmCell></maxnoo 			YES	ignore
>>Measurement ID	M		9.2.1.37		ı	
>>Common Measurement value	0		9.2.1.12D		_	

Range bound	Explanation
maxNoOfGsmCell	Maximum number of GSM Cells in one message

9.1.47 COMMON MEASUREMENT TERMINATION REQUEST

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		-	
Measurement ID	М		9.2.1.37		YES	ignore
Extension Measurement IdList		0 <maxno0 fGsmCell></maxno0 		Applicable to 1.28Mcps TDD only	YES	ignore
>Measurement ID	М		9.2.1.37		_	

Range bound	Explanation
maxNoOfGsmCell	Maximum number of GSM Cells in one message

9.1.48 COMMON MEASUREMENT FAILURE INDICATION

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
	N/A		Reference		YES	ianoro
Message Type	M		9.2.1.40		150	ignore
Transaction ID	M		9.2.1.59		_	
Measurement ID	M		9.2.1.37		YES	ignore
Cause	M		9.2.1.5		YES	ignore
Extension Measurement		0 <maxnoo< td=""><td></td><td>Applicable to</td><td>YES</td><td>ignore</td></maxnoo<>		Applicable to	YES	ignore
IdList		fGsmCell>		1.28Mcps		
TULIST				TDD only		
>Measurement ID	M		9.2.1.37		_	
>Cause	M		9.2.1.5		-	

Range bound	Explanation
maxNoOfGsmCell	Maximum number of GSM Cells in one message

9.1.49 INFORMATION EXCHANGE INITIATION REQUEST

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		1	
Information Exchange ID	M		9.2.1.31A		YES	reject
CHOICE Information	M				YES	reject
Exchange Object Type						
>Cell					_	
>>C-ID	M		9.2.1.6	May be a GERAN cell identifier	-	
>Additional Information					_	
Exchange Object Types						
>>GSM Cell					_	
>>>CGI	M		9.2.1.5D		_	
>>MBMS Bearer Service					_	
>>>MBMS Bearer		1 <maxno< td=""><td></td><td></td><td>GLOBAL</td><td>reject</td></maxno<>			GLOBAL	reject
Service List		ofMBMS>				
>>>TMGI	М		9.2.1.80		-	
>>MBMS Bearer Service in MBMS Cell				FDD only	GLOBAL	reject
>>>MBMS Cell List		1 <maxno ofcell=""></maxno>			_	
>>>>C-ID	M		9.2.1.6	Cell identifier of cell in RNC initiating Information Exchange Initiation procedure	-	
>>>>MBMS Bearer		1 <maxno< td=""><td></td><td></td><td>_</td><td></td></maxno<>			_	
Service List	M	ofMBMS>	9.2.1.80			
>>>>TMGI >>MBMS Cell	IVI		9.2.1.60	FDD only	GLOBAL	reject
>>NBMS Cell List		1 <maxno< td=""><td></td><td>FDD OHly</td><td>GLOBAL</td><td>reject</td></maxno<>		FDD OHly	GLOBAL	reject
		ofcell>			_	
>>>C-ID	M		9.2.1.6	Cell identifier of cell in receiving RNC not initiating Information Exchange Initiation procedure	_	
>>ANR Cell					_	
>>>ANR Cell List		1 <maxno ofanrcelll></maxno 			_	
>>>C-ID	М		9.2.1.6		_	
Information Type	М		9.2.1.31E		YES	reject
Information Report Characteristics	М		9.2.1.31C		YES	reject

Range bound	Explanation
maxnoofMBMS	Maximum number of MBMS bearer services that a UE can join.
Maxnoofcell	Maximum number of cells that can be indicated in the corresponding IE.
maxnoofanrcell	Maximum number of ANR neighbour cells

9.1.50 INFORMATION EXCHANGE INITIATION RESPONSE

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	М		9.2.1.59		_	
Information Exchange ID	M		9.2.1.31A		YES	ignore
CHOICE Information	0				YES	ignore
Exchange Object Type						
>Cell			0.0.4.404		-	
>>Requested Data Value	М		9.2.1.48A		-	
>Additional Information Exchange Object Types					_	
>>MBMS Bearer Service					-	
>>>MBMS Bearer		1 <maxno< td=""><td></td><td></td><td>GLOBAL</td><td>ignore</td></maxno<>			GLOBAL	ignore
Service List		ofMBMS>				
>>>TMGI	M		9.2.1.80		1	
>>>Requested Data Value	M		9.2.1.48A		1	
>>MBMS Bearer Service in MBMS Cell				FDD only	GLOBAL	ignore
>>>MBMS Cell List		1 <maxno ofcell></maxno 			_	
>>>C-ID	M		9.2.1.6	Cell identifier of cell in RNC initiating Information Exchange Initiation procedure	-	
>>>>MBMS Bearer Service List		1 <maxno ofMBMS></maxno 			-	
>>>>TMGI	М		9.2.1.80		_	
>>>>Requested Data Value	M		9.2.1.48A		-	
>>MBMS Cell				FDD only	GLOBAL	ignore
>>>MBMS Cell List		1 <maxno ofcell></maxno 			_	
>>>C-ID	M		9.2.1.6	Cell identifier of cell in sending RNC not initiating Information Exchange Initiation procedure	-	
>>>>Requested Data Value	М		9.2.1.48A		-	
>>ANR Cell		+			_	
>>>ANR Cell List		1 <maxno ofanrcell></maxno 			_	
>>>>C-ID	М	Oldinoen>	9.2.1.6		_	
>>>Requested Data Value	M		9.2.1.48A		_	
Criticality Diagnostics	0		9.2.1.13		YES	ignore

Range bound	Explanation
maxnoofMBMS	Maximum number of MBMS bearer services that a UE can join.
Maxnoofcell	Maximum number of cells that can be indicated in the corresponding IE.
maxnoofanrcell	Maximum number of ANR neighbour cells

9.1.51 INFORMATION EXCHANGE INITIATION FAILURE

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
Information Exchange ID	M		9.2.1.31A		YES	ignore
Cause	M		9.2.1.5		YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore

9.1.52 INFORMATION REPORT

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	ignore
Information Exchange ID	М		9.2.1.31A		YES	ignore
CHOICE Information Exchange Object Type	М				YES	ignore
>Cell					_	
>>Requested Data Value Information	М		9.2.1.48B		_	
>Additional Information Exchange Object Types					_	
>>MBMS Bearer Service in MBMS Cell				FDD only	GLOBAL	ignore
>>>MBMS Cell List		1 <maxno ofcell=""></maxno>			ı	
>>>>C-ID	M		9.2.1.6	Cell identifier of cell in receiving RNC initiating Information Exchange Initiation procedure	T	
>>>MBMS Bearer Service List		1 <maxno ofMBMS></maxno 			_	
>>>>TMGI	М	OIIVIDIVIS>	9.2.1.80		_	
>>>>Requested Data Value Information	M		9.2.1.48B			
>>MBMS Cell				FDD only	GLOBAL	ignore
>>>MBMS Cell List		1 <maxno ofcell></maxno 			_	-
>>>C-ID	M		9.2.1.6	Cell identifier of cell in sending RNC not initiating Information Exchange Initiation procedure	_	
>>>>Requested Data Value Information	M		9.2.1.48B		-	

Range bound	Explanation
maxnoofMBMS	Maximum number of MBMS bearer services that a UE can join.
Maxnoofcell	Maximum number of cells that can be indicated in the corresponding IE.

9.1.53 INFORMATION EXCHANGE TERMINATION REQUEST

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		-	
Information Exchange ID	M		9.2.1.31A		YES	ignore

9.1.54 INFORMATION EXCHANGE FAILURE INDICATION

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	
Information Exchange ID	M		9.2.1.31A		YES	ignore
Cause	M		9.2.1.5		YES	ignore

9.1.55 RESET REQUEST

IE/Group Name	Presence	Range	IE Type and Reference	Semantic s Descripti on	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59			

RNC-ID	М		9.2.1.50	Identity of the sending RNC. If the Extended RNC-ID IE is included in the message, the RNC-ID IE shall be ignored.	YES	reject
CHOICE Reset Indicator	М				YES	reject
>Context					-	
>>Context Information		1 <maxre setContext ></maxre 			EACH	reject
>>>CHOICE Context Type	М				_	
>>>SRNTI					-	
>>>>S-RNTI	М		9.2.1.53		1	
>>>DRNTI					-	
>>>>D-RNTI	М		9.2.1.24		-	
>All Contexts			NULL			
>Context Group						
>>Context Group Information		1 <maxre setContext Groups></maxre 			EACH	reject
>>>S-RNTI Group	М		9.2.1.53a		_	
Extended RNC-ID	0		9.2.1.50a	Identity of the sending RNC. The Extended RNC-ID IE shall be used if the RNC identity has a value larger than 4095.	YES	reject

Range bound	Explanation
maxResetContext	Maximum number of contexts that can be reset by
	one RESET message.
maxResetContextGroups	Maximum number of context groups that can be reset
	by one RESET message.

9.1.56 RESET RESPONSE

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	М		9.2.1.59		_	
RNC-ID	M		9.2.1.50	Identity of the sending RNC. If the Extended RNC-ID IE is included in the message, the RNC-ID IE shall be ignored.	YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore
Extended RNC-ID	0		9.2.1.50a	Identity of the sending RNC. The Extended RNC-ID IE shall be used if the RNC identity has a value larger than 4095.	YES	reject

9.1.57 RADIO LINK ACTIVATION COMMAND

9.1.57.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	М		9.2.1.46		YES	ignore
Transaction ID	М		9.2.1.62		-	
Delayed activation		1 <maxnoofrl< td=""><td></td><td></td><td>EACH</td><td>ignore</td></maxnoofrl<>			EACH	ignore
Information		S>				
>RL ID	М		9.2.1.49		_	
>Delayed Activation Update	M		9.2.1.19Ab		_	

9.1.57.2 TDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.46		YES	ignore
Transaction ID	M		9.2.1.62		-	
Delayed activation		1 <maxnoofrl< td=""><td></td><td></td><td>EACH</td><td>ignore</td></maxnoofrl<>			EACH	ignore
Information		S>				
>RL ID	М		9.2.1.49		_	
>Delayed Activation Update	M		9.2.1.19Ab		-	

9.1.58 RADIO LINK PARAMETER UPDATE INDICATION

9.1.58.1 FDD Message

IE/Group name	Presence	Range	IE Type and Reference	Semantic Description	Criticality	Assigned Criticality
Message type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		-	ignore
HS-DSCH FDD Update Information	O		9.2.2.19c		YES	ignore
RL Information		0 <max noofRLs ></max 			EACH	ignore
>RL Id	M		9.2.1.49		_	
>Phase Reference Update Indicator	0		9.2.2.27B		_	
E-DCH FDD Update Information	0		9.2.2.19e		YES	ignore
Additional HS Cell Information RL Param Upd		0 <max noofHS DSCH- 1></max 		For secondary serving HS-DSCH cell. Max 3 in this 3GPP release.	EACH	ignore
>HS-PDSCH RL ID	M		RL ID 9.2.1.49		_	
>HS-DSCH FDD Secondary Serving Update Information	0		9.2.2.19ca		_	
Additional E-DCH Cell Information RL Param Upd		0 <max noofED CH-1></max 		For E-DCH on multiple frequencies in this DRNS. E-DCH on Secondary uplink frequency – max 1 in this 3GPP release.	EACH	ignore
>Additional E-DCH FDD Update Information	М		9.2.2.122		_	
CPC Recovery Report	0		ENUMERA TED(Initiat ed,)		YES	ignore

Range bound	Explanation
maxnoofHSDSCH-1	Maximum number of Secondary Serving HS-DSCH cells for one UE.
maxnoofEDCH-1	Maximum number of uplink frequencies -1 for E-DCH for one UE

9.1.58.2 TDD Message

IE/Group name	Presence	Range	IE Type and Reference	Semantic Description	Criticality	Assigned Criticality
Message type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	
HS-DSCH TDD Update Information	0		9.2.3.3ac		YES	ignore

9.1.59 UE MEASUREMENT INITIATION REQUEST [TDD]

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
Allowed Queing Time	0		9.2.1.2		YES	reject
Measurement ID	M		9.2.1.37		YES	reject
UE Measurement Type	M		9.2.3.13Fh		YES	reject
UE Measurement Timeslot information HCR	0		9.2.3.13Fe	3.84 Mcps TDD only	YES	reject
UE Measurement Timeslot information LCR	0		9.2.3.13Ff	1.28 Mcps TDD only	YES	reject
UE Measurement Timeslot information 7.68Mcps	0		9.2.3.33	7.68 Mcps TDD only	YES	reject
Measurement Filter Coefficient	0		9.2.1.36		YES	reject
UE Measurement Report Characteristics	М		9.2.3.13Fc		YES	reject
UE Measurement Parameter Modification Allowed	0		9.2.3.13Fb		YES	reject

9.1.60 UE MEASUREMENT INITIATION RESPONSE [TDD]

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
Measurement ID	M		9.2.1.37		YES	ignore
Measurement Filter Coefficient	0		9.2.1.36		YES	reject
UE Measurement Report Characteristics	0		9.2.3.13Fc		YES	reject
Criticality Diagnostics	0		9.2.1.13		YES	ignore

9.1.61 UE MEASUREMENT INITIATION FAILURE [TDD]

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
Measurement ID	M		9.2.1.37		YES	ignore
Cause	M		9.2.1.5		YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore

9.1.62 UE MEASUREMENT REPORT [TDD]

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	
Measurement ID	M		9.2.1.37		YES	ignore
UE Measurement Value Information	М		9.2.3.13Fj		YES	ignore

9.1.63 UE MEASUREMENT TERMINATION REQUEST [TDD]

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		-	
Measurement ID	M		9.2.1.37		YES	ignore

9.1.64 UE MEASUREMENT FAILURE INDICATION [TDD]

IE/Group Name	Presence	Range	IE Type	Semantics	Criticality	Assigned
			and	Description		Criticality
			Reference			
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	
Measurement ID	M		9.2.1.37		YES	ignore
Cause	M		9.2.1.5		YES	ignore

9.1.65 IUR INVOKE TRACE

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
			Reference	Description		Officiality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		-	
D-RNTI	0		9.2.1.24		YES	ignore
Trace Reference	M		9.2.1.58c		YES	ignore
UE Identity	M		9.2.1.66A		YES	ignore
Trace Recording Session Reference	М		9.2.1.58b		YES	ignore
List Of Interfaces To Trace		0maxnoo fInterfaces			EACH	ignore
>Interface	M		ENUMERA TED (lub, lur,)		-	
Trace Depth	M		9.2.1.58a		YES	ignore
MDT Configuration	0		9.2.1.139		YES	ignore
Trace Collection Entity IP Address	0		9.2.1.62		YES	ignore

Range bound	Explanation
maxnoofInterfaces	Maximum of Interfaces to be traced.

9.1.66 IUR DEACTIVATE TRACE

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	
D-RNTI	0		9.2.1.24		YES	ignore
Trace Reference	M		9.2.1.58c		YES	ignore

9.1.67 MBMS ATTACH COMMAND

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		1	
MBMS Bearer Service List		1 <maxno ofMBMS></maxno 			GLOBAL	ignore
>TMGI	M		9.2.1.80		_	
CHOICE UE State	0				YES	ignore
>CELL_FACH/CELL_PCH					ı	
>>D-RNTI	M		9.2.1.24		1	
>URA_PCH					1	
>>SRNC-ID	М		RNC-ID 9.2.1.50	If the Extended SRNC-ID IE is included in the message, the SRNC-ID IE shall be ignored.	_	
>>URA-ID	M		9.2.1.70		_	
>>Extended SRNC-ID	0		Extended RNC-ID 9.2.1.50a	The Extended SRNC-ID IE shall be used if the RNC identity has a value larger than 4095.	YES	reject

Range bound	Explanation					
maxnoofMBMS	Maximum number of MBMS bearer services that a UE can join.					

9.1.68 MBMS DETACH COMMAND

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		1	
MBMS Bearer Service List		1 <maxno ofMBMS></maxno 			GLOBAL	ignore
>TMGI	M		9.2.1.80		_	
CHOICE UE State	0				YES	ignore
>CELL_FACH/CELL_PCH					ı	
>>D-RNTI	M		9.2.1.24		1	
>URA_PCH					1	
>>SRNC-ID	М		RNC-ID 9.2.1.50	If the Extended SRNC-ID IE is included in the message, the SRNC-ID IE shall be ignored.	_	
>>URA-ID	M		9.2.1.70		_	
>>Extended SRNC-ID	0		Extended RNC-ID 9.2.1.50a	The Extended SRNC-ID IE shall be used if the RNC identity has a value larger than 4095.	YES	reject

Range bound	Explanation					
maxnoofMBMS	Maximum number of MBMS bearer services that a UE can join.					

9.1.69 DIRECT INFORMATION TRANSFER

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
			Reference		\/=0	
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	
RNC-ID	M		9.2.1.50	ID of an RNC which initiates the procedure. If the Extended RNC-ID IE is included in the message, the RNC-ID IE shall be ignored.	YES	ignore
Provided Information	M		9.2.1.85		YES	ignore
Extended RNC-ID	0		9.2.1.50a	The Extended RNC-ID IE shall be used if the RNC identity has a value larger than 4095.	YES	reject

9.1.70 ENHANCED RELOCATION REQUEST

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
			Reference			
Message Type	М		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		1	
Cause	M		9.2.1.5		YES	reject
Permanent NAS UE Identity	M		9.2.1.73		YES	reject
SRNC-ID	0		RNC-ID 9.2.1.50	If the Extended SRNC-ID IE is included in the message, the SRNC-ID IE shall be ignored.	YES	reject
Extended SRNC-ID	0		Extended RNC-ID 9.2.1.50a	The Extended SRNC-ID IE shall be used if the RNC identity has a value larger than 4095.	YES	reject
S-RNTI	M		9.2.1.53		YES	reject
RANAP Enhanced Relocation Information Request	М		9.2.1.124		YES	reject

9.1.71 ENHANCED RELOCATION RESPONSE

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
RANAP Enhanced Relocation	M		9.2.1.125		YES	ignore
Information Response						

9.1.72 ENHANCED RELOCATION FAILURE

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
			Reference			
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		-	
Cause	M		9.2.1.5		YES	ignore
Criticality Diagnostics	0		9.2.1.13		YES	ignore

9.1.73 ENHANCED RELOCATION CANCEL

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		-	
Cause	M		9.2.1.5		YES	ignore

9.1.74 ENHANCED RELOCATION SIGNALLING TRANSFER

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		-	
L3 Information	M		9.2.1.32		YES	ignore

9.1.75 ENHANCED RELOCATION RELEASE

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	
Released CN Domain	M		9.2.1.126		YES	ignore

9.1.76 MBSFN MCCH INFORMATION (FDD)

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
MBSFN Cluster Identity	M		9.2.1.128		YES	ignore
MCCH Message List		1 <maxno ofMCCHM essages></maxno 			YES	reject
>L3 Information	М		9.2.1.32	See Note1 below.	_	
CFN	M		9.2.1.9		YES	reject
MCCH Configuration Info		01			YES	ignore
>Secondary CCPCH system information MBMS	M		9.2.1.127		_	
MBSFN Scheduling Transmission Time Interval info List		0 <maxnr OfMBMSL 3></maxnr 			YES	ignore
>TMGI	М		9.2.1.80		_	
>MBSFN Scheduling Transmission Time Interval	M		9.2.1.129		-	

Note 1: The IE Contains one of the following messages defined in TS 25.331 [16]: MBMS MODIFIED SERVICES INFORMATION, MBMS UNMODIFIED SERVICES INFORMATION, MBMS GENERAL INFORMATION, MBMS COMMON P-T-M RB INFORMATION, MBMS CURRENT Cell PTM RB INFORMATION.

Range bound	Explanation
maxnoofMCCHMessages	Maximum number of MCCH Messages simultaneous sent on MCCH
maxNrOfMBMSL3	Maximum number of MBMS service in L3 information

9.1.77 SECONDARY UL FREQUENCY REPORT

FDD Message 9.1.77.1

IE/Group Name	Presence	Range	IE Type and	Semantics	Criticality	Assigned
			Reference	Description		Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	М		9.2.1.59		_	
Activation Information	М		9.2.2.109		YES	ignore

9.1.78 SECONDARY UL FREQUENCY UPDATE INDICATION

9.1.78.1 FDD Message

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	M		9.2.1.59		_	
Activation Information	M		9.2.2.109		YES	ignore

9.1.79 ENHANCED RELOCATION RESOURCE REQUEST [TDD]

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
IMSI	0		9.2.1.31		YES	reject
Source ID	M		9.2.1.142		YES	ignore
Target ID	M		9.2.1.143		YES	reject
MS Classmark 2	M		9.2.1.144		YES	reject
MS Classmark 3	M		9.2.1.145		YES	ignore
Speech Version	M		9.2.1.146		YES	ignore

9.1.80 ENHANCED RELOCATION RESOURCE RESPONSE [TDD]

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
D-RNTI	M		9.2.1.24		YES	ignore
L3 Information	M		9.2.1.32	The IE contains HANDOVER COMMAND message defined in TS 44.018 [67]	YES	ignore
Cell Capacity Class Value	0		9.2.1.5C		YES	ignore
Load Value	0		9.2.1.33A		YES	ignore

9.1.81 ENHANCED RELOCATION RESOURCE FAILURE [TDD]

IE/Group Name	Presence	Range	IE Type and	Semantics	Criticality	Assigned
			Reference	Description		Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
Cause	M		9.2.1.5		YES	ignore
Cell Capacity Class Value	0		9.2.1.5C		YES	ignore
Load Value	0		9.2.1.33A		YES	ignore

9.1.82 ENHANCED RELOCATION RESOURCE RELEASE COMMAND [TDD]

IE/Group Name	Presence	Range	IE type and reference	Semantics description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	reject
Transaction ID	M		9.2.1.59		_	
Cause	М		9.2.1.5		YES	ignore

9.1.83 ENHANCED RELOCATION RESOURCE RELEASE COMPLETE [TDD]

IE/Group Name	Presence	Range	IE type and reference	Semantics description	Criticality	Assigned Criticality
Message Type	М		9.2.1.40		YES	reject
Transaction ID	М		9.2.1.59		_	

9.1.84 INFORMATION TRANSFER CONTROL REQUEST

IE/Group Name	Presence	Range	IE type and reference	Semantics description	Criticality	Assigned Criticality
Message Type	M		9.2.1.40		YES	ignore
Transaction ID	М		9.2.1.59		_	
CHOICE Control Type	М				YES	ignore
>Suspension					_	
>>Controlled Object Scope	М		9.2.1.147		_	
>Resume					_	
>>Controlled Object Scope	М		9.2.1.147		_	

9.2 Information Element Functional Definition and Contents

9.2.0 General

Subclause 9.2 presents the RNSAP IE definitions in tabular format. The corresponding ASN.1 definition is presented in subclause 9.3. In case there is a contradiction between the tabular format in subclause 9.2 and the ASN.1 definition, the ASN.1 shall take precedence, except for the definition of conditions for the presence of conditional elements, in which the tabular format shall take precedence.

When specifying information elements which are to be represented by bitstrings, if not otherwise specifically stated in the semantics description of the concerned IE or elsewhere, the following principle applies with regards to the ordering of bits:

- The first bit (leftmost bit) contains the most significant bit (MSB);
- The last bit (rightmost bit) contains the least significant bit (LSB);
- When importing bitstrings from other specifications, the first bit of the bitstring contains the first bit of the concerned information;

9.2.1 Common Parameters

This subclause contains parameters that are common to FDD and TDD.

9.2.1.1 Allocation/Retention Priority

This parameter indicates the priority level in the allocation and retention of transport channel resources in DRNS. DRNS may use the Allocation/Retention priority information of the transport channels composing the RL to prioritise requests for RL Setup/addition and reconfiguration. In similar way, DRNS may use the allocation/Retention priority information of the transport channels composing the RL to prioritise which RL shall be set to failure, in case prioritisation is possible. See Annex A.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Priority Level	М		INTEGER(0. .15)	This IE indicates the priority of the request. Usage: Value "0" means "Spare"; It shall be treated as a logical error if received. Values between 1 and 14 are ordered in decreasing order of priority, "1" being the highest and "14" the lowest. Value "15" means "No Priority".
Pre-emption Capability	M		ENUMERAT ED(shall not trigger pre- emption, may trigger pre-emption)	
Pre-emption Vulnerability	М		ENUMERAT ED(not pre- emptable, pre- emptable)	

9.2.1.2 Allowed Queuing Time

This parameter specifies the maximum queuing time that is allowed in the DRNS until the DRNS must start to execute the request.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Allowed Queuing Time			INTEGER(1.	Unit: Seconds
			.60)	

9.2.1.2A Allowed Rate Information

The *Allowed Rate Information* IE indicates the TFI corresponding to the highest allowed bit rate for the uplink and/or the downlink of a DCH. The SRNC is allowed to use any rate being lower than or equal to the rate corresponding to the indicated TFI.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Allowed UL Rate	0		INTEGER(1. .maxTFcount	"1": TFI 0, "2": TFI 1, "3": TFI 2,
Allowed DL Rate	0		INTEGER(1. .maxTFcount	"1": TFI 0, "2": TFI 1, "3": TFI 2,

9.2.1.2B Altitude and Direction

This IE contains a description of Altitude and Direction.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Direction of Altitude	M		ENUMERAT ED(Height, Depth)	
Altitude	M		INTEGER(02 ¹⁵ -1)	The relation between the value (N) and the altitude (a) in meters it describes is N≤ a <n+1, except="" for="" n="2<sup">15-1 for which the range is extended to include all grater values of (a).</n+1,>

9.2.1.2C Antenna Co-location Indicator

The Antenna Co-location Indicator indicates whether the antenna of the serving and neighbouring cells are approximately co-located.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Antenna Co-location			ENUMERAT	
Indicator			ED(co-	
			located,)	

9.2.1.2D Alternative Format Reporting Indicator

This IE indicates if DRNS may report a measurement using an alternative format.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Alternative Format			ENUMERAT	
Reporting Indicator			ED	
,			(Alternative	
			format is	
			allowed,)	

9.2.1.3 Binding ID

The Binding ID is the identifier of a user data stream.

In case of transport bearer establishment with ALCAP (TS 25.426 [3]TS 25.424 [35]), this IE contains the identifier that is allocated at the DRNS and that is unique for each transport bearer under establishment to/from the DRNS.

If the Transport Layer Address contains an IP address (IETF RFC 2460 [33]), this IE contains the UDP port (IETF RFC 768 [34]) intended to be used for the user plane transport.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Binding ID			OCTET STRING (14,)	If the Binding ID includes an UDP port, the UDP port is included in octet 1 and 2. The first octet of the UDP port field shall be included in the first octet of the Binding ID.

9.2.1.4 BLER

This Block Error Rate defines the target radio interface Transport Block Error Rate of the transport channel. BLER is used by the DRNS to determine the needed SIR targets, for admission control and power management reasons.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
BLER			INTEGER(-	Step 0.1. (Range -6.30).
			630)	It is the Log10 of the BLER

9.2.1.4A Block STTD Indicator

Void.

9.2.1.4B Burst Mode Parameters

The Burst Mode Parameters IE provides all the relevant information in order to able IPDL in the Burst mode.

IE/Group name	Presence	Range	IE Type and Reference	Semantics Description
Burst Start	M		INTEGER(015)	See TS 25.214 [10] and TS 25.224 [22]
Burst Length	М		INTEGER(1 025)	See TS 25.214 [10] and TS 25.224 [22]
Burst freq	M		INTEGER(116)	See TS 25.214 [10] and TS 25.224 [22]

9.2.1.5 Cause

The purpose of the cause information element is to indicate the reason for a particular event for the whole protocol.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Cause Group	M			•
>Radio Network Layer				
CHOICE Cause Group		Range	ENUMERATED (Unknown C-ID, Cell not Available, Power Level not Supported, UL Scrambling Code Already in Use, DL Radio Resources not Available, UL Radio Resources not Available, Measurement not Supported For The Object, Combining Resources Not Available, Reconfiguration not Allowed, Requested Configuration not Supported, Synchronisation Failure, Requested Tx Diversity Mode not Supported, Measurement Temporarily not Available, Unspecified, Invalid CM Settings, Reconfiguration CFN not Elapsed, Number of DL Codes Not Supported, Dedicated Transport Channel Type not Supported, UL Shared Channel Type not Supported, UL Shared Channel Type not Supported, UL Spreading Factor not Supported, Common Transport Channel Type not Supported, UL Spreading Factor not Supported, CM not Supported, Transaction not Supported by Destination Node B, RL Already Activated/Allocated,, Number of UL Codes Not Supported, Cell reserved for operator use, DPC Mode Change not Supported, Information temporarily not available, Information Provision not supported for the object, Power Balancing status not compatible, Delayed Activation not Supported, RL Timing Adjustment Not Supported, Unknown RNTI, Measurement Repetition Rate not Compatible with Current Measurements, UE not Capable to Implement Measurements, UE not Capable to Implement Measurement, F-DPCH not supported, Continuous Packet Connectivity DTX- DRX operation not supported,	Semantics Description
			DRX operation not supported, Continuous Packet Connectivity HS- SCCH less operation not supported, MIMO not supported, E-DCH TTI2ms not supported, Continuous Packet Connectivity DTX-	
			DRX operation not available, Continuous Packet Connectivity UE DTX Cycle not available, MIMO not available, SixteenQAM UL not supported, HS-DSCH MAC-d PDU Size Format not supported, EDBCH Slot Format operation not	
			F-DPCH Slot Format operation not supported,	

		E-DCH MAC-d PDU Size Format not available, E-DPCCH Power Boosting not supported, Trelocprep Expiry, Relocation Cancelled, Traffic Load In The Target Cell Higher Than In The Source Cell, Time critical Relocation, Resource optimisation relocation, Relocation desirable for radio reasons, Directed Retry, Reduce Load in Serving Cell, No lu CS UP relocation, SixtyfourQAM DL and MIMO Combined not available, Multi Cell operation not supported, Semi-Persistent scheduling not supported, Continuous Packet Connectivity DRX not supported, Continuous Packet Connectivity DRX not available, Enhanced Relocation not Supported, Relocation Not Supported Due To PUESBINE Feature, Relocation Failure In Target RNC, Relocation Failure In Target RNC, Relocation Algorithms not Supported, SixtyfourQAM DL and MIMO Combined not supported, TX diversity for MIMO UE on DL Control Channels not available, Single Stream MIMO not supported, Single Stream MIMO not supported, Single Stream MIMO not available, Multi Cell operation with MIMO not available, Multi Cell operation with MIMO not available, Multi Cell operation with Single Stream MIMO not available, Multi Cell operation with Single Stream MIMO not supported, Cell Specific Tx Diversity Handling For Multi Cell Operation Not Available, Cell Specific Tx Diversity Handling For Multi Cell Operation Not Available, Cell Specific Tx Diversity Handling For Multi Cell Operation Not Supported, Frequency Specific Compressed Mode Not Available)	
		Frequency Specific Compressed Mode	
>Transport Layer		INOT AVAIIADIE)	
>>Transport Layer Cause	М	ENUMERATED (Transport Resource Unavailable, Unspecified,)	
>Protocol	NA	ENLIMERATED	
>>Protocol Cause >Misc	M	ENUMERATED (Transfer Syntax Error, Abstract Syntax Error (Reject), Abstract Syntax Error (Ignore and Notify), Message not Compatible with Receiver State, Semantic Error, Unspecified, Abstract Syntax Error (Falsely Constructed Message),)	
>>Miscellaneous Cause	М	ENUMERATED	
		(Control Processing Overload,	

Hardware Failure, O&M Intervention, Not enough User Plane Processing Resources,
· · · · · · · · · · · · · · · · · · ·
Unspecified,)

The meaning of the different cause values is described in the following table. In general, "not supported" cause values indicate that the concerned capability is missing. On the other hand, "not available" cause values indicate that the concerned capability is present, but insufficient resources were available to perform the requested action.

Radio Network Layer cause	Meaning
Cell not Available	The concerned cell is not available
Cell reserved for operator use	The concerned cell is reserved for operator use
Cell Specific Tx Diversity Handling For Multi Cell Operation Not Available	Cell specific tx diversity handling for multi cell operation not available in the concerned cell(s)
Cell Specific Tx Diversity Handling For Multi Cell Operation Not Supported	The concerned cell(s) do not support the cell specific tx diversity handling for multi cell operation
CM not Supported	The concerned cell(s) do not support Compressed Mode
Combining not Supported	The DRNS does not support the RL combining for the concerned cells
Combining Resources Not	The value of the received Diversity Control Field IE was set to "Must", but
Available	the DRNS cannot perform the requested combining
Common Transport Channel Type	The concerned cell(s) do not support the RACH and/or FACH Common
not Supported	Transport Channel Type
Continuous Packet Connectivity DTX-DRX operation not available	CPC resources for DTX-DRX operation not available in the concerned cell(s).
Continuous Packet Connectivity DRX not available	HSPA resources for DRX operation not available in the concerned cell(s). (for 1.28Mcps TDD only)
Continuous Packet Connectivity	The concerned cell(s) do not support the Continuous Packet Connectivity
DRX not supported	DRX operation (for 1.28Mcps TDD only)
Continuous Packet Connectivity DTX-DRX operation not Supported	The concerned cell(s) do not support the Continuous Packet Connectivity DTX-DRX operation
Continuous Packet Connectivity	The concerned cell(s) do not support the Continuous Packet Connectivity
HS-SCCH less operation not Supported	HS-SCCH less operation
Continuous Packet Connectivity UE	CPC resources for the UE DTX Cycle not available in the concerned
DTX Cycle not available Dedicated Transport Channel Type not Supported	cell(s). The concerned cell(s) do not support the Dedicated Transport Channel Type
Delayed Activation not Supported	The concerned cell(s) do not support delayed activation of RLs
Directed Retry	The reason for action is Directed Retry
DL Radio Resources not Available	The DRNS does not have sufficient DL radio resources available
DL SF not Supported	The concerned cell(s) do not support the requested DL SF
DL Shared Channel Type not Supported	The concerned cell(s) do not support the Downlink Shared Channel Type
DPC Mode Change not Supported	The concerned cells do not support the DPC mode changes
E-DCH MAC-d PDU Size Format not available	The selected E-DCH MAC-d PDU Size Format is not available in the concerned cell(s).
E-DCH not supported	The concerned cell(s) do not support E-DCH
E-DCH TTI2ms not supported	The concerned cell(s) do not support the E-DCH 2ms TTI operation
E-DPCCH Power Boosting not supported	The concerned cell(s) do not support the E-DPCCH Power Boosting.
Enhanced Relocation not Supported	The DRNS does not support the Enhanced Relocation.
F-DPCH not supported	The concerned cell(s) do not support the Fractional DPCH
F-DPCH Slot Format operation not supported	The concerned cell(s) do not support the F-DPCH Slot Format operation
Frequency Specific Compressed Mode not available	Frequency Specific Compressed Mode is not available in the concerned cell(s)
HS-DSCH MAC-d PDU Size	The concerned cell(s) do not support the selected HS-DSCH MAC-d PDU
Format not supported	Size Format
Information Provision not supported for the object	The RNS doesn't support provision of the requested information for the concerned object types
Information temporarily not available	The RNS can temporarily not provide the requested information
Invalid CM Settings	The concerned cell(s) consider the requested Compressed Mode settings invalid
Measurement not Supported For The Object	At least one of the concerned cell(s) does not support the requested measurement on the concerned object type
Measurement Repetition Rate not	The requested parameters for a forwarded UE measurement are not
Compatible with Current Measurements	compatible with the current measurement schedule in the SRNC.
Measurement Temporarily not Available	The DRNS can temporarily not provide the requested measurement value
MIMO not available	MIMO resources not available in the concerned cell(s).
MIMO not supported	The concerned cell(s) do not support the MIMO operation

Multi Cell E-DCH operation not available	Multi cell E-DCH operation is not available in the concerned cell(s).
Multi Cell E-DCH operation not supported	The concerned cell(s) do not support Multi cell E-DCH operation
Multi Cell operation not available	Multi Cell operation resources not available in the concerned cell(s).
Multi Cell operation not supported	The concerned cell(s) do not support Multi Cell operation
Multi Cell operation with MIMO not available	Multi Cell operation with MIMO resources not available in the concerned cell(s).
Multi Cell operation with MIMO not supported	The concerned cell(s) do not support Multi Cell operationwith MIMO
Multi Cell operation with Single Stream MIMO not available	Multi Cell operation with Single Stream MIMO resources not available in the concerned cell(s).
Multi Cell operation with Single Stream MIMO not supported	The concerned cell(s) do not support Multi Cell operationwith Single Stream MIMO
No lu CS UP relocation	The relocation is triggered by CS call and the source RNC has no lu CS user plane.
Number of DL Codes not Supported	The concerned cell(s) do not support the requested number of DL codes
Number of UL Codes not Supported	The concerned cell(s) do not support the requested number of UL codes
Power Balancing status not compatible	The power balancing status in the SRNC is not compatible with that of the DRNC.
Power Level not Supported	A DL power level was requested which the concerned cell(s) do not support
Reconfiguration CFN not Elapsed	The requested action cannot be performed due to that a COMMIT message was received previously, but the concerned CFN has not yet elapsed
Reconfiguration not Allowed	The SRNC does currently not allow the requested reconfiguration
Reduce Load in Serving Cell	Load on serving cell needs to be reduced.
Relocation Cancelled	The reason for the action is relocation cancellation.
Relocation Desirable For Radio	The reason for requesting relocation is radio related.
Reasons	
Relocation Failure In Target RNC	Relocation failed due to a failure in target RNC.
Relocation Not Supported Due To PUESBINE Feature	The DRNS can not support the relocation due to the PUESBINE Feature.
Relocation Target not allowed	Relocation to the indicated target cell is not allowed for the UE in question.
Requested Ciphering And/Or Integrity Protection Algorithms Not Supported	The DRNS does not support the requested ciphering and/or integrity protection algorithms.
Requested Configuration not Supported	The concerned cell(s) do not support the requested configuration i.e. power levels, Transport Formats, physical channel parameters,
Requested Tx Diversity mode not Supported	The concerned cell(s) do not support the requested transmit diversity mode
Resource Optimisation Relocation	The reason for requesting relocation is resource optimisation.
RL Already Activated/ Allocated	The DRNS has already allocated an RL with the requested RL ID for this UE Context
RL Timing Adjustment not Supported	The concerned cell(s) do not support adjustments of the RL timing
Semi-Persistent scheduling not supported	The concerned cell(s) do not support the Semi-Persistent scheduling operation (for 1.28Mcps TDD only)
SixteenQAM UL not Supported	The concerned cell(s) do not support the 16 QAM UL
SixtyfourQAM DL and MIMO Combined not available	SixtyfourQAM DL and MIMO Combined not available in the concerned cell(s)
SixtyfourQAM DL and MIMO	The DRNS does not support SixtyfourQAM DL and MIMO Combined for
Combined not supported Synchronisation Failure	the concerned cells. Loss of UL Uu synchronisation
Synchronisation Failure	
Time Critical Relocation	Relocation is requested for time critical reason i.e. this cause value is reserved to represent all critical cases where the connection is likely to be dropped if relocation is not performed.
Traffic Load In The Target Cell Higher Than In The Source Cell	Relocation to reduce load in the source cell is rejected, as the target cell's traffic load is higher than that in the source cell.
Transaction not Supported by Destination Node B	The requested action cannot be performed due to lack of support of the corresponding action in the destination Node B
T _{RELOCprep} Expiry	Relocation Preparation procedure is cancelled when timer T _{RELOCprep} expires.
Single Stream MIMO not supported	The concerned cell(s) do not support the Single Stream MIMO.
- igit tilltimit het eappertea	,

Single Stream MIMO not available	Single Stream MIMO resources not available in the concerned cell(s).
TX diversity for MIMO UE on DL	The DRNS does not have sufficient radio resources available to support
Control Channels not available	transmit diversity on downlink control channels when the UE is configured
	in MIMO mode with P-CPICH & S-CPICH as phase references (TS
	25.211 [8])
UE not Capable to Implement	The UE is not capable to initiate/report a requested measurement due to
Measurement	its current state or capabilities.
UL Radio Resources not Available	The DRNS does not have sufficient UL radio resources available
UL Scrambling Code Already in	The concerned UL scrambling code is already in use for another UE
Use	
UL SF not Supported	The concerned cell(s) do not support the requested minimum UL SF
UL Shared Channel Type not	The concerned cell(s) do not support the Uplink Shared Channel Type
Supported	
Unknown C-ID	The DRNS is not aware of a cell with the provided C-ID
Unknown RNTI	The SRNC or DRNC is not aware of a UE indicated with the provided
	RNTI
Unspecified	Sent when none of the above cause values applies but still the cause is
	Radio Network Layer related

Transport Network Layer cause	Meaning
Transport resource unavailable	The required transport resources are not available
Unspecified	Sent when none of the above cause values applies but still the cause is
	Transport Network Layer related

Protocol cause	Meaning
Abstract Syntax Error (Reject)	The received message included an abstract syntax error and the
	concerned criticality indicated "reject" (see subclause 10.3)
Abstract Syntax Error (Ignore and	The received message included an abstract syntax error and the
Notify)	concerned criticality indicated "ignore and notify" (see subclause 10.3)
Abstract syntax error (falsely	The received message contained IEs or IE groups in wrong order or with
constructed message)	too many occurrences (see subclause 10.3)
Message not Compatible with	The received message was not compatible with the receiver state (see
Receiver State	subclause 10.4)
Semantic Error	The received message included a semantic error (see subclause 10.4)
Transfer Syntax Error	The received message included a transfer syntax error (see subclause 10.2)
Unspecified	Sent when none of the above cause values applies but still the cause is
	Protocol related

Miscellaneous cause	Meaning
Control Processing Overload	DRNS control processing overload
Hardware Failure	DRNS hardware failure
Not enough User Plane Processing	DRNS has insufficient user plane processing resources available
Resources	
O&M Intervention	Operation and Maintenance intervention related to DRNS equipment
Unspecified	Sent when none of the above cause values applies and the cause is not related to any of the categories Radio Network Layer, Transport Network Layer or Protocol.

9.2.1.5A Cell Geographical Area Identity (Cell GAI)

The Cell Geographical Area is used to identify the geographical area of a cell. The area is represented as a polygon. See TS 23.032 [25].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Cell GAI Geographical Co-ordinates		1 <maxnoofpoints></maxnoofpoints>		
>Latitude Sign	M		ENUMERAT ED(North, South)	
>Degrees of Latitude	M		INTEGER(02 ²³ -1)	The IE value (N) is derived by this formula: N≤2 ²³ X /90 < N+1 X being the latitude in degree (0°90°)
>Degrees of Longitude	M		INTEGER(-2 ²³ 2 ²³ -1)	The IE value (N) is derived by this formula: N≤2 ²⁴ X /360 < N+1 X being the longitude in degree (-180°+180°)

Range bound	Explanation		
maxnoofPoints	Maximum no. of points in polygon.		

9.2.1.5B Cell Geographical Area Additional Shapes (Cell GAI Additional Shapes)

This IE is used to provide several descriptions of the geographical area of a cell.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Cell GAI				
Additional Shapes				
>GA Point With Uncertainty				
>>GA Point With Uncertainty	М		9.2.1.30A	Ellipsoid point with uncertainty circle
>GA Ellipsoid point with uncertainty Ellipse				
>>GA Ellipsoid point with uncertainty Ellipse	М		9.2.1.30B	Ellipsoid point with uncertainty Ellipse
>GA Ellipsoid point with altitude				
>>GA Ellipsoid point with altitude	М		9.2.1.30C	Ellipsoid point with altitude
>GA Ellipsoid point with altitude and uncertainty Ellipsoid				
>>GA Ellipsoid point with altitude and uncertainty Ellipsoid	M		9.2.1.30D	Ellipsoid point with altitude and uncertainty Ellipsoid
>GA Ellipsoid Arc		-		
>>GA Ellipsoid Arc	M		9.2.1.30E	Ellipsoid Arc

9.2.1.5C Cell Capacity Class Value

The *Cell Capacity Class Value* IE contains the capacity class for both the uplink and downlink. *Cell Capacity Class Value* IE is the value that classifies the cell capacity with regards to the other cells. *Cell Capacity Class Value* IE only indicates resources that are configured for traffic purposes.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Uplink Cell Capacity Class Value	М		INTEGER(1100,)	Value 1 shall indicate the minimum uplink cell capacity, and 100 shall indicate the maximum uplink cell capacity. There should be linear relation between uplink cell capacity and Uplink Cell Capacity Class Value.
Downlink Cell Capacity Class Value	M		INTEGER(1100,)	Value 1 shall indicate the minimum downlink cell capacity, and 100 shall indicate the maximum downlink cell capacity. There should be linear relation between downlink cell capacity and Downlink Cell Capacity Class Value.

NOTE: Cell capacity class for GERAN cells is defined by the number of configured carriers in specific GERAN cells which ranges from integer 1 to 100. The value 1 shall indicate the minimum cell capacity and the value 100 shall indicate the maximum cell capacity.

9.2.1.5D Cell Global Identifier (CGI)

The Cell Global Identifier IE contains the Cell Global Identity as defined in TS 23.003 [1].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
LAI		1		
>PLMN Identity	М		OCTET STRING (3)	- digits 0 to 9, two digits per octet, - each digit encoded 0000 to 1001, - 1111 used as filler - bit 4 to 1 of octet n encoding digit 2n-1 - bit 8 to 5 of octet n encoding digit 2n -The PLMN Identity consists of 3 digits from MCC followed by either -a filler plus 2 digits from MNC (in case of 2 digit MNC) or -3 digits from MNC (in case of a 3 digit MNC).
>LAC	М		OCTET STRING (2)	0000 and FFFE not allowed
CI	М		OCTET STRING (2)	

9.2.1.6 Cell Identifier (C-ID)

The C-ID (Cell Identifier) is the identifier of a cell in one RNS.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
C-ID			INTEGER	
			(065535)	

9.2.1.7 Cell Individual Offset

Cell individual offset is an offset that will be applied by UE to the measurement results for a Primary-CPICH[FDD]/ Primary-CCPCH[TDD] or for GSM Carrier RSSI according to TS 25.331 [16].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Cell Individual Offset			INTEGER(-20+20)	-20 -> -10dB -19 -> -9.5dB
				+20 -> +10dB

9.2.1.8 Cell Parameter ID

The Cell Parameter ID identifies unambiguously the [3.84 Mcps TDD and 7.68Mcps TDD – Code Groups, Scrambling Codes, Midambles and Toffset] [1.28 Mcps TDD – SYNC-DL and SYNC-UL sequences, the scrambling codes and the midamble codes] (see TS 25.223 [13]).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Cell Parameter ID			INTEGER(0127,)	

9.2.1.9 CFN

Connection Frame Number for the radio connection, see TS 25.402 [17].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CFN			INTEGER(0 255)	

9.2.1.10 CFN Offset

Void

9.2.1.11 CN CS Domain Identifier

Identification of the CN node in the CS Domain.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
PLMN Identity	M		OCTET STRING (3)	- digits 0 to 9, two digits per octet, - each digit encoded 0000 to 1001, - 1111 used as filler - bit 4 to 1 of octet n encoding digit 2n-1 - bit 8 to 5 of octet n encoding digit 2n -The PLMN Identity consists of 3 digits from MCC followed by either -a filler plus 2 digits from MNC (in case of 2 digit MNC) or -3 digits from MNC (in case of a 3 digit MNC).
LAC	M		OCTET STRING (2)	0000 and FFFE not allowed

9.2.1.11A CN Domain Type

Identifies the type of core network domain.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CN Domain Type			ENUMERAT ED(CS domain, PS domain, Don't care,)	See in TS 25.331 [16]

9.2.1.12 CN PS Domain Identifier

Identification of the CN Node in the PS Domain.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
PLMN Identity	M		Reference OCTET STRING (3)	- digits 0 to 9, two digits per octet, - each digit encoded 0000 to 1001, - 1111 used as filler - bit 4 to 1 of octet n encoding digit 2n-1 - bit 8 to 5 of octet n encoding digit 2n - The PLMN Identity consists of 3 digits from MCC followed by either -a filler plus 2 digits from MNC (in case of 2 digit MNC) or -3 digits from MNC (in case of a 3 digit MNC).
LAC	M		OCTET STRING (2)	0000 and FFFE not allowed
RAC	М		OCTET STRING (1)	

9.2.1.12A Common Measurement Accuracy

The Common Measurement Accuracy IE indicates the accuracy of the common measurement.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Common Measurement Accuracy	M			
>T _{UTRAN-GPS} Measurement Accuracy Class				
>>T _{UTRAN-GPS} Measurement Accuracy Class	M		Tutran-gps Accuracy Class 9.2.1.59B	
>T _{UTRAN-GANSS} Measurement Accuracy Class				
>>Tutran-ganss Measurement Accuracy Class	M		Tutran-ganss Accuracy Class 9.2.1.112	

9.2.1.12B Common Measurement Object Type

Void.

9.2.1.12C Common Measurement Type

The Common Measurement Type identifies which measurement that shall be performed.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Common Measurement Type			ENUMERATED (UTRAN GPS Timing of Cell Frames for UE Positioning , SFN-SFN Observed Time Difference, load, transmitted carrier power, received total wide band power, UL timeslot ISCP,, RT Load, NRT Load Information, UpPTS interference, UTRAN GANSS Timing of Cell Frames for UE Positioning)	UL timeslot ISCP shall only be used by TDD. For measurements, which are requested on the lur-g interface, only load, RT Load and NRT Load information are used. "UpPTS interference" is used by 1.28Mcps TDD only "UpPTS interference" means "UpPCH interference" in the whole 25.423, refer to TS 25.225 [14] and TS 25.224 [22].

9.2.1.12D Common Measurement Value

The Common Measurement Value shall be the most recent value for this measurement, for which the reporting criteria were met.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
CHOICE Common Measurement Value	М				_	
> T _{UTRAN-GPS} Measurement Value Information				UTRAN only	_	
>>T _{UTRAN-GPS} Measurement Value Information	M		9.2.1.59D		_	
> SFN-SFN Measurement Value Information				UTRAN only	_	
>>SFN-SFN Measurement Value Information	M		9.2.1.52C		_	
>Load Value					_	
>>Load Value	M		9.2.1.33A		_	
>Transmitted Carrier Power Value				UTRAN only	_	
>>Transmitted Carrier Power Value	M		Transmitted Carrier Power 9.2.1.59A		_	
>Received Total Wide Band Power Value				UTRAN only	_	
>>Received Total Wide Band Power Value	М		Received Total Wide Band Power 9.2.2.35A		_	
>UL Timeslot ISCP Value				TDD Only	_	
>>UL Timeslot ISCP Value	М		UL Timeslot ISCP 9.2.3.13A		_	
>Additional Common Measurement Values					-	
>>RT Load Value			0.0.4.500		-	
>>>RT Load Value	М		9.2.1.50B		YES	ignore
>>NRT Load Information Value					_	
>>>NRT Load Information Value	М		9.2.1.411		YES	ignore
>>UpPTS interference				1.28Mcps TDD Only	-	
>>>UpPTS interference Value	М		INTEGER (0127,)	According to mapping in TS 25.123 [24]	YES	reject
>> T _{UTRAN-GANSS} Measurement Value Information				UTRAN only	_	
>>>T _{UTRAN-GANSS} Measurement Value Information	М		9.2.1.114		YES	reject

9.2.1.12E Common Measurement Value Information

The *Common Measurement Value Information* IE provides information both on whether the Common Measurement Value is provided in the message or not and if provided also the Common Measurement Value itself.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
CHOICE Measurement	M			
Availability				
>Measurement Available				
>>Common Measurement	M		9.2.1.12D	
Value				
>Measurement not Available			NULL	

9.2.1.12F Common Transport Channel Resources Initialisation Not Required

If present, this IE indicates that as far as the DRNC is concerned, there is no need to initiate a Common Transport Channel Resources Initialisation procedure if the SRNC wants to allocate common transport channel resources in the new cell.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Common Transport			ENUMERAT	
Channel Resources			ED(Not	
Initialisation Not Required			Required)	

9.2.1.12G Coverage Indicator

The Coverage Indicator indicates whether the serving and the neighbouring cell are overlapped, i.e. the cells have approximately same coverage area or whether the neighbouring cell covers or contained in the serving cell.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Coverage Indicator			ENUMERAT	
-			ED(Overlap,	
			Covers,	
			Contained	
			in,)	

9.2.1.13 Criticality Diagnostics

The *Criticality Diagnostics* IE is sent by an RNC when parts of a received message have not been comprehended or were missing, or if the message contained logical errors. When applicable, it contains information about which IEs that were not comprehended or were missing.

For further details on how to use the Criticality Diagnostics IE, see Annex C.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Procedure ID		01		Procedure ID is to be used if Criticality Diagnostics is part of Error Indication procedure, and not within the response message of the same procedure that caused the error	-	•
>Procedure Code	М		INTEGER(0255	caused the error	_	
>Ddmode	М		ENUMERATED(FDD, TDD, Common)	Common = common to FDD and TDD. Common Ddmode is also applicable for lurg procedures listed in section 7.	-	
Triggering Message	0		ENUMERATED(i nitiating message, successful outcome, unsuccessful outcome, outcome)	The Triggering Message is used only if the Criticality Diagnostics is part of Error Indication.	-	
Procedure Criticality	0		ENUMERATED(r eject, ignore, notify)	This Procedure Criticality is used for reporting the Criticality of the Triggering message (Procedure).	-	
Transaction ID	0		Transaction ID		_	
Information Element Criticality Diagnostics		0 <max noof errors></max 			-	
>IE Criticality	M		ENUMERATED(r eject, ignore, notify)	The IE Criticality is used for reporting the criticality of the triggering IE. The value "Ignore" shall never be used.	-	
>IE ID	M		INTEGER(0655 35)	The IE ID of the not understood or missing IE as defined in the ASN.1 part of the specification.	_	
>Repetition Number	0		INTEGER(0255)	The Repetition Number IE gives In case of a not understood IE: The number of occurrences of the reported IE up to and including the not understood occurrence In case of a missing IE: The number of occurrences up to but not including the missing occurrence. Note: All the counted		

			occurrences of the reported IE must he same topdown hierarchical messa structure of IEs wir assigned criticality above them.	aye h	
>Message Structure	0	9.2.1.3	The Message Structure IE describe structure IE describe structure in whithe not understood missing IE was detected. This IE is included the not understood is not the top level the message.	ich I or if I IE	ignore
>Type of Error	M		MERATED(derstood, g,)	YES	ignore

Range bound	Explanation
maxnooferrors	Maximum number of IE errors allowed to be reported with a single
	message.

9.2.1.14 C-RNTI

C-RNTI (Cell RNTI) is the UE identifier allocated by the DRNS to be used over the radio interface. It is unique in the cell. One UE Context has one unique C-RNTI value allocated in the DRNS.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
C-RNTI			INTEGER(0.	
			.65535)	

9.2.1.14A CTFC

The CTFC is an integer number calculated in accordance with TS 25.331 [16], subclause 14.10. Regarding the channel ordering, for all transport channels, 'TrCH1' corresponds to the transport channel having the lowest transport channel identity among all configured transport channels on this CCTrCH. 'TrCH2' corresponds to the transport channel having the next lowest transport channel identity, and so on.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE CTFC Format				
>2 bits long				
>>CTFC value	M		INTEGER (03)	
>4 bits long				
>>CTFC value	M		INTEGER (015)	
>6 bits long				
>>CTFC value	M		INTEGER (063)	
>8 bits long				
>>CTFC value	M		INTEGER (0255)	
>12 bits long				
>>CTFC value	M		INTEGER (04095)	
>16 bits long				
>>CTFC value	M		INTEGER (065535)	
>max nb bits long				
>>CTFC value	M		INTEGER	
			(0maxCTFC)	

Range Bound	Explanation
MaxCTFC	Maximum number of the CTFC value is calculated according to the following:
	$\sum_{i=1}^{I} (L_i - 1)P_i$
	with the notation according to TS 25.331 [16]

9.2.1.15 DCH Combination Indicator

Void

9.2.1.16 DCH ID

The DCH ID is the identifier of an active dedicated transport channel. It is unique for each active DCH among the active DCHs simultaneously allocated for the same UE.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DCH ID			INTEGER	
			(0255)	

9.2.1.16A DCH Information Response

The DCH Information IE provides information for DCHs that have been established or modified.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
DCH Information Response		1 <maxno ofDCHs></maxno 		Several DCHs belonging to the same set of coordinated DCHs may be included.	1	
>DCH ID	M		9.2.1.16		_	
>Binding ID	0		9.2.1.3		_	
>Transport Layer Address	0		9.2.1.62		_	
>Allowed Rate Information	0		9.2.1.2A		YES	ignore
>Transport Bearer Not Setup Indicator	0		9.2.2.4T	FDD Only	YES	Ignore

Range bound	Explanation		
maxnoofDCHs	Maximum number of DCHs for one UE.		

9.2.1.17 Dedicated Measurement Object Type

Void.

9.2.1.18 Dedicated Measurement Type

The Dedicated Measurement Type identifies the type of measurement that shall be performed.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Dedicated Measurement			ENUMERAT	RSCP and HS-SICH
Type			ED(SIR, SIR	Receptions Quality are used
			Error,	by TDD only, Rx Timing
			Transmitted	Deviation and Rx Timing
			Code Power,	Deviation 384 Extended are
			RSCP, Rx	used by 3.84 Mcps TDD only,
			Timing	Rx Timing Deviation LCR is
			Deviation,	used by 1.28 TDD only,
			Round Trip	Round Trip Time, SIR Error
			Time,, Rx	are used by FDD only.
			Timing	Angle Of Arrival LCR is used
			Deviation	by 1.28Mcps TDD only.
			LCR, Angle	Rx Timing Deviation 768 is
			Of Arrival	used by 7.68Mcps TDD only.
			LCR,	
			HS-SICH	
			Reception	
			Quality, Rx	
			Timing	
			Deviation	
			768, Rx	
			Timing	
			Deviation	
			384	
			Extended)	

NOTE: For definitions of the measurement types refer to TS 25.215 [11] and TS 25.225 [14].

9.2.1.19 Dedicated Measurement Value

The Dedicated Measurement Value shall be the most recent value for this measurement, for which the reporting criteria were met.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
CHOICE Dedicated Measurement Value	М				-	
>SIR Value					_	
>>SIR Value	М		INTEGER(063)	According to mapping in TS 25.133 [23] and TS 25.123 [24]	-	
>SIR Error Value				FDD Only	-	
>>SIR Error Value	М		INTEGER(0125)	According to mapping in TS 25.133 [23]	1	
>Transmitted Code Power Value					1	
>>Transmitted Code Power Value	M		INTEGER(0127)	According to mapping in TS 25.133 [23] and TS 25.123 [24] Values 0 to 9 and 123 to 127 shall not be used.	-	
>RSCP				TDD Only	-	
>>RSCP	М		INTEGER(0127)	According to mapping in TS 25.123 [24]	-	
>Rx Timing Deviation Value				3.84Mcps TDD Only	-	
>>Rx Timing Deviation	M		INTEGER(08191)	According to mapping in TS 25.123 [24]	-	
>Round Trip Time				FDD Only	_	
>>Round Trip Time	М		INTEGER(032767)	According to mapping in TS 25.133 [23]	-	
>Additional Dedicated Measurement Values					_	
>>Rx Timing Deviation Value LCR				1.28Mcps TDD Only	YES	reject
>>>Rx Timing Deviation LCR	M		INTEGER(0511)	According to mapping in TS 25.123 [24]	_	
>>Angle of Arrival Value LCR				1.28Mcps TDD only	YES	reject
>>>AOA LCR	М		INTEGER(0719)	According to mapping in TS 25.123 [24]	-	
>>>AOA LCR Accuracy Class	М		ENUMER ATED(A, B, C, D, E, F, G, H,)	According to mapping in TS 25.123 [24]	-	
>>HS-SICH reception quality			,	Applicable to TDD only	-	
>>>HS-SICH reception quality Value		1			YES	reject
>>>>Failed HS-SICH	М		INTEGER (020)	According to mapping in	_	

			I		
			TS 25.123		
			[24]		
>>>Missed HS-SICH	М	INTEGER	According to	_	
		(020)	mapping in		
		(TS 25.123		
			[24]		
>>>Total HS-SICH	М	INTEGER	According to	_	
77710101110 01011	141	(020)	mapping in		
		(020)	TS 25.123		
			[24]		
Dy Timing Davieties				YES	roinat
>>Rx Timing Deviation			7.68Mcps	152	reject
Value 7.68Mcps		INITE OF D	TDD Only		
>>>Rx Timing Deviation	M	INTEGER(According to	_	
7.68Mcps		065535)	mapping in		
			TS 25.123		
			[24]		
>>Rx Timing Deviation			3.84 Mcps	YES	reject
Value 3.84Mcps Extended			TDD Only		
>>>Rx Timing Deviation	M	INTEGER(According to	_	
3.84Mcps Extended		032767)	mapping in		
·		, , , , , , , , , , , , , , , , , , ,	TS 25.123		
			[24]		
>>Extended Round Trip			FDD Only	YES	ignore
Time					.3
>>>Extended Round	М	INTEGER	Continuation	_	
Trip Time Value		(3276710	of intervals		
The fillic value		3041)	with step size		
		3041)	as defined in		
			TS 25.133		
			[23].		

9.2.1.19A Dedicated Measurement Value Information

The *Dedicated Measurement Value Information* IE provides information both on whether or not the Dedicated Measurement Value is provided in the message and if provided also the Dedicated Measurement Value itself.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
CHOICE Measurement Availability Indicator	М				_	
>Measurement Available					_	
>>Dedicated Measurement Value	М		9.2.1.19		_	
>>CFN	0		9.2.1.9	Dedicated Measuremen t Time Reference	-	
>Measurement not Available			NULL		-	

9.2.1.19Aa Delayed Activation

The *Delayed Activation* IE indicates that the activation of the DL power shall be delayed until an indicated CFN or until a separate activation indication is received.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
CHOICE Delayed Activation	M			
>CFN				
>>Activation CFN	M		CFN 9.2.1.7	
>Separate Indication			NULL	

9.2.1.19Ab Delayed Activation Update

The Delayed Activation Update IE indicates a change of the activation of the DL power for a specific RL.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Delayed Activation Update	М			
>Activate				
>>CHOICE Activation Type	M			
>>>Synchronised				
>>>Activation CFN	M		CFN 9.2.1.7	
>>>Unsynchronised			NULL	
>>Initial DL TX Power	М		DL Power 9.2.1.21	
>>First RLS Indicator	0		9.2.2.16A	FDD Only
>>Propagation Delay	0		9.2.2.35	FDD Only
>>Extended Propagation Delay	0		9.2.2.33a	FDD Only
>Deactivate				
>>CHOICE Deactivation type	М			
>>>Synchronised				
>>>>Deactivation CFN	М		CFN 9.2.1.7	
>>>Unsynchronised			NULL	

9.2.1.19B DGPS Corrections

The *DGPS Corrections* IE contains DGPS information used by the UE Positioning A-GPS method. For further details on the meaning of parameters, see RTCM-SC104 [31].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
GPS TOW	M		INTEGER(060479 9)	Time in seconds. This field indicates the baseline time for which the corrections are valid	-	
Status/Health	М		ENUMERATED (UDRE scale 1.0, UDRE scale 0.75, UDRE scale 0.5, UDRE scale 0.3, UDRE scale 0.1, no data, invalid data)	This field indicates the status of the differential corrections	-	
Satellite DGPS		1 <ma< td=""><td>,</td><td></td><td>-</td><td></td></ma<>	,		-	
Corrections		xNoSa				
Information		t>				
>SatID	М		SAT ID 9.2.1.50A		-	
>IODE	M		BIT STRING(8)	This IE is the sequence number for the ephemeris for the particular satellite. It can be used to determine if new ephemeris is used for calculating the corrections that are provided. This eight-bit IE is incremented for each new set of ephemeris for the satellite and may occupy the numerical range of [0, 239] during normal operations.	-	
>UDRE	M		ENUMERATED (UDRE ≤1.0m, 1.0m < UDRE ≤ 4.0m, 4.0m < UDRE ≤ 8.0m, 8.0m < UDRE,)	User Differential Range Error. This field provides an estimate of the uncertainty (1-o) in the corrections for the particular satellite. The value in this field shall be multiplied by the UDRE Scale Factor in the common Corrections Status/Health field to determine the final UDRE estimate for the particular satellite	-	
>PRC	М		INTEGER(-20472047)	Scaling factor 0.32 meters	-	
>Range Correction Rate	М		INTEGER(-127 127)	Scaling factor 0.032 m/s	-	
>DGNSS Validity Period	0		9.2.1.138		YES	ignore

Range Bound	Explanation		
maxNoSat	Maximum number of satellites for which information can be		
	provided		

9.2.1.19C Discard Timer

The *Discard Timer* IE defines the time to live for a MAC-hs SDU starting from the instant of its arrival into an HSDPA Priority Queue. The DRNS shall use this information to discard out-of-date MAC-hs SDUs from the HSDPA Priority Queues.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
Discard Timer			ENUMERAT	Unit: ms
			ED (20, 40,	
			60, 80, 100,	
			120, 140,	
			160, 180,	
			200, 250,	
			300, 400,	
			500, 750,	
			1000, 1250,	
			1500, 1750,	
			2000, 2500,	
			3000, 3500,	
			4000, 4500,	
			5000, 7500,	
)	

9.2.1.20 Diversity Control Field

The Diversity Control Field indicates if the current RL may, must or must not be combined with the already existing RLs.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Diversity Control Field			ENUMERAT	
			ED(May,	
			Must, Must	
			not,	
)	

9.2.1.21 Diversity Indication

Void.

9.2.1.21A DL Power

The *DL Power* IE indicates a power level relative to the [FDD – primary CPICH power] [TDD – PCCPCH power] configured in a cell. [FDD – If referred to a DPCH, it indicates the power of the transmitted DPDCH symbols. If referred to an F-DPCH, it indicates the Reference F-DPCH TX Power.] If Transmit Diversity is applied to a downlink physical channel, the *DL Power* IE indicates the power offset between the linear sum of the power for this downlink physical channel on all branches and the [FDD – primary CPICH power] [TDD – PCCPCH power] configured in a cell.

[TDD-If referred to a DPCH, it indicates the power of a spreading factor 16 code, the power for a spreading factor 1 code would be 12 dB higher.]

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DL Power			INTEGER (- 350150)	Value = DL Power /10 Unit dB Range –35.0 +15.0 Step 0.1dB

9.2.1.22 Downlink SIR Target

Void

9.2.1.23 DPCH Constant Value

DPCH Constant Value is the power margin used by a UE to set the proper uplink power.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DPCH Constant Value			INTEGER (-	Unit dB
			1010)	Granularity 1 dB.

9.2.1.24 D-RNTI

The D-RNTI identifies the UE Context in the DRNC.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
D-RNTI			INTEGER(02^20 -1)	

9.2.1.25 D-RNTI Release Indication

The D-RNTI Release Indication indicates whether or not a DRNC shall release the D-RNTI allocated for a particular UE.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
D-RNTI Release Indication			ENUMERAT	
			ED(Release	
			D-RNTI, not	
			Release	
			D-RNTI)	

9.2.1.26 DRX Cycle Length Coefficient

The DRX Cycle Length Coefficient is used as input for the formula to establish the paging occasions to be used in DRX.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DRX Cycle Length			INTEGER	Refers to 'k' in the formula as
Coefficient			(39)	specified in TS 25.304 [15],
				Discontinuous Reception.

9.2.1.26A DSCH ID

Void.

9.2.1.26Aa DSCH Initial Window Size

Void.

9.2.1.26B DSCH Flow Control Information

Void.

9.2.1.26Ba DSCH-RNTI

Void.

9.2.1.26Bb Extended GSM Cell Individual Offset

Extended GSM Cell individual offset is an offset that will be applied by UE to the measurement results for GSM carrier RSSI according to TS 25.331 [16]. It shall be used when the offset exceeds the range of values that can be indicated using the *Cell Individual Offset* IE (Subclause 9.2.1.7).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Extended GSM Cell Individual			INTEGER (-	Unit in dB. Step size is 1 dB.
Offset			5011	
			1150)	

9.2.1.26C FACH Flow Control Information

The FACH Flow Control Information IE provides flow control information for each scheduling priority class for the FACH FP over Iur.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
FACH Flow Control Information		116			-	
>FACH Scheduling Priority	М		Scheduling Priority Indicator 9.2.1.51A		_	
>MAC-c/sh SDU Length		1 <maxnb MAC- c/shSDUL ength></maxnb 			_	
>>MAC-c/sh SDU Length	M		9.2.1.34		_	
>FACH Initial Window Size	М		9.2.1.27		_	

Range bound	Explanation		
maxNbMAC-c/shSDULength	Maximum number of different MAC-c/sh SDU lengths.		

9.2.1.27 FACH Initial Window Size

Indicates the initial number of MAC-c/sh SDUs that may be transmitted before an acknowledgement is received from the DRNC.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
FACH Initial Window Size			INTEGER(0255)	Number of frames (MAC-c/sh SDUs.) 255 = Unlimited number of FACH data frames.

9.2.1.28 FACH Priority Indicator

Void

9.2.1.28A FN Reporting Indicator

Frame Number reporting indicator.

Indicates if the SFN or CFN shall be included together with the reported measurement value.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
FN reporting indicator			ENUMERAT	
			ED(FN	
			reporting	
			required, FN	
			reporting not	
			required)	

9.2.1.29 Frame Handling Priority

This parameter indicates the priority level to be used during the lifetime of the DCH, [TDD – DSCH] for temporary restriction of the allocated resources due overload reason.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Frame Handling Priority			INTEGER (015)	0=Lowest Priority,
			(/	15=Highest Priority

9.2.1.30 Frame Offset

Frame Offset is the required offset between the dedicated channel downlink transmission frames (CFN, Connection Frame Number) and the broadcast channel frame offset (Cell Frame Number). The Frame Offset is used in the translation between Connection Frame Number (CFN) on Iub/Iur and least significant 8 bits of SFN (System Frame Number) on Uu. The Frame Offset is UE and cell specific.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Frame Offset			INTEGER (0255)	Frames

9.2.1.30A GA Point with Uncertainty

This IE contains one of the possible descriptions of a Cell Geographical Area.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Geographical Coordinates	M		9.2.1.30F	
Uncertainty Code	М		INTEGER(0127)	The uncertainty "r" is derived from the "uncertainty code" k by r = 10x(1.1 ^k -1)

9.2.1.30B GA Ellipsoid Point with Uncertainty Ellipse

This IE contains one of the possible descriptions of a Cell Geographical Area.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Geographical Coordinates	M		9.2.1.30F	
Uncertainty Ellipse	M		9.2.1.68A	
Confidence	М		INTEGER(0127)	

9.2.1.30C GA Ellipsoid Point with Altitude

This IE contains one of the possible descriptions of a Cell Geographical Area.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Geographical Coordinates	M		9.2.1.30F	
Altitude and direction	M		9.2.1.2B	

9.2.1.30D GA Ellipsoid Point with Altitude and Uncertainty Ellipsoid

This IE contains one of the possible descriptions of a Cell Geographical Area.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Geographical Coordinates	M		9.2.1.30F	
Altitude and direction	M		9.2.1.2B	
Uncertainty Ellipse	M		9.2.1.68A	
Uncertainty Altitude	M		INTEGER(
			0127)	
Confidence	M		INTEGER(
			0127)	

9.2.1.30E GA Ellipsoid Arc

This IE contains one of the possible descriptions of a Cell Geographical Area.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Geographical Coordinates	M		9.2.1.30F	
Inner radius	М		INTEGER(02 ¹⁶ -1)	The relation between the value (N) and the radius I in meters it describes is 5N≤ r <5(N+1), except for N=2 ¹⁶ -1 for which the range is extended to include all grater values of I.
Uncertainty radius	М		INTEGER(0127)	The uncertainty "r" is derived from the "uncertainty code" k by r = 10x(1.1 ^k -1)
Offset angle	М		INTEGER(0179)	The relation between the value (N) and the angle (a) in degrees it describes is 2N≤ a <2(N+1)
Included angle	М		INTEGER(0179)	The relation between the value (N) and the angle (a) in degrees it describes is 2N< a ≤2(N+1)
Confidence	M		INTEGER(0127)	

9.2.1.30F Geographical Coordinates

This IE contains the description of geographical coordinates.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Latitude Sign	M		ENUMERAT ED(North, South)	
Degrees Of Latitude	M		INTEGER(02 ²³ -1)	The IE value (N) is derived by this formula: N≤2 ²³ X /90 < N+1 X being the latitude in degree (0° 90°)
Degrees Of Longitude	M		INTEGER(-2 ²³ 2 ²³ -1)	The IE value (N) is derived by this formula: N≤2 ²⁴ X /360 < N+1 X being the longitude in degree (-180°+180°)

9.2.1.30Fa GERAN Cell Capability

The GERAN Cell Capability IE is used to transfer the capabilities of a certain GERAN cell via the Iur interface.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
GERAN Cell Capability	M		BIT STRING (16)	Each bit indicates whether a cell supports a particular functionality or not. The value 1 of a bit indicates that the corresponding functionality is supported in a cell and value 0 indicates that the corresponding functionality is not supported in a cell. Each bit is defined as follows. The first bit: A/Gb mode. The second bit: lu mode. Note that undefined bits are considered as a spare bit and spare bits shall be set to 0 by the transmitter and shall be ignored by the receiver.

9.2.1.30Fb GERAN Classmark

The GERAN Classmark IE is used to transfer the capabilities of a certain GERAN Iu-mode capable cell via the Iur interface.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
GERAN Classmark	М		OCTET STRING	Contents defined in TS 48.008 [38]

9.2.1.30Fc GERAN System Information

The GERAN System Information IE provides GERAN specific information.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
GERAN System Info		1 <maxnrofger ANSI></maxnrofger 		
>GERAN System Info Block	M		OCTET STRING (123)	The first octet contains octet 1 of the GERAN system information block, the second octet contains octet 2 of the GERAN system information block and so on.

Range bound	Explanation
maxNrOfGERANSI	Maximum number of GERAN SI blocks that can be provided as
	part of NACC information

9.2.1.30G GPS Almanac

This IE provides the information regarding the GPS Almanac. For further details on the meaning of parameters, see ICD-GPS-200 [30].

IE/Group name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
WNa	M		BIT STRING(8)		_	
Satellite Almanac Information	М	1 <maxn oOfSatAl manac></maxn 		See Note 1.	_	
>DataID	М		INTEGER (03)		_	
>SatID	М		SAT ID 9.2.1.50A		_	
>e	M		BIT STRING(16)		_	
>t _{oa}	M		BIT STRING(8)		_	
>δi	M		BIT STRING(16)		_	
>OMEGADOT	М		BIT STRING(16)		_	
>SV Health	М		BIT STRING(8)		_	
>A ^{1/2}	M		BIT STRING(24)		_	
>OMEGA ₀	M		BIT STRING(24)		_	
>M ₀	M		BIT STRING(24)		_	
>ω	M		BIT STRING(24)		_	
>af ₀	М		BIT STRING(11)		_	
>af ₁	М		BIT STRING(11)		_	
SV Global Health	0		BIT STRING(364)		_	
Complete Almanac Provided	0		BOOLEAN	This field indicates whether almanac is provided for the full GPS constellation or not. TRUE means complete GPS almanac is provided.	YES	ignore
descriptior through m	n. Repetitions	1 through ma	ed representation of axNoSat and repetition of presented by separa			

Range Bound	Explanation
maxNoOfSatAlmanac	Maximum number of satellite almanacs for which information
	can be provided

9.2.1.30H GPS Ionospheric Model

This IE provides the information regarding the GPS Ionospheric Model. For further details on the meaning of parameters, see ICD-GPS-200 [30].

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
α_0	M		BIT	
			STRING(8)	
α_1	M		BIT	
			STRING(8)	
α_2	M		BIT	
			STRING(8)	
0/3	M		BIT	
			STRING(8)	
β_0	M		BIT	
			STRING(8)	
β1	M		BIT	
•			STRING(8)	
β_2	M	•	BIT	
			STRING(8)	
β3	M		BIT	·
-			STRING(8)	

9.2.1.30I GPS Navigation Model and Time Recovery

This IE contains subframes 1 to 3 of the GPS navigation message. For further details on the meaning of parameters, see ICD-GPS-200 [30].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Navigation Message 1to3		1 <maxnosat></maxnosat>	11010101100	200011011
>Transmission TOW	M		INTEGER010485	Time of the Week
			75)	when the message is
				broadcast.
>SatID	M		SAT ID	
			9.2.1.50A	
>TLM Message	M		BIT STRING(14)	
>Tlm Revd I	M		BIT STRING(2)	
>HO-Word	M		BIT STRING(22)	
>WN	M		BIT STRING(10)	
>C/A or P on L2	M		BIT STRING(2)	
>User Range Accuracy	М		BIT STRING(4)	
Index			DIT 070 (0)	
>SV Health	M		BIT STRING(6)	
>IODC	M		BIT STRING(10)	
>L2 P Data Flag	M		BIT STRING(1)	
>SF 1 Reserved	M		BIT STRING(87)	
>T _{GD}	M		BIT STRING(8)	
>t _{oc}	M		BIT STRING(16)	
>af ₂	M		BIT STRING(8)	
>af₁	М		BIT STRING(16)	
>af ₀	M		BIT STRING(22)	
>C _{rs}	M		BIT STRING(16)	
>∆n	M		BIT STRING(16)	
>M ₀	M		BIT STRING(32)	
>C _{uc}	M		BIT STRING(16)	
>e	M		BIT STRING(32)	
>C _{us} >(A) ^{1/2}	M		BIT STRING(16)	
>(A) ^{1/2}	M		BIT STRING(32)	
>t _{oe}	M		BIT STRING(16)	
>Fit Interval Flag	M		BIT STRING(1)	
>AODO	M		BIT STRING(5)	
>C _{ic}	M		BIT STRING(16)	
>OMEGA ₀	M		BIT STRING(32)	
>C _{is}	M		BIT STRING(16)	
>i ₀	M		BIT STRING(32)	
>C _{rc}	M		BIT STRING(16)	
>ω	M		BIT STRING(32)	
>OMEGAdot	M		BIT STRING(24)	
>ldot	M		BIT STRING(14)	
>Spare/zero fill	M		BIT STRING(20)	

Range Bound	Explanation
maxNoSat	Maximum number of satellites for which information can be
	provided

9.2.1.30J GPS Real-Time Integrity

This IE provides the information regarding the status of the GPS constellation. For further details on the meaning of parameters, see ICD-GPS-200 [30].

IE/Group name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Bad Satellites Presence	M			
>Bad Satellites				
>>Satellite Information		1 <maxn oSat></maxn 		
>>>BadSatID	М		SAT ID 9.2.1.50A	
>No Bad Satellites			NULL	

Range Bound	Explanation
MaxNoSat	Maximum number of satellites for which information can be
	provided

9.2.1.30K GPS Receiver Geographical Position (GPS RX Pos)

The GPS Receiver Geographical Position is used to identify the geographical coordinates of a GPS receiver relevant for a certain Information Exchange Object.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Geographical Coordinates	M		9.2.1.30F	
Altitude and direction	М		9.2.1.2B	

9.2.1.30L GPS UTC Model

This IE provides the information regarding the GPS UTC Model. For further details on the meaning of parameters, see ICD-GPS-200 [30].

IE/Group name	Presence	Range	IE Type and Reference	Semantics Description
A ₁	M		BIT STRING(24)	
A ₀	M		BIT STRING(32)	
tot	M		BIT STRING(8)	
Δt_{LS}	M		BIT STRING(8)	
WNt	M		BIT STRING(8)	
WN _{LSF}	M		BIT STRING(8)	
DN	M		BIT STRING(8)	
Δt_{LSF}	M		BIT STRING(8)	

9.2.1.30M Guaranteed Rate Information

The *Guaranteed Rate Information* IE indicates the TFI corresponding to the guaranteed bit rate for the uplink and/or the downlink of a DCH.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Guaranteed UL Rate	0		INTEGER(1. .maxTFcount	"1": TFI 0, "2": TFI 1, "3": TFI 2,
Guaranteed DL Rate	0		INTEGER(1. .maxTFcount	"1": TFI 0, "2": TFI 1, "3": TFI 2,

9.2.1.30N HCS Prio

The HCS Prio is the characteristics of the cell as defined in TS 25.304 [15].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
HCS Prio			INTEGER	0=Lowest Priority,
			(07)	
				7=Highest Priority

9.2.1.30NA HS-DSCH Information To Modify Unsynchronised

The *HS-DSCH Information To Modify Unsynchronised* IE is used for modification of HS-DSCH information in a UE Context with the Unsynchronised Radio Link Reconfiguration procedure.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
HS-DSCH MAC-d Flow Specific Information		0 <maxn oofMACd Flows></maxn 		•	_	
>HS-DSCH MAC-d Flow ID	М	110000	9.2.1.300		_	
>Allocation/Retention Priority	0		9.2.1.1		_	
>Transport Bearer Request Indicator	М		9.2.1.61		_	
>Traffic Class	0		9.2.1.58A		_	
>Binding ID	0		9.2.1.3	Shall be ignored if bearer establishment with ALCAP.	_	
>Transport Layer Address	0		9.2.1.62	Shall be ignored if bearer establishment with ALCAP.	_	
>TNL QoS	0		9.2.1.56A	Shall be ignored if bearer establishment with ALCAP.	YES	ignore
Priority Queue Information		0 <maxn oofPrioQ ueues></maxn 			_	
>Priority Queue ID	М		9.2.1.45A		_	
>Scheduling Priority Indicator	0		9.2.1.51A		_	
>Discard Timer	0		9.2.1.19C		_	
>MAC-hs Guaranteed Bit Rate	0		9.2.1.34Aa		_	
CQI Power Offset	0		9.2.2.24b	For FDD only	_	
ACK Power Offset	0		9.2.2.b	For FDD only	_	
NACK Power Offset	0		9.2.2.26a	For FDD only	_	
HS-SCCH Power Offset TDD ACK NACK Power Offset	0		9.2.2.19d 9.2.3.7l	For FDD only For TDD only	_	
HARQ Preamble Mode	0		9.2.2.57	For FDD only	YES	ignore
MIMO Mode Indicator	Ö		9.2.1.135	For FDD and 1.28Mcps TDD only	YES	reject
Sixtyfour QAM Usage Allowed Indicator	0		9.2.2.79A	For FDD only	YES	ignore
Enhanced HS Serving CC Abort	0		ENUMERAT ED (Abort Enhanced HS Serving CC,)	For FDD only	YES	reject
UE Support Indicator Extension	0		9.2.2.103		YES	ignore
Power Offset For S-CPICH for MIMO Request Indicator	0		9.2.2.105	For FDD only	YES	ignore
Single Stream MIMO Mode Indicator	0		9.2.2.107	For FDD only	YES	reject

9.2.1.30Na HS-DSCH Initial Capacity Allocation

The *HS-DSCH Initial Capacity Allocation* IE provides flow control information for each scheduling priority class for the HS-DSCH FP over Iur.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
HS-DSCH Initial Capacity Allocation		1< maxnoof PrioQueu es>			_	
>Scheduling Priority Indicator	М		9.2.1.51A		_	
>Maximum MAC-d PDU Size	M		MAC-d PDU Size 9.2.1.34A	Shall be ignored if Maximum MAC-d PDU Size Extended IE is present.	-	
>HS-DSCH Initial Window Size	М		9.2.1.30Nb		_	
>Maximum MAC-d PDU Size Extended	0		MAC PDU Size Extended 9.2.1.34D		YES	ignore

Range Bound	Explanation		
maxnoofPrioQueuess	Maximum number of Priority Queues		

9.2.1.30Nb HS-DSCH Initial Window Size

Indicates the initial number of MAC-d PDUs (or octets in case *HS-DSCH MAC-d PDU Size Format* = "Flexible MAC-d PDU Size") that may be transmitted before new credits are received from the DRNC.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
HS-DSCH Initial Window Size			INTEGER (1255)	Number of MAC-d PDUs If HS-DSCH MAC-d PDU Size Format = "Flexible MAC-d PDU Size" the credit shall be determined in octets: credit (in octets) = Maximum MAC-d PDU Size extended* HS-DSCH Initial Window Size

9.2.1.300 HS-DSCH MAC-d Flow ID

HS-DSCH MAC-d Flow ID is the unique identifier for one MAC-d flow.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
HS-DSCH MAC-d Flow ID			INTEGER (07)	

9.2.1.30OA HS-DSCH MAC-d Flows Information

The *HS-DSCH MAC-d Flows Information* IE is used for the establishment of HS-DSCH MAC-d flows for a UE Context.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
HS-DSCH MAC-d Flow Specific Information		1 <maxn oofMACd Flows></maxn 		•	_	
>HS-DSCH MAC-d Flow ID	М		9.2.1.300		_	
>Allocation/Retention Priority	М		9.2.1.1		_	
>Traffic Class	M		9.2.1.58A		_	
>Binding ID	0		9.2.1.3	Shall be ignored if bearer establishment with ALCAP.	_	
>Transport Layer Address	O		9.2.1.62	Shall be ignored if bearer establishment with ALCAP.	_	
>TNL QoS	0		9.2.1.56A	Shall be ignored if bearer establishment with ALCAP.	YES	ignore
>TrCH Source Statistics Descriptor	0		9.2.1.65		YES	ignore
Priority Queue Information		1 <maxn oofPrioQ ueues></maxn 			_	
>Priority Queue ID	М	40400	9.2.1.45A		_	
>Associated HS-DSCH MAC-d Flow	M		HS-DSCH MAC-d Flow ID 9.2.1.30O	The HS-DSCH MAC-d Flow ID shall be one of the flow IDs defined in the HS-DSCH MAC-d Flow Specific Information of this IE. Multiple Priority Queues can be associated with the same HS- DSCH MAC-d Flow ID.	_	
>Scheduling Priority Indicator	M		9.2.1.51A		_	
>T1	М		9.2.1.54A		_	
>Discard Timer	0		9.2.1.19C		_	
>MAC-hs Window Size	M		9.2.1.34C		_	
>MAC-hs Guaranteed Bit Rate	0		9.2.1.34Aa		_	
>MAC-d PDU Size Index		1 <maxn oofMACd PDUinde xes></maxn 			_	
>>SID	M		9.2.1.52D	Shall be ignored if Maximum MAC-d PDU Size extended IE is present.	-	
>>MAC-d PDU Size	М		9.2.1.34A	Shall be ignored if <i>Maximum</i> <i>MAC-d PDU</i>	_	

			Size extended IE is present.		
>RLC Mode	M	9.2.1.48D		_	
>Maximum MAC-d PDU	0	MAC PDU		YES	reject
Size extended		Size			
		Extended			
		9.2.1.34D			
>DL RLC PDU Size	0	9.2.1.136		YES	ignore
Format					
>UE Aggregate Maximum	0	NULL		YES	ignore
Bit Rate Enforcement					
Indicator					

Range Bound	Explanation
maxnoofMACdFlows	Maximum number of HS-DSCH MAC-d flows
maxnoofPrioQueues	Maximum number of Priority Queues
maxnoofMACdPDUindexes	Maximum number of different MAC-d PDU SIDs

9.2.1.30OB HS-DSCH MAC-d Flows To Delete

The HS-DSCH MAC-d Flows To Delete IE is used for the removal of HS-DSCH MAC-d flows from a UE Context.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
HS-DSCH MAC-d Flows To Delete		1 <maxno ofMACdFl ows></maxno 		
>HS-DSCH MAC-d Flow ID	М		9.2.1.300	

Range Bound	Explanation		
maxnoofMACdFlows	Maximum number of HS-DSCH MAC-d flows		

9.2.1.30OC HS-DSCH MAC-d PDU Size Format

The *HS-DSCH MAC-d PDU Size Format* IE provides information about the type of MAC-d PDU Size Format used for HS-DSCH. "Indexed MAC-d PDU Size" uses MAC-d PDU sizes based on *SID* IE and *MAC-d PDU Size* IE of *MAC-d PDU Size* IE. "Flexible MAC-d PDU Size" uses a flexible MAC-d PDU size with a maximum PDU size as defined by *Maximum MAC-d PDU Size extended* IE of *Priority Queue Information* IE. The actual MAC-d PDU size is determined as specified in TS 25.425 [32] and TS 25.321 [41].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
HS-DSCH MAC-d PDU Size			ENUMERATED	
Format			(Indexed MAC-d	
			PDU Size, Flexible	
			MAC-d PDU Size)	

9.2.1.30Oa HS-DSCH Physical Layer Category

The *HS-DSCH Physical Layer Category* IE defines a set of UE radio access capabilities related to HSDPA, as defined in TS 25.306 [42].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
HS-DSCH Physical Layer Category			INTEGER (164,)	

9.2.1.30P HS-DSCH-RNTI

The HS-DSCH-RNTI is needed for the UE-specific CRC in HS-SCCH and HS-DSCH.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
HS-DSCH-RNTI			INTEGER (065535)	

9.2.1.30Q HS-DSCH Information To Modify

The HS-DSCH Information To Modify IE is used for modification of HS-DSCH information in a UE Context.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
HS-DSCH MAC-d Flow Specific Information		0 <maxn oofMACd Flows></maxn 			-	
>HS-DSCH MAC-d Flow ID	М		9.2.1.300		_	
>Allocation/Retention Priority	0		9.2.1.1		_	
>Transport Bearer Request Indicator	M		9.2.1.61		_	
>Traffic Class	0		9.2.1.58A		_	
>Binding ID	0		9.2.1.3	Shall be ignored if bearer establishment with ALCAP.	-	
>Transport Layer Address	0		9.2.1.62	Shall be ignored if bearer establishment with ALCAP.	_	
>TNL QoS	0		9.2.1.56A	Shall be ignored if bearer establishment with ALCAP.	YES	ignore
Priority Queue Information		0 <maxn oofPrioQ ueues></maxn 			_	
>CHOICE Priority Queue	M				_	
>>Add Priority Queue					_	
>>>Priority Queue ID	M		9.2.1.45A		_	
>>>Associated HS-DSCH MAC-d Flow	M		HS-DSCH MAC-d Flow ID 9.2.1.300	Shall only refer to a HS- DSCH MAC-d flow already existing in the old configuration. Multiple Priority Queues can be associated with the same HS-DSCH MAC-d Flow ID.	-	
>>>Scheduling Priority Indicator	M		9.2.1.51A		_	
>>>T1	M		9.2.1.54A		_	
>>> Discard Timer	0		9.2.1.19C		_	
>>>MAC-hs Window Size >>>MAC-hs Guaranteed	M O		9.2.1.34C 9.2.1.34Aa		_	
Bit Rate >>>MAC-d PDU Size Index		1 <maxn oofMACd PDUinde xes></maxn 			_	
>>>SID	М		9.2.1.52D	Shall be ignored if Maximum MAC-d PDU Size extended IE is present.	-	
>>>MAC-d PDU Size	M		9.2.1.34A	Shall be ignored if	_	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
			Reference	Maximum		
				MAC-d PDU		
				Size extended		
>>>RLC Mode	M		9.2.1.48D	IE is present.	_	
>>>Maximum MAC-d	O		MAC PDU		YES	reject
PDU Size extended			Size		120	10,000
			Extended			
	_		9.2.1.34D			
>>>DL RLC PDU Size Format	0		9.2.1.136		Yes	ignore
>>Modify Priority Queue					_	
>>Priority Queue ID	М		9.2.1.45A	Shall only	_	
	141		J.Z.1.40/1	refer to a		
				Priority Queue		
				already		
				existing in the		
				old configuration.		
>>>Scheduling Priority	0		9.2.1.51A	configuration.	_	
Indicator			0.2.1.017			
>>>T1	0		9.2.1.54A		_	
>>>Discard Timer	0		9.2.1.19C		_	
>>>MAC-hs Window Size	0		9.2.1.34C		_	
>>>MAC-hs Guaranteed Bit Rate	0		9.2.1.34Aa		_	
>>>MAC-d PDU Size		0 <maxn< td=""><td></td><td></td><td>_</td><td></td></maxn<>			_	
Index		oofMACd PDUinde xes>				
>>>SID	М		9.2.1.52D	Shall be	_	
				ignored if		
				Maximum MAC-d PDU		
				Size extended		
				IE is present.		
>>>>MAC-d PDU Size	М		9.2.1.34A	Shall be	_	
				ignored if		
				Maximum		
				MAC-d PDU Size extended		
				IE is present.		
>>>Maximum MAC-d	0		MAC PDU	ie io prosent.	YES	reject
PDU Size extended			Size			-
			Extended			
DI DI O DDI O			9.2.1.34D			
>>>DL RLC PDU Size Format	0		9.2.1.136		Yes	ignore
>>Delete Priority Queue					_	
>>>Priority Queue ID	М		9.2.1.45A	Shall only	_	
,				refer to a		
				Priority Queue		
				already		
				existing in the old		
				configuration.		
MAC-hs Reordering Buffer Size for RLC-UM	0		9.2.1.34Ab		-	
CQI Feedback Cycle k	0		9.2.2.24a	For FDD only	_	
CQI Repetition Factor	0		9.2.2.24c	For FDD only	_	
ACK-NACK Repetition Factor	0		9.2.2.a	For FDD only	_	
CQI Power Offset	0		9.2.2.24b	For FDD only	_	
ACK Power Offset	0		9.2.2.b	For FDD only	_	
NACK Power Offset	0	1	9.2.2.26a	For FDD only	_	

IE/Group Name	Presence	Range	IE Type	Semantics	Criticality	Assigned
			and Reference	Description		Criticality
HS-SCCH Power Offset	0		9.2.2.19d	For FDD only	_	
HS-SCCH Code Change Grant	0		9.2.1.30S		_	
TDD ACK NACK Power Offset	0		9.2.3.71	For TDD only	_	
HARQ Preamble Mode	0		9.2.2.57	For FDD only	YES	ignore
HS-PDSCH Code Change	0		9.2.1.30W	For FDD only	YES	ignore
Grant						ig
MIMO Mode Indicator	0		9.2.1.135	For FDD and	YES	reject
				1.28Mcps		
				TDD only		
HS-DSCH MAC-d PDU Size	0		9.2.1.300		YES	reject
Format			С			
Sixtyfour QAM Usage Allowed	0		9.2.2.79A	For FDD only	YES	ignore
Indicator	0				\/F0	
UE Capabilities Information	O M		0.04.000		YES	ignore
>HS-DSCH Physical Layer	IVI		9.2.1.300		_	
Category	0		a	Appliants to	VEC	:
>1.28 Mcps TDD uplink	O		9.2.3.10D	Applicable to	YES	ignore
physical channel capability				1.28Mcps TDD only		
>Number of Supported	0		ENUMER	Applicable to	YES	roinat
Carriers			ATED (1.28Mcps	IES	reject
Carriers			One-one	TDD only		
			carrier.	This IE		
			One-three	indicates the		
			carrier,	number of		
			Three-	carrier that UE		
			three	can support at		
			carrier,	the same		
			One-six	time,where "		
			carrier,	One-three		
			Tree-six	carrier" means		
			carrier,	the number of		
			Six-six	supported		
			carrier,,	carrier is one		
			One-Two	for the		
			carrier	uplink,and		
			Discontigu	three for the		
			ous, _	downlink.		
			Two-Two	One-Two		
			carrier	carrier		
			Discontigu	Discontiguous		
			ous,	and Two-Two		
			One-Two	carrier		
			carrier Contiguou	Discontiguous mean that the		
			_	UE is capable		
			s, Two-Two	of supporting		
			carrier	two non-		
			Contiguou	adjacent		
			s)	carriers.		
			-'	One-Two		
				carrier		
				Contiguous		
				and Two-Two		
				carrier		
				Contiguous		
				mean that the		
				UE is only		
				capable of		
				supporting two		
				adjacent		
			1	carriers.		
>Multi-carrier HS-DSCH	0		9.2.1.300	Applicable to	YES	ignore
Physical Layer Category			а	1.28Mcps		
				TDD only		j

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>MIMO SF Mode Supported For HS-PDSCH dual stream	0		ENUMER ATED (SF1, SF1/SF16)	Applicable to 1.28Mcps TDD only	YES	ignore
>UE TS0 Capability LCR	0		ENUMER ATED (TS0 Capable, TS0 Non- Capable)	Applicable to 1.28Mcps TDD only	YES	ignore
>UE RF Band Capability LCR	C- NofSupport edCarriers		9.2.3.84	Applicable to 1.28Mcps TDD only.	YES	ignore
Enhanced HS Serving CC Abort	0		ENUMER ATED (Abort Enhanced HS Serving CC,)	For FDD only	YES	reject
UE Support Indicator Extension	0		9.2.2.103		YES	ignore
Power Offset For S-CPICH for MIMO Request Indicator	0		9.2.2.105	For FDD only	YES	ignore
Single Stream MIMO Mode Indicator	0		9.2.2.107	For FDD only	YES	reject

Condition	Explanation
NofSupportedCarriers	This IE shall be present if the Number of Supported Carriers IE is equal
	to "One-Two carrier Discontiguous" or "Two-Two carrier Discontiguous"
	and the concerned cell and the UE support more than one RF band.

Range bound	Explanation
maxnoofMACdFlows	Maximum number of MAC-d flows.
maxnoofPrioQueues	Maximum number of Priority Queues.
maxnoofMACdPDUindexes	Maximum number of MAC-d PDU Size Indexes
	(SIDs).

9.2.1.30R HS-SCCH Code Change Indicator

The HS-SCCH Code Change Indicator indicates whether the HS-SCCH Code change is needed or not.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
HS-SCCH Code Change Indicator			ENUMERAT ED (HS- SCCH Code Change needed)	

9.2.1.30S HS-SCCH Code Change Grant

The HS-SCCH Code Change Grant IE indicates that modification of HS-SCCH Codes is granted.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
HS-SCCH Code Change			ENUMERAT	
Grant			ED(Change	
			Granted)	

9.2.1.30T IMEI

The IMEI is a permanent UE Equipment Identity, see TS 23.003 [1].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
IMEI			OCTET STRING (SIZE (8))	- hexadecimal digits 0 to F, two hexadecimal digits per octet, - each hexadecimal digit encoded 0000 to 1111, - 1111 used as filler for bits 8 to 5 of last octet - bit 4 to 1 of octet n encoding digit 2n-1 - bit 8 to 5 of octet n encoding digit 2n
				shall be 15.

9.2.1.30U IMEISV

The IMEISV is a permanent UE Equipment Identity, see TS 23.003 [1].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
IMEISV			OCTET STRING (SIZE (8))	- hexadecimal digits 0 to F, two hexadecimal digits per octet, - each hexadecimal digit encoded 0000 to 1111, - 1111 used as filler for bits 8 to 5 of last octet - bit 4 to 1 of octet n encoding digit 2n-1 - bit 8 to 5 of octet n encoding digit 2n
				Number of hexadecimal digits shall be 16.

9.2.1.30V HS-PDSCH Code Change Indicator [FDD]

The HS-PDSCH Code Change Indicator indicates whether the HS-PDSCH Code change is needed or not.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
HS-PDSCH Code Change			ENUMERATED (HS-	
Indicator			PDSCH Code	
			Change needed)	

9.2.1.30W HS-PDSCH Code Change Grant [FDD]

The HS-PDSCH Code Change Grant IE indicates that modification of HS-PDSCH Codes is granted.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
HS-PDSCH Code Change			ENUMERATED(Chan	
Grant			ge Granted)	

9.2.1.31 IMSI

The IMSI is the permanent UE user Identity, see TS 23.003 [1].

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
IMSI			OCTET	-Decimal digits coded in
			STRING	BCD
			(SIZE(38))	-"1111" used as filler
				-bit 4 to 1 of octet n is
				encoding digit 2n-1
				-bit 8 to 5 of octet n is
				encoding digit 2n

9.2.1.31A Information Exchange ID

The Information Exchange ID uniquely identifies any requested information per RNS.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Information Exchange ID	М		INTEGER(0 2^20-1)	

9.2.1.31B Information Exchange Object Type

Void.

9.2.1.31C Information Report Characteristics

The information report characteristics define how the reporting shall be performed.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Information Report Characteristics Type	М			
>On Demand			NULL	
>Periodic				
>>CHOICE Information Report Periodicity Scale	M			The frequency with which the Node B shall send information reports.
>>>minute				
>>>Report Periodicity Value	M		INTEGER (160,)	
>>>hour				
>>>Report Periodicity Value	M		INTEGER (124,)	
>On Modification				
>>Information Threshold	0		9.2.1.31D	

9.2.1.31D Information Threshold

The Information Threshold indicates which kind of information shall trigger the Information Reporting procedure.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
CHOICE Information Type Item	M				_	
>DGPS Corrections						
>>PRC Deviation	M		ENUMERATED(1, 2, 5, 10,)	PRC deviation in meters from the previously reported value, which shall trigger a report	_	
>DGANSS						
>>PRC Deviation	М		ENUMERATED (1, 2, 5, 10,)	PRC deviation in meters from the previously reported value, which shall trigger a report	_	

9.2.1.31E Information Type

The Information Type indicates which kind of information the RNS shall provide.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Information Type Item	M		ENUMERATED (UTRAN Access Point Position with Altitude, UTRAN Access Point Position, IPDL Parameters, GPS Information, DGPS Corrections, GPS RX Pos, SFN-SFN Measurement Reference Point Position,, Cell Capacity Class, NACC Related Data, MBMS Bearer Service Full Address, Inter-frequency Cell Information, GANSS Information, DGANSS Corrections, GANSS RX Pos, MBMS Counting Information, MBMS Transmission Mode, MBMS Neighbouring Cell Information, MBMS RLC Sequence Number, ANR Cell Information)	For information exchange on the lur-g interface, only the Cell Capacity Class is used. MBMS Counting Information, MBMS Transmission Mode, MBMS Neighbouring Cell Information and MBMS RLC Sequence Numbe shall only be used by FDD.		
GPS Information	C-GPS	1 <maxn oofGPST ypes></maxn 			-	
>GPS Information Item			ENUMERATED (GPS Navigation Model and Time Recovery, GPS Ionospheric Model, GPS UTC Model, GPS Almanac, GPS Real-Time Integrity,)		_	
GANSS Information	C-GANSS	0.1			YES	Ignore
>GANSS Common Data		01			_	
>>Ionospheric Model	0		BOOLEAN	True means requested	-	
>>Additional lonospheric Model	0		Additional Ionospheric Model Request 9.2.1.122d	Presence means requested.	YES	Ignore
>>Earth Orientation Parameters	0		Earth Orientation Parameters Request		YES	Ignore

			9.2.1.122e			
>GANSS Generic		0 <maxn< th=""><th>0.2.111220</th><th></th><th>_</th><th></th></maxn<>	0.2.111220		_	
Data		oofGANS				1
044100 15		S>	0.04.440			
>>GANSS ID	0		9.2.1.119	-	_	
>>GANSS	0		BOOLEAN	True means	_	
Navigation				requested		
Model And Time						
Recovery			DIT CTDING(0)	Defines the times		
>>GANSS Time Model GNSS-	0		BIT STRING(9)	Defines the time	_	
GNSS				model required.		
GNSS				Bit 1 is the MSB and		
				bit 9 is the LSB (see		
				section 9.2.0).		
				36011011 9.2.0).		
				Bit 1:GPS,		
				Bit 2:Galileo,		
				Bit 3:QZSS,		
				Bit 4:GLONASS.		
				Dit 1.02010.000.		
				Other bits are		1
				reserved.		1
>>GANSS UTC	0		BOOLEAN	True means	_	
Model				requested		1
>>GANSS	0		BOOLEAN	True means	_	
Almanac	<u> </u>			requested		<u> </u>
>>GANSS Real	0		BOOLEAN	True means	_]
Time Integrity				requested		
>>GANSS Data		01			_]
Bit Assistance						
>>>GANSS	M		INTEGER	The GANSS Time Of		
TOD			(086399)	Day for which the		
				data bits are		
				requested		
>>>Data Bit		1			_	
Assistance						
>>>DGANS	M		BIT STRING(8)	Defined in TS 25.331	_	
S Signal ID				[16]		
>>>GANSS	M		INTEGER (015)	Defined in TS 25.331	_	
Data Bit				[16]		
Interval						
>>>Satellite		0 <max< td=""><td></td><td></td><td>_</td><td></td></max<>			_	
Information		GANSS				
Oat ID	N4	Sat>	INITECED(0, co)	Identifies the setallite		
>>>Sat ID	М		INTEGER(063)	Identifies the satellite	_	
				and is equal to (SV ID No – 1)		
>>GANSS	0		GANSS	110 - 1)	YES	Ignore
>>GANSS Additional			Additional		IES	ignore
			Navigation			1
Navigation Models And			Models And			1
Time Recovery			Time Recovery			1
Time Necovery			Request			1
			9.2.1.122f			
>>GANSS	0		GANSS		YES	Ignore
Additional UTC	-		Additional UTC		5	.9.1010
Models			Models Request			1
			9.2.1.122g			1
>>GANSS	0		GANSS Auxiliary		YES	Ignore
Auxiliary			Information		_	
Information			Request			1
			9.2.1.122h			1
>>SBAS ID	C-GANSS-		9.2.1.122b		YES	Ignore
	ID					
DGANSS	C-	1			YES	ignore
Corrections Req	DGANSS					1
	Correction					

	S					
>DGANSS Signal ID	М		BIT STRING(8)	Defined in TS 25.331 [16]	-	
>GANSS ID	0		9.2.1.119		YES	Ignore
MBMS RLC	C-			FDD only	YES	Ignore
Sequence Number	MBMSRL					-
Information	CSequenc					
	eNumber					
>MBMS Cell List		1 <max noofcell</max 			-	
>>C-ID	M		9.2.1.6		_	
>>MBMS Bearer Service List		1 <max noofMB MS></max 			_	
>>>TMGI	M		9.2.1.80		_	
>>>Time Stamp	М		9.2.2.98		_	

Condition	Explanation
DGANSSCorrections	The IE shall be present if the Information Type Item IE
	indicates "DGANSS Corrections".
GPS	This IE shall be present if the Information Type Item IE
	indicates "GPS Information".
GANSS	This IE shall be present if the Information Type Item IE
	indicates "GANSS Information".
GANSS-ID	This IE shall be present if the GANSS ID IE indicates "SBAS".
MBMSRLCSequenceNumber	This IE shall be present if the Information Type Item IE
	indicates " MBMS RLC Sequence Number ".

Range Bound	Explanation
maxGANSSSat	Maximum number of satellites for which data is included in the
	IE .
maxnoofGPSTypes	Maximum number of GPS Information Types supported in one
	Information Exchange.
maxnoofGANSS	Maximum number of GANSS Systems.
maxnoofMBMS	Maximum number of MBMS bearer services that a UE can
	join.
Maxnoofcell	Maximum number of cells that can be indicated in the
	corresponding IE.

9.2.1.31F IPDL Parameters

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
CHOICE IPDL Parameters					-	
>IPDL FDD Parameters						
>>IPDL FDD parameters	M		9.2.2.21B		1	
>IPDL TDD Parameters				Applicable to 3.84Mcps TDD and 7.68Mcps TDD only		
>>IPDL TDD parameters	M		9.2.3.4B		ı	
>Additional IPDL Parameters						
>>IPDL TDD Parameters LCR				Applicable to 1.28Mcps TDD only	_	
>>>IPDL TDD parameters LCR	M		9.2.3.4Bb		YES	reject

9.2.1.31G Inter-frequency Cell Information

This IE contains the inter-frequency cell information of a cell in the DRNS broadcased in SIB11 or SIB12.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
SIB11		02		
>Inter-frequency Cell Indication- SIB11	M		Integer(01)	Value tag in 10.3.7.45 in TS 25.331 [16] with the same IE name.
>Inter-frequency Cell List in SIB11		0 <maxcellsib11 OrSIB12></maxcellsib11 		
>>Inter-frequency Cell Id	М		Integer(031)	The order of the inter- frequency cell in SIB11.
>>DL UARFCN	М		UARFCN 9.2.1.66	
>>UL UARFCN	0		UARFCN 9.2.1.66	If this IE is not present, the default duplex distance defined for the operating frequency band shall be used (TS 25.101 [43])
>>Primary Scrambling Code	М		9.2.1.45	
SIB12		02		
>Inter-frequency Cell Indication- SIB12	М			Value tag in 10.3.7.45 in TS 25.331 [16] with the same IE name.
>Inter-frequency Cell List in SIB12		0 <maxcellsib11 OrSIB12></maxcellsib11 		
>>Inter-frequency Cell Id			Integer(031)	The order of the inter- frequency cell in SIB12.
>>DL UARFCN	М		UARFCN 9.2.1.66	
>>UL UARFCN	0		UARFCN 9.2.1.66	If this IE is not present, the default duplex distance defined for the operating frequency band shall be used (TS 25.101 [43])
>>Primary Scrambling Code	М		9.2.1.45	

Range bound	Explanation
maxCellSIB11OrSIB12	Maximum number of inter-frequency cells broadcased in SIB11 or
	SIB12.

9.2.1.32 L3 Information

This parameter contains the Layer 3 Information from a Uu message as received from the UE over the Uu interface or the Layer 3 Information for a Uu message to be sent to a UE by the DRNC, as defined in TS 25.331 [16].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
L3 Information			BIT STRING	The content is defined in TS 25.331 [16]

9.2.1.33 Limited Power Increase

Void.

9.2.1.33A Load Value

The *Load Value* IE contains the total load on the measured object relative to the maximum planned load for both the uplink and downlink. It is defined as the load percentage of the Cell Capacity Class.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Uplink Load Value	M		INTEGER(0100)	Value 0 shall indicate the minimum load, and 100 shall indicate the maximum load. Load should be measured on a linear scale.
Downlink Load Value	М		INTEGER(0100)	Value 0 shall indicate the minimum load, and 100 shall indicate the maximum load. Load should be measured on a linear scale.

9.2.1.34 MAC-c/sh SDU Length

Indicates the MAC-c/sh SDU Length. Which is used for FACH, [TDD – DSCH and USCH]. There may be multiple MAC-c/sh SDU Lengths per priority class.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
MAC-c/sh SDU Length			INTEGER(15000)	Size of the MAC-c/sh SDU in number of bits.

9.2.1.34A MAC-d PDU Size

The MAC-d PDU Size IE provides the size in bits of the MAC-d PDU.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
MAC-d PDU Size			INTEGER (15000,)	In case of E-DCH, value 8 and values not multiple of 8
			(1.10000,111)	shall not be used.

9.2.1.34Aa MAC-hs Guaranteed Bit Rate

The MAC-hs Guaranteed Bit Rate IE indicates the guaranteed number of bits per second that Node B should deliver over the air interface under normal operating conditions (provided there is data to deliver). If the MAC-hs Guaranteed Bit Rate IE is received with the value set to 0 during RL set up or modification, no guarantee is applied.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
MAC-hs Guaranteed Bit			INTEGER	Unit: bit/s
Rate			(02^24-1,,	
			2^24256,000,	
			000)	

9.2.1.34Ab MAC-hs Reordering Buffer Size for RLC-UM

The *MAC-hs Reordering Buffer Size for RLC-UM* IE indicates the portion of the buffer in the UE that can be used for RLC-UM traffic (i.e. for Priority Queues whose *RLC Mode* IE is set to "RLC-UM").

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
MAC-hs Reordering Buffer			INTEGER	Unit: kBytes
Size for RLC-UM			(0300,)	And N kBytes = N*1024
				Bytes.
				The DRNS shall use this
				value to avoid the overflow of
				the UE buffer.

9.2.1.34B MAC-hs Reset Indicator

The MAC-hs Reset Indicator IE indicates that a reset of the MAC-hs is not required.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
MAC-hs Reset Indicator			ENUMERATED (MAC-hs	
			Not Reset)	

9.2.1.34C MAC-hs Window Size

The MAC-hs Window Size IE is used for MAC-hs/MAC-ehs PDU retransmission as defined in TS 25.321 [41]. [FDD – the values 64 and 128 is only allowed when the MAC header type is MAC-ehs and under conditions defined in TS 25.425 [32]].

IE/Group Name	Presence	Range	IE type and reference	Semantics description
MAC-hs Window Size			ENUMERAT ED (4, 6, 8, 12, 16, 24, 32,)	

9.2.1.34D MAC PDU Size Extended

The MAC PDU Size Extended IE provides the size in octets of the MAC level PDU when an extended MAC level PDU size is required.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
MAC PDU Size Extended			INTEGER (115041505)	In case of E-DCH, value 1 shall not be used

9.2.1.35 Maximum Allowed UL Tx Power

Maximum Allowed UL Tx Power is the maximum power that a UE in a particular cell is allowed to transmit.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Maximum Allowed UL Tx			INTEGER(-	dBm
Power			50+33)	

9.2.1.35A Measurement Availability Indicator

Void

9.2.1.35B Measurement Change Time

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Measurement Change Time	М		INTEGER	Unit: ms
			(16000,)	Range: 1060000 ms
				Step: 10 ms

9.2.1.36 Measurement Filter Coefficient

The Measurement Filter Coefficient determines the amount of filtering to be applied for measurements.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Measurement Filter			ENUMERAT	
Coefficient			ED(0, 1, 2,	
			3, 4, 5, 6, 7,	
			8, 9, 11, 13,	
			15, 17,	
			19,)	

9.2.1.36A Measurement Hysteresis Time

The Measurement Hysteresis Time provides the duration during which a reporting criterion has to be fulfilled for the Measurement Reporting procedure to be triggered.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Measurement Hysteresis Time			INTEGER	Unit: ms
			(16000,)	Range: 1060000 ms
				Step: 10 ms

9.2.1.37 Measurement ID

The Measurement ID uniquely identifies a dedicated measurement within a UE Context or a common measurement within a Distant RNC Context [TDD – or a UE measurement within a UE Context].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Measurement ID			INTEGER(0	
			2^20-1)	

9.2.1.38 Measurement Increase/Decrease Threshold

The Measurement Increase/Decrease Threshold defines the threshold that shall trigger Event C or D.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
CHOICE Measurement Increase/Decrease Threshold	М				_	,
>SIR						
>>SIR	M		INTEGER(062)	0: 0 dB 1: 0.5 dB 2: 1 dB	_	
>SIR Error				62: 31dB FDD Only		
>>SIR Error	М		INTEGER(0124)	0: 0 dB 1: 0.5 dB 2: 1 dB 124: 62 dB	_	
>Transmitted Code Power				124. 02 UD		
>>Transmitted Code Power	М		INTEGER(0112 ,)	0: 0 dB 1: 0.5 dB 2: 1 dB 112: 56 dB	_	
>RSCP				TDD Only		
>>RSCP	М		INTEGER(0126)	0: 0 dB 1: 0.5 dB 2: 1 dB	_	
Dound Trin Time				126: 63 dB FDD Only		
>Round Trip Time >>Round Trip Time	M		INTEGER(0327 66)	0: 0 chips 1: 0.0625 chips 2: 0.1250 chips 32766: 2047.875	-	
>Additional Measurement Thresholds				chips		
>>Load						
>>>Load	M		INTEGER(0100)	Units are the same as for the Uplink Load Value IE and Downlink Load Value IE.	_	
>>Transmitted Carrier Power						
>>>Transmitted Carrier Power	M		INTEGER(0100)	According to mapping in TS 25.133 [23] and TS 25.123 [24].	YES	reject
>>Received Total Wide Band Power						
>>>Received Total Wide Band Power	М		INTEGER(0620)	0: 0dB 1: 0.1dB 2: 0.2dB 620: 62dB	YES	reject
>>UL Timeslot ISCP				TDD Only		
>>>UL Timeslot ISCP	М		INTEGER(0126)	0: 0dB 1: 0.5dB 2: 1dB	YES	reject
				126: 63dB		

>>RT Load					
>>>RT Load	М	INTEGER(0100)	Units are the same as for the Uplink RT Load Value IE and Downlink RT Load Value IE.	YES	reject
>>NRT Load Information					
>>>NRT Load Information	М	INTEGER(03)		YES	reject
>>UpPTS interference			1.28Mcps TDD Only		
>>>UpPTS interference Value	М	INTEGER (0127,)	According to mapping in TS 25.123 [24]	YES	reject

9.2.1.38A Measurement Recovery Behavior

This IE controls the Measurement Recovery Behavior.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Measurement Recovery Behavior			NULL	

9.2.1.38B Measurement Recovery Reporting Indicator

This IE indicates the Measurement Recovery Reporting.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Measurement Recovery Reporting Indicator			NULL	

9.2.1.38C Measurement Recovery Support Indicator

This IE indicates the Measurement Recovery Support.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Measurement Recovery Support Indicator			NULL	

9.2.1.39 Measurement Threshold

The Measurement Threshold defines which threshold that shall trigger Event A, B, E, F or On Modification.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
CHOICE Measurement Threshold				, , ,	-	,
>SIR						
>>SIR	М		INTEGER(063)	According to mapping in TS 25.133 [23] and TS 25.123 [24].	_	
>SIR Error				FDD Only		
>>SIR Error	М		INTEGER(0125	According to mapping in TS 25.133 [23]	_	
>Transmitted Carrier Power						
>>Transmitted Code Power	М		INTEGER(0127	According to mapping in TS 25.133 [23] and TS 25.123 [24].	-	
>RSCP				TDD Only		
>>RSCP	М		INTEGER(0127)	According to mapping in TS 25.123 [24]	-	
>Rx Timing Deviation				Applicable to 3.84Mcps TDD Only		
>>Rx Timing Deviation	М		INTEGER(0819 1)	According to mapping in TS 25.123 [24]	_	
>Round Trip Time				FDD Only		
>>Round Trip Time	M		INTEGER(0327 67)	According to mapping in TS 25.133 [23]	ı	
>Additional Measurement						
Thresholds						
>>T _{UTRAN-GPS} Measurement Threshold Information						
>>>Tutran-gps Measurement Threshold Information	M		9.2.1.59C		YES	reject
>>SFN-SFN Measurement Threshold Information						
>>>SFN-SFN Measurement Threshold Information	M		9.2.1.52B		YES	reject
>>Load >>>Load	M		INTEGER(0100)	0 is the minimum indicated load, and 100 is the maximum indicated load.	YES	reject
>>Transmitted Carrier Power						
>>>Transmitted Carrier Power	М		INTEGER(0100)	According to mapping in TS 25.133 [23] and TS 25.123 [24].	YES	reject
>>Received Total Wide Band Power						
>>>Received Total Wide Band Power	М		INTEGER(0621	According to mapping in TS 25.133 [23] and TS 25.123 [24].	YES	reject
>>UL Timeslot ISCP				TDD Only		
>>>UL Timeslot ISCP	M		INTEGER(0127	According to mapping in TS 25.123 [24]	YES	reject
>>RT Load						<u> </u>

>>>RT Load	M	INTEGER(0100		YES	reject
>>NRT Load Information		1			
>>>NRT Load Information	М	INTEGER(03)		YES	reject
>>Rx Timing Deviation LCR			Applicable to 1.28Mcps TDD Only		
>>>Rx Timing Deviation LCR	M	INTEGER(0511)	According to mapping in TS 25.123 [24]	YES	reject
>>HS-SICH reception quality			Applicable to TDD Only		
>>>HS-SICH reception quality	М	INTEGER (020)	According to mapping in TS 25.123 [24]	YES	reject
>>UpPTS interference			1.28Mcps TDD Only		
>>>UpPTS interference Value	М	INTEGER (0127,)	According to mapping in TS 25.123 [24]	YES	reject
>>Rx Timing Deviation 768			Applicable to 7.68Mcps TDD Only		
>>>Rx Timing Deviation 768	M	INTEGER(0655 35)	According to mapping in TS 25.123 [24]	YES	reject
>>Rx Timing Deviation 384 Extended			Applicable to 3.84Mcps TDD Only		
>>>Rx Timing Deviation 384 Extended	М	INTEGER(0327 67)	According to mapping in TS 25.123 [24]	YES	reject
>>Extended Round Trip Time			FDD Only		
>>>Extended Round Trip Time Value	M	INTEGER (32767103041)	Continuation of intervals with step size as defined in TS 25.133 [23].	YES	reject
>>T _{UTRAN-GANSS} Measurement Threshold Information					
>>>T _{UTRAN-} GANSS Measurement Threshold Information	M	9.2.1.113		YES	reject

9.2.1.39A Message Structure

The *Message Structure* IE gives information for each level with assigned criticality in an hierarchical message structure from top level down to the lowest level above the reported level for the occurred error (reported in the *Information Element Criticality Diagnostics* IE).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Message structure		1 <maxnoo flevels></maxnoo 		The first repetition of the Message Structure IE corresponds to the top level of the message. The last repetition of the Message Structure IE corresponds to the level above the reported level for the occurred error of the message.	_	
>IE ID	M		INTEGER(065535)	The IE ID of this level's IE containing the not understood or missing IE.	-	
>Repetition Number	0		INTEGER(1256)	The Repetition Number IE gives, if applicable, the number of occurrences of this level's reported IE up to and including the occurrence containing the not understood or missing IE. Note: All the counted occurrences of the reported IE must have the same topdown hierarchical message structure of IEs with assigned criticality above them.	_	

Range bound	Explanation
maxnooflevels	Maximum no. of message levels to report. The value for
	maxnooflevels is 256.

9.2.1.40 Message Type

The Message Type uniquely identifies the message being sent.

Procedure ID >Procedure Code M INTEGER (0255) "0" = Common Transport Channel Resources Initialisation "1" = Common Transport Channel Resources Release "2" = Compressed Mode Command "3" = Downlink Power Timeslot Control "4" = Downlink Signalling Transfer "6" = Error Indication "7" = Dedicated Measurement Failure "8" = Dedicated Measurement Initiation "9" = Dedicated Measurement Reporting "10" = Dedicated Measurement Termination "11" = Paging "12" = Physical Channel Reconfiguratio "14" = Radio Link Addition "15" = Radio Link Deletion "16" = Radio Link Failure "17" = Radio Link Preemption "18" = Radio Link Restoration "18" = Radio Link Restoration "19" = Radio Link Setup "20" = Relocation Commit "21" = Synchronised Radio Link
>Procedure Code M INTEGER (0255) "0" = Common Transport Channel Resources Initialisation "1" = Common Transport Channel Resources Release "2" = Compressed Mode Command "3" = Downlink Power Control "4" = Downlink Signalling Transfer "6" = Error Indication "7" = Dedicated Measurement Failure "8" = Dedicated Measurement Initiation "9" = Dedicated Measurement Termination "11" = Paging "12" = Physical Channel Reconfiguratio "14" = Radio Link Addition "15" = Radio Link Deletion "16" = Radio Link Preemption "18" = Radio Link Restoration "18" = Radio Link Restoration "19" = Relocation Commit "21" = Synchronised Radio Link
Reconfiguration Cancellation "22" = Synchronised Radio Link Reconfiguration Commit "23" = Synchronised Radio Link Reconfiguration Preparation "24" = UnSynchronised Radio Link Reconfiguration "24" = UnSynchronised Radio Link Reconfiguration "25" = Uplink Signalling Transfer "26" = Common Measurement Failure "27" = Common Measurement Initiation "28" = Common Measurement Reportin "29" = Common Measurement Termination "30" = Information Exchange Failure "31" = Information Exchange Initiation "32" = Information Reporting "33" = Information Exchange Termination "34" = Radio Link Congestion "35" = Reset "36" = Radio Link Activation "37" = GERAN Uplink Signalling Transfe "38" = Radio Link Parameter Update "39" = UE Measurement Failure "40" = UE Measurement Failure "40" = UE Measurement Initiation "41" = UE Measurement Reporting "42" = UE Measurement Trace "44" = Iur Invoke Trace "45" = MBMS Detach "46" = MBMS Detach "48" = Direct Information Transfer "49" = Enhanced Relocation Cancel
"51" = Enhanced Relocation Signalling Transfer

			"52" = Enhanced Relocation Release "53" = MBSFN MCCH Information "54" = Secondary UL Frequency Reporting "55" = Secondary UL Frequency Update "56" = Information Transfer Control "60" = Enhanced Relocation Resource Allocation "61" = Enhanced Relocation Resource Release
>Ddmode	M	ENUMERATED(FDD, TDD, Common,)	Common = common to FDD and TDD.
Type of Message	М	ENUMERATED(Initiati ng Message, Successful Outcome, Unsuccessful Outcome, Outcome)	

9.2.1.41 Multiple URAs Indicator

The Multiple URAs Indicator indicates whether the accessed cell has multiple URAs.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Multiple URAs Indicator			ENUMERAT	
			ED(Multiple	
			URA s exist,	
			Single URA	
			Exists)	

9.2.1.41a NACC Related Data

The NACC related data IE provides NACC related information for the indicated GSM cell.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE GERAN System Info Type	M			
>SI				
>>SI	M		9.2.1.30Fc	GERAN system information SI3, SI13, SI1 (TS 44.060 [47])
>PSI				
>>PSI	M		9.2.1.30Fc	GERAN system information PSI1, PSI2, PSI4 (TS 44.060 [47])

9.2.1.41A Neighbouring UMTS Cell Information

The *Neighbouring UMTS Cell Information* IE provides information for UMTS Cells that are neighbouring cells to a cell in the DRNC. The neighbouring cell information is provided for each RNC (including the DRNC) that has cells that are neighbouring cells to the cell in the DRNC.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Neighbouring UMTS Cell Information		1 <maxnoof neighbourin gRNCs></maxnoof 			EACH	ignore
>RNC-ID	M		9.2.1.50	If the Extended RNC-ID IE is included in the Neighbourin g UMTS Cell Information IE, the RNC-ID IE shall be ignored.		
>CN PS Domain Identifier	0		9.2.1.12		_	
>CN CS Domain Identifier	0		9.2.1.11		_	
>Neighbouring FDD Cell Information	0		9.2.1.41B		1	
>Neighbouring TDD Cell Information	0		9.2.1.41D		-	
>Neighbouring TDD Cell Information LCR	0		9.2.1.72		YES	ignore
>Extended RNC-ID	0		9.2.1.50a	The Extended RNC-ID IE shall be used if the RNC identity has a value larger than 4095.	YES	reject

Range bound	Explanation
maxnoofneighbouringRNCs	Maximum number of neighbouring RNCs.

9.2.1.41B Neighbouring FDD Cell Information

The *Neighbouring FDD Cell Information* IE provides information for FDD cells that are neighbouring cells to a cell in the DRNC.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Neighbouring FDD Cell Information		1 <max noofFDD neighbou rs></max 			-	
>C-ID	M		9.2.1.6		_	
>UL UARFCN	М		UARFCN 9.2.1.66	Corresponds to Nu in TS 25.104 [6]	_	
>DL UARFCN	М		UARFCN 9.2.1.66	Corresponds to Nd in TS 25.104 [6]	_	
>Frame Offset	0		9.2.1.30		_	
>Primary Scrambling Code	M		9.2.1.45		_	
>Primary CPICH Power	0		9.2.1.44		_	
>Cell Individual Offset	0		9.2.1.7		_	
>Tx Diversity Indicator	М		9.2.2.50			
>STTD Support Indicator	0		9.2.2.45		_	
>Closed Loop Mode1 Support Indicator	0		9.2.2.2		_	
>Not Used	0		NULL		_	
>Restriction State Indicator	0		9.2.1.48C		YES	ignore
>DPC Mode Change Support Indicator	0		9.2.2.56		YES	ignore
>Coverage Indicator	0		9.2.1.12G		YES	ignore
>Antenna Co-location Indicator	0		9.2.1.2C		YES	ignore
>HCS Prio	0		9.2.1.30N		YES	ignore
>Cell Capability Container FDD	0		9.2.2.D		YES	ignore
>SNA Information	0		9.2.1.52Ca		YES	ignore
>Frequency Band Indicator	0		9.2.2.59		YES	ignore
>Max UE DTX Cycle	C-CPC- DTX- DRXCapab le		9.2.2.87		YES	ignore
>Multiple PLMN List	0		9.2.1.117		YES	ignore
>Secondary Serving Cell List	C-MC- Capable		9.2.2.101		YES	ignore
>Dual Band Secondary Serving Cell List	C-DB- Capable		Secondary Serving Cell List 9.2.2.101		YES	ignore
>Cell Capability Container Extension FDD	0		9.2.2.123		YES	ignore
>Cell List Validity Indicator	0		ENUMERAT ED (Ignore Secondary Serving Cell List, Ignore Dual Band Secondary Serving Cell List, Ignore Both)		YES	ignore

Range bound	Explanation
maxnoofFDDneighbours	Maximum number of neighbouring FDD cell for one cell.

Condition	Explanation
CPC-DTX-DRXCapable	The IE shall be present if the the fifteenth bit Continuous Packet
	Connectivity DTX-DRX Support Indicator in the Cell Capability Container
	FDD IE is set to the value "1".
MC-Capable	The IE shall be present if the the Multi Cell Support Indicator in the Cell
	Capability Container FDD IE is set to the value "1".
DB-Capable	The IE shall be present if the the Dual Band Support Indicator in the Cell
	Capability Container FDD IE is set to the value "1".

9.2.1.41C Neighbouring GSM Cell Information

The *Neighbouring GSM Cell Information* IE provides information for all GSM Cells that are a neighbouring cell to a cell in the DRNC.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Neighbouring GSM Cell Information		1 <max noofGS Mneighb ours></max 			GLOBAL	ignore
>CGI		1		Cell Global Identity as defined in TS 23.003 [1].	_	
>>LAI		1			_	
>>>PLMN Identity	M		OCTET STRING (3)	- digits 0 to 9, two digits per octet, - each digit encoded 0000 to 1001, - 1111 used as filler - bit 4 to 1 of octet n encoding digit 2n-1 - bit 8 to 5 of octet n encoding digit 2n -The PLMN Identity consists of 3 digits from MCC followed by either -a filler plus 2 digits from MNC (in case of 2 digit MNC) or -3 digits from MNC (in case of a 3 digit MNC).		
>>>LAC	М		OCTET STRING (2)	0000 and FFFE not allowed	_	
>>Cl	М		OCTET STRING (2)		_	
>Cell Individual Offset	0		9.2.1.7	The Cell Individual Offset to be used for Ues using DCHs. If the Extended GSM Cell Individual Offset IE is present, the Cell Individual Offset IE shall be set to a) -10dB if the Extended GSM Cell Individual Offset IE is < -10dB and b) 10dB if the Extended GSM Cell Individual Offset IE is > 10dB.	_	
>BSIC		1		Base Station Identity Code as defined in TS 23.003 [1].	_	
>>NCC	M		BIT STRING(3)	Network Colour Code.	_	
>>BCC	M		BIT STRING(3)	Base Station Colour Code.	_	
>Band Indicator	M		ENUMERAT ED(DCS 1800 band, PCS 1900 band,)	Indicates whether or not the BCCH ARFCN belongs to the 1800 band or 1900 band of GSM frequencies.	-	
>BCCH ARFCN	M		INTEGER(01023)	BCCH Frequency as defined in TS 45.005 [69].	_	
>Coverage Indicator	0		9.2.1.12G		YES	ignore
>Antenna Co-location	0		9.2.1.2C	1	YES	ignore

Indicator					
>HCS Prio	0	9.2.1.30N		YES	ignore
> SNA Information	0	9.2.1.52Ca		YES	ignore
>GERAN Cell Capability	0	9.2.1.30Fa		YES	ignore
>GERAN Classmark	0	9.2.1.30Fb		YES	ignore
>Extended GSM Cell Individual Offset	0	9.2.1.26Bb	The Extended GSM Cell Individual Offset to be used for Ues using DCHs, for values that exceed the range of the Cell Individual Offset IE.	YES	ignore

Range bound	Explanation
maxnoofGSMneighbours	Maximum number of neighbouring GSM cells for one cell.

9.2.1.41D Neighbouring TDD Cell Information

The *Neighbouring TDD Cell Information* IE provides information for 3.84Mcps TDD or 7.68Mcps TDD cells that are neighbouring cells to a cell in the DRNC.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Neighbouring TDD Cell Information		1 <maxnoo fTDDneighb ours></maxnoo 			_	
>C-ID	M		9.2.1.6		_	
>UARFCN	M		9.2.1.66	Corresponds to Nt in TS 25.105 [7]	_	
>Frame Offset	0		9.2.1.30		_	
>Cell Parameter ID	M		9.2.1.8		_	
>Sync Case	M		9.2.1.54		_	
>Time Slot For SCH	C-Case1		Time Slot 9.2.1.56		_	
>SCH Time Slot	C-Case2		9.2.1.51		_	
>SCTD Indicator	M		9.2.1.78		_	
>Cell Individual Offset	0		9.2.1.7		_	
>DPCH Constant Value	0		9.2.1.23		_	
>PCCPCH Power	0		9.2.1.43		_	
>Restriction State Indicator	0		9.2.1.48C		YES	ignore
>Coverage Indicator	0		9.2.1.12G		YES	ignore
>Antenna Co-location Indicator	0		9.2.1.2C		YES	ignore
>HCS Prio	0		9.2.1.30N		YES	ignore
>Cell Capability Container TDD	0		9.2.3.1a		YES	ignore
>Cell Capability Container 7.68Mcps TDD	0		9.2.3.31		YES	ignore
> SNA Information	0		9.2.1.52Ca		YES	ignore
>Multiple PLMN List	0		9.2.1.117		YES	ignore

Condition	Explanation
Case1	The IE shall be present if the Sync Case IE is set to "Case1".
Case2	The IE shall be present if the Sync Case IE is set to "Case2".

Range bound	Explanation
maxnoofTDDneighbours	Maximum number of neighbouring 3.84Mcps TDD or 7.68Mcps TDD cell for one cell.

9.2.1.41Dd Neighbouring TDD Cell Measurement Information LCR

This IE provides information on the 1.28Mcps TDD neighbouring cells used for the purpose of Measurements. Since the measurement can be performed on every time slot and midamble shift, the *Time slot LCR* IE and *Midamble shift LCR* IE shall be included if available.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UTRAN Cell Identifier	M		9.2.1.71	
UARFCN	М		9.2.1.66	Corresponds to Nt TS 25.105 [7]
Cell Parameter ID	M		9.2.1.8	
Time Slot LCR	0		9.2.3.12a	
Midamble shift LCR	0		9.2.3.4C	

9.2.1.41De Neighbouring E-UTRA Cell Information

The *Neighbouring E-UTRA Cell Information* IE provides information for all E-UTRA Cells that are a neighbouring cell to a cell in the DRNC.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Neighbouring E-UTRA Cell Information		1 <max noofEUT RAneigh bours></max 			-	,
>ECGI		1		EUTRAN Cell Global Identity as defined in TS 36.401 [61].	_	
>>PLMN Identity	M		OCTET STRING (3)	- digits 0 to 9, two digits per octet, - each digit encoded 0000 to 1001, - 1111 used as filler - bit 4 to 1 of octet n encoding digit 2n-1 - bit 8 to 5 of octet n encoding digit 2n -The PLMN Identity consists of 3 digits from MCC followed by either -a filler plus 2 digits from MNC (in case of 2 digit MNC) or -3 digits from MNC (in case of a 3 digit MNC).		
>>E-UTRAN Cell Identifier	М		BIT STRING (28)	The leftmost bits of the E-UTRAN Cell Identifier IE value correspond to the value of the eNB ID.	-	
>CHOICE EARFCN	М				_	
Information >>FDD						
>>FDD		1				
>>>UL EARFCN	М		9.2.1.41Df EARFCN	Corresponds to NuL in TS 36.104 [62]	_	
>>>DL EARFCN	M		9.2.1.41Df EARFCN	Corresponds to NdL in TS 36.104 [62]	_	
>>TDD	N.4		0.04.44D6	Corresponde to Nell		
>>> EARFCN	M		9.2.1.41Df EARFCN	Corresponds to NdL in TS 36.104 [62]	_	
>PCI	0		INTEGER (0503,)	Physical Cell Identifier of the neighbour cell.	YES	ignore
>TAC	0		OCTET STRING (2)	Tracking Area Code of the neighbour cell.	YES	ignore
>PLMN List		0 <maxnr OfBroad castPLM Ns></maxnr 		List of Broadcast PLMNs of the neighbour cell. This field contains the list of identities starting from the second entry of PLMN Identities in the broadcast information.	GLOBAL	ignore
>>PLMN Identity	M		OCTET STRING (3)	- digits 0 to 9, encoded 0000 to 1001, - 1111 used as filler digit, two digits per octet, - bits 4 to 1 of octet n encoding digit 2n-1 - bits 8 to 5 of octet n	-	

	encoding digit 2n	
	-The PLMN identity consists of 3 digits from MCC followed by either -a filler digit plus 2 digits from MNC (in case of 2 digit MNC) or -3 digits from MNC (in case of a 3 digit MNC).	

Range bound	Explanation
maxnoofLTEneighbours	Maximum number of neighbouring LTE cells for one cell.
maxNrOfBroadcastPLMNs	Maximum number of additional PLMN identitys that can be
	broadcasted in a cell involved in a MOCN or GWCN Shared Network
	configuration. The value for maxNrOfBroadcastPLMNs is 5.

9.2.1.41Df EARFCN

The EARFCN (E-UTRA Absolute Radio Frequency Channel Number) defines the carrier.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
EARFCN			INTEGER	Defined in TS 36.104 [62].
			(0maxEAR	
			FCN)	

9.2.1.41E Paging Cause

Cause for a CN originated page.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Paging Cause			ENUMERAT	See in TS 25.331 [16]
			ED(
			Terminating	
			Conversatio	
			nal Call,	
			Terminating	
			Streaming	
			Call,	
			Terminating	
			Interactive	
			Call,	
			Terminating	
			Background	
			Call,	
			Terminating	
			Low Priority	
			Signalling,	
			, Terminating	
			High Priority	
			Signalling,	
			Terminating	
			- cause	
			unknown	
)	

9.2.1.41F Paging Record Type

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Paging Record Type			ENUMERAT	See TS 25.331 [16]
			ED(IMSI	
			(GSM-MAP),	
			TMSI (GSM-	
			MAP), P-	
			TMSI (GSM-	
			MAP), IMSI	
			(DS-41),	
			TMSI (DS-	
			41),)	

9.2.1.41Fa Partial Reporting Indicator

This IE indicates if DRNS may report partially successful measurements.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
Partial Reporting Indicator			ENUMERAT ED(partial reporting allowed)	

9.2.1.41G Neighbouring FDD Cell Measurement Information

This IE provides information on the FDD neighbouring cells used for the purpose of Measurements.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UTRAN Cell Identifier	М		9.2.1.71	
UARFCN	М		9.2.1.66	Corresponds to Nd TS 25.104 [6]
Primary Scrambling Code	M		9.2.1.45	

9.2.1.41H Neighbouring TDD Cell Measurement Information

This IE provides information on the 3.84Mcps TDD neighbouring cells used for the purpose of Measurements. Since the measurement can be performed on every time slot and midamble shift, the *Time slot* IE and *Midamble shift and burst type* IE shall be included if available.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UTRAN Cell Identifier	M		9.2.1.71	
UARFCN	M		9.2.1.66	Corresponds to Nt TS 25.105
				[7]
Cell Parameter ID	M		9.2.1.8	
Time slot	0		9.2.1.56	
Midamble Shift And Burst Type	0		9.2.3.4	

9.2.1.41I NRT Load Information Value

The NRT Load Information IE indicates the load situation on the cell for the Non Real-Time traffic. Non Real Time traffic corresponds to the Interactive and Background traffic classes.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Uplink NRT Load Information Value	M		INTEGER(03)	Mapping of the status: 0: low: The Uplink NRT load is low. 1: medium: The Uplink NRT load is medium. 2: high: Uplink NRT load is high. Probability to admit a new user is low. 3: overloaded: Uplink NRT overload. The probability to admit a new user is low, packets are discarded and the source is recommended to reduce the data flow.
Downlink NRT Load Information Value	M		INTEGER(03)	Mapping of the status: 0: low: The Downlink NRT load is low. 1: medium: The Downlink NRT load is medium. 2: high: Downlink NRT load is high. Probability to admit a new user is low. 3: overloaded: Downlink NRT overload. The probability to admit a new user is low, packets are discarded and the source is recommended to reduce the data flow.

9.2.1.42 Payload CRC Present Indicator

This parameter indicates whether FP payload 16 bit CRC is used or not.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Payload CRC Presence			ENUMERAT	
Indicator			ED(CRC	
			Included,	
			CRC not	
			included)	

9.2.1.43 PCCPCH Power

Primary CCPCH power is the power that shall be used for reference power value in a TDD cell. The reference point is the antenna connector. If Transmit Diversity is applied to the Primary CCPCH, the PCCPCH Power is the linear sum of the power that is used for transmitting the PCCPCH on all branches.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
PCCPCH Power			NTEGER (- 150400,)	Unit dBm Range −15.0 to 40.0 dBm, Step size 0.1 dB. -15.0 shall indicate P≤ -15dBm +40.0 shall indicate P≥ 40dBm.

9.2.1.44 Primary CPICH Power

Primary CPICH power is the power that is used for transmitting the Primary CPICH in a cell. The reference point is the antenna connector. If Transmit Diversity is applied to the Primary CPICH, the Primary CPICH Power is the linear sum of the power that is used for transmitting the Primary CPICH on all branches.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Primary CPICH Power			INTEGER (- 100500)	Value = Primary CPICH Power/10 Unit dBm Range –10.0+50.0 Step 0.1 dB

9.2.1.45 Primary Scrambling Code

The Primary scrambling code to be used in the cell.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Primary Scrambling Code			INTEGER(0 511)	

9.2.1.45A Priority Queue ID

The *Priority Queue ID* IE provides the identity of the Priority Queue. The Priority Queue ID is unique across all MAC-d flows that are currently allocated for one UE Context or across all Common MAC flows within a cell.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Priority Queue ID			INTEGER	
			(07)	

9.2.1.45B Process Memory Size

The *Process Memory Size* IE is the size of an HARQ process in the DRNS expressed in bits. It provides the maximum number of soft channel bits in the virtual IR buffer (TS 25.212 [9]) or (TS 25.222 [46]).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Process Memory Size			ENUMERATED (
			800, 1600, 2400, 3200,	
			4000, 4800, 5600, 6400,	
			7200, 8000, 8800, 9600,	
			10400, 11200, 12000,	
			12800, 13600, 14400,	
			15200, 16000, 17600,	
			19200, 20800, 22400,	
			24000, 25600, 27200,	
			28800, 30400, 32000,	
			36000, 40000, 44000,	
			48000, 52000, 56000,	
			60000, 64000, 68000,	
			72000, 76000, 80000,	
			88000, 96000, 104000,	
			112000, 120000, 128000,	
			136000, 144000, 152000,	
			160000, 176000, 192000,	
			208000, 224000, 240000,	
			256000, 272000, 288000,	
			304000,)	

9.2.1.46 Puncture Limit

The maximum amount of puncturing for a transport channel in rate matching.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Puncture Limit			INTEGER (015)	0: 40% 1: 44 % 14: 96% 15: 100% (no puncturing) [FDD – Value 0 is not applicable for E-DPCH.]

9.2.1.46A QE-Selector

The QE-Selector indicates from which source the value for the quality estimate (QE) shall be taken.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
QE-Selector			ENUMERAT	
			ED(selected,	
			non-	
			selected)	

9.2.1.47 RANAP Relocation Information

This parameter is transparent to the RNSAP. The parameter contains information for the Relocation procedure as defined in TS 25.413 [2].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
RANAP Relocation			BIT STRING	The content is defined in TS
Information				25.413 [2].

9.2.1.48 Report Characteristics

The Report Characteristics, defines how the reporting shall be performed.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
CHOICE Report Characteristics	М			•	_	_
>On Demand			NULL		_	
>Periodic			11022			
>>Report Periodicity	M		9.2.1.48a	The periodicity with which the DRNS shall send measurement reports.	-	
>Event A						
>>Measurement Threshold	M		9.2.1.39	The threshold for which the DRNS shall trigger a measurement report.	_	
>>Measurement Hysteresis Time	0		9.2.1.36A		_	
>Event B						
>>Measurement Threshold	М		9.2.1.39	The threshold for which the DRNS shall trigger a measurement report.	_	
>>Measurement Hysteresis Time	0		9.2.1.36A		-	
>Event C	24		0.04.00			
>>Measurement Increase/Decrease Threshold	М		9.2.1.38		_	
>>Measurement Change Time	М		9.2.1.35B	The time within which the measurement entity shall rise, in order to trigger a measurement report.	_	
>Event D						
>>Measurement Increase/Decrease Threshold	М		9.2.1.38		_	
>>Measurement Change Time	М		9.2.1.35B	The time within which the measurement entity shall fall, in order to trigger a measurement report.	_	
>Event E						
>>Measurement Threshold 1	М		Measureme nt Threshold 9.2.1.39		_	
>>Measurement Threshold 2	0		Measureme nt Threshold 9.2.1.39		-	
>>Measurement Hysteresis Time	0		9.2.1.36A	The hysteresis time in ms	_	
>>Report Periodicity	0		9.2.1.48a	The periodicity with which the DRNS shall send measurement reports.	_	
>Event F						
>>Measurement Threshold 1	M		Measureme nt Threshold 9.2.1.39		-	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>>Measurement Threshold 2	0		Measureme nt Threshold 9.2.1.39		_	,
>>Measurement Hysteresis Time	0		9.2.1.36A	The hysteresis time in ms	-	
>>Report Periodicity	0		9.2.1.48a	The periodicity with which the DRNS shall send measurement reports.	-	
>Additional Report Characteristics						
>>On Modification						
>>>On Modification		1			YES	reject
>>>Measurem ent Threshold	M		9.2.1.39			
>>Event H						
>>>Event H		1			YES	reject
>>>Measurem ent Threshold 1	М		Measureme nt Threshold 9.2.1.39		_	
>>>Measurem ent Threshold 2	0		Measureme nt Threshold 9.2.1.39		_	
>>>Measurem ent Hysteresis Time	0		9.2.1.36A	The hysteresis time in ms	-	
>>>Report Periodicity	0		9.2.1.48a	The periodicity with which the DRNS shall send measurement reports.	-	
>>>Measurem ent Fluctuation Range	0	0-100			-	

9.2.1.48a Report Periodicity

The Report Periodicity defines the frequency at which the Node B shall send measurement reports.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Report Periodicity Scale	М			
>millisecond				
>>Report Periodicity Value	М		INTEGER (16000,)	Unit: ms Range: 1060000 ms Step: 10 ms
>minute				·
>>Report Periodicity Value	М		INTEGER (160,)	Unit: min Range: 160 min Step: 1 min

9.2.1.48A Requested Data Value

The Requested Data Value contains the relevant data concerned the ongoing information exchange. *Requested Data Value* IE shall include at least one of the following IE.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
UTRAN Access Point Position	0		9.2.1.75		-	
with Altitude	0		0.04.045			
IPDL Parameters	0		9.2.1.31F		_	
DGPS Corrections	0		9.2.1.19B		_	
GPS Navigation Model and	0		9.2.1.301		_	
Time Recovery	0		0.04.0011			
GPS Ionospheric Model GPS UTC Model	0		9.2.1.30H		_	
GPS OTC Model GPS Almanac	0		9.2.1.30L 9.2.1.30G		_	
	0				_	
GPS Real-Time Integrity GPS RX Pos	0		9.2.1.30J 9.2.1.30K		_	
SFN-SFN Measurement	0				_	
	U		9.2.1.74		_	
Reference Point Position			9.2.1.5C		YES	ianoro
Cell Capacity Class Value NACC Related Data	0		9.2.1.5C 9.2.1.41a		YES	ignore
MBMS Bearer Service Full	0		9.2.1.41a 9.2.1.84		YES	ignore
Address	O		9.2.1.84		YES	ignore
Inter-frequency Cell Information	0		9.2.1.31G		YES	ignore
GANSS Common Data	1	01	1		YES	ignore
>GANSS Ionospheric Model	0	U 1	9.2.1.105		-	ignote
>GANSS RX Pos	0	1	9.2.1.109		_	
>GANSS Additional	0		9.2.1.105		YES	Ignore
Ionospheric Model			3.2.1.103a		120	ignore
>GANSS Earth Orientation	0		9.2.1.122a		YES	Ignore
Parameters			0.2			19
GANSS Generic Data		0 <maxno< td=""><td></td><td></td><td>GLOBAL</td><td>ignore</td></maxno<>			GLOBAL	ignore
		ofGANSS >				g
>GANSS ID	0		9.2.1.119		_	
>DGANSS Corrections	0		9.2.1.102		_	
>GANSS Navigation Model	0		9.2.1.120		_	
And Time Recovery			0.220			
>GANSS Time Model	0		9.2.1.110		_	
>GANSS UTC Model	0		9.2.1.111		_	
>GANSS Almanac	0		9.2.1.103		_	
>GANSS Real Time Integrity	0		9.2.1.108		_	
>GANSS Data Bit	Ō		9.2.1.118		_	
Assistance	1	1				
>GANSS Additional Time	0		9.2.1.110a		YES	Ignore
Models						
>GANSS Additional Navigation Models And Time	0		9.2.1.120a		YES	Ignore
Recovery		1				
>GANSS Additional UTC	0		9.2.1.111a		YES	Ignore
Models >GANSS Auxiliary	0		9.2.1.122c		YES	Ignore
Information						
>SBAS ID	C-GANSS- ID		9.2.1.122b		YES	Ignore
Counting Information	0		9.2.2.94	FDD only	YES	ignore
Transmission Mode	0		9.2.2.95	FDD only	YES	ignore
Information						g
MBMS Neighbouring Cell Information	0		9.2.2.96	FDD only	YES	ignore
RLC Sequene Number	0		9.2.2.97	FDD only	YES	ignoro
	0			רטט טוווע		ignore
ANR Cell Information	I U	1	9.2.1.149	L	YES	ignore

Condition	Explanation
GANSS-ID	This IF shall be present if the GANSS ID IF indicates "SBAS"

Range Bound	Explanation
maxnoofGANSS	Maximum number of GANSS Systems

9.2.1.48B Requested Data Value Information

The *Requested Data Value Information* IE provides information on whether or not the Requested Data Value is available in the message and also the Requested Data Value itself if available. In case of "Periodic" and "On Modification" reporting, "Information Not Available" shall be used when at least one part of the requested information was not available at the moment of initiating the Information Reporting procedure.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
CHOICE Information Availability Indicator	M				_	
>Information Available					_	
>>Requested Data Value	М		9.2.1.48A		ı	
>Information not Available			NULL		_	

9.2.1.48C Restriction State Indicator

The Restriction state indicator is the identifier indicates whether the cell is "Cell Reserved for Operator Use" or not. It is provided by DRNS and reported to SRNC.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Restriction state indicator			ENUMERAT	
			ED(Cell Not	
			Reserved for	
			Operator	
			Use, Cell	
			Reserved for	
			Operator	
			Use)	

9.2.1.48D RLC Mode

The RLC Mode IE indicates the RLC Mode used for a Priority Queue.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
RLC Mode			ENUMERAT ED (RLC-AM, RLC-UM,)	

9.2.1.49 RL ID

The RL ID is the unique identifier for one RL associated with a UE.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
RL ID			INTEGER (031)	

9.2.1.49A RL Specific DCH Information

The *RL Specific DCH Information* IE provides RL Specific DCH Information for DCHs. In case of a set of co-ordinated DCHs requiring a new transport bearer on Iur, the *Transport Layer Address* IE and the *Binding ID* IE in the *RL Specific DCH Information* IE shall be included only for one of the DCHs in the set of co-ordinated DCHs.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
RL Specific DCH Information		1 <maxno ofDCHs></maxno 			_	
>DCH ID	M		9.2.1.16		_	
>Binding ID	0		9.2.1.3	Shall be ignored if bearer establishme nt with ALCAP.	-	
>Transport Layer Address	0		9.2.1.62	Shall be ignored if bearer establishme nt with ALCAP.	-	
>Transport Bearer Not Requested Indicator	0		9.2.2.4\$	FDD Only	YES	Ignore

Range bound	Explanation
maxnoofDCHs	Maximum number of DCHs for one UE.

9.2.1.50 RNC-ID

This is the identifier of one RNC in UTRAN.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
RNC-ID			INTEGER(0.	
			.4095)	

9.2.1.50a Extended RNC-ID

This is the identifier of one RNC in UTRAN.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Extended RNC-ID			INTEGER(4	Note: Application of the
			09665535)	Extended RNC-ID IE to very
				large networks is FFS.

9.2.1.50A SAT ID

The SAT ID indicates the identity of the satellite.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
SATID			INTEGER(0. .63)	Identifies the satellite and is equal to (SV ID No – 1) where SV ID No is defined in ICD-GPS-200 [30].

9.2.1.50B RT Load Value

The *RT Load Value* IE indicates in percents the ratio of the load generated by Real Time traffic, relative to the measured Load Value. Real Time traffic corresponds to the Conversational and Streaming traffic classes.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Uplink RT Load Value	M		INTEGER(0100)	
Downlink RT Load Value	M		INTEGER(0100)	

9.2.1.51 SCH Time Slot

The *SCH Time Slot* IE represents the first time slot (k) of a pair of time slots inside a Radio Frame that is assigned to the Physical Channel SCH. The *SCH Time Slot* IE is only applicable if the value of *Sync Case* IE is Case 2 since in this case the SCH is allocated in TS#k and TS#k+8.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
SCH Time Slot			INTEGER(0.	
			.6)	

9.2.1.51A Scheduling Priority Indicator

Indicates the relative priority of the FACH, [TDD – DSCH, USCH,] HS-DSCH [FDD – or E-DCH] data frame. Used by the DRNC when scheduling FACH, [TDD – DSCH, USCH,] HS-DSCH [FDD – or E-DCH] traffic.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Scheduling Priority Indicator			INTEGER(015)	Relative priority of the FACH, [TDD – DSCH, USCH,] HS- DSCH [FDD – or E-DCH] data frame: 0=Lowest Priority 15=Highest Priority

9.2.1.52 Service Area Identifier (SAI)

This information element is used to identify an area consisting of one or more cells belonging to the same Location Area. Such an area is called a Service Area and can be used for indicating the location of a UE to the CN. For this protocol, only a Service Area that is defined to be applicable to the PS and CS domains shall be used.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
PLMN Identity	M		OCTET STRING (3)	- digits 0 to 9, two digits per octet, - each digit encoded 0000 to 1001, - 1111 used as filler - bit 4 to 1 of octet n encoding digit 2n-1 - bit 8 to 5 of octet n encoding digit 2n -The PLMN Identity consists of 3 digits from MCC followed by either -a filler plus 2 digits from MNC (in case of 2 digit MNC) or -3 digits from MNC (in case of a 3 digit MNC).
LAC	M		OCTET STRING (2)	0000 and FFFE not allowed
SAC	M		OCTET STRING (2)	

9.2.1.52A SFN

System Frame Number of the cell, see TS 25.402 [17].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
SFN			INTEGER(04095)	

9.2.1.52B SFN-SFN Measurement Threshold Information

The SFN-SFN Measurement Threshold Information defines the related thresholds SFN-SFN Observed Time Difference measurements which shall trigger the Event On Modification.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
SFN-SFN Change Limit	0		INTEGER(1256)	Change of SFN-SFN value compared to previously reported value, which shall trigger a new report. Unit in 1/16 chip.
Predicted SFN-SFN Deviation Limit	0		INTEGER(1. .256)	Deviation the Predicted SFN- SFN from the latest measurement result, which shall trigger a new report. Unit in 1/16 chip.

9.2.1.52C SFN-SFN Measurement Value Information

The *SFN-SFN Measurement Value Information* IE indicates the measurement result related to SFN-SFN Observed Time Difference measurements as well as other related information.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Successful Neighbouring cell SFN-SFN Observed Time Difference Measurement Information		1 <maxnoofmeasn Cell></maxnoofmeasn 		
>UTRAN Cell Identifier	М		9.2.1.71	
>SFN-SFN Value	М		9.2.1.77	
>SFN-SFN Quality	0		INTEGER(0255)	Indicates the standard deviation (std) of the SFN-SFN otd (observed time difference) measurements in 1/16 chip. SFN-SFN Quality = $\sqrt{E[(x-\mu)^2]}$ = std of reported SFN-SFN Value, where x is the reported SFN-SFN Value and μ = $E[x]$ is the expectation value of x.
>SFN-SFN Drift Rate	М		INTEGER(- 100100)	Indicates the SFN-SFN drift rate in 1/256 chip per second. A positive value indicates that the Reference cell clock is running at a greater frequency than the measured neighbouring cell.
>SFN-SFN Drift Rate Quality	0		INTEGER(0100)	Indicates the standard deviation (std) of the SFN-SFN drift rate measurements in 1/256 chip per second. SFN-SFN Drift Rate Quality = $\sqrt{E[(x-\mu)^2]}$ = std of reported SFN-SFN Drift Rate, where x is the reported SFN-SFN Drift Rate and $\mu = E[x]$ is the expectation value of x.
>SFN-SFN Measurement Time Stamp	М		9.2.1.76	,
Unsuccessful Neighbouring cell SFN- SFN Observed Time Difference Measurement Information		0 <maxnoofmeasn Cell-1></maxnoofmeasn 		
>UTRAN Cell Identifier	М		9.2.1.71	

Range bound	Explanation		
maxnoofMeasNCell	Maximum number of neighbouring cells on which		
	measurements can be performed.		

9.2.1.52Ca Shared Network Area (SNA) Information

This information element contains a list of Shared Network Areas, identified by the Shared Network Area Code (SNAC, see TS 23.003 [1]) which a certain cell belongs to. For a broader description of the SNA access control see TS 25.401 [40].

IE/Group Name	Presence	Range	IE type and reference	Semantics description
PLMN Identity	M		OCTET STRING (3)	- digits 0 to 9, two digits per octet, - each digit encoded 0000 to 1001, - 1111 used as filler - bit 4 to 1 of octet n encoding digit 2n-1 - bit 8 to 5 of octet n encoding digit 2n - The PLMN Identity consists of 3 digits from MCC followed by either -a filler plus 2 digits from MNC (in case of 2 digit MNC) or -3 digits from MNC (in case of a 3 digit MNC).
List of SNAs		0 <maxnoofsnas< td=""><td></td><td></td></maxnoofsnas<>		
> SNAC	M		INTEGER (0 65535)	

Range bound	Explanation
maxnoofSNAs	Maximum number of SNAs one cell can be part of.

9.2.1.52D SID

The SID IE provides the identity of the Size Index.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
SID			INTEGER (07)	

9.2.1.53 S-RNTI

The S-RNTI identifies the UE in the SRNC.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
S-RNTI			INTEGER(0.	
			.2^20 -1)	

9.2.1.53a S-RNTI Group

The S-RNTI Group identifies a group of Ues in the SRNC.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
S-RNTI	M		9.2.1.53	
S-RNTI bit mask index	M		Enumerated(
			b1,	
			b2,b19,)	

The S-RNTI group is identified by all S-RNTI values whose bits starting from the most significant bit down to, and including, the bit indicated by S-RNTI bit mask index, are equal to the corresponding bits of the S-RNTI in this IE.

The bits of the S-RNTI in this IE that are less significant than the bit position indicated by the S-RNTI bit mask index shall be ignored.

9.2.1.54 Sync Case

The SCH and PCCPCH in a TDD cell are mapped on one or two downlink slots per frame. There are two cases of Sync Case as follows:

Case 1) SCH and PCCPCH allocated in a single TS#k

Case 2) SCH allocated in two TS: TS#k and TS#k+8

PCCPCH allocated in TS#k

[1.28Mcps TDD – There is no Sync Case indication needed for 1.28Mcps TDD. If the *Sync Case* IE must be included in a message from DRNC to SRNC used for 1.28Mcps TDD, the DRNC shall indicate Sync Case 1 and the SRNC shall ignore it.]

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Sync Case			INTEGER	
			(12,)	

9.2.1.54A T1

The T1 IE is used as described in TS 25.321 [41] subclause 11.6.2.3.

IE/Group Name	Presence	Range	IE type and	Semantics description
			reference	
T1			ENUMERAT	Unit: ms
			ED (10, 20,	Node B may use this value to
			30, 40, 50,	stop the re-transmission of
			60, 70, 80,	the corresponding MAC-hs
			90, 100, 120,	PDU.
			140, 160,	
			200, 300,	
			400,)	

9.2.1.55 TFCI Presence

The TFCI Presence parameter indicates whether the TFCI shall be included. [TDD – If it is present in the timeslot, it will be mapped to the channelisation code defined by TS 25.221 [12].]

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
TFCI Presence			ENUMERATE	
			D(Present,	
			not present)	

9.2.1.56 Time Slot

The Time Slot represents the time interval assigned to a Physical Channel referred to the start of a Radio Frame.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Time Slot			INTEGER	
			(014)	

9.2.1.56A TNL QoS

This IE indicates the TNL QoS characteristics of the transport bearer for the uplink data traffic.

When the DS field IE is used, the value of this IE is configurable by the operator.

When the Generic Traffic Category IE is used, generic traffic categories are implementation-specific (e.g. they may be determined by the sender from the application parameters). The value assigned to each of these categories and sent in the Generic Traffic Category IE is configurable by the operator, as well as the mapping of this value to DS field (IETF RFC 2474 [44]) at the DRNS side.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE TNL QoS type	M			
>DS Field				
>>DS field	M		BIT STRING (8)	DS field as defined in IETF RFC 2474 [44]. Typically used when the DRNS and its SRNC are in the same DS domain as defined in IETF RFC 2475 [45].
>Generic Traffic				
Category				
>>Generic Traffic Category	М		BIT STRING (8)	

9.2.1.57 ToAWE

ToAWE is the window endpoint. DL data frames are expected to be received before this window endpoint. ToAWE is defined with a positive value relative Latest Time of Arrival (LtoA). A data frame arriving after ToAWE gives a Timing Adjustment Control frame response.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
ToAWE			INTEGER (02559)	Unit: msec.

9.2.1.58 ToAWS

ToAWS is the window startpoint. DL data frames are expected to be received after this window startpoint. ToAWS is defined with a positive value relative Time of Arrival Window Endpoint (ToAWE). A data frame arriving before ToAWS gives a Timing Adjustment Control frame response.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
ToAWS			INTEGER (01279)	Unit: msec.

9.2.1.58a Trace Depth

The Trace Depth IE is Trace Configuration Parameter what should be traced by the DRNC on the indicated interfaces.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Trace Depth			ENUMERATED (Minimum,	Meaning of this parameter is described in TS 32.422 [49]
			Medium, Maximum)	

9.2.1.58b Trace Recording Session Reference

The *Trace Recording Session Reference* IE provides a Trace Recording Session Reference allocated by the triggering entity.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Trace Recording Session Reference			INTEGER (065535)	

9.2.1.58c Trace Reference

The Trace Reference IE provides a Trace Reference allocated by the triggering entity.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Trace Reference			OCTET STRING	
			(SIZE(23))	

9.2.1.58A Traffic Class

This IE indicates the type of application the Radio Bearer is optimised for.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Traffic Class			ENUMERATED	
			(conversational,	
			streaming,	
			interactive,	
			background,	
)	

9.2.1.59 Transaction ID

The Transaction ID is used to associate all the messages belonging to the same procedure. Messages belonging to the same procedure shall use the same Transaction ID.

The Transaction ID is determined by the initiating peer of a procedure.

For procedures addressed to a specific UE Context, the Transaction ID shall uniquely identify a procedure among all ongoing parallel procedures for the same UE using the same procedure code, and initiated by the same protocol peer.

For procedures not addressed to a specific UE Context, the Transaction ID shall uniquely identify a procedure among all ongoing parallel procedures using the same procedure code, and initiated by the same protocol peer.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Transaction ID Length				The Transaction ID shall be interpreted for its integer value, not for the type of encoding ("short" or "long").
>Short				
>>Transaction ID Value	М		INTEGER (0127)	
>Long				
>>Transaction ID Value	М		INTEGER (032767)	

9.2.1.59A Transmitted Carrier Power

The *Transmitted Carrier Power* IE contains the Transmitted Carrier Power in a cell, as defined in TS 25.215 [11] & TS 25.225 [14].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Transmitted Carrier Power			INTEGER(0100)	According to mapping in TS 25.133 [23] and TS 25.123
				[24].

9.2.1.59B T_{UTRAN-GPS} Accuracy Class

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
T _{UTRAN-GPS} Accuracy Class			ENUMERAT	More information about
			ED(Accuracy	Measurement Accuracy Class is
			Class A,	included in TS 25.133 [23].
			Accuracy	
			Class B,	
			Accuracy	
			Class C,)	

9.2.1.59C T_{UTRAN-GPS} Measurement Threshold Information

The $T_{UTRAN-GPS}$ Measurement Threshold Information defines the related thresholds for UTRAN GPS Timing of Cell Frames for UE Positioning measurements shall trigger the Event On Modification.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Tutran-gps Change Limit	0		INTEGER(1256)	Change of T _{UTRAN-GPS} value compared to previously reported value, which shall trigger a new report. Unit in 1/16 chip.
Predicted Tutran-gps Deviation Limit	0		INTEGER(1256)	Deviation of the Predicted T _{UTRAN-GPS} from the latest measurement result, which shall trigger a new report. Unit in 1/16 chip.

9.2.1.59D T_{UTRAN-GPS} Measurement Value Information

The $T_{UTRAN-GPS}$ *Measurement Value Information* IE indicates the measurement results related to the UTRAN GPS Timing of Cell Frames for UE Positioning measurements.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Tutran-gps		1		Indicates the UTRAN GPS Timing of Cell Frames for UE Positioning. According to mapping in TS 25.133 [23] and TS 25.123 [24]; significant values range from 0 to 37158911999999.
>MS	M		INTEGER (016383)	Most Significant Part
>LS	М		INTEGER (04294967 295)	Least Significant Part
T _{UTRAN-GPS} Quality	0		INTEGER(0. .255)	Indicates the standard deviation (std) of the $T_{UTRAN\text{-}GPS}$ measurements in 1/16 chip. $T_{UTRAN\text{-}GPS}$ Quality = $\sqrt{E[(x-\mu)^2]}$ = std of reported $T_{UTRAN\text{-}GPS}$ Value, where x is the reported $T_{UTRAN\text{-}GPS}$ Value and μ = $E[x]$ is the expectation value of x.
Tutran-gps Drift Rate	M		INTEGER(- 5050)	Indicates the T _{UTRAN-GPS} drift rate in 1/256 chip per second. A positive value indicates that the UTRAN clock is running at a lower frequency than GPS clock.
Tutran-gps Drift Rate Quality	0		INTEGER(0. .50)	Indicates the standard deviation (std) of the $T_{UTRAN-GPS}$ drift rate measurements in 1/256 chip per second. $T_{UTRAN-GPS}$ Drift Rate Quality = $\sqrt{E[(x-\mu)^2]}$ = std of reported $T_{UTRAN-GPS}$ Drift Rate, where x is the reported $T_{UTRAN-GPS}$ Drift Rate and $\mu = E[x]$ is the expectation value of x.

9.2.1.60 Transport Bearer ID

The Transport Bearer ID uniquely identifies an Iur transport bearer.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Transport Bearer ID			INTEGER(04095)	

9.2.1.61 Transport Bearer Request Indicator

Indicates whether a new Iur transport bearer needs to be established for carrying the corresponding data stream(s), or whether an existing transport bearer will be used.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Transport Bearer Request			ENUMERAT	
Indicator			ED(Bearer	
			Requested,	
			Bearer not	
			Requested,	
)	

9.2.1.62 Transport Layer Address

In case of transport bearer establishment with ALCAP (TS 25.426 [3] TS 25.424 [35]), this IE contains the address to be used for Transport Network Control Plane signalling to establish the transport bearer according to TS 25.426 [3], TS 25.424 [35].

In order to allow transport bearer establishment without ALCAP, this IE contains the address of the transport bearer to be used for the user plane transport.

For details on the Transport Address used see TS 25.426 [3].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Transport Layer Address			BIT	
			STRING(11	
			60,)	

9.2.1.63 Transport Format Combination Set (TFCS)

The Transport Format Combination Set is defined as a set of Transport Format Combinations on a Coded Composite Transport Channel. It is the allowed Transport Format Combinations of the corresponding Transport Channels. The DL Transport Format Combination Set is applicable to DL Transport Channels.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE TFCS Values	M			
>Always Used				This choice is always made.
>>TFCS		1 <maxnooftfcs ></maxnooftfcs 		The first instance of the parameter corresponds to TFCI zero, the second to 1 and so on. [TDD – The first entry (for TFCI 0) should be ignored by the receiver.]
>>>CTFC	М		9.2.1.14A	
>>>CHOICE Gain Factors	C- PhysChan			
>>>Signalled Gain Factors			_	
>>>>Gain Factor βc	М		INTEGER(0 15)	[FDD – For UL DPCCH or control part of PRACH TS 25.213 [21].] [TDD - β for UL DPCH mapping in accordance to TS 25.223 [13].]
>>>>Gain Factor β _D	М		INTEGER(0 15)	[FDD – For UL DPDCH or data part of PRACH TS 25.213 [21].] [TDD – Should be set to 0 by the sender, and shall be ignored by the receiver.]
>>>>Reference TFC nr	0		INTEGER(0 15)	If this TFC is a reference TFC, this IE indicates the reference number
>>>>Computed Gain Factors				
>>>>Reference TFC nr	M		INTEGER(0 15)	Indicates the reference TFC to be used to calculate the gain factors for this TFC
>Not Used			NULL	This choice shall never be made by the SRNC and the DRNC shall consider the procedure as failed if it is received.

Condition	Explanation
PhysChan	The choice shall be present if the TFCS concerns a UL DPCH
	[FDD – or PRACH channel].

Range bound	Explanation
maxnoofTFCs	The maximum number of Transport Format Combinations.

9.2.1.64 Transport Format Set

The Transport Format Set is defined as the set of Transport Formats associated to a Transport Channel, e.g. DCH.

[TDD – The Transport Format Set for each transport channel within the same CCTrCH shall have the same value for the 2^{nd} Interleaving Mode IE.]

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Dynamic Transport Format Information		1 <maxtfcount></maxtfcount>		The first instance of the parameter corresponds to TFI zero, the second to 1 and so on.
>Number of Transport Blocks	М		INTEGER (0512)	
>Transport Block Size	C – Blocks		INTEGER (05000)	Unit: Bits
>CHOICE Mode	M			
>>TDD				
>>>Transmission	C-	1 <maxttlcount></maxttlcount>		
Time Interval Information	TTIdynamic			
>>>Transmission Time Interval	M		ENUMERAT ED(10, 20, 40, 80,)	Unit: msec
Semi-static Transport Format Information		1		
>Transmission Time Interval	М		ENUMERAT ED (10, 20, 40, 80, dynamic,)	Unit: msec Value "dynamic" for TDD only. For FDD DCH, the value "80" is applicable only when DL DPCH Slot Format IE indicates a slot format with SF=512.
>Type of Channel Coding	M		ENUMERAT ED (No codingTDD, Convolutiona I, Turbo,)	[FDD – The value "No codingTDD" shall be treated as logical error if received]
>Coding Rate	C – Coding		ENUMERAT ED (1/2, 1/3,)	
>Rate Matching	М		INTEGER	
Attribute			(1maxRM)	
>CRC size	М		ENUMERAT ED (0, 8, 12, 16, 24,)	
>CHOICE Mode	М			
>>TDD >>>2 nd Interleaving Mode	M		ENUMERAT ED(Frame related, Timeslot related,)	

Condition	Explanation
Blocks	The IE shall be present if the Number of Transport Blocks IE is set
	to a value greater than 0.
Coding	The IE shall be present if <i>Type of Channel Coding</i> IE is set to
	"Convolutional" or "Turbo".
TTIdynamic	The IE shall be present if the <i>Transmission Time Interval</i> IE in the
	Semi-static Transport Format Information IE is set to "dynamic".

Range bound	Explanation
maxTFcount	The maximum number of different transport formats that can be
	included in the Transport format set for one transport channel.
maxRM	The maximum number that could be set as rate matching attribute
	for a transport channel.
maxTTlcount	The amount of different TTI that are possible for that transport
	format is.

9.2.1.65 TrCH Source Statistics Descriptor

Defines the statistics of the data transmitted in the transport channel. This information may be used in reserving resources in the DRNS.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
TrCH Source Statistics			ENUMERAT	"Speech" = Statistics of the
Descriptor			ED(Speech, RRC, Unknown,)	data corresponds to speech. "RRC" = Statistics of the data corresponds to RRC signalling "Unknown" = The statistics of the data is unknown

9.2.1.66 UARFCN

The UTRA Absolute Radio Frequency Channel Number defines the carrier.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UARFCN			INTEGER(016383,)	Corresponds to: 0.0Hz 3276.6MHz see TS 25.104 [6] and TS 25.105 [7].

9.2.1.66A UE Identity

The UE Identity IE identifies the UE by one of its Permanent NAS Identifier.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE UE Identity	M			
>IMSI				
>>IMSI	M		9.2.1.31	
>IMEI				
>>IMEI	M		9.2.1.30T	
>IMEISV				
>>IMEISV	M		9.2.1.30U	

9.2.1.67 UL FP Mode

This parameter defines if normal or silent mode of the Frame Protocol shall be used for the UL.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UL FP Mode			ENUMERAT	
			ED(Normal,	
			Silent,)	

9.2.1.68 UL Interference Level

Void

9.2.1.68A Uncertainty Ellipse

This IE contains the uncertainty ellipse used to describe a possible shape of the geographical area of a cell.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Uncertainty semi-major	M		INTEGER(0127)	The uncertainty "r" is derived from the "uncertainty code" k by r = 10x(1.1 ^k -1)
Uncertainty semi-minor	M		INTEGER(0127)	The uncertainty "r" is derived from the "uncertainty code" k by $r = 10x(1.1^k-1)$
Orientation of major axis	М		INTEGER(0179)	The relation between the IE value (N) and the angle (a) in degrees it describes is 2N≤ a <2(N+1). The values 90179 shall not be used.

9.2.1.68B Unidirectional DCH Indicator

The Unidirectional DCH Indicator IE indicates that the DCH is unidirectional.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Unidirectional DCH Indicator			ENUMERATED	
			(Downlink DCH only,	
			Uplink DCH only)	

9.2.1.69 Uplink SIR

The UL SIR indicates a received UL SIR.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Uplink SIR			INTEGER (- 82173)	Value = Uplink SIR/10 Unit dB Range -8.2+17.3 Step 0.1 dB

9.2.1.70 URA ID

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
URA ID			INTEGER(0. .65 535)	

9.2.1.70A UTRAN Access Point Position

The UTRAN Access Point Position indicates the exact geographical position of the base station antenna.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Latitude Sign	M		ENUMERAT ED(North, South)	
Degrees of Latitude	M		INTEGER(02 ²³ -1)	The IE value (N) is derived by this formula: N≤2 ²³ X /90 < N+1 X being the latitude in degree (0° 90°)
Degrees of Longitude	М		INTEGER(-2 ²³ 2 ²³ -1)	The IE value (N) is derived by this formula: N≤2 ²⁴ X /360 < N+1 X being the longitude in degree (-180°+180°)

9.2.1.70B URA Information

The URA Information IE contains URA Information for one cell.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
URA ID	М		9.2.1.70		_	
Multiple URAs Indicator	М		9.2.1.41		_	
RNCs with Cells in the Accessed URA		0 <maxrncin URA-1></maxrncin 		Other RNCs having at least one cell in the URA identified by the URA ID IE.	-	
>RNC-ID	М		9.2.1.50	If the Extended RNC-ID IE is included in the URA Information IE, the RNC-ID IE shall be ignored.	-	
>Extended RNC-ID	0		9.2.1.50a	The Extended RNC-ID IE shall be used if the RNC identity has a value larger than 4095.	YES	reject

Range Bound	Explanation
maxRNCinURA	Maximum number of RNC in one URA.

9.2.1.70C User Plane Congestion Fields Inclusion

The *User Plane Congestion Fields Inclusion* IE is used by the DRNC to indicate to the SRNC to include in the HS-DSCH Data Frames the User Plane fields related to TNL Congestion Control for HSDPA (namely the Frame Sequence Number and the DRT, see TS 25.425 [32]).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
User Plane Congestion Fields			ENUMERATED (
Inclusion			Shall be included)	

9.2.1.71 UTRAN Cell Identifier (UC-ID)

The UC-ID (UTRAN Cell identifier) is the identifier of a cell in one UTRAN.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
RNC-ID	M		9.2.1.50	If the Extended RNC-ID IE is included in the UC-ID IE, the RNC-ID IE shall be ignored.
C-ID	М		9.2.1.6	
Extended RNC-ID	0		9.2.1.50a	The Extended RNC-ID IE shall be used if the RNC identity has a value larger than 4095.

9.2.1.72 Neighbouring TDD Cell Information LCR

The *Neighbouring TDD Cell Information LCR* IE provides information for 1.28Mcps TDD cells that are neighbouring cells to a cell in the DRNC.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Neighbouring TDD Cell Information LCR		1 <maxno ofLCRTDD neighbour s></maxno 			-	
>C-ID	M		9.2.1.6		_	
>UARFCN	M		9.2.1.66	Corresponds to Nt in TS 25.105 [7]	-	
>Frame Offset	0		9.2.1.30		1	
>Cell Parameter ID	M		9.2.1.8		1	
>SCTD Indicator	M		9.2.1.78		_	
>Cell Individual Offset	0		9.2.1.7		_	
>DPCH Constant Value	0		9.2.1.23		-	
>PCCPCH Power	0		9.2.1.43		_	
>Restriction State Indicator	0		9.2.1.48C		-	
>Coverage Indicator	0		9.2.1.12G		YES	ignore
>Antenna Co-location Indicator	0		9.2.1.2C		YES	ignore
>HCS Prio	0		9.2.1.30N		YES	ignore
>Cell Capability Container TDD LCR	0		9.2.3.1b		YES	ignore
>SNA Information	0		9.2.1.52Ca		YES	ignore
>Multiple PLMN List	0		9.2.1.117		YES	ignore
>Cell Capability Container Extension TDD LCR	0		9.2.3.80		YES	ignore

Range bound	Explanation
maxnoofLCRTDDneighbours	Maximum number of neighbouring 1.28Mcps TDD cell for one cell.

9.2.1.73 Permanent NAS UE Identity

This element is used to identify the UE in UTRAN.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Choice Permanent NAS UE Identity				
>IMSI				
>>IMSI	M		9.2.1.31	

9.2.1.74 SFN-SFN Measurement Reference Point Position

The SFN-SFN Measurement Reference Point Position indicates the exact geographical position of the SFN-SFN measurement reference point. The altitude shall be included when available.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Geographical Coordinates	M		9.2.1.30F	
Altitude and direction	0		9.2.1.2B	

9.2.1.75 UTRAN Access Point Position with Altitude

The UTRAN Access Point Position with Altitude indicates the exact geographical position of the base station antenna. The altitude shall be included when available.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Geographical Coordinates	M		9.2.1.30F	
Altitude and direction	0		9.2.1.2B	

9.2.1.76 SFN-SFN Measurement Time Stamp

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Mode	M			
>FDD				
>>SFN	М		9.2.1.52A	Indicates the SFN of the reference cell at which the measurement has been performed.
>TDD				
>>SFN	М		9.2.1.52A	Indicates the SFN of the reference cell at which the measurement has been performed.
>>Time Slot	M		9.2.1.56	Indicates the Time Slot of the reference cell at which this measurement has been performed.

9.2.1.77 SFN-SFN Value

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Mode	M			
>FDD				
>>SFN-SFN	M		INTEGER(0.	According to mapping in TS
			. 614399)	25.133 [23].
>TDD				1.28Mcps or 3.84Mcps TDD
>>SFN-SFN	M		INTEGER(0.	According to mapping in TS
			. 40961)	25.123 [24].
>TDD 7.68Mcps				
>>SFN-SFN	M		INTEGER(0.	According to mapping in TS
			. 81923)	25.123 [24].

9.2.1.78 SCTD Indicator

Indicates if SCTD antenna diversity is applied or not to the PCCPCH and PICH [3.84Mcps TDD].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
SCTD Indicator			ENUMERAT ED(active, inactive)	

9.2.1.79 Congestion Cause

The Congestion Cause IE indicates the cause of a congestion situation:

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Congestion Cause			ENUMERATED (UTRAN Dynamic Resources, UTRAN Semistatic Resources,)	

The meaning of the different congestion cause values is described in the following table:

Congestion cause	Meaning
UTRAN Dynamic Resources	UL and/or DL resource congestion situation mainly caused by the UL
	and/or DL UTRAN Dynamic Resources. This type of congestion situation
	is, e.g. related to the limitation of the DL transmitted carrier power of the
	cell(s), or the UL Interference situation in the concerned cell(s).
UTRAN Semistatic Resources	UL and/or DL resource congestion situation mainly related to UTRAN
	Semistatic Resources (e.g. channelisation codes, Node-B resources,).

9.2.1.80 TMGI

The TMGI is the unique identifier for an MBMS bearer service, see TS 23.003 [1].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
PLMN Identity	M		OCTET STRING (3)	- digits 0 to 9, two digits per octet, - each digit encoded 0000 to 1001, - 1111 used as filler - bit 4 to 1 of octet n encoding digit 2n-1 - bit 8 to 5 of octet n encoding digit 2n -The PLMN Identity consists of 3 digits from MCC followed by either -a filler plus 2 digits from MNC (in case of 2 digit MNC) or -3 digits from MNC (in case of a 3 digit MNC).
Service ID	М		OCTET STRING (3)	

9.2.1.81 Transmission Mode

The Transmission Mode IE indicates the transmission mode used for MBMS data transmission in one cell.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Transmission Mode			ENUMERAT ED(PTP, PTM, Not Provided).	PTP: The MBMS data is transmitted through point to point channel. PTM: The MBMS data is transmitted through point to multipoint channel. Not Provided: The MBMS data is not transmitted in the DRNC.

9.2.1.82 Access Point Name

The APN and IP Multicast Address uniquely identify an MBMS bearer service.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
APN	M		OCTET STRING	
			(1255)	

9.2.1.83 IP Multicast Address

The APN and IP Multicast Address uniquely identify an MBMS bearer service.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
IP Multicast Address	M		OCTET STRING (416)	

9.2.1.84 MBMS Bearer Service Full Address

This IE provides the full address of an MBMS Bearer Service otherwise identified by its TMGI.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Access Point Name	M		9.2.1.82	
IP Multicast Address	M		9.2.1.83	

9.2.1.85 Provided Information

This IE contains the relevant data concerned the direct information transfer procedure. *Provided Information* IE shall include at least one of the following IEs.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
MBMS Channel Type Information	0		9.2.1.86			
MBMS Preferred Frequency Layer Information	0		9.2.1.87			
UpPCH Information LCR	0		9.2.3.55	Applicable to 1.28Mcps TDD only.	YES	ignore
ANR Report Indication	0		9.2.1.148		YES	ignore

9.2.1.86 MBMS Channel Type Information

This IE contains the channel types of a MBMS Bearer Service indicated by *TMGI* IE in one or more cells. *MBMS Channel Type Information* IE shall include at least one *C-ID* IE and *Affected UE Information for MBMS* IE in the *PTM Cell List* IE, the *PTP Cell List* IE and/or *Not Provided Cell List* IE.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
TMGI	M		9.2.1.80	
PTM Cell List		0 <maxnoofcells></maxnoofcells>		
>C-ID	M		9.2.1.6	
>Affected UE Information		0 <maxnoofues></maxnoofues>		
for MBMS				
>>S-RNTI	M		9.2.1.53	
PTP Cell List		0 <maxnoofcells></maxnoofcells>		
>C-ID	M		9.2.1.6	
>Affected UE Information		0 <maxnoofues></maxnoofues>		
for MBMS				
>>S-RNTI	M		9.2.1.53	
Not Provided Cell List		0 <maxnoofcells></maxnoofcells>		
>C-ID	M		9.2.1.6	
>Affected UE Information		0 <maxnoofues></maxnoofues>		
for MBMS				
>>S-RNTI	M		9.2.1.53	

Range Bound	Explanation
maxnoofCells	Maximum number of cells that can be indicated in the corresponding IE.
maxnoofUEs	Maximum number of S-RNTIs that can be indicated per cell in the respective IEs.

9.2.1.87 MBMS Preferred Frequency Layer Information

This IE contains the preferred frequency layer of a MBMS Bearer Service indicated by *TMGI* IE in one or more cells that host at least one CELL_DCH UE whose UE Link contains the concerned MBMS Bearer Service and whose SRNC is different from the CRNC.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
TMGI	M		9.2.1.80	
Preferred Frequency Layer Information				
>Default Preferred	M		UARFCN	
Frequency			9.2.1.66	
>Additional Preferred		0 <maxnoofaddfr< td=""><td></td><td>Preferred frequencies</td></maxnoofaddfr<>		Preferred frequencies
Frequency		eq>		different from default preferred frequency
>>DL UARFCN	M		UARFCN	
			9.2.1.66	
>>Corresponding Cells		1 <maxnoofcellsp erFreq></maxnoofcellsp 		
>>>C-ID	М		9.2.1.6	

Range Bound	Explanation
maxnoofAddFreq	Maximum number of additional preferred frequencies different from
	default preferred frequency in an RNC.
maxnoofCellsPerFreq	Maximum number of cells whose preferred frequency is the same.

9.2.1.88 E-DCH DDI Value

The *E-DCH DDI Value* IE is the Data Description Indicator value identifying a unique combination of E-DCH MAC-d Flow ID and MAC-d PDU Size.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH DDI Value			INTEGER	
			(062)	

9.2.1.89 E-DCH MAC-d Flow Multiplexing List

The E-DCH MAC-d Flow Multiplexing List indicates which E-DCH MAC-d flows are allowed to be multiplexed within a MAC-e PDU with the MAC-d flow it is associated to. If the E-DCH MAC-d Flow Multiplexing List is signalled for an E-DCH MAC-d flow it indicates that E-DCH MAC-d PDUs of this E-DCH MAC-d flow are the first E-DCH MAC-d PDU in the MAC-e PDU. If an E-DCH MAC-d Flow Multiplexing List was already received within a previous Radio Link related procedure and no E-DCH MAC-d Flow Multiplexing List is signalled for a E-DCH MAC-d flow, the DRNS shall continue to use the previously received one. If no E-DCH MAC-d Flow Multiplexing List was ever received for an E-DCH MAC-d flow no restrictions shall be assumed for the related E-DCH MAC-d flow for multiplexing E-DCH MAC-d flows.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH MAC-d Flow Multiplexing List			BIT STRING (8)	The first Bit corresponds to E-DCH MAC-d flow 0, the second bit corresponds to E-DCH MAC-d flow 1, etc. For 1.28Mcps TDD, if the IE is included in the IE Common E-DCH MAC-d Flow Specific Information LCR, the first Bit corresponds to E-DCH MAC-d with the lowest E-DCH MAC-d Flow ID within the same frequency, the second bit corresponds to E-DCH MAC-d flow with the second lowest E-DCH MAC-d Flow ID within the same frequency, etc.

9.2.1.90 E-DCH MAC-d Flows To Delete

The E-DCH MAC-d Flows To Delete IE is used for the removal of E-DCH MAC-d flows.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH MAC-d Flows To Delete		1 <maxnoofedch MACdFlows></maxnoofedch 		
>E-DCH MAC-d Flow ID	М		9.2.1.91	

Range Bound	Explanation
maxnoofEDCHMACdFlows	Maximum number of E-DCH MAC-d flows

9.2.1.91 E-DCH MAC-d Flow ID

The E-DCH MAC-d Flow ID IE is the unique identifier for one MAC-d flow on E-DCH.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH MAC-d Flow ID			INTEGER (0 maxnoofEDC HMACdFlow s-1)	

Range Bound	Explanation
maxnoofEDCHMACdFlows	Maximum number of E-DCH MAC-d flows

9.2.1.91A E-DCH MAC-d PDU Size Format

The *E-DCH MAC-d PDU Size Format* IE provides information about the type of MAC-d PDU Size Format thet shall be used for the E-DCH in the new configuration. "Fixed MAC-d PDU Size" uses MAC-d PDU sizes defined in *MAC-d PDU Size List* IE of the *E-DCH Logical Channel Information* IE. "Flexible MAC-d PDU Size" uses a flexible MAC-d PDU size with a maximum PDU size as defined by *Maximum MAC-d PDU Size Extended* IE of *E-DCH Logical Channel Information* IE. The actual MAC-d PDU size is determined as specified in TS 25.123 [24] and TS 25.425 [32].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH MAC-d PDU Size			ENUMERATED	
Format			(Fixed MAC-d PDU	
			Size, Flexible MAC-d	
			PDU Size)	

9.2.1.92 E-DCH Logical Channel Information

The E-DCH Logical Channel Information IE is used for the establishment of E-DCH Logical Channels.

IE/Group Name	Presenc e	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
E-DCH Logical Channel Information		1 <maxnoofl ogicalchanne ls></maxnoofl 	Reference		-	
>Logical Channel ID	М	102	9.2.1.97			
>Scheduling Priority	M		9.2.1.51A		_	
Indicator	'''		0.2.110171			
>Scheduling Information	M		9.2.1.101		_	
>MAC-es Guaranteed Bit Rate	0		9.2.1.98		_	
>E-DCH DDI Value	M		9.2.1.88	If more than 1 MAC-d PDU size is configured for this Logical Channel, the different sizes will use subsequent DDI values starting from this DDI value. Value "0x3F" is reserved. Shall be ignored if Maximum MAC-d PDU Size Extended IE is present.	_	
>MAC-d PDU Size List		1< maxnoofMA CdPDUSize			-	
>>MAC-d PDU Size	М		9.2.1.34A	Shall be ignored if Maximum MAC-d PDU Size Extended IE is present.	-	
>Maximum MAC-d PDU Size Extended	0		MAC PDU Size Extended 9.2.1.34D		YES	reject
>MAC-es Maximum Bit Rate LCR	0		9.2.3.59	1.28Mcps TDD only	YES	ignore
>UE Aggregate Maximum Bit Rate Enforcement Indicator	0		NULL	·	YES	ignore

Range Bound	Explanation
maxnooflogicalchannels	Maximum number of logical channels
maxnoofMACdPDUSize	Maximum number of MAC-d PDU size per Logical Channels

9.2.1.93 E-DCH Logical Channel To Modify

The *E-DCH Logical Channel To Modify* IE is used for the reconfiguration of E-DCH Logical Channels.

IE/Group Name	Presenc e	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
E-DCH Logical Channel Information		1 <maxnoofl ogicalchanne ls></maxnoofl 	Reference		-	
>Logical Channel ID	M		9.2.1.97		_	
>Scheduling Priority Indicator	0		9.2.1.51A		_	
>Scheduling Information	0		9.2.1.101		_	
>MAC-es Guaranteed Bit Rate	0		9.2.1.98		_	
>E-DCH DDI Value	0		9.2.1.88	If more than 1 MAC-d PDU size is configured for this Logical Channel, the different sizes will use subsequent DDI values starting from this DDI value. Value "0x3F" is reserved. Shall be ignored if Maximum MAC-d PDU Size Extended IE is present.		
>MAC-d PDU Size List		0< maxnoofMA CdPDUSize			_	
>>MAC-d PDU Size	M		9.2.1.34A		_	
>Maximum MAC-d PDU Size Extended	0		MAC PDU Size Extended 9.2.1.34D		YES	reject
>MAC-es Maximum Bit Rate LCR	0		9.2.3.59	1.28Mcps TDD only	YES	ignore

Range Bound	Explanation
maxnooflogicalchannels	Maximum number of logical channels
maxnoofMACdPDUSize	Maximum number of MAC-d PDU size per Logical Channels

9.2.1.94 E-RNTI

The *E-RNTI* IE is needed for the UE (or UE group) specific CRC in E-AGCH, see TS 25.319 [52].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-RNTI			INTEGER	
			(065535)	

9.2.1.95 E-DCH Processing Overload Level

The *E-DCH Processing Overload Level* IE defines the threshold that determines when DRNS shall indicate processing issue problems to the SRNC.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
E-DCH Processing Overload Level			INTEGER (010,)	Number of consecutive TTIs. The value "0" is a special value, that means infinity, i.e. when this value is used, the DRNS shall never indicate processing issue to the RNC.

9.2.1.96 E-DCH Power Offset for Scheduling Info

The E-DCH Power Offset for Scheduling Info is used to calculate the [FDD – E-DPDCH][TDD – E-PUCH] power for transmision of scheduling information without any MAC-d PDUs.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH Power Offset for Scheduling Info			INTEGER (06)	Unit: dB Step: 1 dB

9.2.1.97 Logical channel ID

The Logical Channel ID IE is used to identify a E-DCH logical channel in Scheduling Information that is sent over Uu.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Logical Channel ID		INTEGER		
		(115)		

9.2.1.98 MAC-es Guaranteed Bit Rate

The MAC-es Guaranteed Bit Rate IE indicates the guaranteed number of bits per second to be delivered over the air interface under normal operating conditions (provided there is data to deliver) for which the Node B shall provide sufficient UL resources. If the MAC-es Guaranteed Bit Rate IE is received with the value set to 0 during RL set up or modification, no guarantee is applied.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
MAC-es Guaranteed Bit Rate			INTEGER	Unit: bit/s
			(02^24-1,,	
			2^24256,000,	
			000)	

9.2.1.99 MAC-e Reset Indicator

Indicates the MAC-e (or MAC-i) Reset is performed in UE.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
MAC-e Reset Indicator			ENUMERAT	Means MAC-I Reset in case
			ED (MAC-e	Maximum MAC-d PDU Size
			Reset)	Extended is configured for
				an E-DCH Logical Channel.

9.2.1.100 Maximum Number of Retransmissions for E-DCH

The *Maximum Number of Retransmissions for E-DCH* IE specifies the upper boundary for retransmissions for a single MAC-d flow.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Maximum Number of			INTEGER	
Retransmissions for E-DCH			(015)	

9.2.1.101 Scheduling Information

The *Scheduling Information* IE indicates whether the scheduling information is included for the E-DCH logical channel or not.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Scheduling Information			ENUMERAT ED (Included, Not Included)	

9.2.1.102 DGANSS Corrections

This IE contains DGANSS corrections.

IE/Group name	Presence	Range	IE Type and Reference	Semantics description	Criticality	Assigned Criticality
DGANSS Reference Time	М		INTEGER(035 70 by step of 30)	Seconds. Time in GNSS system time (modulo 3600 s) when the DGANSS corrections were calculated	-	
DGANSS		1 to			-	
Information		<maxsg nType></maxsg 				
>GANSS Signal ID	0		9.2.1.121		ı	
>Status/Health	M		ENUMERATED (UDRE scale 1.0, UDRE scale 0.75, UDRE scale 0.5, UDRE scale 0.3, UDRE scale 0.2, UDRE scale 0.1, no data, invalid data)		-	
>DGANSS Signal Information	C- Status/He alth	1 to <maxg ANSSS</maxg 		If the Cipher information is included these fields	-	
		at>		are ciphered		

IE/Group name	Presence	Range	IE Type and Reference	Semantics description	Criticality	Assigned Criticality
>>Sat ID	М		INTEGER(063	Defined in TS 25.331 [16].	-	
>>IOD	М		BIT STRING(10)		-	
>>UDRE	М		ENUMERATED (UDRE \leq 1.0 m, 1.0m < UDRE \leq 4.0m, 4.0m < UDRE \leq 8.0m, 8.0m < UDRE)	The value in this field shall be multiplied by the UDRE Scale Factor in the IE Status/Health to determine the final UDRE estimate for the particular satellite.	-	
>>PRC	M		INTEGER(- 20472047)	Scaling factor 0.32 meters	-	
>>RRC	М		INTEGER(- 127127)	Scaling factor 0.032 meters/sec	-	
>>DGNSS Validity Period	0		9.2.1.138		YES	ignore

Condition	Explanation
Status/Health	This IE shall be present if the Status/Health IE value
	is not equal to "no data" or "invalid data".

Range Bound	Explanation
maxGANSSSat	Maximum number of satellites for which data is included in the IE
maxSanTvpe	Maximum number of signals for which data is included in the IE

9.2.1.103 GANSS Almanac

This IE contains a reduced-precision subset of the ephemeris and clock correction parameters.

IE/Group name	Presence	Range	IE Type and Reference	Semantics description	Criticality	Assigned Criticality
Week Number	M		INTEGER(02 55)	Almanac reference week, number of weeks since the beginning of GANSS specific system time (mod 256)	-	
CHOICE Almanac Model	M				ı	
>Keplerian Parameters				Model 1		
>>T _{oa}	M		INTEGER(02 55)	Scaling factor 2 ¹² s Reference time of almanac within week in GANSS TOD time base	_	
>>IOD _a	М		INTEGER(03	Issue-Of –Data, common to all satellites	_	
>>Satellite Information KP		1 to <maxga NSSSatA Imanac></maxga 		Almanacs are in the order of the SV IDs, the smallest ID first.	-	
>>>Sat ID	М		INTEGER(06 3)	Defined in TS 25.331 [16].	-	
>>>e	М		BIT STRING(11)	Eccentricity, dimensionless (OS SIS ICD [53])	_	
>>>δi	М		BIT STRING(11)	semi-circles (OS SIS ICD [53])	_	
>>>OMEGADOT	M		BIT STRING(11)	Longitude of Ascending Node of Orbit Plane at Weekly Epoch (semi- circles/sec) (OS SIS ICD [53])	П	
>>>SV Health KP	M		BIT STRING(4)	dimensionless	_	
>>>delta A ^{1/2}	M		BIT STRING(17)	Semi-Major Axis delta (meters) ^{1/2} (OS SIS ICD [53])	-	
>>>OMEGA ₀	М		BIT STRING(16)	Longitude of Ascending Node of Orbit Plane at Weekly Epoch (semi-circles) (OS SIS ICD [53])	-1	
>>>M ₀	M		BIT STRING(16)	Mean Anomaly at Reference Time (semi-circles) (OS SIS ICD [53])	ı	
>>0	М		BIT STRING(16)	Argument of Perigee (semi-circles) (OS SIS ICD [53])	-	
>>>af ₀	М		BIT STRING(14)	Seconds (OS SIS ICD [53])	_	
>>>af ₁	М		BIT STRING(11)	sec/sec (OS SIS ICD [53])	ı	
>NAV Keplerian Parameters				Model 2		
>>Keplerian NAV Almanac	М				YES	ignore
>>>T _{oa}	М		INTEGER(02 55)	Scaling factor 2 ¹² s Reference time of almanac within week	-	

				in GANSS TOD time base		
>>>Satellite information NAV-KP		1 <maxga NSSSatA Imanac></maxga 			_	
>>>Sat ID	M		INTEGER (063)	Defined in TS 25.331 [16].	_	
>>>e	M		BIT STRING(16)	Eccentricity, dimensionless (IS- QZSS [59])	_	
>>>δi	M		BIT STRING (16)	Correction to inclination, semi-circles (IS-QZSS [59])	_	
>>>OMEGADOT	M		BIT STRING (16)	Rate of right ascension, semi-circles/sec (IS- QZSS [59])	_	
>>>SV Health	М		BIT STRING (8)	Satellite health (IS- QZSS [59])	_	
>>>A ^{1/2}	М		BIT STRING (24)	Square root of the semi-major axis, meters ^{1/2} (IS-QZSS [59])	_	
>>>OMEGA ₀	M		BIT STRING (24)	Longitude of ascending node of orbit plane at weekly epoch, semi-circles (IS-QZSS [59])	_	
>>>0	M		BIT STRING (24)	Argument of perigee semi-circles (IS-QZSS [59])	-	
>>>M ₀	M		BIT STRING (24)	Mean anomaly at reference time semi-circles (IS-QZSS [59])	_	
>>>af ₀	M		BIT STRING (11)	Apparent satellite clock correction seconds (IS-QZSS [59])	-	
>>>af ₁	М		BIT STRING (11)	Apparent satellite clock correction sec/sec (IS-QZSS [59])	-	
>Reduced Keplerian Parameters				Model 3		
>>Keplerian Reduced Almanac	М				YES	ignore
>>>T _{oa}	M		INTEGER(02 55)	Scaling factor 2 ¹² s Reference time of almanac within week in GANSS TOD time base	_	
>>>Satellite information RED-KP		1 <maxga NSSSatA Imanac></maxga 			-	
>>>Sat ID	М		INTEGER (063)	Defined in TS 25.331 [16].	_	
>>>>δ _A	M		BIT STRING(8)	meters (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS- QZSS [59])	-	
$>>>>\Omega_0$	M		BIT STRING (7)	semi-circles (IS-GPS- 200 [55], IS-GPS-705 [56], IS-GPS-800 [57],	_	

				IS-QZSS [59])		
>>>> Φ ₀	M		BIT STRING	semi-circles (IS-GPS-	_	
			(7)	200 [55], IS-GPS-705		
				[56], IS-GPS-800 [57],		
I 1 Hoolth	M		DIT CTDING	IS-QZSS [59])		
>>>L1 Health	IVI		BIT STRING	dimensionless (IS-	_	
			(1)	GPS-200 [55], IS- GPS-705 [56], IS-		
				GPS-800 [57], IS-		
				QZSS [59])		
>>>>L2 Health	М		BIT STRING	dimensionless (IS-		
>>>LZ Health	IVI		(1)	GPS-200 [55], IS-	_	
			(1)	GPS-705 [56], IS-		
				GPS-800 [57], IS-		
				QZSS [59])		
>>>L5 Health	М		BIT STRING	dimensionless (IS-	_	
			(1)	GPS-200 [55], ÌS-		
				GPS-705 [56], IS-		
				GPS-800 [57], IS-		
				QZSS [59])		
>Midi Keplerian				Model 4		
Parameters		1				
>> Keplerian Midi	M	1			YES	ignore
Almanac		1		12		
>>>T _{oa}	M	1	INTEGER(02	Scaling factor 2 ¹² s	_	
			55)	Reference time of		
				almanac within week		
				in GANSS TOD time		
>>>Satellite		4		base		
>>>Satellite information MIDI-KP		1			_	
information wildi-KP		<maxga NSSSatA</maxga 				
		Imanac>				
>>>Sat ID	M	iiiiaiiac>	INTEGER	Defined in TS 25.331	_	
>>>>0at 15	I IVI		(063)	[16].	_	
>>>e	М		BIT	dimensionless (IS-	_	
			STRING(11)	GPS-200 [55], IS-		
				GPS-705 [56], IS-		
				GPS-800 [57], IS-		
				QZSS [59])		
>>>δ _i	М		BIT STRING	semi-circles (IS-GPS-	_	
•			(11)	200 [55], IS-GPS-705		
				[56], IS-GPS-800 [57],		
				IS-QZSS [59])		
>>>Ω_dot	M	1	BIT STRING	semi-circles/sec (IS-	_	
		1	(11)	GPS-200 [55], IS-		
		1		GPS-705 [56], IS-		
		1		GPS-800 [57], IS-		
	<u> </u>	 		QZSS [59])		
>>>sqrtA	М	1	BIT STRING	meters ^{1/2} (IS-GPS-200	_	
		1	(17)	[55], IS-GPS-705 [56],		
		1		IS-GPS-800 [57], IS-		
	N4	1	DIT CTDING	QZSS [59])		
$>>> \Omega_0$	M	1	BIT STRING	semi-circles (IS-GPS-	_	
		1	(16)	200 [55], IS-GPS-705		
		1		[56], IS-GPS-800 [57],		
2555.00	M	+	BIT STRING	IS-QZSS [59]) semi-circles (IS-GPS-		
>>>>0	IVI	1	(16)	200 [55], IS-GPS-705	_	
		1	(10)	[56], IS-GPS-800 [57],		
		1		IS-QZSS [59])		
>>>M ₀	М	†	BIT STRING	semi-circles (IS-GPS-	_	
()	141	1	(16)	200 [55], IS-GPS-705	_	
		1	(10)	[56], IS-GPS-800 [57],		
		1		IS-QZSS [59])		
>>>a _{fo}	М	1	BIT STRING	seconds (IS-GPS-200	_	
		1	(11)	[55], IS-GPS-705 [56],		
		1	` ′	IS-GPS-800 [57], IS-		
<u> </u>	1	1	1	[],	l	

			_			
				QZSS [59])		
>>>a _{f1}	М		BIT STRING (10)	sec/sec (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-	_	
				QZSS [59])		
>>>L1 Health	M		BIT STRING (1)	Dimensionless (IS- GPS-200 [55], IS- GPS-705 [56], IS- GPS-800 [57], IS- QZSS [59])	_	
>>>L2 Health	M		BIT STRING (1)	dimensionless (IS- GPS-200 [55], IS- GPS-705 [56], IS- GPS-800 [57], IS- QZSS [59])	_	
>>>L5 Health	М		BIT STRING (1)	dimensionless (IS- GPS-200 [55], IS- GPS-705 [56], IS- GPS-800 [57], IS- QZSS [59])	-	
>GLONASS Keplerian				Model 5		
Parameters >> Keplerian GLONASS	M		1		YES	ignore
>> Kepielian GLONASS >>>Satellite	IVI	1			150	ignore
information GLO-KP		<maxga NSSSatA Imanac></maxga 			_	
>>>N ^A	М		BIT STRING(11)	days [60]	_	
>>>n ^A	М		BIT STRING (5)	dimensionless [60]	_	
>>>H _n ^A	М		BIT STRING (5)	dimensionless [60]	_	
>>>\lambda_n^A	М		BIT STRING (21)	semi-circles [60]	_	
>>>t _{\(\lambda\)n\(^{A}\)}	М		BIT STRING (21)	seconds [60]	_	
>>>∆i _n ^A	М		BIT STRING (18)	semi-circles [60]	_	
>>>ΔT _n ^A	М		BIT STRING (22)	sec/orbit period [60]	_	
>>>ΔT_DOT _n ^A	М		BIT STRING (7)	sec/orbit period ² [60]	_	
>>>ε _n ^A	М		BIT STRING (15)	dimensionless [60]	_	
>>>∞ _n ^A	М		BIT STRING (16)	semi-circles [60]	_	
>>>\tau_A	M		BIT STRING (10)	seconds [60]	_	
>>>I	М		BIT STRING (1)	dimensionless [60]	_	
>>>Mn ^A	0		BIT STRING (2)	dimensionless [60]	_	
>SBAS ECEF Parameters	1.4		1	Model 6	VEC	: ·
>> ECEF SBAS Almanac	М				YES	ignore
>>>Satellite information SBAS- ECEF		1 <maxga NSSSatA Imanac></maxga 			_	
>>>>Data ID	М		BIT STRING(2)	Dimensionless (DTFA01-96-C-00025 [58])	_	
>>>SV ID	М		INTEGER (063)	Defined in TS 25.331 [16].	_	
>>>Health	М		BIT STRING (8)	Dimensionless (DTFA01-96-C-00025	_	

			[58])		
>>>X _G	М	BIT STRING (15)	meters (DTFA01-96- C-00025 [58])	-	
>>>Y _G	М	BIT STRING (15)	meters (DTFA01-96- C-00025 [58])	-	
>>>Z _G	М	BIT STRING (9)	meters (DTFA01-96- C-00025 [58])	-	
>>>X _G Rate-of- Change	М	BIT STRING (3)	meters/sec (DTFA01- 96-C-00025 [58])	_	
>>>Y _G Rate-of- Change	М	BIT STRING (3)	meters/sec (DTFA01- 96-C-00025 [58])	_	
>>>Z _G Rate-of- Change	М	BIT STRING (4)	meters/sec (DTFA01- 96-C-00025 [58])	_	
>>>t ₀	М	BIT STRING (11)	seconds (DTFA01-96- C-00025 [58])	_	
Complete Almanac Provided	0	BOOLEAN	This field indicates whether almanac is provided for the full GANSS constellation or not. TRUE means complete GANSS almanac is provided.	YES	ignore

Range Bound	Explanation
maxGANSSSatAlmanac	Maximum number of satellites for which data is included in the IE

9.2.1.104 GANSS Clock Model

The IE contains fields needed to model the GANSS clock parameters.

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
Satellite Clock Model		1 to <maxgan SSClockM od></maxgan 		Model -1 There may be more than one clock model included if defined in SIS ICD (e.g. two for Galileo)
>t _{oc}	М		BIT STRING(14)	defined in OS SIS ICD [53]
>a _{i2}	M		BIT STRING(12)	defined in OS SIS ICD [53]
>a _{i1}	M		BIT STRING(18)	defined in OS SIS ICD [53]
>a _{i0}	М		BIT STRING(28)	defined in OS SIS ICD [53]
>T _{GD}	0		BIT STRING(10)	defined in OS SIS ICD [53]
>Model ID	0		INTEGER(01)	Coded as defined in TS 25.331 [16].

Range bound	Explanation
maxGANSSClockMod	Maximum number of satellite clock models for which data is included in the IE.

9.2.1.104a GANSS Additional Clock Models

The IE contains fields needed to model the GANSS clock parameters.

IE/Group name	Presence	Range	IE Type and	Semantics description
			Reference	

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
CHOICE Additional Clock Models				
>NAV-Clock Model				Model-2
>>t _{oc}	М		BIT STRING(16)	Time of clock (seconds) (IS-QZSS [59])
>>af ₂	М		BIT STRING (8)	Clock correction polynomial coefficient (sec/sec²) (IS-QZSS [59])
>>af ₁	М		BIT STRING (16)	Clock correction polynomial coefficient (sec/sec) (IS-QZSS [59])
>>af ₀	M		BIT STRING (22)	Clock correction polynomial coefficient (seconds) (IS-QZSS [59])
>>T _{GD}	М		BIT STRING (8)	Group delay (seconds) (IS-QZSS [59])
>CNAV/CNAV-2 Clock Model				Model-3
>>t _{oc}	M		BIT STRING (11)	Clock data reference time of week (seconds) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>t _{op}	M		BIT STRING (11)	Clock data predict time of week (seconds) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>URA _{oc} Index	М		BIT STRING (5)	SV clock accuracy index (dimensionless) (IS-GPS-200 [55], IS-GPS-705 [56], IS- GPS-800 [57], IS-QZSS [59])
>>URA _{oc1} Index	M		BIT STRING (3)	SV clock accuracy change index (dimensionless) (IS-GPS-200 [55], IS-GPS-705 [56], IS- GPS-800 [57], IS-QZSS [59])
>>URA _{oc2} Index	M		BIT STRING (3)	SV clock accuracy change rate index (dimensionless) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>a _{f2-n}	M		BIT STRING (10)	SV clock drift rate correction coefficient (sec/sec ²) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>a _{f1-n}	M		BIT STRING (20)	SV clock drift correction coefficient (sec/sec) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>a _{f0-n}	M		BIT STRING (26)	SV clock bias correction coefficient (seconds) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>T _{GD}	М		BIT STRING (13)	Group delay correction (seconds) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>ISC _{L1CP}	0		BIT STRING (13)	Inter signal group delay correction (seconds) (IS-GPS-800 [57], IS-QZSS [59])
>>ISC _{L1CD}	0		BIT STRING (13)	Inter signal group delay correction

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
				(seconds) (IS-GPS-800 [57], IS-QZSS [59])
>>ISC _{L1C/A}	0		BIT STRING (13)	Inter signal group delay correction (seconds) (IS-GPS-200 [55], IS-GPS-705 [56], IS-QZSS [59])
>>ISC _{L2C}	0		BIT STRING (13)	Inter signal group delay correction (seconds) (IS-GPS-200 [55], IS-GPS-705 [56], IS-QZSS [59])
>>ISC _{L5I5}	0		BIT STRING (13)	Inter signal group delay correction (seconds) (IS-GPS-705 [56], IS-QZSS [59])
>>ISC _{L5Q5}	0		BIT STRING (13)	Inter signal group delay correction (seconds) (IS-GPS-705 [56], IS-QZSS [59])
>GLONASS Satellite Clock Model				Model-4
$>\tau_{n}(t_{b})$	М		BIT STRING (22)	Satellite clock offset (seconds) [60]
$>\gamma_{n}(t_{b})$	М		BIT STRING (11)	Relative frequency offset from nominal value (dimensionless) [60]
$>\Delta au_n$	0		BIT STRING (5)	Time difference between transmission in G2 and G1 (seconds) [60]
>SBAS Satellite Clock Model				Model-5
>t ₀	М		BIT STRING (13)	(seconds) (DTFA01-96-C- 00025 [58])
>a _{Gfo}	М		BIT STRING (12)	(seconds) (DTFA01-96-C- 00025 [58])
>a _{Gf1}	М		BIT STRING (8)	(sec/sec) (DTFA01-96-C- 00025 [58])

9.2.1.105 GANSS Ionospheric Model

The IE contains fields needed to model the propagation delays of the GANSS signals through the ionosphere.

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
a _{i0}	М		BIT STRING(12)	This parameter is used as defined in OS SIS ICD [53]
a _{i1}	М		BIT STRING(12)	This parameter is used as defined in OS SIS ICD [53]
a _{i2}	М		BIT STRING(12)	This parameter is used as defined in OS SIS ICD [53]
GANSS Ionosphere Regional Storm Flags		01		
>Storm Flag 1	М		BOOLEAN	This parameter is used as defined in OS SIS ICD [53]
>Storm Flag 2	M		BOOLEAN	This parameter is used as defined in OS SIS ICD [53]
>Storm Flag 3	М		BOOLEAN	This parameter is used as defined in OS SIS ICD [53]
>Storm Flag 4	М		BOOLEAN	This parameter is used as defined in OS SIS ICD [53]
>Storm Flag 5	M		BOOLEAN	This parameter is used as defined in OS SIS ICD [53]

9.2.1.105a GANSS Additional Ionospheric Model

The IE contains fields needed to model the propagation delays of the GANSS signals through the ionosphere.

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
Data ID	М		BIT STRING(2)	Coded as defined in TS 25.331 [16]
α_0	М		BIT STRING (8)	seconds (IS-QZSS [59])
α_1	М		BIT STRING (8)	sec/semi-circle (IS-QZSS [59])
α_2	М		BIT STRING (8)	sec/(semi-circle) ² (IS-QZSS [59])
α ₃	М		BIT STRING (8)	sec/(semi-circle) ³ (IS-QZSS [59])
β_0	М		BIT STRING (8)	seconds (IS-QZSS [59])
β1	М		BIT STRING (8)	sec/semi-circle (IS-QZSS [59])
β_2	М		BIT STRING (8)	sec/(semi-circle) ² (IS-QZSS [59])
β ₃	M		BIT STRING (8)	sec/(semi-circle) ³ (IS-QZSS [59])

9.2.1.106 GANSS Navigation Model

Void.

9.2.1.107 GANSS Orbit Model

This IE contains information for GANSS orbit model parameters.

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
CHOICE Orbit Model	M			
>Keplerian Parameters				Model-1
>>t _{oe}	M		BIT STRING(14)	Time-of-Ephemeris in seconds, scale factor 60 (OS SIS ICD [53])
>>ω	М		BIT STRING(32)	Argument of Perigee (semi- circles) (OS SIS ICD [53])
>>∆n	M		BIT STRING(16)	Mean Motion Difference From Computed Value (semi- circles/sec) (OS SIS ICD [53])
>>M ₀	M		BIT STRING(32)	Mean Anomaly at Reference Time (semi-circles) (OS SIS ICD [53])
>>OMEGAdot	M		BIT STRING(24)	Longitude of Ascending Node of Orbit Plane at Weekly Epoch (semi-circles/sec) (OS SIS ICD [53])
>>e	М		BIT STRING(32)	Eccentricity, scale factor 2 ⁻³³ (OS SIS ICD [53])
>>ldot	M		BIT STRING(14)	Rate of Inclination Angle (semi-circles/sec) (OS SIS ICD [53])
>>sqrtA	M		BIT STRING(32)	Least significant bits of Semi- Major Axis in (meters) ^{1/2} , scale factor 2 ⁻¹⁹ (OS SIS ICD [53])
>>i ₀	М		BIT STRING (32)	Inclination Angle at Reference Time (semi-circles) (OS SIS ICD [53])

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
>>OMEGA ₀	М		BIT STRING(32)	Longitude of Ascending Node of Orbit Plane at Weekly Epoch (semi-circles) (OS SIS ICD [53])
>>C _{rs}	M		BIT STRING(16)	Amplitude of the Sine Harmonic Correction Term to the Orbit Radius (meters) (OS SIS ICD [53])
>>C _{is}	M		BIT STRING(16)	Amplitude of the Sine Harmonic Correction Term To The Angle Of Inclination (radians) (OS SIS ICD [53])
>>C _{us}	М		BIT STRING(16)	Amplitude of the Sine Harmonic Correction Term To The Argument Of Latitude (radians) (OS SIS ICD [53])
>>C _{rc}	M		BIT STRING(16)	Amplitude of the Cosine Harmonic Correction Term to the Orbit Radius (meters) (OS SIS ICD [53])
>>C _{ic}	M		BIT STRING(16)	Amplitude of the Cosine Harmonic Correction Term To The Angle Of Inclination (radians) (OS SIS ICD [53])
>>C _{uc}	M		BIT STRING(16)	Amplitude of the Cosine Harmonic Correction Term To The Argument Of Latitude (radians) (OS SIS ICD [53])

9.2.1.107a GANSS Additional Orbit Models

This IE contains information for GANSS orbit model parameters.

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
CHOICE Additional Orbit Models				
>NAV-Keplerian Parameters				Model-2
>>URA Index	M		BIT STRING(4)	SV accuracy (dimensionless) (IS-QZSS [59])
>>Fit Interval Flag	M		BIT STRING (1)	Fit interval indication (dimensionless) (IS-QZSS [59])
>>t _{oe}	М		BIT STRING(16)	Time of ephemeris (seconds) (IS-QZSS [59])
>>ω	М		BIT STRING (32)	Argument of perigee (semi-circles) (IS-QZSS [59])
>>∆n	M		BIT STRING (16)	Mean motion difference from computed value (semi-circles/sec) (IS-QZSS [59])
>>M ₀	M		BIT STRING (32)	Mean anomaly at reference time (semi-circles) (IS-QZSS [59])
>>OMEGAdot	M		BIT STRING (24)	Rate of right ascension (semi-circles/sec) (IS-QZSS [59])
>>e	M		BIT STRING (32)	Eccentricity (dimensionless) (IS-QZSS [59])
>>ldot	M		BIT STRING (14)	Rate of inclination angle (semi-circles/sec) (IS-QZSS [59])

IE/Group name	Presence	Range	IE Type and	Semantics description
12,0.040	1.00000	. tange	Reference	Comanico accompilon
>>sqrtA	М		BIT STRING (32)	Square root of semi-major axis (meters ^{1/2}) (IS-QZSS [59])
>>i ₀	M		BIT STRING (32)	Inclination angle at reference time (semi-circles) (IS-QZSS [59])
>>OMEGA ₀	M		BIT STRING (32)	Longitude of ascending node of orbit plane at weekly epoch (semi-circles) (IS-QZSS [59])
>>C _{rs}	М		BIT STRING (16)	Amplitude of sine harmonic correction term to the orbit radius (meters) (IS-QZSS [59])
>>C _{is}	M		BIT STRING (16)	Amplitude of sine harmonic correction term to the angle of inclination (radians) (IS-QZSS [59])
>>C _{us}	М		BIT STRING (16)	Amplitude of sine harmonic correction term to the argument of latitude (radians) (IS-QZSS [59])
>>C _{rc}	М		BIT STRING (16)	Amplitude of cosine harmonic correction term to the orbit radius (meters) (IS-QZSS [59])
>>C _{ic}	М		BIT STRING (16)	Amplitude of cosine harmonic correction term to the angle of inclination (radians) (IS-QZSS [59])
>>C _{uc}	М		BIT STRING (16)	Amplitude of cosine harmonic correction term to the argument of latitude (radians) (IS-QZSS [59])

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
>CNAV/CNAV-2 Keplerian Parameters				Model-3
>>t _{op}	M		BIT STRING (11)	Data predict time of week (seconds) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>URA _{oe} Index	M		BIT STRING (5)	SV accuracy (dimensionless) (IS-GPS-200 [55], IS-GPS-705 [56], IS- GPS-800 [57], IS-QZSS [59])
>>ΔA	M		BIT STRING (26)	Semi-major axis difference at reference time (meters) (IS-GPS-200 [55], IS- GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>A_dot	M		BIT STRING (25)	Chane rate in semi-major axis (meters/sec) (IS-GPS-200 [55], IS-GPS-705 [56], IS- GPS-800 [57], IS-QZSS [59])
>>∆n ₀	M		BIT STRING (17)	Mean motion difference from computed value at reference time (semi-circles/sec) (IS-GPS- 200 [55], IS-GPS-705 [56], IS- GPS-800 [57], IS-QZSS [59])
>>∆n ₀ _dot	М		BIT STRING (23)	Rate of mean motion difference from computed value (semi-circles/sec ²) (IS-GPS- 200 [55], IS-GPS-705 [56], IS- GPS-800 [57], IS-QZSS [59])
>>M _{0-n}	М		Bit String(33)	Mean anomaly at reference time (semi-circles) (IS-GPS-200 [55], IS-GPS-705 [56], IS- GPS-800 [57], IS-QZSS [59])
>>en	M		BIT STRING (33)	Eccentricity (dimensionless) (IS-GPS-200 [55], IS-GPS-705 [56], IS- GPS-800 [57], IS-QZSS [59])
>>\omega_n	M		Bit String(33)	Argument of perigee (semi-circles) (IS-GPS-200 [55], IS-GPS-705 [56], IS- GPS-800 [57], IS-QZSS [59])
>>Ω _{0-n}	М		BIT STRING (33)	Reference right ascension angle (semi-circles) (IS-GPS-200 [55], IS-GPS-705 [56], IS- GPS-800 [57], IS-QZSS [59])
>>ΔΩ_dot	М		BIT STRING (17)	Rate of right ascension difference (semi-circles/sec) (IS-GPS- 200 [55], IS-GPS-705 [56], IS- GPS-800 [57], IS-QZSS [59])
>>i _{o-n}	М		BIT STRING (33)	Inclination angle at reference time (semi-circles) (IS-GPS-200 [55], IS-GPS-705 [56], IS- GPS-800 [57], IS-QZSS [59])
>>I _{0-n} _dot	М		BIT STRING (15)	Rate of inclination angle (semi-circles/sec) (IS-GPS- 200 [55], IS-GPS-705 [56], IS- GPS-800 [57], IS-QZSS [59])

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
>>C _{is-n}	M		BIT STRING (16)	Amplitude of sine harmonic correction term to the angle of inclination (radians) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>C _{ic-n}	M		BIT STRING (16)	Amplitude of cosine harmonic correction term to the angle of inclination (radians) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>C _{rs-n}	M		BIT STRING (24)	Amplitude of sine harmonic correction term to the orbit radius (meters) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>C _{rc-n}	M		BIT STRING (24)	Amplitude of cosine harmonic correction term to the orbit radius (meters) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>C _{us-n}	M		BIT STRING (21)	Amplitude of sine harmonic correction term to the argument of latitude (radians) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>C _{uc-n}	М		BIT STRING (21)	Amplitude of cosine harmonic correction term to the argument of latitude (radians) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>GLONASS Earth-Centered, Earth-fixed Parameters				Model-4
>>E _n	M		BIT STRING (5)	Age of data (days) [60]
>>P1	M		BIT STRING (2)	Time interval between two adjacent values of t₀ (minutes) [60]
>>P2	М		BIT STRING (1)	Change of t _b flag (dimensionless) [60]
>>M	0		BIT STRING (2)	Type of satellite (dimensionless) [60]
$\Rightarrow x_n(t_b)$	М		BIT STRING (27)	x-coordinate of satellite at time t _b (kilometers) [60]
$\Rightarrow \dot{x}_n(t_b)$	М		BIT STRING (24)	x-coordinate of satellite velocity at time t _b (kilometers/sec) [60]
$\Rightarrow \ddot{x}_n(t_b)$	М		BIT STRING (5)	x-coordinate of satellite acceleration at time t _b (kilometers/sec ²) [60]
$\Rightarrow y_n(t_b)$	М		BIT STRING (27)	y-coordinate of satellite at time t _b (kilometers) [60]
$\Rightarrow \dot{y}_n(t_b)$	М		BIT STRING (24)	y-coordinate of satellite velocity at time t _b (kilometers/sec) [60]
$\Rightarrow \ddot{y}_n(t_b)$	М		BIT STRING (5)	y-coordinate of satellite acceleration at time t _b (kilometers/sec ²) [60]

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
$\Rightarrow z_n(t_b)$	M		BIT STRING (27)	z-coordinate of satellite at time t _b (kilometers) [60]
$\Rightarrow \dot{z}_n(t_b)$	М		BIT STRING (24)	z-coordinate of satellite velocity at time t _b (kilometers/sec) [60]
$\Rightarrow \ddot{z}_n(t_b)$	M		BIT STRING (5)	z-coordinate of satellite acceleration at time t _b (kilometers/sec ²) [60]
>SBAS Earth-Centered, Earth- fixed Parameters				Model-5
>>t ₀	C-ClockMo del		BIT STRING (13)	Time of applicability (seconds) (DTFA01-96-C- 00025 [58])
>>Accuracy	М		BIT STRING (4)	(dimensionless) (DTFA01-96- C-00025 [58])
>>X _G	М		BIT STRING (30)	(meters) (DTFA01-96-C-00025 [58])
>>Y _G	М		BIT STRING (30)	(meters) (DTFA01-96-C-00025 [58])
>>Z _G	М		BIT STRING (25)	(meters) (DTFA01-96-C-00025 [58])
>>X _G Rate-of-Change	М		BIT STRING (17)	(meters/sec) (DTFA01-96-C- 00025 [58])
>>Y _G Rate-of-Change	М		BIT STRING (17)	(meters/sec) (DTFA01-96-C- 00025 [58])
>>Z _G Rate-of-Change	М		BIT STRING (18)	(meters/sec) (DTFA01-96-C- 00025 [58])
>>X _G Acceleration	М		BIT STRING (10)	(meters/sec ²) (DTFA01-96-C- 00025 [58])
>>Y _G Acceleration	М		BIT STRING (10)	meters/sec ²) (DTFA01-96-C- 00025 [58])
>>Z _G Acceleration	М		BIT STRING (10)	meters/sec ²) (DTFA01-96-C- 00025 [58])

Condition	Explanation		
ClockModel	This IE shall be present if "SBAS Earth-Centered,		
	Earth-fixed Parameters" (Model-5) in IE GANSS		
	Additional Clock Models is not included in GANSS		
	Additional Navigation Models IE.		

9.2.1.108 GANSS Real Time Integrity

This IE contains parameters that describe the real-time status of the GANSS constellation.

IE/Group name	Presence	Range	IE Type and	Semantics description
			Reference	
Satellite Information		1 to		
		<maxgan< td=""><td></td><td></td></maxgan<>		
		SSSat>		
>Bad GANSS Sat ID	M		INTEGER(0.	Defined in TS 25.331 [16].
			.63)	
>Bad GANSS Signal ID	0		BIT	Coded as defined in TS
_			STRING(8)	25.331 [16].

Range Bound	Explanation
maxGANSSSat	Maximum number of satellites for which data is included in the IE

9.2.1.109 GANSS Receiver Geographical Position (GANSS RX Pos)

The GANSS Receiver Geographical Position IE is used to identify the geographical coordinates of a GANSS receiver relevant for a certain Information Exchange Object.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Latitude Sign	М		ENUMERATED (North, South)	
Degrees of Latitude	M		INTEGER (02 ³¹ -1)	The IE value (N) is derived by this formula: N≤2 ³¹ X /90 < N+1 X being the latitude in degree (0° 90°)
Degrees of Longitude	M		INTEGER (-2 ³¹ 2 ³¹ -1)	The IE value (N) is derived by this formula: N≤2 ³² X /360 < N+1 X being the longitude in degree (-180°+180°)
Direction of Altitude	M		ENUMERATED (Height, Depth)	
Altitude	M		INTEGER (02 ¹⁵ -1)	The relation between the value (N) and the altitude (a) in meters it describes is $N \le a < N+1$, except for $N=2^{15}-1$ for which the range is extended to include all greater values of (a).

9.2.1.110 GANSS Time Model

The $GANSS\ Time\ Model\ IE$ contains a set of parameters needed to relate GANSS time to selected time reference indicated by GNSS_TO_ID.

IE/Group name	Presence	Range	IE Type and Reference	Semantics description	Criticality	Assigned Criticality
GANSS Time Model Reference Time	M		INTEGER(0377 99)	GANSS reference time (modulo 1 week) in seconds. The scale factor is 2 ⁴	-	
T _{A0}	M		INTEGER(- 214748364821 47483647)	Seconds, scale factor 2 ⁻	-	
T _{A1}	0		INTEGER (- 838860883886 07)	sec/sec, scale factor 2 ⁻⁵¹	-	
T _{A2}	0		INTEGER (- 6463)	sec/sec ² , scale factor 2 ⁻	_	
GNSS_TO_ID	M		ENUMERATED(GPS,, Galileo, QZSS, GLONASS)		-	
Week Number	0		INTEGER(0819 1)	Reference week of GANSS Time Model	-	
Delta_T	0		INTEGER (- 128127)	This field specifies the integer seconds of the GNSS-GNSS Time Offset. Scale factor 1 second.	YES	ignore

9.2.1.110a GANSS Additional Time Models

The GANSS Additional Time Models IE contains a set of parameters needed to relate GANSS time to selected time references.

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
GNSS-GNSS Time Model		1 <maxga NSS-1></maxga 		
>GANSS Time Model			9.2.1.110	

Range Bound	Explanation
maxGANSS-1	Maximum number of GANSS systems for which data is included in this IE.

9.2.1.111 GANSS UTC Model

The *GANSS UTC Model* IE contains a set of parameters needed to relate GANSS time to Universal Time Coordinate (UTC).

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
A ₁	М		BIT STRING(24)	sec/sec (OS SIS ICD [53])
A ₀	М		BIT STRING(32)	seconds (OS SIS ICD [53])
tot	М		BIT STRING(8)	seconds (OS SIS ICD [53])
WNt	М		BIT STRING(8)	weeks (OS SIS ICD [53])
Δt_{LS}	М		BIT STRING(8)	seconds (OS SIS ICD [53])
WN _{LSF}	М		BIT STRING(8)	weeks (OS SIS ICD [53])
DN	М		BIT STRING(8)	days (OS SIS ICD [53])
Δt_{LSF}	M		BIT STRING(8)	seconds (OS SIS ICD [53])

9.2.1.111a GANSS Additional UTC Models

The *GANSS Additional UTC Models* IE contains several sets of parameters needed to relate GANSS time to Universal Time Coordinate (UTC), as defined in IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], DTFA01-96-C-00025 [58], IS-QZSS [59], [60].

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
CHOICE Additional UTC Models				
>Model Set 1			DIT	D: (5: 1 (O) 100 (:
>>A _{0-n}	M		BIT STRING(16)	Bias coefficient of GNSS time scale relative to UTC time scale (seconds) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>A _{1-n}	M		BIT STRING (13)	Drift coefficient of GNSS time scale relative to UTC time scale (sec/sec) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>A _{2-n}	М		BIT STRING (7)	Drift rate correction coefficient of GNSS time scale relative to UTC time scale (sec/sec ²) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>∆t∟s	М		BIT STRING (8)	Current or past leap second count (seconds) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>t _{ot}	M		BIT STRING (16)	Time data reference time of week (seconds) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>WN _{ot}	М		BIT STRING (13)	Time data reference week number (weeks) (IS-GPS-200 [55], IS- GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>WN _{LSF}	М		BIT STRING (8)	Leap second reference week number (weeks) (IS-GPS-200 [55], IS- GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>DN	М		BIT STRING (4)	Leap second reference day number (days) (IS-GPS-200 [55], IS- GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>>∆t _{LSF}	М		BIT STRING (8)	Current or future leap second count (seconds) (IS-GPS-200 [55], IS-GPS-705 [56], IS-GPS-800 [57], IS-QZSS [59])
>Model Set 2				
>>N ^A	M		BIT STRING (11)	Callendar day number within four-year period beginning since the leap year (days) [60]
>>tc	М		BIT STRING (32)	GLONASS time scale correction to UTC(SU) (seconds) [60]
>>Delta UT1	0		DIT OTONIC	0 (" :
>>>B1	М		BIT STRING (11)	Coefficient to determine ∆UT1 (seconds) [60]
>>>B2	М		BIT STRING (10)	Coefficient to determine ΔUT1 (seconds/msd) [60]
>>KP	0		BIT STRING (2)	Notification of expected leap second correction

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
				(dimensionless) [60]
>Model Set 3				
>>A _{1WNT}	M		BIT STRING (24)	sec/sec (DTFA01-96-C-00025 [58], Message Type 12)
>>A _{0WNT}	М		BIT STRING (32)	seconds (DTFA01-96-C-00025 [58], Message Type 12)
>>t _{ot}	М		BIT STRING (8)	seconds (DTFA01-96-C-00025 [58], Message Type 12)
>>WN _t	М		BIT STRING (8)	weeks (DTFA01-96-C-00025 [58], Message Type 12)
>>∆t∟s	M		BIT STRING (8)	seconds (DTFA01-96-C-00025 [58], Message Type 12)
>>WN _{LSF}	М		BIT STRING (8)	weeks (DTFA01-96-C-00025 [58], Message Type 12)
>>DN	M		BIT STRING (8)	days (DTFA01-96-C-00025 [58], Message Type 12)
>>∆t _{LSF}	М		BIT STRING (8)	seconds (DTFA01-96-C-00025 [58], Message Type 12)
>>UTC Standard ID	M		BIT STRING (3)	dimensionless Coded as defined in TS 25.331 [16]

9.2.1.112 T_{UTRAN-GANSS} Accuracy Class

The $T_{UTRAN-GANSS}$ Accuracy Class IE indicates the accuracy class of the UTRAN GANSS Timing of Cell Frames for UE Positioning measurement.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
T _{UTRAN-GANSS} Accuracy Class			ENUMERAT ED (Accuracy Class A, Accuracy Class B, Accuracy Class C,)	More information about Measurement Accuracy Class is included in TS 25.133 [23].

9.2.1.113 T_{UTRAN-GANSS} Measurement Threshold Information

The $T_{UTRAN-GANSS}$ Measurement Threshold Information IE defines the related thresholds for UTRAN GANSS Timing of Cell Frames for UE Positioning measurements shall trigger the Event On Modification.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
T _{UTRAN-GANSS} Change Limit	0		INTEGER(1256)	Change of T _{UTRAN-GANSS} value compared to previously reported value, which shall trigger a new report. Unit in 1/16 chip.
Predicted Tutran-ganss Deviation Limit	0		INTEGER(1256)	Deviation of the Predicted T _{UTRAN-GANSS} from the latest measurement result, which shall trigger a new report. Unit in 1/16 chip.

9.2.1.114 T_{UTRAN-GANSS} Measurement Value Information

The $T_{UTRAN-GANSS}$ Measurement Value Information IE indicates the measurement results related to the UTRAN GANSS Timing of Cell Frames for UE Positioning measurements.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Tutran-ganss	M			Indicates the UTRAN GANSS Timing of Cell Frames for UE Positioning. According to mapping in TS 25.133 [23] and TS 25.123 [24]; significant values range from 0 to 371589119999 99.	-	
>MS	М		INTEGER(016383)	Most Significant Part	_	
>LS	M		INTEGER(0 42949672 95)	Least Significant Part	_	
Tutran-ganss Quality	0		INTEGER(0 255)	Indicates the standard deviation (std) of the T_{UTRAN} -GANSS measurements in 1/16 chip. T_{UTRAN} -GANSS Quality = $\sqrt{E[(x-\mu)^2]}$ = std of reported T_{UTRAN} -GANSS Value, where x is the reported T_{UTRAN} -GANSS Value and $\mu = E[x]$ is the expectation value of x.	-	
T _{UTRAN-GANSS} Drift Rate	M		INTEGER(- 5050)	Indicates the Tutran-Ganss drift rate in 1/256 chip per second. A positive value indicates that the UTRAN clock is running at a lower frequency than GANSS clock.	-	
Tutran-ganss Drift Rate Quality	0		INTEGER(050)	Indicates the standard deviation (std) of the Tutran-Ganss drift rate measurements in 1/256 chip per second. Tutran-Ganss Drift Rate Quality = √E[(x-µ)²] = std of reported Tutran-Ganss Drift Rate, where x is the	_	

			reported $T_{UTRAN-GANSS}$ Drift Rate and $\mu = E[x]$ is the expectation value of x.		
GANSS Time ID	0	9.2.1.119a	Absence of this IE means Galileo system time.	YES	ignore

9.2.1.115 GANSS Reference Time

Void.

9.2.1.116 HARQ Memory Partitioning

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
CHOICE HARQ Memory Partitioning		1			_	
>Implicit					_	
>>Number of Processes	M		INTEGER (18,12,1 4,16)	For HARQ process IDs going from 0 to "Number of Processes" – 1 the Total number of soft channel bits (TS 25.306 [42]) is partitioned equally between all HARQ processes according to the rules in TS 25.331 [16].	_	
>Explicit					1	
>>HARQ Memory Partitioning I		1 <maxno ofHARQpr ocesses></maxno 		The first instance of the parameter corresponds to HARQ process with identifier 0, the second instance to HARQ process with identifier 1, and so on.	_	
>>>Process Memory Size	М		9.2.1.49D	See TS 25.331 [16]	_	
>>HARQ Memory Partitioning Information Extension For MIMO		0, 4, 6 or 8		FDD and 1.28Mcps TDD only The 1 st instance corresponds to HARQ process with identifier set to "maxnoofHARQp rocesses", the 2 nd instance to HARQ process with identifier set to "maxnoofHARQp rocesses", and instance to HARQ process with identifier set to "maxnoofHARQp rocesses+1", and so on.	GLOBAL	ignore
>>>Process Memory Size	М		9.2.1.49D	See TS 25.331 [16]	-	

Range Bound	Explanation
MaxnoofHARQprocesses	Maximum number of HARQ processes for one UE [FDD – per stream
	(the maximum number of HARQ processes per UE is 2 *
	MaxnoofHARQprocesses in dual stream transmission mode)]

9.2.1.117 Multiple PLMN List

This information element contains a list of PLMN identities, which identifies the broadcasted PLMN Identities in MOCN and GWCN shared network configurations. The mandatory PLMN Identity in the MIB (called common PLMN in TS 23.251 [54]) is the first PLMN.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
PLMN Identity	M		OCTET STRING (SIZE (3))	- digits 0 to 9, two digits per octet, - each digit encoded 0000 to 1001, - 1111 used as filler - bit 4 to 1 of octet n encoding digit 2n-1 - bit 8 to 5 of octet n encoding digit 2n -The PLMN identity consists of 3 digits from MCC followed by either
				-a filler plus 2 digits from MNC (in case of 2 digit MNC) or -3 digits from MNC (in case of a 3 digit MNC).
List of PLMNs		0 <maxnrofbroadc astPLMNs></maxnrofbroadc 		
>PLMN Identity	М		OCTET STRING (SIZE (3))	- digits 0 to 9, two digits per octet, - each digit encoded 0000 to 1001, - 1111 used as filler - bit 4 to 1 of octet n encoding digit 2n-1 - bit 8 to 5 of octet n encoding digit 2n -The PLMN identity consists of 3 digits from MCC followed by
				either -a filler plus 2 digits from MNC (in case of 2 digit MNC) or -3 digits from MNC (in case of a 3 digit MNC).

Range bound	Explanation
maxNrOfBroadcastPLMNs	Maximum number of additional PLMN identitys that can be
	broadcasted in a cell involved in a MOCN or GWCN Shared
	Network configuration. The value for maxNrOfBroadcastPLMNs is 5.

9.2.1.118 GANSS Data Bit Assistance

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
GANSS TOD	M		INTEGER(059,)	Reference time (modulo 1 minute) of the first bit of the data in <i>Data Bits</i> IE, in seconds.
Data Bit Assistance		1 <maxgans< td=""><td></td><td></td></maxgans<>		
List		SSat>		
>Sat ID	M		INTEGER(063)	Defined in TS 25.331 [16].
>Data Bit Assistance		1 <maxsgnty< td=""><td></td><td></td></maxsgnty<>		
Sgn List		pe>		
>>GANSS Signal ID	M		9.2.1.121	
>>Data Bits	М		BIT STRING(11024)	Raw data bits as transmitted from a specific satellite at the time indicated by GANSS_TOD. See TS 25.331 [16].

Range Bound	Explanation
maxGANSSSat	Maximum number of satellites for which data is included in the IE
maxSgnType	Maximum number of GANSS signals included in the IE

9.2.1.119 GANSS ID

This IE defines a particular GANSS.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
GANSS ID	М		INTEGER(07	Defines the GANSS and is
			,)	coded as defined in TS
				25.331 [16].

9.2.1.119a GANSS Time ID

This IE defines a particular GANSS system time.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
GANSS Time ID	M		INTEGER(07 ,)	Defines the GANSS system time for the UTRAN GANSS Timing of Cell Frames for UE Positioning. Coded as defined in TS 25.331 [16], subclause 10.3.7.93a.

9.2.1.120 GANSS Navigation Model And Time Recovery

This IE contain information required to manage the transfer of precise navigation data to the GANSS-capable UE.

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
GANSS Transmission Time	M		9.2.1.122	GANSS Time when the Navigation model has been retrieved
Non-Broadcast Indication	0		ENUMERAT ED(true)	If this IE is present, GANSS navigation model is not derived from satellite broadcast. See NOTE 1
Satellite Information		1 to <maxgan SSSat></maxgan 		
>Sat ID	M		INTEGER(063)	Defined in TS 25.331 [16].
>SV Health	M		BIT STRING(5)	Coded as defined in OS SIS ICD [53]
>IOD	M		BIT STRING(10)	
>GANSS Clock Model	М		9.2.1.104	
>GANSS Orbit Model	M		9.2.1.107	

NOTE 1: The Non-Broadcast Indication allows to inform that the navigation model is not bit-to-bit the one broadcast by the satellite. If it is set to 1, the UE is informed that techniques such as data wiping off applied to the navigation model may not work for instance.

Condition	Explanation		
Orbit model	The IE shall be present if the GANSS Orbit Model IE		
	indicates "Keplerian Parameters".		

Range bound	Explanation		
maxGANSSSat	Maximum number of satellites for which data is included in the IE.		

9.2.1.120a GANSS Additional Navigation Models And Time Recovery

This IE contain information required to manage the transfer of precise navigation data to the GANSS-capable UE.

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
GANSS Transmission Time	M		9.2.1.122	GANSS Time when the Navigation model has been retrieved
Non-Broadcast Indication	0		ENUMERAT ED(true)	If this IE is present, GANSS navigation model is not derived from satellite broadcast. See NOTE 1 in 9.2.1.120.
Satellite Information		1 <maxga NSSSat></maxga 		
>Sat ID	M		INTEGER(063)	Defined in TS 25.331 [16].
>SV Health	M		BIT STRING(6)	Coded as defined in TS 25.331 [16].
>IOD	M		BIT STRING(11)	Coded as defined in TS 25.331 [16].
>GANSS Additional Clock Models	M		GANSS I Clock Models 9.2.1.104a	
>GANSS Additional Orbit Models	M		GANSS Additional Orbit Models 9.2.1.107a	

Range bound	Explanation
maxGANSSSat	Maximum number of satellites for which data is included in this IE.
	The value of maxGANSSSat is 64

9.2.1.121 GANSS Signal ID

This IE defines a specific signal within a particular GANSS.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
GANSS Signal ID	M		INTEGER(07,)	Coded as defined in TS 25.331 [16].

9.2.1.122 GANSS Transmission Time

This IE indicates the GANSS Transmission Time.

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
GANSS Day	0		INTEGER(0 8191)	The sequential number of days from the origin of the GNSS system time (indicated by the GANSS_ID given in the Requested Data Value IE) modulo 8192 days (about 22 years).
GANSS TOD	М		INTEGER(0 86399)	GANSS Time of Day in seconds

9.2.1.122a GANSS Earth Orientation Parameters

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
t _{EOP}	М		BIT STRING(16)	EOP data reference time (seconds) (IS-GPS-200 [55])
PM_X	M		BIT STRING (21)	X-axis polar motion value at reference time (arc-seconds) (IS-GPS-200 [55])
PM_X_dot	М		BIT STRING (15)	X-axis polar motion drift at reference time (arc-seconds/day) (IS-GPS-200 [55])
PM_Y	М		BIT STRING (21)	Y-axis polar motion value at reference time (arc-seconds) (IS-GPS-200 [55])
PM_Y_dot	М		BIT STRING (15)	Y-axis polar motion drift at reference time (arc-seconds/day) (IS-GPS- 200 [55])
ΔUT1	М		BIT STRING (31)	UT1-UTC difference at reference time (seconds) (IS-GPS-200 [55])
ΔUT1_dot	М		BIT STRING (19)	Rate of UT1-UTC difference at reference time (seconds/day) (IS-GPS-200 [55])

9.2.1.122b SBAS ID

This IE defines a specific SBAS.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
SBAS ID	M		ENUMERATED(WAAS, EGNOS, MSAS, GAGAN,)	

9.2.1.122c GANSS Auxiliary Information

IE/Group name	Presence	Range	IE Type and	Semantics description
			Reference	

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
CHOICE GANSS-ID				
>GANSS-ID-1				This choice may only be present if GANSS ID indicated "Modernized GPS"
>>Aux Info List		1 <maxgan SSSat></maxgan 		
>>>Sat ID	M		INTEGER(063)	Defined in TS 25.331 [16].
>>>Signals Available	M		BIT STRING(8)	Coded as defined in TS 25.331 [16].
>GANSS-ID-3				This choice may be present if GANSS ID indicated "GLONASS"
>>Aux Info List		1 <maxgan SSSat></maxgan 		
>>>Sat ID	M		INTEGER(063)	Defined in TS 25.331 [16].
>>>Signals Available	M		BIT STRING(8)	Coded as defined in TS 25.331 [16].
>>>Channel Number	M		INTEGER (-713)	This field indicates the GLONASS carrier frequency number of the satellite identified by <i>Sat ID</i> , as defined in [60].

Range Bound	Explanation
maxGANSSSat	Maximum number of GANSS satellites for which data is included in this IE.

9.2.1.122d Additional Ionospheric Model Request

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Additional Ionospheric Model Request	M		BIT STRING(2)	Data ID for GANSS Additional lonospheric Model as defined in TS 25.331 [16], subclause 10.3.7.92b.

9.2.1.122e Earth Orientation Parameters Request

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Earth Orientation	M		BOOLEAN	True means requested.
Parameters Request				

9.2.1.122f GANSS Additional Navigation Models And Time Recovery Request

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
GANSS Additional Navigation Models And Time Recovery Request	M		BOOLEAN	True means requested.

9.2.1.122g GANSS Additional UTC Models Request

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
GANSS Additional UTC Models Request	M		BOOLEAN	True means requested.

9.2.1.122h GANSS Auxiliary Information Request

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
GANSS Auxiliary Information	М		BOOLEAN	True means requested.
Request				

9.2.1.123 SixtyfourQAM DL Support Indicator

The SixtyfourQAM DL Support Indicator indicates whether the particular cell is capable to support Sixtyfour QAM in DL or not.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
SixtyfourQAM DL Support			ENUMERAT	
Indicator			ED	
			(SixtyfourQA	
			M DĽ	
			Supported,	
			SixtyfourQA	
			M DL Not	
			Supported)	

9.2.1.124 RANAP Enhanced Relocation Information Request

This parameter is transparent to the RNSAP. The parameter contains information for the Enhanced Relocation procedure as defined in TS 25.413 [2].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
RANAP Enhanced Relocation			BIT STRING	The content is defined in TS
Information Request				25.413 [2].

9.2.1.125 RANAP Enhanced Relocation Information Response

This parameter is transparent to the RNSAP. The parameter contains information for the Enhanced Relocation procedure as defined in TS 25.413 [2].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
RANAP Enhanced Relocation Information Response			BIT STRING	The content is defined in TS 25.413 [2].

9.2.1.126 Released CN Domain

The parameter indicates the CD Domain(s) which the RNC shall release the related resource for.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Released CN Domain	M			
>PS Domain			NULL	
>CS Domain			NULL	
>PS and CS Domain			NULL	

9.2.1.127 Secondary CCPCH system information MBMS

The parameter contains information for the Secondary CCPCH system information MBMS as defined in TS 25.331 [16].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Secondary CCPCH system information MBMS			BIT STRING	The content is defined in TS 25.331 [16].

9.2.1.128 MBSFN Cluster Identity

The parameter is the identifier of a MBSFN cluster in one PLMN.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
MBSFN Cluster Identity			INTEGER (065535)	the identifier of a MBSFN cluster in one PLMN

9.2.1.129 MBSFN Scheduling Transmission Time Interval

The parameter is the identifier of an MBSFN Scheduling Transmission Time Interval.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
MBSFN Scheduling			INTEGER	Number of TTIs
Transmission Time Interval			(4,8,16,32,	
			64,128,256)	

9.2.1.130 MAC-ehs Reset Timer

The MAC-ehs Reset Timer IE is used as Reset Timer(Treset) described in TS 25.321 [41] subclause 11.6.4.5.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
MAC-ehs Reset Timer			ENUMERAT ED (1, 2, 3, 4,)	Timer in multiples of T1 values (milliseconds). Used when MAC-ehs reordering queue is reset in CELL_FACH and CELL_PCH

9.2.1.131 Enhanced FACH Support Indicator

This IE indicates the Enhanced FACH Support. [1.28Mcps TDD – This IE indicates the Enhanced FACH Support in both downlink and uplink.]

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Enhanced FACH Support Indicator			NULL	

9.2.1.132 Enhanced PCH Capability

This IE indicates the UE is capable of Enhanced PCH or not.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
- · · · · · · · · · · · · · · · · · · ·				
Enhanced PCH Capability			ENUMERAT	
			ED	
			(Enhanced	
			PCH	
			Capable,	
			Enhanced	
			PCH Not	
			Capable)	

9.2.1.133 Priority Queue Information for Enhanced FACH/PCH

The *Priority Queue Information for Enhanced FACH/PCH* IE provides information associated to HSDPA Priority Queue used for Enhanced FACH and/or Enhanced PCH.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Priority Queue Information		1 <maxnoo fPrioQueue</maxnoo 		
		S>		
>Priority Queue ID	M		9.2.1.45A	
>Scheduling Priority Indicator	M		9.2.1.51A	
>T1	M		9.2.1.54A	
>MAC-ehs Reset Timer	M		9.2.1.130	
>Discard Timer	0		9.2.1.19C	
>MAC-hs Window Size	M		9.2.1.34C	
>Maximum MAC-d PDU Size	M		MAC PDU	
			Size	
			Extended	
			9.2.1.34D	

Range Bound	Explanation
maxnoofPrioQueues	Maximum number of Priority Queues

9.2.1.134 MIMO Activation Indicator

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
MIMO Activation Indicator	M		NULL	

9.2.1.135 MIMO Mode Indicator

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
MIMO Mode Indicator			ENUMERATED	
			(Activate,	
			Deactivate)	

9.2.1.136 DL RLC PDU Size Format

The DL RLC PDU Size Format IE indicates the downlink RLC PDU size format used for a Priority Queue.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DL RLC PDU Size Format			ENUMERATED (
			Fixed RLC PDU	
			size, Flexible RLC	
			PDU size ,)	

9.2.1.137 UE Aggregate Maximum Bit Rate

The *UE Aggregate Maximum Bitrate* IE is applicable for all Non-GBR bearers per UE which is defined for the Downlink and the Uplink direction and provided by the CN to the RNC. At least one of the *UE Aggregate Maximum Bit Rate Downlink* IE and *UE Aggregate Maximum Bit Rate Uplink* IE shall be included in the *UE Aggregate Maximum Bit Rate* IE.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
UE Aggregate Maximum Bit Rate				Desc: Applicable for non-GBR bearers
>UE Aggregate Maximum Bit Rate Downlink	0		INTEGER (11,000,00 0,000)	Desc.: This IE indicates the aggregated maximum number of bits delivered by UTRAN and to UTRAN in DL within a period of time, divided by the duration of the period for all non-GBR bearers in one UE. The MBR of non-GBR bearers shall be ignored if this IE present.
>UE Aggregate Maximum Bit Rate Uplink	0		INTEGER (11,000,00 0,000)	Desc.: This IE indicates the aggregated maximum number of bits delivered by UTRAN and to UTRAN in UL within a period of time, divided by the duration of the period for all non-GBR bearers in one UE. The MBR of non-GBR bearers shall be ignored if this IE present.

9.2.1.138 DGNSS Validity Period

This IE defines the validity period of the GNSS differential corrections provided in *DGPS corrections* and *DGANSS corrections* IEs.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UDRE Growth Rate	М		Enumerated(UDRE growth 1.5, UDRE growth 2, UDRE growth 4, UDRE growth 6, UDRE growth 8, UDRE growth 10, UDRE growth 12, UDRE growth 16)	This field provides an estimate of the growth rate of uncertainty (1-σ) in the corrections. The UDRE at time value specified in the <i>Time of Validity for UDRE Growth Rate field</i> is the value of this field times the value of UDRE provided in <i>DGPS Corrections</i> or <i>DGANSS corrections</i> IE (TS 25.331 [16]).
Time of Validity for UDRE Growth Rate	M		Enumerated(val20sec, val40sec, val80sec, val160sec, val320sec, val640sec, val1280sec, val2560sec)	This field specifies the time when the <i>UDRE Growth Rate</i> field applies (TS 25.331 [16]).

9.2.1.139 MDT Configuration

The IE defines the MDT function parameters.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
MDT Activation	М		ENUMERATED(MDT Only, MDT and Trace,)	
CHOICE MDT Area Scope	М		11aoc,)	
>Cell based	101			
>>Cell ID List		1 to		
77 30 12 2.00		<maxnoofce< td=""><td></td><td></td></maxnoofce<>		
		IIID>		
>>>Cell-ID	М	INTEGER (02684354 55)		This information element identifies a cell uniquely within UTRAN and consists of RNC-ID and C-ID as defined in TS 25.401 [40].
>LA Based				
>>LAI List		1 to <maxnoofla Is></maxnoofla 		
>>>LAI	М			
>>>PLMN Identity	M		OCTET STRING (3)	- digits 0 to 9, two digits per octet, - each digit encoded 0000 to 1001, - 1111 used as filler - bit 4 to 1 of octet n encoding digit 2n-1 - bit 8 to 5 of octet n encoding digit 2n -The PLMN Identity consists of 3 digits from MCC followed by either -a filler plus 2 digits from MNC (in case of 2 digit MNC) or -3 digits from MNC (in case of a 3 digit MNC).
>>>LAC	М		OCTET STRING (2)	0000 and FFFE not allowed
>RA Based				
>>RAI List		0 to <maxnoofra Is></maxnoofra 		
>>>RAI				This element identifies an area in which the MDT Configuration applies.
>>>PLMN Identity	M		OCTET STRING (3)	- digits 0 to 9, two digits per octet, - each digit encoded 0000 to 1001, - 1111 used as filler - bit 4 to 1 of octet n encoding digit 2n-1 - bit 8 to 5 of octet n encoding digit 2n -The PLMN Identity consists of 3 digits from MCC followed by either -a filler plus 2 digits from MNC (in case of 2 digit MNC) or -3 digits from MNC (in case of a 3 digit MNC).
>>>LAC	M		OCTET STRING (2)	0000 and FFFE not allowed
>>>RAC	M		OCTET STRING (1)	
>PLMN Area Based			NULL	

M1 Report	0	9.2.2.128	M1: FDD only CPICH RSCP and CPICH Ec/No measurement by UE. This information element shall not be sent, ignored if received.
M2 Report	0	9.2.3.83	M2: P-CCPCH RSCP and Timeslot ISCP for UTRA 1.28 TDD. This information element shall not be sent, ignored if received.
M3 Report	0	NULL	

Range bound	Explanation
maxnoofCellID	Maximum no. of Cell ID subject for MDT scope. Value is 32.
maxnoofLAIs	Maximum no. of LAI subject for MDT scope. Value is 8.
maxnoofRAIs	Maximum no of RAI subject for MDT scope. Value is 8.

9.2.1.140 MDT Report parameters

This IE defines the report parameters for MDT periodic reports. This IE is not used by the DRNS.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
MDT Report Parameters				
>Report interval	М		ENUMERATED (ms250, ms500, ms1000, ms2000, ms3000, ms4000, ms6000, ms12000, ms16000, ms20000, ms24000, ms32000, ms64000,)	This IE is defined in TS25.331[10]
>Report amount	M		ENUMERATED (1, 2, 4, 8, 16, 32, 64, infinity,)	

9.2.1.141 Neighbouring UMTS Cell Information Extension

The Neighbouring UMTS Cell Information Extension IE is an extension IE to the Neighbouring UMTS Cell Information IE and indicates the UMTS neighbouring cells in the same way as in the Neighbouring UMTS Cell Information IE. The DRNC may use the Neighbouring UMTS Cell Information Extension IE to indicate remaining UMTS neighbouring cells if the number of neighbouring RNCs exceeds the predefined maximum number of neighbouring RNCs (maxnoofneighbouringRNCs).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Neighbouring UMTS Cell Information Extension		1 <maxno ofextended neighbouri ngRNCs></maxno 		
>RNC-ID	M		9.2.1.50	If the Extended RNC-ID IE is included in the Neighbouring UMTS Cell Information IE, the RNC-ID IE shall be ignored.
>CN PS Domain Identifier	0		9.2.1.12	
>CN CS Domain Identifier	0		9.2.1.11	
>Neighbouring FDD Cell Information	0		9.2.1.41B	
>Neighbouring TDD Cell Information	0		9.2.1.41D	
>Neighbouring TDD Cell Information LCR	0		9.2.1.72	
>Extended RNC-ID	0		9.2.1.50a	The Extended RNC-ID IE shall be used if the RNC identity has a value larger than 4095.

Range bound	Explanation
maxnoofextendedneighbouringRNCs	Maximum number of extended neighbouring RNCs.

9.2.1.142 Source ID

The Source ID IE identifies the source for the relocation of SRNS. The Source ID shall be the SAI of the relocation source.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
SAI	М		9.2.1.52	

9.2.1.143 Target ID

The *Target ID* IE identifies the target for the relocation of SRNS. The target ID shall be the Cell Global ID of the relocation target.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
CGI	M		9.2.1.5D	

9.2.1.144 MS Classmark 2

The coding of this element is described in TS 24.008 [66].

IE/Group Name	Presence	Range	IE type and reference	Semantics description
MS Classmark 2	M		OCTET STRING	Coded same way as the Mobile Station Classmark 2 IE defined in TS 24.008 [66]

9.2.1.145 MS Classmark 3

The coding of this element is described in TS 24.008 [66].

IE/Group Name	Presence	Range	IE type and reference	Semantics description
MS Classmark 3	M		OCTET STRING	Coded same way as the Mobile Station Classmark 3 IE defined in TS 24.008 [66].

9.2.1.146 Speech Version

The Speech Version IE identifies the speech version supported.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
Speech Version	М		BIT STRING (4)	The coding of this IE is described in TS 24.008 [66].

9.2.1.147 Controlled Object Scope

Controlled Object Scope IE indicates the scope of objects which the control of information transfer shall be performed.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
RNC-ID	M		9.2.1.50	If the Extended RNC-ID IE is
				included, the RNC-ID IE shall be
				ignored.
Extended RNC-ID	0		9.2.1.50a	The Extended RNC-ID IE shall be
				used if the RNC identity has a
				value larger than 4095
Multiple PLMN List	0		9.2.1.1	_
UMTS Cell Information	0	0 <maxnoofc< td=""><td></td><td></td></maxnoofc<>		
		ells>		
>C-ID	M		9.2.1.6	

Range bound	Explanation
maxnoofCells	Maximum number of cells that can be indicated in the
	corresponding IE.

9.2.1.148 ANR Report Indication

ANR Report Indication IE contains information about neighbour cells detected by the ANR function in UE and sent to the initiating RNC (RNC₁) over Uu.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
PLMN Identity	M		OCTET STRING (3)	The registed PLMN of UE when the ANR result was logged digits 0 to 9, two digits per octet, - each digit encoded 0000 to 1001, - 1111 used as filler - bit 4 to 1 of octet n encoding digit 2n-1 - bit 8 to 5 of octet n encoding digit 2n -The PLMN Identity consists of 3 digits from MCC followed by either -a filler plus 2 digits from MNC (in case of 2 digit MNC) or -3 digits from MNC (in case of a 3 digit MNC).
L3 Information	М		9.2.1.32	The IE Contains UE INFORMATION RESPONSE defined in ref. TS 25.331 [16].

9.2.1.149 ANR Cell Information

The ANR Cell Information IE provides information about an UTRAN Cell.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
RNC-ID	M		9.2.1.50	If the Extended RNC-ID IE is included in the ANR Cell Information IE, the RNC-ID IE shall be ignored.
LAC	0	OCTET STRING (2)		0000 and FFFE not allowed
RAC	0	OCTET STRING (1)		
ANR FDD Cell Information	0		9.2.1.150	
ANR TDD Cell Information	0		9.2.1.151	
ANR TDD Cell Information LCR	0		9.2.1.152	
Extended RNC-ID	0		9.2.1.50a	The Extended RNC-ID IE shall be used if the RNC identity has a value larger than 4095.

9.2.1.150 ANR FDD Cell Information

The ANR FDD Cell Information IE provides information for FDD cell that is neighbouring cell to the Base UTRAN cell in ANR neighbouring relation..

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Primary CPICH Power	0		9.2.1.44	
Tx Diversity Indicator	M		9.2.2.50	
STTD Support Indicator	0		9.2.2.45	
Closed Loop Mode1 Support Indicator	0		9.2.2.2	
Restriction State Indicator	0		9.2.1.48C	
DPC Mode Change Support Indicator	0		9.2.2.56	
Cell Capability Container FDD	0		9.2.2.D	
SNA Information	0		9.2.1.52Ca	
Frequency Band Indicator	0		9.2.2.59	
Max UE DTX Cycle	0		9.2.2.87	
ANR Multiple PLMN List	0		9.2.1.153	
Secondary Serving Cell List	0		9.2.2.101	
Dual Band Secondary Serving Cell List	0		Secondary Serving Cell List 9.2.2.101	
Cell Capability Container Extension FDD	0		9.2.2.123	

9.2.1.151 ANR TDD Cell Information

The ANR TDD Cell Information IE provides information for 3.84Mcps TDD or 7.68Mcps TDD cell that is neighbouring cell to the Base UTRAN cell in ANR neighbouring relation..

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Sync Case	M		9.2.1.54	
Time Slot For SCH	0		Time Slot	
			9.2.1.56	
SCH Time Slot	0		9.2.1.51	
SCTD Indicator	M		9.2.1.78	
DPCH Constant Value	0		9.2.1.23	
PCCPCH Power	0		9.2.1.43	
Restriction State Indicator	0		9.2.1.48C	
Cell Capability Container TDD	0		9.2.3.1a	
Cell Capability Container	0		9.2.3.31	
7.68Mcps TDD				
SNA Information	0		9.2.1.52Ca	
ANR Multiple PLMN List	0		9.2.1.153	

9.2.1.152 ANR TDD Cell Information LCR

The *ANR TDD Cell Information LCR* IE provides information for 1.28Mcps TDD cell that is neighbouring cell to the Base UTRAN cell in ANR neighbouring relation..

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
SCTD Indicator	M		9.2.1.78	
DPCH Constant Value	0		9.2.1.23	
PCCPCH Power	0		9.2.1.43	
Restriction State Indicator	0		9.2.1.48C	
Cell Capability Container TDD LCR	0		9.2.3.1b	
SNA Information	0		9.2.1.52Ca	
ANR Multiple PLMN List	0		9.2.1.153	
Cell Capability Container Extension TDD LCR	0		9.2.3.80	

9.2.1.153 ANR Multiple PLMN List

This information element contains a list of PLMN identities, which identifies the broadcasted PLMN Identities in MOCN and GWCN shared network configurations. The common PLMN Identify (mandatory PLMN Identity that is broascasted in the MIB) is not included in the list.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
List of PLMNs		1 <maxnrofbroadc astPLMNs></maxnrofbroadc 		
>PLMN Identity	М		OCTET STRING (SIZE (3))	- digits 0 to 9, two digits per octet, - each digit encoded 0000 to 1001, - 1111 used as filler - bit 4 to 1 of octet n encoding digit 2n-1 - bit 8 to 5 of octet n encoding digit 2n -The PLMN identity consists of 3 digits from MCC followed by either -a filler plus 2 digits from MNC (in case of 2 digit MNC) or -3 digits from MNC (in case of a 3 digit MNC).

Range bound	Explanation
maxNrOfBroadcastPLMNs	Maximum number of additional PLMN identitys that can be
	broadcasted in a cell involved in a MOCN or GWCN Shared
	Network configuration. The value for maxNrOfBroadcastPLMNs is 5.

9.2.2 FDD Specific Parameters

This subclause contains parameters that are specific to FDD.

9.2.2.a ACK-NACK Repetition Factor

The ACK-NACK Repetition Factor IE indicates the consecutive repetition of the ACK and NACK.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
ACK-NACK Repetition			INTEGER	Step: 1
Factor			(1,4,)	

9.2.2.b ACK Power Offset

The *ACK Power Offset* IE indicates Power offset used in the UL between the HS-DPCCH slot carrying HARQ ACK information and the associated DPCCH.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
ACK Power Offset			INTEGER (08,)	According to mapping in TS 25.213 [21] subclause 4.2.1.

9.2.2.A Active Pattern Sequence Information

Defines the parameters for the compressed mode gap pattern sequence activation. For details see TS 25.331 [16].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
CM Configuration Change CFN	М		CFN 9.2.1.9	Description	-	- Criticality
Transmission Gap Pattern Sequence Status		0 <maxtgp S></maxtgp 		If the group is not present, none of the pattern sequences are activated.	-	
>TGPSI Identifier	М		INTEGER(1< MaxTGPS>)	Establish a reference to the compressed mode pattern sequence. Up to <maxtgps> simultaneous compressed mode pattern sequences can be activated.</maxtgps>	-	
>TGPRC	M		INTEGER(05 11)	The number of transmission gap patterns within the Transmission Gap Pattern Sequence. 0=Infinity.	-	
>TGCFN	М		CFN 9.2.1.9	Connection Frame Number of the first frame of the first pattern 1 within the Transmission Gap Pattern Sequence.	-	
>Affected HS- DSCH serving cell List		0 <maxno ofHSDSC H></maxno 		The HS-DSCH serving cells affected by the TGPS when activating frequency specific compressed mode. Max 4 in this 3GPP release.	EACH	reject
>>C-ID	M		9.2.1.6		-	

Range bound	Explanation		
maxTGPS	Maximum number of active pattern sequences. Value 6.		
maxnoofHSDSCH	Maximum number of Primary Serving plus Secondary Serving HS-		
	DSCH cells for one UE		

9.2.2.B Adjustment Period

Adjustment Period IE defines the period to be used for power balancing.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Adjustment Period			INTEGER (1 256)	Unit: Frames

9.2.2.C Adjustment Ratio

Adjustment Ratio IE (Radj) defines the convergence rate used for the associated Adjustment Period.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Adjustment Ratio			INTEGER (0 100)	The Adjustment Ratio is given with a granularity of 0.01 0 -> 0.00 1 -> 0.01 100 -> 1.00

9.2.2.Ca Bundling Mode Indicator

The Bundling Mode Indicator indicates whether the bundling shall be done or shall not be done for Iur.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Bundling Mode Indicator			ENUMERATED (The value "Bundling" is
			Bundling, No bundling)	applicable only when E-TTI indicates "2ms".

9.2.2.D Cell Capability Container FDD

The Cell Capability Container FDD indicates which functionalities a cell supports.

FDD (32) cell supp functions value 1 of the supplementary of the supplem	t indicates whether a ports a particular ality or not. The of a bit indicates that
FDD (32) cell suppression value 1 (32)	ality or not. The
functions value 1 of	ality or not. The
	of a bit indicates that
the corre	
	esponding
	ality is supported in a
	value 0 indicates
	corresponding
	ality is not supported
	. Each bit is defined
as follow	·· · ·
	t bit:Reserved.
	ond bit: Delayed on Support Indicator.
	d bit: HS-DSCH
	Indicator.
	rth bit:Reserved.
	bit: F-DPCH
	Indicator.
	h bit: E-DCH Support
Indicator	
	renth bit: E-DCH
TTI2ms	Support Indicator.
The eight	hth bit: E-DCH
	l2sf4 and all inferior
	pport Indicator.
	th bit: E-DCH 2sf2
	nferior SFs Support
Indicato	
	th bit: E-DCH 2sf4
	nferior SFs Support
Indicator The class	
	venth bit: E-DCH sf4 nferior SFs Support
Indicato	
	lveth bit: E-DCH sf8
	nferior SFs Support
Indicato	
	teenth bit: E-DCH
	R Combining
	Indicator.
	rteenth bit: E-DCH
HARQ C	Chase Combining
Support	Indicator.
	enth bit: Continuous
	Connectivity DTX-
	ipport Indicator.
	eenth bit: Continuous
	Connectivity HS-
	ess Support
Indicato	r. venteenth bit: MIMO
	Indicator.
	hteenth bit:
	QAM UL Support
Indicato	
	eteenth bit: Flexible
	PDU Size Support
Indicato	
	entieth bit: F-DPCH
	mat Support
Indicato	
The twe	entyfirst bit:
Sixtyfou	rQAM DL Support
Indicato	
The twe	entysecond bit:

	Flexible E-DCH MAC-d PDU Size Support Indicator. The twentythird bit: E- DPCCH Power Boosting Support Indicator. The twentytfourth bit: SixtyfourQAM DL and MIMO Combined Support Indicator. This bit shall not be set to 1 if SixtyfourQAM DL Support Indicator is set to 0 or MIMO Support Indicator is set to 0. The twentyfifth bit: Multi Cell Support Indicator The twentysixth bit: MBMS Support Indicator. The twentyseventh bit: TX Diversity on DL Control Channels by MIMO Capable UE when MIMO operation is Active Support Indicator. The twentyeighth bit: Dual Band Support Indicator The twentyninth bit: Single Stream MIMO Support Indicator. The thirtieth bit: Preferred Precoding Weight Set Restriction Support Indicator. (See TS 25.331 [16], the value 1 indicates preferred)
	Note that undefined bits are considered as a spare bit and spare bits shall be set to 0 by the transmitter and shall be ignored by the receiver. Note that Reserved bits are not considered as a spare bit. They shall however be set to 0 by the transmitter and shall be ignored by the receiver.

9.2.2.E Cell Portion ID

Cell Portion ID is the unique identifier for a cell portion within a cell. See TS 25.215 [11].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Cell Portion ID			INTEGER (063,)	

9.2.2.1 Chip Offset

The Chip Offset is defined as the radio timing offset inside a radio frame. The Chip Offset is used as offset for the DL DPCH relative to the Primary CPICH timing for the DL DPCH or for the F-DPCH.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Chip Offset			INTEGER	Unit: Chips
			(038399)	

9.2.2.2 Closed Loop Mode1 Support Indicator

The Closed Loop Mode1 Support Indicator indicates whether the particular cell is capable to support Closed loop mode1 or not

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Closed Loop Mode1 Support			ENUMERAT	
Indicator			ED(Closed	
			loop mode1	
			Supported,	
			Closed loop	
			mode1 not	
			supported).	

9.2.2.3 Closed Loop Mode2 Support Indicator

Void.

9.2.2.3A Closed Loop Timing Adjustment Mode

Indicates when the phase/amplitude adjustment is performed in the DL in relation to the receipt of the UL feedback command in case of closed loop mode transmit diversity on DPCH.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Closed Loop Timing Adjustment			ENUMERAT	According to TS 25.214 [10]
Mode			ED(Offset1,	subclause 7.1:
			Offset2,)	Offset1 = slot(j+1)mod15
				Offset2 = slot(j+2)mod15

9.2.2.4 Compressed Mode Method

Void

9.2.2.4A DCH FDD Information

The DCH FDD Information IE provides information for DCHs to be established.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
DCH FDD Information		1 <maxno ofDCHs></maxno 	TROTOTOTO		_	
>Payload CRC Presence Indicator	М		9.2.1.42		-	
>UL FP Mode	М		9.2.1.67		_	
>ToAWS	М		9.2.1.58		_	
>ToAWE	М		9.2.1.57		_	
>DCH Specific Info		1 <maxno ofDCHs></maxno 			_	
>>DCH ID	М		9.2.1.16		_	
>>TrCH Source Statistics Descriptor	М		9.2.1.65		_	
>>Transport Format Set	М		9.2.1.64	For the UL.	_	
>>Transport Format Set	М		9.2.1.64	For the DL.	_	
>>BLER	M		9.2.1.4	For the UL.	_	
>>BLER	M		9.2.1.4	For the DL.	_	
>>Allocation/Retention Priority	М		9.2.1.1		_	
>>Frame Handling Priority	M		9.2.1.29		_	
>>QE-Selector	M		9.2.1.46A		_	
>>DRAC control	M		9.2.2.13		_	
>>Guaranteed Rate Information	0		9.2.1.30M		YES	ignore
>>Traffic Class	М		9.2.1.58A		YES	ignore
>>Unidirectional DCH Indicator	0		9.2.1.68B		YES	reject
>TNL QoS	0		9.2.1.56A		YES	ignore

Range bound	Explanation
maxnoofDCHs	Maximum number of DCHs for one UE.

9.2.2.4B E-DCH FDD Information

The E-DCH FDD Information IE provides information for an E-DCH to be established.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
E-DCH MAC-d Flows Information	М		9.2.2.4MC		-	
HARQ Process Allocation For 2ms Scheduled Transmission Grant	0		HARQ Process Allocation for 2ms TTI 9.2.2.40	If this IE is not included, scheduled transmission in all HARQ processes is allowed.	I	
E-DCH Maximum Bitrate	0		9.2.2.4MG		_	
E-DCH Processing Overload Level	0		9.2.1.95		-	
E-DCH Reference Power Offset	0		9.2.2.4MI		-	
E-DCH Power Offset for Scheduling Info	0		9.2.1.96		YES	ignore
SixteenQAM UL Operation Indicator	0		9.2.2.90		YES	reject
E-AGCH Table Choice	C- SixteenQA M UL Operation		9.2.2.61A	If the SixteenQAM UL operation is not configured for this UE, Table 16B for E- AGCH in TS 25.212 [9] shall be used.	YES	ignore

Condition	Explanation
SixteenQAM UL Operation	The IE shall be present if the SixteenQAM UL Operation Indicator IE is
	set to "Activate".

9.2.2.4C E-DCH FDD Information Response

The *E-DCH FDD Information Response* IE provides information for E-DCH MAC-d flows that have been established or modified. It also provides additional E-DCH information determined within the DRNS.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
E-DCH MAC-d Flow Specific Information Response		1 <maxno ofEDCHM ACdFlows ></maxno 			-	
>E-DCH MAC-d Flow ID	M		9.2.1.91	If only HARQ Process Allocation For 2ms Scheduled Transmissio n Grant IE and this IE (E-DCH MAC-d Flow ID) are present in the E-DCH FDD Information Response IE, the content of this IE shall be considered invalid		
>Binding ID	0		9.2.1.3		1	
>Transport Layer Address	0		9.2.1.62		_	
>HARQ Process Allocation For 2ms Non- Scheduled Transmission Grant	0		HARQ Process Allocation for 2ms TTI 9.2.2.40		-	
>Transport Bearer Not Setup Indicator	0		9.2.2.4T		YES	ignore
HARQ Process Allocation For 2ms Scheduled Transmission Grant	0		HARQ Process Allocation for 2ms TTI 9.2.2.40		-	

Range bound	Explanation
maxnoofEDCHMACdFlows	Maximum number of E-DCH MAC-d flows.

9.2.2.4D E-DCH FDD DL Control Channel Information

The E-DCH FDD DL Control Channel Information IE provides information for E-DCH specific DL Control Channels to be provided to UE via RRC signalling.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
E-AGCH And E-RGCH/E- HICH FDD Scrambling Code	0		DL Scrambling Code 9.2.2.11	Scrambling code on which E-AGCH, E-RGCH and E-HICH are transmitted. 0= Primary scrambling code of the cell 115 = Secondary scrambling code	-	
E-AGCH Channelisation Code	0		FDD DL Channelisat ion Code Number 9.2.2.14		-	
Primary E-RNTI	0		E-RNTI 9.2.1.94		_	
Secondary E-RNTI	0		E-RNTI 9.2.1.94		-	
E-RGCH/E-HICH Channelisation Code	М		FDD DL Channelisat ion Code Number 9.2.2.14		-	
E-RGCH Signature Sequence	0		INTEGER (0maxnoof SigSeqERG HICH-1)		-	
E-HICH Signature Sequence	0		INTEGER (0maxnoof SigSeqERG HICH-1)		-	
Serving Grant Value	0		INTEGER (037,38)	(037) indicates E- DCH serving grant index as defined in TS 25.321 [41]; index 38 means zero grant	-	
Primary/Secondary Grant Selector	0		ENUMERA TED (Primary, Secondary)	Indicates whether the Serving Grant Value is granted with a primary E- RNTI or a secondary E- RNTI	-	
E-RGCH Release Indicator	0		9.2.2.60		_	
E-RGCH and E-HICH Channelisation Code Validity Indicator	0		9.2.2.68	Indicates whether the value of E- RGCH and E- HICH Channelisatio n Code is invalid	YES	ignore
Default Serving Grant in	0		INTEGER	Serving Grant	YES	ignore

DTX Cycle 2	(037,38)	value to be
		used in DTX-
		Cycle-2.
		(037)
		indicates E-
		DCH serving
		grant index as
		defined in TS
		25.425 [32];
		index 38
		means zero
		grant

Range bound	Explanation
maxnoofSigSeqERGHICH	Maximum number Signature Sequences for E-RGCH
	/ E-HICH

9.2.2.4E E-DCH RL Indication

Indicates whether a RL is an E-DCH RL.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH RL Indication			ENUMERAT	
			ED(E-DCH,	
			non E-DCH)	

9.2.2.4F E-DCH FDD Information To Modify

The E-DCH FDD Information IE provides information for an E-DCH to be modified.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
E-DCH MAC-d Flow Specific Information		1 <maxno ofEDCHM ACdFlows ></maxno 	Reference	See Note1 below.	-	
>E-DCH MAC-d Flow ID	М		9.2.1.91		_	
>Allocation/Retention Priority	0		9.2.1.1		1	
>Transport Bearer Request Indicator	М		9.2.1.61		-	
>TNL QoS	0		9.2.1.56A		_	
>Maximum Number of Retransmissions for E- DCH	0		9.2.1.100		-	
>Traffic Class	0		9.2.1.58A		_	
>E-DCH HARQ Power Offset FDD	0		9.2.2.4L		I	
>E-DCH MAC-d Flow Multiplexing List	0		9.2.1.89		ı	
> CHOICE <i>E-DCH</i> grant type	0					
>>E-DCH Non- Scheduled Transmission Grant						
>>>Maximum Number of Bits per MAC-e PDU for Non-scheduled Transmission	M		9.2.2.4N	If the Extended Maximum Number of Bits per MAC-e PDU for Non- scheduled Transmission IE is present, this IE shall be ignored. When Maximum MAC-d PDU Size Extended IE is configured for an E-DCH Logical Channel this IE indicates the maximum number of bits per MAC-I PDU.	-	
>>>HARQ Process Allocation For 2ms Non-Scheduled Transmission Grant	0		HARQ Process Allocation for 2ms TTI 9.2.2.40		-	

>>>Extended Maximum	0		9.2.2.4R	When	YES	reject
Number of Bits per				Maximum		•
MAC-e PDU for Non-				MAC-d PDU		
scheduled				Size Extended		
Transmission				IE is		
				configured for		
				an E-DCH		
				Logical		
				Channel this		
				IE indicates		
				the extended		
				maximum		
				number of bits		
				per MAC-I		
				PDU.		
>>E-DCH Scheduled			NULL			
Transmission Grant			HOLL			
			0000			
>Bundling Mode Indicator	0		9.2.2.Ca		_	
>E-DCH Logical Channel	0		E-DCH		_	
To Add			Logical			
			Channel			
			Information			
E DOLLI : : : : :	-		9.2.1.92			
>E-DCH Logical Channel			9.2.1.93		_	
To Modify						
>E-DCH Logical Channel		0<			_	
To Delete		maxnooflo				
		gicalchann				
		els>				
>>Logical Channel ID	M		9.2.1.97		_	
HARQ Process Allocation	0		HARQ		_	
For 2ms Scheduled			Process			
Transmission Grant			Allocation			
Transmission Stant			for 2ms TTI			
			9.2.2.40			
E-DCH Maximum Bitrate	0		9.2.2.4MG		_	
E-DCH Processing Overload	0		9.2.1.95		_	
Level						
E-DCH Reference Power	0		9.2.2.4MI		_	
Offset			0.2.2. 11111			
			0.04.00			
MAC-e Reset Indicator	0		9.2.1.99		-	
E-DCH Power Offset for	0		9.2.1.96	1	YES	ignore
Scheduling Info	1			<u> </u>		
SixteenQAM UL Operation	0		9.2.2.90		YES	reject
Indicator				1	-	,
E-DCH MAC-d PDU Size	0		9.2.1.91A		YES	reject
	~		3.2.1.31A		123	reject
Format	-				01.0541	
E-DCH DL Control Channel		0 <maxno< td=""><td></td><td></td><td>GLOBAL</td><td>ignore</td></maxno<>			GLOBAL	ignore
Grant Information		ofEDCHR				
		Ls>		1		
>E-DCH RL ID	М		RL ID		_	
, = = = = = = = = = = = = = = = = = = =			9.2.1.49			
F ACCUTABLE OF STATE				If aives an CANA	VEC	ia:
E-AGCH Table Choice	C-		9.2.2.61A	If sixteenQAM	YES	ignore
	SixteenQA			UL operation		
	M UL			is not used in		
	Operation			the new		
				configuration		
				for this UE,		
				Table 16B for		
				E-AGCH in TS		
				25.212 [9]		
				shall be used		
				in the new		
	i .	i .	I	configuration.		

Note 1: Even if no E-DCH MAC-d Flow Specific Information needs to be modified, one E-DCH MAC-d Flow Information shall be included, which only contains the *E-DCH MAC-d Flow ID* IE and the *Transport BearerRequest Indicator* IE set to "Bearer not Requested".

Condition	Explanation
SixteenQAM UL Operation	The IE shall be present if the SixteenQAM UL Operation Indicator IE
	is set to "Activate".

Range bound	Explanation
maxnoofEDCHMACdFlows	Maximum number of E-DCH MAC-d flows.
Maxnooflogicalchannels	Maximum number of Logical Channels
maxnoofEDCHRLs	Maximum number of E-DCH RLs for one UE

9.2.2.4G E-DCH Transport Format Combination Set Information (E-TFCS Information)

Whereas the related Transport Block sizes are standardised in TS 25.321 [41] this IE gives details on the referenced Transport Block Size Table, the E-DCH Minimum Set E-TFCI, the Reference E-TFCIs and configuration parameters used for the calculation of the gain factors β_{ec} and β_{ed} defined in TS 25.214 [10].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
E-TFCI Table Index	M		INTEGER (01,, 27)	Indicates which standardised E-TFCS Transport Block Size Table shall be used. The related tables are specified in TS 25.321 [41].	_	
E-DCH Minimum Set E-TFCI	M		INTEGER (0127)	For the concept of "E-DCH Minimum Set of TFCs" see TS 25.321 [41] and TS 25.331 [16].	-	
Reference E-TFCI		1 <maxno< td=""><td></td><td></td><td>-</td><td></td></maxno<>			-	
Information		ofRefETF Cls>				
>Reference E-TFCI	М		INTEGER (0127)		_	
>Reference E-TFCI Power Offset	М		9.2.2.4P	If the Extended Reference E- TFCI Power Offset IE is present, this IE shall be ignored		
>Extended Reference E- TFCI Power Offset	0		9.2.2.4Q		YES	reject
E-DCH Minimum Set E- TFCI Validity Indicator	0		9.2.2.69	Indicates whether the value of E- DCH Minimum Set E-TFCI is invalid	YES	reject
E-TFCI Boost Informatiion	0		9.2.2.91		YES	reject
E-DPDCH Power Interpolation	0		BOOLEAN	True means that the E-DPDCH power interpolation formula shall be applied, False means that the E-DPDCH power extrapolation formula shall be applied for the computation of the gain factor β _{ed} according to TS 25.214 [10]	YES	reject

Range Bound	Explanation
maxnoofRefETFCIs	Maximum number of signalled reference E-TFCIs

9.2.2.4J E-TTI

The E-TTI parameter indicates the Transmission Time Interval for E-DPCH operation.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-TTI			ENUMERAT	
			ED (2ms,	
			10ms)	

9.2.2.4K E-DPCCH Power Offset

The E-DPCCH Power Offset is used to calculate the E-DPCCH gain factor β_{ec} as defined in TS 25.214 [10], whereas β_{ec} is related to the power difference between DPCCH and E-DPCCH.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DPCCH Power Offset			INTEGER (08)	According to mapping in TS 25.213 [21] subclause 4.2.1.3

9.2.2.4KA Void

9.2.2.4L E-DCH HARQ Power Offset FDD

The E-DCH HARQ Power Offset FDD is used to calculate the unquantised gain factor for an E-TFC ($\beta_{ed,j,uq}$) as defined in TS 25.214 [10].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH HARQ Power Offset FDD			INTEGER (06)	According to mapping in TS 25.213 [21] subclause 4.2.1.3.

9.2.2.4M Void

9.2.2.4MA Void

9.2.2.4MB Void

9.2.2.4MC E-DCH MAC-d Flows Information

The E-DCH MAC-d Flows Information IE is used for the establishment of E-DCH MAC-d flows.

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
= DOULDE A:			Reference			
E-DCH MAC-d Flow Specific Information		1 <maxno ofEDCHM ACdFlows</maxno 			_	
>E-DCH MAC-d Flow ID	М		9.2.1.91		_	
>Allocation/Retention Priority	0		9.2.1.1		-	
>TNL QoS	0		9.2.1.56A		_	
>Payload CRC Presence Indicator	М		9.2.1.42		_	
>Maximum Number of Retransmissions for E- DCH	M		9.2.1.100		_	
>Traffic Class	М		9.2.1.58A		_	
>E-DCH HARQ Power Offset FDD	М		9.2.2.4L		_	
>E-DCH MAC-d Flow Multiplexing List	0		9.2.1.89		_	
>CHOICE E-DCH grant type	М				_	
>>E-DCH Non- Scheduled Transmission Grant						
>>>Maximum Number of Bits per MAC-e PDU for Non-scheduled Transmission	M		9.2.2.4N	If the Extended Maximum Number of Bits per MAC-e PDU for Non- scheduled Transmission IE is present, this IE shall be ignored. When Maximum MAC-d PDU Size Extended IE is configured for an E-DCH Logical Channel this IE indicates the maximum number of bits per MAC-I PDU.	Į.	
>>>HARQ Process Allocation For 2ms Non-Scheduled Transmission Grant	0		HARQ Process Allocation for 2ms TTI 9.2.2.40	If this IE is not included, transmission in all HARQ processes is allowed.	-	

>>>Extended Maximum Number of Bits per MAC-e PDU for Non- scheduled Transmission	0	9.2.2.4R	When Maximum MAC-d PDU Size Extended IE is configured for an E-DCH Logical Channel this IE indicates the extended maximum number of bits per MAC-I PDU.	YES	reject
>>E-DCH Scheduled Transmission Grant		NULL			
>Bundling Mode Indicator	0	9.2.2.Ca		_	
>E-DCH Logical Channel Information	М	9.2.1.92		-	
>TrCH Source Statistics Descriptor	0	9.2.1.65		YES	ignore

Range bound	Explanation		
maxnoofEDCHMACdFlows	Maximum number of E-DCH MAC-d flows.		

9.2.2.4MD Void

9.2.2.4ME Void

9.2.2.4MF Void

9.2.2.4MG E-DCH Maximum Bitrate

The E-DCH Maximum Bitrate parameter indicates the Maximum Bitrate for an E-DCH.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH Maximum Bitrate			INTEGER (05742,, 574311498)	Bitrate on transport block level. Unit is kbits per second.

9.2.2.4MH Void

9.2.2.4MI E-DCH Reference Power Offset

The E-DCH Reference Power Offset is used to estimate the E-DPDCH power from E-TFCI without decoding MAC-e PDUs.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH Reference Power Offset			INTEGER (06)	According to mapping in TS 25.213 [21] subclause 4.2.1.3.

9.2.2.4MJ Void

9.2.2.4N Maximum Number of Bits per MAC-e PDU for Non-scheduled Transmission

The Maximum Number of Bits per MAC-e PDU for Non-scheduled Transmission indicates the maximum numbers of bits allowed to be included in a MAC-e (or MAC-i) PDU per E-DCH MAC-d flow configured for non-scheduled transmissions. If the range of the *Maximum Number of Bits per MAC-e PDU for Non-scheduled Transmission* IE is insufficient to represent the value to be sent to the DRNS, the *Extended Maximum Number of Bits per MAC-e PDU for Non-scheduled Transmission* IE shall be used to represent the value to be sent to the DRNS, see section 9.2.2.4R.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Maximum Number of Bits per			INTEGER (119982)	
MAC-e PDU for Non-				
Scheduled Transmission				

9.2.2.40 HARQ Process Allocation For 2ms TTI

The HARQ Process Allocation for 2ms TTI indicates those HARQ processes that are allowed. MAC-d PDU's for a MAC-d flow are only allowed to be transmitted in those processes for which the bit is set to "1".

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
HARQ Process Allocation For 2ms TTI			BIT STRING (8)	The first Bit corresponds to HARQ process ID = 0, the second bit corresponds to HARQ process ID = 1, etc. The HARQ process ID for 2ms TTI is defined in TS 25.321 [41], chapter 11.8.1.3.

9.2.2.4P Reference E-TFCI Power Offset

The Reference E-TFCI Power Offset is used to calculate the reference E-TFC gain factor $\beta_{ed,ref}$ as defined in TS 25.214 [10]. If the range of the *Reference E-TFCI Power Offset* IE is insufficient to represent the value to be sent to the DRNS, the *Extended Reference E-TFCI Power Offset* IE shall be used to represent the value to be sent to the DRNS, see section 9.2.2.4Q.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Reference E-TFCI Power Offset			INTEGER (029)	According to mapping in TS 25.213 [21] subclause 4.2.1.3

9.2.2.4Q Extended Reference E-TFCI Power Offset

The Extended Reference E-TFCI Power Offset IE shall be used if the range of the Reference E-TFCI Power Offset IE (see section 9.2.2.4P) is insufficient to represent the value of the Reference E-TFCI Power Offset to be sent to the DRNS.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Extended Reference E-TFCI Power Offset			INTEGER (3031,)	According to mapping in TS 25.213 [21] subclause 4.2.1.3

9.2.2.4R Extended Maximum Number of Bits per MAC-e PDU for Non-scheduled Transmission

The Extended Maximum Number of Bits per MAC-e PDU for Non-scheduled Transmission IE shall be used if the range of the Maximum Number of Bits per MAC-e PDU for Non-scheduled Transmission IE (see section 9.2.2.4N) is insufficient to represent the value of the Maximum Number of Bits per MAC-e (or MAC-i) PDU for Non-scheduled Transmission to be sent to the DRNS.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Extended Maximum Number of			INTEGER	
Bits per MAC-e PDU for Non-			(1998322978,)	
scheduled Transmission				

9.2.2.4S Transport Bearer Not Requested Indicator

The Transport Bearer Not Requested Indicator parameter indicates that a transport bearer shall not be established or may not to be established for DCH or an E-DCH MAC-d flow.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Transport Bearer Not Requested Indicator			ENUMERATED (Transport Bearer shall not be Established, Transport Bearer may not be Established)	

9.2.2.4T Transport Bearer Not Setup Indicator

The Transport Bearer Not Setup Indicator parameter indicates that a transport bearer will not be established for a DCH or an E-DCH MAC-d flow.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Transport Bearer Not Setup			ENUMERATED	
Indicator			(Transport Bearer	
			Not Setup)	

9.2.2.5 D-Field Length

Void

9.2.2.6 Diversity Control Field

Void.

9.2.2.7 Diversity Indication

Void.

9.2.2.8 Diversity Mode

Define the diversity mode to be applied.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Diversity Mode			ENUMERAT	The Diversity Mode IE shall
			ED(None,	never be set to "Not Used". If
			STTD,	received it shall be rejected.
			Closed loop	-
			mode 1, Not	
			Used,)	

9.2.2.9 DL DPCH Slot Format

Indicates the slot format used in DPCH in DL, according to TS 25.211 [8].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DL DPCH Slot Format			INTEGER	
			(016,)	

9.2.2.9A DL DPCH Timing Adjustment

The DL DPCH Timing Adjustment indicates that a timing adjustment of the related radio link is required or that an Initial DL DPCH Timing Adjustment has been performed by the DRNS. It also indicates whether the timing adjustment consists of a timing advance or a timing delay with respect to the SFN timing. The adjustment always consists of 256 chips.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DL DPCH Timing			ENUMERAT	The size of the timing
Adjustment			ED(timing	adjustment is 256 chips.
_			advance,	
			timing delay)	

9.2.2.10 DL Power

Void

9.2.2.10A DL Power Balancing Information

The *DL Power Balancing Information* IE provides information for power balancing to be activated in the relevant RL(s).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Power Adjustment Type	M		9.2.2.28		_	
DL Reference Power	C-Common		DL power 9.2.1.21A	Power on DPCH or on F-DPCH	_	
DL Reference Power Information	C-Individual	1 <maxnoof RLs></maxnoof 			_	
>RL ID	M		9.2.1.49		_	
>DL Reference Power	M		DL power 9.2.1.21A	Power on DPCH or on F-DPCH	_	
Max Adjustment Step	C- CommonOrIn dividual		9.2.2.23		_	
Adjustment Period	C- CommonOrIn dividual		9.2.2.B		-	
Adjustment Ratio	C- CommonOrIn dividual		9.2.2.C		_	

Condition	Explanation
Common	The IE shall be present if the Power Adjustment Type IE is set to
	"Common".
Individual	The IE shall be present if the Power Adjustment Type IE is set to
	"Individual".
CommonOrIndividual	The IE shall be present if the Power Adjustment Type IE is set to
	"Common" or "Individual".

Range Bound	Explanation
maxnoofRLs	Maximum number of Radio Links for a UE.

9.2.2.10B DL Power Balancing Activation Indicator

The *DL Power Balancing Activation Indicator* IE indicates that the power balancing is activated in the RL.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DL Power Balancing			ENUMERATED(DL	
Activation Indicator			Power Balancing	
			Activated).	

9.2.2.10C DL Reference Power Information

The *DL Reference Power Information* IE provides reference power of the power balancing to be used in the relevant RL(s).

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
			Reference			
Common DL Reference	0		DL power	Power on	_	
Power			9.2.1.21A	DPCH or on		
				F-DPCH		
Individual DL Reference		0 <maxnoof< td=""><td></td><td></td><td>_</td><td></td></maxnoof<>			_	
Power Information		RLs>				
>RL ID	M		9.2.1.49		-	
>DL Reference Power	M		DL power	Power on	-	
			9.2.1.21A	DPCH or on		
				F-DPCH		

Range bound	Explanation
maxnoofRLs	Maximum number of RLs for a UE.

9.2.2.10D DL Power Balancing Updated Indicator

The *DL Power Balancing Updated Indicator* IE indicates that the power balancing related parameters is updated in the RL.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DL Power Balancing			ENUMERATED(DL	
Updated Indicator			Power Balancing	
			Updated).	

9.2.2.11 DL Scrambling Code

DL Scrambling code to be used by the RL. One cell may have multiple DL Scrambling codes available.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DL Scrambling Code			INTEGER (015)	0= Primary scrambling code of the cell
				115= Secondary scrambling code

9.2.2.12 Downlink Frame Type

Void

9.2.2.12A DPC Mode

The DPC Mode IE indicates the DPC mode to be applied TS 25.214 [10].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DPC Mode			ENUMERAT TED (Mode0, Mode1,)	Mode0: The DRNS shall estimate the UE transmitted TPC command and update the DL power in every slot Mode1: The DRNS shall estimate the UE transmitted TPC command over three slots and shall update the DL power in every three slots

9.2.2.13 DRAC Control

The possibility to use DRAC control has been removed.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
DRAC Control			ENUMERAT	The DRAC Control IE shall
			ED (Not	never be set to "Not Used".
			Used, Not-	
			Requested)	

9.2.2.13A DSCH FDD Information

Void.

9.2.2.13B DSCH FDD Information Response

Void.

9.2.2.13Bb DSCH-RNTI

Void.

9.2.2.13C FDD DCHs To Modify

The FDD DCHs To Modify IE provides information for DCHs to be modified.

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
			Reference			
FDD DCHs To Modify		1 <maxno ofDCHs></maxno 			-	
>UL FP Mode	0		9.2.1.67		_	
>ToAWS	0		9.2.1.58		_	
>ToAWE	0		9.2.1.57		_	
>Transport Bearer Request Indicator	М		9.2.1.61		_	
>DCH Specific Info		1 <maxno ofDCHs></maxno 			_	
>>DCH ID	M		9.2.1.16		_	
>>Transport Format Set	0		9.2.1.64	For the UL.	_	
>>Transport Format Set	0		9.2.1.64	For the DL.	_	
>>Allocation/Retention Priority	0		9.2.1.1		_	
>>Frame Handling Priority	0		9.2.1.29		_	
>>Not Used	0		NULL		_	
>>Guaranteed Rate Information	0		9.2.1.30M		YES	ignore
>>Traffic Class	0		9.2.1.58A		YES	ignore
>>Unidirectional DCH Indicator	0		9.2.1.68B		YES	reject
>TNL QoS	0		9.2.1.56A		YES	ignore

Range bound	Explanation
maxnoofDCHs	Maximum number of DCHs for one UE.

9.2.2.13D Enhanced DSCH PC

Void.

9.2.2.13E Enhanced DSCH PC Counter

Void.

9.2.2.13F Enhanced DSCH PC Indicator

Void.

9.2.2.13G Enhanced DSCH PC Wnd

Void.

9.2.2.13H Enhanced DSCH Power Offset

Void.

9.2.2.13I Enhanced Primary CPICH Ec/No

Energy per PN chip divided by the total received power spectral density measured on the Primary CPICH by the UE.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Enhanced Primary CPICH Ec/No			INTEGER(049)	According to the mapping of the Primary CPICH Ec/lo UE measurement defined in TS 25.133 [23] and TS 25.123 [24]

9.2.2.14 FDD DL Channelisation Code Number

The DL Channelisation Code Number indicates the DL Channelisation Code number for a specific DL physical channel.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
FDD DL Channelisation Code Number			INTEGER(0. . 511)	According to the mapping in TS 25.213 [27].
				The maximum value is equal to the DL spreading factor –1

9.2.2.14A FDD DL Code Information

The FDD DL Code Information IE provides FDD DL Code information for all DPCHs or for the F-DPCH of one Radio Link.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
FDD DL Code Information		1 <maxnoof DLCodes</maxnoof 			_	
>DL Scrambling Code	М		9.2.2.11		_	
>FDD DL Channelisation Code Number	М		9.2.2.14		_	
>Transmission Gap Pattern Sequence Scrambling Code Information	0		9.2.2.47B		_	

Range bound	Explanation
maxnoofDLCodes	Maximum number of DL Channelisation Codes for
	one UE.

9.2.2.15 FDD S-CCPCH Offset

Void.

9.2.2.16 FDD TPC Downlink Step Size

This parameter indicates step size for the DL power adjustment.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
FDD TPC Downlink Step			ENUMERAT	
Size			ED(0.5, 1,	
			1.5, 2,)	

9.2.2.16A First RLS Indicator

The First *RLS Indicator* IE indicates if a specific Radio Link and all Radio Links which are part of the same Radio Link Set, shall be considered as the first radio links established towards the UE or not.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
First RLS Indicator			ENUMERAT	
			ED(first RLS,	
			not first RLS)	

9.2.2.17 Gap Position Mode

Void.

9.2.2.18 Gap Period (TGP)

Void.

9.2.2.19 Gap Starting Slot Number (SN)

Void

9.2.2.19a HS-DSCH FDD Information

The HS-DSCH FDD Information IE is used for initial addition of HS-DSCH information to UE Context.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
HS-DSCH MAC-d Flows	М		9.2.1.30OA		_	, , , ,
Information UE Capabilities		1				
Information		l			_	
>HS-DSCH Physical	M		9.2.1.30Oa		_	
Layer Category						
>1.28 Mcps TDD uplink physical channel capability	0		9.2.3.10D	Not to be used.	YES	ignore
>Number of Supported Carriers	O		ENUMERATE D (One-one carrier, One- three carrier, Three-three carrier, One- six carrier, Tree-six carrier, Six-six carrier,, One-Two carrier Discontiguous, Two-Two carrier Discontiguous, One-Two carrier Contiguous, Two-Two carrier Contiguous, Contiguous, Contiguous, Contiguous, Contiguous, Contiguous, Contiguous, Contiguous)	Not to be used.	YES	reject
>Multi-carrier HS-DSCH Physical Layer Category	0		9.2.1.30Oa	Not to be used.	YES	ignore
>UE RF Band Capability LCR	C- NofSupport edCarriers		9.2.3.84	Not to be used.	YES	ignore
MAC-hs Reordering Buffer Size for RLC-UM	M		9.2.1.34Ab		-	
CQI Feedback Cycle k	М		9.2.2.24a		_	
CQI Repetition Factor	C- CQICyclek		9.2.2.24c		_	
ACK-NACK Repetition Factor	M		9.2.2.a		_	
CQI Power Offset	М		9.2.2.24b		_	
ACK Power Offset	M		9.2.2.b		_	
NACK Power Offset	М		9.2.2.26a		_	
HS-SCCH Power Offset	0		9.2.2.19d		_	
HARQ Preamble Mode	0		9.2.2.57		YES	ignore
MIMO Activation Indicator	0		9.2.1.134		YES	reject
HS-DSCH MAC-d PDU Size Format	0		9.2.1.30OC	If not present, "Indexed MAC-d PDU Size" shall be used.	YES	reject
Sixtyfour QAM Usage Allowed Indicator	0		9.2.2.79A		YES	ignore
UE with enhanced HS- SCCH support indicator	0		NULL	UE supports enhanced HS-SCCH functionality: - UE supports different HS-SCCH in consecutive TTIs and,	YES	ignore

			- in HS-SCCH- less operation mode the UE supports HS- SCCH orders		
Enhanced HS Serving CC Abort	0	ENUMERATE D (Abort Enhanced HS Serving CC,)	Shall be ignored in Radio Link Setup and Radio Link Addition procedures.	YES	reject
UE Support Indicator Extension	0	9.2.2.103		YES	ignore
Power Offset For S-CPICH for MIMO Request Indicator	0	9.2.2.105		YES	ignore
Single Stream MIMO Activation Indicator	0	9.2.2.106		YES	reject

Condition	Explanation
CQICyclek	The IE shall be present if the CQI Feedback Cycle k IE is set to
	a value greater than 0.

9.2.2.19aa HS-DSCH FDD Secondary Serving Information

The *HS-DSCH FDD Secondary Serving Information* IE is used for initial addition of Secondary Serving HS-DSCH information to UE Context and defines the cell specific parameters for the secondary serving HS-DSCH Radio Link.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
HS-SCCH Power Offset	0		9.2.2.19d		_	
Sixtyfour QAM Usage Allowed Indicator	0		9.2.2.79A		_	
MIMO Activation Indicator	0		9.2.1.119		YES	reject
Single Stream MIMO Activation Indicator	0		9.2.2.106		YES	reject
Diversity Mode	0		9.2.2.8	If Diversity mode = "Closed loop mode 1" the procedure shall be rejected.	YES	reject
Transmit Diversity Indicator	0		9.2.2.48		YES	reject
Power Offset For S-CPICH for MIMO Request Indicator	0		9.2.2.105		YES	ignore
Ordinal Number Of Frequency	0		INTEGER (132,)	Value = "1" indicates 1st secondary serving HS- DSCH cell, Value = "2" indicates 2nd secondary serving HS- DSCH cell etc. TS 25.214 [10]. The IE shall be ignored by the DRNS if the new configuration contains one secondary serving radio link.	YES	reject

9.2.2.19b HS-DSCH FDD Information Response

The *HS-DSCH FDD Information Response* IE provides information for HS-DSCH MAC-d flows that have been established or modified. It also provides additional HS-DSCH information determined within the DRNS.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
HS-DSCH MAC-d		0 <max< td=""><td></td><td>•</td><td>_</td><td></td></max<>		•	_	
Flow Specific		noofMA				
Information		CdFlow				
Response		s>				
>HS-DSCH MAC-d	M		9.2.1.300		_	
Flow ID						
>Binding ID	0		9.2.1.3		_	
>Transport Layer	0		9.2.1.62		_	
Address						
>HS-DSCH Initial	0		9.2.1.30Na		_	
Capacity Allocation						
HS-SCCH Specific		0 <max< td=""><td></td><td></td><td>_</td><td></td></max<>			_	
Information		noofHS				
Response		SCCHc				
		odes>				
>Code Number	M		INTEGER		_	
			(0127)			
HS-PDSCH And HS-	0		DL Scrambling		_	
SCCH Scrambling			Code			
Code			9.2.2.11			
Measurement Power	0		9.2.2.24d		_	
Offset						
HARQ Memory	0		9.2.1.116		_	
Partitioning						
User Plane Congestion	0		9.2.1.70C		YES	ignore
Fields Inclusion						
HARQ Preamble Mode	0		9.2.2.58		YES	ignore
Activation Indicator						
MIMO Information	0		9.2.2.78		YES	Ignore
Response						
SixtyfourQAM DL	0		9.2.2.79B		YES	Ignore
Usage Indicator						
HS-DSCH TB Size	0		9.2.2.19G		YES	ignore
Table Indicator						
Power Offset For S-	0		9.2.2.104		YES	ignore
CPICH for MIMO						
Support of dynamic	0		9.2.2.129		YES	ignore
DTXDRX related HS-						
SCCH order						

Range bound	Explanation		
maxnoofMACdFlows	Maximum number of MAC-d flows.		
maxnoofHSSCCHcodes	Maximum number of HS-SCCH codes.		

9.2.2.19ba HS-DSCH FDD Secondary Serving Information Response

The *HS-DSCH FDD Secondary Serving Information Response* IE provides Secondary Serving HS-DSCH information determined within the DRNS.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
HS-SCCH Specific Secondary Serving Information Response		0 <maxn oofHSSC CHcodes ></maxn 			-	
>Code Number	М		INTEGER (0127)		_	
HS-PDSCH And HS- SCCH Scrambling Code	0		DL Scrambling Code 9.2.2.11		-	
Measurement Power Offset	0		9.2.2.24d		_	
SixtyfourQAM DL Usage Indicator	0		9.2.2.79B		_	
HS-DSCH TB Size Table Indicator	0		9.2.2.19G		I	
MIMO Information Response	0		9.2.2.78		YES	ignore
Power Offset For S- CPICH for MIMO	0		9.2.2.104		YES	ignore

Range bound	Explanation
maxnoofHSSCCHcodes	Maximum number of HS-SCCH codes.

9.2.2.19bb HS-DSCH FDD Secondary Serving Information To Modify

The *HS-DSCH FDD Secondary Serving Information To Modify* IE is used for modification of cell specific Secondary Serving HS-DSCH information in a UE Context.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
HS-SCCH Power Offset	0		9.2.2.19d		_	_
HS-SCCH Code Change Grant	0		9.2.1.30S		_	
Sixtyfour QAM Usage Allowed Indicator	0		9.2.2.79A		-	
MIMO Mode Indicator	0		9.2.1.135		YES	reject
Single Stream MIMO Mode Indicator	0		9.2.2.107		YES	reject
Diversity Mode	0		9.2.2.8	If Diversity mode = "Closed loop mode 1" the procedure shall be rejected.	YES	reject
Transmit Diversity Indicator	C- DiversityM ode		9.2.2.48		YES	reject
Non Cell Specific Tx Diversity	O		ENUMERAT ED (Tx Diversity,)	Value = "Tx Diversity": Diversity Mode and Transmit Diversity Indicator shall be non cell specific.	YES	reject
Power Offset For S-CPICH for MIMO Request Indicator	0		9.2.2.105		YES	ignore
Ordinal Number Of Frequency	0		INTEGER (132,)	Value = "1" indicates 1st secondary serving HS- DSCH cell, Value = "2" indicates 2nd secondary serving HS- DSCH cell etc. TS 25.214 [10]. The IE shall be ignored by the DRNS if the new configuration contains one secondary serving radio link.	YES	reject

Condition	Explanation
DiversityMode	The IE shall be present if Diversity Mode IE is present and not
	set to "None".

9.2.2.19bc HS-DSCH FDD Secondary Serving Information To Modify Unsynchronised

The *HS-DSCH FDD Secondary Serving Information To Modify Unsynchronised* IE is used for modification of Secondary Serving HS-DSCH information in a UE Context with the Unsynchronised Radio Link Reconfiguration procedure.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
HS-SCCH Power Offset	0		9.2.2.19d		_	
Sixtyfour QAM Usage	0		9.2.2.79A		_	
Allowed Indicator						
MIMO Mode Indicator	0		9.2.1.135		YES	reject
Single Stream MIMO Mode Indicator	0		9.2.2.107		YES	reject
Power Offset For S-	0		9.2.2.105		YES	ignore
CPICH for MIMO						
Request Indicator						
Ordinal Number Of	0		INTEGER	Value = "1"	YES	reject
Frequency			(132,)	indicates 1st		
				secondary		
				serving HS-		
				DSCH cell,		
				Value = "2"		
				indicates 2nd		
				secondary		
				serving HS- DSCH cell		
				etc. TS		
				25.214 [10]. The IE shall		
				be ignored		
				by the DRNS		
				if the new		
				configuration		
				contains one		
				secondary		
				serving radio		
				link.		

9.2.2.19c HS-DSCH FDD Update Information

The *HS-DSCH FDD Update Information* IE provides information for HS-DSCH to be updated. At least one IE shall be presented.

IE/Group name	Presence	Range	IE Type and	Semantic Description	Criticality	Assigned Criticality
			Reference			
HS-SCCH Code Change Indicator	0		9.2.1.30R		_	
CQI Feedback Cycle k	0		9.2.2.24a		_	
CQI Repetition Factor	0		9.2.2.24c		_	
ACK-NACK Repetition Factor	0		9.2.2.a		_	
CQI Power Offset	0		9.2.2.24b		_	
ACK Power Offset	0		9.2.2.b		_	
NACK Power Offset	0		9.2.2.26a		_	
HS-PDSCH Code Change Indicator	0		9.2.1.30V		YES	ignore

9.2.2.19ca HS-DSCH FDD Secondary Serving Update Information

The *HS-DSCH FDD Secondary Serving Update Information* IE provides information for HS-DSCH to be updated. At least one IE shall be presented.

IE/Group name	Presence	Range	IE Type and Reference	Semantic Description
HS-SCCH Code Change Indicator	0		9.2.1.30R	
HS-PDSCH Code Change Indicator	0		9.2.1.30V	This IE shall never be included. If received it shall be ignored.

9.2.2.19C HS-DSCH configured indicator

The *HS-DSCH Configured Indicator* IE indicates the configuration of HS-DSCH for the UE. The *HS-DSCH Configured Indicator* IE shall be used for the configuration of the E-DPDCH IQ branch mapping (TS 25.213 [21]).

IE/Group Name	Presence	Range	IE type and reference	Semantics description
HS-DSCH Configured Indicator			ENUMERATED (HS- DSCH configured, HS-DSCH not configured)	Indicator of the HS-DSCH configuration for configuration of the E-DPDCHs IQ branch mapping (TS 25.213 [21]).

9.2.2.19d HS-SCCH Power Offset

The *HS-SCCH Power Offset* IE indicates the Power offset relative to the pilot bits on the DL DPCCH except when FDPCH is configured. When F-DPCH is configured, the *HS-SCCH Power Offset* IE indicates the Power offset relative to the power of transmitted TPC bits on the F-DPCH.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
HS-SCCH Power Offset			INTEGER (0255)	Step 0.25 dB, range -32- +31.75 dB

9.2.2.19e E-DCH FDD Update Information

The *E-DCH FDD Update Information* IE provides information for E-DCH to be updated. At least one IE shall be present.

IE/Group Name	Presence	Range	IE Type and	Semantics	Criticality	Assigned
			Reference	Description		Criticality
E-DCH MAC-d Flow		0 <maxn< td=""><td></td><td></td><td>_</td><td></td></maxn<>			_	
Specific Update		oofEDCH				
Information		MACdFlo				
		WS>				
>E-DCH MAC-d Flow	M		9.2.1.91		-	
ID						
>HARQ Process	0		HARQ		-	
Allocation For 2ms			Process			
Non-Scheduled			Allocation for			
Transmission Grant			2ms TTI			
			9.2.2.40			
HARQ Process	0		HARQ		-	
Allocation For 2ms			Process			
Scheduled Transmission			Allocation for			
Grant			2ms TTI			
			9.2.2.40			
E-DCH DL Control		0 <maxn< td=""><td></td><td></td><td>GLOBAL</td><td>ignore</td></maxn<>			GLOBAL	ignore
Channel Change		oofEDCH				
Information		RLs>				
>E-DCH RL ID	M		RL ID		-	_
			9.2.1.49			

Range bound	Explanation
maxnoofEDCHMACdFlows	Maximum number of E-DCH MAC-d flows.
maxnoofEDCHRLs	Maximum number of E-DCH RLs for one UE

9.2.2.19f HS-DSCH Serving Cell Change Information

The HS-DSCH Serving Cell Change Information IE contains information which is used in HS-DSCH Serving Cell change.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
HS-PDSCH RL ID	М		RL ID 9.2.1.49		_	
HS-DSCH Information	0		HS-DSCH FDD Information 9.2.2.19a		_	
Continuous Packet Connectivity HS-SCCH less Information	0		9.2.2.74		YES	reject
Continuous Packet Connectivity DTX-DRX Information	0		9.2.2.72		YES	reject

9.2.2.19g HS-DSCH Serving Cell Change Information Response

The *HS-DSCH Serving Cell Change Information Response* IE contains information which is used in HS-DSCH Serving Cell change.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
CHOICE Serving Cell Change					_	
>Successful					_	
>>HS-DSCH FDD Information Response	М		9.2.2.19b		_	
>>HS-DSCH-RNTI	M		9.2.1.30P		_	
>>Continuous Packet Connectivity HS-SCCH less Information Response	0		9.2.2.75		YES	Ignore
>Unsuccessful					_	
>>Cause	M		9.2.1.5		_	

9.2.2.19ga HS-DSCH Secondary Serving Cell Change Information Response

The *HS-DSCH Secondary Serving Cell Change Information Response* IE contains information which is used in HS-DSCH Secondary Serving Cell change.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Secondary Serving Cell Change				
>Successful				
>>HS-DSCH FDD	M		9.2.2.19ba	
Secondary Serving				
Information Response				
>>HS-DSCH-RNTI	M		9.2.1.30P	
>Unsuccessful				
>>Cause	M		9.2.1.5	

9.2.2.19G HS-DSCH TB Size Table Indicator

The HS-DSCH TB Size Table Indicator IE is used to indicate that octet aligned table (TS 25.321 [41]) shall be used.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
HS-DSCH TB Size Table			ENUMERATED	
Indicator			(octet aligned)	

9.2.2.19h E-DCH Serving Cell Change Information Response

The *E-DCH Serving Cell Change Information Response* IE contains information which is used in E-DCH Serving Cell change.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Serving Cell Change				
>Successful				
>>RL Information		0 <maxno< td=""><td></td><td></td></maxno<>		
Response		ofRLs>		
>>>RL ID	M		9.2.1.49	
>>>E-DCH FDD DL	M		9.2.2.4D	
Control Channel				
Information				
>Unsuccessful				
>>Cause	M		9.2.1.5	

Range bound	Explanation
maxnoofRLs	Maximum number of RLs for one UE

9.2.2.20 IB_SG_POS

Void.

9.2.2.21 IB_SG_REP

Void.

9.2.2.21a Inner Loop DL PC Status

The *Inner Loop DL PC Status* IE indicates whether inner loop DL control shall be active or inactive for all radio links for the UE Context.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Inner Loop DL PC Status			ENUMERAT	
			ED(Active,	
			Inactive)	

9.2.2.21b Initial DL DPCH Timing Adjustment Allowed

The *Initial DL DPCH Timing Adjustment Allowed* IE indicates that the DRNS is allowed to perform a timing adjustment (either a timing advance or a timing delay with respect to the SFN timing) when establishing a radio link.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Initial DL DPCH Timing			ENUMERATED (
Adjustment Allowed			initial DL DPCH	
_			Timing Adjustment	
			Allowed)	

9.2.2.21A Limited Power Increase

The parameter is used for a more efficient use of the inner loop DL power control for non real time data.

If the limited power increase is used, DRNS shall use the limited power increase algorithm as specified in TS 25.214 [10], subclause 5.2.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Limited Power Increase			ENUMERAT	
			ED(Used,	
			Not used ,)	

9.2.2.21B IPDL FDD Parameters

The IPDL FDD Parameters IE provides the information for the IPDL Configuration applied in FDD mode.

IE/Group name	Presence	Range	IE Type and Reference	Semantics Description
IP spacing FDD	M		ENUMERAT ED(5,7,10,1 5,20,30,40,5 0,)	See TS 25.214 [10]
IP length	M		ENUMERAT ED(5,10,)	See TS 25.214 [10]
IP offset	M		INTEGER(09)	See TS 25.214 [10]
Seed	M		INTEGER(063)	See TS 25.214 [10]
Burst mode parameters	0		9.2.1.4B	

9.2.2.21C Length of TFCI2

Void.

9.2.2.21D Void

9.2.2.21E Void

9.2.2.21F Void

9.2.2.22 Max Adjustment Period

Void.

9.2.2.23 Max Adjustment Step

Defines the maximum allowed value for the change of DL power level during a certain number of slots that can be utilised by the downlink power balancing algorithm. *Max Adjustment Step* IE defines a time period, in terms of number of slots, in which the accumulated power adjustments shall be maximum 1 dB. This value does not include the DL inner loop PC adjustment.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Max Adjustment Step			INTEGER (110)	Slots

9.2.2.24 Max Number of UL DPDCHs

Maximum number of uplink DPDCHs during the connection. Needed by the rate matching algorithm.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Max Number of UL DPDCHs			INTEGER (16)	

9.2.2.24a CQI Feedback Cycle k

The CQI Feedback Cycle k IE provides the duration of the CQI feedback cycle.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CQI Feedback Cycle k			ENUMERAT ED (0, 2, 4, 8, 10, 20, 40, 80, 160,, 16, 32, 64)	Unit ms The allowed values for this IE depend on the configured CQI Repetition Factor and the HS-DSCH configuration as defined in TS 25.214 [10].

9.2.2.24b CQI Power Offset

The CQI Power Offset IE indicates Power offset used in the UL between the HS-DPCCH slots carrying CQI information and the associated DPCCH.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
CQI Power Offset			INTEGER	According to mapping in TS
			(08)	25.213 [21] subclause 4.2.1.

9.2.2.24c CQI Repetition Factor

The $\emph{CQI Repetition Factor}$ IE indicates the consecutive repetition of the CQI.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
CQI Repetition Factor			INTEGER (1,4,)	Step: 1

9.2.2.24d Measurement Power Offset

The Measurement Power Offset IE is used as defined in TS 25.214 [10] subclause 6A.2.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Measurement Power Offset			INTEGER (-1226)	Unit: dB Range: -613dB Step: 0.5dB

9.2.2.24e Maximum Set of E-DPDCHs

The Maximum Set of E-DPDCHs as defined in TS 25.212 [9]. Needed by rate matching algorithm.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Maximum Set of E-DPDCHs			ENUMERATED (vN256, vN128, vN64, vN32, vN16, vN8, vN4, v2xN4, v2xN2, v2xN2plus2xN4,, v2xM2plus2xM4)	

9.2.2.24f Void

9.2.2.24A Min DL Channelisation Code Length

Void

9.2.2.25 Min UL Channelisation Code Length

Minimum UL channelisation code length (spreading factor) of a DPDCH during the connection. Needed by rate matching algorithm.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Min UL Channelisation Code			ENUMERAT	
Length			ED(4,8,16,	
			32,64,128,	
			256)	

9.2.2.26 Multiplexing Position

Multiplexing Position specifies whether fixed or flexible positions of transport channels shall be used in the physical channel.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Multiplexing Position			ENUMERAT	
			ED(Fixed,	
			Flexible)	

9.2.2.26a NACK Power Offset

The NACK Power Offset IE indicates Power offset used in the UL between the HS-DPCCH slot carrying HARQ NACK information and the associated DPCCH.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
NACK Power Offset			INTEGER (08,)	According to mapping in TS 25.213 [21] subclause 4.2.1.

9.2.2.26A Number of DL Channelisation Codes

This parameter notifies DRNS of the number of DL channelisation codes required for the Radio Link(s).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Number of DL			INTEGER	
Channelisation Codes			(18)	

9.2.2.27 Pattern Duration (PD)

Void

9.2.2.27a PC Preamble

Indicates DPDCH power control preamble length see TS 25.105 [7].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
PCP Preamble			INTEGER	In number of frames.
			(07,)	

9.2.2.27A PDSCH Code Mapping

Void.

9.2.2.27B Phase Reference Update Indicator

The Phase Reference Update Indicator IE indicates that the phase reference for the radio link needs to be changed.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Phase Reference Update indicator			ENUMERATED (Phase	
			Reference needs to be	
			changed)	

9.2.2.28 Power Adjustment Type

Defines the characteristic of the power adjustment.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Power Adjustment Type			ENUMERAT	
			ED(None,	
			Common,	
			Individual)	

9.2.2.29 Power Control Mode (PCM)

Void.

9.2.2.30 Power Offset

This IE defines a power offset relative to the Downlink transmission power of a DPCH in case the UE Context is configured to use DPCH in the downlink.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Power Offset			INTEGER	Unit dB,
			(024)	Step 0.25 dB,
				Range 06 dB

9.2.2.31 Power Resume Mode (PRM)

Void.

9.2.2.31A Preamble Signatures

Void.

9.2.2.32 Primary CPICH Ec/No

Energy per chip divided by the power density per band measured on the Primary CPICH by the terminal.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Primary CPICH Ec/No			INTEGER (-30+30)	Unit dB, step 1 dB The value range is typically within the range of -24 dB to 0 dB according to the CPICH Ec/lo UE measurement defined in TS 25.133 [23].

9.2.2.32A Primary CPICH Usage For Channel Estimation

The *Primary CPICH Usage For Channel Estimation* IE indicates whether the Primary CPICH may be used for channel estimation or not.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Primary CPICH Usage For			ENUMERATED	
Channel Estimation			(Primary CPICH	
			may be used,	
			Primary CPICH	
			shall not be	
			used)	

9.2.2.33 Propagation Delay (PD)

Propagation delay is the one-way propagation delay of the radio signal from the UE to the Node B. If the range of the *Propagation Delay* IE is insufficient to represent the measured value, it shall be set to its maximum value, and the *Extended Propagation Delay* IE (see 9.2.2.33a) shall be used to represent the propagation delay value.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Propagation Delay			INTEGER (0255)	Unit: Chips. Step: 3 chips. 0=0 chips,
				1=3 chips,

9.2.2.33a Extended Propagation Delay

The Extended Propagation delay is the one-way propagation delay of the radio signal from the MS to the Node B. It shall be used if the *Propagation Delay* IE (see 9.2.2.33) cannot represent the measured value, due to range limitation.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Extended Propagation Delay			INTEGER (2551023)	Continuation of intervals as defined in TS 25.133 [23]. Unit: chip Range: 7653069 chips Step: 3 chips

9.2.2.33A PRACH Minimum Spreading Factor

Void.

9.2.2.34 QE-Selector

Void.

9.2.2.34a Qth Parameter

Void.

9.2.2.34A RACH Sub Channel Numbers

Void.

9.2.2.35 RL Set ID

The RL Set ID uniquely identifies one RL Set within a UE Context.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
RL Set ID			INTEGER	
			(031)	

9.2.2.35a RL Specific E-DCH Information

The RL Specific E-DCH Information IE provides RL specific E-DCH Information.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
RL Specific E-DCH Information		1 <maxnoof EDCHMACd Flows></maxnoof 			_	
>E-DCH MAC-d Flow ID	М		9.2.1.91		_	
>Binding ID	0		9.2.1.3	Shall be ignored if bearer establishment with ALCAP.	-	
>Transport Layer Address	0		9.2.1.62	Shall be ignored if bearer establishment with ALCAP.	-	
>Transport Bearer Not Requested Indicator	0		9.2.2.4S		YES	ignore
E-AGCH Power Offset	0		9.2.2.61		_	
E-RGCH Power Offset	0		9.2.2.62		_	
E-HICH Power Offset	0		9.2.2.63		_	

Range Bound	Explanation	
maxnoofEDCHMACdFlows	Maximum number of E-DCH MAC-d flows	

9.2.2.35A Received Total Wide Band Power

The parameter indicates the Received total wide band power in a cell, see TS 25.215 [11].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Received Total Wide Band Power			INTEGER(0. .621)	According to mapping in TS 25.133 [23].

9.2.2.36 S-Field Length

Void.

9.2.2.36A Void

9.2.2.37 Scrambling Code Change

Void.

9.2.2.37A Scrambling Code Number

Void.

9.2.2.37B Secondary CCPCH Info

Void.

9.2.2.38 Secondary CCPCH Slot Format

Void.

9.2.2.38A Secondary CPICH Information

The Secondary CPICH Information IE provides the information on the Secondary CPICH when it can be used for channel estimation.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DL Scrambling Code	M		9.2.2.11	
FDD DL Channelisation Code Number	М		9.2.2.14	

9.2.2.38B Secondary CPICH Information Change

The Secondary CPICH Information Change IE indicates modification of information of the Secondary CPICH for channel estimation.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Secondary CPICH Information Change	М			
>New Secondary CPICH				
>>Secondary CPICH Information	М		9.2.2.38A	
>Secondary CPICH Shall Not Be Used			NULL	

9.2.2.38C Serving E-DCH RL

The Serving E-DCH RL IE indicates whether the Serving E-DCH RL is in the DRNS.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Serving E-DCH RL	M			
>Serving E-DCH RL in this DRNS				
>>Serving E-DCH RL ID	М		RL ID 9.2.1.49	
>Serving E-DCH RL not in this DRNS			NULL	

9.2.2.39 Slot Number (SN)

Void

9.2.2.39a Split Type

Void.

9.2.2.39A SRB Delay

Indicates the number of frames after the PC Preamble period during which transmission of data on some RRC Signalling Bearers shall be prohibited by UE in accordance with TS 25.331 [16].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
SRB Delay			INTEGER(0.	In number of frames.
			.7,)	

9.2.2.40 SSDT Cell Identity

Void.

9.2.2.40A SSDT Cell Identity for EDSCHPC

Void.

9.2.2.41 SSDT Cell Identity Length

Void.

9.2.2.42 SSDT Indication

Void.

9.2.2.43 SSDT Support Indicator

The possibility to use SSDT Support Indicator has been removed.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
SSDT Support Indicator			ENUMERAT ED(Not Used, SSDT	The SSDT Support Indicator IE shall never be set to "Not Used".
			not supported).	

9.2.2.44 STTD Indicator

Void.

9.2.2.45 STTD Support Indicator

The STTD Support Indicator indicates whether the STTD can be applied to DL DPCH and F-DPCH in the cell or not.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
STTD Support Indicator			ENUMERAT ED(STTD	
			Supported,	
			STTD not	
			Supported).	

9.2.2.45A Synchronisation Indicator

The *Synchronisation Indicator* IE indicates that Timing Maintained Synchronisation shall be used at start of Radio Link, see also [10].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Synchronisation Indicator			ENUMERATED	
			(Timing Maintained	
			Synchronisation,)	

9.2.2.46 TFCI Signalling Mode

This parameter indicates has only one value with any meaning.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
TFCI Signalling Mode			ENUMERAT ED(Normal, Not Used)	The value "Not Used" shall not be used by the SRNC. The procedure shall be rejected by the DRNC if the value "Not Used" is received.

9.2.2.46A TFCI PC Support Indicator

Void.

9.2.2.47 Transmission Gap Distance (TGD)

Void.

9.2.2.47A Transmission Gap Pattern Sequence Information

Defines the parameters for the compressed mode gap pattern sequence. For details see TS 25.331 [16].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Transmission Gap Pattern Sequence Information		1 <maxtgps></maxtgps>		
>TGPSI Identifier	М		INTEGER(1< MaxTGPS>)	Transmission Gap Pattern Sequence Identifier Establish a reference to the compressed mode pattern sequence. Up to <maxtgps> simultaneous compressed mode pattern sequences can be used.</maxtgps>
>TGSN	М		INTEGER(01 4)	Transmission Gap Starting Slot Number The slot number of the first transmission gap slot within the TGCFN.
>TGL1	M		INTEGER(11 4)	The length of the first Transmission Gap within the transmission gap pattern expressed in number of slots.
>TGL2	0		INTEGER(11 4)	The length of the second Transmission Gap within the transmission gap pattern. If omitted, then TGL2=TGL1.
>TGD	M		INTEGER (0, 15 269)	Transmission gap distance indicates the number of slots between the starting slots of two consecutive transmission gaps within a transmission gap pattern. If there is only one transmission gap in the transmission gap pattern, this parameter shall be set to 0 (0 = undefined).
>TGPL1	М		INTEGER(1 144,)	The duration of transmission gap pattern 1 in frames.
>Not-to-be-used-1	0		INTEGER(1 144,)	This IE shall never be included in the IE group. If received it shall be ignored.
>UL/DL mode	M		ENUMERATE D(UL only, DL only, UL/DL)	Defines whether only DL, only UL, or combined UL/DL compressed mode is used.
>Downlink Compressed Mode Method	C-DL		ENUMERATE D(not Used, SF/2, higher layer scheduling,)	Method for generating downlink compressed mode gap The Downlink Compressed Mode Method IE shall never be set to "not Used".
>Uplink Compressed Mode Method	C-UL		ENUMERATE D(SF/2, higher layer scheduling,)	Method for generating uplink compressed mode gap.
>Downlink Frame Type	М		ENUMERATE D(A, B,)	Defines if frame type "A" or "B" shall be used in downlink compressed mode.
>DeltaSIR1	М		INTEGER(03 0)	Delta in SIR target value to be set in the DRNS during the frame containing the start of the first transmission gap in the transmission gap pattern (without including the effect of the bit-rate increase)
>DeltaSIRafter1	M		INTEGER (030)	Step 0.1 dB, Range 0-3dB Delta in SIR target value to be set in the DRNS one frame after the frame containing the start of the first transmission gap in the

			transmission gap pattern,. Step 0.1 dB, Range 0-3dB
>DeltaSIR2	0	INTEGER (030)	Delta in SIR target value to be set in the DRNS during the frame containing the start of the second transmission gap in the transmission gap pattern (without including the effect of the bit-rate increase) When omitted, DeltaSIR2 = DeltaSIR1. Step 0.1 dB, Range 0-3dB
>DeltaSIRafter2	0	INTEGER (030)	Delta in SIR target value to be set in the DRNS one frame after the frame containing the start of the second transmission gap in the transmission gap pattern. When omitted, DeltaSIRafter2 = DeltaSIRafter1. Step 0.1 dB, Range 0-3dB

Condition	Explanation
UL	The IE shall be present if the <i>UL/DL mode</i> IE is set to "UL only" or
	"UL/DL".
DL	The IE shall be present if the <i>UL/DL mode</i> IE is set to "DL only" or
	"UL/DL".

Range bound	Explanation
maxTGPS	Maximum number of transmission gap pattern sequences.

9.2.2.47B Transmission Gap Pattern Sequence Scrambling Code Information

This IE indicates whether or not the alternative scrambling code will be used in the DRNS for the Downlink compressed mode method "SF/2" in the Transmission Gap Pattern Sequence. For details see TS 25.331 [16].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Transmission Gap Pattern Sequence Scrambling Code Information			ENUMERAT ED(code change, no code change)	Code change = alternative scrambling code will be used.

9.2.2.48 Transmit Diversity Indicator

The Transmit Diversity Indicator indicates whether Transmit Diversity shall be active or not.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Transmit Diversity Indicator			ENUMERAT	
-			ED(active,	
			inactive)	

9.2.2.49 Transmit Gap Length (TGL)

Void

9.2.2.50 Tx Diversity Indicator

The Tx Diversity Indicator indicates if the following conditions are satisfied:

- Primary CPICH is broadcast from two antennas
- STTD is applied to Primary CCPCH
- TSTD is applied to Primary SCH and Secondary SCH

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Tx Diversity Indicator			ENUMERAT	
-			ED(true,	
			false).	

9.2.2.50A UE Support Of Dedicated Pilots For Channel Estimation

Void.

9.2.2.50B UE Support Of Dedicated Pilots For Channel Estimation Of HS-DSCH

Void.

9.2.2.51 UL/DL Compressed Mode Selection

Void

9.2.2.52 UL DPCCH Slot Format

Indicates the slot format used in DPCCH in UL, according to TS 25.211 [8].

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
UL DPCCH Slot Format			INTEGER	Value 5 shall not be used.
			(05,)	If value 5 is received, the
				procedure shall be rejected.

9.2.2.52A UL DPDCH Indicator for E-DCH operation

This IE indicated whether the requested configuration actually contain an UL DPDCH.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
UL DPDCH Indicator for E-			ENUMERAT	
DCH operation			ED (UL-	
			DPDCH	
			present, UL-	
			DPDCH not	
			present)	

9.2.2.53 UL Scrambling Code

The UL Scrambling Code is the scrambling code used by UE. Every UE has its specific UL Scrambling Code.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
UL Scrambling Code	M		INTEGER	
Number			(0 2 ²⁴ -1)	
UL Scrambling Code Length	M		ENUMERAT	
			ED(Short,	
			Long)	

9.2.2.54 Uplink Delta SIR

Void

9.2.2.55 Uplink Delta SIR After

Void

9.2.2.56 DPC Mode Change Support Indicator

The DPC Mode Change Support Indicator IE indicates that the particular cell is capable to support DPC mode change.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DPC Mode Change Support Indicator			ENUMERATTE D (DPC Mode Change Supported)	

9.2.2.57 HARQ Preamble Mode

The HARQ Preamble Mode IE is used as described as described in TS 25.214 [10].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
HARQ Preamble Mode			ENUMERATED(mod e0, mode1)	"mode0" means HARQ Preamble Mode =0 "mode1" means HARQ Preamble Mode =1

9.2.2.58 HARQ Preamble Mode Activation Indicator

The HARQ Preamble Activation Indicator indicates if the configured HARQ Preamble Mode has been activated in the DRNS.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
HARQ Preamble Mode			ENUMERAT	
Activation Indicator			ED(HARQ	
			Preamble	
			Mode	
			Activated).	

9.2.2.59 Frequency Band Indicator

The Frequency Band Indicator IE indicates frequency band as defined in TS 25.104 [6].

IE/Group Name	Presence	Range	IE type and	Semantics description
			reference	
Frequency Band Indicator			ENUMERAT	
			ED (Band I,	
			Band II,	
			Band III,	
			Band IV,	
			Band V,	
			Band VI,	
			Band VII,	
			Band VIII,	
			Band IX,	
			Band X,	
			Band XÍ,	
			Band XII,	
			Band XIII,	
			Band XIV,	
			Band XV,	
			Band XVI,	
			Band XVII,	
			Band XVIII,	
			Band XIX,	
			Band XX,	
			Band XXI,	
			Band XXII,	
			·,	
			Reserved23,	
			Reserved24,	
			Band XXV)	

9.2.2.60 E-RGCH Release Indicator

Indicates that the E-RGCH is released..

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-RGCH Release Indicator			ENUMERATED (E- RGCH released)	

9.2.2.61 E-AGCH Power Offset

The *E-AGCH Power Offset* IE indicates the Power offset relative to the pilot bits on the DL DPCCH except when F-DPCH is configured. When F-DPCH is configured, the *E-AGCH Power Offset* IE indicates the Power offset relative to the power of transmitted TPC bits on the F-DPCH.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
E-AGCH Power Offset			INTEGER (0255,)	Unit: dB Range: -32 +31.75 dB Step: 0.25 dB

9.2.2.61A E-AGCH Table Choice

The E-AGCH Table Choice IE indicates the choice of the E-AGCH table in TS 25.212 [9].

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
E-AGCH Table Choice	М		ENUMERATED (Table 16B, Table 16B-1,)	Table 16B indicates the Table 16B: Mapping of Absolute Grant Value in [9] and Table 16B-1 indicates the Table 16B.1: Alternative Mapping of Absolute Grant Value in TS 25.212 [9].

9.2.2.62 E-RGCH Power Offset

The *E-RGCH Power Offset* IE indicates the Power offset relative to the pilot bits on the DL DPCCH except when F-DPCH is configured. When F-DPCH is configured, the *E-RGCH Power Offset* IE indicates the Power offset relative to the power of transmitted TPC bits on the F-DPCH.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-RGCH Power Offset			INTEGER (0255,)	Unit: dB Range: -32 +31.75 dB Step: 0.25 dB

9.2.2.63 E-HICH Power Offset

The *E-HICH Power Offset* IE indicates the Power offset relative to the pilot bits on the DL DPCCH except when F-DPCH is configured. When F-DPCH is configured, the *E-HICH Power Offset* IE indicates the Power offset relative to the power of transmitted TPC bits on the F-DPCH.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-HICH Power Offset			INTEGER (0255,)	Unit: dB Range: -32 +31.75 dB Step: 0.25 dB

9.2.2.64 E-RGCH 2-Index-Step Threshold

The *E-RGCH 2-index-step-threshold* IE is used to determine the Serving Grant.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-RGCH 2-Index-Step			INTEGER	Refers to an index in the "SG-
Threshold			(037)	Table" (see TS 25.321 [41]).

9.2.2.65 E-RGCH 3-Index-Step Threshold

The *E-RGCH 3-index-step-threshold* IE is used to determine the Serving Grant.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-RGCH 3-Index-Step			INTEGER	Refers to an index in the "SG-
Threshold			(037)	Table" (see TS 25.321 [41]).

9.2.2.66 HARQ Info for E-DCH

The HARQ Info for E-DCH is used to indicate the use of redundancy version (RV) for the EDCH HARQ transmissions.

IE/Group name	Presence	Range	IE Type and Reference	Semantics description
HARQ Info for E-DCH			ENUMERATED (rv0, rvtable)	"rv0" indicates that the UE will only use E_DCH RV index 0. "rvtable" indicates that the UE will use an RSN based RV index as specified in TS 25.212 [9]

9.2.2.67 DCH Indicator For E-DCH-HSDPA Operation

The DCH Indicator For E-DCH-HSDPA Operation parameter indicates whether *DCH Information* IE should be ignored in the message in which the *DCH Indicator For E-DCH-HSDPA Operation* IE is included.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DCH Indicator For E-DCH- HSDPA Operation			ENUMERATED (DCH not present)	

9.2.2.68 E-RGCH and E-HICH Channelisation Code Validity Indicator

The E-RGCH and E-HICH Channelisation Code Validity Indicator parameter indicates if the E-RGCH/E-HICH Channelisation Code IE shall be ignored in the E-DCH FDD DL Control Channel Information IE in which the E-RGCH and E-HICH Channelisation Code Validity Indicator IE was included.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
E-RGCH and E-HICH			ENUMERATED	
Channelisation Code Validity			(E-RGCH and E-	
Indicator			HICH Channelisation	
			Code not valid)	

9.2.2.69 E-DCH Minimum Set E-TFCI Validity Indicator

The *E-DCH Minimum Set E-TFCI Validity Indicator* parameter indicates if the *E-DCH Minimum Set E-TFCI* IE shall be ignored in the *E-DCH Transport Format Combination Set Information* IE in which the *E-DCH Minimum Set E-TFCI Validity Indicator* IE was included.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH Minimum Set E-TFCI			ENUMERATED	
Validity Indicator			(E-DCH Minimum	
-			Set E-TFCI not valid)	

9.2.2.70 Fast Reconfiguration Mode

The Fast Reconfiguration Mode IE is used to notify the DRNS that the SRNC would like to use the activation time "when the UE is detected on the new configuration" as the timing for the reconfiguration.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Fast Reconfiguration Mode			ENUMERATED (
			Fast)	

9.2.2.71 Fast Reconfiguration Permission

The Fast Reconfiguration Permission IE is used to indicate to the SRNC that the DRNS can apply the activation time "when the UE is detected on the new configuration" for this reconfiguration.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Fast Reconfiguration			ENUMERATED (
Permission			Allowed)	

9.2.2.72 Continuous Packet Connectivity DTX-DRX Information

The *Continuous Packet Connectivity DTX-DRX Information* IE defines the parameters used for Continuos Packet Connectivity DTX-DRX operation (see TS 25.214 [10]).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UE DTX DRX Offset	М		INTEGER (0159)	Units of subframes. Offset of the UE DTX and DRX cycles at the given TTI
Enabling Delay	M		ENUMERATED (0, 1, 2, 4, 8, 16, 32, 64, 128)	Units of radio frames
DTX Information		1		
>CHOICE E-DCH TTI Length	М			
>>2ms				
>>>UE DTX Cycle 1	М		ENUMERATED (1, 4, 5, 8, 10, 16, 20)	Units of subframes
>>>UE DTX Cycle 2	M		ENUMERATED (4, 5, 8, 10, 16, 20, 32, 40, 64, 80, 128, 160)	Units of subframes
>>>MAC DTX Cycle	М		ENUMERATED (1, 4, 5, 8, 10, 16, 20)	Units of subframes
>>10ms				
>>>UE DTX Cycle 1	M		ENUMERATED (1, 5, 10, 20)	Units of subframes
>>>UE DTX Cycle 2	M		ENUMERATED (5, 10, 20, 40, 80, 160)	Units of subframes
>>>MAC DTX Cycle	М		ENUMERATED (5, 10, 20)	Units of subframes
>Inactivity Threshold for UE DTX Cycle 2	М		ENUMERATED (1, 4, 8, 16, 32, 64, 128, 256)	Units of E-DCH TTIs
>UE DTX Long Preamble	М		ENUMERATED (2,4,15)	Units of slots
>MAC Inactivity Threshold	М		ENUMERATED (1, 2, 4, 8, 16, 32, 64, 128, 256, 512, Infinity)	Units of E-DCH TTIs
>CQI DTX Timer	M		ENUMERATED (0, 1, 2, 4, 8, 16, 32, 64, 128, 256, 512, Infinity)	Units of subframes
>UE DPCCH burst1	М		ENUMERATED (1, 2, 5)	Units of subframes
>UE DPCCH burst2	М		ENÚMERATED (1, 2, 5)	Units of subframes
DRX Information		01		
>UE DRX Cycle	М		ENUMERATED (4, 5, 8, 10, 16, 20)	Units of subframes
>Inactivity Threshold for UE DRX Cycle	М		ENUMERATED (0, 1, 2, 4, 8, 16, 32, 64, 128, 256, 512)	Units of subframes
>Inactivity Threshold for UE	M		ENUMERATED (0,	Units of E-DCH TTIs

Grant Monitoring		1, 2, 4, 8, 16, 32, 64, 128, 256)	
>UE DRX Grant Monitoring	M	BOOLEAN	True: DRX Grant Monitoring shall be applied. False: DRX Grant Monitoring shall not be applied.

9.2.2.73 Continuous Packet Connectivity DTX-DRX Information To Modify

The *Continuous Packet Connectivity DTX-DRX Information To Modify* IE is used for modification of Continuous Packet Connectivity DTX-DRX information in a UE Context. The *Continuous Packet Connectivity DTX-DRX Information To Modify* IE shall include at least one of the following IE.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UE DTX DRX Offset	0		INTEGER (0159)	Units of subframes. Offset of the UE DTX and DRX cycles at the given TTI
Enabling Delay	0		ENUMERATED (0, 1, 2, 4, 8, 16, 32, 64, 128)	Units of radio frames
CHOICE DTX Information To Modify	0			
>Modify >>CHOICE E-DCH TTI Length	0			
>>>2ms				
>>>UE DTX Cycle 1	0		ENUMERATED (1, 4, 5, 8, 10, 16, 20)	Units of subframes
>>>>UE DTX Cycle 2	0		ENUMERATED (4, 5, 8, 10, 16, 20, 32, 40, 64, 80, 128, 160)	Units of subframes
>>>MAC DTX Cycle	0		ENUMERATED (1, 4, 5, 8, 10, 16, 20)	Units of subframes
>>>10ms				
>>>UE DTX Cycle 1	0		ENUMERATED (1, 5, 10, 20)	Units of subframes
>>>UE DTX Cycle 2	0		ENUMERATED (5, 10, 20, 40, 80, 160)	Units of subframes
>>>MAC DTX Cycle	0		ENUMERATED (5, 10, 20)	Units of subframes
>>Inactivity Threshold for UE DTX Cycle 2	0		ENUMERATED (1, 4, 8, 16, 32, 64, 128, 256)	Units of E-DCH TTIs
>>UE DTX Long Preamble	0		ENUMERATED (2,4,15)	Units of slots
>>MAC Inactivity Threshold	0		ENUMERATED (1, 2, 4, 8, 16, 32, 64, 128, 256, 512, Infinity)	Units of E-DCH TTIs
>>CQI DTX Timer	0		ENUMERATED (0, 1, 2, 4, 8, 16, 32, 64, 128, 256, 512, Infinity)	Units of subframes
>>UE DPCCH burst1	0		ENUMERATED (1, 2, 5)	Units of subframes
>>UE DPCCH burst2	0		ENÚMERATED (1, 2, 5)	Units of subframes
>Deactivate				
CHOICE DRX Information To Modify	0			
>Modify				
>>UE DRX Cycle	0		ENUMERATED (4, 5, 8, 10, 16, 20)	Units of subframes
>>Inactivity Threshold for	0		ENUMERATED (0,	Units of subframes

UE DRX Cycle		1, 2, 4, 8, 16, 32, 64,	
		128, 256, 512)	
>>Inactivity Threshold for	0	ENUMERATED (0,	Units of E-DCH TTIs
UE Grant Monitoring		1, 2, 4, 8, 16, 32, 64,	
_		128, 256)	
>>UE DRX Grant	0	BOOLEAN	True = DRX Grant Monitoring
Monitoring			shall be applied.
			False = DRX Grant Monitoring
			shall not be applied.
>Deactivate		NULL	

9.2.2.74 Continuous Packet Connectivity HS-SCCH less Information

The *Continuous Packet Connectivity HS-SCCH less Information* IE defines the parameters used for Continuos Packet Connectivity HS-SCCH less operation (see TS 25.214 [10]).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Transport Block Size List		1 <maxno ofHS- DSCHTBS sHS- SCCHless ></maxno 		
>Transport Block Size Index	М		INTEGER (1maxnoofHS-DSC HTBSs)	
>HS-PDSCH Second Code Support	M		BOOLEAN	True = The second HS- PDSCH code shall also be used False = The second HS- PDSCH code shall not be used

Range Bound	Explanation
maxnoofHS-DSCHTBSsHS-SCCHless	Maximum number of HS-DSCH Transport Block Sizes used for HS-
	SCCH-less operation
maxnoofHS-DSCHTBSs	Maximum number of HS-DSCH Transport Block Sizes

9.2.2.75 Continuous Packet Connectivity HS-SCCH less Information Response

The *Continuous Packet Connectivity HS-SCCH less Information Response* IE provides information for HS-SCCH less operation determined within the Node B (see TS 25.214 [10]).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
HS-PDSCH First Code Index	M		INTEGER (1maxHS-PDSCHC odeNrComp-1)	Index of first HS-PDSCH code
HS-PDSCH Second Code Index	0		INTEGER (1maxHS-PDSCHC odeNrComp-1)	Index of second HS-PDSCH code. See Note 1.

NOTE 1: The "HS-PDSCH second code index" value is the value of IE "HS-PDSCH First Code Index" incremented by 1.

Range Bound	Explanation
maxHS-PDSCHCodeNrComp	Maximum number of codes at the defined spreading factor, within the
	complete code tree

9.2.2.75A Continuous Packet Connectivity HS-SCCH Less Deactivate Indicator

The Continuous Packet Connectivity HS-SCCH Less Deactivate Indicator IE is used to deactive HS-SCCH less operation.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Continuous Packet	M		NULL	
Connectivity HS-SCCH Less				
Deactivate Indicator				

9.2.2.76 MIMO Activation Indicator

Void

9.2.2.77 MIMO Mode Indicator

Void

9.2.2.78 MIMO Information Response

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Pilot Configuration	M			
>Primary and Secondary CPICH				
>>MIMO S-CPICH Channelisation Code	М		INTEGER (0255)	
>Normal and Diversity Primary CPICH			NULL	
MIMO N/M Ratio	М		ENUMERATED (1/2, 2/3, ¾, 4/5, 5/6, 6/7, 7/8, 8/9, 9/10, 1/1,)	

9.2.2.79 SixtyfourQAM DL Support Indicator

Void.

9.2.2.79A Sixtyfour QAM Usage Allowed Indicator

The Sixtyfour QAM Usage Allowed Indicator IE indicates whether the Node B is allowed to use 64 QAM modulation for HS-DSCH transmission or not.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Sixtyfour QAM Usage Allowed	М		ENUMERATED	
Indicator			(Allowed, Not-	
			Allowed)	

9.2.2.79B SixtyfourQAM DL Usage Indicator

The SixtyfourQAM DL Usage Indicator IE indicates if the Node B is using 64 QAM modulation for the HS-DSCH transmission, or if the Node B is not using 64 QAM modulation.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
SixtyfourQAM DL Usage Indicator			ENUMERATED (SixtyfourQAM DL Used, SixtyfourQAM DL Not Used)	

9.2.2.80 Enhanced FACH Support Indicator

Void.

9.2.2.81 Enhanced PCH Support Indicator

Void.

9.2.2.82 Priority Queue Information for Enhanced FACH/PCH

Void.

9.2.2.83 SixteenQAM UL Information

Void.

9.2.2.84 SixteenQAM UL Information To Modify

Void.

9.2.2.85 F-DPCH Slot Format

The F-DPCH Slot Format IE defines the F-DPCH slot format for the TPC bits, as defined in TS 25.211 [8].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
F-DPCH Slot Format			INTEGER (09)	

9.2.2.86 F-DPCH Slot Format Support Request

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
F-DPCH Slot Format Support			NULL	
Request				

9.2.2.87 Max UE DTX Cycle

The *Max UE DTX Cycle* IE defines the maximum UE DTX cycle supported by the Node B for Continuous Packet Connectivity DTX-DRX operation.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Max UE DTX Cycle	M		ENUMERATED (v5,	Units of subframes
			v10, v20, v40, v64,	
			v80. v128. v160)	

9.2.2.88 Enhanced PCH Capability

Void.

9.2.2.89 MAC-ehs Reset Timer

Void.

9.2.2.90 SixteenQAM UL Operation Indicator

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
SixteenQAM UL Operation	0		ENUMERATED	
Indicator			(Activate,	
			Deactivate)	

9.2.2.91 E-TFCI Boost Information

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-TFCI BetaEC Boost	M		INTEGER (0127,)	E-TFCI threshold beyond which boosting of E-DPCCH is enabled
UL Delta T2TP	C-E- TFClboost 127		INTEGER (06,)	Total E-DPDCH power across all codes to the combined power of DPCCH and E-DPCCH

Condition	Explanation		
E-TFClboost127	The IE shall be present if the E-TFCI BetaEC Boost		
	IE value is not set o 127.		

9.2.2.92 Common E-DCH Support Indicator

This IE indicates the Common E-DCH Support.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Common E-DCH Support Indicator			NULL	

9.2.2.93 Common E-DCH MAC-d Flow Specific Information

The *Common E-DCH MAC-d Flow Specific Information* IE provides information associated to Common E-DCH MAC-d Flow used for Common E-DCH.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Common E-DCH MAC-d Flow Specific Information		1 <maxno ofEDCHM ACdFlows</maxno 		
>Common E-DCH MAC-d Flow ID	М	>	E-DCH MAC-d flow	
>Maximum Number Of Retransmissions For E-DCH	М		9.2.1.100	
>E-DCH HARQ Power Offset FDD	M		9.2.2.4L	
>E-DCH MAC-d Flow Multiplexing List	0		9.2.1.89	
>Common E-DCH Logical Channel information	M	1 <maxno oflogicalch annels></maxno 		
>>Logical Channel ID	M		9.2.1.97	
>>Maximum MAC-d PDU Size Extended	M		MAC PDU Size Extended 9.2.1.34D	

Range bound	Explanation
maxnoofEDCHMACdFlows	Maximum number of E-DCH MAC-d Flows
maxnooflogicalchannels	Maximum number of logical channels

9.2.2.94 Counting Information

The Counting Information IE provides counting result for MBMS service for each cell.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Counting Information		1 <maxno ofFDDneig hbours></maxno 		
>C-ID	M		9.2.1.6	
>Counting Result	М		INTEGER (063)	The number of Ues listen to the MBMS Service. If the number of the UE is more than 63, this IE set to 63.

Range bound	Explanation
maxnoofFDDneighbours	Maximum number of neighbouring FDD cell for one cell.

9.2.2.95 Transmission Mode Information

The Transmission Mode Information IE provides transmission mode for MBMS service for each cell.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Counting Information		1 <maxno ofFDDneig hbours></maxno 		
>C-ID	M		9.2.1.6	
>Transmission Mode	M		9.2.1.81	

Range bound	Explanation
maxnoofFDDneighbours	Maximum number of neighbouring FDD cell for one cell.

9.2.2.96 MBMS Neighbouring Cell Information

The parameter contains information for the MBMS p-t-m radio bearer configuration procedure as defined in TS 25.331 [16].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
MBMS Neighbouring Cell Information				
>MBMS Concatenated Service List		1 <maxlen gthMBMSco ncatservlist s ></maxlen 		TMGI shall be uniquely defined by a reference to this index from the <i>MBMS short</i> transmission identity IE (TS 25.331 [16]) in the <i>L3</i> Information IE.
>>TMGI	М		9.2.1.80	
>L3 Information	0		9.2.1.32	The IE Contains MBMS COMMON P-T-M RB INFORMATION defined in TS 25.331 [16].
>L3 Information	0		9.2.1.32	The IE Contains MBMS CURRENT CELL P-T- M RB INFORMATION defined in TS 25.331 [16].

Range bound	Explanation
maxlengthMBMSconcatservlists	Maximum length of the concatenated service lists contained in MBMS
	MODIFIED SERVICES INFORMATION and the MBMS UNMODIFIED SERVICES INFORMATION messages defined in TS 25.331 [16]

9.2.2.97 RLC Sequence Number

This parameter indicates the RLC Sequence Number.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
RLC Sequence Number			INTEGER (0127)	

9.2.2.98 Time Stamp

This parameter indicates the Time Stamp used for Inter-RNC MBMS synchronisation.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Time Stamp			INTEGER (09999)	Units: 10ms

9.2.2.99 HS-DSCH Preconfiguration Info

The *HS-DSCH Preconfiguration Info* IE provides information of the target cell preconfiguration in the DRNS as defined in TS 25.331 [16].

IE/Group Name	Presence	Range	IE Type	Semantics Description	Criticality	Assigned
			and Reference			Criticality
Sets of HS-SCCH Codes		1 <max noofHSD SCH></max 	Reference	Index 1 refers to the serving HS-DSCH cell Index 2 <maxnoofhsdsch> refer to secondary serving HS-DSCH cells in the order as listed in 9.2.2.100 HS-DSCH Preconfiguration Setup. Max index is 4 in this 3GPP release.</maxnoofhsdsch>	Ŧ	
>HS-SCCH Preconfigured Codes		1 <maxn oofHSSC CHcodes</maxn 			-	
>>Code Number	М		INTEGER (0127)		_	
>HS-DSCH- RNTI	М		9.2.1.31J		-	
>HS-PDSCH And HS-SCCH Scrambling Code	М		DL Scramblin g Code 9.2.2.11		-	
>SixtyfourQAM DL Support Indicator	0		9.2.1.123		_	
>SixtyfourQAM DL Usage Indicator	0		9.2.2.79B		-	
>HS-DSCH TB Size Table Indicator	0		9.2.2.19G		_	
>MIMO Information Response	0		9.2.2.78	Applicable for multicarrier mode of operation.	YES	ignore
>Power Offset For S-CPICH for MIMO	0		9.2.2.104	Applicable for multicarrier mode of operation. The "Power Offset For S-CPICH for MIMO" in the index 1 of "Sets of HS-SCCH Codes" shall be ignored.	YES	ignore
>Measurement Power Offset	0		9.2.2.24d		YES	ignore
HARQ Memory Partitioning	М		9.2.1.116		-	
E-DCH FDD DL Control Channel Information	0		9.2.2.4D	For the primary UL frequency in Dual-cell E-DCH mode of operation.	ı	
HARQ Preamble Mode Activation Indicator	0		9.2.2.58		-	
MIMO Information Response	0		9.2.2.78	Only applicable for MIMO in singe carrier mode of operation. Shall be ignored in multicarrier mode of operation.	-	
Continuous Packet Connectivity HS- SCCH less Information Response	0		9.2.2.75	·	-	
Power Offset For S- CPICH for MIMO	0		9.2.2.104	For the serving HS-DSCH cell in both the single carrier mode and	YES	ignore

				multicarrier mode of		
				operation.		
Additional E-DCH		0 <maxn< td=""><td></td><td>For E-DCH on multiple</td><td>EACH</td><td>ignore</td></maxn<>		For E-DCH on multiple	EACH	ignore
Preconfiguration		oofEDCH		frequencies in this DRNS.		_
Information		-1>		E-DCH on Secondary		
				uplink frequency – max 1		
				in this 3GPP release.		
				Index 1 correspond to the		
				secondary serving HS-		
				DSCH cells with index 2		
				in the IE Sets of HS-		
				SCCH Codes. The list is		
				in the order as listed in		
				9.2.2.100 HS-DSCH		
				Preconfiguration Setup.		
>E-DCH FDD DL	M		9.2.2.4D	For the secondary UL	_	
Control Channel				frequency In Dual-cell E-		
Information				DCH mode of operation.		
Support of dynamic	0		9.2.2.129		YES	ignore
DTXDRX related						
HS-SCCH order						

Range bound	Explanation
maxnoofHSSCCHcodes	Maximum number of HS-SCCH codes
maxnoofHSDSCH	Maximum number of Primary Serving plus Secondary Serving HS-DSCH cells for one UE
maxnoofEDCH-1	Maximum number of uplink frequencies -1 for E-DCH for one UE

9.2.2.100 HS-DSCH Preconfiguration Setup

The *HS-DSCH Preconfiguration Setup* IE indicates that the DRNS shall preconfigure set(s) of HS-SCCH codes and may contain a list of secondary serving HS-DSCH cells to be preconfigured for Enhanced Service Cell Change. The Cell Change procedure for Dual Cell operation is described in TS 25.308 [63]

IE/Group Name	Prese nce	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
MAC-hs/ehs reset scheme	M		ENUMERAT ED (Always, Inter NodeB Change)	MAC-hs/ehs reset handling at enhanced HS serving cell change: "Always" means always reset "Inter NodeB Change" means Only reset at inter Node B cell change	-	
HS-DSCH Physical Layer Category	М		9.2.1.30Oa		_	
MAC-hs Reordering Buffer Size for RLC-UM	М		9.2.1.34Ab		_	
Secondary Cells		0 <maxn oofHSDS CH-1></maxn 		Preconfigured secondary serving HS-DSCH cell. maxnoofHSDSCH-1 is max 3 in this 3GPP release.	-	
>Secondary C-ID	М		9.2.1.9	C-ID of the preconfigured secondary serving HS-DSCH cell	-	
>Num Secondary HS- SCCH Codes	0		INTEGER (1maxnoofH SSCCHcode s)	For the secondary serving HS-DSCH cell	-	
>Sixtyfour QAM Usage Allowed Indicator	0		9.2.2.79A	For the secondary serving HS-DSCH cell	_	
>MIMO Activation Indicator	0		9.2.1.134	For the secondary serving HS-DSCH cell	YES	ignore
>E-DCH Indicator	0		NULL	The secondary serving HS-DSCH cell shall be preconfigured with E-DCH.	YES	ignore
>Power Offset For S- CPICH for MIMO Request Indicator	0		9.2.2.105	For the secondary serving HS-DSCH cell	YES	ignore
>Ordinal Number Of Frequency	0		INTEGER (132,)	Value = "1" indicates 1st secondary serving HS-DSCH cell, Value = "2" indicates 2nd secondary serving HS-DSCH cell etc. TS 25.214 [10]. The IE shall be ignored by the Node B if the new configuration contains one secondary serving radio link.	YES	ignore
Num Primary HS-SCCH Codes	0		INTEGER (1 maxnoofHSS CCHcodes)	For the primary serving HS-DSCH cell	-	
MIMO Activation Indicator	0		9.2.1.134 9.2.1.134	In multicarrier mode of operation the IE is for the serving HS- DSCH cell	<u> </u>	
HS-DSCH MAC-d PDU Size Format	0		9.2.1.30OC	If not present, "Indexed MAC-d PDU Size" shall be assumed.	_	

Sixtyfour QAM Usage Allowed Indicator	0	9.2.2.79A	For the serving HS- DSCH cell	_	
UE with enhanced HS- SCCH support indicator	0	NULL	UE supports enhanced HS-SCCH functionality: - UE supports different HS-SCCH in consecutive TTIs and, - in HS-SCCH-less operation mode the UE supports HS- SCCH orders	-	
Continuous Packet Connectivity HS-SCCH less Information	0	9.2.2.74		_	
UE Support Indicator Extension	0	9.2.2.103		YES	ignore
Power Offset For S- CPICH for MIMO Request Indicator	0	9.2.2.105	For the serving HS- DSCH cell in both the single carrier mode and multicarrier mode of operation.	YES	ignore

Range bound	Explanation		
maxnoofHSDSCH-1	Maximum number of Secondary Serving HS-DSCH cells for one UE		
maxnoofHSSCCHcodes	Maximum number of HS-SCCH codes		

9.2.2.101 Secondary Serving Cell List

This *Secondary Serving Cell List* IE identifies the possible secondary serving HS-DSCH cells for a Multi Cell/Dual-Band capable cell that is able to serve as a serving HS-DSCH cell.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Possible Secondary Serving Cell List		1 <maxnoof HSDSCH-1></maxnoof 		For secondary serving HS-DSCH cell.	_	
>Possible Secondary Serving Cell	M		C-ID 9.2.1.9		_	
>Multicell E-DCH Restriction	0		BOOLEAN	TRUE means restricted FALSE or not included means no restrictions	YES	ignore

Range bound	Explanation				
maxnoofHSDSCH-1	Maximum number of Secondary Serving HS-DSCH cells for one UE.				
	See NOTE below.				
NOTE: In this case, "maxnoofHSDSCH-1" represents the maximum number of possible secondary serving cells					
for a Multi Cell/Dual-Band capable cell.					

9.2.2.102 Minimum Reduced E-DPDCH Gain Factor

The minimum gain factor ($\beta_{ed,k,reduced,min}$) defined in TS 25.214 [10].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Minimum Reduced E-DPDCH Gain Factor			ENUMERATED (8/15, 11/15, 15/15, 21/15, 30/15, 42/15,	
			60/15, 84/15,)	

9.2.2.103 UE Support Indicator Extension

The *UE Support Indicator Extension* IE is used to indicate the support level in the UE for optional HSDPA functions to the DRNS.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UE support indicator extension			BIT STRING (32)	Each bit indicates whether the UE supports a particular HSDPA function or not. The value 1 of a bit indicates that the corresponding functionality is supported in the UE and value 0 indicates that the corresponding functionality is not supported in the UE. Each bit is defined as follows: the first bit: Different HS-SCCH In Consecutive TTIs Support Indicator, the second bit: HS-SCCH orders in HS-SCCH-less Operation Support Indicator, the third bit: RRC Rel-9 (onwards) handling of DL secondary HS-DSCH (de)activation state Support Indicator, the fourth bit: UE DTXDRX related HS-SCCH orders uniform behavior indicator. Note that undefined bits are considered as a spare bit and spare bits shall be set to 0 by the transmitter and shall be ignored by the receiver.

9.2.2.104 Power Offset For S-CPICH for MIMO

The *Power Offset For S-CPICH for MIMO* IE indicates the the relative transmit power of the S-CPICH compared to the primary CPICH transmit power, when S-CPICH is used as a phase reference for a second transmit antenna in MIMO mode TS 25.214 [10].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Power Offset For S-CPICH for MIMO			INTEGER(-6 0)	Offset in dB

9.2.2.105 Power Offset For S-CPICH for MIMO Request Indicator

The *Power Offset For S-CPICH for MIMO Request Indicator* IE is present when the SRNC needs the DRNS to supply, if possible, the *Power Offset For S-CPICH for MIMO* IE when S-CPICH is used as a phase reference for a second transmit antenna in MIMO mode TS 25.214 [10].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Power Offset For S-CPICH for			NULL	
MIMO Request Indicator				

9.2.2.106 Single Stream MIMO Activation Indicator

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Single Stream MIMO	M		NULL	
Activation Indicator				

9.2.2.107 Single Stream MIMO Mode Indicator

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Single Stream MIMO Mode			ENUMERATED	
Indicator			(Activate,	
			Deactivate)	

9.2.2.108 HS-DSCH MAC-ehs Format

Void.

9.2.2.109 Activation Information

The *Activation Information* IE defines the local activation state of the secondary uplink frequency of the UE in Dual Cell E-DCH operation.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Activation Information		1 <maxnoo< th=""><th>For secondary E-</th><th></th></maxnoo<>	For secondary E-	
		fEDCH-1>	DCH. Max 1 in this	
			3GPP release.	
>Uu Activation State	M		ENUMERATED	The activation state of the
			(Activated,	secondary UL frequency
			De-activated,)	

Range Bound	Explanation
maxnoofEDCH-1	Maximum number of uplink frequencies -1 for E-DCH for one UE

9.2.2.110 Additional E-DCH FDD Setup Information

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
UL DPCH Information		1			_	
>UL Scrambling Code	M		9.2.2.53		_	
>UL SIR Target	0		UL SIR 9.2.1.69		_	
Additional E-DCH RL Specific Information To Setup	M		9.2.2.115		_	
Additional E-DCH FDD	0		9.2.2.112		_	
Information						
F-DPCH Information		1			_	
>FDD TPC DL Step Size	M		9.2.2.16		_	
>Limited Power Increase	М		9.2.2.21A		_	
>Inner Loop DL PC Status	М		9.2.2.21a		_	
>F-DPCH Slot Format Support Request	0		9.2.2.86		_	
Multicell E-DCH Information	0		9.2.2.114		YES	ignore

9.2.2.111 Additional E-DCH Configuration Change Information

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
UL DPCH Information		01			_	
>UL Scrambling Code	0		9.2.2.53		_	
>UL SIR Target	0		UL SIR 9.2.1.69		_	
Additional E-DCH RL Specific Information To Add	0		9.2.2.116	Used when the E-DCH RL to add does not exist in the current UE context on the secondary UL frequency.	_	
Additional E-DCH RL Specific Information To Modify	0		9.2.2.117	Used when an existing E-DCH RL on the secondary UL frequency is modified.	_	
Additional E-DCH FDD Information To Modify	0		Additional E- DCH FDD Information 9.2.2.112	Used to modify the current additional E-DCH configuration with or without a new RL added in this procedure	_	
F-DPCH Information		01			_	
>FDD TPC DL Step Size	M		9.2.2.16		_	
>Limited Power Increase	M		9.2.2.21A		_	
>Inner Loop DL PC Status	M		9.2.2.21a		_	
>F-DPCH Slot Format Support Request	0		9.2.2.86		_	
Multicell E-DCH Information	0		9.2.2.114		YES	ignore

9.2.2.112 Additional E-DCH FDD Information

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Additional E-DCH FDD Information				
>HARQ Process Allocation For 2ms Scheduled Transmission Grant	0		HARQ Process Allocation for 2ms TTI 9.2.2.40	
>E-DCH Maximum Bitrate	0		9.2.2.4MG	
>E-DCH Processing Overload Level	0		9.2.1.95	
>E-DCH Minimum Set E- TFCI	0		INTEGER (0127)	For the concept of "E-DCH Minimum Set of TFCs" see TS 25.321 [41] and TS 25.331 [16].

9.2.2.113 Multicell E-DCH Transport Bearer Mode

This parameter indicates the Multicell E-DCH Transport Bearer Mode. For *Multicell E-DCH Transport Bearer Mode* = "Separate Iur Transport Bearer Mode" the Mac-d flows from each carrier uses different Iur transport bearers, for *Multicell E-DCH Transport Bearer Mode* = "UL Flow Multiplexing Mode" the Mac-d flows received on the different carriers in the DRNS is multiplexed on one Iur transport bearer (per Mac-d flow). The SRNC should apply the stored cell capabilities for the cell on primary UL frequency for the capabilities related to Multicell E-DCH Transport Bearer Mode.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Multicell E-DCH Transport			ENUMERATED	
Bearer Mode			(Separate lur	
			Transport Bearer	
			Mode, UL Flow	
			Multiplexing Mode)	

9.2.2.114 Multicell E-DCH Information

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DL Power Balancing Information	0		9.2.2.10A	
Minimum Reduced E-DPDCH Gain Factor	0		9.2.2.102	
Secondary UL Frequency Activation State	0		ENUMERATED (Activated, Deactivated,)	
F-DPCH Slot Format	0		9.2.2.85	
Common DL Reference Power	0		DL power 9.2.1.21A	Power on F-DPCH

9.2.2.115 Additional E-DCH RL Specific Information To Setup

IE/Group Name	Presence	Range	IE Type and	Semantics	Criticality	Assigned
E-DCH Additional RL Specific Information		1 <maxn oofEDCH RLs></maxn 	Reference	Description	_	Criticality
>E-DCH Additional RL ID	М		RL ID 9.2.1.49		_	
>C-ID	0		9.2.1.6		_	
>First RLS Indicator	М		9.2.2.16A		_	
>Propagation Delay	0		9.2.2.33		_	
>Initial DL Tx Power	0		DL Power 9.2.1.21A			
>Primary CPICH Ec/No	0		9.2.2.32		_	
>E-AGCH Power Offset	0		9.2.2.61		_	
>E-RGCH Power Offset	0		9.2.2.62		_	
>E-HICH Power Offset	0		9.2.2.63		_	
>Additional E-DCH MAC-d Flow Specific Information	0		9.2.2.118		-	
>Multicell E-DCH RL Specific Information	0		9.2.2.119		YES	ignore

Range bound	Explanation
maxnoofEDCHRLs	Maximum number of E-DCH RLs for one UE

9.2.2.116 Additional E-DCH RL Specific Information To Add

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
E-DCH Additional RL Specific Information To Add		1 <maxn oofEDCH RLs></maxn 			_	
>E-DCH Additional RL ID	M		RL ID 9.2.1.49		_	
>C-ID	М		9.2.1.6		_	
>Primary CPICH Ec/No	0		9.2.2.32		_	
>E-AGCH Power Offset	0		9.2.2.61		-	
>E-RGCH Power Offset	0		9.2.2.62		_	
>E-HICH Power Offset	0		9.2.2.63		_	
>Additional E-DCH MAC-d Flow Specific Information	0		9.2.2.118		_	
>Multicell E-DCH RL Specific Information	0		9.2.2.119	_	YES	ignore

Range bound	Explanation
maxnoofEDCHRLs	Maximum number of E-DCH RLs for one UE

9.2.2.117 Additional E-DCH RL Specific Information To Modify

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
E-DCH Additional RL Specific Information to Modify		1 <maxno ofEDCHRL s></maxno 			ı	
>E-DCH Additional RL ID	M		RL ID 9.2.1.49		_	
>E-AGCH Power Offset	0		9.2.2.61		_	
>E-RGCH Power Offset	0		9.2.2.62		_	
>E-HICH Power Offset	0		9.2.2.63		_	
>Additional E-DCH MAC-d Flow Specific Information	0		9.2.2.118		-	
>Multicell E-DCH RL Specific Information	0		9.2.2.119		YES	ignore

Range bound	Explanation
maxnoofEDCHRLs	Maximum number of E-DCH RLs for one UE

9.2.2.118 Additional E-DCH MAC-d Flow Specific Information

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Additional E-DCH MAC-d Flow Specific Information		1 <maxno ofEDCHM ACdFlows ></maxno 		
>E-DCH MAC-d Flow ID	M		9.2.1.91	
>Binding ID	0		9.2.1.3	
>Transport Layer Address	0		9.2.1.62	

Range Bound	Explanation
maxnoofEDCHMACdFlows	Maximum number of E-DCH MAC-d flows

9.2.2.119 Multicell E-DCH RL Specific Information

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Extended Propagation Delay	0		9.2.2.33a	
Enhanced Primary CPICH Ec/No	0		9.2.2.131	
DL Reference Power	0		DL power 9.2.1.21A	
Phase Reference Update Indicator	0		9.2.2.27B	
E-DCH DL Control Channel Grant	0		NULL	

9.2.2.120 Additional E-DCH FDD Information Response

The Additional E-DCH FDD Information Response IE provides information for new E-DCH radio links on the secondary UL frequency.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Additional E-DCH RL		1 <maxno< td=""><td></td><td></td></maxno<>		
Information Response		ofEDCHRL s>		
>E-DCH Additional RL ID	M		RL ID 9.2.1.49	
>Received Total Wide Band Power	M		9.2.2.35A	
>DL Power Balancing Activation Indicator	0		9.2.2.10B	
>RL Set ID	М		9.2.2.35	
>E-DCH RL Set ID	M		RL Set ID 9.2.2.35	
>E-DCH FDD DL Control Channel Information	М		9.2.2.4D	
>DL Code Information	M		FDD DL Code Information 9.2.2.14A	
>Additional E-DCH MAC-d Flow Specific Information Response		0 <maxno ofEDCHM ACdFlows ></maxno 		
>>E-DCH MAC-d Flow ID	М		9.2.1.91	
>>Binding ID	0		9.2.1.3	
>>Transport Layer Address	0		9.2.1.62	
>HARQ Process Allocation For 2ms Scheduled Transmission Grant	0		HARQ Process Allocation for 2ms TTI 9.2.2.40	
>Maximum Uplink SIR	М		Uplink SIR 9.2.1.69	
>Minimum Uplink SIR	М		Uplink SIR 9.2.1.69	
>Maximum Allowed UL Tx Power	М		9.2.1.35	
>Maximum DL TX Power	М		DL Power 9.2.1.21A	
>Minimum DL TX Power	M		DL Power 9.2.1.21A	
>Primary Scrambling Code	0		9.2.1.45	
>UL UARFCN	0		UARFCN 9.2.1.66	Corresponds to Nu in TS 25.104 [6]
>DL UARFCN	0		UARFCN 9.2.1.66	Corresponds to Nd in TS 25.104 [6]
>Primary CPICH Power	М		9.2.1.44	
>PC Preamble	M		9.2.2.27a	
>Primary CPICH Usage For	0		9.2.2.32A	
Channel Estimation				
>Secondary CPICH Information	0		9.2.2.38A	
>F-DPCH Slot Format	0	1	9.2.2.85	

Range bound	Explanation
maxnoofEDCHRLs	Maximum number of E-DCH RLs for one UE

9.2.2.121 Additional Modified E-DCH FDD Information Response

The Additional Modified E-DCH RL Information Response IE provides information for RLs on the secondary UL frequency that has been modified and existied in the UE Context configuration before the reconfiguration procedure.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Additional Modified E-DCH		1 <maxno< td=""><td></td><td></td></maxno<>		
RL Information Response		ofEDCHRL		
		s>>		
>E-DCH Additional RL ID	M		RL ID 9.2.1.49	
>DL Power Balancing Updated Indicator	0		9.2.2.10D	
>E-DCH FDD DL Control	0		9.2.2.4D	
Channel Information				
>Additional E-DCH MAC-d Flow Specific Information Response		0 <maxno ofEDCHM ACdFlows</maxno 		
•		>	0.04.04	
>>E-DCH MAC-d Flow ID	M		9.2.1.91	
>>Binding ID	0		9.2.1.3	
>>Transport Layer Address	0		9.2.1.62	
>HARQ Process Allocation	0		HARQ Process	
For 2ms Scheduled			Allocation for 2ms	
Transmission Grant			TTI 9.2.2.4O	
>Maximum Uplink SIR	0		Uplink SIR 9.2.1.69	
>Minimum Uplink SIR	0		Uplink SIR 9.2.1.69	
>Maximum DL TX Power	0		DL Power 9.2.1.21A	
>Minimum DL TX Power	0		DL Power 9.2.1.21A	
>Primary CPICH Usage For Channel Estimation	0		9.2.2.32A	
>Secondary CPICH Information Change	0		9.2.2.38B	
>F-DPCH Slot Format	0		9.2.2.85	

Range bound	Explanation
maxnoofEDCHRLs	Maximum number of E-DCH RLs for one UE

9.2.2.122 Additional E-DCH FDD Update Information

IE/Group Name	Presenc e	Range	IE Type and Reference	Semantics Description
HARQ Process Allocation For 2ms Scheduled Transmission Grant	0		HARQ Process Allocation for 2ms TTI 9.2.2.40	
Additional E-DCH DL Control Channel Change Information		0 <max noofED CHRLs ></max 		
> E-DCH Additional RL ID	М		RL ID 9.2.1.49	

Range bound	Explanation
maxnoofEDCHRLs	Maximum number of E-DCH RLs for one UE

9.2.2.123 Cell Capability Container Extension FDD

The Cell Capability Container Extension FDD IE is an extension to the Cell Capability Container FDD IE and indicates the cell capability in the same way as Cell Capability Container Extension FDD IE.

The cell capability of multi-cell related functions may depend on that the cell is multi-cell capable (adjacent carrier) or Dual Band capable. Such support indicators in this *Cell Capability Container Extension FDD* IE shall be ignored by the SRNC if the cell does not have the required support indicated in the *Cell Capability Container FDD* IE: Multi Cell Support Indicator = "1" and/or Dual Band Support Indicator = "1". Support indicators that depend on multi-cell (adjacent carrier) support are indicated in the table below with /Adjacent-carrier/. Support indicators that depend on Dual Band support are indicated in the table below with /Dual-band/. Support indicators that depend on that the cell supports one or both of multi-cell (adjacent carrier) and Dual Band are indicated in the table below with /Multi-cell/. The marked support indicators indicate the support regardless of the supported multi-cell type in a multicell configuration: supported multi-cell type is - both serving HS-DSCH and secondary serving HS-DSCH, - secondary serving HS-DSCH or - serving HS-DSCH.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
IE/Group Name Cell Capability Container Extension FDD	Presence	Range	IE Type and Reference BIT STRING (128)	Each bit indicates whether a cell supports a particular functionality or not. The value 1 of a bit indicates that the corresponding functionality is supported in a cell and value 0 indicates that the corresponding functionality is not supported in a cell. Each bit is defined as follows. The first bit: Cell Specific Tx Diversity Handling For Multi Cell Operation Support Indicator, /Multi-cell/. The second bit: Multi Cell and MIMO Support Indicator, /Adjacent-carrier/. The third bit: Multi Cell and Single Stream MIMO Support Indicator, /Adjacent-carrier/. The fourth bit: Multi Cell E-DCH Support Indicator, /Adjacent-carrier/. This bit shall be ignored by the SRNC if the fifth bit: Separate lur Transport Bearer Support Indicator = "0" and the sixth bit: E-DCH UL Flow Multiplexing Support Indicator, /Adjacent-carrier/. This bit shall be ignored by the SRNC if the fourth bit: Multi Cell E-DCH Support Indicator, /Adjacent-carrier/. This bit shall be ignored by the SRNC if the fourth bit: Multi Cell E-DCH Support Indicator = "0" The sixth bit: E-DCH UL Flow Multiplexing Support Indicator = "0" The sixth bit: E-DCH UL Flow Multiplexing Support Indicator, /Adjacent-carrier/. This bit shall be ignored by the sixth bit: E-DCH UL Flow Multiplexing Support Indicator, /Adjacent-carrier/. This bit shall be ignored by
				The fifth bit: Separate Iur Transport Bearer Support Indicator, /Adjacent-carrier/. This bit shall be ignored by the SRNC if the fourth bit: Multi Cell E-DCH Support Indicator = "0" The sixth bit: E-DCH UL Flow Multiplexing Support Indicator, /Adjacent-carrier/.
				the SRNC if the fourth bit: Multi Cell E-DCH Support Indicator = "0" The seventh to eleventh bit: Maximum No of HSDPA Frequencies Support Indicator, /Multi-cell/. This support indicator is coded as the binary representation of the maximum number of HSDPA
				frequencies, with the seventh bit as the MSB and the eleventh bit as the LSB. Hexadecimal digit 0 means no support for 4C-HSDPA. Hexadecimal digits 1 and 2 are reserved. The twelfth bit: Dual Band and MIMO Support Indicator, /Dual Band/. The thirteenth bit: HSDPA 3 or 4 Carrier and MIMO

	Single Band Support Indicator, /Adjacent-carrier/ The fourteenth bit: HSDPA 3 or 4 Carrier and MIMO Dual Band Support Indicator, /Dual Band/. The fifteenth bit: Dual band and Single Stream MIMO Support Indicator,/Dual Band/. The sixteenth bit: HSDPA 3 or 4 Carrier and Single Stream MIMO Single Band Support Indicator, /Adjacent-Carrier/. The seventeenth bit: HSDPA 3 or 4 Carrier and Single Stream MIMO Dual Band Support Indicator,/Dual Band/. The eighteenth bit: Frequency Specific Compress Mode Capability/Multi-cell/. Note that undefined bits are considered as a spare bit and spare bits shall be set to
	considered as a spare bit

9.2.2.124 Non-Serving RL Preconfiguration Setup

The *Non-Serving RL Preconfiguration Setup* IE indicates that the DRNS may preconfigure E-DCH DL Code Information configured for new non-serving RL for Enhanced Service Cell Change and contains the information for the location of new serving RL after the Enhanced Serving Cell Change.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
CHOICE new Serving RL	M				_	
>New Serving RL in the DRNS			NULL		_	
>New Serving RL Not in the DRNS			NULL		_	
>New Serving RL in the DRNS or New Serving RL Not in the DRNS			NULL		-	
Additional E-DCH Non- Serving RL Preconfiguration Setup	0		NULL		YES	ignore

9.2.2.125 Non-Serving RL Preconfiguration Info

The *Non-Serving RL Preconfiguration Info* IE provides information for the new non-serving RL after Enhanced Serving Cell Change.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
New non-serving RL E-DCH FDD DL Control Channel Information A	0		9.2.2.4D E-DCH FDD DL Control Channel Information	E-DCH FDD DL Control Channel Information for non- serving RL in Serving E- DCH RLS	_	
New non-serving RL E-DCH FDD DL Control Channel Information B	0		9.2.2.4D E-DCH FDD DL Control Channel Information	E-DCH FDD DL Control Channel Information for non- serving RL in non serving E-DCH RLS in in case serving RL is in the DRNS	-	
New non-serving RL E-DCH FDD DL Control Channel Information C	0		9.2.2.4D E-DCH FDD DL Control Channel Information	E-DCH FDD DL Control Channel Information for non- serving RL in case serving RL is not in the DRNS	-	
Additional E-DCH New non-serving RL E-DCH FDD DL Control Channel Information		0 <maxno ofEDCH- 1></maxno 		E-DCH on Secondary uplink frequency - max 1 in this 3GPP release.	EACH	ignore
>New non-serving RL E- DCH FDD DL Control Channel Information A	0		9.2.2.13Dc E-DCH FDD DL Control Channel Information	E-DCH FDD DL Control Channel Information for Additional non-serving RL in Serving E- DCH RLS	_	
>New non-serving RL E- DCH FDD DL Control Channel Information B	0		9.2.2.13Dc E-DCH FDD DL Control Channel Information	E-DCH FDD DL Control Channel Information for Additional non-serving RL in non serving E- DCH RLS in case Additional serving RL is in the DRNS	-	
>New non-serving RL E- DCH FDD DL Control Channel Information C	0		9.2.2.13Dc E-DCH FDD DL Control Channel Information	E-DCH FDD DL Control Channel Information for Additional non-serving RL in case Additional	-	

		serving RL is	
		not in the	
		DRNS	

9.2.2.126 Void

9.2.2.127 Usefulness of Battery Optimization

This IE, when present, indicates whether the device can benefit from UTRAN-based battery consumption optimisation.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Usefulness of Battery Optimization			Enumerated (CanBenefit, CannotBenefit)	

9.2.2.128 M1 Report

This IE defines the parameters for M1 report, FDD report of UE radio measurements. This IE is not used by the DRNS.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
M1 Report				
>CHOICE Report trigger	M			
>>Periodic				
>>>MDT Report Parameters	M		9.2.1.140	
>>Event1F				
>>>Measurement quantity	M		ENUMERATED(CPICH Ec/N0, CPICH RSCP, Pathloss,)	
>>>threshold	М		INTEGER(-120165)	Range used depends on measurement quantity. CPICH RSCP -12025 dBm CPICH Ec/No -240 dB Pathloss 30165dB

9.2.2.129 Support of Dynamic DTXDRX Related HS-SCCH Order

The Support of dynamic DTXDRX related HS-SCCH order IE is to indicate if DRNS supports the DRX/DTX related HS-SCCH order for CPC non-uniform UE.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Support of dynamic DTXDRX			ENUMERATED	
related HS-SCCH order			(Supported, Not	
			Supported)	

9.2.3 TDD Specific Parameters

This subclause contains parameters that are specific to TDD.

9.2.3.a Alpha Value

Used to support signalling of cell specific Alpha Value to SRNS.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Alpha Value			ENUMERAT	
			ED(0, 1/8, 2/8, 3/8, 4/8,	
			5/8, 6/8, 7/8,	
			1)	

9.2.3.A Block STTD Indicator

Void.

9.2.3.1 Burst Type

Void.

9.2.3.1a Cell Capability Container TDD

The Cell Capability Container TDD indicates which functionalities a 3.84Mcps TDD cell supports.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Cell Capability Container TDD			BIT STRING (32)	Each bit indicates whether a cell supports a particular functionality or not. The value 1 of a bit indicates that the corresponding functionality is supported in a cell and value 0 indicates that the corresponding functionality is not supported in a cell. Each bit is defined as follows. The first bit: Delayed Activation Support Indicator. The second bit: HS-DSCH Support Indicator. The third bit: DSCH Support Indicator. The fourth bit: Flexible MAC-d PDU Size Support Indicator. The fifth: MBMS Support Indicator. Note that undefined bits are considered as a spare bit and spare bits shall be set to 0 by the transmitter and shall be ignored by the receiver.

9.2.3.1b Cell Capability Container TDD LCR

The Cell Capability Container TDD LCR indicates which functionalities a cell supports.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Cell Capability Container TDD LCR			BIT STRING (32)	Each bit indicates whether a cell supports a particular functionality or not. The value 1 of a bit indicates that the corresponding functionality is supported in a cell and value 0 indicates that the corresponding functionality is not supported in a cell. Each bit is defined as follows. The first bit: Delayed Activation Support Indicator. The second bit: HS-DSCH Support Indicator. The third bit: DSCH Support Indicator. The fourth bit: Flexible MAC-d PDU Size Support Indicator. Note that undefined bits are considered as a spare bit and spare bits shall be set to 0 by the transmitter and shall be ignored by the receiver.

9.2.3.2 CCTrCH ID

The CCTrCH ID identifies unambiguously a CCTrCH inside a Radio Link.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CCTrCH ID			INTEGER (015)	

9.2.3.2A DCH TDD Information

The DCH TDD Information IE provides information for DCHs to be established.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
DCH Information		1 <maxno ofDCHs></maxno 			_	
>Payload CRC Presence Indicator	М		9.2.1.42		_	
>UL FP Mode	М		9.2.1.67		_	
>ToAWS	M		9.2.1.58		_	
>ToAWE	М		9.2.1.57		_	
>DCH Specific Info		1 <maxno ofDCHs></maxno 			_	
>>DCH ID	M		9.2.1.16		_	
>>CCTrCH ID	M		9.2.3.2	UL CCTrCH in which the DCH is mapped	_	
>>CCTrCH ID	М		9.2.3.2	DL CCTrCH in which the DCH is mapped	-	
>>TrCH Source Statistics Descriptor	M		9.2.1.65		_	
>>Transport Format Set	M		9.2.1.64	For the UL.	_	
>>Transport Format Set	М		9.2.1.64	For the DL.	_	
>>BLER	М		9.2.1.4	For the UL.	_	
>>BLER	М		9.2.1.4	For the DL.	_	
>>Allocation/Retention Priority	М		9.2.1.1		_	
>>Frame Handling Priority	М		9.2.1.29		_	
>>QE-Selector	C- CoorDCH		9.2.1.46A		_	
>>Guaranteed Rate Information	0		9.2.1.30M		YES	ignore
>>Traffic Class	М		9.2.1.58A		YES	ignore
>>Unidirectional DCH Indicator	0		9.2.1.68B		YES	reject
>TNL QoS	0		9.2.1.56A		YES	ignore

Condition	Explanation
CoorDCH	The IE shall be present if this DCH is part of a set of coordinated DCHs (number of instances of the <i>DCH Specific Info</i> IE is greater than 1).

Range bound	Explanation
maxnoofDCHs	Maximum number of DCHs for one UE.

9.2.3.2B DCH TDD Information Response

Void

9.2.3.2C DL Timeslot Information

The *DL Timeslot Information* IE provides information on the time slot allocation for a DL DPCH at 3.84Mcps.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
DL Timeslot Information		1 <maxno OfTS></maxno 			_	
>Time Slot	M		9.2.1.56		_	
>Midamble Shift And Burst Type	М		9.2.3.4		_	
>TFCI Presence	M		9.2.1.55		_	
>DL Code Information	М		TDD DL Code Information 9.2.3.8C		_	

Range bound	Explanation
maxnoofTSs	Maximum number of Timeslots for a UE.

9.2.3.2D DL Time Slot ISCP Info

The DL Time Slot ISCP Info IE gives interference level for each DL time slot within the Radio Link.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
DL Time Slot ISCP Info		1 <maxno ofDLts></maxno 			_	
>Time Slot	М		9.2.1.56		_	
>DL Timeslot ISCP	М		9.2.3.12		ı	

Range bound	Explanation
maxnoofDLts	Maximum number of downlink time slots per Radio Link for
	3.84Mcps TDD.

9.2.3.2E DL Timeslot Information LCR

The DL Timeslot Information LCR IE provides information for DL Timeslot to be established for 1.28Mcps TDD.

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
			Reference			
DL Timeslot Information LCR		1 <maxnoof DLtsLCR></maxnoof 			-	
>Time Slot LCR	М		9.2.3.12a		-	
>Midamble Shift LCR	М		9.2.3.4C		_	
>TFCI Presence	М		9.2.1.57		_	
>DL Code Information LCR	М		TDD DL Code Information LCR 9.2.3.8D		ľ	
>Maximum DL TX Power	0		DL Power 9.2.1.21A	Maximum allowed power on DPCH	YES	ignore
>Minimum DL TX Power	0		DL Power 9.2.1.21A	Minimum allowed power on DPCH	YES	ignore

Range bound	Explanation
maxnoofDLtSLCR	Maximum number of Downlink time slots per Radio Link for
	1.28Mcps TDD.

9.2.3.2F DL Time Slot ISCP Info LCR

The DL *Time Slot ISCP Info LCR* IE provides information for DL Interference level for each time slot within the Radio Link for 1.28Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
DL Time Slot ISCP Info LCR		1 <maxnooful tsLCR></maxnooful 			_	
>Time Slot LCR	M		9.2.3.12a		_	
>DL Timeslot ISCP	M		9.2.3.12		_	

Range bound	Explanation
maxnoofULtsLCR	Maximum number of Uplink time slots per Radio Link for 1.28Mcps
	TDD

9.2.3.3 DPCH ID

The DPCH ID identifies unambiguously a DPCH inside a Radio Link.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DPCH ID			INTEGER	
			(0239)	

9.2.3.3a DSCH TDD Information

The DSCH TDD Information IE provides information for DSCHs to be established.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
DSCH TDD Information		1 <maxno ofDSCHs></maxno 			_	
>DSCH ID	M		9.2.3.3ae		-	
>CCTrCH ID	M		9.2.3.2	DL CCTrCH in which the DSCH is mapped.	_	
>TrCH Source Statistics Descriptor	М		9.2.1.65		_	
>Transport Format Set	M		9.2.1.64		-	
>Allocation/Retention Priority	M		9.2.1.1		_	
>Scheduling Priority Indicator	M		9.2.1.51A		_	
>BLER	M		9.2.1.4		_	
>Traffic Class	M		9.2.1.58A		YES	ignore
>Binding ID	0		9.2.1.3	Shall be ignored if bearer establishme nt with ALCAP.	YES	ignore
>Transport Layer Address	0		9.2.1.62	Shall be ignored if bearer establishme nt with ALCAP.	YES	ignore
>TNL QoS	0		9.2.1.56A	Shall be ignored if bearer establishme nt with ALCAP.	YES	ignore

Range bound	Explanation		
maxnoofDSCHs	Maximum number of DSCHs for one UE.		

9.2.3.3aa HS-DSCH TDD Information

The HS-DSCH TDD Information IE is used for initial addition of HS-DSCH information to a UE Context.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
HS-DSCH MAC-d Flows	М		9.2.1.30OA	•	_	•
Information		4				
VE Capabilities Information >HS-DSCH Physical Layer	M	1	9.2.1.30Oa			
Category	IVI		9.2.1.300a		_	
>1.28 Mcps TDD uplink	0		9.2.3.10D	Applicable to	YES	ignore
physical channel capability				1.28Mcps		
>Number of Supported	0		ENUMERATE	TDD only	YES	
Carriers			D (One-one carrier, One- three carrier,	Applicable to 1.28Mcps TDD only This IE indicates the	120	reject
			Three-three carrier, One-six carrier,	number of carrier that UE can		
			Tree-six carrier,	support at the same time,where "		
			, One-Two carrier Discontiguous,	One-three carrier" means the		
			Two-Two carrier Discontiguous,	number of supported carrier is one		
			One-Two carrier Contiguous,	for the uplink,and three for the		
			Two-Two carrier Contiguous)	downlink. One-Two carrier		
				Discontiguou s and Two- Two carrier Discontiguou		
				s mean that the UE is capable of supporting		
				two non- adjacent carriers.		
				One-Two carrier		
				Contiguous and Two- Two carrier		
				Contiguous mean that the UE is		
				only capable of supporting two adjacent carriers.		
>Multi-carrier HS-DSCH Physical Layer Category	0		9.2.1.30Oa	Applicable to 1.28Mcps TDD only	YES	ignore
>MIMO SF Mode Supported For HS-PDSCH dual stream	0		Enumerated (SF1, SF1/SF16)	Applicable to 1.28Mcps TDD only	YES	ignore
>UE TS0 Capability LCR	0		ENUMERATE D (TS0 Capable, TS0	Applicable to 1.28Mcps TDD only	YES	ignore
>UE RF Band Capability	C-		Non-Capable) 9.2.3.84	Applicable to	YES	ignore
LCR	NofSupport		3.2.3.04	1.28Mcps	ILO	ignore

	edCarriers		TDD only.		
MAC-hs Reordering Buffer Size for RLC-UM	М	9.2.1.34Ab		_	
TDD ACK NACK Power Offset	M	9.2.3.71		_	
HS-DSCH MAC-d PDU Size Format	0	9.2.1.30OC	If not present, "Indexed MAC-d PDU Size" shall be used.	YES	reject
HS-SICH SIR Target	0	UL SIR 9.2.1.69	Applicable to 1.28Mcps TDD only	YES	ignore
HS-SICH TPC step size	0	9.2.3.10a	Applicable to 1.28Mcps TDD only	YES	ignore
TSN-Length	0	9.2.3.3ai	Applicable for 1.28Mcps TDD when using multiple frequencies	YES	reject
MIMO Activation Indicator	0	9.2.1.134		YES	reject

Condition	Explanation
NofSupportedCarriers	This IE shall be present if the Number of Supported Carriers IE is equal
	to "One-Two carrier Discontiguous" or "Two-Two carrier Discontiguous"
	and the concerned cell and the UE support more than one RF band.

9.2.3.3ab HS-DSCH TDD Information Response

The *HS-DSCH TDD Information Response* IE provides information for HS-DSCH that have been established or modified. It also provides additional HS-DSCH information determined within the DRNS.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
HS-DSCH MAC-d Flow Specific Information Response		0 <maxno ofMACdFl ows></maxno 			_	
>HS-DSCH MAC-d Flow ID	M	OWS>	9.2.1.300		_	
>Binding ID	O		9.2.1.3		_	
>Transport Layer Address	0		9.2.1.62		_	
>HS-DSCH Initial Capacity	Ō		9.2.1.30Na		_	
Allocation						
HS-SCCH Specific Information Response		0 <maxno ofHSSCC Hcodes></maxno 		Not applicable to 1.28 Mcps TDD or 7.68Mcps TDD	GLOBAL	reject
>Time Slot	M		9.2.1.56		_	
>Midamble Shift And Burst Type	M		9.2.3.4		_	
>TDD Channelisation Code	M		9.2.3.8		_	
>HS-SICH Information		1			_	
>>HS SICH ID	M		9.2.3.3ad		_	
>>Time Slot	M	1	9.2.1.56		_	
>>Midamble Shift And Burst Type	M		9.2.3.4		_	
>>TDD Channelisation Code	М		9.2.3.8		_	
HS-SCCH Specific Information Response LCR		0 <maxno ofHSSCC Hcodes></maxno 		Not applicable to 3.84 Mcps TDD or 7.68Mcps TDD	GLOBAL	reject
>Time Slot LCR	M		9.2.3.12a		_	
>Midamble shift LCR	M		9.2.3.4C		_	
>First TDD Channelisation Code	M		TDD Channelisa tion Code 9.2.3.8		-	
>Second TDD Channelisation Code	M		TDD Channelisa tion Code 9.2.3.8		_	
>HS-SICH Information LCR		1			_	
>>HS SICH ID	M		9.2.3.3ad		_	
>>Time Slot LCR	M	1	9.2.3.12a		_	
>>Midamble shift LCR >>TDD Channelisation	M		9.2.3.4C 9.2.3.8			
Code				A 11 11	-	
>Used Frequency	0		UARFCN 9.2.1.66	Applicable for 1.28Mcps TDD when using multiple frequencies. This IE indicates the frequency which is actually used by the HS-SCCH.	YES	reject
>UARFCN	0		9.2.1.66	Corresponds to Nt (3GPP TS 25.105) Applicable	YES	ignore

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
				for 1.28Mcps TDD when using multiple frequencies. See note1 below		
HS-SCCH Specific Information Response 7.68 Mcps		0 <maxno ofHSSCC Hcodes></maxno 		Applicable to 7.68 Mcps TDD only	YES	ignore
>Time Slot	M	11codes>	9.2.1.56	TOD OHIY	_	
>Midamble Shift And Burst Type 7.68Mcps	M		9.2.3.23		_	
>TDD Channelisation Code 7.68Mcps	М		9.2.3.25		_	
>HS-SICH Information		1			_	
>>HS SICH ID	M		9.2.3.3ad		_	
>>Time Slot	M		9.2.1.56		_	
>>Midamble Shift And Burst Type 7.68Mcps	М		9.2.3.23		_	
>>TDD Channelisation Code 7.68Mcps	М		9.2.3.25		_	-
HS-PDSCH Timeslot Specific Information Response		0 <maxno ofDLts></maxno 		Not Applicable to 1.28Mcps TDD or 7.68Mcps TDD.	GLOBAL	reject
>Time Slot	M		9.2.1.56		_	
>Midamble Shift And Burst Type	M		9.2.3.4		_	
HS-PDSCH Timeslot Specific Information Response LCR		0 <maxno ofDLtsLCR ></maxno 		Not Applicable to 3.84Mcps TDD or 7.68Mcps TDD.	GLOBAL	reject
>Time Slot LCR	M		9.2.3.12a		_	
>Midamble Shift LCR	M		9.2.3.4C		_	
HS-PDSCH Timeslot Specific Information Response 7.68Mcps		0 <maxno ofDLts></maxno 		Applicable to 7.68Mcps TDD only.	YES	Ignore
>Time Slot	M		9.2.1.56		_	
>Midamble Shift And Burst Type 7.68Mcps	М		9.2.3.23		_	
HARQ Memory Partitioning	0		9.2.1.116		_	
User Plane Congestion Fields Inclusion	0		9.2.1.70C		YES	ignore
HS-SCCH Specific Information Response LCR per UARFCN		0 <maxh SDPAFreq uency-1></maxh 		Applicable for 1.28Mcps TDD	GLOBAL	reject
>HS-SCCH Specific Information Response LCR		1 <maxno OfHSSCC Hcodes></maxno 			_	
>>Time Slot LCR	М		9.2.3.12a		_	
>>Midamble Shift LCR	М		9.2.3.4C		_	
>>First TDD Channelisation Code	M		TDD Channelisa tion Code 9.2.3.8		_	
>>Second TDD Channelisation Code	М		TDD Channelisa tion Code 9.2.3.8		_	

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>>HS-SICH Information		1	TKOTOT OTTOO		_	
LCR						
>>>HS SICH ID	M		9.2.3.3ad			
>>>Time Slot LCR	M		9.2.3.12a		_	
>>>Midamble Shift LCR	M		9.2.3.4C		_	
>>>TDD Channelisation Code	М		9.2.3.8		_	
>>Used Frequency	O		UARFCN 9.2.1.66	Applicable for 1.28Mcps TDD when using multiple frequencies. This IE indicates the frequency which is actually used by the HS-SCCH.	YES	reject
>UARFCN	0		9.2.1.66	Corresponds to Nt □3GPP TS 25.105□ Applicable for 1.28Mcps TDD when using multiple frequencies. See note 1 below	YES	ignore
>HARQ Memory Partitioning per UARFCN		0 <maxh SDPAFreq uency-1></maxh 				
>>HARQ Memory Partitioning	0		9.2.1.116		_	
>UARFCN	O		9.2.1.66	Corresponds to Nt □3GPP TS 25.105□ Applicable for 1.28Mcps TDD when using multiple frequencies. See note 1 below	YES	ignore
>TS0 HS-PDSCH Indication LCR	0		9.2.3.74	1.28Mcps TDD only	YES	ignore
Multi-Carrier number	0		Integer(1 maxHSDP AFrequenc y)	Applicable for 1.28Mcps TDD when using multiple frequencies.	YES	ignore
MIMO SF Mode for HS- PDSCH dual stream	0		Enumerate d (SF1, SF1/SF16)	Applicable for 1.28Mcps TDD when MIMO is configured	YES	reject
MIMO Reference Signal Information	0	0 <maxno OfHSSCC Hcodes></maxno 		Applicable for 1.28Mcps TDD when MIMO is configured	YES	reject

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
>HS-SICH Reference Signal Information	М		9.2.3.72		YES	
Out-of-sync Detection Window	0		ENUMERA TED (40, 80, 160, 320, 640,)	Unit: ms Applicable to 1.28Mcps TDD.	YES	reject
Note 1: This information elemen	t is a simplified	representation	on of the ASN.	1 description.		

Range bound	Explanation
maxnoofMACdFlows	Maximum number of MAC-d flows.
maxnoofHSSCCHcodes	Maximum number of HS-SCCH codes.
maxnoofDLts	Maximum number of downlink time slots per Radio Link for 3.84Mcps TDD.
maxnoofDLtsLCR	Maximum number of Downlink time slots per Radio Link for 1.28Mcps TDD.
maxHSDPAFrequency	Maximum number of Frequency that UE can support HSDPA

9.2.3.3ac HS-DSCH TDD Update Information

The *HS-DSCH TDD Update Information* IE provides information for HS-DSCH to be updated. At least one IE shall be presented.

IE/Group name	Presence	Range	IE Type and Reference	Semantic Description	Criticality	Assigned Criticality
HS-SCCH Code Change Indicator	0		9.2.1.30R		_	
TDD ACK NACK Power Offset	0		9.2.3.71		_	

9.2.3.3ad HS-SICH ID

The HS-SICH ID identifies unambiguously a HS-SICH.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
HS SICH ID			INTEGER (031)	For 1.28Mcps TDD, the IE is INTEGER (0255). In ASN.1, it is presented by another IE for the value beyond the 31.

9.2.3.3ae DSCH ID

The DSCH ID is the identifier of an active downlink shared channel. It is unique for each active DSCH among the active DSCHs simultaneously allocated for the same UE.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DSCH ID			INTEGER	
			(0255)	

9.2.3.3af DSCH Initial Window Size

Indicates the initial number of MAC-c/sh SDUs that may be transmitted before new credits are received from the DRNC.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
DSCH Initial Window Size			INTEGER (1255)	Number of MAC-c/sh SDUs: 255 = Unlimited number of MAC-c/sh SDUs.

9.2.3.3ag DSCH Flow Control Information

The DSCH Flow Control Information IE provides flow control information for each scheduling priority class for the DSCH FP over Iur.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
DSCH Flow Control Information		116			_	
>DSCH Scheduling Priority	M		Scheduling Priority Indicator 9.2.1.51A		-	
>MAC-c/sh SDU Length		1 <maxnb MAC- c/shSDUL ength></maxnb 			-	
>>MAC-c/sh SDU Length	М		9.2.1.34		_	
>DSCH Initial Window Size	0		9.2.3.3af		YES	ignore

Range bound	Explanation
maxNbMAC-c/shSDULength	Maximum number of different MAC-c/sh SDU lengths.

9.2.3.3ah DSCH-RNTI

DSCH-RNTI is the UE identifier allocated by DRNS to be used over the radio interface by Ues having one or several DSCHs and/or USCHs. It is unique within a cell.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
DSCH-RNTI			INTEGER(0.	
			.65535)	

9.2.3.3ai TSN-Length

The IE indicates the TSN length.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
TSN-Length			ENUMERATED	
			(tsn-6bits, tsn-9bits)	

9.2.3.3A Maximum Number of Timeslots

Defines the maximum number of timeslots the UE has the capability of receiving or transmitting. [3.84Mcps TDD and 7.68Mcps TDD – in a frame] [1.28Mcps TDD – in a subframe]

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Maximum Number of			INTEGER	For 1.28Mcps TDD the values 7
Timeslots			(114)	through 14 are not used.

9.2.3.3B Maximum Number of UL Physical Channels per Timeslot

Defines the maximum number of physical channels [3.84Mcps TDD and 7.68Mcps TDD – per frame] [1.28Mcps TDD – per subframe] that the UE is capable to transmit.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Maximum Number of UL			INTEGER	
Physical Channels per			(12)	
Timeslot				

9.2.3.3C Maximum Number of DL Physical Channels

Defines the maximum number of physical channels [3.84Mcps TDD – per frame] [1.28Mcps TDD – per subframe] that the UE is capable to receive.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Maximum Number of DL			INTEGER	For 1.28Mcps TDD the values
Physical Channels			(1224)	97 through 224 are not used.

9.2.3.3D Maximum Number of DL Physical Channels per Timeslot

Defines the maximum number of physical channels per timeslot that the UE is capable to receive.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Maximum Number of DL			INTEGER	
Physical Channels per			(116)	
Timeslot				

9.2.3.4 Midamble Shift And Burst Type

This information element indicates burst type and midamble allocation.

Three different midamble allocation schemes exist:

- Default midamble: the midamble is allocated by layer 1 depending on the associated channelisation code (DL and UL);
- Common midamble: the midamble is allocated by layer 1 depending on the number of channelisation codes (possible in DL only);
- UE specific midamble: a UE specific midamble is explicitly assigned (DL and UL).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Burst Type				-
>Type 1				
>> Midamble Configuration Burst Type 1 And 3	M		ENUMERATED(4, 8, 16)	As defined in TS 25.221 [12]
>>Midamble Allocation Mode	M		ENUMERATED(Defa ult midamble, Common midamble, UE specific midamble)	
>>Midamble Shift Long	C-UE		INTEGER(015)	
>Type 2				
>> Midamble Configuration Burst Type 2	M		ENUMERATED (3, 6)	As defined in TS 25.221 [12]
>>Midamble Allocation Mode	M		ENUMERATED(Defa ult midamble, Common midamble, UE specific midamble)	
>>Midamble Shift Short	C-UE		INTEGER (015)	
>Type 3				UL only
>> Midamble Configuration Burst Type 1 And 3	M		ENUMERATED (4, 8, 16)	As defined in TS 25.221 [12]
>>Midamble Allocation Mode	M		ENUMERATED(Defa ult midamble, UE specific midamble)	
>>Midamble Shift Long	C-UE		INTEGER(015)	

Condition	Explanation
UE	The IE shall be present if the Midamble Allocation
	Mode IE is set to "UE-specific midamble".

9.2.3.4A Minimum Spreading Factor

Defines the minimum spreading factor the UE has the capability of receiving or transmitting.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Minimum Spreading			INTEGER	
Factor			(116)	

9.2.3.4B IPDL TDD parameters

The IPDL TDD Parameters IE provides the information for the IPDL Configuration applied in 3.84Mcps TDD mode.

IE/Group name	Presence	Range	IE Type and Reference	Semantics Description
IP Spacing TDD	M		ENUMERAT ED(30,40,50 , 70, 100,)	See TS 25.224 [22]
IP Start	М		INTEGER(0. .4095)	See TS 25.224 [22]
IP Slot	М		INTEGER(014)	See TS 25.224 [22]
IP P-CCPCH	М		ENUMERAT ED(Switch off 1 frame, Switch off 2 frames)	See TS 25.224 [22]
Burst mode parameters	0		9.2.1.4B	

9.2.3.4Bb IPDL TDD parameters LCR

The *IPDL TDD Parameters LCR* IE provides the information for the IPDL Configuration applied in 1.28Mcps TDD mode.

IE/Group name	Presence	Range	IE Type and Reference	Semantics Description
IP Spacing TDD	M		ENUMERAT ED(30,40,50 , 70, 100,)	See TS 25.224 [22]
IP Start	M		INTEGER(04095)	See TS 25.224 [22]
IP_Sub	M		ENUMERAT ED(First,Sec ond,Both)	See TS 25.224 [22]
Burst mode parameters	0		9.2.1.4B	

9.2.3.4C Midamble shift LCR

This information element indicates midamble allocation in 1.28Mcps TDD.

Three different midamble allocation schemes exist:

- Default midamble: the midamble is allocated by layer 1 depending on the associated channelisation code (DL and UL);
- Common midamble: the midamble is allocated by layer 1 depending on the number of channelisation codes (possible in DL only);
 - UE specific midamble: a UE specific midamble is explicitly assigned (DL and UL).

IE/Group name	Presence	Range	IE Type and	Semantics Description
			Reference	
Midamble Allocation Mode	M		ENUMERAT	
			ED(Default	
			midamble,	
			Common	
			midamble,	
			UE specific	
			midamble,)	
Midamble Shift Long	C-UE		INTEGER(0.	
			.15)	
Midamble Configuration LCR	M		ENUMERAT	As defined in TS 25.221 [12]
_			ED (2, 4, 6,	
			8, 10, 12, 14,	
			16,)	

Condition	Explanation
UE	The IE shall be present if the Midamble Allocation
	Mode IE is set to "UE-specific midamble".

9.2.3.4D Neighbouring TDD Cell Information LCR

Void

9.2.3.5 Primary CCPCH RSCP

Received Signal Code Power is the received power on PCCPCH of the target cell after despreading. The reference point for the RSCP is the antenna connector at the UE, see TS 25.225 [14].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Primary CCPCH RSCP			INTEGER(According to mapping of the
			091)	non-negative values in TS
				25.123 [24].

9.2.3.5a Primary CCPCH RSCP Delta

Primary CCPCH RSCP Delta is the offset used to report the negative reporting range of P-CCPCH RSCP as per TS 25.123 [24].

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
Primary CCPCH RSCP Delta			INTEGER(If present, the actual value of
			-51,)	Primary CCPCH RSCP =
				Primary CCPCH RSCP Delta

9.2.3.5A PRACH Midamble

Void.

9.2.3.5B RB Identity

The RB Identity is the identifier of a radio bearer. It is unique for each active Radio bearer among the active radio bearers simultaneously allocated for the same UE.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
RB Identity			INTEGER (031)	In line with TS 25.331 [16], ch. 10.3.4.11

9.2.3.6 Repetition Length

The Repetition Length represents the number of consecutive Radio Frames inside a Repetition Period in which the same Time Slot is assigned to the same Physical Channel see TS 25.331 [16].

[1.28Mcps TDD- When applied to configure the E-DCH Non-scheduled Grant Information, the Repetition Length represents the number of consecutive Subframes, i.e. 5ms inside a Repetition Period in which the same Time Slot is assigned to the same Physical Channel see TS 25.331 [16].]

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Repetition Length			INTEGER(163	

9.2.3.7 Repetition Period

The Repetition Period represents the number of consecutive Radio Frames after which the same assignment scheme of Time Slots to a Physical Channel is repeated. This means that if the Time Slot K is assigned to a physical channel in the Radio Frame J, it is assigned to the same physical channel also in all the Radio Frames J+n*Repetition Period (where n is an integer) see TS 25.331 [16].

[1.28Mcps TDD- When applied to configure the E-DCH Non-scheduled Grant Information, the Repetition Period represents the number of consecutiveSubframes, i.e. 5ms after which the same assignment scheme of Time Slots to a Physical Channel is repeated see TS 25.331 [16].]

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Repetition Period			ENUMERATED	
			(1,2,4,8,16,32,6	
			4)	

9.2.3.7A Rx Timing Deviation

Measured Rx Timing Deviation as a basis for timing advance, either measured directly from a RACH burst, or calculated from the Rx Timing Deviation measurement on the USCH by adding the current Timing Advance value. For 1.28Mcps TDD this IE must be set to 0.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Rx Timing Deviation			INTEGER	As specified in TS 25.435
			(0127)	[5], ch. 6.2.7.6

9.2.3.7B Secondary CCPCH Info TDD

The Secondary CCPCH Info TDD IE provides information on the Secondary CCPCH that carries the logical channel SHCCH for the UE.

IE/Group Name	Presence	Range	IE Type	Semantics	Criticality	Assigned
			and	Description		Criticality
			Reference			
TFCS	M		9.2.1.63	For the DL.	_	
TFCI Coding	M		9.2.3.11		_	
Secondary CCPCH		0 <maxno ofSCCPC</maxno 			_	
		Hs>				
>Time Slot	M		9.2.1.56		_	
>Midamble Shift And Burst Type	M		9.2.3.4		_	
>TFCI Presence	M		9.2.1.55		_	
>Secondary CCPCH TDD Code Information	М		9.2.3.7C		_	
>TDD Physical Channel Offset	М		9.2.3.9		_	
>Repetition Length	M		9.2.3.6		_	
>Repetition Period	M		9.2.3.7		_	
FACH		0maxnoo fFACHs			_	
>TFS	M		9.2.1.64	For the DL.	_	
PCH		01			_	
>TFS	М		9.2.1.64	For the DL.	_	

Range bound	Explanation
maxnoofSCCPCHs	Maximum number of Secondary CCPCHs per CCTrCH.
maxnoofFACHs	Maximum number of FACHs mapped onto a Secondary CCPCH.

9.2.3.7C Secondary CCPCH TDD Code Information

The Secondary CCPCH TDD Code Information IE provides TDD Channelisation Code information for all SCCPCHs of one Time Slot.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Secondary CCPCH TDD Code Information		1 <maxno OfSCCPC Hs></maxno 			_	
>TDD Channelisation Code	М		9.2.3.8		_	

Range bound	Explanation
maxnoofSCCPCHs	Maximum number of SCCPCHs for one CCTrCH.

9.2.3.7D Special Burst Scheduling

The number of frames between special burst transmissions during DTX.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Special Burst Scheduling			INTEGER(1,	Number of frames between
			2,, 256)	special burst transmissions
				during DTX

9.2.3.7E Synchronisation Configuration

The Synchronisation Configuration parameters that are used by the DRNS in the Radio Link Failure/Restore procedure.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
N_INSYNC_IND	M		INTEGER(1,	
			2,, 256)	
N_OUTSYNC_IND	M		INTEGER(1,	
			2,, 256)	
T_RLFAILURE	M		ENUMERAT	Unit: seconds
			ED(0, 0.1,	
			0.2 25.5)	

9.2.3.7F Secondary CCPCH Info TDD LCR

The Secondary CCPCH Info TDD LCR IE provides information on the Secondary CCPCH that carries the logical channel SHCCH for the UE.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
TFCS	M		9.2.1.63	For the DL.	_	
TFCI Coding	M		9.2.3.11		_	
Secondary CCPCH		0 <maxno ofSCCPC Hs></maxno 			_	
>Time Slot LCR	M		9.2.3.12a		_	
>Midamble Shift LCR	M		9.2.3.4C		_	
>TFCI Presence	M		9.2.1.55		_	
>Secondary CCPCH TDD Code Information LCR	М		9.2.3.7G		_	
>TDD Physical Channel Offset	М		9.2.3.9		_	
>Repetition Length	M		9.2.3.6		_	
>Repetition Period	M		9.2.3.7		_	
FACH		0 <maxno ofFACHs></maxno 			_	
>TFS	М		9.2.1.64	For the DL.	_	
PCH		01			_	
>TFS	М		9.2.1.64	For the DL.		

Range bound	Explanation
maxnoofSCCPCHs	Maximum number of Secondary CCPCHs per CCTrCH.
maxnoofFACHs	Maximum number of FACHs mapped onto a Secondary CCPCH.

9.2.3.7G Secondary CCPCH TDD Code Information LCR

The *Secondary CCPCH TDD Code Information LCR* IE provides LCR TDD Channelisation Code information for all SCCPCHs of one Time Slot.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Secondary CCPCH TDD Code Information		1 <maxno OfSCCPC Hs></maxno 			-	
>TDD Channelisation Code LCR	М		9.2.3.8a		_	
>SCCPCH Time Slot Format LCR	М		TDD DL DPCH Time Slot Format LCR 9.2.3.8E		-	

Range bound	Explanation
maxnoofSCCPCHs	Maximum number of SCCPCHs for one CCTrCH.

9.2.3.7H Support of 8PSK

The Support of 8PSK IE indicates whether 8PSK is supported or not.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Support of 8PSK			ENUMERAT	
			ED(supported	
)	

9.2.3.7I TDD ACK NACK Power Offset

The *TDD ACK NACK Power Offset* IE indicates Power offset used in the UL in the HS-SICH between transmissions carrying positive and negative acknowledgements as per TS 25.331 [16].

IE/Group Name	Presence	Range	IE type and reference	Semantics description
TDD ACK NACK Power			INTEGER (-	Unit: dB
Offset			78,)	Range: -7+8 dB
				Step: 1 dB

9.2.3.8 TDD Channelisation Code

The Channelisation Code Number indicates which Channelisation Code is used for a given Physical Channel. In TDD the Channelisation Code is an Orthogonal Variable Spreading Factor code that can have a spreading factor of 1, 2, 4, 8 or 16.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
TDD Channelisation Code			ENUMERATED ((1/1), (2/1), (2/2), (4/1), (4/4), (8/1), (8/8), (16/1), (16/16),)	

9.2.3.8a TDD Channelisation Code LCR

The Channelisation Code Number indicates which Channelisation Code is used for a given Physical Channel. In 1.28Mcps TDD the Channelisation Code is an Orthogonal Variable Spreading Factor code, that can have a spreading factor of 1, 2, 4, 8 or 16 and there is a choice between QPSK and 8PSK modulation.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
TDD Channelisation Code	M		ENUMERAT ED((1/1), (2/1), (2/2), (4/1),(4/4), (8/1),(8/8), (16/1) (16/16),)	
Modulation	М		ENUMERAT ED(QPSK, 8PSK,)	Modulation options for 1.28Mcps TDD in contrast to 3.84Mcps TDD

9.2.3.8A TDD DPCH Offset

The Offset represents the phase information for the allocation of a group of dedicated physical channels. The *Offset Type* IE = "No Initial Offset" is used when a starting offset is not required and the TDD Physical channel offset for each DPCH in the CCTrCH shall be directly determined from the TDD DPCH Offset. The *Offset Type* IE = "Initial Offset" is used when a starting offset is required. The TDD DPCH Offset shall map to the CFN and the TDD Physical Channel Offset for each DPCH in this CCTrCH shall calculated by TDD DPCH Offset *mod* Repetition period, see TS 25.331 [16].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Offset Type				
>Initial Offset				
>>TDD DPCH Offset Value	M		INTEGER	
			(0255)	
>No Initial Offset				
>>TDD DPCH Offset Value	М		INTEGER	
	1		(063)	

9.2.3.8B TDD DCHs To Modify

The $TDD\ DCHs\ To\ Modify\ IE$ provides information for DCHs to be modified.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
TDD DCHs To Modify		1 <maxno ofDCHs></maxno 			_	
>UL FP Mode	0		9.2.1.67		_	
>ToAWS	0		9.2.1.58		_	
>ToAWE	0		9.2.1.57		_	
>Transport Bearer Request Indicator	M		9.2.1.61		_	
>DCH Specific Info		1 <maxno ofDCHs></maxno 			_	
>>DCH ID	M		9.2.1.16		_	
>>CCTrCH ID	0		9.2.3.2	UL CCTrCH in which the DCH is mapped.	-	
>>CCTrCH ID	0		9.2.3.2	DL CCTrCH in which the DCH is mapped	-	
>>Transport Format Set	0		9.2.1.64	For the UL.	_	
>>Transport Format Set	0		9.2.1.64	For the DL.	_	
>>Allocation/Retention Priority	0		9.2.1.1		_	
>>Frame Handling Priority	0		9.2.1.29		_	
>>Guaranteed Rate Information	0		9.2.1.30M		YES	ignore
>>Traffic Class	0		9.2.1.58A		YES	ignore
>TNL QoS	0		9.2.1.56A		YES	ignore

Range bound	Explanation
maxnoofDCHs	Maximum number of DCHs for one UE.

9.2.3.8C TDD DL Code Information

The $TDD\ DL\ Code\ Information\ IE\ provides\ TDD\ DL\ Code\ information\ for\ all\ DPCHs\ of\ one\ DL\ Time\ Slot.$

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
TDD DL Code Information		1 <maxno OfDPCHs ></maxno 			_	
>DPCH ID	М		9.2.3.3		_	
>TDD Channelisation Code	М		9.2.3.8		_	

Range bound	Explanation
maxnoofDPCHs	Maximum number of DPCHs for one CCTrCH.

9.2.3.8D TDD DL Code Information LCR

The TDD DL Code Information LCR IE provides DL Code information for the RL for 1.28Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
TDD DL Code Information LCR		1 <maxnoof DPCHLCR ></maxnoof 			-	
>DPCH ID	M		9.2.3.5		_	
>TDD Channelisation Code LCR	M		9.2.3.8a		-	
> TDD DL DPCH Time Slot Format LCR	М		9.2.3.8E		1	

Range bound	Explanation
maxnoOfDPCHLCR	Maximum number of DPCH in one CCTrCH for 1.28Mcps TDD

9.2.3.8E TDD DL DPCH Time Slot Format LCR

TDD DL DPCH Time Slot Format LCR indicates the time slot formats used in DL DPCH for 1.28Mcps TDD (see TS 25.221 [12]).

IE/Group Name	Presence	Range	IE type and reference	Semantics description
CHOICE Modulation				
> QPSK				
>>QPSK TDD DL DPCH	M		INTEGER	
TimeSlot Format LCR			(024,)	
> 8PSK				
>>8PSK TDD DL DPCH	M		INTEGER	
TimeSlot Format LCR			(024,)	

9.2.3.9 TDD Physical Channel Offset

The TDD Physical Channel Offset represents the phase information for the allocation of a non DPCH physical channel. (CFN mod Repetition Period = TDD Physical Channel Offset) see TS 25.331 [16].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
TDD Physical Channel			INTEGER	
Offset			(063)	

9.2.3.10 TDD TPC Downlink Step Size

This parameter indicates step size for the DL power adjustment (see TS 25.224 [22]).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
TDD TPC Downlink Step Size			ENUMERAT ED(1, 2,	Unit: dB
			3,)	

9.2.3.10a TDD TPC Uplink Step Size

This parameter indicates step size for the UL power adjustment (see TS 25.224 [22]).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
TDD TPC Uplink Step Size			ENUMERAT ED (1, 2, 3,)	Unit: dB

9.2.3.10A TDD UL Code Information

The TDD UL Code Information IE provides TDD UL Code information for all DPCHs of one UL Time Slot.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
TDD UL Code Information		1 <maxno OfDPCHs</maxno 			_	
		>				
>DPCH ID	M		9.2.3.3		_	
>TDD Channelisation Code	M		9.2.3.8		_	

Range bound	Explanation
maxnoofDPCHs	Maximum number of DPCHs for one CCTrCH.

9.2.3.10B TDD UL Code Information LCR

The TDD UL Code Information LCR IE provides information for UL Code to be established for 1.28Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
TDD UL Code Information LCR		1 <maxno OfDPCH LCR></maxno 			_	
>DPCH ID	M		9.2.3.5		_	
>TDD Channelisation Code LCR	M		9.2.3.8a		_	
> TDD UL DPCH Time Slot Format LCR	M		9.2.3.10C		_	

Range bound	Explanation
maxnoOfDPCHLCR	Maximum number of DPCH in one CCTrCH for 1.28Mcps TDD.

9.2.3.10C TDD UL DPCH Time Slot Format LCR

TDD UL DPCH Time Slot Format LCR indicates the time slot formats used in UL DPCH for 1.28Mcps TDD (see TS 25.221 [12]).

IE/Group Name	Presence	Range	IE type and	Semantics description
			reference	
CHOICE Modulation				
> QPSK				
>>QPSK TDD UL DPCH	М		INTEGER	
Time Slot Format LCR			(069,)	
> 8PSK				
>>8PSK TDD UL DPCH	M		INTEGER	
Time Slot Format LCR			(024,)	

9.2.3.10D 1.28 Mcps TDD uplink physical channel capability

1.28 Mcps TDD uplink physical channel capability IE defines the UE uplink physical channel capability for 1.28 Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Maximum Number of	М		INTEGER	
timeslots per subframe			(16)	
Maximum number of physical	M		ENUMERATED	
channels per timeslot			(1,2,3,4)	ļ

9.2.3.11 TFCI Coding

The TFCI Coding describes how the TFCI bits are coded. By default 1 TFCI bit is coded with 4 bits, 2 TFCI bits are coded with 8 bits, 3-5 TFCI bits are coded with 16 bits and 6-10 TFCI bits are coded with 32 bits.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
TFCI Coding			ENUMERATE	
			D(4, 8, 16,	
			32,)	

9.2.3.12 DL Timeslot ISCP

DL Timeslot ISCP is the measured interference in a downlink timeslot at the UE, see TS 25.225 [14].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DL Timeslot ISCP			INTEGER(091)	According to mapping in TS 25.123 [24].

9.2.3.12a Time Slot LCR

The Time Slot LCR is the number of the traffic time slot within a 5 ms subframe of LCR TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Time Slot LCR			INTEGER	
			(06)	

9.2.3.12A Timing Advance Applied

Defines the need for Timing Advance functions such as Rx Timing Deviation measurement in a particular cell.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Timing Advance Applied			ENUMERAT	
			ED(Yes, No)	

9.2.3.13 Transport Format Management

Defines whether the cell transmits the transport format information via broadcast or whether the transport format information is transmitted to the UE using dedicated RRC procedures

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Transport Format			ENUMERAT	
Management			ED(Cell	
			Based, UE	
			Based)	

9.2.3.13A UL Timeslot ISCP

UL Timeslot ISCP is the measured interference in a uplink timeslot at the DRNS, see TS 25.225 [14].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UL Timeslot ISCP			INTEGER(0127)	According to mapping in TS 25.123 [24].

9.2.3.13B UL PhysCH SF Variation

Indicates whether variation of SF in UL is supported by Radio Link or not.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UL PhysCH SF Variation			ENUMERAT	
-			ED(SF_Vari	
			ation_suppor	
			ted,	
			SF_Variation	
			_NOT_supp	
			orted)	

9.2.3.13C UL Timeslot Information

The UL Timeslot Information IE provides information on the time slot allocation for a UL DPCH.

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
			Reference	2000		
UL Timeslot Information		1 <maxno OfTS></maxno 			_	
>Time Slot	M		9.2.1.56		_	
>Midamble Shift And Burst Type	M		9.2.3.4		_	
>TFCI Presence	М		9.2.1.55		_	
>UL Code Information	М		TDD UL Code Information 9.2.3.10A		_	

Range bound	Explanation		
maxnoofTSs	Maximum number of Timeslots for a UE.		

9.2.3.13D UL Time Slot ISCP Info

The UL Time Slot ISCP Info IE gives interference level for each UL time slot within the Radio Link.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
UL Time Slot ISCP Info		1 <maxnoof ULts></maxnoof 			_	
>Time Slot	M		9.2.1.56		_	
>UL Timeslot ISCP	M		9.2.3.13A		_	

Range bound	Explanation		
maxnoofULts	Maximum number of uplink time slots per Radio Link.		

9.2.3.13E TSTD Indicator

Indicates if TSTD shall be active or not for the DL DPCH.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
TSTD Indicator			ENUMERAT	
			ED(active,	
			inactive)	

9.2.3.13F TSTD Support Indicator

Indicates if UE support TSTD or not for DL DPCH.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
TSTD Support Indicator			ENUMERAT ED(TSTD supported, TSTD not supported)	

9.2.3.13Fa UE Measurement Hysteresis Time

The UE Measurement Hysteresis Time provides the duration during which a reporting criterion has to be fulfilled for the UE Measurement Reporting procedure to be triggered, see TS 25.331 [16]..

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UE Measurement			INTEGER(0	Unit: dB
Hysteresis Time			15)	Range: 07.5 dB
			·	Step: 0.5 dB

9.2.3.13Fb UE Measurement Parameter Modification Allowed

 $Indicates\ if\ the\ SRNC\ may\ modify\ the\ UE\ measurement\ parameters\ based\ on\ its\ existing\ measurement\ schedule.$

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
UE Measurement			ENUMERAT	
Parameter Modification			ED	
Allowed			(Parameter	
			Modification	
			Allowed,)	

9.2.3.13Fc UE Measurement Report Characteristics

The UE Measurement Report Characteristics, defines how the reporting shall be performed. For definition of the event criteria see TS 25.331 [16].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE UE Report				
Characteristics				
>Periodic				
>>Amount of Reporting	M		ENUMERAT	
			ED(1, 2, 4, 8,	
			16, 32, 64,	
			infinity)	
>>Reporting Interval	M		ENUMERAT	Indicates the interval of
			ED (250,	periodical report interval in
			500, 1000,	milliseconds
			2000, 3000,	
			4000, 6000,	
			8000, 12000,	
			16000,	
			20000,	
			24000,	
			28000,	
			32000,	
			64000)	
>Event 1h			0.000/	
>>UE Measurement	M		9.2.3.13Fd	The threshold for which the
Threshold				DRNS shall trigger a
				measurement report.
>>UE Measurement	M		9.2.3.13Fg	
Time to Trigger				
>>Hysteresis	M		9.2.3.13Fa	
>Event 1i				
>>UE Measurement	M		9.2.3.13Fd	The threshold for which the
Threshold				DRNS shall trigger a
				measurement report.
>>UE Measurement	M		9.2.3.13Fg	
Time to Trigger				
>>Hysteresis	M		9.2.3.13Fa	
>Event 6a				
>>UE Measurement	M		9.2.3.13Fd	
Threshold	<u> </u>			
>>UE Measurement	M		9.2.3.13Fg	
Time to Trigger				
>Event 6b				
>>UE Measurement	M		9.2.3.13Fd	
Threshold				
>>UE Measurement	М		9.2.3.13Fg	
Time to Trigger				
>Event 6c				
>>UE Measurement	М		9.2.3.13Fg	
Time to Trigger	"		5. <u>2</u> .5.15.19	
>Event 6d	1			
	М		9.2.3.13Fg	
>>UE Measurement			1 9 2 3 13 10	

9.2.3.13Fd UE Measurement Threshold

The Measurement Threshold defines which threshold that shall trigger Event 1h, 1i, 6a or 6b, see TS 25.331 [16].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE UE Measurement Threshold				
>Timeslot ISCP				
>>Timeslot ISCP	М		INTEGER (-11525)	In dBm
>UE Tx Power				
>>UE Transmitted Power	М		INTEGER(- 5033)	In dBm

9.2.3.13Fe UE Measurement Timeslot Information HCR

The *UE Measurement Time Slot Information* IE provides information for DL timeslots for the UE to measure, see TS 25.331 [16].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UE Measurement Timeslot Information		1 <maxnoofts></maxnoofts>		
>Time Slot	М		9.2.1.56	
>Burst Type	М		ENUMERAT ED(Type1, Type 2, Type 3,)	

Range bound	Explanation
maxnoofTSs	Maximum number of Timeslots for a UE for 3.84Mcps TDD.

9.2.3.13Ff UE Measurement Timeslot Information LCR

The *UE Measurement Time Slot Information LCR* IE provides information for DL timeslots for the UE to measure, see TS 25.331 [16].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UE Measurement Time Slot Information LCR		1 <maxnooftslcr ></maxnooftslcr 		
>Time Slot LCR	M		9.2.3.12a	

Range bound	Explanation
maxnoOfTSLCR	Maximum number of Timeslots for a UE for 1.28Mcps TDD

9.2.3.13Fg UE Measurement Time to Trigger

The UE time to trigger indicates the period of time between the timing of event detection and the timing of sending Measurement Report, see TS 25.331 [16].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UE Measurement Time to trigger	M		ENUMERAT ED(0, 10, 20,	Time in ms.
			40, 60, 80, 100, 120,	

		160, 200,	
		240, 320,	
		640, 1280,	
		2560, 5000)	

9.2.3.13Fh UE Measurement Type

The UE Measurement Type identifies the type of measurement that shall be performed see TS 25.331 [16].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UE Measurement Type	М		ENUMERAT	
			ED(Primary	
			CCPCH	
			RSCP, DL	
			Timeslot	
			ISCP, UE	
			Transmitted	
			Power,)	

9.2.3.13Fi UE Measurement Value

The UE Measurement Value shall be the most recent value for this measurement, for which the reporting criteria were met.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE UE Measurement Value	М			
>UE Transmitted Power				
>>UE Transmitted Power list HCR		0 <maxnoofts></maxnoofts>		Mandatory for 3.84Mcps TDD, not applicable to 1.28Mcps TDD or 7.68Mcps TDD
>>>Time Slot	M		9.2.1.56	
>>>UE Transmitted Power	M		INTEGER (0104)	According to mapping in TS 25.123 [24] Values 020 are not used
>>UE Transmitted Power list LCR		0< maxnoOfTSLCR>		Mandatory for 1.28Mcps TDD, not applicable to 3.84Mcps TDD or 7.68Mcps TDD
>>>Time Slot LCR	М		9.2.3.12a	
>>>UE Transmitted Power	M		INTEGER (0104)	According to mapping in TS 25.123 [24] Values 020 are not used
>>UE Transmitted Power list 768		0 <maxnoofts></maxnoofts>		Mandatory for 7.68Mcps TDD, not applicable to 1.28Mcps TDD or 3.84Mcps TDD
>>>Time Slot	M		9.2.1.56	
>>>UE Transmitted Power	M		INTEGER (0104)	According to mapping in TS 25.123 [24] Values 020 are not used
>P-CCPCH RSCP				
>>Primary CCPCH RSCP	0		9.2.3.5	According to mapping in TS 25.123 [24]
>>Primary CCPCH RSCP Delta	0		9.2.3.5a	According to mapping in TS 25.123 [24]
>DL Timeslot ISCP				
>>Timeslot list HCR		0 <maxnoofts></maxnoofts>		Mandatory for 3.84Mcps TDD, not applicable to 1.28Mcps TDD or 7.68Mcps TDD
>>>Time Slot	М		9.2.1.56	
>>>Timeslot	M		9.2.3.12	

ISCP				
>>Timeslot list LCR		0 <maxnooftsl CR></maxnooftsl 		Mandatory for 1.28Mcps TDD, not applicable to 3.84Mcps TDD or 7.68Mcps TDD
>>>Time Slot LCR	М		9.2.3.12a	
>>>Timeslot ISCP	M		9.2.3.12	
>>Timeslot list 768		0 <maxnoofts></maxnoofts>		Mandatory for 7.68Mcps TDD, not applicable to 1.28Mcps TDD or 3.84Mcps TDD
>>>Time Slot	М		9.2.1.56	
>>>Timeslot ISCP	М		9.2.3.12	

Range bound	Explanation
maxnoOfTS	Maximum number of Timeslots for a UE for 3.84Mcps TDD or
	7.68Mcps TDD.
maxnoofTSLCR	Maximum number of Timeslots for a UE for 1.28Mcps TDD.

9.2.3.13Fj UE Measurement Value Information

The *UE Measurement Value Information* IE provides information both on whether or not the UE Measurement Value is provided in the message and if provided also the UE Measurement Value itself.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Measurement Availability Indicator	М			
>Measurement Available				
>>UE Measurement Value	М		9.2.3.13Fi	
>Measurement not Available			NULL	

9.2.3.13G UL Timeslot Information LCR

The UL Timeslot Information LCR IE provides information on the timeslot allocation for an UL DPCH.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
UL Timeslot Information LCR		1 <maxn oofULts LCR></maxn 			-	
>Time Slot LCR	M		9.2.3.12a		_	
>Midamble Shift LCR	M		9.2.3.4C		_	
>TFCI Presence	M		9.2.1.57		_	
>UL Code Information LCR	M		TDD UL Code Information LCR 9.2.3.10B			
>PLCCH Information	0		9.2.3.17		YES	ignore

Range bound	Explanation
maxnoofULtsLCR	Maximum number of Uplink time slots per Radio Link for 1.28Mcps
	TDD.

9.2.3.13H UL Time Slot ISCP Info LCR

The *UL Time Slot ISCP Info LCR* IE provides information for UL Interference level for each time slot within the Radio Link for 1.28Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
UL Time Slot ISCP Info		1 <maxnooful tsLCR></maxnooful 			_	
>Time Slot LCR	M		9.2.3.12a		_	
>UL Timeslot ISCP	M		9.2.3.26A		-	

Range bound	Explanation
maxnoofULtsLCR	Maximum number of Uplink time slots per Radio Link for 1.28Mcps
	TDD

9.2.3.13I Uplink Synchronisation Frequency

The UL Synchronisation Frequency IE specifies the frequency of the adjustment of the uplink transmission timing.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Uplink synchronisation frequency			INTEGER (18)	Unit: subframe, step: 1

9.2.3.13J Uplink Synchronisation Step Size

The *UL Synchronisation Step Size* IE specifies the step size to be used for the adjustment of the uplink transmission timing.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Uplink synchronisation step size			INTEGER (18)	Unit: 1/8 chip, step: 1.

9.2.3.13K Uplink Timing Advance Control LCR

The Uplink Timing Advance Control LCR indicates the parameters which are used to support Uplink Synchronisation for the UE in 1.28Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
SYNC UL codes bitmap	М		BITSTRING (8)	Each bit indicates the availability of a SYNC_UL code.
FPACH info		1		
>Time Slot LCR	M		9.2.3.12a	
>TDD Channelisation Code LCR	М		9.2.3.8a	
>Midamble Shift LCR	M		9.2.3.4C	
>WT	М		INTEGER (14)	Maximum number of subframes to wait for transmission of FPACH.
PRXupPCHdes	М		INTEGER (-120 – 58,)	Desired UpPCH receive power. Unit: dBm Step size: 1
SYNC UL procedure		1		
parameters				
>Maximum Sync UL transmissions	М		ENUMERATED (1,2,4,8,)	
>Power Ramp Step	M		INTEGER (03,)	
Mmax	М		INTEGER (132)	Maximum number of synchronisation attempts

9.2.3.13L USCH ID

The USCH ID is the identifier of an uplink shared channel. It is unique among the USCHs simultaneously allocated for the same UE.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
USCH ID			INTEGER (0255)	

9.2.3.14 USCH Information

The USCH $\mathit{Information}$ IE provides information for USCHs to be established.

IE/Group Name	Presenc e	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
USCH Information		1 to <maxnoofu SCHs></maxnoofu 			1	
>USCH ID	M		9.2.3.14		ı	
>CCTrCH ID	M		9.2.3.2	UL CCTrCH in which the USCH is mapped	-	
>TrCH Source Statistics Descriptor	М		9.2.1.65		ı	
>Transport Format Set	M		9.2.1.64	For USCH	_	
>Allocation/Retention Priority	M		9.2.1.1		_	
>Scheduling Priority Indicator	М		9.2.1.51A		-	
>RB Info		1 <maxnoof RB></maxnoof 		All Radio Bearers using this USCH	-	
>>RB Identity	М		9.2.3.5B		_	
>Traffic class	М		9.2.1.58A		YES	ignore
>Binding ID	0		9.2.1.3	Shall be ignored if bearer establishme nt with ALCAP.	YES	ignore
>Transport Layer Address	0		9.2.1.62	Shall be ignored if bearer establishme nt with ALCAP.	YES	ignore
>TNL QoS	0		9.2.1.56A	1	YES	ignore

Range bound	Explanation
maxnoofUSCHs	Maximum number of USCHs for one UE.
maxnoofRBs	Maximum number of Radio Bearers for one UE.

9.2.3.16 Support of PLCCH

The Support of PLCCH IE indicates whether PLCCH is supported or not.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Support of PLCCH			ENUMERAT	
			ED(supported	
)	

9.2.3.17 PLCCH Information

The *PLCCH Information* IE carres a PLCCH assignment for a timeslot of an UL DCH-type CCTrCH.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
TDD Channelisation Code	M		9.2.3.8	Only QPSK modulation is used with PLCCH
Time Slot LCR	M		9.2.3.12a	
Midamble Shift LCR	M		9.2.3.4C	
PLCCH Sequence Number	M		9.2.3.18	

9.2.3.18 PLCCH Sequence Number

This sequence number represents a portion of a PLCCH used to signal TPC / SS bits to a single UE. A value of zero indicates that the PLCCH assignment has been deleted.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
PLCCH Sequence Number			INTEGER (014)	

9.2.3.19 Minimum Spreading Factor 7.68Mcps

Defines the minimum spreading factor the UE has the capability of receiving or transmitting for 7.68Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Minimum Spreading Factor 768			INTEGER (132)	

9.2.3.20 Maximum Number of DL Physical Channels 7.68Mcps

Defines the maximum number of physical channels for 7.68Mcps TDD – per frame that the UE is capable to receive.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Maximum Number of DL			INTEGER	
Physical Channels 768			(1448)	

9.2.3.21 Maximum Number of DL Physical Channels per Timeslot 7.68Mcps

Defines the maximum number of physical channels per timeslot that the UE is capable to receive for 7.68 Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Maximum Number of DL Physical Channels per Timeslot 768			INTEGER (132)	

9.2.3.22 Secondary CCPCH Info 7.68Mcps TDD

The *Secondary CCPCH Info 7.68Mcps TDD* IE provides information on the Secondary CCPCH that carries the logical channel SHCCH for the UE for 7.68Mcps TDD.

IE/Group Name	Presence	Range	IE Type and	Semantics Description	Criticality	Assigned Criticality
			Reference			
TFCS	M		9.2.1.63	For the DL.	_	
TFCI Coding	M		9.2.3.11		_	
Secondary CCPCH		0 <maxno ofSCCPC Hs768></maxno 			_	
>Time Slot	М		9.2.1.56		_	
>Midamble Shift And Burst Type 7.68Mcps	М		9.2.3.23		_	
>TFCI Presence	M		9.2.1.55		_	
>Secondary CCPCH TDD Code Information 7.68Mcps	М		9.2.3.24		_	
>TDD Physical Channel Offset	М		9.2.3.9		_	
>Repetition Length	M		9.2.3.6		_	
>Repetition Period	M		9.2.3.7		_	
FACH		0maxnoo fFACHs			_	
>TFS	M		9.2.1.64	For the DL.	_	
PCH		01			_	
>TFS	M		9.2.1.64	For the DL.	_	

Range bound	Explanation
maxnoofSCCPCHs768	Maximum number of Secondary CCPCHs per CCTrCH.
maxnoofFACHs	Maximum number of FACHs mapped onto a Secondary CCPCH.

9.2.3.23 Midamble Shift And Burst Type 7.68Mcps

This information element indicates burst type and midamble allocation for 7.68Mcps TDD.

Three different midamble allocation schemes exist:

- Default midamble: the midamble is allocated by layer 1 depending on the associated channelisation code (DL and UL);
- Common midamble: the midamble is allocated by layer 1 depending on the number of channelisation codes (possible in DL only);
- UE specific midamble: a UE specific midamble is explicitly assigned (DL and UL).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CHOICE Burst Type				
>Type 1				
>> Midamble Configuration Burst Type 1 And 3	M		ENUMERATED(4, 8, 16)	As defined in TS 25.221 [12]
>>Midamble Allocation Mode	M		ENUMERATED(Defa ult midamble, Common midamble, UE specific midamble)	
>>Midamble Shift Long	C-UE		INTEGER(015)	
>Type 2				
>> Midamble Configuration Burst Type 2	М		ENUMERATED (4, 8)	As defined in TS 25.221 [12]
>>Midamble Allocation Mode	M		ENUMERATED(Defa ult midamble, Common midamble, UE specific midamble)	
>>Midamble Shift Short	C-UE		INTEGER (07)	
>Type 3				UL only
>> Midamble Configuration Burst Type 1 And 3	M		ENUMERATED (4, 8, 16)	As defined in TS 25.221 [12]
>>Midamble Allocation Mode	М		ENUMERATED(Defa ult midamble, UE specific midamble)	
>>Midamble Shift Long	C-UE		INTEGER(015)	

Condition	Explanation
UE	The IE shall be present if the Midamble Allocation
	Mode IE is set to "UE-specific midamble".

9.2.3.24 Secondary CCPCH TDD Code Information 7.68Mcps

The Secondary CCPCH TDD Code Information 7.68Mcps IE provides TDD Channelisation Code information for all SCCPCHs of one Time Slot for 7.68Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Secondary CCPCH TDD Code Information 7.68Mcps		1 <maxno OfSCCPC Hs768></maxno 			_	
>TDD Channelisation Code 7.68Mcps	М		9.2.3.25		_	

Range bound	Explanation
maxnoofSCCPCHs768	Maximum number of SCCPCHs for one CCTrCH.

9.2.3.25 TDD Channelisation Code 7.68Mcps

The Channelisation Code Number indicates which Channelisation Code is used for a given Physical Channel. In 7.68Mcps TDD the Channelisation Code is an Orthogonal Variable Spreading Factor code that can have a spreading factor of 1, 2, 4, 8, 16 or 32.

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
TDD Channelisation			ENUMERATED((1/1)	
Code			, (2/1), (2/2), (4/1),	
			(4/4), (8/1), (8/8),	
			(16/1), (16/16),	
			(32/1), (32,32),)	

9.2.3.26 UL Timeslot Information 7.68Mcps

The *UL Timeslot Information* IE provides information on the time slot allocation for a UL DPCH for 7.68Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
UL Timeslot Information		1 <maxno OfTS></maxno 			_	
>Time Slot	M		9.2.1.56		_	
>Midamble Shift And Burst Type 7.68Mcps	М		9.2.3.23		_	
>TFCI Presence	M		9.2.1.55		_	
>UL Code Information 7.68Mcps	М		TDD UL Code Information 7.68Mcps 9.2.3.27		_	

Range bound	Explanation		
maxnoofTSs	Maximum number of Timeslots for a UE.		

9.2.3.27 TDD UL Code Information 7.68Mcps

The *TDD UL Code Information 7.68Mcps* IE provides TDD UL Code information for all DPCHs of one UL Time Slot for 7.68Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
TDD UL Code Information		1 <maxno OfDPCHs 768></maxno 			_	
>DPCH ID	M		9.2.3.3		_	
>TDD Channelisation Code 7.68Mcps	М		9.2.3.25		_	

Range bound	Explanation		
maxnoofDPCHs768	Maximum number of DPCHs for one CCTrCH.		

9.2.3.28 DL Timeslot Information 7.68Mcps

The *DL Timeslot Information 7.68Mcps* IE provides information on the time slot allocation for a DL DPCH for 7.68Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
DL Timeslot Information		1 <maxno OfTS></maxno 			_	
>Time Slot	М		9.2.1.56		_	
>Midamble Shift And Burst Type 7.68Mcps	M		9.2.3.23		_	
>TFCI Presence	М		9.2.1.55		_	
>DL Code Information 7.68Mcps	М		TDD DL Code Information 7.68Mcps 9.2.3.29		_	

Range bound	Explanation		
maxnoofTSs	Maximum number of Timeslots for a UE.		

9.2.3.29 TDD DL Code Information 7.68Mcps

The *TDD DL Code Information* IE provides TDD DL Code information for all DPCHs of one DL Time Slot for 7.68Mpcs TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
TDD DL Code Information		1 <maxno OfDPCHs 768></maxno 			-	
>DPCH ID	M		9.2.3.3		-	
>TDD Channelisation Code 7.68Mcps	М		9.2.3.25		_	

Range bound	Explanation		
maxnoofDPCHs768	Maximum number of DPCHs for one CCTrCH.		

9.2.3.30 Rx Timing Deviation 7.68Mcps

Measured Rx Timing Deviation as a basis for timing advance, either measured directly from a RACH burst, or calculated from the Rx Timing Deviation measurement on the USCH by adding the current Timing Advance value..

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Rx Timing Deviation			INTEGER	As specified in TS 25.435 [5]
			(01023)	

9.2.3.31 Cell Capability Container 7.68 Mcps TDD

The Cell Capability Container 7.68 McpsTDD indicates which functionalities a cell supports.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Cell Capability Container TDD			BIT STRING (32)	Each bit indicates whether a cell supports a particular functionality or not. The value 1 of a bit indicates that the corresponding functionality is supported in a cell and value 0 indicates that the corresponding functionality is not supported in a cell. Each bit is defined as follows. The first bit: Delayed Activation Support Indicator. The second bit: HS-DSCH Support Indicator. The third bit: DSCH Support Indicator. The fourth bit: Flexible MAC-d PDU Size Support Indicator. Note that undefined bits are considered as a spare bit and spare bits shall be set to 0 by the transmitter and shall be ignored by the receiver.

9.2.3.32 Neighbouring TDD Cell Measurement Information 7.68Mcps

This IE provides information on the 7.68Mcps TDD neighbouring cells used for the purpose of Measurements. Since the measurement can be performed on every time slot and midamble shift, the *Time slot* IE and *Midamble shift and burst type* IE shall be included if available.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UTRAN Cell Identifier	M		9.2.1.71	
UARFCN	М		9.2.1.66	Corresponds to Nt TS 25.105 [7]
Cell Parameter ID	М		9.2.1.8	
Time slot	0		9.2.1.56	
Midamble Shift And Burst Type 7.68Mcps	0		9.2.3.23	

9.2.3.33 UE Measurement Timeslot Information 7.68Mcps

The *UE Measurement Time Slot Information* IE provides information for DL timeslots for the UE to measure, see TS 25.331 [16].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UE Measurement		1 <maxnoofts></maxnoofts>		
Timeslot Information				
>Time Slot	M		9.2.1.56	
>Burst Type	M		ENUMERATED	
			(Type1, Type 2,	
			Type 3,)	

Range bound	Explanation		
maxnoofTSs	Maximum number of Timeslots for a UE for 7.68Mcps TDD.		

9.2.3.34 DPCH ID 7.68Mcps

The DPCH ID 7.68Mcps identifies unambiguously a DPCH inside a downlink Radio Link for 7.68Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
DPCH ID			INTEGER (0479)	

9.2.3.35 Rx Timing Deviation 3.84Mcps Extended

Measured Rx Timing Deviation as a basis for timing advance, either measured directly from a RACH burst, or calculated from the Rx Timing Deviation measurement on the USCH by adding the current Timing Advance value. This is used when the extended timing advance is in use at 3.84 Mcps.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Rx Timing Deviation			INTEGER	As specified in TS 25.435 [5]
			(0511)	

9.2.3.36 E-PUCH Information

The *E-PUCH Information* IE provides parameters to configure the E-PUCH physical channel for 3.84Mcps TDD and 7.68 Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Minimum code rate	M		INTEGER (063)	Unit: - Range: 0.0551 Step: 0.015
Maximum code rate	M		INTEGER (063)	Unit: - Range: 0.0551 Step: 0.015
HARQ Info for E-DCH	M		ENUMERATED (rv0, rvtable)	"rv0" indicates that the UE will only use E_DCH RV index 0. "rvtable" indicates that the UE will use an RSN based RV index as specified in TS 25.211 [8]
N _{E-UCCH}	M		INTEGER (112)	Number of slots that are required to carry TPC and TFCI (consecutively allocated slots beginning with the first).

9.2.3.36a E-PUCH Information LCR

The *E-PUCH Information LCR* IE provides parameters to configure the E-PUCH physical channel for 1.28Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Minimum code rate	М		INTEGER (063)	Unit: - Range: 0.055 1 Step: 0.015	-	
Maximum code rate	M		INTEGER (063)	Unit: - Range: 0.0551 Step: 0.015	-	
HARQ Info for E-DCH	M		ENUMERAT ED (rv0, rvtable)	"rv0" indicates that the UE will only use E_DCH RV index 0. "rvtable" indicates that the UE will use an RSN based RV index as specified in TS 25.211 [8]	-	
PRXdes_base	М		INTEGER (-11250)	dBm. Reference Desired RX power level for E-PUCH	-	
E-PUCH TPC Step Size	M		9.2.3.10a		-	
Ne-ucch	M		INTEGER (18)	Number of E- UCCH and TPC instances within an E- DCH TTI. Details are described in TS 25.221 [12].	-	
E-PUCH Power Control GAP	0		INTEGER (1255)	Unit: Number of subframes. Reference to E-PUCH Power Control for 1.28Mcps TDD in TS 25.224 [22]. If it is not present, UE shall deem it to be infinite in which case closed loop power control shall always be used.	YES	ignore

9.2.3.37 E-TFCS Information TDD

Whereas the related E-DCH Transport Block sizes are standardised in TS 25.425 [32] this IE gives details on the Reference Betas.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Reference Beta Information QPSK		1 <maxnoofrefbe tas=""></maxnoofrefbe>		
>Reference Code Rate	М		INTEGER (010)	Unit: - Range: 01 Step: 0.1
>Reference Beta	М		INTEGER(-1516)	Unit: - Range: -15+16 Step: 1 dB
Reference Beta Information 16QAM		1 <maxnoofrefbe tas=""></maxnoofrefbe>		
>Reference Code Rate	М		INTEGER (010)	Unit: - Range: 01 Step: 0.1
>Reference Beta	M		INTEGER(-1516)	Unit: - Range: -15+16 Step: 1 dB

Range Bound	Explanation	
maxnoofRefbetas	Maximum number of signalled reference betas	

9.2.3.38 E-DCH MAC-d Flows Information TDD

The *E-DCH MAC-d Flows Information TDD* IE is used for the establishment of E-DCH MAC-d flows for TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
E-DCH MAC-d Flow Specific Information		1 <maxno ofEDCHM ACdFlows ></maxno 			-	•
>E-DCH MAC-d Flow ID	М		9.2.1.91		_	
>Allocation/Retentio n Priority	М		9.2.1.1		ı	
>TNL QoS	0		9.2.1.56A		_	
>Binding ID	0		9.2.1.3	Shall be ignored if bearer establishmen t with ALCAP.	-	
>Transport Layer Address	0		9.2.1.62	Shall be ignored if bearer establishmen t with ALCAP.	-	
>Payload CRC Presence Indicator	М		9.2.1.42		-	
>Maximum Number Of Retransmissions For E-DCH	М		9.2.1.100		-	
>E-DCH HARQ Power Offset TDD	М		9.2.3.49		-	
>E-DCH MAC-d Flow Multiplexing List	0		9.2.1.89		-	
>E-DCH Grant Type	М		9.2.3.43		-	
>E-DCH Logical Channel Information	М		9.2.1.92		_	
>E-DCH MAC-d Flow Retransmission Timer	0		9.2.3.49a	Mandatory for LCR TDD. Not applicable for 3.84Mcps TDD and 7.68Mcps TDD.	YES	YES
>Traffic Class	М		9.2.1.58A		YES	ignore

Range Bound	Explanation
maxnoofEDCHMACdFlows	Maximum number of E-DCH MAC-d flows

9.2.3.39 E-DCH Non-scheduled Grant Information TDD

The *E-DCH Non-scheduled Grant Information TDD* IE is used to specify the details of an non-scheduled grant for 3.84Mcps and 7.68Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Timeslot Resource Related Information	M		9.2.3.44	
Power Resource Related Information	M		9.2.3.45	
Repetition Period	M		9.2.3.6	
Repetition Length	M		9.2.3.7	
TDD E-PUCH Offset	M		9.2.3.46	
TDD Channelisation Code	M		9.2.3.8	

9.2.3.39a E-DCH Non-scheduled Grant Information LCR TDD

The *E-DCH Non-scheduled Grant Information LCR TDD* IE is used to specify the details of an non-scheduled grant for 1.28Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Timeslot Resource Related Information LCR	М		9.2.3.44a	
Power Resource Related Information	М		9.2.3.45	
Repetition Period	M		9.2.3.6	
Repetition Length	M		9.2.3.7	
Subframe Number	М		ENUMERATED (0,1)	Used to indicate from which subframe of the Radio Frame indicated by TDD E-PUCH Offset IE the physical resources are assigned to the E-DCH Non-scheduled Grant.
TDD E-PUCH Offset	M		9.2.3.46	
TDD Channelisation Code	M		9.2.3.8	

9.2.3.40 E-DCH TDD Information

The *E-DCH TDD Information* specifies the details of the maximum bit rate and processing overload level.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH TDD Maximum Bitrate	0		9.2.3.47	
E-DCH Processing Overload Level	0		9.2.1.95	
E-DCH Power Offset for Scheduling Info	0		9.2.1.96	

9.2.3.40a E-DCH TDD Information LCR

The *E-DCH TDD Information LCR* IE specifies the details of UE physical layer category, NodeB processing overload level and power offset, Maximum Number of Retransmission and E-DCH Retransmission timer for scheduling info. The *E-AGCH Inactivity Monitor Threshold* IE is used for E-AGCH channel monitoring control for scheduled transmission.

IE/Group Name	Presenc e	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
E-DCH Physical Layer Category LCR	0		9.2.3.54	If the Extended E-DCH Physical Layer Category LCR IE is included in the E-DCH TDD Information LCR IE, the E-DCH Physical Layer Category LCR IE shall be ignored. In case of multicarrier E-DCH, this IE indicates the capability for each carrier.	-	
E-DCH Processing Overload Level	0		9.2.1.95		_	
E-DCH Power Offset for Scheduling Info	0		9.2.1.96		_	
Extended E-DCH Physical Layer Category LCR	0		9.2.3.54A	The Extended E-DCH Physical Layer Category LCR IE shall be used if the E-DCH Physical Layer Category has a value larger than 5. In case of multi- carrier E-DCH, this IE indicates the capability for each carrier.	YES	reject
Maximum Number of Retransmission for Scheduling Info LCR	0		9.2.1.100		YES	ignore
E-DCH Retransmission timer for Scheduling Info LCR	0		9.2.3.49a		YES	ignore
E-AGCH Inactivity Monitor Threshold	0		Enumerated (0, 1, 2, 4, 8, 16, 32, 64, 128, 256, 512, spare5,, infinity)	Units of subframes.	YES	ignore
SNPL Carrier Group Indicator	0		INTEGER (13)	Applicable to 1.28Mcps TDD in multi-carrier E- DCH operation only. The absence of this IE indicates the corresponding frequency belongs to a separate SNPL carrier group which only contains this carrier. The SNPL carrier group is defined in [16].	YES	reject

Multi-Carrier E-DCH Physical Layer Category LCR	0	9.2.3.54B	Applicable to 1.28Mcps TDD in multi-carrier E- DCH operation only.	YES	reject
UE TS0 Capability LCR	0	ENUMERAT ED (TS0 Capable, TS0 Non- Capable)	Applicable to 1.28Mcps TDD only.	YES	ignore

9.2.3.41 E-DCH TDD Information Response

The *E-DCH TDD Information Response* IE provides information for E-DCH MAC-d flows that have been established or modified. It also provides additional E-DCH information determined within the Node B.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH MAC-d Flow		0 <maxnoofedc< td=""><td></td><td></td></maxnoofedc<>		
Specific Information		HMACdFlows>		
Response				
>E-DCH MAC-d Flow ID	M		9.2.1.91	
>Binding ID	0		9.2.1.3	
>Transport Layer	0		9.2.1.62	
Address				
E-AGCH Specific		0 <maxnoofeag< td=""><td></td><td></td></maxnoofeag<>		
Information Response		CHcodes>		
>Time Slot	M		9.2.1.56	
>Midamble Shift And	M		9.2.3.4	
Burst Type				
>TDD Channelisation	M		9.2.3.8	
Code				
E-HICH Information		01		
Response				
>Time Slot	M		9.2.1.56	
>Midamble Shift And	M		9.2.3.4	
Burst Type				
>TDD Channelisation	M		9.2.3.8	
Code				
>E-HICH Time Offset	M		9.2.3.48	
E-DCH Non-scheduled	0		9.2.3.39	
Grant Information TDD				
E-RNTI	0		9.2.1.94	

Range bound	Explanation
maxnoofEDCHMACdFlows	Maximum number of MAC-d flows
maxnoofEAGCHcodes	Maximum number of E-AGCHs assigned to one UE

9.2.3.41a E-DCH TDD Information Response 1.28Mcps

Only for 1.28Mcps TDD. The *E-DCH TDD Information Response 1.28Mcps* IE provides information for E-DCH MAC-d flows that have been established or modified. It also provides additional E-DCH information determined within the Node B.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH MAC-d Flow		0 <maxnoofedc< td=""><td></td><td></td></maxnoofedc<>		
Specific Information		HMACdFlows>		
Response				
>E-DCH MAC-d Flow ID	M		9.2.1.91	
>Binding ID	0		9.2.1.3	
>Transport Layer	0		9.2.1.62	
Address				
E-AGCH Specific		0 <maxnoofeag< td=""><td></td><td></td></maxnoofeag<>		
Information Response		CHcodes>		
>Time Slot LCR	M		9.2.3.12a	
>Midamble Shift LCR	М		9.2.3.4C	
>TDD Channelisation	M		9.2.3.8	
Code				
E-HICH Scheduled		01		
specific Information				
Response				
>Scheduled		0<		
		maxNoOfEHICHc		
		odes>		
>>El	М		INTEGER (03)	E-HICH indication which is used to indicate UE on which E-HICH the feedback
				info is carried.
>>Time Slot LCR	M		9.2.3.12a	
>>Midamble Shift LCR	M		9.2.3.4C	
>>TDD Channelisation	M		9.2.3.8	
Code				
>Non-Scheduled		01		
>>Time Slot LCR	M		9.2.3.12a	
>>Midamble Shift LCR	M		9.2.3.4C	
>>TDD Channelisation	M		9.2.3.8	
Code				
>>Signature Sequence	M		INTEGER	
Group Index			(019)	
>E-HICH time offset LCR	M		9.2.3.48a	
E-DCH Non-scheduled	0		9.2.3.39a	
Grant Information LCR				
TDD				
E-RNTI	0		9.2.1.94	

Range bound	Explanation
maxnoofEDCHMACdFlows	Maximum number of MAC-d flows
maxnoofEAGCHcodes	Maximum number of E-AGCHs assigned to one UE
maxnoofEHICHcodes	Maximum number of E-HICHs assigned to one UE

9.2.3.42 E-DCH TDD Information to Modify

The *E-DCH MAC-d Flows Information TDD* IE is used for the establishment of E-DCH MAC-d flows for TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
E-DCH MAC-d Flow Specific Information		1 <maxno ofEDCHM ACdFlows ></maxno 			_	
>E-DCH MAC-d Flow ID	М		9.2.1.91		_	
>Allocation/Retention Priority	0		9.2.1.1		_	
>Transport Bearer Request Indicator	М		9.2.1.61		_	
>Binding ID	0		9.2.1.3	Shall be ignored if bearer establishment with ALCAP.	_	
>Transport Layer Address	0		9.2.1.62	Shall be ignored if bearer establishment with ALCAP.	_	
>TNL QoS	0		9.2.1.56A		_	
>Maximum Number Of Retransmissions For E-DCH	0		9.2.1.100		-	
>E-DCH HARQ Power Offset TDD	0		9.2.3.49		_	
>E-DCH MAC-d Flow Multiplexing List	0		9.2.1.89		_	
>E-DCH Grant Type	0		9.2.3.43		_	
>E-DCH Logical Channel To Add	0		E-DCH Logical Channel Information 9.2.1.92		-	
>E-DCH Logical Channel To Modify	0		9.2.1.93		_	
>E-DCH Logical Channel To Delete		0< maxnooflo gicalchann els>			_	
>>Logical Channel ID	М		9.2.1.97		_	
>E-DCH MAC-d Flow Retransmission Timer	0		9.2.3.49a	Applicable for 1.28Mcps TDD only	YES	ignore
>Traffic Class	0		9.2.1.58A		YES	ignore
MAC-e Reset Indicator	0		9.2.1.99		_	
E-DCH MAC-d PDU Size Format	0		9.2.1.91A		YES	reject
UE TS0 Capability LCR	0		ENUMERATE D (TS0 Capable, TS0 Non-Capable)	Applicable to 1.28Mcps TDD only.	YES	ignore

Range Bound	Explanation
maxnoofEDCHMACdFlows	Maximum number of E-DCH MAC-d flows
maxnooflogicalchannels	Maximum number of logical channels

9.2.3.43 E-DCH Grant Type

The $E ext{-}DCH$ Grant Type identifies whether a MAC-d flow is scheduled or non-scheduled.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH Grant Type			ENUMERATED	
			(Scheduled,	
			Non-scheduled)	

9.2.3.44 Timeslot Resource Related Information

The *Timeslot Resource Related Information* is a bitmap indicating which of the timeslots configured for E-DCH are allocated for non-scheduled transmissions.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Timeslot Resource Related			BIT STRING	
Information			(13)	

9.2.3.44a Timeslot Resource Related Information LCR

The *Timeslot Resource Related Information LCR* IE is a bitmap indicating which of the timeslots configured for E-DCH are allocated for non-scheduled transmissions.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Timeslot Resource Related Information LCR			BIT STRING (5)	

9.2.3.45 Power Resource Related Information

The *Power Resource Related Information* specifies the maximum allowed E-PUCH power resource (dB relative to P_{e-base}) that the UE may use for non-scheduled transmissions.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Power Resource Related			INTEGER	
Information			(132)	

9.2.3.46 E-PUCH Offset

The E-PUCH Offset represents the CFN offset at which an non-scheduled E-DCH grant begins.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-PUCH Offset			INTEGER (0255)	
L	1		(0200)	

9.2.3.47 E-DCH TDD Maximum Bitrate

The E-DCH TDD Maximum Bitrate parameter indicates the Maximum Bitrate for an E-DCH in TDD mode.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH TDD Maximum			INTEGER	Bitrate on transport block
Bitrate			(09201,)	level. Unit is kbits per
				second.

9.2.3.48 E-HICH Time Offset

The E-HICH Time Offset (aka $n_{\text{E-HICH}}$ (TS 25.221 [12])) is determined by the Node B.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-HICH Time Offset			INTEGER (444)	

9.2.3.48a E-HICH Time Offset LCR

The *E-HICH Time Offset LCR* IE(aka n_{E-HICH} (TS 25.221 [12])) is determined by the Node B.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-HICH Time Offset LCR			INTEGER (415)	

9.2.3.49 E-DCH HARQ Power Offset TDD

The *E-DCH HARQ Power Offset TDD* is the power offset measured in dB.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH HARQ Power Offset TDD			INTEGER (06)	

9.2.3.49a E-DCH MAC-d Flow Retransmission Timer

The *E-DCH MAC-d Flow Retransmission Timer* IE is used in the E-DCH retransmission control as defined in TS 25.425 [32].

IE/Group Name	Presence	Range	IE Type and	Semantics Description
			Reference	
E-DCH MAC-d Flow			ENUMERATED (10,	Unit: ms
Retransmission Timer			15, 20, 25, 30, 35,	Node B may use this value to
			40, 45, 50, 55, 60,	stop the re-transmission of the
			65, 70, 75, 80, 85,	corresponding MAC-e PDU.
			90, 95, 100, 110,	
			120, 140, 160, 200,	
			240, 280, 320, 400,	
			480, 560,)	

9.2.3.50 E-DCH Non-scheduled Grant Information 7.68Mcps TDD

The *E-DCH Non-scheduled Grant Information 7.68Mcps TDD* IE is used to specify the details of an non-scheduled grant for TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Timeslot Resource Related Information	М		9.2.3.44	
Power Resource Related Information	М		9.2.3.45	
Repetition Period	M		9.2.3.6	
Repetition Length	M		9.2.3.7	
TDD E-PUCH Offset	M		9.2.3.46	
TDD Channelisation Code 7.68Mcps	М		9.2.3.25	

9.2.3.51 E-DCH TDD Information 7.68Mcps

The *E-DCH TDD Information 7.68Mcps* specifies the details of the maximum bit rate and processing overload level for 7.68Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH TDD Maximum Bitrate 7.68Mcps	0		9.2.3.53	
E-DCH Processing Overload Level	0		9.2.1.95	
E-DCH Power Offset for Scheduling Info	0		9.2.1.96	

9.2.3.52 E-DCH TDD Information Response 7.68Mcps

The *E-DCH TDD Information Response 7.68Mcps* IE provides information for E-DCH MAC-d flows that have been established or modified for 7.68Mcps TDD. It also provides additional E-DCH information determined within the Node B

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH MAC-d Flow Specific Information Response		0 <maxnoofedc HMACdFlows></maxnoofedc 		
>E-DCH MAC-d Flow ID	М		9.2.1.91	
>Binding ID	0		9.2.1.3	
>Transport Layer Address	0		9.2.1.62	
E-AGCH Specific Information Response 7.68Mcps		0 <maxnoofeag CHcodes></maxnoofeag 		
>Time Slot	M		9.2.1.56	
>Midamble Shift And Burst Type 7.68Mcps	М		9.2.3.23	
>TDD Channelisation Code 7.68Mcps	М		9.2.3.25	
E-HICH Information Response 7.68Mcps		01		
>Time Slot	M		9.2.1.56	
>Midamble Shift And Burst Type 7.68Mcps	M		9.2.3.23	
>TDD Channelisation Code 7.68Mcps	М		9.2.3.25	
>E-HICH Time Offset	М		9.2.3.48	
E-DCH Non-scheduled Grant Information 7.68Mcps TDD	0		9.2.3.50	
E-RNTI	0		9.2.1.94	

Range Bound	Explanation
maxnoofEDCHMACdFlows	Maximum number of E-DCH MAC-d flows
maxnoofEAGCHcodes	Maximum number of E-AGCHs assigned to one UE

9.2.3.53 E-DCH TDD Maximum Bitrate 7.68Mcps

The *E-DCH TDD Maximum Bitrate 7.68Mcps* parameter indicates the Maximum Bitrate for an E-DCH in 7.68Mcps TDD mode.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH TDD Maximum			INTEGER	Bitrate on transport block
Bitrate 7.68Mcps			(017713,)	level. Unit is kbits per
				second.

9.2.3.54 E-DCH Physical Layer Category LCR

Only for 1.28Mcps TDD. The *E-DCH Physical Layer Category LCR* IE parameter indicates the E-DCH physical layer capability of UE in LCR TDD mode.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH Physical Layer			INTEGER (15)	As defined in TS 25.306 [42]
Category LCR				

9.2.3.54A Extended E-DCH Physical layer Category LCR

Only for 1.28Mcps TDD. The *Extended E-DCH Physical Layer Category LCR* IE parameter indicates the E-DCH physical layer capability of UE in LCR TDD mode.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Extended E-DCH Physical Layer Category LCR			INTEGER(6,)	As defined in TS 25.306 [42]

9.2.3.54B Multi-Carrier E-DCH Physical Layer Category LCR

Only for 1.28Mcps TDD. The *Multi-Carrier E-DCH Physical Layer Category LCR* IE parameter indicates the E-DCH physical layer capability of UE in multi-carrier E-DCH operation mode.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Multi-Carrier E-DCH Physical			INTEGER (18,)	As defined in [42]
Layer Category LCR				

9.2.3.55 UpPCH Information LCR

Only for 1.28Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
UpPCH Information LCR		1 <maxfr equencyin Cell></maxfr 			EACH	ignore
>UARFCN	0		9.2.1.66		_	
>UpPCH Position LCR	0		9.2.3.56		_	

Range Bound	Explanation
maxFrequencyinCell	Maximum number of Frequency that can be defined in a Cell

9.2.3.56 UpPCH Position LCR

Only for 1.28Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UpPCH Position LCR			INTEGER	
			(1127)	

9.2.3.57 Common E-DCH MAC-d Flow ID

The Common E-DCH MAC-d Flow ID IE is the unique identifier for one MAC-d flow on E-DCH.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Common E-DCH MAC-d			INTEGER	
Flow ID			(0255)	

9.2.3.58 Common E-DCH MAC-d Flow Specific Information LCR

The *Common E-DCH MAC-d Flow Specific Information LCR* IE provides information associated to Common E-DCH MAC-d Flow used for Common E-DCH.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Common E-DCH MAC-d Flow Specific		1 <maxnoofedc HMACdFlowsLCR</maxnoofedc 		
Information LCR		>		
>Common E-DCH MAC- d Flow ID	M		9.2.3.57	
>Maximum Number Of Retransmissions For E- DCH	М		9.2.1.100	
>E-DCH HARQ Power Offset TDD	M		9.2.3.49	
>E-DCH MAC-d Flow Multiplexing List	0		9.2.1.89	
>Common E-DCH Logical Channel information	M	1 <maxnooflogica lchannelsLCR></maxnooflogica 		
>>Logical Channel ID	M		9.2.1.97	
>>Maximum MAC-d PDU Size Extended	M		MAC PDU Size Extended 9.2.1.34D	

Range bound	Explanation
maxnoofEDCHMACdFlowsLCR	Maximum number of E-DCH MAC-d Flows for 1.28Mcps TDD
maxnooflogicalchannelsLCR	Maximum number of logical channels

9.2.3.59 MAC-es Maximum Bit Rate LCR

The MAC-es Maximum Bit Rate LCR IE indicates the maximum number of bits per second to be delivered over the air interface.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
MAC-es Maximum Bit Rate LCR			INTEGER (0 256,000,000,	Unit: bit/s
)	

9.2.3.60 Idle Interval Information

The *Idle Interval Information* IE indicates the idle interval used for E-UTRAN measurements by a multi-RAT UE in CELL_DCH state. See TS 36.133 [64].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
K	М		INTEGER (23)	The actual idle interval period = 2 ^k .
Offset	M		INTEGER (07)	The idle interval position in the period.

9.2.3.61 Continuous Packet Connectivity DRX Information LCR

The *Continuous Packet Connectivity DRX Information LCR* IE defines the parameters used for Continuous Packet Connectivity DRX operation for 1.28 Mcps TDD (see TS 25.224 [22]).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Enabling Delay	М		ENUMERATED (0, 1, 2, 4, 8, 16, 32, 64, 128)	Units of radio frames	-	
HS-SCCH DRX Information		1				
>UE DRX Cycle	М		ENUMERATED(1,2,4 ,8,16,32,64,)	Units of subframes	-	
>Inactivity Threshold for UE DRX Cycle	0		ENUMERATED(1,2,4 ,8,16,32,64,)	Units of subframes	-	
>UE DRX Offset	М		INTEGER (063)	Units of subframes. Offset of the UE DRX cycles at the given TTI	-	
>Inactivity Threshold for UE DRX Cycle Ext	0		ENUMERATED(128, 256,512,)	Units of subframes	YES	ignore
E-AGCH DRX Information		01				
CHOICE E-AGCH DRX information type	М					
>Same as HS-SCCH			NULL	Indicate the E-AGCH DRX Cycle and Offset are the same as the HS-SCCH DRX Cycle and Offset, and the E-AGCH Inactivity Monitor Threshold is absent	-	
>E-AGCH DRX parameters						
>>E-AGCH DRX cycle	М		ENUMERATED (1, 2, 4, 8, 16, 32, 64,)	Units of subframes.	-	
>>E-AGCH Inactivity Monitor Threshold	0		ENUMERATED (0, 1, 2, 4, 8, 16, 32, 64, 128, 256, 512, infinity,)	Units of subframes.	-	
>>E-AGCH DRX Offset	М		INTEGER (0 63)	Units of subframes. Offset of the E-AGCH DRX cycles.	-	

9.2.3.62 Continuous Packet Connectivity DRX Information To Modify LCR

The *Continuous Packet Connectivity DRX Information To Modify LCR* IE is used for modification of Continuous Packet Connectivity DRX information in a Node B Communication Context. The *Continuous Packet Connectivity DRX Information To Modify LCR* IE shall include at least one of the following IE.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Enabling Delay	0		ENUMERATED (0, 1, 2, 4, 8, 16, 32, 64, 128)	Units of radio frames	-	
CHOICE DRX Information To Modify	0					
>Modify						
>>HS-SCCH DRX Information		01				
>>>UE DRX Cycle	М		ENUMERATED(1,2,4 ,8,16,32,64,)	Units of subframes	-	
>>>Inactivity Threshold for UE DRX Cycle	0		ENUMERATED(1,2,4 ,8,16,32,64,)	Units of subframes	-	
>>>UE DRX Offset	М		INTEGER (063)	Units of subframes. Offset of the UE DRX cycles at the given TTI	-	
>>>Inactivity Threshold for UE DRX Cycle Ext	0		ENUMERATED(128, 256,512,)	Units of subframes.	YES	ignore
>>E-AGCH DRX Information		01				
>>>CHOICE E-AGCH DRX information type	М				ı	
>>>>Same as HS- SCCH			NULL	Indicate the E-AGCH DRX Cycle and Offset are the same as the HS-SCCH DRX Cycle and Offset, and the E-AGCH Inactivity Monitor Threshold is absent	,	
>>>E-AGCH DRX parameters						
>>>>E-AGCH DRX cycle	М		ENUMERATED (1,2,4,8,16,32,64,)	Units of subframes.	-	
>>>>E-AGCH Inactivity Monitor Threshold	0		ENUMERATED (0, 1, 2, 4, 8, 16, 32, 64, 128, 256, 512, infinity,)	Units of subframes.	-	
>>>>E-AGCH DRX Offset	М		INTEGER (0 63)	Units of subframes. Offset of the E-AGCH DRX cycles.	-	
>Deactivate			NULL		-	

9.2.3.63 Continuous Packet Connectivity DRX Information Response LCR

DRNS uses the *Continuous Packet Connectivity DRX Information Response LCR* IE to inform the SRNS the parameters used for Continuous Packet Connectivity DRX operation for 1.28 Mcps TDD (see TS 25.224 [22]). Continuous Packet Connectivity DRX related parameters shall be configured by SRNS. For the parameters which can be accepted by DRNS, the DRNS shall not included the related IEs in the *Continuous Packet Connectivity DRX Information Response LCR* IE. For the parameters which can be not accepted by DRNS, the DRNS shall included the related IEs in the *Continuous Packet Connectivity DRX Information Response LCR* IE.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Enabling Delay	0		ENUMERATED (0, 1, 2, 4, 8, 16, 32, 64, 128)	Units of radio frames	-	,
HS-SCCH DRX Information		01				
>UE DRX Cycle	0		ENUMERATED(1,2,4 ,8,16,32,64,)	Units of subframes	-	
>Inactivity Threshold for UE DRX Cycle	0		ENUMERATED(1,2,4 ,8,16,32,64,)	Units of subframes	-	
>UE DRX Offset	0		INTEGER (063)	Units of subframes. Offset of the UE DRX cycles at the given TTI	-	
>Inactivity Threshold for UE DRX Cycle Ext	0		ENUMERATED(128, 256,512,)	Units of subframes. This IE can only be used when the Inactivity Threshold for UE DRX Cycle Ext is included in the request message, otherwise, the IE shall not be used	YES	ignore
E-AGCH DRX Information		01				
CHOICE E-AGCH DRX information type	М					
>Same as HS-SCCH			NULL	Indicate the E-AGCH DRX Cycle and Offset are the same as the HS-SCCH DRX Cycle and Offset, and the E-AGCH Inactivity Monitor Threshold is absent	-	
>E-AGCH DRX parameters						
>>E-AGCH DRX cycle	0		ENUMERATED (1,2,4,8,16,32,64,)	Units of subframes.	-	
>>E-AGCH Inactivity Monitor Threshold	0		ENUMERATED (0, 1, 2, 4, 8, 16, 32, 64, 128, 256, 512, infinity,)	Units of subframes.	-	
>>E-AGCH DRX Offset	0		INTEGER (0 63)	Units of subframes. Offset of the E-AGCH DRX cycles.	-	

9.2.3.64 HS-DSCH Semi-Persistent scheduling Information LCR

The *HS-DSCH Semi-Persistent scheduling Information LCR* IE defines the parameters used for HS-DSCH semi-Persistent scheduling for 1.28 Mcps TDD (see TS 25.224 [22]).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Transport Block Size List		1< maxnoofT BSsMappi ng >		
>Transport Block Size maping Index	M		INTEGER (0 maxnoofTBSsMappi ng-1)	Corresponds to the <i>Transport-block size information</i> field carried on HS-SCCH (see TS 25.222 [46]).
>Transport Block Size Index	M		INTEGER (1 maxnoofHS- DSCHTBSsLCR)	Corresponds to the <i>TB index</i> in the related Transport Block Size table (see TS 25.425 [32]).
Repetition Period list		1 <maxno ofRepetitio nPeriodLC</maxno 		

		R>		
>Repetition Period Index	M		INTEGER (0 maxnoofRepetitionP eriodLCR-1)	Corresponds to the Resource repetition period index field carried on HS-SCCH (see TS 25.222 [46]).
>Repetition Period	М		ENUMERATED (1, 2, 4, 8, 16, 32, 64,)	Units of subframes
>Repetition Length	0		INTEGER (163))	Absence means Repetition Length equal to 1.
HS-DSCH Semi-Persistent Resource Reservation Indicator	0		ENUMERATED(Res erve)	Reserve means the HS-DSCH Semi-Persistent Resource is required to be reserved and be informed via response message.
HS-DSCH Semi-Persistent scheduling operation Indicator		1		
>CHOICE configuration				
>>Logical Channel level			BIT STRING (16)	Available when MAC-ehs is configured. Indicates the logical channels for which the HS-DSCH Semi-Persistent operation is intended to be used. Bit 0 is for logical channel 0, Bit 1 is for logical channel 1, Value '1' for a bit means that the HS-DSCH Semi-Persistent operation is allowed. Bit 0 is the first/leftmost bit of the bit string.
>> Priority Queue level			BIT STRING (8)	Indicates the Priority Queues for which the HS-DSCH Semi-Persistent operation is intended to be used. Bit 0 is for priority queue 0, Bit 1 is for priority queue 1, Value '1' for a bit means that the HS-DSCH Semi-Persistent operation is allowed. Bit 0 is the first/leftmost bit of the bit string.

Range Bound	Explanation
maxnoofHS-DSCHTBSsLCR	Maximum number of HS-DSCH Transport Block Sizes
maxnoofRepetitionPeriodLCR	Maximum number of Repetition Period for 1.28Mcps TDD
maxnoofTBSsMapping	Maximum number of Transport Block Size mapping index on HS-SCCH.

9.2.3.65 HS-DSCH Semi-Persistent scheduling Information to modify LCR

The *HS-PSCH Semi-Persistent scheduling Information to modify LCR* IE is used for the modification of HS-DSCH Semi-Persistent scheduling information for 1.28 Mcps TDD (see TS 25.224 [22]).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Transport Block Size List		0< maxnoofT BSsMappi ng >		
> Transport Block Size maping Index	M		INTEGER (0 maxnoofTBSsMappi ng-1)	Corresponds to the <i>Transport-block size information</i> field carried on HS-SCCH (see TS 25.222 [46]).

>Transport Block Size Index	M		INTEGER (1 maxnoofHS- DSCHTBSsLCR)	Corresponds to the <i>TB index</i> in the related Transport Block Size table (see TS 25.425 [32]).
Repetition Period list		0 <maxno ofRepetitio nPeriodLC R></maxno 		
>Repetition Period Index	M		INTEGER (0 maxnoofRepetitionP eriodLCR)	Corresponds to the Resource repetition period index field carried on HS-SCCH (see TS 25.222 [46]).
>Repetition Period	М		ENUMERATED (1, 2, 4, 8, 16, 32, 64,)	Units of subframes
>Repetition Length	0		INTEGER (163))	Absence means Repetition Length equal to 1.
HS-DSCH Semi-Persistent Resource Reservation Indicator	0		ENUMERATED(Res erve)	Reserve means the Semi- Persistent HS-DSCH Resource is required to be reserved and be informed via response message.
HS-DSCH Semi-Persistent scheduling operation Indicator		01		
>CHOICE configuration				
>>Logical Channel level			BIT STRING (16)	Available when MAC-ehs is configured. Indicates the logical channels for which the HS-DSCH Semi-Persistent operation is intended to be used. Bit 0 is for logical channel 0, Bit1 is for logical channel 1, Value '1' for a bit means that the HS-DSCH Semi-Persistent operation is allowed. Bit 0 is the first/leftmost bit of the bit string.
>> Priority Queue level			BIT STRING (8)	Indicates the Priority Queues for which the HS-DSCH Semi-Persistent operation is intended to be used. Bit 0 is for prority queue 0, Bit1 is for priority queue 1, Value '1' for a bit means that the HS-DSCH Semi-Persistent operation is allowed. Bit 0 is the first/leftmost bit of the bit string.

Range Bound	Explanation
maxnoofHS-DSCHTBSsLCR	Maximum number of HS-DSCH Transport Block Sizes
maxnoofRepetitionPeriodLCR	Maximum number of Repetition Period for 1.28Mcps TDD
maxnoofTBSsMapping	Maximum number of Transport Block Size mapping index on HS-

9.2.3.66 E-DCH Semi-Persistent scheduling Information LCR

The E-DCH Semi-Persistent scheduling Information LCR IE defines the parameters used for E-DCH semi-Persistent scheduling for 1.28 Mcps TDD (see TS 25.224 [22]).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Repetition Period list		1 <maxno< th=""><th></th><th></th></maxno<>		

Departition Desired Index		ofRepetitio nPeriodL CR>	INTEGER (O	
>Repetition Period Index	М		INTEGER (0 maxnoofRepetitionP eriodLCR-1)	
>Repetition Period	M		ENUMERATED (1, 2, 4, 8, 16, 32, 64,)	Units of subframes
>Repetition Length	0		INTEGER (163))	Absence means Repetition Length equal to 1.
E-DCH Semi-Persistent scheduling Indicator	M		BIT STRING (16)	Indicates the logical channels for which the E-DCH Semi-Persistent operation is intended to be used. Bit 0 is for logical channel 0, Bit1 is for logical channel 1, Value '1' for a bit means that the HS-DSCH Semi-Persistent operation is allowed. Bit 0 is the first/leftmost bit of the bit string.
E-DCH Semi-Persistent Resource Reservation Indicator	0		ENUMERATED(Res erve)	Reserve means the E-DCH Semi-Persistent Resource is required to be reserved and be informed via response message.

Range Bound	Explanation
maxnoofRepetitionPeriodLCR	Maximum number of Repetition Period for 1.28Mcps TDD

9.2.3.67 E-DCH Semi-Persistent scheduling Information to modify LCR

The *E-DCH Semi-Persistent scheduling Information to modify LCR* IE is used for the modification of E-DCH Semi-Persistent scheduling information for 1.28 Mcps TDD (see TS 25.224 [22]).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Repetition Period list		0 <maxno ofRepetitio nPeriodL CR></maxno 		
>Repetition Period Index	M		INTEGER (0 maxnoofRepetitionP eriodLCR-1)	
>Repetition Period	M		ENUMERATED (1, 2, 4, 8, 16, 32, 64,)	Units of subframes
>Repetition Length	0		INTEGER (163))	Absence means Repetition Length equal to 1.
E-DCH Semi-Persistent scheduling Indicator	0		BIT STRING (16)	Indicates the logical channels for which the E-DCH Semi-Persistent operation is intended to be used. Bit 0 is for logical channel 0, Bit1 is for logical channel 1, Value '1' for a bit means that the HS-DSCH Semi-Persistent operation is allowed. Bit 0 is the first/leftmost bit of the bit string.
E-DCH Semi-Persistent Resource Reservation Indicator	0		ENUMERATED(Res erve)	Reserve means the E-DCH Semi-Persistent Resource is required to be reserved and be

		informed via response
		message.

Range Bound	Explanation
maxnoofRepetitionPeriodLCR	Maximum number of Repetition Period for 1.28Mcps TDD

9.2.3.68 HS-DSCH Semi-Persistent scheduling Information Response LCR

The *HS-DSCH Semi-Persistent scheduling Information Response LCR* IE provides information for HS-DSCH Semi-Persistent scheduling determined within the Node B (see TS 25.224 [22]).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
HS-SICH information for HS- DSCH Semi-Persistent Scheduling operation		1< maxnoofH S- SICHforSP S>		
>HS-SICH mapping index	М		INTEGER (0 maxnoofHS- SICHforSPS-1)	
>CHIOCE HS-SICH type >>HS-SCCH associated HS-				
>>HS-SICH ID	M		HS SICH ID 9.2.3.3ad	
>>Non-HS-SCCH associated HS-SICH				
>>>Time Slot LCR	M		9.2.3.12a	
>>>Midamble shift LCR	M		9.2.3.4C	
>>>TDD Channelisation Code	М		9.2.3.8	
Allcoated HS-PDSCH Semi- persistent resource		01		
>Repetition Period Index	М		INTEGER (0 maxnoofRepetitionP eriodLCR-1)	
>Repetition Length for HS- PDSCH Semi-persistent Resouce	0		INTEGER (163))	Absence means Repetition Length equal to 1.
>HS-PDSCH offset	М		INTEGER (063))	Units of subframes
>HS-PDSCH Midamble Configuation	М		Midamble Shift LCR 9.2.3.7A	
>Timeslot Resource Related Information	М		BIT STRING(5)	Each bit indicates availability of a timeslot, where the bit 0 corresponds to TS2, the bit 1 is TS3, the bit 3 is TS4 bit 5 corresponds to TS6. The value 1 of a bit indicates that the corresponding timeslot is available. Bit 0 is the first/leftmost bit of the bit string.
>Start Code	M		TDD Channelisation Code 9.2.3.19	-
>End Code	M		TDD Channelisation Code 9.2.3.19	
>Transport Block Size Index	М		INTEGER (0 maxnoofTBSsMappi ng-1)	
>Modulation type	М		ENUMERATED (QPSK, 16QAM)	
>HS-SICH mapping index	M		INTEGER (0	

		maxnoofHS- SICHforSPS-1)	
Buffer Size for HS-DSCH Semi-Persistent scheduling	0	ENUMERATED (800304000,)	Indicats the buffer size that shall be reserved for HS-DSCH semi-persistent scheduling operation. 800 16000 by step of 800, 17600 32000 by step of 1600, 36000 80000 by step of 4000, 88000 160000 by step of 8000, 176000 304000 by step of 16000
Number of Processes for HS- DSCH Semi-Persistent scheduling	0	INTEGER (116)	

Range Bound	Explanation					
maxnoofHS-SICHforSPS	Maximum number of HS-SICH for HS-DSCH Semi-Persistent					
	scheduling operation					
maxnoofTBSsMapping	Maximum number of Transport Block Size mapping index on HS-SCCH.					

9.2.3.69 E-DCH Semi-Persistent scheduling Information Response LCR

The *E-DCH Semi-Persistent scheduling Information Response LCR* IE provides information for E-DCH Semi-Persistent scheduling information determined within the Node B (see TS 25.2243 [22]).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Allcoated E-DCH Semi- persistent resource		01		
>Timeslot Resource Related Information LCR	M		9.2.3.54a	
>Power Resource Related Information	M		9.2.3.55	
>Repetition Period Index	M		INTEGER (0 maxnoofRepetitionP eriodLCR-1)	
>Repetition Length	M		INTEGER (163))	Absence means Repetition Length equal to 1.
>Subframe Number	M		ENUMERATED (0,1)	Used to indicate from which subframe of the Radio Frame indicated by TDD E-PUCH Offset IE the physical resources are assigned to the E-DCH Non-scheduled Grant.
>TDD E-PUCH Offset	M		9.2.3.56	
>TDD Channelisation Code	M		9.2.3.19	
>NE-UCCH	M		INTEGER (18)	Number of E-UCCH and TPC instances within an E-DCH TTI. Details are described in TS 25.221 [12].
E-DCH SPS E-HICH information		01		

>CHOICE E-HICH configuration	М		
>>same as scheduled E- HICH			
>>> EI		INTEGER (03)	
>>explicit			
>>>Time Slot LCR	М	9.2.3.12a	
>>>Midamble Shift LCR	М	9.2.3.4C	
>>>TDD Channelisation Code	М	9.2.3.8	
>Signature Sequence Group Index	М	INTEGER (019)	

9.2.3.70 HS-DSCH Semi-Persistent scheduling Deactivate Indicator LCR

The *HS-DSCH Semi-Persistent scheduling Deactivate Indicator LCR* IE is used to deactivate HS-DSCH Semi-Persistent scheduling operation for 1.28 Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
HS-DSCH Semi-Persistent scheduling Deactivate	M		NULL	
Indicator				

9.2.3.71 E-DCH Semi-Persistent scheduling Deactivate Indicator LCR

The *E-DCH Semi-Persistent scheduling Deactivate Indicator LCR* IE is used to deactivate E-DCH Semi-Persistent schedulung operation for 1.28 Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
E-DCH Semi-Persistent scheduling Deactivate Indicator	M		NULL	

9.2.3.72 HS-SICH Reference Signal Information

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description	Criticality	Assigned Criticality
Midamble Configuration LCR	М		ENUMERATE D (2, 4, 6, 8,	As defined in TS 25.221 [12]		
Midamble Obiff	100		10, 12, 14, 16,)			
Midamble Shift	M		INTEGER (015)			
Time Slot LCR	M		9.2.3.12a			

9.2.3.73 Cell Portion LCR ID

Cell Portion LCR ID is the unique identifier for a cell portion within a cell for 1.28 Mcps TDD. See TS 25.225 [14].

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Cell Portion LCR ID			INTEGER	
			(0255,)	

9.2.3.74 TS0 HS-PDSCH Indication LCR

Only for 1.28Mcps TDD. The *TS0 HS-PDSCH Indication LCR* IE indicates the first bit of timeslot information included in the HS-SCCH can be used to allocate the HS-PDSCH resources on TS0.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
TS0 HS-PDSCH Indication LCR			NULL	

9.2.3.75 DCH Measurement Occasion Information

The *DCH Measurement Occasion Information* IE indicates Measurement Occasion Information used for interfrequency/ inter-RAT measurements in CELL_DCH state for 1.28Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
CELL_DCH measurement occasion pattern sequence		I to <maxd CHMeas urement Occasio nPattern Sequenc e></maxd 		
>Pattern sequence identifier	M		Integer(1 maxDCHMeas urementOccasi onPatternSequ ence)	
>Status Flag	M		Enumerated(ac tivate, deactivate)	This flag indicates whether the measurement occasion pattern sequence shall be activated or deactivated.
>Measurement purpose	O		BIT STRING (5)	Measurement Purpose. Bit 0 is for Inter- frequency measurement. Bit 1 is for GSM carrier RSSI measurement. Bit 2 is for Initial BSIC identification. Bit 3 is for BSIC re- confirmation. Bit 4 is for E-UTRA measurement. The value 1 of a bit means that the measurement occasion pattern sequence is applicable for the corresponding type of measurement. Bit 0 is the first/leftmost bit of the bit string.
>Measurement occasion pattern	О			

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
sequence parameters				
>>k	M		Integer(19)	CELL_DCH measurement occasion cycle length coefficient. The actual measurement occasion period equal to 2 ^k radio frames. Value 0 indicates continuous allocation.
>>Offset	M		Integer(0511)	In frames. The measurement occasion position in the measurement period.
>>M_Length	M		Integer(1512)	The measurement occasion length in frames starting from the Offset.
>>Timeslot Bitmap	M		Bit string (7)	Bitmap indicating which of the timeslot(s) is/are allocated for measurement.
				Bit 0 is for timeslot 0. Bit 1 is for timeslot 1. Bit 2 is for timeslot 2. Bit 3 is for timeslot 3. Bit 4 is for timeslot 4. Bit 5 is for timeslot 5. Bit 6 is for timeslot 6.
				The value 0 of a bit means the corresponding timeslot is not used for measurement. The value 1 of a bit means the corresponding timeslot is used for measurement.
				Bit 0 is the first/leftmost bit of the bit string.

Condition	Explanation		
Measurementoccasionpatternsequence parameters	The IE shall be present if <i>Measurement occasion</i> pattern sequence parameters IE is present.		

Range Bound	Explanation		
maxDCHMeasurementOccasionPatternSequence	Maximum number of measurement occasion pattern sequence		

9.2.3.76 DCH Measurement Type Indicator

The *DCH Measurement Type Indicator* IE indicates the measurement type(s) which the DRNS shall configured for the UE in CELL_DCH state for 1.28Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Measurement type	M		BIT STRING (5)	Measurement type. Bit 0 is for Inter-frequency measurement. Bit 1 is for GSM carrier RSSI measurement. Bit 2 is for Initial BSIC identification. Bit 3 is for BSIC reconfirmation. Bit 4 is for E-UTRA measurement. The value 1 of a bit means that the measurement occasion pattern sequence should be configured for the corresponding type of measurement. Bit 0 is the first/leftmost bit of the bit string.

9.2.3.77 Multi-Carrier E-DCH Information LCR

The Multi-Carrier E-DCH $Information\ LCR$ IE defines the parameters used for Multi-Carrier E-DCH operation for 1.28 Mcps TDD.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Multi-Carrier E-DCH		1 <maxtdd12< td=""><td></td><td></td></maxtdd12<>		
Information		8Carrier-1>		
>UARFCN	M		9.2.1.66	Corresponds to Nt (3GPP TS 25.105)
>SNPL Carrier Group Indicator	0		INTEGER (13)	Indicates to which SNPL carrier Group this frequency belongs. The absence of this IE indicates the corresponding frequency belongs to a separate SNPL carrier group which only contains this carrier. The SNPL carrier Group is defined in TS 25.331 [16].
>PRXdes_base	М		INTEGER (-11250)	dBm. Reference Desired RX power level for E-PUCH.
> Multi-Carrier E-DCH TDD MAC-d Flow Specific Information		0 <maxnoofe DCHMACdFlo ws></maxnoofe 		Shall be ignored if bearer establishment with ALCAP. Shall be present only if the Separate lur transport bearer mode is used.
>>E-DCH MAC-d Flow ID	M		9.2.1.91	
>>Binding ID	M		9.2.1.3	
>>Transport Layer Address	M		9.2.1.62	

Range Bound	Explanation
maxTDD128Carrier	Maximum number of uplink frequencis in Multi-Carrier E-DCH Operation
maxnoofEDCHMACdFlows	Maximum number of MAC-d flows.

9.2.3.78 Multi-Carrier E-DCH Information Response LCR

The *Multi-Carrier E-DCH Information Response LCR* IE provides information for E-DCH MAC-d flows that determined within the DRNS.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Multi-Carrier E-DCH		1 <maxtdd12< td=""><td></td><td></td></maxtdd12<>		
Information Response		8Carrier-1>		
>UARFCN	M		9.2.1.66	Corresponds to Nt (3GPP TS 25.105)
>E-DCH TDD MAC-d Flow		0 <maxnoofe< td=""><td></td><td></td></maxnoofe<>		
Specific Information		DCHMACdFlo		
Response		WS>		
>>E-DCH MAC-d Flow ID	M		9.2.1.91	
>>Binding ID	0		9.2.1.3	
>>Transport Layer Address	0		9.2.1.62	
>E-AGCH Specific		0 <maxnoofe< td=""><td></td><td></td></maxnoofe<>		
Information Response		AGCHcodes>		
>>Time Slot LCR	M		9.2.3.12a	
>>Midamble Shift LCR	M		9.2.3.4C	
>>TDD Channelisation Code	M		9.2.3.8	
>E-HICH Scheduled specific		0<		
Information Response		maxNoOfEHIC Hcodes>		
>>EI	M		INTEGER	E-HICH indication which is used
			(03)	to indicate UE on which E-HICH
				the feedback info is carried.
>>Time Slot LCR	M		9.2.3.12a	
>>Midamble Shift LCR	M		9.2.3.4C	
>>TDD Channelisation Code	M		9.2.3.8	

Range bound	Explanation
maxTDD128Carrier	Maximum number of uplink frequencis in Multi-Carrier E-DCH
	Operation
maxnoofEDCHMACdFlows	Maximum number of MAC-d flows.
maxNoofEAGCHcodes	Maximum number of E-AGCHs assigned to one UE
maxNoofEHICHcodes	Maximum number of E-HICHs assigned to one UE

9.2.3.79 Multi-Carrier E-DCH Transport Bearer Mode LCR

This parameter indicates the Multicarrier E-DCH Transport Bearer Mode. For *Multi-Carrier E-DCH Transport Bearer Mode LCR* = " Separate Iur transport bearer mode" the Mac-d flows from each carrier uses different Iur transport bearers, for *Multi-Carrier E-DCH Transport Bearer Mode LCR* = " E-DCH UL flow multiplexing mode " the Mac-d flow received on the different carriers in the DRNS is multiplexed on one Iur transport bearer.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Multicarrier E-DCH Transport			ENUMERATED	
Bearer Mode			(Separate lur transport bearer mode,E-DCH UL flow multiplexing mode,)	

9.2.3.80 Cell Capability Container Extension TDD LCR

The *Cell Capability Container Extension TDD LCR* IE is an extension to the *Cell Capability Container TDD LCR* IE and indicates the cell capability in the same way as *Cell Capability Container TDD LCR* IE.

The Cell Capability Container Extension TDD LCR IE indicates the cell capability of Multi-Carrier related functions.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
Cell Capability Container Extension TDD LCR			BIT STRING (32)	Each bit indicates whether a cell supports a particular functionality or not. The value 1 of a bit indicates that the corresponding functionality is supported in a cell and value 0 indicates that the corresponding functionality is not supported in a cell. Each bit is defined as follows. The first bit: Multi-Carrier E-DCH Operation Support Indicator. This bit shall be ignored by the SRNC if the second bit: Separate lur Transport Bearer Support Indicator = "0" and the third bit: E-DCH UL Flow Multiplexing Support Indicator = "0". The second bit: Separate lur Transport Bearer Support Indicator, /Multi-carrier/. This bit shall be ignored by the SRNC if the first bit: Multi-Carrier E-DCH Operation Support Indicator = "0". The third bit: E-DCH UL flow multiplexing mode Indicator, /Multi-carrier/. This bit shall be ignored by the SRNC if the first bit: Multi-Carrier E-DCH Operation Support Indicator = "0". Note that undefined bits are considered as a spare bit and spare bits shall be set to 0 by the transmitter and shall be ignored by the receiver. Note that Reserved bits are not considered as a spare bit. They shall however be set to 0 by the transmitter and shall be ignored by the receiver.

9.2.3.81 MU-MIMO Information

The MU-MIMO Information IE defines the parameters used for MU-MIMO operation for 1.28 Mcps TDD (see TS 25.224 [22]).

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
MU-MIMO Operation	M		ENUMERATED (MU-MIMO Used, MU-MIMO Not Used)	
Standalone Midamble Channel Information		01		
>Standalone Midamble Configuration	М		ENUMERATED (2, 4, 6, 8, 10, 12, 14, 16,)	As defined in TS 25.221 [12]
>Standalone Midamble Shift	M		INTEGER (015)	
>Timeslot	M		9.2.3.12a	
>Repetition Period	M		ENUMERATED (1, 2,4, 8, 16, 32, 64)	Units of subframes.
>Offset	M		INTEGER (063)	Units of subframes.
>Reference Beta	C-E-DCH		INTEGER (-1516)	Unit range -15db to +16db

Condition	Explanation		
E-DCH	This IE shall be present if IE "E-DCH Information 1.28Mcps" is present. Otherwise it is not needed.		

9.2.3.82 MU-MIMO Indicator

The *MU-MIMO Indicator* IE indicates the DRNC can use MU-MIMO on UL and/or DL. It also indicates that whether Standalone Midamble Channel should be used or not.

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
MU-MIMO Usage Indicator	M		ENUMERATED (UL Only, DL Only, UL and DL)	
Standalone Midamble Channel indicator	М		ENUMERATED (Used, Not Used)	

9.2.3.83 M2 Report

This IE defines the parameters for a M2 report, TDD report of UE radio measurements. This IE is not used by the DRNS.

IE/Group Name	Presence	Range	IE type and reference	Semantics description
M2 Report				
>CHOICE Report trigger	M			
>>Periodic				
>>>MDT Report	M		9.2.1.140	
Parameters				
>>Event1I		•		
>>>threshold	M	•	INTEGER(-12025)	

9.2.3.84 UE RF Band Capability LCR

IE/Group Name	Presence	Range	IE Type and Reference	Semantics Description
UE RF Band Capability Info		1<		
		maxFreqBan		
		dsTDD>		
>UE RF Band Capability	M		ENUMERATED	Corresponds to the radio
			(a,b,c,d,e,f,g,h,i,j,k,l,m,n	bands definition (TS
			,o,p,)	25.105 [7]).

9.3 Message and Information Element Abstract Syntax (with ASN.1)

9.3.0 General

RNSAP ASN.1 definition conforms with ITU-T Rec. X.680 [18] and ITU-T Rec. X.681 [19].

Subclause 9.3 presents the Abstract Syntax of RNSAP protocol with ASN.1. In case there is contradiction between the ASN.1 definition in this subclause and the tabular format in subclause 9.1 and 9.2, the ASN.1 shall take precedence, except for the definition of conditions for the presence of conditional elements, in which the tabular format shall take precedence.

The ASN.1 definition specifies the structure and content of RNSAP messages. RNSAP messages can contain any IEs specified in the object set definitions for that message without the order or number of occurrence being restricted by ASN.1. However, for this version of the standard, a sending entity shall construct a RNSAP message according to the PDU definitions module and with the following additional rules:

- IEs shall be ordered (in an IE container) in the order they appear in object set definitions.
- Object set definitions specify how many times IEs may appear. An IE shall appear exactly once if the presence field in an object has value "mandatory". An IE may appear at most once if the presence field in an object has value "optional" or "conditional". If in a tabular format there is multiplicity specified for an IE (i.e. an IE list) then in the corresponding ASN.1 definition the list definition is separated into two parts. The first part defines an IE container list in which the list elements reside. The second part defines list elements. The IE container list appears as an IE of its own. For this version of the standard an IE container list may contain only one kind of list elements.

NOTE: In the above "IE" means an IE in the object set with an explicit ID. If one IE needs to appear more than once in one object set, then the different occurrences have different IE IDs.

If a RNSAP message that is not constructed as defined above is received, this shall be considered as Abstract Syntax Error, and the message shall be handled as defined for Abstract Syntax Error in subclause 10.3.6.

9.3.1 Usage of Private Message Mechanism for Non-standard Use

The private message mechanism for non-standard use may be used:

- for special operator (and/or vendor) specific features considered not to be part of the basic functionality, i.e. the functionality required for a complete and high-quality specification in order to guarantee multivendor inter-operability.
- by vendors for research purposes, e.g. to implement and evaluate new algorithms/features before such features are proposed for standardisation.

The private message mechanism shall not be used for basic functionality. Such functionality shall be standardised.

9.3.2 Elementary Procedure Definitions

```
-- Elementary Procedure definitions
__ *********************
RNSAP-PDU-Descriptions {
itu-t (0) identified-organization (4) etsi (0) mobileDomain (0)
umts-Access (20) modules (3) rnsap (1) version1 (1) rnsap-PDU-Descriptions (0) }
DEFINITIONS AUTOMATIC TAGS ::=
BEGIN
  *****************
-- IE parameter types from other modules.
__ ********************
IMPORTS
   Criticality,
   ProcedureID,
   TransactionID
FROM RNSAP-CommonDataTypes
   CommonMeasurementFailureIndication.
   CommonMeasurementInitiationFailure,
   CommonMeasurementInitiationRequest,
   CommonMeasurementInitiationResponse,
   CommonMeasurementReport,
   CommonMeasurementTerminationRequest,
   CommonTransportChannelResourcesFailure,
   CommonTransportChannelResourcesRequest,
   CommonTransportChannelResourcesReleaseRequest,
   CommonTransportChannelResourcesResponseFDD,
   CommonTransportChannelResourcesResponseTDD,
   CompressedModeCommand,
   DedicatedMeasurementFailureIndication,
   DedicatedMeasurementInitiationFailure,
   DedicatedMeasurementInitiationRequest,
   DedicatedMeasurementInitiationResponse,
   DedicatedMeasurementReport,
   DedicatedMeasurementTerminationRequest,
   DirectInformationTransfer,
   DL-PowerControlRequest,
   DL-PowerTimeslotControlRequest,
   DownlinkSignallingTransferRequest,
   ErrorIndication,
   EnhancedRelocationCancel,
   EnhancedRelocationFailure,
   EnhancedRelocationRequest,
   EnhancedRelocationResponse,
   EnhancedRelocationSignallingTransfer,
   EnhancedRelocationRelease,
```

```
EnhancedRelocationResourceRequest,
EnhancedRelocationResourceResponse,
EnhancedRelocationResourceFailure.
EnhancedRelocationResourceReleaseCommand,
EnhancedRelocationResourceReleaseComplete,
InformationExchangeFailureIndication,
InformationExchangeInitiationFailure,
InformationExchangeInitiationReguest,
InformationExchangeInitiationResponse,
InformationExchangeTerminationRequest,
InformationReport,
InformationTransferControlRequest,
IurDeactivateTrace,
IurInvokeTrace,
MBMSAttachCommand.
MBMSDetachCommand,
MBSFNMCCHInformation,
PagingRequest,
PhysicalChannelReconfigurationCommand,
PhysicalChannelReconfigurationFailure,
PhysicalChannelReconfigurationRequestFDD,
PhysicalChannelReconfigurationRequestTDD,
PrivateMessage,
RadioLinkActivationCommandFDD,
RadioLinkActivationCommandTDD,
RadioLinkAdditionFailureFDD.
RadioLinkAdditionFailureTDD,
RadioLinkAdditionRequestFDD,
RadioLinkAdditionRequestTDD,
RadioLinkAdditionResponseFDD,
RadioLinkAdditionResponseTDD,
RadioLinkCongestionIndication,
RadioLinkDeletionRequest,
RadioLinkDeletionResponse,
RadioLinkFailureIndication,
RadioLinkParameterUpdateIndicationFDD,
RadioLinkParameterUpdateIndicationTDD,
RadioLinkPreemptionRequiredIndication,
RadioLinkReconfigurationCancel,
RadioLinkReconfigurationCommit,
RadioLinkReconfigurationFailure,
RadioLinkReconfigurationPrepareFDD,
RadioLinkReconfigurationPrepareTDD,
RadioLinkReconfigurationReadyFDD,
RadioLinkReconfigurationReadyTDD,
RadioLinkReconfigurationRequestFDD,
RadioLinkReconfigurationRequestTDD,
RadioLinkReconfigurationResponseFDD,
RadioLinkReconfigurationResponseTDD,
RadioLinkRestoreIndication,
RadioLinkSetupFailureFDD,
RadioLinkSetupFailureTDD,
RadioLinkSetupRequestFDD,
RadioLinkSetupRequestTDD,
```

```
RadioLinkSetupResponseFDD,
    RadioLinkSetupResponseTDD,
    RelocationCommit.
    ResetRequest,
    ResetResponse,
    UEMeasurementFailureIndication,
    UEMeasurementInitiationFailure.
    UEMeasurementInitiationRequest,
    UEMeasurementInitiationResponse,
    UEMeasurementReport,
    UEMeasurementTerminationRequest,
    SecondaryULFrequencyReport,
    SecondaryULFrequencyUpdateIndication,
    UplinkSignallingTransferIndicationFDD,
    UplinkSignallingTransferIndicationTDD,
    GERANUplinkSignallingTransferIndication
FROM RNSAP-PDU-Contents
    id-commonMeasurementFailure,
    id-commonMeasurementInitiation,
    id-commonMeasurementReporting,
    id-commonMeasurementTermination,
    id-commonTransportChannelResourcesInitialisation,
    id-commonTransportChannelResourcesRelease,
    id-compressedModeCommand,
    id-downlinkPowerControl,
    id-downlinkSignallingTransfer,
    id-downlinkPowerTimeslotControl,
    id-enhancedRelocation,
    id-enhancedRelocationCancel,
    id-enhancedRelocationSignallingTransfer,
    id-enhancedRelocationRelease,
    id-errorIndication,
    id-informationExchangeFailure,
    id-informationExchangeInitiation,
    id-informationReporting,
    id-informationExchangeTermination,
    id-informationTransferControl,
    id-iurDeactivateTrace,
    id-iurInvokeTrace,
    id-dedicatedMeasurementFailure,
    id-dedicatedMeasurementInitiation,
    id-dedicatedMeasurementReporting,
    id-dedicatedMeasurementTermination,
    id-directInformationTransfer,
    id-mBMSAttach,
    id-mBMSDetach,
    id-mBSFNMCCHInformation,
    id-paging,
    id-physicalChannelReconfiguration,
    id-privateMessage,
    id-radioLinkActivation,
    id-radioLinkAddition,
    id-radioLinkCongestion,
```

```
id-radioLinkDeletion,
   id-radioLinkFailure.
   id-radioLinkParameterUpdate,
   id-radioLinkPreemption,
   id-radioLinkRestoration.
   id-radioLinkSetup,
   id-relocationCommit,
   id-reset,
   id-synchronisedRadioLinkReconfigurationCancellation,
   id-synchronisedRadioLinkReconfigurationCommit,
   id-synchronisedRadioLinkReconfigurationPreparation,
   id-uEMeasurementFailure,
   id-uEMeasurementInitiation,
   id-uEMeasurementReporting,
   id-uEMeasurementTermination,
   id-secondaryULFrequencyReporting,
   id-secondaryULFrequencyUpdate,
   id-unSynchronisedRadioLinkReconfiguration,
   id-uplinkSignallingTransfer,
   id-gERANuplinkSignallingTransfer,
   id-enhancedRelocationResourceAllocation,
   id-enhancedRelocationResourceRelease
FROM RNSAP-Constants;
     *****************
-- Interface Elementary Procedure Class
RNSAP-ELEMENTARY-PROCEDURE ::= CLASS {
   &InitiatingMessage
   &SuccessfulOutcome
                                  OPTIONAL,
   &UnsuccessfulOutcome
                                     OPTIONAL,
   &Outcome
                              OPTIONAL,
   &procedureID
                          ProcedureID
                                         UNIQUE,
   &criticality
                          Criticality
                                         DEFAULT ignore
WITH SYNTAX {
                          &InitiatingMessage
   INITIATING MESSAGE
                          &SuccessfulOutcome]
    [SUCCESSFUL OUTCOME
                              &UnsuccessfulOutcome]
    [UNSUCCESSFUL OUTCOME
    [OUTCOME
                      &Outcome]
   PROCEDURE ID
                          &procedureID
                          &criticality]
    [CRITICALITY
-- Interface PDU Definition
  *******************
```

```
RNSAP-PDU ::= CHOICE {
   initiatingMessage InitiatingMessage,
    successfulOutcome SuccessfulOutcome.
   unsuccessfulOutcome UnsuccessfulOutcome,
   out.come
                   Out.come.
    . . .
InitiatingMessage ::= SEQUENCE
   procedureID RNSAP-ELEMENTARY-PROCEDURE.&procedureID
                                                           ({RNSAP-ELEMENTARY-PROCEDURES}),
   criticality RNSAP-ELEMENTARY-PROCEDURE.&criticality
                                                           ({RNSAP-ELEMENTARY-PROCEDURES}{@procedureID}),
    transactionID TransactionID,
               RNSAP-ELEMENTARY-PROCEDURE.&InitiatingMessage
                                                            ({RNSAP-ELEMENTARY-PROCEDURES}{@procedureID})
    value
SuccessfulOutcome ::= SEOUENCE
   procedureID RNSAP-ELEMENTARY-PROCEDURE.&procedureID
                                                           ({RNSAP-ELEMENTARY-PROCEDURES}),
                                                           ({RNSAP-ELEMENTARY-PROCEDURES}{@procedureID}),
   criticality RNSAP-ELEMENTARY-PROCEDURE.&criticality
    transactionID TransactionID,
                                                              ({RNSAP-ELEMENTARY-PROCEDURES}{@procedureID})
    value
               RNSAP-ELEMENTARY-PROCEDURE. & Successful Outcome
UnsuccessfulOutcome ::= SEQUENCE {
   procedureID RNSAP-ELEMENTARY-PROCEDURE.&procedureID
                                                           ({RNSAP-ELEMENTARY-PROCEDURES}),
                                                           ({RNSAP-ELEMENTARY-PROCEDURES}{@procedureID}),
   criticality RNSAP-ELEMENTARY-PROCEDURE.&criticality
    transactionID TransactionID,
    value
               RNSAP-ELEMENTARY-PROCEDURE. &UnsuccessfulOutcome ({RNSAP-ELEMENTARY-PROCEDURES}{@procedureID})
Outcome ::= SEOUENCE {
                                                           ({RNSAP-ELEMENTARY-PROCEDURES}),
   procedureID RNSAP-ELEMENTARY-PROCEDURE.&procedureID
   criticality RNSAP-ELEMENTARY-PROCEDURE.&criticality
                                                           ({RNSAP-ELEMENTARY-PROCEDURES}{@procedureID}),
    transactionID TransactionID,
               RNSAP-ELEMENTARY-PROCEDURE. & Outcome
                                                       ({RNSAP-ELEMENTARY-PROCEDURES}{@procedureID})
    value
      -- Interface Elementary Procedure List
RNSAP-ELEMENTARY-PROCEDURES RNSAP-ELEMENTARY-PROCEDURE ::= {
    RNSAP-ELEMENTARY-PROCEDURES-CLASS-1
   RNSAP-ELEMENTARY-PROCEDURES-CLASS-2
   RNSAP-ELEMENTARY-PROCEDURES-CLASS-3
    . . .
RNSAP-ELEMENTARY-PROCEDURES-CLASS-1 RNSAP-ELEMENTARY-PROCEDURE ::= {
   radioLinkSetupFDD
   radioLinkSetupTDD
   radioLinkAdditionFDD
    radioLinkAdditionTDD
```

```
radioLinkDeletion
    synchronisedRadioLinkReconfigurationPreparationFDD
    synchronisedRadioLinkReconfigurationPreparationTDD
    unSynchronisedRadioLinkReconfigurationFDD
    unSynchronisedRadioLinkReconfigurationTDD
    physicalChannelReconfigurationFDD
    physicalChannelReconfigurationTDD
    dedicatedMeasurementInitiation
    commonTransportChannelResourcesInitialisationFDD
    commonTransportChannelResourcesInitialisationTDD
    commonMeasurementInitiation
    informationExchangeInitiation
    reset
    uEMeasurementInitiation
    enhancedRelocation
    enhancedRelocationResourceAllocation
    enhancedRelocationResourceRelease
RNSAP-ELEMENTARY-PROCEDURES-CLASS-2 RNSAP-ELEMENTARY-PROCEDURE ::= {
    uplinkSignallingTransferFDD
    uplinkSignallingTransferTDD
    downlinkSignallingTransfer
    relocationCommit
    paging
    synchronisedRadioLinkReconfigurationCommit
    synchronisedRadioLinkReconfigurationCancellation
    radioLinkFailure
    radioLinkPreemption
    radioLinkRestoration
    dedicatedMeasurementReporting
    dedicatedMeasurementTermination
    dedicatedMeasurementFailure
    downlinkPowerControlFDD
    downlinkPowerTimeslotControl
    compressedModeCommandFDD
    commonTransportChannelResourcesRelease
    errorIndication
    privateMessage
    radioLinkCongestion
    commonMeasurementFailure
    commonMeasurementReporting
    commonMeasurementTermination
    informationExchangeFailure
    informationExchangeTermination
    informationReporting
    radioLinkActivationFDD
    radioLinkActivationTDD
    gERANuplinkSignallingTransfer
    radioLinkParameterUpdateFDD
    radioLinkParameterUpdateTDD
    uEMeasurementReporting
```

```
uEMeasurementTermination
   uEMeasurementFailure
   iurInvokeTrace
   iurDeactivateTrace
   mBMSAttach
   mBMSDetach
   directInformationTransfer
   enhancedRelocationCancel
   enhancedRelocationSignallingTransfer
   enhancedRelocationRelease
   mBSFNMCCHInformation
   secondaryULFrequencyReportingFDD
   secondaryULFrequencyUpdateFDD
   informationTransferControl
RNSAP-ELEMENTARY-PROCEDURES-CLASS-3 RNSAP-ELEMENTARY-PROCEDURE ::= {
        -- Interface Elementary Procedures
__ ********************************
radioLinkSetupFDD RNSAP-ELEMENTARY-PROCEDURE ::= {
   INITIATING MESSAGE RadioLinkSetupRequestFDD
   SUCCESSFUL OUTCOME RadioLinkSetupResponseFDD
   UNSUCCESSFUL OUTCOME
                          RadioLinkSetupFailureFDD
                      { procedureCode id-radioLinkSetup, ddMode fdd }
   PROCEDURE ID
   CRITICALITY
                  reject
radioLinkSetupTDD RNSAP-ELEMENTARY-PROCEDURE ::= {
   INITIATING MESSAGE RadioLinkSetupRequestTDD
   SUCCESSFUL OUTCOME RadioLinkSetupResponseTDD
                         RadioLinkSetupFailureTDD
   UNSUCCESSFUL OUTCOME
                      { procedureCode id-radioLinkSetup, ddMode tdd }
   PROCEDURE ID
   CRITICALITY
                  reject
radioLinkAdditionFDD RNSAP-ELEMENTARY-PROCEDURE ::= {
   INITIATING MESSAGE RadioLinkAdditionRequestFDD
   SUCCESSFUL OUTCOME RadioLinkAdditionResponseFDD
   UNSUCCESSFUL OUTCOME
                         RadioLinkAdditionFailureFDD
                      { procedureCode id-radioLinkAddition , ddMode fdd }
   PROCEDURE ID
   CRITICALITY
                  reject
```

```
radioLinkAdditionTDD RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE RadioLinkAdditionRequestTDD
    SUCCESSFUL OUTCOME RadioLinkAdditionResponseTDD
    UNSUCCESSFUL OUTCOME
                           RadioLinkAdditionFailureTDD
    PROCEDURE ID
                        { procedureCode id-radioLinkAddition , ddMode tdd }
    CRITICALITY
                    reject
radioLinkDeletion RNSAP-ELEMENTARY-PROCEDURE ::=
    INITIATING MESSAGE RadioLinkDeletionRequest
    SUCCESSFUL OUTCOME RadioLinkDeletionResponse
    PROCEDURE ID
                        { procedureCode id-radioLinkDeletion, ddMode common }
    CRITICALITY
                    reject
synchronisedRadioLinkReconfigurationPreparationFDD RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE RadioLinkReconfigurationPrepareFDD
    SUCCESSFUL OUTCOME RadioLinkReconfigurationReadyFDD
                           RadioLinkReconfigurationFailure
    UNSUCCESSFUL OUTCOME
                        { procedureCode id-synchronisedRadioLinkReconfigurationPreparation, ddMode fdd }
    PROCEDURE ID
    CRITICALITY
                    reject
synchronisedRadioLinkReconfigurationPreparationTDD RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE RadioLinkReconfigurationPrepareTDD
    SUCCESSFUL OUTCOME RadioLinkReconfigurationReadyTDD
                           RadioLinkReconfigurationFailure
    UNSUCCESSFUL OUTCOME
                        { procedureCode id-synchronisedRadioLinkReconfigurationPreparation, ddMode tdd }
    PROCEDURE ID
    CRITICALITY
                    reject
unSynchronisedRadioLinkReconfigurationFDD RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE RadioLinkReconfigurationRequestFDD
    SUCCESSFUL OUTCOME RadioLinkReconfigurationResponseFDD
                           RadioLinkReconfigurationFailure
    UNSUCCESSFUL OUTCOME
                        { procedureCode id-unSynchronisedRadioLinkReconfiguration, ddMode fdd }
    PROCEDURE ID
    CRITICALITY
                    reject
unSynchronisedRadioLinkReconfigurationTDD RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE RadioLinkReconfigurationRequestTDD
    SUCCESSFUL OUTCOME RadioLinkReconfigurationResponseTDD
    UNSUCCESSFUL OUTCOME
                           RadioLinkReconfigurationFailure
                        { procedureCode id-unSynchronisedRadioLinkReconfiguration, ddMode tdd }
    PROCEDURE ID
    CRITICALITY
                    reject
physicalChannelReconfigurationFDD RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE PhysicalChannelReconfigurationRequestFDD
    SUCCESSFUL OUTCOME PhysicalChannelReconfigurationCommand
                           PhysicalChannelReconfigurationFailure
    UNSUCCESSFUL OUTCOME
    PROCEDURE ID
                        { procedureCode id-physicalChannelReconfiguration, ddMode fdd }
    CRITICALITY
                    reject
```

```
physicalChannelReconfigurationTDD RNSAP-ELEMENTARY-PROCEDURE ::=
    INITIATING MESSAGE PhysicalChannelReconfigurationRequestTDD
    SUCCESSFUL OUTCOME PhysicalChannelReconfigurationCommand
    UNSUCCESSFUL OUTCOME
                           PhysicalChannelReconfigurationFailure
                        { procedureCode id-physicalChannelReconfiguration, ddMode tdd }
    PROCEDURE ID
    CRITICALITY
                    reject
dedicatedMeasurementInitiation RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE DedicatedMeasurementInitiationRequest
    SUCCESSFUL OUTCOME DedicatedMeasurementInitiationResponse
                           DedicatedMeasurementInitiationFailure
    UNSUCCESSFUL OUTCOME
    PROCEDURE ID
                        { procedureCode id-dedicatedMeasurementInitiation, ddMode common }
    CRITICALITY
                   reject
commonTransportChannelResourcesInitialisationFDD RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE CommonTransportChannelResourcesRequest
    SUCCESSFUL OUTCOME CommonTransportChannelResourcesResponseFDD
    UNSUCCESSFUL OUTCOME
                           CommonTransportChannelResourcesFailure
                        { procedureCode id-commonTransportChannelResourcesInitialisation, ddMode fdd }
    PROCEDURE ID
    CRITICALITY
                    reject
commonTransportChannelResourcesInitialisationTDD RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE CommonTransportChannelResourcesRequest
    SUCCESSFUL OUTCOME CommonTransportChannelResourcesResponseTDD
                           CommonTransportChannelResourcesFailure
    UNSUCCESSFUL OUTCOME
                        { procedureCode id-commonTransportChannelResourcesInitialisation, ddMode tdd }
    PROCEDURE ID
    CRITICALITY
                    reject
uplinkSignallingTransferFDD RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE UplinkSignallingTransferIndicationFDD
    PROCEDURE ID
                        { procedureCode id-uplinkSignallingTransfer, ddMode fdd }
    CRITICALITY
                    ignore
uplinkSignallingTransferTDD RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE UplinkSignallingTransferIndicationTDD
                        { procedureCode id-uplinkSignallingTransfer, ddMode tdd }
    PROCEDURE ID
    CRITICALITY
                    ignore
downlinkSignallingTransfer RNSAP-ELEMENTARY-PROCEDURE ::=
    INITIATING MESSAGE DownlinkSignallingTransferRequest
    PROCEDURE ID
                        { procedureCode id-downlinkSignallingTransfer, ddMode common }
    CRITICALITY
                    ignore
relocationCommit RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE RelocationCommit
                        { procedureCode id-relocationCommit, ddMode common }
    PROCEDURE ID
```

```
CRITICALITY
                    ignore
paging RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE PagingRequest
                        { procedureCode id-paging, ddMode common }
    PROCEDURE ID
    CRITICALITY
                    ignore
synchronisedRadioLinkReconfigurationCommit RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE RadioLinkReconfigurationCommit
    PROCEDURE ID
                        { procedureCode id-synchronisedRadioLinkReconfigurationCommit, ddMode common }
    CRITICALITY
                    ignore
synchronisedRadioLinkReconfigurationCancellation RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE RadioLinkReconfigurationCancel
                        { procedureCode id-synchronisedRadioLinkReconfigurationCancellation, ddMode common }
    PROCEDURE ID
    CRITICALITY
                    ignore
radioLinkFailure RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE RadioLinkFailureIndication
    PROCEDURE ID
                        { procedureCode id-radioLinkFailure, ddMode common }
    CRITICALITY
                    ignore
radioLinkPreemption RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE RadioLinkPreemptionRequiredIndication
                        { procedureCode id-radioLinkPreemption, ddMode common }
    PROCEDURE ID
    CRITICALITY
                    ignore
radioLinkRestoration RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE RadioLinkRestoreIndication
    PROCEDURE ID
                        { procedureCode id-radioLinkRestoration, ddMode common }
    CRITICALITY
                    ignore
dedicatedMeasurementReporting RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE DedicatedMeasurementReport
                        { procedureCode id-dedicatedMeasurementReporting, ddMode common }
    PROCEDURE ID
    CRITICALITY
                    ignore
dedicatedMeasurementTermination RNSAP-ELEMENTARY-PROCEDURE ::=
    INITIATING MESSAGE DedicatedMeasurementTerminationRequest
    PROCEDURE ID
                        { procedureCode id-dedicatedMeasurementTermination, ddMode common }
    CRITICALITY
                    ignore
dedicatedMeasurementFailure RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE DedicatedMeasurementFailureIndication
                        { procedureCode id-dedicatedMeasurementFailure, ddMode common }
    PROCEDURE ID
```

691

```
CRITICALITY
                    ignore
radioLinkCongestion RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE RadioLinkCongestionIndication
                        { procedureCode id-radioLinkCongestion, ddMode common }
    PROCEDURE ID
    CRITICALITY
                    ignore
downlinkPowerControlFDD RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE DL-PowerControlRequest
    PROCEDURE ID
                        { procedureCode id-downlinkPowerControl, ddMode fdd }
    CRITICALITY
                    ignore
downlinkPowerTimeslotControl RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE DL-PowerTimeslotControlRequest
                        { procedureCode id-downlinkPowerTimeslotControl, ddMode tdd }
    PROCEDURE ID
    CRITICALITY
                    ignore
compressedModeCommandFDD RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE CompressedModeCommand
    PROCEDURE ID
                        { procedureCode id-compressedModeCommand, ddMode fdd }
    CRITICALITY
                    ignore
commonTransportChannelResourcesRelease RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE CommonTransportChannelResourcesReleaseRequest
                        { procedureCode id-commonTransportChannelResourcesRelease, ddMode common }
    PROCEDURE ID
    CRITICALITY
                    ignore
errorIndication RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE ErrorIndication
    PROCEDURE ID
                        { procedureCode id-errorIndication, ddMode common }
    CRITICALITY
                    ignore
commonMeasurementInitiation RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE
                            CommonMeasurementInitiationRequest
    SUCCESSFUL OUTCOME
                            CommonMeasurementInitiationResponse
    UNSUCCESSFUL OUTCOME
                            CommonMeasurementInitiationFailure
                            { procedureCode id-commonMeasurementInitiation, ddMode common }
    PROCEDURE ID
    CRITICALITY
                            reject
commonMeasurementReporting RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE CommonMeasurementReport
    PROCEDURE ID
                        { procedureCode id-commonMeasurementReporting, ddMode common }
    CRITICALITY
                        ignore
commonMeasurementTermination RNSAP-ELEMENTARY-PROCEDURE ::= {
```

692

```
INITIATING MESSAGE CommonMeasurementTerminationRequest
    PROCEDURE ID
                        { procedureCode id-commonMeasurementTermination, ddMode common }
    CRITICALITY
                    ignore
commonMeasurementFailure RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE CommonMeasurementFailureIndication
                        { procedureCode id-commonMeasurementFailure, ddMode common }
    PROCEDURE ID
    CRITICALITY
                    ignore
informationExchangeInitiation RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE
                            InformationExchangeInitiationRequest
    SUCCESSFUL OUTCOME
                            InformationExchangeInitiationResponse
                            InformationExchangeInitiationFailure
    UNSUCCESSFUL OUTCOME
    PROCEDURE ID
                            { procedureCode id-informationExchangeInitiation, ddMode common }
    CRITICALITY
                            reject
informationReporting RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE
                            InformationReport
    PROCEDURE ID
                            { procedureCode id-informationReporting, ddMode common }
    CRITICALITY
informationExchangeTermination RNSAP-ELEMENTARY-PROCEDURE ::= {
                            InformationExchangeTerminationRequest
    INITIATING MESSAGE
    PROCEDURE ID
                            { procedureCode id-informationExchangeTermination, ddMode common }
    CRITICALITY
                            ignore
informationExchangeFailure RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE
                            InformationExchangeFailureIndication
    PROCEDURE ID
                            { procedureCode id-informationExchangeFailure, ddMode common }
    CRITICALITY
                            ignore
privateMessage RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE PrivateMessage
    PROCEDURE ID
                        { procedureCode id-privateMessage, ddMode common }
    CRITICALITY
                    ignore
reset RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE
                            ResetRequest
    SUCCESSFUL OUTCOME
                            ResetResponse
    PROCEDURE ID
                            { procedureCode id-reset, ddMode common }
    CRITICALITY
                            reject
radioLinkActivationFDD RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE
                            RadioLinkActivationCommandFDD
    PROCEDURE ID
                            { procedureCode id-radioLinkActivation, ddMode fdd }
```

```
CRITICALITY
                            ignore
radioLinkActivationTDD RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE
                            RadioLinkActivationCommandTDD
                            { procedureCode id-radioLinkActivation, ddMode tdd }
    PROCEDURE ID
    CRITICALITY
                            ignore
gERANuplinkSignallingTransfer RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE GERANUplinkSignallingTransferIndication
                        { procedureCode id-qERANuplinkSignallingTransfer, ddMode common }
    PROCEDURE ID
    CRITICALITY
                    ignore
radioLinkParameterUpdateFDD RNSAP-ELEMENTARY-PROCEDURE ::= {
                            RadioLinkParameterUpdateIndicationFDD
    INITIATING MESSAGE
                            { procedureCode id-radioLinkParameterUpdate, ddMode fdd }
    PROCEDURE ID
    CRITICALITY
                            ignore
radioLinkParameterUpdateTDD RNSAP-ELEMENTARY-PROCEDURE ::= {
                            RadioLinkParameterUpdateIndicationTDD
    INITIATING MESSAGE
    PROCEDURE ID
                            { procedureCode id-radioLinkParameterUpdate, ddMode tdd }
    CRITICALITY
uEMeasurementInitiation RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE UEMeasurementInitiationRequest
    SUCCESSFUL OUTCOME UEMeasurementInitiationResponse
    UNSUCCESSFUL OUTCOME
                            UEMeasurementInitiationFailure
    PROCEDURE ID
                        { procedureCode id-uEMeasurementInitiation, ddMode tdd }
    CRITICALITY
                    reject
uEMeasurementReporting RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE UEMeasurementReport
                        { procedureCode id-uEMeasurementReporting, ddMode tdd }
    PROCEDURE ID
    CRITICALITY
                    ignore
uEMeasurementTermination RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE UEMeasurementTerminationRequest
    PROCEDURE ID
                        { procedureCode id-uEMeasurementTermination, ddMode tdd }
    CRITICALITY
                    ignore
uEMeasurementFailure RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE UEMeasurementFailureIndication
    PROCEDURE ID
                        { procedureCode id-uEMeasurementFailure, ddMode tdd }
    CRITICALITY
                    ignore
iurInvokeTrace RNSAP-ELEMENTARY-PROCEDURE ::= {
```

```
INITIATING MESSAGE IurInvokeTrace
    PROCEDURE ID
                        { procedureCode id-iurInvokeTrace, ddMode common }
    CRITICALITY
iurDeactivateTrace RNSAP-ELEMENTARY-PROCEDURE ::= {
    { procedureCode id-iurDeactivateTrace, ddMode common }
    PROCEDURE ID
    CRITICALITY
mbmsAttach RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE
                           MBMSAttachCommand
    PROCEDURE ID
                            { procedureCode id-mBMSAttach, ddMode common }
    CRITICALITY
                           ignore
mBMSDetach RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE
                           MBMSDetachCommand
                            { procedureCode id-mBMSDetach, ddMode common }
    PROCEDURE ID
    CRITICALITY
                           ignore
directInformationTransfer RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE
                           DirectInformationTransfer
    PROCEDURE ID
                           { procedureCode id-directInformationTransfer, ddMode common }
    CRITICALITY
                           ignore
enhancedRelocation RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE EnhancedRelocationRequest
    SUCCESSFUL OUTCOME EnhancedRelocationResponse
    UNSUCCESSFUL OUTCOME
                           EnhancedRelocationFailure
                       { procedureCode id-enhancedRelocation, ddMode common }
    PROCEDURE ID
    CRITICALITY
                   reject
enhancedRelocationCancel RNSAP-ELEMENTARY-PROCEDURE ::= {
                           EnhancedRelocationCancel
    INITIATING MESSAGE
    PROCEDURE ID
                            { procedureCode id-enhancedRelocationCancel, ddMode common }
    CRITICALITY
                           ignore
enhancedRelocationSignallingTransfer RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE
                           EnhancedRelocationSignallingTransfer
                            { procedureCode id-enhancedRelocationSignallingTransfer, ddMode common }
    PROCEDURE ID
    CRITICALITY
                           ignore
enhancedRelocationRelease RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE
                           EnhancedRelocationRelease
    PROCEDURE ID
                            { procedureCode id-enhancedRelocationRelease, ddMode common }
    CRITICALITY
                           ignore
```

```
mbsfnmcchinformation RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE
                           MBSFNMCCHInformation
    PROCEDURE ID
                            { procedureCode id-mBSFNMCCHInformation, ddMode common }
    CRITICALITY
                            reject
secondaryULFrequencyReportingFDD RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE
                            SecondaryULFrequencyReport
    PROCEDURE ID
                            { procedureCode id-secondaryULFrequencyReporting, ddMode fdd }
    CRITICALITY
secondaryULFrequencyUpdateFDD RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE
                            SecondaryULFrequencyUpdateIndication
    PROCEDURE ID
                            { procedureCode id-secondaryULFrequencyUpdate, ddMode fdd }
    CRITICALITY
enhancedRelocationResourceAllocation RNSAP-ELEMENTARY-PROCEDURE ::= {
                            EnhancedRelocationResourceRequest
    INITIATING MESSAGE
    SUCCESSFUL OUTCOME
                            EnhancedRelocationResourceResponse
                            EnhancedRelocationResourceFailure
   UNSUCCESSFUL OUTCOME
                            { procedureCode id-enhancedRelocationResourceAllocation, ddMode tdd }
    PROCEDURE ID
    CRITICALITY
                            reject
enhancedRelocationResourceRelease RNSAP-ELEMENTARY-PROCEDURE ::=
    INITIATING MESSAGE
                            EnhancedRelocationResourceReleaseCommand
    SUCCESSFUL OUTCOME
                            EnhancedRelocationResourceReleaseComplete
                            { procedureCode id-enhancedRelocationResourceRelease, ddMode tdd }
    PROCEDURE ID
    CRITICALITY
                            reject
informationTransferControl RNSAP-ELEMENTARY-PROCEDURE ::= {
    INITIATING MESSAGE
                            InformationTransferControlRequest
    PROCEDURE ID
                            { procedureCode id-informationTransferControl, ddMode common }
    CRITICALITY
                            ignore
END
```

9.3.3 PDU Definitions

```
DEFINITIONS AUTOMATIC TAGS ::=
BEGIN
__ **********************
-- IE parameter types from other modules.
IMPORTS
    Active-Pattern-Sequence-Information,
   Active-MBMS-Bearer-Service-ListFDD,
   Active-MBMS-Bearer-Service-ListFDD-PFL,
   Active-MBMS-Bearer-Service-ListTDD,
   Active-MBMS-Bearer-Service-ListTDD-PFL,
   AllocationRetentionPriority,
   AllowedOueuingTime,
   Allowed-Rate-Information,
   AlphaValue,
    AlternativeFormatReportingIndicator,
    AntennaColocationIndicator,
    BLER.
    SCTD-Indicator,
    BindingID,
    C-ID,
    C-RNTI,
    CCTrCH-ID,
    CFN,
    CGI,
    ClosedLoopModel-SupportIndicator,
    Closedlooptimingadjustmentmode,
    CN-CS-DomainIdentifier,
    CN-PS-DomainIdentifier,
    CNDomainType,
    Cause,
    CellCapabilityContainer-FDD,
    CellCapabilityContainerExtension-FDD,
    CellCapabilityContainer-TDD,
    CellCapabilityContainer-TDD-LCR,
    CellCapabilityContainer-TDD768,
    CellParameterID,
    CellPortionID,
    ChipOffset,
    CommonMeasurementAccuracy,
    CommonMeasurementType,
    CommonMeasurementValue,
    CommonMeasurementValueInformation,
    CommonTransportChannelResourcesInitialisationNotRequired,
    Common-EDCH-MAC-d-Flow-Specific-InformationFDD,
    Common-EDCH-Support-Indicator,
    CongestionCause,
    Continuous-Packet-Connectivity-DTX-DRX-Information,
    Continuous-Packet-Connectivity-HS-SCCH-Less-Information,
```

EDCH-Serving-RL,

```
Continuous-Packet-Connectivity-HS-SCCH-Less-Information-Response,
CPC-Information.
CoverageIndicator.
CriticalityDiagnostics,
CellPortionLCRID.
D-RNTI.
D-RNTI-ReleaseIndication.
DCH-FDD-Information,
DCH-ID,
DCH-Indicator-For-E-DCH-HSDPA-Operation,
DPCH-ID768,
DCH-InformationResponse,
DCH-TDD-Information,
DL-DPCH-SlotFormat,
DL-TimeslotISCP,
DL-Power.
DL-PowerBalancing-Information,
DL-PowerBalancing-ActivationIndicator,
DL-PowerBalancing-UpdatedIndicator,
DL-ReferencePowerInformation,
DL-ScramblingCode,
DL-Timeslot-Information,
DL-Timeslot-Information768,
DL-TimeslotLCR-Information,
DL-TimeSlot-ISCP-Info,
DL-TimeSlot-ISCP-LCR-Information,
DPC-Mode,
DPC-Mode-Change-SupportIndicator,
DPCH-ID,
DL-DPCH-TimingAdjustment,
DRXCycleLengthCoefficient,
DedicatedMeasurementType,
DedicatedMeasurementValue,
DedicatedMeasurementValueInformation,
DelayedActivation,
DelayedActivationUpdate,
DiversityControlField,
DiversityMode,
DSCH-FlowControlInformation,
DSCH-FlowControlItem,
DSCH-TDD-Information,
DSCH-ID,
DSCH-RNTI,
EDCH-FDD-Information,
EDCH-FDD-InformationResponse,
EDCH-FDD-Information-To-Modify,
EDCH-FDD-DL-ControlChannelInformation.
EDCH-DDI-Value,
EDCH-MACdFlow-ID,
EDCH-MACdFlow-Specific-InfoList,
EDCH-MACdFlows-To-Delete,
EDCH-MACdFlows-Information,
EDCH-RL-Indication,
```

```
E-DCH-Serving-cell-change-informationResponse,
EDPCH-Information-FDD.
EDPCH-Information-RLReconfPrepare-FDD.
EDPCH-Information-RLReconfRequest-FDD,
E-DCH-FDD-Update-Information,
E-DPCCH-PO,
E-RGCH-2-IndexStepThreshold,
E-RGCH-3-IndexStepThreshold,
E-RNTI,
E-TFCS-Information,
E-TTI,
Enhanced-FACH-Support-Indicator,
Enhanced-FACH-Information-ResponseFDD,
Enhanced-PCH-Capability,
ExtendedPropagationDelay,
Extended-RNC-ID,
SchedulingPriorityIndicator,
Enhanced-PrimaryCPICH-EcNo,
F-DPCH-SlotFormat,
F-DPCH-SlotFormatSupportRequest,
FACH-FlowControlInformation,
Fast-Reconfiguration-Mode,
Fast-Reconfiguration-Permission,
FDD-DCHs-to-Modify,
FDD-DL-ChannelisationCodeNumber,
FDD-DL-CodeInformation.
FDD-TPC-DownlinkStepSize,
FirstRLS-Indicator,
FNReportingIndicator,
FrameHandlingPriority,
FrameOffset,
GA-AccessPointPosition,
GA-Cell,
GA-CellAdditionalShapes,
HARO-Info-for-E-DCH,
HCS-Prio,
HSDSCH-Configured-Indicator,
HSDSCH-FDD-Information,
HSDSCH-FDD-Information-Response,
HSDSCH-FDD-Update-Information,
HSDSCH-TDD-Update-Information,
HSDSCH-Information-to-Modify,
HSDSCH-Information-to-Modify-Unsynchronised,
HSDSCH-MACdFlow-ID,
HSDSCH-MACdFlows-Information,
HSDSCH-MACdFlows-to-Delete,
HSDSCH-Physical-Layer-Category,
HSDSCH-RNTI,
HS-DSCH-serving-cell-change-information,
HS-DSCH-serving-cell-change-informationResponse,
HSDSCH-TDD-Information,
HSDSCH-TDD-Information-Response,
HS-SICH-ID,
IMSI,
```

```
InformationExchangeID,
InformationReportCharacteristics,
InformationType.
Initial-DL-DPCH-TimingAdjustment-Allowed,
InnerLoopDLPCStatus,
Inter-Frequency-Cell-List,
L3-Information.
LimitedPowerIncrease,
MaximumAllowedULTxPower,
MaxNrDLPhysicalchannels,
MaxNrDLPhysicalchannelsTS,
MaxNrDLPhysicalchannels768,
MaxNrDLPhysicalchannelsTS768.
MaxNrOfUL-DPCHs,
MaxNrTimeslots,
MaxNrULPhysicalchannels,
MACes-Guaranteed-Bitrate,
MaxNr-Retransmissions-EDCH,
Max-Set-E-DPDCHs,
Max-UE-DTX-Cycle,
MeasurementFilterCoefficient,
MeasurementID,
MeasurementRecoveryBehavior,
MeasurementRecoveryReportingIndicator,
MeasurementRecoverySupportIndicator,
MBMS-Bearer-Service-List,
MBSFN-Cluster-Identity,
MCCH-Configuration-Info,
MCCH-Message-List,
MBSFN-Scheduling-Transmission-Time-Interval-Info-List,
MidambleAllocationMode,
MidambleShiftAndBurstType,
MidambleShiftAndBurstType768,
MidambleShiftLCR,
MinimumSpreadingFactor,
MinimumSpreadingFactor768,
MinUL-ChannelisationCodeLength,
Multiple-PLMN-List,
MultiplexingPosition,
NeighbouringFDDCellMeasurementInformation,
NeighbouringTDDCellMeasurementInformation,
NeighbouringTDDCellMeasurementInformation768,
Neighbouring-GSM-CellInformation,
Neighbouring-UMTS-CellInformation,
NeighbouringTDDCellMeasurementInformationLCR,
Neighbouring-E-UTRA-CellInformation,
NrOfDLchannelisationcodes,
PagingCause,
PagingRecordType,
PartialReportingIndicator,
PayloadCRC-PresenceIndicator,
PCCPCH-Power,
PC-Preamble,
Permanent-NAS-UE-Identity,
```

```
Phase-Reference-Update-Indicator,
PowerAdjustmentType,
PowerOffset.
PrimaryCCPCH-RSCP,
PrimaryCPICH-EcNo,
PrimaryCPICH-Power,
Primary-CPICH-Usage-For-Channel-Estimation,
PrimaryScramblingCode,
PropagationDelay,
ProvidedInformation,
PunctureLimit,
OE-Selector,
RANAP-EnhancedRelocationInformationRequest,
RANAP-EnhancedRelocationInformationResponse,
RANAP-RelocationInformation,
RB-Info.
Released-CN-Domain,
RL-ID,
RL-Set-ID,
RL-Specific-EDCH-Information,
RNC-ID,
RepetitionLength,
RepetitionPeriod,
ReportCharacteristics,
Received-total-wide-band-power,
RequestedDataValue,
RequestedDataValueInformation,
RL-Specific-DCH-Info,
RxTimingDeviationForTA,
RxTimingDeviationForTA768,
S-RNTI,
S-RNTI-Group,
SCH-TimeSlot,
SAI,
SFN,
Secondary-CCPCH-Info-TDD,
Secondary-CCPCH-Info-TDD768,
Secondary-CCPCH-System-Information-MBMS,
Secondary-CPICH-Information,
Secondary-CPICH-Information-Change,
Secondary-LCR-CCPCH-Info-TDD,
Secondary-Serving-Cell-List,
SNA-Information,
SpecialBurstScheduling,
SSDT-SupportIndicator,
STTD-SupportIndicator,
AdjustmentPeriod,
ScaledAdjustmentRatio,
MaxAdjustmentStep,
SRB-Delay,
Support-8PSK,
SyncCase,
SynchronisationConfiguration,
SixtyfourQAM-DL-SupportIndicator,
```

```
TDD-ChannelisationCode,
TDD-ChannelisationCode768.
TDD-DCHs-to-Modify.
TDD-DL-Code-Information,
TDD-DPCHOffset.
TDD-PhysicalChannelOffset,
TDD-TPC-DownlinkStepSize,
TDD-ChannelisationCodeLCR,
TDD-DL-Code-LCR-Information,
TDD-DL-Code-Information768,
TDD-UL-Code-Information,
TDD-UL-Code-LCR-Information,
TDD-UL-Code-Information768,
TFCI-Coding,
TFCI-Presence,
TFCI-SignallingMode,
TimeSlot,
TimeSlotLCR,
TimingAdvanceApplied,
TMGI,
TnlQos,
ToAWE,
ToAWS,
TraceDepth,
TraceRecordingSessionReference,
TraceReference,
TrafficClass,
TransmitDiversityIndicator,
TransportBearerID,
TransportBearerRequestIndicator,
Transmission-Gap-Pattern-Sequence-Information,
TransportFormatManagement,
TransportFormatSet,
TransportLayerAddress,
TrCH-SrcStatisticsDescr.
TSTD-Indicator,
TSTD-Support-Indicator,
UARFCN,
UC-ID,
UE-AggregateMaximumBitRate,
UEIdentity,
UEMeasurementType,
UEMeasurementTimeslotInfoHCR,
UEMeasurementTimeslotInfoLCR,
UEMeasurementTimeslotInfo768,
UEMeasurementReportCharacteristics.
UEMeasurementParameterModAllow,
UEMeasurementValueInformation.
UE-State,
UL-DPCCH-SlotFormat,
UL-DPDCHIndicatorEDCH,
UL-SIR,
UL-FP-Mode,
```

```
UL-PhysCH-SF-Variation,
UL-ScramblingCode,
UL-Timeslot-Information.
UL-Timeslot-Information768.
UL-TimeslotLCR-Information.
UL-TimeSlot-ISCP-Info,
UL-TimeSlot-ISCP-LCR-Info.
URA-ID,
URA-Information,
USCH-ID,
USCH-Information,
UL-Synchronisation-Parameters-LCR,
TDD-DL-DPCH-TimeSlotFormat-LCR.
TDD-UL-DPCH-TimeSlotFormat-LCR,
MAChs-ResetIndicator,
UL-TimingAdvanceCtrl-LCR,
TDD-TPC-UplinkStepSize-LCR,
PrimaryCCPCH-RSCP-Delta,
SynchronisationIndicator,
Support-PLCCH,
PLCCHinformation,
RxTimingDeviationForTAext,
E-DCH-Information,
E-DCH-Information-Reconfig,
E-DCH-Information-Response,
E-DCH-768-Information,
E-DCH-768-Information-Reconfig,
E-DCH-768-Information-Response,
E-DCH-LCR-Information,
E-DCH-LCR-Information-Reconfig,
E-DCH-LCR-Information-Response,
ControlGAP,
IdleIntervalInformation,
NeedforIdleInterval,
HS-SICH-ID-Extension,
TSN-Length,
UPPCHPositionLCR,
Common-EDCH-MAC-d-Flow-Specific-InformationLCR,
Enhanced-FACH-Information-ResponseLCR,
HSDSCH-PreconfigurationSetup,
HSDSCH-PreconfigurationInfo,
NoOfTargetCellHS-SCCH-Order,
EnhancedHSServingCC-Abort,
GANSS-Time-ID,
HS-DSCH-FDD-Secondary-Serving-Update-Information,
HS-DSCH-Secondary-Serving-Remove,
HS-DSCH-FDD-Secondary-Serving-Information-To-Modify-Unsynchronised,
HS-DSCH-Secondary-Serving-Information-To-Modify,
HS-DSCH-Secondary-Serving-Cell-Change-Information-Response,
HS-DSCH-FDD-Secondary-Serving-Information-Response,
HS-DSCH-FDD-Secondary-Serving-Information,
MinimumReducedE-DPDCH-GainFactor,
ContinuousPacketConnectivity-DRX-InformationLCR,
ContinuousPacketConnectivity-DRX-Information-ResponseLCR,
```

```
CPC-InformationLCR,
    E-DCH-Semi-PersistentScheduling-Information-LCR,
    HS-DSCH-Semi-PersistentScheduling-Information-LCR,
    HS-DSCH-Semi-PersistentScheduling-Information-ResponseLCR,
    E-DCH-Semi-PersistentScheduling-Information-ResponseLCR,
    RNTI-Allocation-Indicator,
    ActivationInformation.
    Additional-EDCH-Setup-Info,
    Additional-EDCH-Cell-Information-Response-List,
    Additional-EDCH-FDD-Update-Information,
    Additional-EDCH-Cell-Information-To-Add-List,
    Additional-EDCH-Cell-Information-Response-RLReconf-List,
    DCH-MeasurementOccasion-Information,
    DCH-MeasurementType-Indicator,
    Setup-Or-ConfigurationChange-Or-Removal-Of-EDCH-On-secondary-UL-Frequency,
    Additional-EDCH-Cell-Information-Response-RLAddList,
    Non-Serving-RL-Preconfig-Setup,
    Non-Serving-RL-Preconfig-Info,
    CellCapabilityContainerExtension-TDD-LCR,
   Multi-Carrier-EDCH-Info,
   Multi-Carrier-EDCH-Reconfigure,
   Multi-Carrier-EDCH-Information-Response,
   MU-MIMO-InformationLCR,
   MU-MIMO-Indicator,
    Usefulness-Of-Battery-Optimization,
   MDT-Configuration,
   Neighbouring-UMTS-CellInformation-Ext,
    SourceID,
    TargetID,
    ClassmarkInformation2,
    ClassmarkInformation3,
    SpeechVersion,
    Cell-Capacity-Class-Value,
    LoadValue,
    Controlled-Object-Scope,
    CPC-RecoveryReport
FROM RNSAP-IEs
    PrivateIE-Container{},
    ProtocolExtensionContainer{},
    ProtocolIE-ContainerList{},
    ProtocolIE-ContainerPair{},
    ProtocolIE-ContainerPairList{},
    ProtocolIE-Container{},
    ProtocolIE-Single-Container{},
    RNSAP-PRIVATE-IES,
    RNSAP-PROTOCOL-EXTENSION,
    RNSAP-PROTOCOL-IES,
    RNSAP-PROTOCOL-IES-PAIR
FROM RNSAP-Containers
```

```
maxCellsMeas,
maxNoOfDSCHs.
maxNoOfUSCHs.
maxNrOfCCTrCHs,
maxNrOfDCHs,
maxNrOfTS,
maxNrOfDPCHs.
maxNrOfDPCHs768,
maxNrOfDPCHsPerRL-1,
maxNrOfDPCHs768PerRL-1,
maxNrOfInterfaces,
maxNrOfRLs,
maxNrOfRLSets,
maxNrOfRLSets-1,
maxNrOfRLs-1,
maxNrOfRLs-2,
maxNrOfULTs,
maxNrOfDLTs,
maxResetContext,
maxResetContextGroup,
maxNoOfDSCHsLCR,
maxNoOfUSCHsLCR,
maxNrOfCCTrCHsLCR,
maxNrOfTsLCR,
maxNrOfDLTsLCR,
maxNrOfULTsLCR,
maxNrOfDPCHsLCR,
maxNrOfDPCHsLCRPerRL-1,
maxNrOfLCRTDDNeighboursPerRNC,
maxNrOfMeasNCell,
maxNrOfMACdFlows,
maxNrOfMACdPDUSize,
maxNrOfMCCHMessages,
maxNrOfMBMSL3,
maxNrOfEDCHMACdFlows,
maxNrOfHSSICHs,
maxNrOfHSSICHs-1,
maxNrOfActiveMBMSServices,
maxNrOfMBMSServices,
maxNrofSigSeqERGHICH-1,
maxNrOfCells,
maxNrOfHSDSCH-1,
maxNrOfEDCH-1,
maxNrOfULCarriersLCR-1,
maxNoOfGsmCell,
maxNrOfANRCells.
id-Active-MBMS-Bearer-ServiceFDD,
id-Active-MBMS-Bearer-ServiceFDD-PFL,
id-Active-MBMS-Bearer-ServiceTDD,
id-Active-MBMS-Bearer-ServiceTDD-PFL,
id-Active-Pattern-Sequence-Information,
id-AdjustmentRatio,
id-AllowedQueuingTime,
id-AlternativeFormatReportingIndicator,
```

```
id-AntennaColocationIndicator,
id-BindingID.
id-C-ID.
id-C-RNTI,
id-CFN.
id-CFNReportingIndicator,
id-CN-CS-DomainIdentifier.
id-CN-PS-DomainIdentifier,
id-Cause.
id-CauseLevel-RL-AdditionFailureFDD,
id-CauseLevel-RL-AdditionFailureTDD,
id-CauseLevel-RL-ReconfFailure,
id-CauseLevel-RL-SetupFailureFDD,
id-CauseLevel-RL-SetupFailureTDD,
id-CCTrCH-InformationItem-RL-FailureInd.
id-CCTrCH-InformationItem-RL-RestoreInd.
id-CellCapabilityContainer-FDD,
id-CellCapabilityContainerExtension-FDD,
id-CellCapabilityContainer-TDD,
id-CellCapabilityContainer-TDD-LCR,
id-CellPortionID,
id-ChipOffset,
id-ClosedLoopModel-SupportIndicator,
id-CNOriginatedPage-PagingRgst,
id-CommonMeasurementAccuracy,
id-CommonMeasurementObjectType-CM-Rprt,
id-CommonMeasurementObjectType-CM-Rqst,
id-CommonMeasurementObjectType-CM-Rsp,
id-CommonMeasurementType,
id-CommonTransportChannelResourcesInitialisationNotRequired,
id-Common-EDCH-MAC-d-Flow-Specific-InformationFDD,
id-Common-EDCH-Support-Indicator,
id-CongestionCause,
id-Continuous-Packet-Connectivity-DTX-DRX-Information,
id-Continuous-Packet-Connectivity-HS-SCCH-Less-Information,
id-Continuous-Packet-Connectivity-HS-SCCH-Less-Information-Response,
id-CPC-Information,
id-CoverageIndicator,
id-CriticalityDiagnostics,
id-CellPortionLCRID,
id-D-RNTI,
id-D-RNTI-ReleaseIndication.
id-DCHs-to-Add-FDD,
id-DCHs-to-Add-TDD,
id-DCH-DeleteList-RL-ReconfPrepFDD,
id-DCH-DeleteList-RL-ReconfPrepTDD.
id-DCH-DeleteList-RL-ReconfRastFDD,
id-DCH-DeleteList-RL-ReconfRgstTDD,
id-DCH-FDD-Information,
id-DCH-TDD-Information,
id-DCH-Indicator-For-E-DCH-HSDPA-Operation,
id-FDD-DCHs-to-Modify,
id-TDD-DCHs-to-Modify,
id-DCH-InformationResponse,
```

```
id-DCH-Rate-InformationItem-RL-CongestInd,
id-DL-CCTrCH-InformationAddItem-RL-ReconfPrepTDD.
id-DL-CCTrCH-InformationDeleteItem-RL-ReconfPrepTDD.
id-DL-CCTrCH-InformationModifyItem-RL-ReconfPrepTDD,
id-DL-CCTrCH-InformationListIE-RL-ReconfReadyTDD.
id-DL-CCTrCH-InformationModifyItem-RL-ReconfRgstTDD,
id-DL-CCTrCH-InformationDeleteItem-RL-ReconfRgstTDD,
id-DL-CCTrCH-InformationItem-RL-SetupRgstTDD,
id-DL-CCTrCH-InformationListIE-PhyChReconfRgstTDD,
id-DL-CCTrCH-InformationListIE-RL-AdditionRspTDD.
id-DL-CCTrCH-InformationListIE-RL-SetupRspTDD,
id-DL-CCTrCH-InformationAddList-RL-ReconfPrepTDD,
id-DL-CCTrCH-InformationDeleteList-RL-ReconfPrepTDD.
id-DL-CCTrCH-InformationModifyList-RL-ReconfPrepTDD,
id-DL-CCTrCH-InformationDeleteList-RL-ReconfRgstTDD,
id-DL-CCTrCH-InformationModifyList-RL-ReconfRqstTDD,
id-DL-CCTrCH-InformationList-RL-SetupRgstTDD,
id-FDD-DL-CodeInformation,
id-DL-DPCH-Information-RL-ReconfPrepFDD,
id-DL-DPCH-Information-RL-SetupRgstFDD,
id-DL-DPCH-Information-RL-ReconfRqstFDD,
id-DL-DPCH-InformationItem-PhyChReconfRqstTDD,
id-DL-DPCH-InformationItem-RL-AdditionRspTDD,
id-DL-DPCH-InformationItem-RL-SetupRspTDD,
id-DL-DPCH-InformationAddListIE-RL-ReconfReadyTDD,
id-DL-DPCH-InformationDeleteListIE-RL-ReconfReadyTDD,
id-DL-DPCH-InformationModifyListIE-RL-ReconfReadyTDD,
id-DL-DPCH-TimingAdjustment,
id-DL-DPCH-Power-Information-RL-ReconfPrepFDD,
id-DL-Physical-Channel-Information-RL-SetupRgstTDD,
id-DL-PowerBalancing-Information,
id-DL-PowerBalancing-ActivationIndicator,
id-DL-PowerBalancing-UpdatedIndicator,
id-DL-ReferencePowerInformation,
id-DLReferencePower,
id-DLReferencePowerList-DL-PC-Rgst,
id-DL-ReferencePowerInformation-DL-PC-Rgst,
id-DRXCycleLengthCoefficient,
id-DedicatedMeasurementObjectType-DM-Fail,
id-DedicatedMeasurementObjectType-DM-Fail-Ind,
id-DedicatedMeasurementObjectType-DM-Rprt,
id-DedicatedMeasurementObjectType-DM-Rgst,
id-DedicatedMeasurementObjectType-DM-Rsp,
id-DedicatedMeasurementType,
id-DelayedActivation,
id-DelayedActivationList-RL-ActivationCmdFDD,
id-DelayedActivationList-RL-ActivationCmdTDD.
id-DelayedActivationInformation-RL-ActivationCmdFDD,
id-DelayedActivationInformation-RL-ActivationCmdTDD,
id-DPC-Mode,
id-DPC-Mode-Change-SupportIndicator,
id-DSCHs-to-Add-TDD,
id-DSCH-DeleteList-RL-ReconfPrepTDD,
id-DSCH-InformationListIE-RL-AdditionRspTDD,
```

```
id-DSCH-InformationListIEs-RL-SetupRspTDD,
id-DSCH-TDD-Information.
id-DSCH-ModifyList-RL-ReconfPrepTDD.
id-DSCH-RNTI.
id-DSCHToBeAddedOrModifiedList-RL-ReconfReadvTDD.
id-Dual-Band-Secondary-Serving-Cell-List,
id-EDPCH-Information.
id-EDCH-RL-Indication,
id-EDCH-FDD-Information.
id-Serving-EDCHRL-Id,
id-EDCH-FDD-DL-ControlChannelInformation,
id-EDCH-FDD-InformationResponse,
id-E-DCH-FDD-Update-Information,
id-EDCH-MACdFlows-To-Add,
id-EDCH-FDD-Information-To-Modify,
id-EDCH-MACdFlows-To-Delete,
id-EDPCH-Information-RLReconfRequest-FDD,
id-EDPCH-Information-RLAdditionReg-FDD,
id-EDCH-MacdFlowSpecificInformationList-RL-PreemptRequiredInd,
id-EDCH-MacdFlowSpecificInformationItem-RL-PreemptRequiredInd,
id-EDCH-MacdFlowSpecificInformationList-RL-CongestInd,
id-EDCH-MacdFlowSpecificInformationItem-RL-CongestInd,
id-Enhanced-FACH-Support-Indicator,
id-Enhanced-FACH-Information-ResponseFDD,
id-Enhanced-PCH-Capability,
id-ExtendedPropagationDelay,
id-Extended-SRNC-ID,
id-Extended-RNC-ID,
id-Serving-cell-change-CFN,
id-E-DCH-Serving-cell-change-informationResponse,
id-E-RNTI-For-FACH,
id-H-RNTI-For-FACH,
id-RNTI-Allocation-Indicator,
id-Enhanced-PrimaryCPICH-EcNo,
id-E-RNTI,
id-F-DPCH-SlotFormat,
id-F-DPCH-SlotFormatSupportRequest,
id-FACH-InfoForUESelectedS-CCPCH-CTCH-ResourceRspFDD,
id-FACH-InfoForUESelectedS-CCPCH-CTCH-ResourceRspTDD,
id-Fast-Reconfiguration-Mode,
id-Fast-Reconfiguration-Permission,
id-FrameOffset.
id-F-DPCH-Information-RL-ReconfPrepFDD,
id-F-DPCH-Information-RL-SetupRgstFDD,
id-GA-Cell,
id-GA-CellAdditionalShapes,
id-GSM-Cell-InfEx-Rost,
id-HCS-Prio,
id-HSDSCH-Configured-Indicator,
id-HSDSCH-FDD-Information,
id-HSDSCH-FDD-Information-Response,
id-HSDSCH-FDD-Update-Information,
id-HSDSCH-TDD-Update-Information,
id-HSDSCH-Information-to-Modify,
```

```
id-HSDSCH-Information-to-Modify-Unsynchronised,
id-HSDSCH-MACdFlows-to-Add.
id-HSDSCH-MACdFlows-to-Delete.
id-HSDSCHMacdFlowSpecificInformationList-RL-PreemptRequiredInd,
id-HSDSCHMacdFlowSpecificInformationItem-RL-PreemptRequiredInd,
id-HSDSCH-Physical-Layer-Category,
id-HSDSCH-RNTI,
id-HS-DSCH-serving-cell-change-information,
id-HS-DSCH-serving-cell-change-informationResponse,
id-HSDSCH-TDD-Information,
id-HSDSCH-TDD-Information-Response,
id-HSPDSCH-RL-ID,
id-HSPDSCH-Timeslot-InformationList-PhyChReconfRqstTDD,
id-HSPDSCH-Timeslot-InformationListLCR-PhyChReconfRgstTDD.
id-HSSICH-Info-DM-Rprt,
id-HSSICH-Info-DM-Rgst,
id-HSSICH-Info-DM,
id-IMSI,
id-InformationExchangeID,
id-InformationExchangeObjectType-InfEx-Rprt,
id-InformationExchangeObjectType-InfEx-Rgst,
id-InformationExchangeObjectType-InfEx-Rsp,
id-InformationReportCharacteristics,
id-InformationType,
id-Initial-DL-DPCH-TimingAdjustment,
id-Initial-DL-DPCH-TimingAdjustment-Allowed,
id-InnerLoopDLPCStatus,
id-InterfacesToTraceItem,
id-Inter-Frequency-Cell-List,
id-L3-Information,
id-AdjustmentPeriod,
id-ListOfInterfacesToTrace,
id-MaxAdjustmentStep,
id-Max-UE-DTX-Cycle,
id-MBMS-Bearer-Service-List,
id-MBMS-Bearer-Service-List-InfEx-Rsp,
id-MBMS-Bearer-Service-in-MBMS-Cell-InfEx-Rgst,
id-MBMS-Bearer-Service-in-MBMS-Cell-InfEx-Rsp,
id-MBMS-Bearer-Service-in-MBMS-Cell-InfEx-Rprt,
id-MBMS-Cell-InfEx-Rgst,
id-MBMS-Cell-InfEx-Rsp,
id-MBMS-Cell-InfEx-Rprt,
id-MBSFN-Cluster-Identity,
id-MBSFN-Scheduling-Transmission-Time-Interval-Info-List,
id-MCCH-Configuration-Info,
id-MCCH-Message-List,
id-MeasurementFilterCoefficient,
id-MeasurementID,
id-MeasurementRecoveryBehavior,
id-MeasurementRecoveryReportingIndicator,
id-MeasurementRecoverySupportIndicator,
id-Multiple-PLMN-List,
id-Multiple-RL-InformationResponse-RL-ReconfReadyTDD,
id-NACC-Related-Data,
```

```
id-Neighbouring-E-UTRA-CellInformation,
id-Old-URA-ID.
id-PagingArea-PagingRost.
id-PartialReportingIndicator,
id-PDSCH-RL-ID.
id-Permanent-NAS-UE-Identity,
id-Phase-Reference-Update-Indicator,
id-FACH-FlowControlInformation,
id-PLCCH-Information-PhyChReconfRgstTDD,
id-PowerAdjustmentType,
id-PrimCCPCH-RSCP-DL-PC-RqstTDD,
id-Primary-CPICH-Usage-For-Channel-Estimation,
id-PropagationDelay,
id-ProvidedInformation,
id-RANAP-EnhancedRelocationInformationRequest,
id-RANAP-EnhancedRelocationInformationResponse,
id-RANAP-RelocationInformation,
id-ResetIndicator,
id-Released-CN-Domain,
id-EDCH-RLSet-Id.
id-RL-Information-PhyChReconfRqstFDD,
id-RL-Information-PhyChReconfRqstTDD,
id-RL-Information-RL-AdditionRqstFDD,
id-RL-Information-RL-AdditionRgstTDD,
id-RL-Information-RL-DeletionRgst,
id-RL-Information-RL-FailureInd.
id-RL-Information-RL-ReconfPrepFDD,
id-RL-Information-RL-ReconfPrepTDD,
id-RL-Information-RL-RestoreInd,
id-RL-Information-RL-SetupRgstFDD,
id-RL-Information-RL-SetupRgstTDD,
id-RL-InformationItem-RL-CongestInd,
id-RL-InformationItem-DM-Rprt,
id-RL-InformationItem-DM-Rqst,
id-RL-InformationItem-DM-Rsp.
id-RL-InformationItem-RL-PreemptRequiredInd,
id-RL-InformationItem-RL-SetupRqstFDD,
id-RL-InformationList-RL-CongestInd,
id-RL-InformationList-RL-AdditionRgstFDD,
id-RL-InformationList-RL-DeletionRgst,
id-RL-InformationList-RL-PreemptRequiredInd,
id-RL-InformationList-RL-ReconfPrepFDD,
id-RL-InformationResponse-RL-AdditionRspTDD,
id-RL-InformationResponse-RL-ReconfReadyTDD,
id-RL-InformationResponse-RL-ReconfRspTDD,
id-RL-InformationResponse-RL-SetupRspTDD,
id-RL-InformationResponseItem-RL-AdditionRspFDD,
id-RL-InformationResponseItem-RL-ReconfReadyFDD,
id-RL-InformationResponseItem-RL-ReconfRspFDD,
id-RL-InformationResponseItem-RL-SetupRspFDD,
id-RL-InformationResponseList-RL-AdditionRspFDD,
id-RL-InformationResponseList-RL-ReconfReadyFDD,
id-RL-InformationResponseList-RL-ReconfRspFDD,
id-RL-InformationResponseList-RL-SetupRspFDD,
```

```
id-RL-ParameterUpdateIndicationFDD-RL-Information-Item,
id-RL-ParameterUpdateIndicationFDD-RL-InformationList,
id-RL-ReconfigurationFailure-RL-ReconfFail.
id-RL-ReconfigurationRequestFDD-RL-InformationList,
id-RL-ReconfigurationRequestFDD-RL-Information-IEs.
id-RL-ReconfigurationRequestTDD-RL-Information,
id-RL-ReconfigurationResponseTDD-RL-Information,
id-RL-Specific-DCH-Info,
id-RL-Specific-EDCH-Information,
id-RL-Set-InformationItem-DM-Rprt,
id-RL-Set-InformationItem-DM-Rgst,
id-RL-Set-InformationItem-DM-Rsp,
id-RL-Set-Information-RL-FailureInd,
id-RL-Set-Information-RL-RestoreInd,
id-RL-Set-Successful-InformationItem-DM-Fail,
id-RL-Set-Unsuccessful-InformationItem-DM-Fail,
id-RL-Set-Unsuccessful-InformationItem-DM-Fail-Ind.
id-RL-Successful-InformationItem-DM-Fail,
id-RL-Unsuccessful-InformationItem-DM-Fail,
id-RL-Unsuccessful-InformationItem-DM-Fail-Ind,
id-ReportCharacteristics,
id-Reporting-Object-RL-FailureInd,
id-Reporing-Object-RL-RestoreInd,
id-RNC-ID.
id-RxTimingDeviationForTA,
id-S-RNTI,
id-SAI,
id-Secondary-CPICH-Information,
id-Secondary-CPICH-Information-Change,
id-Secondary-Serving-Cell-List,
id-Dual-Band-Secondary-Serving-Cell-List,
id-SixtyfourOAM-DL-SupportIndicator,
id-SFN,
id-SFNReportingIndicator,
id-SNA-Information,
id-SRNC-ID,
id-STTD-SupportIndicator,
id-SuccessfulRL-InformationResponse-RL-AdditionFailureFDD.
id-SuccessfulRL-InformationResponse-RL-SetupFailureFDD,
id-TDD-maxNrDLPhysicalchannels,
id-TDD-Support-8PSK,
id-TDD-Support-PLCCH,
id-timeSlot-ISCP,
id-TimeSlot-RL-SetupRspTDD,
id-TnlOos,
id-TraceDepth,
id-TraceRecordingSessionReference,
id-TraceReference,
id-TransportBearerID,
id-TransportBearerRequestIndicator,
id-TransportLayerAddress,
id-UC-ID.
id-ContextInfoItem-Reset,
id-ContextGroupInfoItem-Reset,
```

```
id-Transmission-Gap-Pattern-Sequence-Information,
id-UE-AggregateMaximumBitRate.
id-UEIdentity.
id-UEMeasurementType,
id-UEMeasurementTimeslotInfoHCR.
id-UEMeasurementTimeslotInfoLCR,
id-UEMeasurementReportCharacteristics,
id-UEMeasurementParameterModAllow,
id-UEMeasurementValueInformation.
id-UE-State,
id-UE-with-enhanced-HS-SCCH-support-indicator,
id-UL-CCTrCH-AddInformation-RL-ReconfPrepTDD,
id-UL-CCTrCH-DeleteInformation-RL-ReconfPrepTDD,
id-UL-CCTrCH-ModifyInformation-RL-ReconfPrepTDD,
id-UL-CCTrCH-InformationDeleteItem-RL-ReconfRgstTDD,
id-UL-CCTrCH-InformationModifyItem-RL-ReconfRqstTDD,
id-UL-CCTrCH-InformationAddList-RL-ReconfPrepTDD,
id-UL-CCTrCH-InformationDeleteList-RL-ReconfPrepTDD,
id-UL-CCTrCH-InformationModifyList-RL-ReconfPrepTDD,
id-UL-CCTrCH-InformationDeleteList-RL-ReconfRqstTDD,
id-UL-CCTrCH-InformationModifyList-RL-ReconfRgstTDD,
id-UL-CCTrCH-InformationItem-RL-SetupRqstTDD,
id-UL-CCTrCH-InformationList-RL-SetupRqstTDD,
id-UL-CCTrCH-InformationListIE-PhyChReconfRgstTDD,
id-UL-CCTrCH-InformationListIE-RL-AdditionRspTDD,
id-UL-CCTrCH-InformationListIE-RL-ReconfReadyTDD,
id-UL-CCTrCH-InformationListIE-RL-SetupRspTDD,
id-UL-DPCH-Information-RL-ReconfPrepFDD,
id-UL-DPCH-Information-RL-ReconfRgstFDD,
id-UL-DPCH-Information-RL-SetupRgstFDD,
id-UL-DPDCHIndicatorEDCH,
id-UL-DPCH-InformationItem-PhyChReconfRqstTDD,
id-UL-DPCH-InformationItem-RL-AdditionRspTDD,
id-UL-DPCH-InformationItem-RL-SetupRspTDD,
id-UL-DPCH-InformationAddListIE-RL-ReconfReadyTDD,
id-UL-DPCH-InformationDeleteListIE-RL-ReconfReadyTDD,
id-UL-DPCH-InformationModifyListIE-RL-ReconfReadyTDD,
id-UL-Physical-Channel-Information-RL-SetupRgstTDD,
id-UL-SIRTarget,
id-URA-ID,
id-URA-Information,
id-UnsuccessfulRL-InformationResponse-RL-AdditionFailureFDD,
id-UnsuccessfulRL-InformationResponse-RL-AdditionFailureTDD,
id-UnsuccessfulRL-InformationResponse-RL-SetupFailureFDD,
id-UnsuccessfulRL-InformationResponse-RL-SetupFailureTDD,
id-USCHs-to-Add,
id-USCH-DeleteList-RL-ReconfPrepTDD.
id-USCH-InformationListIE-RL-AdditionRspTDD,
id-USCH-InformationListIEs-RL-SetupRspTDD,
id-USCH-Information,
id-USCH-ModifyList-RL-ReconfPrepTDD,
id-USCHToBeAddedOrModifiedList-RL-ReconfReadyTDD,
id-DL-Timeslot-ISCP-LCR-Information-RL-SetupRqstTDD,
id-RL-LCR-InformationResponse-RL-SetupRspTDD,
```

```
id-UL-CCTrCH-LCR-InformationListIE-RL-SetupRspTDD,
id-UL-DPCH-LCR-InformationItem-RL-SetupRspTDD.
id-DL-CCTrCH-LCR-InformationListIE-RL-SetupRspTDD.
id-DL-DPCH-LCR-InformationItem-RL-SetupRspTDD,
id-DSCH-LCR-InformationListIEs-RL-SetupRspTDD.
id-USCH-LCR-InformationListIEs-RL-SetupRspTDD,
id-DL-Timeslot-ISCP-LCR-Information-RL-AdditionRgstTDD,
id-RL-LCR-InformationResponse-RL-AdditionRspTDD,
id-UL-CCTrCH-LCR-InformationListIE-RL-AdditionRspTDD,
id-UL-DPCH-LCR-InformationItem-RL-AdditionRspTDD.
id-DL-CCTrCH-LCR-InformationListIE-RL-AdditionRspTDD,
id-DL-DPCH-LCR-InformationItem-RL-AdditionRspTDD,
id-DSCH-LCR-InformationListIEs-RL-AdditionRspTDD,
id-USCH-LCR-InformationListIEs-RL-AdditionRspTDD,
id-UL-DPCH-LCR-InformationAddListIE-RL-ReconfReadyTDD,
id-UL-Timeslot-LCR-InformationModifyList-RL-ReconfReadyTDD,
id-DL-DPCH-LCR-InformationAddListIE-RL-ReconfReadyTDD,
id-DL-Timeslot-LCR-InformationModifyList-RL-ReconfReadyTDD,
id-UL-Timeslot-LCR-InformationList-PhyChReconfRgstTDD,
id-DL-Timeslot-LCR-InformationList-PhyChReconfRgstTDD,
id-timeSlot-ISCP-LCR-List-DL-PC-Rgst-TDD,
id-TSTD-Support-Indicator-RL-SetupRgstTDD,
id-PrimaryCCPCH-RSCP-RL-ReconfPrepTDD,
id-DL-TimeSlot-ISCP-Info-RL-ReconfPrepTDD,
id-DL-Timeslot-ISCP-LCR-Information-RL-ReconfPrepTDD,
id-neighbouringTDDCellMeasurementInformationLCR,
id-UL-SIR-Target-CCTrCH-InformationItem-RL-SetupRspTDD,
id-UL-SIR-Target-CCTrCH-LCR-InformationItem-RL-SetupRspTDD,
id-TrafficClass,
id-UL-Synchronisation-Parameters-LCR,
id-TDD-DL-DPCH-TimeSlotFormatModifyItem-LCR-RL-ReconfReadyTDD,
id-TDD-UL-DPCH-TimeSlotFormatModifyItem-LCR-RL-ReconfReadyTDD,
id-MAChs-ResetIndicator,
id-UL-TimingAdvanceCtrl-LCR,
id-CCTrCH-Maximum-DL-Power-RL-SetupRspTDD,
id-CCTrCH-Minimum-DL-Power-RL-SetupRspTDD,
id-CCTrCH-Maximum-DL-Power-RL-AdditionRspTDD.
id-CCTrCH-Minimum-DL-Power-RL-AdditionRspTDD,
id-CCTrCH-Maximum-DL-Power-RL-ReconfReadyTDD,
id-CCTrCH-Minimum-DL-Power-RL-ReconfReadyTDD,
id-Maximum-DL-Power-TimeslotLCR-InformationModifyItem-RL-ReconfReadyTDD,
id-Minimum-DL-Power-TimeslotLCR-InformationModifyItem-RL-ReconfReadyTDD,
id-DL-CCTrCH-InformationList-RL-ReconfRspTDD,
id-DL-DPCH-InformationModifyItem-LCR-RL-ReconfRspTDD,
id-TDD-TPC-UplinkStepSize-LCR-RL-SetupRgstTDD,
id-UL-CCTrCH-InformationList-RL-AdditionRgstTDD,
id-UL-CCTrCH-InformationItem-RL-AdditionRgstTDD,
id-DL-CCTrCH-InformationList-RL-AdditionRgstTDD,
id-DL-CCTrCH-InformationItem-RL-AdditionRgstTDD,
id-TDD-TPC-UplinkStepSize-InformationAdd-LCR-RL-ReconfPrepTDD,
id-TDD-TPC-UplinkStepSize-InformationModify-LCR-RL-ReconfPrepTDD,
id-TDD-TPC-DownlinkStepSize-InformationAdd-RL-ReconfPrepTDD,
id-TDD-TPC-DownlinkStepSize-InformationModify-RL-ReconfPrepTDD,
id-PrimaryCCPCH-RSCP-Delta,
```

```
id-multiple-DedicatedMeasurementValueList-TDD-DM-Rsp,
id-multiple-DedicatedMeasurementValueList-LCR-TDD-DM-Rsp.
id-SynchronisationIndicator.
id-secondary-LCR-CCPCH-Info-TDD,
id-multiple-HSSICHMeasurementValueList-TDD-DM-Rsp,
id-CellCapabilityContainer-TDD768,
id-neighbouringTDDCellMeasurementInformation768,
id-RL-InformationResponse-RL-SetupRspTDD768,
id-UL-CCTrCH-InformationListIE-RL-SetupRspTDD768.
id-DL-CCTrCH-InformationListIE-RL-SetupRspTDD768,
id-UL-DPCH-InformationItem-RL-SetupRspTDD768,
id-DL-DPCH-InformationItem-RL-SetupRspTDD768,
id-TDD768-minimumSpreadingFactor-UL,
id-TDD768-minimumSpreadingFactor-DL,
id-TDD768-maxNrDLPhysicalchannels,
id-TDD768-maxNrDLPhysicalchannelsTS,
id-RL-InformationResponse-RL-AdditionRspTDD768,
id-UL-CCTrCH-InformationListIE-RL-AdditionRspTDD768,
id-DL-CCTrCH-InformationListIE-RL-AdditionRspTDD768,
id-UL-DPCH-InformationItem-RL-AdditionRspTDD768,
id-DL-DPCH-InformationItem-RL-AdditionRspTDD768,
id-UL-DPCH-InformationAddListIE-RL-ReconfReadyTDD768,
id-UL-Timeslot-InformationModifyList-RL-ReconfReadyTDD768,
id-DL-DPCH-InformationAddListIE-RL-ReconfReadvTDD768.
id-DL-Timeslot-InformationModifyList-RL-ReconfReadyTDD768,
id-secondary-CCPCH-Info-RL-ReconfReadyTDD768,
id-HSPDSCH-Timeslot-InformationList-PhyChReconfRgstTDD768,
id-UL-Timeslot-InformationList-PhyChReconfRgstTDD768,
id-DL-Timeslot-InformationList-PhyChReconfRgstTDD768,
id-multiple-DedicatedMeasurementValueList-TDD768-DM-Rsp,
id-UEMeasurementTimeslotInfo768,
id-DL-DPCH-InformationDeleteList768-RL-ReconfReadyTDD,
id-DPCH-ID768-DM-Rsp.
id-DPCH-ID768-DM-Rqst,
id-DPCH-ID768-DM-Rprt,
id-RxTimingDeviationForTAext,
id-RxTimingDeviationForTA768,
id-E-DCH-Information,
id-E-DCH-Information-Reconfig,
id-E-DCH-Serving-RL-ID,
id-E-DCH-Information-Response,
id-E-DCH-768-Information,
id-E-DCH-768-Information-Reconfig,
id-E-DCH-768-Information-Response,
id-E-DCH-LCR-Information,
id-E-DCH-LCR-Information-Reconfig,
id-E-DCH-LCR-Information-Response,
id-PowerControlGAP,
id-IdleIntervalInformation,
id-NeedforIdleInterval,
id-IdleIntervalConfigurationIndicator,
id-UARFCNforNt,
id-HS-SICH-ID-Extension,
id-HSSICH-Info-DM-Rgst-Extension,
```

```
id-UPPCHPositionLCR,
id-Common-EDCH-MAC-d-Flow-Specific-InformationLCR.
id-Enhanced-FACH-Information-ResponseLCR.
id-HSDSCH-PreconfigurationSetup,
id-HSDSCH-PreconfigurationInfo,
id-NoOfTargetCellHS-SCCH-Order,
id-EnhancedHSServingCC-Abort,
id-GANSS-Time-ID,
id-Additional-HS-Cell-Information-RL-Setup,
id-Additional-HS-Cell-Information-Response,
id-Additional-HS-Cell-Information-RL-Addition,
id-Additional-HS-Cell-Change-Information-Response,
id-Additional-HS-Cell-Information-RL-Reconf-Prep.
id-Additional-HS-Cell-Information-RL-Reconf-Reg,
id-Additional-HS-Cell-RL-Reconf-Response,
id-Additional-HS-Cell-Information-RL-Param-Upd,
id-MinimumReducedE-DPDCH-GainFactor,
id-ContinuousPacketConnectivity-DRX-InformationLCR,
id-ContinuousPacketConnectivity-DRX-Information-ResponseLCR,
id-CPC-InformationLCR.
id-E-DCH-Semi-PersistentScheduling-Information-LCR,
id-HS-DSCH-Semi-PersistentScheduling-Information-LCR,
id-HS-DSCH-Semi-PersistentScheduling-Information-ResponseLCR,
id-E-DCH-Semi-PersistentScheduling-Information-ResponseLCR,
id-ActivationInformation,
id-Additional-EDCH-Cell-Information-RL-Setup-Reg.
id-Additional-EDCH-Cell-Information-Response,
id-Additional-EDCH-Cell-Information-RL-Add-Reg,
id-Additional-EDCH-Cell-Information-Response-RLAdd,
id-Additional-EDCH-Cell-Information-RL-Reconf-Prep,
id-Additional-EDCH-Cell-Information-RL-Reconf-Reg,
id-Additional-EDCH-Cell-Information-RL-Param-Upd,
id-Additional-EDCH-Cell-Information-ResponseRLReconf,
id-DCH-MeasurementOccasion-Information,
id-DCH-MeasurementType-Indicator,
id-Non-Serving-RL-Preconfig-Info,
id-Non-Serving-RL-Preconfig-Setup,
id-Non-Serving-RL-Preconfig-Removal,
id-CellCapabilityContainerExtension-TDD-LCR,
id-Multi-Carrier-EDCH-Setup,
id-Multi-Carrier-EDCH-Reconfigure,
id-Multi-Carrier-EDCH-Response,
id-MU-MIMO-InformationLCR,
id-MU-MIMO-Indicator.
id-Usefulness-Of-Battery-Optimization,
id-MDT-Configuration,
id-Neighbouring-UMTS-CellInformation-Ext,
id-Extension-CommonMeasurementObjectType-CM-Rprt,
id-Extension-CommonMeasurementObjectType-CM-Rgst,
id-Extension-CommonMeasurementObjectType-CM-Rsp,
id-Extension-FailureIndicationMeasurementList,
id-Extension-FailureMeasurementList,
id-Extension-TerminationMeasurementList,
id-GsmCellList-CM-Rprt,
```

```
id-GsmCellList-CM-Rqst,
    id-GsmCellList-CM-Rsp.
    id-GSM-Cell-InfEx-Rast.
    id-SpeechVersion,
    id-SourceID.
    id-TargetID,
    id-ClassmarkInformation2.
    id-ClassmarkInformation3,
    id-GSM-Cell-CM-Rast,
    id-LoadValue,
    id-EventH,
    id-Cell-Capacity-Class-Value,
    id-Control-Type-InformationTransferControlReg
    id-ANR-Cell-InfEx-Rost,
    id-ANR-Cell-InfEx-Rsp,
    id-Trace-Collection-Entity-IP-Address,
    id-CPC-RecoveryReport
FROM RNSAP-Constants;
-- RADIO LINK SETUP REQUEST FDD
RadioLinkSetupRequestFDD ::= SEOUENCE {
    protocolIEs
                                                               {{RadioLinkSetupRequestFDD-IEs}},
                                   ProtocolIE-Container
   protocolExtensions
                                    ProtocolExtensionContainer {{RadioLinkSetupRequestFDD-Extensions}}
                                                                                                                         OPTIONAL,
    . . .
RadioLinkSetupRequestFDD-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-SRNC-ID
                                   CRITICALITY reject TYPE RNC-ID
                                                                                        PRESENCE mandatory}
     ID id-S-RNTI
                                   CRITICALITY reject TYPE S-RNTI
                                                                                        PRESENCE mandatory
     ID id-D-RNTI
                                    CRITICALITY reject TYPE D-RNTI
                                                                                    PRESENCE optional
     ID id-AllowedQueuingTime
                                        CRITICALITY reject TYPE AllowedQueuingTime
                                                                                                PRESENCE optional
     ID id-UL-DPCH-Information-RL-SetupRqstFDD CRITICALITY reject TYPE UL-DPCH-Information-RL-SetupRqstFDD
                                                                                                                        PRESENCE mandatory
     ID id-DL-DPCH-Information-RL-SetupRgstFDD CRITICALITY reject TYPE DL-DPCH-Information-RL-SetupRgstFDD
                                                                                                                        PRESENCE optional
     ID id-DCH-FDD-Information
                                   CRITICALITY reject TYPE DCH-FDD-Information
                                                                                        PRESENCE mandatory
     ID id-RL-Information-RL-SetupRqstFDD
                                               CRITICALITY notify TYPE RL-InformationList-RL-SetupRqstFDD
                                                                                                                        PRESENCE mandatory
     ID id-Transmission-Gap-Pattern-Sequence-Information
                                                                CRITICALITY reject TYPE Transmission-Gap-Pattern-Sequence-Information PRESENCE
    optional }
    { ID id-Active-Pattern-Sequence-Information CRITICALITY reject TYPE Active-Pattern-Sequence-Information
                                                                                                                  PRESENCE optional },
UL-DPCH-Information-RL-SetupRgstFDD ::= SEOUENCE
    ul-ScramblingCode
                                   UL-ScramblingCode,
    minUL-ChannelisationCodeLength
                                           MinUL-ChannelisationCodeLength,
   maxNrOfUL-DPCHs
                                   MaxNrOfUL-DPCHs
                                                           OPTIONAL
    -- This IE shall be present if minUL-ChannelisationCodeLength equals to 4 -- ,
    ul-PunctureLimit
                                   PunctureLimit,
```

```
ul-TFCS
                                  TFCS,
   ul-DPCCH-SlotFormat
                                  UL-DPCCH-SlotFormat,
   ul-SIRTarget
                                  UL-SIR
                                                 OPTIONAL.
   diversityMode
                                  DiversityMode,
   not-Used-sSDT-CellIdLength
                                  NULL
                                                 OPTIONAL.
   not-Used-s-FieldLength
                                  NULL
                                                 OPTIONAL,
   iE-Extensions
                                  ProtocolExtensionContainer { {UL-DPCH-Information-RL-SetupRgstFDD-ExtIEs} } OPTIONAL,
UL-DPCH-Information-RL-SetupRqstFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-DPC-Mode
                                  CRITICALITY reject
                                                         EXTENSION DPC-Mode
                                                                                       PRESENCE optional }
    ID id-UL-DPDCHIndicatorEDCH CRITICALITY reject
                                                         EXTENSION UL-DPDCHIndicatorEDCH PRESENCE optional },
    . . .
DL-DPCH-Information-RL-SetupRgstFDD ::= SEOUENCE {
                                  TFCS,
   dl-DPCH-SlotFormat
                                  DL-DPCH-SlotFormat,
   nrOfDLchannelisationcodes
                                  NrOfDLchannelisationcodes,
    tFCI-SignallingMode
                                  TFCI-SignallingMode,
    tFCI-Presence
                                  TFCI-Presence
                                                         OPTIONAL
    -- This IE shall be present if DL DPCH Slot Format IE is equal to any of the values from 12 to 16 --,
   multiplexingPosition
                                      MultiplexingPosition,
   powerOffsetInformation
                                      PowerOffsetInformation-RL-SetupRqstFDD,
    fdd-dl-TPC-DownlinkStepSize
                                  FDD-TPC-DownlinkStepSize,
   limitedPowerIncrease
                                  LimitedPowerIncrease,
    innerLoopDLPCStatus
                                  InnerLoopDLPCStatus,
                                  ProtocolExtensionContainer { {DL-DPCH-Information-RL-SetupRgstFDD-ExtIEs} } OPTIONAL,
   iE-Extensions
DL-DPCH-Information-RL-SetupRqstFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
PowerOffsetInformation-RL-SetupRqstFDD ::= SEQUENCE
       pol-ForTFCI-Bits
                                      PowerOffset,
       po2-ForTPC-Bits
                                      PowerOffset,
       po3-ForPilotBits
                                      PowerOffset,
                                      ProtocolExtensionContainer { { PowerOffsetInformation-RL-SetupRqstFDD-ExtIEs} } OPTIONAL,
       iE-Extensions
PowerOffsetInformation-RL-SetupRgstFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RL-InformationList-RL-SetupRqstFDD
                                          ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-InformationItemIEs-RL-
SetupRqstFDD } }
RL-InformationItemIEs-RL-SetupRqstFDD RNSAP-PROTOCOL-IES ::= {
    PRESENCE mandatory
```

```
RL-InformationItem-RL-SetupRgstFDD ::= SEQUENCE {
    rL-ID
                                    RL-ID.
    C-TD
                                    C-ID.
    firstRIS-indicator
                                    FirstRLS-Indicator.
    frameOffset
                                    FrameOffset.
    chipOffset
                                    ChipOffset,
                                    PropagationDelay
    propagationDelay
                                                            OPTIONAL,
    diversityControlField
                                    DiversityControlField
                                                                OPTIONAL
    -- This IE shall be present if the RL is not the first one in the RL-InformationList-RL-SetupRgstFDD --.
                                    DL-Power
                                                        OPTIONAL,
    dl-InitialTX-Power
                                    PrimaryCPICH-EcNo
    primaryCPICH-EcNo
                                                                OPTIONAL,
    not-Used-sSDT-CellID
                                    NULL
                                                    OPTIONAL,
    transmitDiversitvIndicator
                                    TransmitDiversitvIndicator
                                                                    OPTIONAL,
    -- This IE shall be present unless Diversity Mode IE in UL DPCH Information group is "none"
    iE-Extensions
                                    ProtocolExtensionContainer { {RL-InformationItem-RL-SetupRqstFDD-ExtIEs} } OPTIONAL,
    . . .
RL-InformationItem-RL-SetupRqstFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
      ID id-Enhanced-PrimaryCPICH-EcNo
                                                CRITICALITY ignore
                                                                         EXTENSION Enhanced-PrimaryCPICH-EcNo
                                                                                                                    PRESENCE optional }
      ID id-RL-Specific-DCH-Info
                                                CRITICALITY ignore
                                                                         EXTENSION RL-Specific-DCH-Info
                                                                                                                    PRESENCE optional
      ID id-DelayedActivation
                                                CRITICALITY reject
                                                                         EXTENSION DelayedActivation
                                                                                                                    PRESENCE optional
      ID id-CellPortionID
                                                                         EXTENSION CellPortionID
                                                                                                                    PRESENCE optional
                                                CRITICALITY ignore
                                                                                                                    PRESENCE optional
      ID id-RL-Specific-EDCH-Information
                                                CRITICALITY reject
                                                                         EXTENSION RL-Specific-EDCH-Information
      ID id-EDCH-RL-Indication
                                                CRITICALITY reject
                                                                          EXTENSION EDCH-RL-Indication
                                                                                                                    PRESENCE optional
      ID id-ExtendedPropagationDelay
                                                CRITICALITY ignore
                                                                         EXTENSION ExtendedPropagationDelay
                                                                                                                    PRESENCE optional
      ID id-SynchronisationIndicator
                                                CRITICALITY reject
                                                                         EXTENSION SynchronisationIndicator
                                                                                                                    PRESENCE optional
      ID id-HSDSCH-PreconfigurationSetup
                                                                         EXTENSION HSDSCH-PreconfigurationSetup
                                                                                                                    PRESENCE optional
                                                CRITICALITY ignore
    { ID id-Non-Serving-RL-Preconfig-Setup
                                                                         EXTENSION Non-Serving-RL-Preconfig-Setup PRESENCE optional },
                                                CRITICALITY ignore
    . . .
RadioLinkSetupRequestFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    ID id-Permanent-NAS-UE-Identity
                                                       CRITICALITY ignore
                                                                            EXTENSION Permanent-NAS-UE-Identity
                                                                                                                                 PRESENCE optional
} |
                                                       CRITICALITY ignore EXTENSION DL-PowerBalancing-Information
      ID id-DL-PowerBalancing-Information
                                                                                                                                 PRESENCE optional |
      ID id-HSDSCH-FDD-Information
                                                       CRITICALITY reject
                                                                            EXTENSION HSDSCH-FDD-Information
                                                                                                                                 PRESENCE optional
    { ID id-HSPDSCH-RL-ID
                                                       CRITICALITY reject
                                                                            EXTENSION RL-ID
                                                                                                                                 PRESENCE
conditional }
    -- This IE shall be present if HS-DSCH Information IE is present.
    { ID id-MBMS-Bearer-Service-List
                                                       CRITICALITY notify
                                                                            EXTENSION MBMS-Bearer-Service-List
                                                                                                                                 PRESENCE
optional }
    { ID id-EDPCH-Information
                                                       CRITICALITY reject
                                                                            EXTENSION EDPCH-Information-FDD
                                                                                                                                 PRESENCE
optional }
    { ID id-EDCH-FDD-Information
                                                       CRITICALITY reject
                                                                            EXTENSION EDCH-FDD-Information
                                                                                                                                 PRESENCE
conditional }
    -- This IE is present if E-DPCH Information IE is present.
    { ID id-Serving-EDCHRL-Id
                                                       CRITICALITY reject EXTENSION EDCH-Serving-RL
                                                                                                                                 PRESENCE
optional }|
    -- This IE is present if E-DCHInformation IE is present.
    { ID id-F-DPCH-Information-RL-SetupRgstFDD
                                                       CRITICALITY reject EXTENSION F-DPCH-Information-RL-SetupRqstFDD
                                                                                                                                 PRESENCE optional
} |
```

```
{ ID id-Initial-DL-DPCH-TimingAdjustment-Allowed
                                                       CRITICALITY ignore EXTENSION Initial-DL-DPCH-TimingAdjustment-Allowed PRESENCE optional
} |
     ID id-DCH-Indicator-For-E-DCH-HSDPA-Operation
                                                       CRITICALITY reject
                                                                            EXTENSION DCH-Indicator-For-E-DCH-HSDPA-Operation
                                                                                                                                PRESENCE optional
     ID id-Serving-cell-change-CFN
                                                       CRITICALITY reject
                                                                          EXTENSION CFN
                                                                                                                                PRESENCE optional
} |
    { ID id-Continuous-Packet-Connectivity-DTX-DRX-Information
                                                                    CRITICALITY reject EXTENSION Continuous-Packet-Connectivity-DTX-DRX-
Information
    PRESENCE optional } |
    { ID id-Continuous-Packet-Connectivity-HS-SCCH-Less-Information CRITICALITY reject EXTENSION Continuous-Packet-Connectivity-HS-SCCH-Less-
Information
                                                                                                                                PRESENCE optional
} |
     ID id-Extended-SRNC-ID
                                                                                                                                PRESENCE optional
                                                       CRITICALITY reject EXTENSION Extended-RNC-ID
    { ID id-Additional-HS-Cell-Information-RL-Setup
                                                                            EXTENSION Additional-HS-Cell-Information-RL-Setup-List
                                                                                                                                       PRESENCE
                                                       CRITICALITY reject
optional }
    { ID id-UE-AggregateMaximumBitRate
                                                       CRITICALITY ignore
                                                                           EXTENSION UE-AggregateMaximumBitRate
                                                                                                                                PRESENCE optional
     ID id-Additional-EDCH-Cell-Information-RL-Setup-Req
                                                                     CRITICALITY reject EXTENSION Additional-EDCH-Setup-Info
                                                                                                                                PRESENCE optional
} |
    { ID id-Usefulness-Of-Battery-Optimization
                                                       CRITICALITY ignore EXTENSION Usefulness-Of-Battery-Optimization
                                                                                                                                PRESENCE optional
},
Additional-HS-Cell-Information-RL-Setup-List
                                              ::= SEQUENCE (SIZE (1..maxNrOfHSDSCH-1)) OF Additional-HS-Cell-Information-RL-Setup-ItemIEs
Additional-HS-Cell-Information-RL-Setup-ItemIEs ::=SEOUENCE{
    hSPDSCH-RL-ID
                                                    RL-ID,
                                                    C-ID,
    c-ID
    hS-DSCH-FDD-Secondary-Serving-Information
                                                    HS-DSCH-FDD-Secondary-Serving-Information,
                                    ProtocolExtensionContainer { { Additional-HS-Cell-Information-RL-Setup-ItemIEs-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
Additional-HS-Cell-Information-RL-Setup-ItemIEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
F-DPCH-Information-RL-SetupRqstFDD ::= SEQUENCE {
    powerOffsetInformation
                                    PowerOffsetInformation-F-DPCH-RL-SetupRqstFDD,
    fdd-dl-TPC-DownlinkStepSize
                                    FDD-TPC-DownlinkStepSize,
    limitedPowerIncrease
                                    LimitedPowerIncrease,
    innerLoopDLPCStatus
                                    InnerLoopDLPCStatus,
    iE-Extensions
                                    ProtocolExtensionContainer { { F-DPCH-Information-RL-SetupRgstFDD-ExtIEs} }
    OPTIONAL,
    . . .
F-DPCH-Information-RL-SetupRgstFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-F-DPCH-SlotFormatSupportRequest
                                                CRITICALITY reject
                                                                            EXTENSION F-DPCH-SlotFormatSupportRequest
                                                                                                                                PRESENCE optional
```

```
PRESENCE optional },
    { ID id-F-DPCH-SlotFormat
                                          CRITICALITY ignore EXTENSION F-DPCH-SlotFormat
PowerOffsetInformation-F-DPCH-RL-SetupRqstFDD ::= SEQUENCE {
   po2-ForTPC-Bits
                                  PowerOffset,
    -- This IE shall be ignored by DRNS
                                  ProtocolExtensionContainer { { PowerOffsetInformation-F-DPCH-RL-SetupRqstFDD-ExtIEs} }
   iE-Extensions
                                                                                                                                  OPTIONAL.
PowerOffsetInformation-F-DPCH-RL-SetupRqstFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
        **************
-- RADIO LINK SETUP REQUEST TDD
  ****************
RadioLinkSetupRequestTDD ::= SEQUENCE {
                                                             {{RadioLinkSetupRequestTDD-IEs}},
   protocolIEs
                                  ProtocolIE-Container
                                  ProtocolExtensionContainer {{RadioLinkSetupRequestTDD-Extensions}}
   protocolExtensions
                                                                                                                     OPTIONAL.
RadioLinkSetupRequestTDD-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-SRNC-ID
                                                                                                           PRESENCE mandatory
                                                          CRITICALITY reject TYPE RNC-ID
     ID id-S-RNTI
                                                                                                           PRESENCE mandatory }
                                                          CRITICALITY reject TYPE S-RNTI
                                                                                                           PRESENCE optional }
     ID id-D-RNTI
                                                          CRITICALITY reject TYPE D-RNTI
     ID id-UL-Physical-Channel-Information-RL-SetupRqstTDD CRITICALITY reject TYPE UL-Physical-Channel-Information-RL-SetupRqstTDD
                                                                                                                                               PRESENCE mand
     ID id-DL-Physical-Channel-Information-RL-SetupRqstTDD CRITICALITY reject TYPE DL-Physical-Channel-Information-RL-SetupRqstTDD
                                                                                                                                               PRESENCE mand
     ID id-AllowedQueuingTime
                                                          CRITICALITY reject TYPE AllowedQueuingTime
                                                                                                           PRESENCE optional } |
     ID id-UL-CCTrCH-InformationList-RL-SetupRgstTDD
                                                          CRITICALITY notify TYPE UL-CCTrCH-InformationList-RL-SetupRgstTDD
                                                                                                                            PRESENCE optional
}
    ID id-DL-CCTrCH-InformationList-RL-SetupRqstTDD
                                                          CRITICALITY notify TYPE DL-CCTrCH-InformationList-RL-SetupRqstTDD
                                                                                                                            PRESENCE optional
     ID id-DCH-TDD-Information
                                                          CRITICALITY reject TYPE DCH-TDD-Information
                                                                                                           PRESENCE optional
     ID id-DSCH-TDD-Information
                                                          CRITICALITY reject TYPE DSCH-TDD-Information
                                                                                                           PRESENCE optional
     ID id-USCH-Information
                                                          CRITICALITY reject TYPE USCH-Information
                                                                                                           PRESENCE optional
     ID id-RL-Information-RL-SetupRgstTDD
                                                         CRITICALITY reject TYPE RL-Information-RL-SetupRqstTDD
                                                                                                                             PRESENCE mandatory
UL-Physical-Channel-Information-RL-SetupRgstTDD ::= SEOUENCE {
   maxNrTimeslots-UL
                                  MaxNrTimeslots,
   minimumSpreadingFactor-UL
                                  MinimumSpreadingFactor,
   maxNrULPhysicalchannels
                                  MaxNrULPhysicalchannels,
    iE-Extensions
                                  ProtocolExtensionContainer { {UL-Physical-Channel-InformationItem-RL-SetupRqstTDD-ExtIEs} } OPTIONAL,
    . . .
```

```
UL-Physical-Channel-InformationItem-RL-SetupRqstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-TDD-Support-8PSK
                                  CRITICALITY ignore
                                                         EXTENSION Support-8PSK
                                                                                    PRESENCE optional
                                                                                                            } |
    -- Applicable to 1.28Mcps TDD only
     ID id-TDD768-minimumSpreadingFactor-UL
                                                  CRITICALITY ignore
                                                                             EXTENSION MinimumSpreadingFactor768
                                                                                                                          PRESENCE optional
    },
    . . .
DL-Physical-Channel-Information-RL-SetupRqstTDD ::= SEQUENCE {
                                  MaxNrTimeslots,
    maxNrTimeslots-DL
   minimumSpreadingFactor-DL
                                  MinimumSpreadingFactor,
                                  MaxNrDLPhysicalchannels,
    maxNrDLPhysicalchannels
                                  ProtocolExtensionContainer { {DL-Physical-Channel-InformationItem-RL-SetupRqstTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
    . . .
DL-Physical-Channel-InformationItem-RL-SetupRgstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-TDD-maxNrDLPhysicalchannels
                                                  CRITICALITY ignore
                                                                             EXTENSION MaxNrDLPhysicalchannelsTS
                                                                                                                                  PRESENCE
optional
    { ID id-TDD-Support-8PSK
                                                  CRITICALITY ignore
                                                                             EXTENSION Support-8PSK
    PRESENCE optional }
    -- Applicable to 1.28Mcps TDD only
    { ID id-TDD-Support-PLCCH
                                                  CRITICALITY ignore
                                                                             EXTENSION Support-PLCCH
    PRESENCE optional }
    { ID id-TDD768-minimumSpreadingFactor-DL
                                                  CRITICALITY ignore
                                                                             EXTENSION MinimumSpreadingFactor768
                                                                                                                                  PRESENCE
optional
     ID id-TDD768-maxNrDLPhysicalchannels
                                                                             EXTENSION MaxNrDLPhysicalchannels768
                                                                                                                          PRESENCE optional
                                                  CRITICALITY ignore
     ID id-TDD768-maxNrDLPhysicalchannelsTS
                                                  CRITICALITY ignore
                                                                             EXTENSION MaxNrDLPhysicalchannelsTS768
                                                                                                                          PRESENCE optional
UL-CCTrCH-InformationList-RL-SetupRqstTDD
                                                  ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHs)) OF ProtocolIE-Single-Container { {UL-CCTrCH-
InformationItemIEs-RL-SetupRgstTDD} }
UL-CCTrCH-InformationItemIEs-RL-SetupRqstTDD RNSAP-PROTOCOL-IES ::= {
     PRESENCE mandatory
UL-CCTrCH-InformationItem-RL-SetupRqstTDD ::= SEQUENCE {
   cCTrCH-ID
                                  CCTrCH-ID,
    ul-TFCS
                                  TFCS,
    tFCI-Coding
                                  TFCI-Coding,
   ul-PunctureLimit
                                  PunctureLimit,
   iE-Extensions
                                  ProtocolExtensionContainer { {UL-CCTrCH-InformationItem-RL-SetupRqstTDD-ExtIEs} } OPTIONAL,
UL-CCTrCH-InformationItem-RL-SetupRqstTDD-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-TDD-TPC-UplinkStepSize-LCR-RL-SetupRqstTDD
                                                         CRITICALITY reject
                                                                                 EXTENSION
                                                                                           TDD-TPC-UplinkStepSize-LCR
                                                                                                                                  PRESENCE
optional
    -- Mandatory for 1.28Mcps TDD, not applicable to 3.84Mcps TDD or 7.68Mcps TDD
```

```
DL-CCTrCH-InformationList-RL-SetupRgstTDD
                                              ::= SEOUENCE (SIZE (1..maxNrOfCCTrCHs)) OF ProtocolIE-Single-Container { {DL-CCTrCH-
InformationItemIEs-RL-SetupRgstTDD} }
DL-CCTrCH-InformationItemIEs-RL-SetupRqstTDD RNSAP-PROTOCOL-IES ::= {
     PRESENCE mandatory
DL-CCTrCH-InformationItem-RL-SetupRqstTDD ::= SEQUENCE {
   cCTrCH-ID
                               CCTrCH-ID,
   dl-TFCS
                               TFCS,
   tFCI-Coding
                               TFCI-Coding,
   dl-PunctureLimit
                               PunctureLimit,
                               TDD-TPC-DownlinkStepSize,
   tdd-TPC-DownlinkStepSize
   cCTrCH-TPCList
                               CCTrCH-TPCList-RL-SetupRgstTDD OPTIONAL,
   iE-Extensions
                                ProtocolExtensionContainer { {DL-CCTrCH-InformationItem-RL-SetupRqstTDD-ExtIEs} } OPTIONAL,
DL-CCTrCH-InformationItem-RL-SetupRqstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   . . .
CCTrCH-TPCList-RL-SetupRqstTDD ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHs)) OF CCTrCH-TPCItem-RL-SetupRqstTDD
CCTrCH-TPCItem-RL-SetupRgstTDD ::= SEQUENCE {
   cCTrCH-ID
                                   CCTrCH-ID,
                                   ProtocolExtensionContainer { { CCTrCH-TPCItem-RL-SetupRqstTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
CCTrCH-TPCItem-RL-SetupRgstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RL-Information-RL-SetupRgstTDD ::= SEQUENCE
   rL-ID
                               RL-ID,
   c-ID
                               C-ID,
   frameOffset
                               FrameOffset,
   specialBurstScheduling
                               SpecialBurstScheduling,
   primaryCCPCH-RSCP
                               PrimaryCCPCH-RSCP
                                                     OPTIONAL,
   dL-TimeSlot-ISCP
                               DL-TimeSlot-ISCP-Info OPTIONAL,
   --for 3.84Mcps TDD and 7.68Mcps TDD only
   iE-Extensions
                               ProtocolExtensionContainer { {RL-Information-RL-SetupRqstTDD-ExtIEs} } OPTIONAL,
RL-Information-RL-SetupRqstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   EXTENSION
                                                                                             DL-TimeSlot-ISCP-LCR-Information
   PRESENCE optional }
```

```
TSTD-Support-Indicator
    { ID id-TSTD-Support-Indicator-RL-SetupRqstTDD
                                                               CRITICALITY ignore
                                                                                        EXTENSION
    PRESENCE optional }
    -- for 1.28Mcps TDD only
     ID id-RL-Specific-DCH-Info CRITICALITY ignore
                                                           EXTENSION RL-Specific-DCH-Info
                                                                                               PRESENCE
                                                                                                                optional
                                                                                                                               } |
     ID id-DelayedActivation CRITICALITY reject EXTENSION DelayedActivation PRESENCE optional }
     ID id-UL-Synchronisation-Parameters-LCR
                                                       CRITICALITY reject
                                                                                EXTENSION UL-Synchronisation-Parameters-LCR
                                                                                                                                       PRESENCE
    optional } -- Mandatory for 1.28Mcps TDD, Not Applicable to 3.84Mcps TDD or 7.68Mcps TDD
     ID id-PrimaryCCPCH-RSCP-Delta
                                       CRITICALITY ignore
                                                               EXTENSION PrimaryCCPCH-RSCP-Delta
                                                                                                                PRESENCE
                                                                                                                               optional
    { ID id-IdleIntervalConfigurationIndicator
                                                                        CRITICALITY ignore EXTENSION
                                                                                                        NULL
                                                                                                                                       PRESENCE
optional }
    { ID id-CellPortionLCRID
                               CRITICALITY ignore EXTENSION CellPortionLCRID PRESENCE optional },
    . . .
RadioLinkSetupRequestTDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-Permanent-NAS-UE-Identity
                                                                CRITICALITY ignore
                                                                                     EXTENSION Permanent-NAS-UE-Identity
                                                                                                                               PRESENCE optional }
                                                                                                                               PRESENCE optional
     ID id-HSDSCH-TDD-Information
                                                                CRITICALITY reject
                                                                                     EXTENSION HSDSCH-TDD-Information
     ID id-HSPDSCH-RL-ID
                                                                CRITICALITY reject
                                                                                                                               PRESENCE
                                                                                     EXTENSION RL-ID
conditional } |
    -- This IE shall be present if HS-DSCH Information IE is present.
     ID id-PDSCH-RL-ID
                                                                CRITICALITY ignore
                                                                                     EXTENSION RL-ID
                                                                                                                               PRESENCE optional }
     ID id-MBMS-Bearer-Service-List
                                                                                                                               PRESENCE optional
                                                               CRITICALITY notify
                                                                                     EXTENSION MBMS-Bearer-Service-List
                                                                                                                               PRESENCE optional }
     ID id-E-DCH-Information
                                                                CRITICALITY reject
                                                                                     EXTENSION E-DCH-Information
                                                                                                                               PRESENCE optional }
     ID id-E-DCH-Serving-RL-ID
                                                                CRITICALITY reject
                                                                                     EXTENSION RL-ID
                                                                                                                               PRESENCE optional
     ID id-E-DCH-768-Information
                                                               CRITICALITY reject
                                                                                     EXTENSION E-DCH-768-Information
     ID id-E-DCH-LCR-Information
                                                                                     EXTENSION E-DCH-LCR-Information
                                                                                                                               PRESENCE optional }
                                                                CRITICALITY reject
     ID id-Extended-SRNC-ID
                                                                                     EXTENSION Extended-RNC-ID
                                                                                                                               PRESENCE optional }
                                                                CRITICALITY reject
     ID id-ContinuousPacketConnectivity-DRX-InformationLCR
                                                                CRITICALITY reject
                                                                                     EXTENSION ContinuousPacketConnectivity-DRX-InformationLCR
    PRESENCE optional } |
    { ID id-HS-DSCH-Semi-PersistentScheduling-Information-LCR
                                                                                     EXTENSION HS-DSCH-Semi-PersistentScheduling-Information-LCR
                                                               CRITICALITY reject
    PRESENCE optional } |
    { ID id-E-DCH-Semi-PersistentScheduling-Information-LCR
                                                                CRITICALITY reject EXTENSION E-DCH-Semi-PersistentScheduling-Information-LCR
    PRESENCE optional } |
                                                                                                                               PRESENCE optional }
    { ID id-RNTI-Allocation-Indicator
                                                                CRITICALITY ignore EXTENSION RNTI-Allocation-Indicator
     ID id-DCH-MeasurementType-Indicator
                                                                CRITICALITY reject EXTENSION DCH-MeasurementType-Indicator
                                                                                                                               PRESENCE optional}
                                                                                                                               PRESENCE optional)
     ID id-Multi-Carrier-EDCH-Setup
                                                                CRITICALITY reject EXTENSION Multi-Carrier-EDCH-Info
    { ID id-MU-MIMO-Indicator
                                                                CRITICALITY reject EXTENSION MU-MIMO-Indicator
                                                                                                                               PRESENCE optional },
-- RADIO LINK SETUP RESPONSE FDD
RadioLinkSetupResponseFDD ::= SEOUENCE {
    protocolIEs
                                    ProtocolIE-Container
                                                               {{RadioLinkSetupResponseFDD-IEs}},
    protocolExtensions
                                    ProtocolExtensionContainer {{RadioLinkSetupResponseFDD-Extensions}}
                                                                                                                          OPTIONAL,
RadioLinkSetupResponseFDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-D-RNTI
                                                                                                                             PRESENCE optional }
                                                        CRITICALITY ignore
                                                                            TYPE D-RNTI
```

```
ID id-CN-PS-DomainIdentifier
                                                         CRITICALITY ignore
                                                                              TYPE CN-PS-DomainIdentifier
                                                                                                                               PRESENCE optional } |
      ID id-CN-CS-DomainIdentifier
                                                         CRITICALITY ignore
                                                                              TYPE CN-CS-DomainIdentifier
                                                                                                                               PRESENCE optional }
                                                                                                                               PRESENCE mandatory } |
      ID id-RL-InformationResponseList-RL-SetupRspFDD
                                                        CRITICALITY ignore
                                                                              TYPE RL-InformationResponseList-RL-SetupRspFDD
      ID id-UL-SIRTarget
                                                         CRITICALITY ignore
                                                                              TYPE UL-SIR
                                                                                                                               PRESENCE optional }
     ID id-CriticalityDiagnostics
                                                         CRITICALITY ignore
                                                                              TYPE CriticalityDiagnostics
                                                                                                                               PRESENCE optional },
RL-InformationResponseList-RL-SetupRspFDD
                                                 ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-
InformationResponseItemIEs-RL-SetupRspFDD} }
RL-InformationResponseItemIEs-RL-SetupRspFDD RNSAP-PROTOCOL-IES ::= {
      ID id-RL-InformationResponseItem-RL-SetupRspFDD CRITICALITY ignore TYPE RL-InformationResponseItem-RL-SetupRspFDD
                                                                                                                                 PRESENCE mandatory
RL-InformationResponseItem-RL-SetupRspFDD ::= SEQUENCE {
    rL-ID
                                    RL-ID,
    rL-Set-ID
                                    RL-Set-ID,
    uRA-Information
                                    URA-Information
                                                         OPTIONAL,
    SAT
                                    SAT.
    qA-Cell
                                    GA-Cell
                                                OPTIONAL,
    gA-AccessPointPosition
                                    GA-AccessPointPosition
                                                                 OPTIONAL,
    received-total-wide-band-power
                                    Received-total-wide-band-power,
    not-Used-secondary-CCPCH-Info
                                            NULL
                                                         OPTIONAL,
    dl-CodeInformation
                                    FDD-DL-CodeInformation.
    diversityIndication
                                    DiversityIndication-RL-SetupRspFDD,
    sSDT-SupportIndicator
                                    SSDT-SupportIndicator,
    maxUL-SIR
                                    UL-SIR,
    minUL-SIR
                                    UL-SIR,
    closedlooptimingadjustmentmode
                                    Closedlooptimingadjustmentmode
                                                                             OPTIONAL,
    maximumAllowedULTxPower
                                    MaximumAllowedULTxPower,
    maximumDLTxPower
                                    DL-Power,
    minimumDLTxPower
                                    DL-Power,
    primaryScramblingCode
                                    PrimaryScramblingCode
                                                                             OPTIONAL,
    uL-UARFCN
                                    UARFCN
                                                                             OPTIONAL,
    dL-UARFCN
                                    UARFCN
                                                                             OPTIONAL,
    primaryCPICH-Power
                                    PrimaryCPICH-Power,
    not-Used-dSCHInformationResponse
                                        NULL
                                                                             OPTIONAL,
    neighbouring-UMTS-CellInformation
                                        Neighbouring-UMTS-CellInformation
                                                                             OPTIONAL,
                                        Neighbouring-GSM-CellInformation
    neighbouring-GSM-CellInformation
                                                                             OPTIONAL,
    pC-Preamble
                                    PC-Preamble,
    sRB-Delay
                                    SRB-Delay,
    iE-Extensions
                                    ProtocolExtensionContainer { {RL-InformationResponseItem-RL-SetupRspFDD-ExtIEs} } OPTIONAL,
    . . .
RL-InformationResponseItem-RL-SetupRspFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-GA-CellAdditionalShapes
                                                         CRITICALITY ignore EXTENSION GA-CellAdditionalShapes
            PRESENCE optional }
    { ID id-DL-PowerBalancing-ActivationIndicator
                                                         CRITICALITY ignore EXTENSION DL-PowerBalancing-ActivationIndicator
    PRESENCE optional } |
    { ID id-HCS-Prio
                                                         CRITICALITY ignore EXTENSION HCS-Prio
                    PRESENCE optional }|
```

```
PRESENCE
optional }|
    { ID id-Secondary-CPICH-Information
                                                     CRITICALITY ignore EXTENSION Secondary-CPICH-Information
       PRESENCE optional }
    { ID id-Active-MBMS-Bearer-ServiceFDD-PFL
                                                     CRITICALITY ignore EXTENSION Active-MBMS-Bearer-Service-ListFDD-PFL
    PRESENCE optional }
    { ID id-EDCH-RLSet-Id
                                                     CRITICALITY ignore EXTENSION RL-Set-ID
                  PRESENCE optional }
    { ID id-EDCH-FDD-DL-ControlChannelInformation
                                                     CRITICALITY ignore EXTENSION EDCH-FDD-DL-ControlChannelInformation
    PRESENCE optional }
    { ID id-Initial-DL-DPCH-TimingAdjustment
                                                     CRITICALITY ignore EXTENSION DL-DPCH-TimingAdjustment
    PRESENCE optional } |
    { ID id-F-DPCH-SlotFormat
                                                     CRITICALITY ignore EXTENSION F-DPCH-SlotFormat
    PRESENCE optional }
    { ID id-FrameOffset
                                                     CRITICALITY ignore EXTENSION FrameOffset
    PRESENCE optional } |
    { ID id-ChipOffset
                                                     CRITICALITY ignore EXTENSION ChipOffset
                  PRESENCE optional }
    { ID id-Neighbouring-E-UTRA-CellInformation
                                                     CRITICALITY ignore EXTENSION Neighbouring-E-UTRA-CellInformation
    PRESENCE optional } |
    { ID id-HSDSCH-PreconfigurationInfo
                                                     CRITICALITY ignore EXTENSION HSDSCH-PreconfigurationInfo
    PRESENCE optional } |
    { ID id-Non-Serving-RL-Preconfig-Info
                                                     CRITICALITY ignore EXTENSION Non-Serving-RL-Preconfig-Info
       PRESENCE optional } |
    { ID id-Neighbouring-UMTS-CellInformation-Ext
                                                     CRITICALITY ignore EXTENSION Neighbouring-UMTS-CellInformation-Ext
    PRESENCE optional },
DiversityIndication-RL-SetupRspFDD ::= CHOICE {
    combining
                                  Combining-RL-SetupRspFDD,
   nonCombiningOrFirstRL
                                  NonCombiningOrFirstRL-RL-SetupRspFDD
Combining-RL-SetupRspFDD ::= SEOUENCE {
   rL-ID
   iE-Extensions
                              ProtocolExtensionContainer { { CombiningItem-RL-SetupRspFDD-ExtIEs} } OPTIONAL,
CombiningItem-RL-SetupRspFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-DCH-InformationResponse
                                         CRITICALITY ignore EXTENSION DCH-InformationResponse
                                                                                                                         PRESENCE optional
    { ID id-EDCH-FDD-InformationResponse
                                                                                                                  PRESENCE optional
                                         CRITICALITY ignore EXTENSION EDCH-FDD-InformationResponse
                                                                                                                                       },
NonCombiningOrFirstRL-RL-SetupRspFDD ::= SEQUENCE {
                              DCH-InformationResponse,
   dCH-InformationResponse
   iE-Extensions
                              ProtocolExtensionContainer { { NonCombiningOrFirstRLItem-RL-SetupRspFDD-ExtIEs} } OPTIONAL,
NonCombiningOrFirstRLItem-RL-SetupRspFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
{ID id-EDCH-FDD-InformationResponse
                                           CRITICALITY ignore EXTENSION EDCH-FDD-InformationResponse
                                                                                                                     PRESENCE optional },
RadioLinkSetupResponseFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-HSDSCH-RNTI
                                              CRITICALITY ignore
                                                                      EXTENSION HSDSCH-RNTI
    PRESENCE optional } |
     ID id-HSDSCH-FDD-Information-Response
                                              CRITICALITY ignore
                                                                      EXTENSION HSDSCH-FDD-Information-Response
                                                                                                                            PRESENCE optional }
    { ID id-Continuous-Packet-Connectivity-HS-SCCH-Less-Information-Response
                                                                                  CRITICALITY ignore
                                                                                                              EXTENSION Continuous-Packet-
Connectivity-HS-SCCH-Less-Information-Response
                                                  PRESENCE optional } |
     ID id-SixtyfourQAM-DL-SupportIndicator
                                              CRITICALITY ignore
                                                                      EXTENSION SixtyfourQAM-DL-SupportIndicator
                                                                                                                            PRESENCE optional } |
     ID id-Additional-HS-Cell-Information-Response CRITICALITY ignore
                                                                          EXTENSION Additional-HS-Cell-Information-Response-List
    PRESENCE optional }
    { ID id-Additional-EDCH-Cell-Information-Response
                                                          CRITICALITY ignore EXTENSION Additional-EDCH-Cell-Information-Response-List
       PRESENCE optional },
Additional-HS-Cell-Information-Response-List ::= SEQUENCE (SIZE (1..maxNrOfHSDSCH-1)) OF Additional-HS-Cell-Information-Response-ItemIEs
Additional-HS-Cell-Information-Response-ItemIEs ::=SEQUENCE{
   hSPDSCH-RL-ID
                                                      RL-ID,
   hSDSCH-RNTI
                                                      HSDSCH-RNTI,
   hS-DSCH-FDD-Secondary-Serving-Information-Response HS-DSCH-FDD-Secondary-Serving-Information-Response,
                                                      SixtyfourOAM-DL-SupportIndicator
    sixtyfourOAM-DL-SupportIndicator
                                                                                         OPTIONAL,
   iE-Extensions
                                   ProtocolExtensionContainer { Additional-HS-Cell-Information-Response-ItemIEs-ExtIEs} } OPTIONAL,
Additional-HS-Cell-Information-Response-ItemIEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
-- RADIO LINK SETUP RESPONSE TDD
         RadioLinkSetupResponseTDD ::= SEQUENCE {
                                                              {{RadioLinkSetupResponseTDD-IEs}},
   protocolIEs
                                   ProtocolIE-Container
                                   ProtocolExtensionContainer {{RadioLinkSetupResponseTDD-Extensions}}
   protocolExtensions
                                                                                                                       OPTIONAL,
    . . .
RadioLinkSetupResponseTDD-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-D-RNTI
                                                   CRITICALITY ignore TYPE D-RNTI
                                                                                                                 PRESENCE optional
     ID id-CN-PS-DomainIdentifier
                                                  CRITICALITY ignore TYPE CN-PS-DomainIdentifier
                                                                                                                 PRESENCE optional
     ID id-CN-CS-DomainIdentifier
                                                  CRITICALITY ignore TYPE CN-CS-DomainIdentifier
                                                                                                                 PRESENCE optional
     ID id-RL-InformationResponse-RL-SetupRspTDD
                                                  CRITICALITY ignore TYPE RL-InformationResponse-RL-SetupRspTDD
                                                                                                                PRESENCE optional
    --Mandatory for 3.84Mcps TDD only
    { ID id-UL-SIRTarget
                                                                                                                 PRESENCE mandatory }
                                                   CRITICALITY ignore TYPE UL-SIR
```

```
{ ID id-CriticalityDiagnostics
                                                CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                                           PRESENCE optional },
RL-InformationResponse-RL-SetupRspTDD ::= SEQUENCE {
   rI.-ID
                             RL-ID.
   uRA-Information
                             URA-Information
                                                OPTIONAL,
   ςΔT
                             SAI.
   qA-Cell
                             GA-Cell
                                        OPTIONAL,
   qA-AccessPointPosition
                             GA-AccessPointPosition OPTIONAL,
   ul-TimeSlot-ISCP-Info
                             UL-TimeSlot-ISCP-Info,
   maxUL-SIR
                             UL-SIR,
   minUL-SIR
                             UL-SIR,
   maximumAllowedULTxPower
                             MaximumAllowedULTxPower,
   maximumDLTxPower
                             DL-Power,
   minimumDLTxPower
                             DL-Power,
   uARFCNforNt.
                             UARFCN
                                                OPTIONAL,
   cellParameterID
                                                OPTIONAL,
                             CellParameterID
   syncCase
                             SyncCase
                                                OPTIONAL,
                             SCH-TimeSlot
   sCH-TimeSlot
                                                OPTIONAL,
   -- This IE shall be present if Sync Case IE is equal to "Case2". --
                             SCTD-Indicator OPTIONAL,
   sCTD-Indicator
   pCCPCH-Power
                             PCCPCH-Power,
   timingAdvanceApplied
                             TimingAdvanceApplied.
   alphaValue
                             AlphaValue,
   ul-PhysCH-SF-Variation
                             UL-PhysCH-SF-Variation,
   synchronisationConfiguration
                                    SynchronisationConfiguration,
   secondary-CCPCH-Info-TDD
                                     Secondary-CCPCH-Info-TDD
                                                               OPTIONAL,
   ul-CCTrCHInformation
                                    UL-CCTrCHInformationList-RL-SetupRspTDD
                                                                              OPTIONAL,
   dl-CCTrCHInformation
                                     DL-CCTrCHInformationList-RL-SetupRspTDD
                                                                              OPTIONAL,
                                    DCH-InformationResponseList-RL-SetupRspTDD
   dCH-InformationResponse
                                                                             OPTIONAL,
   dsch-InformationResponse
                                    DSCH-InformationResponse-RL-SetupRspTDD OPTIONAL,
   usch-InformationResponse
                                    USCH-InformationResponse-RL-SetupRspTDD OPTIONAL,
   neighbouring-UMTS-CellInformation
                                            Neighbouring-UMTS-CellInformation OPTIONAL,
                                            Neighbouring-GSM-CellInformation OPTIONAL,
   neighbouring-GSM-CellInformation
                                 ProtocolExtensionContainer { {RL-InformationResponse-RL-SetupRspTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
RL-InformationResponse-RL-SetupRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-GA-CellAdditionalShapes
                                                                                                                      PRESENCE optional } |
                                                CRITICALITY ignore EXTENSION GA-CellAdditionalShapes
     ID id-HCS-Prio
                                                CRITICALITY ignore EXTENSION HCS-Prio
                                                                                                               PRESENCE optional }
    { ID id-TimeSlot-RL-SetupRspTDD
                                                CRITICALITY ignore EXTENSION TimeSlot
                                                                                                               PRESENCE conditional } |
   -- This IE shall be present if Sync Case IE is Case1. --
     ID id-Neighbouring-E-UTRA-CellInformation
                                                CRITICALITY ignore EXTENSION Neighbouring-E-UTRA-CellInformation
                                                                                                                      PRESENCE optional } |
    PRESENCE optional }.
   . . .
UL-CCTrCHInformationList-RL-SetupRspTDD ::= ProtocolIE-Single-Container {{UL-CCTrCHInformationListIEs-RL-SetupRspTDD}}
UL-CCTrCHInformationListIEs-RL-SetupRspTDD RNSAP-PROTOCOL-IES ::= {
    PRESENCE
mandatory }
```

726

```
UL-CCTrCHInformationListIE-RL-SetupRspTDD ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHs)) OF UL-CCTrCHInformationItem-RL-SetupRspTDD
UL-CCTrCHInformationItem-RL-SetupRspTDD ::= SEQUENCE {
                             CCTrCH-ID,
   cCTrCH-ID
   ul-DPCH-Information
                                 UL-DPCH-InformationList-RL-SetupRspTDD
                                                                           OPTIONAL.
                                 ProtocolExtensionContainer { {UL-CCTrCHInformationItem-RL-SetupRspTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
UL-CCTrCHInformationItem-RL-SetupRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   {ID id-UL-SIR-Target-CCTrCH-InformationItem-RL-SetupRspTDD
                                                                CRITICALITY ignore
                                                                                      EXTENSION UL-SIR
                                                                                                                 PRESENCE optional },
   . . .
UL-DPCH-InformationList-RL-SetupRspTDD ::= ProtocolIE-Single-Container { {UL-DPCH-InformationListIEs-RL-SetupRspTDD} }
UL-DPCH-InformationListIEs-RL-SetupRspTDD RNSAP-PROTOCOL-IES ::= {
    { ID id-UL-DPCH-InformationItem-RL-SetupRspTDD
                                                    CRITICALITY ignore TYPE UL-DPCH-InformationItem-RL-SetupRspTDD PRESENCE mandatory
UL-DPCH-InformationItem-RL-SetupRspTDD ::= SEOUENCE {
   repetitionPeriod
                                 RepetitionPeriod,
   repetitionLength
                                 RepetitionLength,
                                 TDD-DPCHOffset,
   tDD-DPCHOffset
   uL-Timeslot-Information
                                 UL-Timeslot-Information,
                                 ProtocolExtensionContainer { {UL-DPCH-InformationItem-RL-SetupRspTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
UL-DPCH-InformationItem-RL-SetupRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-CCTrCHInformationList-RL-SetupRspTDD ::= ProtocolIE-Single-Container {{DL-CCTrCHInformationListIEs-RL-SetupRspTDD}}
DL-CCTrCHInformationListIEs-RL-SetupRspTDD RNSAP-PROTOCOL-IES ::= {
    DL-CCTrCHInformationListIE-RL-SetupRspTDD ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHs)) OF DL-CCTrCHInformationItem-RL-SetupRspTDD
DL-CCTrCHInformationItem-RL-SetupRspTDD ::= SEQUENCE {
   cCTrCH-ID
                                 CCTrCH-ID,
   dl-DPCH-Information
                                 DL-DPCH-InformationList-RL-SetupRspTDD
   iE-Extensions
                                 ProtocolExtensionContainer { {DL-CCTrCHInformationItem-RL-SetupRspTDD-ExtIEs} } OPTIONAL,
DL-CCTrCHInformationItem-RL-SetupRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-CCTrCH-Maximum-DL-Power-RL-SetupRspTDD CRITICALITY ignore EXTENSION DL-Power PRESENCE optional } | -- this is a DCH type CCTrCH power
    ID id-CCTrCH-Minimum-DL-Power-RL-SetupRspTDD CRITICALITY ignore EXTENSION DL-Power PRESENCE optional }, -- this is a DCH type CCTrCH power
```

```
DL-DPCH-InformationList-RL-SetupRspTDD ::= ProtocolIE-Single-Container { {DL-DPCH-InformationListIEs-RL-SetupRspTDD} }
DL-DPCH-InformationListIEs-RL-SetupRspTDD RNSAP-PROTOCOL-IES ::= {
    { ID id-DL-DPCH-InformationItem-RL-SetupRspTDD
                                                      CRITICALITY ignore TYPE DL-DPCH-InformationItem-RL-SetupRspTDD PRESENCE mandatory
DL-DPCH-InformationItem-RL-SetupRspTDD ::= SEQUENCE {
   repetitionPeriod
                                 RepetitionPeriod,
   repetitionLength
                                  RepetitionLength,
                                  TDD-DPCHOffset,
   tDD-DPCHOffset
   dL-Timeslot-Information
                                  DL-Timeslot-Information,
                                  ProtocolExtensionContainer { {DL-DPCH-InformationItem-RL-SetupRspTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
DL-DPCH-InformationItem-RL-SetupRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DCH-InformationResponseList-RL-SetupRspTDD ::= ProtocolIE-Single-Container {{DCH-InformationResponseListIEs-RL-SetupRspTDD}}
DCH-InformationResponseListIEs-RL-SetupRspTDD RNSAP-PROTOCOL-IES ::= {
    TYPE DCH-InformationResponse PRESENCE mandatory }
DSCH-InformationResponse-RL-SetupRspTDD ::= ProtocolIE-Single-Container {{DSCH-InformationList-RL-SetupRspTDD}}
DSCH-InformationList-RL-SetupRspTDD RNSAP-PROTOCOL-IES ::= {
    { ID id-DSCH-InformationListIEs-RL-SetupRspTDD
                                                      CRITICALITY ignore TYPE DSCH-InformationListIEs-RL-SetupRspTDD PRESENCE mandatory }
DSCH-InformationListIEs-RL-SetupRspTDD ::= SEOUENCE (SIZE(0..maxNoOfDSCHs)) OF DSCHInformationItem-RL-SetupRspTDD
DSCHInformationItem-RL-SetupRspTDD ::= SEQUENCE {
   dsch-ID
                          DSCH-ID,
   dSCH-FlowControlInformation
                                  DSCH-FlowControlInformation,
   bindingID
                          BindingID OPTIONAL,
    transportLayerAddress TransportLayerAddress OPTIONAL,
    transportFormatManagement TransportFormatManagement,
                          ProtocolExtensionContainer { {DSCHInformationItem-RL-SetupRspTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
DSCHInformationItem-RL-SetupRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
USCH-InformationResponse-RL-SetupRspTDD ::= ProtocolIE-Single-Container {{USCH-InformationList-RL-SetupRspTDD}}
USCH-InformationList-RL-SetupRspTDD RNSAP-PROTOCOL-IES ::= {
    { ID id-USCH-InformationListIEs-RL-SetupRspTDD
                                                      CRITICALITY ignore TYPE USCH-InformationListIEs-RL-SetupRspTDD PRESENCE mandatory }
```

```
USCH-InformationListIEs-RL-SetupRspTDD ::= SEOUENCE (SIZE(0,.maxNoOfUSCHs)) OF USCHInformationItem-RL-SetupRspTDD
USCHInformationItem-RL-SetupRspTDD ::= SEQUENCE {
    usch-ID
                              USCH-ID.
   bindingID
                              BindingID OPTIONAL,
    transportLayerAddress
                              TransportLayerAddress OPTIONAL,
    transportFormatManagement
                              TransportFormatManagement,
                              ProtocolExtensionContainer { {USCHInformationItem-RL-SetupRspTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
USCHInformationItem-RL-SetupRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RadioLinkSetupResponseTDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    -- Mandatory for 1.28Mcps TDD only
     ID id-HSDSCH-RNTI
                                                     CRITICALITY ignore EXTENSION HSDSCH-RNTI
                                                                                                                          PRESENCE optional }
     ID id-HSDSCH-TDD-Information-Response
                                                                                                                          PRESENCE optional}
                                                     CRITICALITY ignore EXTENSION HSDSCH-TDD-Information-Response
                                                                                                                          PRESENCE optional }
     ID id-DSCH-RNTI
                                                     CRITICALITY ignore EXTENSION DSCH-RNTI
                                                                                                                          PRESENCE optional }
     ID id-Active-MBMS-Bearer-ServiceTDD-PFL
                                                     CRITICALITY ignore EXTENSION Active-MBMS-Bearer-Service-ListTDD-PFL
                                                     CRITICALITY ignore EXTENSION RL-InformationResponse-RL-SetupRspTDD768 PRESENCE optional
     ID id-RL-InformationResponse-RL-SetupRspTDD768
     ID id-E-DCH-Information-Response
                                                     CRITICALITY ignore EXTENSION E-DCH-Information-Response
                                                                                                                          PRESENCE optional}
     ID id-E-DCH-768-Information-Response
                                                     CRITICALITY ignore EXTENSION E-DCH-768-Information-Response
                                                                                                                          PRESENCE optional}
     ID id-E-DCH-LCR-Information-Response
                                                     CRITICALITY ignore EXTENSION E-DCH-LCR-Information-Response
                                                                                                                          PRESENCE optional }
     ID id-ContinuousPacketConnectivity-DRX-Information-ResponseLCR
                                                                    CRITICALITY ignore EXTENSION ContinuousPacketConnectivity-DRX-Information-
ResponseLCR
               PRESENCE optional |
    { ID id-HS-DSCH-Semi-PersistentScheduling-Information-ResponseLCR
                                                                    CRITICALITY ignore EXTENSION HS-DSCH-Semi-PersistentScheduling-
Information-ResponseLCR
                          PRESENCE optional } |
    { ID id-E-DCH-Semi-PersistentScheduling-Information-ResponseLCR
                                                                     CRITICALITY ignore EXTENSION E-DCH-Semi-PersistentScheduling-Information-
               PRESENCE optional |
ResponseLCR
                                                                                                                          PRESENCE optional }
     ID id-E-RNTI-For-FACH
                                                     CRITICALITY ignore EXTENSION E-RNTI
                                                                                                                          PRESENCE optional }
     ID id-H-RNTI-For-FACH
                                                     CRITICALITY ignore EXTENSION HSDSCH-RNTI
     ID id-DCH-MeasurementOccasion-Information
                                                     CRITICALITY reject EXTENSION DCH-MeasurementOccasion-Information
                                                                                                                          PRESENCE optional }
     ID id-Multi-Carrier-EDCH-Response
                                                     CRITICALITY ignore EXTENSION Multi-Carrier-EDCH-Information-Response
                                                                                                                          PRESENCE optional }
     ID id-MU-MIMO-InformationLCR
                                                     CRITICALITY reject EXTENSION MU-MIMO-InformationLCR
                                                                                                                          PRESENCE optional },
RL-LCR-InformationResponse-RL-SetupRspTDD ::= SEQUENCE {
                              RL-ID,
   uRA-Information
                              URA-Information,
    SAT
                              SAI,
    qA-Cell
                              GA-Cell
                                          OPTIONAL,
   gA-AccessPointPosition
                              GA-AccessPointPosition OPTIONAL,
   ul-TimeSlot-ISCP-LCR-Info
                              UL-TimeSlot-ISCP-LCR-Info,
   maxUL-SIR
                              UL-SIR,
   minUL-SIR
                              UL-SIR,
   maximumAllowedULTxPower
                              MaximumAllowedULTxPower,
   maximumDLTxPower
                              DL-Power,
   minimumDLTxPower
                              DL-Power,
```

```
uARFCNforNt
                                UARFCN
                                                        OPTIONAL,
    cellParameterID
                                CellParameterID
                                                        OPTIONAL.
    sCTD-Indicator
                        SCTD-Indicator OPTIONAL.
    pCCPCH-Power
                                PCCPCH-Power,
    alphaValue
                                AlphaValue,
    ul-PhysCH-SF-Variation
                                UL-PhysCH-SF-Variation,
    synchronisationConfiguration
                                            SynchronisationConfiguration,
    secondary-LCR-CCPCH-Info-TDD
                                            Secondary-LCR-CCPCH-Info-TDD
                                                                                             OPTIONAL,
    ul-LCR-CCTrCHInformation
                                            UL-LCR-CCTrCHInformationList-RL-SetupRspTDD
                                                                                             OPTIONAL,
    dl-LCR-CCTrCHInformation
                                            DL-LCR-CCTrCHInformationList-RL-SetupRspTDD
                                                                                             OPTIONAL,
                                            DCH-InformationResponseList-RL-SetupRspTDD
                                                                                             OPTIONAL,
    dCH-InformationResponse
                                            DSCH-LCR-InformationResponse-RL-SetupRspTDD
    dsch-LCR-InformationResponse
                                                                                             OPTIONAL,
                                            USCH-LCR-InformationResponse-RL-SetupRspTDD
    usch-LCR-InformationResponse
                                                                                             OPTIONAL,
    neighbouring-UMTS-CellInformation
                                            Neighbouring-UMTS-CellInformation
                                                                                             OPTIONAL,
    neighbouring-GSM-CellInformation
                                            Neighbouring-GSM-CellInformation
                                                                                             OPTIONAL,
                                            ProtocolExtensionContainer { { RL-LCR-InformationResponseList-RL-SetupRspTDD-ExtIEs} }
    iE-Extensions
    OPTIONAL,
RL-LCR-InformationResponseList-RL-SetupRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
      ID id-GA-CellAdditionalShapes
                                                    CRITICALITY ignore EXTENSION GA-CellAdditionalShapes
                                                                                                                                 PRESENCE optional }
      ID id-HCS-Prio
                                                    CRITICALITY ignore EXTENSION HCS-Prio
                                                                                                                                 PRESENCE optional
     ID id-UL-TimingAdvanceCtrl-LCR
                                                    CRITICALITY ignore EXTENSION UL-TimingAdvanceCtrl-LCR
                                                                                                                                 PRESENCE optional }
    -- Mandatory for 1.28Mcps TDD only
    { ID id-PowerControlGAP
                                                    CRITICALITY ignore EXTENSION ControlGAP
                                                                                                                                 PRESENCE optional } |
    -- Applicable to 1.28Mcps TDD only
    { ID id-SixtyfourOAM-DL-SupportIndicator
                                                    CRITICALITY ignore EXTENSION SixtyfourOAM-DL-SupportIndicator
                                                                                                                                 PRESENCE optional } |
    -- Applicable to 1.28Mcps TDD only
     ID id-Neighbouring-E-UTRA-CellInformation
                                                    CRITICALITY ignore EXTENSION Neighbouring-E-UTRA-CellInformation
                                                                                                                                 PRESENCE optional }
      ID id-IdleIntervalInformation
                                                                        EXTENSION IdleIntervalInformation
                                                    CRITICALITY ignore
                                                                                                                                 PRESENCE optional }
     ID id-Neighbouring-UMTS-CellInformation-Ext
                                                    CRITICALITY ignore EXTENSION Neighbouring-UMTS-CellInformation-Ext
                                                                                                                                 PRESENCE optional },
    . . .
UL-LCR-CCTrCHInformationList-RL-SetupRspTDD ::= ProtocolIE-Single-Container {{UL-LCR-CCTrCHInformationListIEs-RL-SetupRspTDD}}
UL-LCR-CCTrCHInformationListIEs-RL-SetupRspTDD RNSAP-PROTOCOL-IES ::= {
    { ID id-UL-CCTrCH-LCR-InformationListIE-RL-SetupRspTDD CRITICALITY ignore TYPE UL-LCR-CCTrCHInformationListIE-RL-SetupRspTDD
    PRESENCE mandatory }
UL-LCR-CCTrCHInformationListIE-RL-SetupRspTDD ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHsLCR)) OF UL-LCR-CCTrCHInformationItem-RL-SetupRspTDD
UL-LCR-CCTrCHInformationItem-RL-SetupRspTDD ::= SEQUENCE {
    cCTrCH-ID
                                CCTrCH-ID,
    ul-DPCH-LCR-Information
                                UL-DPCH-LCR-InformationList-RL-SetupRspTDD
                                ProtocolExtensionContainer { {UL-LCR-CCTrCHInformationItem-RL-SetupRspTDD-ExtIEs} } OPTIONAL,
    iE-Extensions
UL-LCR-CCTrCHInformationItem-RL-SetupRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    {ID id-UL-SIR-Target-CCTrCH-LCR-InformationItem-RL-SetupRspTDD
                                                                        CRITICALITY ignore
                                                                                                                         PRESENCE optional },
                                                                                                 EXTENSION UL-SIR
    . . .
```

```
UL-DPCH-LCR-InformationList-RL-SetupRspTDD ::= ProtocolIE-Single-Container { {UL-DPCH-LCR-InformationListIEs-RL-SetupRspTDD} }
UL-DPCH-LCR-InformationListIEs-RL-SetupRspTDD RNSAP-PROTOCOL-IES ::= {
     ID id-UL-DPCH-LCR-InformationItem-RL-SetupRspTDD
                                                        CRITICALITY ignore TYPE UL-DPCH-LCR-InformationItem-RL-SetupRspTDD PRESENCE mandatory
UL-DPCH-LCR-InformationItem-RL-SetupRspTDD ::= SEOUENCE {
                                 RepetitionPeriod,
   repetitionPeriod
   repetitionLength
                                 RepetitionLength,
   tDD-DPCHOffset
                                 TDD-DPCHOffset,
   uL-TimeslotLCR-Information
                                 UL-TimeslotLCR-Information,
   iE-Extensions
                                 ProtocolExtensionContainer { {UL-DPCH-LCR-InformationItem-RL-SetupRspTDD-ExtIEs} } OPTIONAL,
UL-DPCH-LCR-InformationItem-RL-SetupRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-LCR-CCTrCHInformationList-RL-SetupRspTDD ::= ProtocolIE-Single-Container {{DL-LCR-CCTrCHInformationListIEs-RL-SetupRspTDD}}
DL-LCR-CCTrCHInformationListIEs-RL-SetupRspTDD RNSAP-PROTOCOL-IES ::= {
   mandatory }
DL-CCTrCH-LCR-InformationListIE-RL-SetupRspTDD ::= SEOUENCE (SIZE (1..maxNrOfCCTrCHsLCR)) OF DL-CCTrCH-LCR-InformationItem-RL-SetupRspTDD
DL-CCTrCH-LCR-InformationItem-RL-SetupRspTDD ::= SEQUENCE {
   cCTrCH-ID
                             CCTrCH-ID,
   dl-DPCH-LCR-Information
                             DL-DPCH-LCR-InformationList-RL-SetupRspTDD
                                                                          OPTIONAL,
                             ProtocolExtensionContainer { {DL-CCTrCH-LCR-InformationItem-RL-SetupRspTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
   . . .
DL-CCTrCH-LCR-InformationItem-RL-SetupRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-DPCH-LCR-InformationList-RL-SetupRspTDD ::= ProtocolIE-Single-Container { {DL-DPCH-LCR-InformationListIEs-RL-SetupRspTDD} }
DL-DPCH-LCR-InformationListIEs-RL-SetupRspTDD RNSAP-PROTOCOL-IES ::= {
     ID id-DL-DPCH-LCR-InformationItem-RL-SetupRspTDD CRITICALITY ignore TYPE DL-DPCH-LCR-InformationItem-RL-SetupRspTDD PRESENCE mandatory
DL-DPCH-LCR-InformationItem-RL-SetupRspTDD ::= SEQUENCE {
   repetitionPeriod
                                 RepetitionPeriod,
   repetitionLength
                                 RepetitionLength,
   tDD-DPCHOffset
                                 TDD-DPCHOffset,
   dL-Timeslot-LCR-Information
                                 DL-TimeslotLCR-Information,
   tSTD-Indicator
                                 TSTD-Indicator,
```

```
ProtocolExtensionContainer { {DL-DPCH-LCR-InformationItem-RL-SetupRspTDD-ExtIEs} } OPTIONAL,
    iE-Extensions
DL-DPCH-LCR-InformationItem-RL-SetupRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DSCH-LCR-InformationResponse-RL-SetupRspTDD ::= ProtocolIE-Single-Container {{DSCH-LCR-InformationList-RL-SetupRspTDD}}
DSCH-LCR-InformationList-RL-SetupRspTDD RNSAP-PROTOCOL-IES ::= {
    { ID id-DSCH-LCR-InformationListIEs-RL-SetupRspTDD
                                                            CRITICALITY ignore TYPE DSCH-LCR-InformationListIEs-RL-SetupRspTDD PRESENCE mandatory
DSCH-LCR-InformationListIEs-RL-SetupRspTDD ::= SEOUENCE (SIZE(0..maxNoOfDSCHsLCR)) OF DSCH-LCR-InformationItem-RL-SetupRspTDD
DSCH-LCR-InformationItem-RL-SetupRspTDD ::= SEQUENCE {
    dsch-ID
                                        DSCH-ID,
    dSCH-FlowControlInformation
                                        DSCH-FlowControlInformation,
    bindingID
                                        BindingID OPTIONAL,
    transportLayerAddress
                                        TransportLayerAddress OPTIONAL,
    transportFormatManagement
                                        TransportFormatManagement,
    iE-Extensions
                                        ProtocolExtensionContainer { {DSCH-LCR-InformationItem-RL-SetupRspTDD-ExtIEs} } OPTIONAL.
DSCH-LCR-InformationItem-RL-SetupRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
USCH-LCR-InformationResponse-RL-SetupRspTDD ::= ProtocolIE-Single-Container {{USCH-LCR-InformationList-RL-SetupRspTDD}}
USCH-LCR-InformationList-RL-SetupRspTDD RNSAP-PROTOCOL-IES ::= {
    { ID id-USCH-LCR-InformationListIEs-RL-SetupRspTDD
                                                            CRITICALITY ignore TYPE USCH-LCR-InformationListIEs-RL-SetupRspTDD PRESENCE mandatory
USCH-LCR-InformationListIEs-RL-SetupRspTDD ::= SEQUENCE (SIZE(0..maxNoOfUSCHsLCR)) OF USCH-LCR-InformationItem-RL-SetupRspTDD
USCH-LCR-InformationItem-RL-SetupRspTDD ::= SEQUENCE {
    usch-ID
                                USCH-ID,
    bindingID
                                BindingID OPTIONAL,
    transportLayerAddress
                                TransportLayerAddress
                                                       OPTIONAL,
                               TransportFormatManagement,
    transportFormatManagement
    iE-Extensions
                                ProtocolExtensionContainer { {USCH-LCR-InformationItem-RL-SetupRspTDD-ExtIEs} } OPTIONAL,
    . . .
USCH-LCR-InformationItem-RL-SetupRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RL-InformationResponse-RL-SetupRspTDD768 ::= SEQUENCE
```

RL-ID,

rL-ID

```
uRA-Information
                              URA-Information
                                                  OPTIONAL,
    sAI
                              SAI.
    gA-Cell
                              GA-Cell
                                          OPTIONAL.
    qA-AccessPointPosition
                              GA-AccessPointPosition OPTIONAL.
   ul-TimeSlot-ISCP-Info
                              UL-TimeSlot-ISCP-Info,
   maxUL-SIR
                              UL-SIR,
   minUL-SIR
                              UL-SIR,
   maximumAllowedULTxPower
                              MaximumAllowedULTxPower,
   maximumDLTxPower
                              DL-Power,
   minimumDLTxPower
                              DL-Power,
    uARFCNforNt
                              UARFCN
                                                  OPTIONAL,
    cellParameterID
                              CellParameterID
                                                  OPTIONAL,
    svncCase
                              SyncCase
                                                  OPTIONAL,
    sCH-TimeSlot
                              SCH-TimeSlot
                                                  OPTIONAL,
    -- This IE shall be present if Sync Case IE is equal to "Case2". --
                              SCTD-Indicator OPTIONAL,
    sCTD-Indicator
    pCCPCH-Power
                              PCCPCH-Power,
    timingAdvanceApplied
                              TimingAdvanceApplied,
    alphaValue
                              AlphaValue,
    ul-PhysCH-SF-Variation
                              UL-PhysCH-SF-Variation,
    synchronisationConfiguration
                                      SynchronisationConfiguration,
    secondary-CCPCH-Info-TDD768
                                      Secondary-CCPCH-Info-TDD768
                                                                     OPTIONAL,
    ul-CCTrCHInformation768
                                      UL-CCTrCHInformationList-RL-SetupRspTDD768
                                                                                     OPTIONAL,
    dl-CCTrCHInformation768
                                      DL-CCTrCHInformationList-RL-SetupRspTDD768
                                                                                     OPTIONAL,
    dCH-InformationResponse
                                      DCH-InformationResponseList-RL-SetupRspTDD
                                      DSCH-InformationResponse-RL-SetupRspTDD OPTIONAL,
    dsch-InformationResponse
    usch-InformationResponse
                                      USCH-InformationResponse-RL-SetupRspTDD OPTIONAL,
    neighbouring-UMTS-CellInformation
                                              Neighbouring-UMTS-CellInformation OPTIONAL,
                                              Neighbouring-GSM-CellInformation OPTIONAL,
    neighbouring-GSM-CellInformation
    qA-CellAdditionalShapes
                                              GA-CellAdditionalShapes
                                                                         OPTIONAL,
   hCS-Prio
                                                      OPTIONAL,
                                      HCS-Prio
    timeSlot-RL-SetupRspTDD
                                      TimeSlot
                                                  OPTIONAL,
    -- This IE shall be present if Sync Case IE is Case1. --
    iE-Extensions
                                   ProtocolExtensionContainer { {RL-InformationResponse-RL-SetupRspTDD768-ExtIEs} } OPTIONAL,
RL-InformationResponse-RL-SetupRspTDD768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
                                                      CRITICALITY ignore EXTENSION Neighbouring-E-UTRA-CellInformation
     ID id-Neighbouring-E-UTRA-CellInformation
                                                                                                                           PRESENCE optional }
    { ID id-Neighbouring-UMTS-CellInformation-Ext
                                                      CRITICALITY ignore EXTENSION Neighbouring-UMTS-CellInformation-Ext
                                                                                                                           PRESENCE optional },
    . . .
UL-CCTrCHInformationList-RL-SetupRspTDD768 ::= ProtocolIE-Single-Container {{UL-CCTrCHInformationListIEs-RL-SetupRspTDD768}}
UL-CCTrCHInformationListIEs-RL-SetupRspTDD768 RNSAP-PROTOCOL-IES ::= {
    PRESENCE mandatory }
UL-CCTrCHInformationListIE-RL-SetupRspTDD768 ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHs)) OF UL-CCTrCHInformationItem-RL-SetupRspTDD768
```

```
UL-CCTrCHInformationItem-RL-SetupRspTDD768 ::= SEQUENCE {
   cCTrCH-ID
                             CCTrCH-ID.
   ul-DPCH-Information768
                                     UL-DPCH-InformationList-RL-SetupRspTDD768
                                                                                   OPTIONAL.
   uL-SIR-Target-CCTrCH-InformationItem-RL-SetupRspTDD768
                                                            UL-SIR
                                                                       OPTIONAL.
   iE-Extensions
                                 ProtocolExtensionContainer { {UL-CCTrCHInformationItem-RL-SetupRspTDD768-ExtIEs} } OPTIONAL,
UL-CCTrCHInformationItem-RL-SetupRspTDD768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UL-DPCH-InformationList-RL-SetupRspTDD768 ::= ProtocolIE-Single-Container { {UL-DPCH-InformationListIEs-RL-SetupRspTDD768} }
UL-DPCH-InformationListIEs-RL-SetupRspTDD768 RNSAP-PROTOCOL-IES ::= {
     ID id-UL-DPCH-InformationItem-RL-SetupRspTDD768
                                                        CRITICALITY ignore TYPE UL-DPCH-InformationItem-RL-SetupRspTDD768 PRESENCE mandatory
UL-DPCH-InformationItem-RL-SetupRspTDD768 ::= SEQUENCE {
   repetitionPeriod
                                 RepetitionPeriod,
   repetitionLength
                                 RepetitionLength,
                                 TDD-DPCHOffset,
   tDD-DPCHOffset
   uL-Timeslot-Information768
                                     UL-Timeslot-Information768,
   iE-Extensions
                                 ProtocolExtensionContainer { {UL-DPCH-InformationItem-RL-SetupRspTDD768-ExtIEs} } OPTIONAL,
   . . .
UL-DPCH-InformationItem-RL-SetupRspTDD768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-CCTrCHInformationList-RL-SetupRspTDD768 ::= ProtocolIE-Single-Container {{DL-CCTrCHInformationListIEs-RL-SetupRspTDD768}}
DL-CCTrCHInformationListIEs-RL-SetupRspTDD768 RNSAP-PROTOCOL-IES ::= {
    mandatory }
DL-CCTrCHInformationListIE-RL-SetupRspTDD768 ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHs)) OF DL-CCTrCHInformationItem-RL-SetupRspTDD768
DL-CCTrCHInformationItem-RL-SetupRspTDD768 ::= SEQUENCE {
   cCTrCH-ID
                              CCTrCH-ID,
   dl-DPCH-Information768
                                     DL-DPCH-InformationList-RL-SetupRspTDD768
                                                                                   OPTIONAL.
   cCTrCH-Maximum-DL-Power
                                                    OPTIONAL, -- this is a DCH type CCTrCH power
                                     DL-Power
   cCTrCH-Minimum-DL-Power
                                     DL-Power
                                                    OPTIONAL, -- this is a DCH type CCTrCH power
   iE-Extensions
                                 ProtocolExtensionContainer { {DL-CCTrCHInformationItem-RL-SetupRspTDD768-ExtIEs} } OPTIONAL,
DL-CCTrCHInformationItem-RL-SetupRspTDD768-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
   . . .
```

```
DL-DPCH-InformationList-RL-SetupRspTDD768 ::= ProtocolIE-Single-Container { {DL-DPCH-InformationListIEs-RL-SetupRspTDD768} }
DL-DPCH-InformationListIEs-RL-SetupRspTDD768 RNSAP-PROTOCOL-IES ::= {
     ID id-DL-DPCH-InformationItem-RL-SetupRspTDD768
                                                           CRITICALITY ignore TYPE DL-DPCH-InformationItem-RL-SetupRspTDD768 PRESENCE mandatory
DL-DPCH-InformationItem-RL-SetupRspTDD768 ::= SEQUENCE {
   repetitionPeriod
                                   RepetitionPeriod,
                                   RepetitionLength.
    repetitionLength
    tDD-DPCHOffset
                                   TDD-DPCHOffset,
    dL-Timeslot-Information768
                                   DL-Timeslot-Information768,
                                   ProtocolExtensionContainer { {DL-DPCH-InformationItem-RL-SetupRspTDD768-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
DL-DPCH-InformationItem-RL-SetupRspTDD768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
-- RADIO LINK SETUP FAILURE FDD
  *****************
RadioLinkSetupFailureFDD ::= SEQUENCE {
    protocolIEs
                                   ProtocolIE-Container
                                                              {{RadioLinkSetupFailureFDD-IEs}},
                                   ProtocolExtensionContainer {{RadioLinkSetupFailureFDD-Extensions}}
   protocolExtensions
                                                                                                                       OPTIONAL
RadioLinkSetupFailureFDD-IES RNSAP-PROTOCOL-IES ::= {
                                           CRITICALITY ignore TYPE D-RNTI
                                                                                                   PRESENCE optional
     ID id-D-RNTI
     ID id-CN-PS-DomainIdentifier
                                           CRITICALITY ignore TYPE CN-PS-DomainIdentifier
                                                                                                   PRESENCE optional
     ID id-CN-CS-DomainIdentifier
                                           CRITICALITY ignore TYPE CN-CS-DomainIdentifier
                                                                                                   PRESENCE optional
     ID id-CauseLevel-RL-SetupFailureFDD
                                           CRITICALITY ignore TYPE CauseLevel-RL-SetupFailureFDD
                                                                                                   PRESENCE mandatory } |
     ID id-UL-SIRTarget
                                           CRITICALITY ignore TYPE UL-SIR
                                                                                                   PRESENCE optional
    ID id-CriticalityDiagnostics
                                           CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                                   PRESENCE optional },
    . . .
CauseLevel-RL-SetupFailureFDD ::= CHOICE {
                       GeneralCauseList-RL-SetupFailureFDD,
    generalCause
    rLSpecificCause
                       RLSpecificCauseList-RL-SetupFailureFDD,
GeneralCauseList-RL-SetupFailureFDD ::= SEOUENCE
    cause
                                               ProtocolExtensionContainer { { GeneralCauseItem-RL-SetupFailureFDD-ExtIEs} } }
    iE-Extensions
                                                                                                                                     OPTIONAL,
    . . .
```

```
GeneralCauseItem-RL-SetupFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RLSpecificCauseList-RL-SetupFailureFDD ::= SEOUENCE {
    unsuccessful-RL-InformationRespList-RL-SetupFailureFDD
                                                                UnsuccessfulRL-InformationResponseList-RL-SetupFailureFDD,
    successful-RL-InformationRespList-RL-SetupFailureFDD
                                                                SuccessfulRL-InformationResponseList-RL-SetupFailureFDD OPTIONAL,
    iE-Extensions
                                                ProtocolExtensionContainer { { RLSpecificCauseItem-RL-SetupFailureFDD-ExtIEs} }
                                                                                                                                        OPTIONAL.
RLSpecificCauseItem-RL-SetupFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-HSDSCH-RNTI
                                                CRITICALITY ignore
                                                                        EXTENSION HSDSCH-RNTI
    PRESENCE optional } |
     ID id-HSDSCH-FDD-Information-Response
                                                CRITICALITY ignore
                                                                                                                                 PRESENCE optional } |
                                                                        EXTENSION HSDSCH-FDD-Information-Response
     ID id-Continuous-Packet-Connectivity-HS-SCCH-Less-Information-Response
                                                                                     CRITICALITY ignore
                                                                                                                 EXTENSION Continuous-Packet-
Connectivity-HS-SCCH-Less-Information-Response
                                                    PRESENCE optional }
      ID id-SixtyfourOAM-DL-SupportIndicator
                                                                        EXTENSION SixtyfourOAM-DL-SupportIndicator
                                                CRITICALITY ignore
                                                                                                                                 PRESENCE optional }
      ID id-Additional-HS-Cell-Information-Response CRITICALITY ignore
                                                                             EXTENSION Additional-HS-Cell-Information-Response-List
    PRESENCE optional } |
    { ID id-Additional-EDCH-Cell-Information-Response
                                                            CRITICALITY ignore EXTENSION Additional-EDCH-Cell-Information-Response-List
        PRESENCE optional },
UnsuccessfulRL-InformationResponseList-RL-SetupFailureFDD ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { {UnsuccessfulRL-
InformationResponse-RL-SetupFailureFDD-IEs} }
UnsuccessfulRL-InformationResponse-RL-SetupFailureFDD-IES RNSAP-PROTOCOL-IES ::= {
    { ID id-UnsuccessfulRL-InformationResponse-RL-SetupFailureFDD
                                                                        CRITICALITY ignore TYPE UnsuccessfulRL-InformationResponse-RL-
SetupFailureFDD
                    PRESENCE mandatory }
UnsuccessfulRL-InformationResponse-RL-SetupFailureFDD ::= SEQUENCE {
    rL-ID
                                RL-ID,
    cause
    iE-Extensions
                                    ProtocolExtensionContainer { {UnsuccessfulRL-InformationResponse-RL-SetupFailureFDD-ExtIEs} } OPTIONAL.
UnsuccessfulRL-InformationResponse-RL-SetupFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-Max-UE-DTX-Cycle
                                    CRITICALITY ignore
                                                            EXTENSION Max-UE-DTX-Cycle
                                                                                                   PRESENCE conditional },
    -- This IE shall be present if the Cause IE is set to "Continuous Packet Connectivity UE DTX Cycle not Available".
Successful RL-Information Response List-RL-Setup Failure FDD ::= SEOUENCE (SIZE (0...maxNrOfRLs-1)) OF Protocol IE-Single-Container { {Successful RL-
InformationResponse-RL-SetupFailureFDD-IEs} }
SuccessfulRL-InformationResponse-RL-SetupFailureFDD-IES RNSAP-PROTOCOL-IES ::= {
    { ID id-SuccessfulRL-InformationResponse-RL-SetupFailureFDD
                                                                    CRITICALITY ignore TYPE SuccessfulRL-InformationResponse-RL-SetupFailureFDD
        PRESENCE mandatory }
```

```
SuccessfulRL-InformationResponse-RL-SetupFailureFDD ::= SEOUENCE {
    rI.-ID
                                            RL-ID.
    rL-Set-ID
                                            RL-Set-ID.
    uRA-Information
                                            URA-Information
                                                                                 OPTIONAL,
                                            SAI.
                                            GA-Cell
                                                        OPTIONAL.
    gA-Cell
    qA-AccessPointPosition
                                            GA-AccessPointPosition
                                                                                 OPTIONAL,
    received-total-wide-band-power
                                            Received-total-wide-band-power,
    not-Used-secondary-CCPCH-Info
                                                    NIII.I.
                                                                        OPTIONAL,
    dl-CodeInformation
                                            FDD-DL-CodeInformation,
    diversityIndication
                                            DiversityIndication-RL-SetupFailureFDD,
    sSDT-SupportIndicator
                                            SSDT-SupportIndicator,
    maxUL-SIR
                                            UL-SIR,
   minUL-SIR
                                            UL-SIR,
    closedlooptimingadjustmentmode
                                            Closedlooptimingadjustmentmode
                                                                                 OPTIONAL,
    maximumAllowedULTxPower
                                            MaximumAllowedULTxPower,
    maximumDLTxPower
                                            DL-Power,
    minimumDLTxPower
                                            DL-Power,
                                            PrimaryCPICH-Power,
    primaryCPICH-Power
                                            PrimaryScramblingCode
    primaryScramblingCode
                                                                                 OPTIONAL.
    uL-UARFCN
                                            HARFON
                                                                                 OPTIONAL,
                                            UARFCN
    dL-UARFCN
                                                                                OPTIONAL,
    not-Used-dSCH-InformationResponse-RL-SetupFailureFDD
                                                            NULL
                                                                                OPTIONAL,
    neighbouring-UMTS-CellInformation
                                            Neighbouring-UMTS-CellInformation
                                                                                OPTIONAL,
    neighbouring-GSM-CellInformation
                                            Neighbouring-GSM-CellInformation
                                                                                OPTIONAL,
    pC-Preamble
                                            PC-Preamble.
    sRB-Delay
                                            SRB-Delay,
                                            ProtocolExtensionContainer { {SuccessfulRL-InformationResponse-RL-SetupFailureFDD-ExtIEs} } OPTIONAL,
    iE-Extensions
SuccessfulRL-InformationResponse-RL-SetupFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
      ID id-GA-CellAdditionalShapes
                                                        CRITICALITY ignore EXTENSION GA-CellAdditionalShapes
                                                                                                                                 PRESENCE optional }
      ID id-DL-PowerBalancing-ActivationIndicator
                                                        CRITICALITY ignore EXTENSION DL-PowerBalancing-ActivationIndicator
                                                                                                                                 PRESENCE optional }
                                                                                                                                 PRESENCE optional }
      ID id-HCS-Prio
                                                        CRITICALITY ignore EXTENSION HCS-Prio
                                                                                                                                        PRESENCE
     ID id-Primary-CPICH-Usage-For-Channel-Estimation CRITICALITY ignore EXTENSION Primary-CPICH-Usage-For-Channel-Estimation
optional }
      ID id-Secondary-CPICH-Information
                                                        CRITICALITY ignore EXTENSION Secondary-CPICH-Information
                                                                                                                                 PRESENCE optional
      ID id-Active-MBMS-Bearer-ServiceFDD-PFL
                                                        CRITICALITY ignore EXTENSION Active-MBMS-Bearer-Service-ListFDD-PFL
                                                                                                                                 PRESENCE optional
      ID id-EDCH-RLSet-Id
                                                        CRITICALITY ignore EXTENSION RL-Set-ID
                                                                                                                                 PRESENCE optional
      ID id-EDCH-FDD-DL-ControlChannelInformation
                                                        CRITICALITY ignore EXTENSION EDCH-FDD-DL-ControlChannelInformation
                                                                                                                                 PRESENCE optional
      ID id-Initial-DL-DPCH-TimingAdjustment
                                                        CRITICALITY ignore EXTENSION DL-DPCH-TimingAdjustment
                                                                                                                                 PRESENCE optional
      ID id-Neighbouring-E-UTRA-CellInformation
                                                        CRITICALITY ignore EXTENSION Neighbouring-E-UTRA-CellInformation
                                                                                                                                 PRESENCE optional
      ID id-HSDSCH-PreconfigurationInfo
                                                        CRITICALITY ignore EXTENSION HSDSCH-PreconfigurationInfo
                                                                                                                                 PRESENCE optional
      ID id-F-DPCH-SlotFormat
                                                        CRITICALITY ignore EXTENSION F-DPCH-SlotFormat
                                                                                                                                 PRESENCE optional }
                                                        CRITICALITY ignore EXTENSION Non-Serving-RL-Preconfig-Info
      ID id-Non-Serving-RL-Preconfig-Info
                                                                                                                                 PRESENCE optional } |
                                                        CRITICALITY ignore EXTENSION Neighbouring-UMTS-CellInformation-Ext
      ID id-Neighbouring-UMTS-CellInformation-Ext
                                                                                                                                 PRESENCE optional },
DiversityIndication-RL-SetupFailureFDD ::= CHOICE {
    combining
                                    Combining-RL-SetupFailureFDD,
    nonCombiningOrFirstRL
                                NonCombiningOrFirstRL-RL-SetupFailureFDD
```

```
Combining-RL-SetupFailureFDD ::= SEQUENCE {
   rL-ID
   iE-Extensions
                            ProtocolExtensionContainer { { CombiningItem-RL-SetupFailureFDD-ExtIEs} } OPTIONAL,
   . . .
CombiningItem-RL-SetupFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-DCH-InformationResponse
                                      CRITICALITY ignore EXTENSION DCH-InformationResponse
                                                                                                   PRESENCE optional
    ID id-EDCH-FDD-InformationResponse
                                      CRITICALITY ignore EXTENSION EDCH-FDD-InformationResponse
                                                                                                         PRESENCE optional
NonCombiningOrFirstRL-RL-SetupFailureFDD ::= SEQUENCE {
   dCH-InformationResponse
                                      DCH-InformationResponse,
   iE-Extensions
                                      ProtocolExtensionContainer { { NonCombiningOrFirstRLItem-RL-SetupFailureFDD-ExtIEs} } OPTIONAL,
   . . .
NonCombiningOrFirstRLItem-RL-SetupFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   PRESENCE optional
   . . .
RadioLinkSetupFailureFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    -- RADIO LINK SETUP FAILURE TDD
  RadioLinkSetupFailureTDD ::= SEOUENCE {
   protocolIEs
                               ProtocolIE-Container
                                                        {{RadioLinkSetupFailureTDD-IEs}},
   protocolExtensions
                               ProtocolExtensionContainer {{RadioLinkSetupFailureTDD-Extensions}}
                                                                                                           OPTIONAL.
RadioLinkSetupFailureTDD-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-CauseLevel-RL-SetupFailureTDD CRITICALITY ignore TYPE CauseLevel-RL-SetupFailureTDD
                                                                                                   PRESENCE mandatory } |
   { ID id-CriticalityDiagnostics
                                      CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                                   PRESENCE optional
   . . .
CauseLevel-RL-SetupFailureTDD ::= CHOICE {
   generalCause
                    GeneralCauseList-RL-SetupFailureTDD,
   rLSpecificCause
                    RLSpecificCauseList-RL-SetupFailureTDD,
GeneralCauseList-RL-SetupFailureTDD ::= SEQUENCE {
   cause
                            Cause,
```

```
ProtocolExtensionContainer { { GeneralCauseItem-RL-SetupFailureTDD-ExtIEs} }
   iE-Extensions
                                                                                                            OPTIONAL,
GeneralCauseItem-RL-SetupFailureTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
RLSpecificCauseList-RL-SetupFailureTDD ::= SEQUENCE {
   unsuccessful-RL-InformationRespItem-RL-SetupFailureTDD Unsuccessful-RL-InformationRespItem-RL-SetupFailureTDD,
                                                      iE-Extensions
   OPTIONAL,
   . . .
RLSpecificCauseItem-RL-SetupFailureTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   EXTENSION SixtyfourOAM-DL-SupportIndicator
                                                                                                                  PRESENCE optional },
Unsuccessful-RL-InformationRespItem-RL-SetupFailureTDD ::= ProtocolIE-Single-Container { {Unsuccessful-RL-InformationRespItemIE-RL-SetupFailureTDD}
Unsuccessful-RL-InformationRespItemIE-RL-SetupFailureTDD RNSAP-PROTOCOL-IES ::= {
         id-UnsuccessfulRL-InformationResponse-RL-SetupFailureTDD
                                                                    CRITICALITY ignore
                                                                                       TYPE
                                                                                              UnsuccessfulRL-InformationResponse-RL-
SetupFailureTDD
                  PRESENCE
                            mandatory
UnsuccessfulRL-InformationResponse-RL-SetupFailureTDD ::= SEQUENCE {
   rL-ID
                            RL-ID,
   cause
                            ProtocolExtensionContainer { {UnsuccessfulRL-InformationResponse-RL-SetupFailureTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
   . . .
UnsuccessfulRL-InformationResponse-RL-SetupFailureTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RadioLinkSetupFailureTDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
-- RADIO LINK ADDITION REQUEST FDD
  *****************
RadioLinkAdditionRequestFDD ::= SEQUENCE {
                                                         {{RadioLinkAdditionRequestFDD-IEs}},
   protocolIEs
                                ProtocolIE-Container
   protocolExtensions
                                ProtocolExtensionContainer {{RadioLinkAdditionRequestFDD-Extensions}}
                                                                                                               OPTIONAL,
```

```
RadioLinkAdditionRequestFDD-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-UL-SIRTarget
                                        CRITICALITY reject TYPE UL-SIR
                                                                                        PRESENCE mandatory
     ID id-RL-InformationList-RL-AdditionRqstFDD CRITICALITY notify TYPE RL-InformationList-RL-AdditionRqstFDD
                                                                                                                        PRESENCE mandatory
                                                                                                                                               } |
     ID id-Active-Pattern-Sequence-Information CRITICALITY reject TYPE Active-Pattern-Sequence-Information
                                                                                                                  PRESENCE optional },
RL-InformationList-RL-AdditionRgstFDD
                                                ::= SEQUENCE (SIZE (1..maxNrOfRLs-1)) OF ProtocolIE-Single-Container { {RL-Information-RL-
AdditionRqstFDD-IEs} }
RL-Information-RL-AdditionRqstFDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-Information-RL-AdditionRqstFDD CRITICALITY notify TYPE RL-Information-RL-AdditionRqstFDD
                                                                                                                        PRESENCE mandatory
RL-Information-RL-AdditionRgstFDD ::= SEQUENCE {
    rL-ID
                                    RL-ID,
    c-ID
                                    C-ID,
    frameOffset
                                    FrameOffset,
    chipOffset
                                    ChipOffset,
    diversityControlField
                                    DiversityControlField,
                                    PrimaryCPICH-EcNo
    primaryCPICH-EcNo
                                                            OPTIONAL,
    not-Used-sSDT-CellID
                                    NULL
                                                    OPTIONAL,
    transmitDiversitvIndicator
                                    TransmitDiversitvIndicator
                                                                    OPTIONAL,
    iE-Extensions
                                    ProtocolExtensionContainer { {RL-Information-RL-AdditionRqstFDD-ExtIEs} } OPTIONAL,
    . . .
RL-Information-RL-AdditionRqstFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-DLReferencePower
                               CRITICALITY ignore
                                                        EXTENSION DL-Power
                                                                                    PRESENCE optional } |
     ID id-Enhanced-PrimaryCPICH-EcNo
                                                    CRITICALITY ignore EXTENSION Enhanced-PrimaryCPICH-EcNo
                                                                                                                                       PRESENCE
optional
    { ID id-RL-Specific-DCH-Info
                                                    CRITICALITY ignore EXTENSION RL-Specific-DCH-Info
    PRESENCE optional }|
    { ID id-DelayedActivation
                                                    CRITICALITY reject EXTENSION DelayedActivation
    PRESENCE optional }
    { ID id-RL-Specific-EDCH-Information
                                                    CRITICALITY reject EXTENSION RL-Specific-EDCH-Information
                                                                                                                                PRESENCE optional } |
     ID id-EDCH-RL-Indication
                                                    CRITICALITY reject EXTENSION EDCH-RL-Indication
    PRESENCE optional }
    { ID id-SynchronisationIndicator
                                                    CRITICALITY ignore EXTENSION SynchronisationIndicator
                                                                                                                                       PRESENCE
optional }|
     ID id-HSDSCH-PreconfigurationSetup
                                                    CRITICALITY ignore EXTENSION HSDSCH-PreconfigurationSetup
                                                                                                                                PRESENCE optional }
    { ID id-Non-Serving-RL-Preconfig-Setup
                                                    CRITICALITY ignore EXTENSION Non-Serving-RL-Preconfig-Setup
                                                                                                                                PRESENCE optional },
RadioLinkAdditionRequestFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-DPC-Mode
                                                        CRITICALITY reject EXTENSION DPC-Mode
                    PRESENCE optional }
    { ID id-Permanent-NAS-UE-Identity
                                                        CRITICALITY ignore EXTENSION Permanent-NAS-UE-Identity
        PRESENCE optional }
        { ID id-Serving-EDCHRL-Id
                                                        CRITICALITY reject EXTENSION EDCH-Serving-RL
                PRESENCE optional } |
```

```
{ ID id-Initial-DL-DPCH-TimingAdjustment-Allowed
                                                    CRITICALITY ignore EXTENSION Initial-DL-DPCH-TimingAdjustment-Allowed
                                                                                                                               PRESENCE
optional }
    { ID id-HS-DSCH-serving-cell-change-information
                                                    CRITICALITY reject EXTENSION HS-DSCH-serving-cell-change-information
                                                                                                                               PRESENCE
optional }
    { ID id-Serving-cell-change-CFN
                                                    CRITICALITY reject EXTENSION CFN
                  PRESENCE optional }
    { ID id-EDPCH-Information
                                                    CRITICALITY reject EXTENSION EDPCH-Information-RLAdditionReg-FDD
    PRESENCE optional } |
    { ID id-EDCH-FDD-Information
                                                    CRITICALITY reject EXTENSION EDCH-FDD-Information
               PRESENCE optional }
    optional }|
    -- This IE shall be present if E-DPCH Information is present
    { ID id-UE-AggregateMaximumBitRate
                                                    CRITICALITY ignore EXTENSION UE-AggregateMaximumBitRate
       PRESENCE optional }|
    { ID id-Additional-EDCH-Cell-Information-RL-Add-Reg
                                                        CRITICALITY reject EXTENSION Additional-EDCH-Cell-Information-RL-Add-Req
    PRESENCE optional },
Additional-HS-Cell-Information-RL-Addition-List ::= SEQUENCE (SIZE (1..maxNrOfHSDSCH-1)) OF Additional-HS-Cell-Information-RL-Addition-ItemIEs
Additional-HS-Cell-Information-RL-Addition-ItemIEs ::=SEOUENCE{
   hSPDSCH-RL-ID
                                             RL-ID.
   c-ID
                                             C-ID,
   hs-Dsch-Fdd-secondary-serving-Information Hs-Dsch-Fdd-secondary-serving-Information,
   iE-Extensions
                                 ProtocolExtensionContainer { { Additional-HS-Cell-Information-RL-Addition-ItemIEs-ExtIEs} } OPTIONAL,
Additional-HS-Cell-Information-RL-Addition-ItemIEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Additional-EDCH-Cell-Information-RL-Add-Req ::=SEQUENCE{
    setup-Or-Addition-Of-EDCH-On-secondary-UL-Frequency
                                                                           Setup-Or-Addition-Of-EDCH-On-secondary-UL-Frequency,
                                 ProtocolExtensionContainer { { Additional-EDCH-Cell-Information-RL-Add-Reg-ExtIEs} } OPTIONAL,
   iE-Extensions
    . . .
Additional-EDCH-Cell-Information-RL-Add-Req-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Setup-Or-Addition-Of-EDCH-On-secondary-UL-Frequency::= CHOICE {
                  Additional-EDCH-Setup-Info,
   addition
                  Additional-EDCH-Cell-Information-To-Add-List,
EDPCH-Information-RLAdditionReq-FDD::= SEQUENCE
   maxSet-E-DPDCHs
                                             Max-Set-E-DPDCHs,
```

```
ul-PunctureLimit
                                           PunctureLimit,
   e-TFCS-Information
                                           E-TFCS-Information.
   e-TTI
                                           E-TTI.
   e-DPCCH-PO
                                           E-DPCCH-PO,
   e-RGCH-2-IndexStepThreshold
                                           E-RGCH-2-IndexStepThreshold,
   e-RGCH-3-IndexStepThreshold
                                           E-RGCH-3-IndexStepThreshold,
   hARO-Info-for-E-DCH
                                           HARO-Info-for-E-DCH,
   iE-Extensions
                                           ProtocolExtensionContainer { { EDPCH-Information-RLAdditionReg-FDD-ExtIEs} }
                                                                                                                          OPTIONAL,
EDPCH-Information-RLAdditionReq-FDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
{ ID id-HSDSCH-Configured-Indicator
                                    CRITICALITY reject EXTENSION HSDSCH-Configured-Indicator
                                                                                                         PRESENCE mandatory}
-- This shall be present for EDPCH configuration with HSDCH
{ ID id-MinimumReducedE-DPDCH-GainFactor
                                           CRITICALITY ignore EXTENSION MinimumReducedE-DPDCH-GainFactor
                                                                                                         PRESENCE optional },
    -- RADIO LINK ADDITION REQUEST TDD
    RadioLinkAdditionRequestTDD ::= SEQUENCE {
   protocolIEs
                                ProtocolIE-Container
                                                          {{RadioLinkAdditionRequestTDD-IEs}},
                                ProtocolExtensionContainer {{RadioLinkAdditionRequestTDD-Extensions}}
   protocolExtensions
                                                                                                                OPTIONAL,
RadioLinkAdditionRequestTDD-IES RNSAP-PROTOCOL-IES ::= {
   PRESENCE mandatory
   . . .
RL-Information-RL-AdditionRgstTDD ::= SEQUENCE {
                                RL-ID,
   c-ID
                                C-ID,
   frameOffset
                                FrameOffset,
   diversityControlField
                                DiversityControlField,
                                PrimaryCCPCH-RSCP
   primaryCCPCH-RSCP
                                                      OPTIONAL,
   dL-TimeSlot-ISCP-Info
                                DL-TimeSlot-ISCP-Info
                                                      OPTIONAL,
   --for 3.84Mcps TDD only
                                ProtocolExtensionContainer { {RL-Information-RL-AdditionRqstTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
   . . .
RL-Information-RL-AdditionRqstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   { ID id-DL-Timeslot-ISCP-LCR-Information-RL-AdditionRqstTDD CRITICALITY reject
                                                                                  EXTENSION DL-TimeSlot-ISCP-LCR-Information
   PRESENCE optional } |
   --for 1.28Mcps TDD only
     ID id-RL-Specific-DCH-Info
                                                CRITICALITY ignore
                                                                       EXTENSION RL-Specific-DCH-Info
                                                                                                                   PRESENCE optional }
     ID id-DelayedActivation
                                                CRITICALITY reject
                                                                       EXTENSION DelayedActivation
                                                                                                                   PRESENCE optional }
    { ID id-UL-Synchronisation-Parameters-LCR
                                                                       EXTENSION UL-Synchronisation-Parameters-LCR
                                                                                                                   PRESENCE optional }
                                                CRITICALITY reject
```

```
-- Mandatory for 1.28Mcps TDD, Not Applicable to 3.84Mcps TDD or 7.68Mcps TDD
     ID id-PrimaryCCPCH-RSCP-Delta
                                               CRITICALITY ignore
                                                                       EXTENSION PrimaryCCPCH-RSCP-Delta
                                                                                                                    PRESENCE optional }
     ID id-IdleIntervalConfigurationIndicator
                                                CRITICALITY ignore
                                                                       EXTENSION NULL
                                                                                                                    PRESENCE optional }.
RadioLinkAdditionRequestTDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-Permanent-NAS-UE-Identity
                                                       CRITICALITY ignore EXTENSION Permanent-NAS-UE-Identity
                                                                                                              PRESENCE optional |
    ID id-UL-CCTrCH-InformationList-RL-AdditionRqstTDD
                                                      CRITICALITY notify EXTENSION UL-CCTrCH-InformationList-RL-AdditionRqstTDD PRESENCE
optional}|
    { ID id-DL-CCTrCH-InformationList-RL-AdditionRgstTDD
                                                       CRITICALITY notify EXTENSION DL-CCTrCH-InformationList-RL-AdditionRqstTDD
   PRESENCE optional | |
     ID id-HSDSCH-TDD-Information
                                                                                                              PRESENCE optional }
                                                       CRITICALITY reject EXTENSION HSDSCH-TDD-Information
     ID id-HSPDSCH-RL-ID
                                                       CRITICALITY reject EXTENSION RL-ID
                                                                                                              PRESENCE optional}
     ID id-E-DCH-Information
                                                       CRITICALITY reject EXTENSION E-DCH-Information
                                                                                                              PRESENCE optional }
     ID id-E-DCH-Serving-RL-ID
                                                       CRITICALITY reject EXTENSION RL-ID
                                                                                                              PRESENCE optional}
     ID id-E-DCH-768-Information
                                                                                                              PRESENCE optional}
                                                       CRITICALITY reject EXTENSION E-DCH-768-Information
     ID id-E-DCH-LCR-Information
                                                       CRITICALITY reject EXTENSION E-DCH-LCR-Information
                                                                                                              PRESENCE optional}
     ID id-ContinuousPacketConnectivity-DRX-InformationLCR
                                                          CRITICALITY reject EXTENSION ContinuousPacketConnectivity-DRX-InformationLCR
   PRESENCE optional } |
    PRESENCE optional }
   { ID id-E-DCH-Semi-PersistentScheduling-Information-LCR
                                                          CRITICALITY reject EXTENSION E-DCH-Semi-PersistentScheduling-Information-LCR
   PRESENCE optional | |
     ID id-DCH-MeasurementType-Indicator
                                                       CRITICALITY reject EXTENSION DCH-MeasurementType-Indicator PRESENCE optional }
     ID id-Multi-Carrier-EDCH-Setup
                                                       CRITICALITY reject EXTENSION Multi-Carrier-EDCH-Info
                                                                                                              PRESENCE optional }
    ID id-MU-MIMO-Indicator
                                                      CRITICALITY reject EXTENSION MU-MIMO-Indicator
                                                                                                              PRESENCE optional },
   . . .
                                         ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHs)) OF ProtocolIE-Single-Container { {UL-CCTrCH-
UL-CCTrCH-InformationList-RL-AdditionRgstTDD
InformationItemIEs-RL-AdditionRqstTDD} }
UL-CCTrCH-InformationItemIEs-RL-AdditionRqstTDD RNSAP-PROTOCOL-IES ::= {
   PRESENCE
optional },
    . . .
UL-CCTrCH-InformationItem-RL-AdditionRqstTDD ::= SEQUENCE
   cCTrCH-ID
                             CCTrCH-ID,
   uplinkStepSizeLCR
                             TDD-TPC-UplinkStepSize-LCR
                                                        OPTIONAL.
   -- Applicable to 1.28Mcps TDD only
                             ProtocolExtensionContainer { {UL-CCTrCH-InformationItem-RL-AdditionRqstTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
   . . .
UL-CCTrCH-InformationItem-RL-AdditionRqstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-CCTrCH-InformationList-RL-AdditionRgstTDD
                                           ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHs)) OF ProtocolIE-Single-Container { {DL-CCTrCH-
InformationItemIEs-RL-AdditionRgstTDD} }
```

```
DL-CCTrCH-InformationItemIEs-RL-AdditionRqstTDD RNSAP-PROTOCOL-IES ::= {
    { ID id-DL-CCTrCH-InformationItem-RL-AdditionRgstTDD
                                                         CRITICALITY notify TYPE DL-CCTrCH-InformationItem-RL-AdditionRgstTDD
                                                                                                                                  PRESENCE
optional},
DL-CCTrCH-InformationItem-RL-AdditionRqstTDD ::= SEQUENCE
   cCTrCH-ID
                              CCTrCH-ID,
   downlinkStepSize
                              TDD-TPC-DownlinkStepSize OPTIONAL,
   iE-Extensions
                              ProtocolExtensionContainer { {DL-CCTrCH-InformationItem-RL-AdditionRqstTDD-ExtIEs} } OPTIONAL,
DL-CCTrCH-InformationItem-RL-AdditionRqstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
               *****************
-- RADIO LINK ADDITION RESPONSE FDD
__ **********************
RadioLinkAdditionResponseFDD ::= SEOUENCE {
   protocolIEs
                                  ProtocolIE-Container
                                                             {{RadioLinkAdditionResponseFDD-IEs}},
                                  ProtocolExtensionContainer {{RadioLinkAdditionResponseFDD-Extensions}}
   protocolExtensions
                                                                                                                         OPTIONAL,
RadioLinkAdditionResponseFDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-InformationResponseList-RL-AdditionRspFDD
                                                          CRITICALITY ignore TYPE RL-InformationResponseList-RL-AdditionRspFDD
   PRESENCE mandatory } |
    { ID id-CriticalityDiagnostics
                                          CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                              PRESENCE optional
                                                                                                                    },
    . . .
RL-InformationResponseList-RL-AdditionRspFDD
                                                  ::= SEQUENCE (SIZE (1..maxNrOfRLs-1)) OF ProtocolIE-Single-Container { {RL-
InformationResponseItemIEs-RL-AdditionRspFDD} }
RL-InformationResponseItemIEs-RL-AdditionRspFDD RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-InformationResponseItem-RL-AdditionRspFDD
                                                             CRITICALITY ignore TYPE RL-InformationResponseItem-RL-AdditionRspFDD PRESENCE
mandatory }
RL-InformationResponseItem-RL-AdditionRspFDD ::= SEQUENCE
   rL-ID
                                  RL-ID,
   rL-Set-ID
                                  RL-Set-ID,
   uRA-Information
                                  URA-Information
                                                      OPTIONAL,
   sAI
                                  SAI,
   gA-Cell
                                  GA-Cell
                                              OPTIONAL,
   gA-AccessPointPosition
                                  GA-AccessPointPosition OPTIONAL,
   received-total-wide-band-power Received-total-wide-band-power,
   not-Used-secondary-CCPCH-Info
                                          NULL
                                                     OPTIONAL,
   dl-CodeInformation
                                  DL-CodeInformationList-RL-AdditionRspFDD,
```

```
diversityIndication
                                    DiversityIndication-RL-AdditionRspFDD,
    sSDT-SupportIndicator
                                        SSDT-SupportIndicator,
    minUL-SIR
                                        UL-SIR,
    maxUL-SIR
                                        UL-SIR.
    closedlooptimingadjustmentmode
                                        Closedlooptimingadjustmentmode OPTIONAL,
    maximumAllowedULTxPower
                                        MaximumAllowedULTxPower.
    maximumDLTxPower
                                        DL-Power,
    minimumDLTxPower
                                        DL-Power,
    neighbouring-UMTS-CellInformation
                                        Neighbouring-UMTS-CellInformation OPTIONAL,
    neighbouring-GSM-CellInformation
                                        Neighbouring-GSM-CellInformation OPTIONAL,
    pC-Preamble
                                        PC-Preamble,
    sRB-Delav
                                        SRB-Delay,
    primaryCPICH-Power
                                        PrimaryCPICH-Power,
    iE-Extensions
                                        ProtocolExtensionContainer { {RL-InformationResponseItem-RL-AdditionRspFDD-ExtIEs} } OPTIONAL,
RL-InformationResponseItem-RL-AdditionRspFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-GA-CellAdditionalShapes
                                                    CRITICALITY ignore EXTENSION GA-CellAdditionalShapes
                                                                                                                                PRESENCE optional }
     ID id-DL-PowerBalancing-ActivationIndicator
                                                    CRITICALITY ignore EXTENSION DL-PowerBalancing-ActivationIndicator
                                                                                                                                PRESENCE optional
     ID id-HCS-Prio
                                                    CRITICALITY ignore EXTENSION HCS-Prio
                                                                                                                                PRESENCE optional
     ID id-Active-MBMS-Bearer-ServiceFDD-PFL
                                                    CRITICALITY ignore EXTENSION Active-MBMS-Bearer-Service-ListFDD-PFL
                                                                                                                                PRESENCE optional
     ID id-EDCH-RLSet-Id
                                                    CRITICALITY ignore
                                                                        EXTENSION RL-Set-ID
                                                                                                                                PRESENCE optional
     ID id-EDCH-FDD-DL-ControlChannelInformation
                                                    CRITICALITY ignore EXTENSION EDCH-FDD-DL-ControlChannelInformation
                                                                                                                                PRESENCE optional
     ID id-Initial-DL-DPCH-TimingAdjustment
                                                    CRITICALITY ignore EXTENSION DL-DPCH-TimingAdjustment
                                                                                                                                PRESENCE optional
     ID id-F-DPCH-SlotFormat
                                                                        EXTENSION F-DPCH-SlotFormat
                                                                                                                                PRESENCE optional
                                                    CRITICALITY ignore
     ID id-Neighbouring-E-UTRA-CellInformation
                                                    CRITICALITY ignore EXTENSION Neighbouring-E-UTRA-CellInformation
                                                                                                                                PRESENCE optional
     ID id-HSDSCH-PreconfigurationInfo
                                                                        EXTENSION HSDSCH-PreconfigurationInfo
                                                    CRITICALITY ignore
                                                                                                                                PRESENCE optional
     ID id-Non-Serving-RL-Preconfig-Info
                                                    CRITICALITY ignore EXTENSION Non-Serving-RL-Preconfig-Info
                                                                                                                                PRESENCE optional }
     ID id-Neighbouring-UMTS-CellInformation-Ext
                                                                        EXTENSION Neighbouring-UMTS-CellInformation-Ext
                                                    CRITICALITY ignore
                                                                                                                                PRESENCE optional },
DL-CodeInformationList-RL-AdditionRspFDD ::= ProtocolIE-Single-Container {{ DL-CodeInformationListIEs-RL-AdditionRspFDD }}
DL-CodeInformationListIEs-RL-AdditionRspFDD RNSAP-PROTOCOL-IES ::= {
    ID id-FDD-DL-CodeInformation CRITICALITY ignore TYPE FDD-DL-CodeInformation
                                                                                        PRESENCE mandatory }
DiversityIndication-RL-AdditionRspFDD ::= CHOICE {
    combining
                                    Combining-RL-AdditionRspFDD,
    nonCombining
                                    NonCombining-RL-AdditionRspFDD
Combining-RL-AdditionRspFDD ::= SEQUENCE {
    rL-ID
    iE-Extensions
                                ProtocolExtensionContainer { { CombiningItem-RL-AdditionRspFDD-ExtIEs} } OPTIONAL,
CombiningItem-RL-AdditionRspFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-DCH-InformationResponse
                                            CRITICALITY ignore EXTENSION DCH-InformationResponse
                                                                                                                PRESENCE optional
     ID id-EDCH-FDD-InformationResponse
                                            CRITICALITY ignore EXTENSION EDCH-FDD-InformationResponse
                                                                                                                        PRESENCE optional
```

```
NonCombining-RL-AdditionRspFDD ::= SEQUENCE {
   dCH-InformationResponse
                                         DCH-InformationResponse,
                                             ProtocolExtensionContainer { { NonCombiningItem-RL-AdditionRspFDD-ExtIEs} } OPTIONAL,
   iE-Extensions
   . . .
NonCombiningItem-RL-AdditionRspFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   { ID id-EDCH-FDD-InformationResponse
                                         CRITICALITY ignore EXTENSION EDCH-FDD-InformationResponse
                                                                                                                 PRESENCE optional
                                                                                                                                      },
   . . .
RadioLinkAdditionResponseFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-HS-DSCH-serving-cell-change-informationResponse CRITICALITY ignore EXTENSION HS-DSCH-serving-cell-change-informationResponse
       PRESENCE optional |
     PRESENCE optional |
    { ID id-MAChs-ResetIndicator
                                                        CRITICALITY ignore EXTENSION MAChs-ResetIndicator
                          PRESENCE optional } |
   { ID id-Additional-HS-Cell-Change-Information-Response CRITICALITY ignore EXTENSION Additional-HS-Cell-Change-Information-Response-List
   PRESENCE optional } |
   { ID id-Additional-EDCH-Cell-Information-Response-RLAdd CRITICALITY ignore EXTENSION Additional-EDCH-Cell-Information-Response-RLAddList
   PRESENCE optional },
   . . .
Additional-HS-Cell-Change-Information-Response-List ::= SEQUENCE (SIZE (1..maxNrOfHSDSCH-1)) OF Additional-HS-Cell-Change-Information-Response-
ItemIEs
Additional-HS-Cell-Change-Information-Response-ItemIEs ::=SEQUENCE{
   hSPDSCH-RL-ID
                                                            RL-ID,
   hSDSCH-RNTI
                                                            HSDSCH-RNTI,
   hS-DSCH-Secondary-Serving-Cell-Change-Information-Response HS-DSCH-Secondary-Serving-Cell-Change-Information-Response,
                                 ProtocolExtensionContainer { { Additional-HS-Cell-Change-Information-Response-ItemIEs-ExtIEs} } OPTIONAL,
   iE-Extensions
Additional-HS-Cell-Change-Information-Response-ItemIEs-ExtIES RNSAP-PROTOCOL-EXTENSION ::=
-- RADIO LINK ADDITION RESPONSE TDD
RadioLinkAdditionResponseTDD ::= SEQUENCE {
                                                           {{RadioLinkAdditionResponseTDD-IEs}},
   protocolIEs
                                 ProtocolIE-Container
```

```
ProtocolExtensionContainer {{RadioLinkAdditionResponseTDD-Extensions}}
    protocolExtensions
                                                                                                                        OPTIONAL,
RadioLinkAdditionResponseTDD-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-RL-InformationResponse-RL-AdditionRspTDD
                                                         CRITICALITY ignore TYPE RL-InformationResponse-RL-AdditionRspTDD PRESENCE optional
    -- Mandatory for 3.84Mcps TDD only
    { ID id-CriticalityDiagnostics
                                          CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                              PRESENCE optional
                                                                                                                   },
   . . .
RL-InformationResponse-RL-AdditionRspTDD ::= SEQUENCE {
    rL-ID
                                      RL-ID,
    uRA-Information
                                      URA-Information
                                                          OPTIONAL,
    SΔT
                                      SAI.
   qA-Cell
                                      GA-Cell
                                                  OPTIONAL,
    qA-AccessPointPosition
                                      GA-AccessPointPosition OPTIONAL,
    ul-TimeSlot-ISCP-Info
                                      UL-TimeSlot-ISCP-Info,
   minUL-SIR
                                      UL-SIR,
   maxUL-SIR
                                      UL-SIR,
   maximumAllowedULTxPower
                                      MaximumAllowedULTxPower,
   maximumDLTxPower
                                      DL-Power,
   minimumDLTxPower
                                      DL-Power,
   pCCPCH-Power
                                      PCCPCH-Power,
    timingAdvanceApplied
                                      TimingAdvanceApplied,
    alphaValue
                                      AlphaValue,
    ul-PhysCH-SF-Variation
                                      UL-PhysCH-SF-Variation,
    synchronisationConfiguration
                                      SynchronisationConfiguration,
    secondary-CCPCH-Info-TDD
                                      Secondary-CCPCH-Info-TDD
                                                                                    OPTIONAL,
    ul-CCTrCHInformation
                                      UL-CCTrCHInformationList-RL-AdditionRspTDD
                                                                                    OPTIONAL,
   dl-CCTrCHInformation
                                      DL-CCTrCHInformationList-RL-AdditionRspTDD
                                                                                    OPTIONAL,
    dCH-Information
                                      DCH-Information-RL-AdditionRspTDD
                                                                                    OPTIONAL,
                                      DSCH-InformationResponse-RL-AdditionRspTDD
   dSCH-InformationResponse
                                                                                    OPTIONAL,
                                      USCH-InformationResponse-RL-AdditionRspTDD
    uSCH-InformationResponse
                                                                                    OPTIONAL,
                                      Neighbouring-UMTS-CellInformation OPTIONAL,
    neighbouring-UMTS-CellInformation
   neighbouring-GSM-CellInformation
                                      Neighbouring-GSM-CellInformation OPTIONAL,
   iE-Extensions
                                      ProtocolExtensionContainer { {RL-InformationResponse-RL-AdditionRspTDD-ExtIEs} } OPTIONAL,
RL-InformationResponse-RL-AdditionRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-GA-CellAdditionalShapes
                                                  CRITICALITY ignore EXTENSION GA-CellAdditionalShapes
                                                                                                                           PRESENCE optional }
     ID id-HCS-Prio
                                                  CRITICALITY ignore EXTENSION HCS-Prio
                                                                                                                           PRESENCE optional }
     ID id-Neighbouring-E-UTRA-CellInformation
                                                  CRITICALITY ignore EXTENSION Neighbouring-E-UTRA-CellInformation
                                                                                                                           PRESENCE optional }
     PRESENCE optional },
UL-CCTrCHInformationList-RL-AdditionRspTDD ::= ProtocolIE-Single-Container {{UL-CCTrCHInformationListIEs-RL-AdditionRspTDD}}
UL-CCTrCHInformationListIEs-RL-AdditionRspTDD RNSAP-PROTOCOL-IES ::= {
    { ID id-UL-CCTrCH-InformationListIE-RL-AdditionRspTDD CRITICALITY ignore TYPE UL-CCTrCHInformationListIE-RL-AdditionRspTDD
    PRESENCE mandatory }
```

```
UL-CCTrCHInformationListIE-RL-AdditionRspTDD ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHs)) OF UL-CCTrCHInformationItem-RL-AdditionRspTDD
UL-CCTrCHInformationItem-RL-AdditionRspTDD ::= SEQUENCE {
    cCTrCH-ID
                              CCTrCH-ID,
   ul-DPCH-Information
                                 UL-DPCH-InformationList-RL-AdditionRspTDD
                                                                               OPTIONAL.
                                  ProtocolExtensionContainer { {UL-CCTrCHInformationItem-RL-AdditionRspTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
UL-CCTrCHInformationItem-RL-AdditionRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UL-DPCH-InformationList-RL-AdditionRspTDD ::= ProtocolIE-Single-Container { {UL-DPCH-InformationListIEs-RL-AdditionRspTDD} }
UL-DPCH-InformationListIEs-RL-AdditionRspTDD RNSAP-PROTOCOL-IES ::= {
     ID id-UL-DPCH-InformationItem-RL-AdditionRspTDD
                                                        CRITICALITY ignore TYPE UL-DPCH-InformationItem-RL-AdditionRspTDD PRESENCE mandatory
UL-DPCH-InformationItem-RL-AdditionRspTDD ::= SEQUENCE {
   repetitionPeriod
                                 RepetitionPeriod,
   repetitionLength
                                 RepetitionLength,
    tDD-DPCHOffset
                                 TDD-DPCHOffset,
                                 UL-Timeslot-Information,
   uL-Timeslot-Information
   iE-Extensions
                                  ProtocolExtensionContainer { {UL-DPCH-InformationItem-RL-AdditionRspTDD-ExtIEs} } OPTIONAL,
UL-DPCH-InformationItem-RL-AdditionRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-CCTrCHInformationList-RL-AdditionRspTDD ::= ProtocolIE-Single-Container {{DL-CCTrCHInformationListIEs-RL-AdditionRspTDD}}
DL-CCTrCHInformationListIEs-RL-AdditionRspTDD RNSAP-PROTOCOL-IES ::= {
    PRESENCE mandatory }
DL-CCTrCHInformationListIE-RL-AdditionRspTDD ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHs)) OF DL-CCTrCHInformationItem-RL-AdditionRspTDD
DL-CCTrCHInformationItem-RL-AdditionRspTDD ::= SEQUENCE {
   cCTrCH-ID
                              CCTrCH-ID,
   dl-DPCH-Information
                                  DL-DPCH-InformationList-RL-AdditionRspTDD
                                  ProtocolExtensionContainer { {DL-CCTrCHInformationItem-RL-AdditionRspTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
DL-CCTrCHInformationItem-RL-AdditionRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-CCTrCH-Maximum-DL-Power-RL-AdditionRspTDD
                                                        CRITICALITY ignore
                                                                                                    PRESENCE optional
                                                                                                                       } | -- this is a DCH
                                                                               EXTENSION DL-Power
type CCTrCH power
```

```
PRESENCE optional
                                                                                                                               }, -- this is a DCH
    { ID id-CCTrCH-Minimum-DL-Power-RL-AdditionRspTDD
                                                            CRITICALITY ignore
                                                                                     EXTENSION DL-Power
type CCTrCH power
    . . .
DL-DPCH-InformationList-RL-AdditionRspTDD ::= ProtocolIE-Single-Container { {DL-DPCH-InformationListIEs-RL-AdditionRspTDD} }
DL-DPCH-InformationListIEs-RL-AdditionRspTDD RNSAP-PROTOCOL-IES ::= {
     ID id-DL-DPCH-InformationItem-RL-AdditionRspTDD
                                                            CRITICALITY ignore TYPE DL-DPCH-InformationItem-RL-AdditionRspTDD PRESENCE mandatory
DL-DPCH-InformationItem-RL-AdditionRspTDD ::= SEQUENCE {
    repetitionPeriod
                                    RepetitionPeriod,
    repetitionLength
                                    RepetitionLength,
    tDD-DPCHOffset
                                    TDD-DPCHOffset,
    dL-Timeslot-Information
                                    DL-Timeslot-Information,
    iE-Extensions
                                    ProtocolExtensionContainer { {DL-DPCH-InformationItem-RL-AdditionRspTDD-ExtIEs} } OPTIONAL,
    . . .
DL-DPCH-InformationItem-RL-AdditionRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DCH-Information-RL-AdditionRspTDD ::= SEQUENCE {
    diversityIndication
                                        DiversityIndication-RL-AdditionRspTDD,
                                    ProtocolExtensionContainer { { DCH-Information-RL-AdditionRspTDD-ExtIEs} } OPTIONAL,
    iE-Extensions
DCH-Information-RL-AdditionRspTDD-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
DiversityIndication-RL-AdditionRspTDD ::= CHOICE {
                    Combining-RL-AdditionRspTDD,
    combining
    nonCombining
                   NonCombining-RL-AdditionRspTDD
Combining-RL-AdditionRspTDD ::= SEQUENCE {
    rL-ID
    iE-Extensions
                                ProtocolExtensionContainer { { CombiningItem-RL-AdditionRspTDD-ExtIEs} } OPTIONAL,
    . . .
CombiningItem-RL-AdditionRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-DCH-InformationResponse
                                            CRITICALITY ignore EXTENSION DCH-InformationResponse
                                                                                                                 PRESENCE optional
    . . .
NonCombining-RL-AdditionRspTDD ::= SEQUENCE {
    dCH-InformationResponse
                                DCH-InformationResponse,
```

```
ProtocolExtensionContainer { { NonCombiningItem-RL-AdditionRspTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
NonCombiningItem-RL-AdditionRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DSCH-InformationResponse-RL-AdditionRspTDD ::= ProtocolIE-Single-Container {{DSCH-InformationListIEs-RL-AdditionRspTDD}}
DSCH-InformationListIEs-RL-AdditionRspTDD RNSAP-PROTOCOL-IES ::= {
   { ID id-DSCH-InformationListIE-RL-AdditionRspTDD
                                                  CRITICALITY ignore TYPE DSCH-InformationListIE-RL-AdditionRspTDD
                                                                                                                               PRESENCE
mandatory }
DSCH-InformationListIE-RL-AdditionRspTDD ::= SEQUENCE (SIZE(0..maxNoOfDSCHs)) OF DSCHInformationItem-RL-AdditionRspTDD
DSCHInformationItem-RL-AdditionRspTDD ::= SEQUENCE
   dsch-ID
                          DSCH-ID,
   transportFormatManagement TransportFormatManagement,
   dSCH-FlowControlInformation
                                 DSCH-FlowControlInformation,
                       DiversityIndication-RL-AdditionRspTDD2 OPTIONAL,
   diversityIndication
   -- diversityIndication present, if CHOICE = nonCombining
   iE-Extensions
                         ProtocolExtensionContainer { {DSCHInformationItem-RL-AdditionRspTDD-ExtIEs} } OPTIONAL,
DSCHInformationItem-RL-AdditionRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DiversityIndication-RL-AdditionRspTDD2 ::= SEQUENCE {
   bindingID
                         BindingID OPTIONAL,
   transportLayerAddress TransportLayerAddress OPTIONAL,
   iE-Extensions
                         ProtocolExtensionContainer { { DiversityIndication-RL-AdditionRspTDD2-ExtIEs} } OPTIONAL,
DiversityIndication-RL-AdditionRspTDD2-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
USCH-InformationResponse-RL-AdditionRspTDD ::= ProtocolIE-Single-Container {{USCH-InformationListIEs-RL-AdditionRspTDD}}
USCH-InformationListIEs-RL-AdditionRspTDD RNSAP-PROTOCOL-IES ::= {
   PRESENCE
mandatory }
USCH-InformationListIE-RL-AdditionRspTDD ::= SEQUENCE (SIZE(0..maxNoOfUSCHs)) OF USCHInformationItem-RL-AdditionRspTDD
USCHInformationItem-RL-AdditionRspTDD ::= SEQUENCE {
   uSCH-ID
                          USCH-ID,
   transportFormatManagement TransportFormatManagement,
   diversityIndication
                         DiversityIndication-RL-AdditionRspTDD2 OPTIONAL,
```

```
-- diversityIndication present, if CHOICE = nonCombining
    iE-Extensions
                            ProtocolExtensionContainer { {USCHInformationItem-RL-AdditionRspTDD-ExtIEs} } OPTIONAL,
    . . .
USCHInformationItem-RL-AdditionRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RadioLinkAdditionResponseTDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-RL-LCR-InformationResponse-RL-AdditionRspTDD
                                                            CRITICALITY ignore EXTENSION RL-LCR-InformationResponse-RL-AdditionRspTDD
    PRESENCE optional }
    -- Mandatory for 1.28Mcps TDD only
     ID id-Active-MBMS-Bearer-ServiceTDD-PFL
                                                    CRITICALITY ignore EXTENSION Active-MBMS-Bearer-Service-ListTDD-PFL
                                                                                                                                 PRESENCE optional }
                                                    CRITICALITY ignore EXTENSION HSDSCH-TDD-Information-Response
      ID id-HSDSCH-TDD-Information-Response
                                                                                                                                 PRESENCE optional }
      ID id-DSCH-RNTI
                                                    CRITICALITY ignore EXTENSION DSCH-RNTI
                                                                                                                                 PRESENCE optional}
     ID id-RL-InformationResponse-RL-AdditionRspTDD768 CRITICALITY ignore EXTENSION RL-InformationResponse-RL-AdditionRspTDD768
                                                                                                                                         PRESENCE
optional}
                                                    CRITICALITY ignore EXTENSION E-DCH-Information-Response
                                                                                                                                 PRESENCE optional }
      ID id-E-DCH-Information-Response
      ID id-E-DCH-768-Information-Response
                                                    CRITICALITY ignore EXTENSION E-DCH-768-Information-Response
                                                                                                                                 PRESENCE optional }
      ID id-E-DCH-LCR-Information-Response
                                                    CRITICALITY ignore EXTENSION E-DCH-LCR-Information-Response
                                                                                                                                 PRESENCE optional}
     ID id-ContinuousPacketConnectivity-DRX-Information-ResponseLCR
                                                                         CRITICALITY ignore EXTENSION ContinuousPacketConnectivity-DRX-Information-
                PRESENCE optional } |
ResponseLCR
    { ID id-HS-DSCH-Semi-PersistentScheduling-Information-ResponseLCR
                                                                         CRITICALITY ignore EXTENSION HS-DSCH-Semi-PersistentScheduling-
                           PRESENCE optional } |
Information-ResponseLCR
    { ID id-E-DCH-Semi-PersistentScheduling-Information-ResponseLCR
                                                                         CRITICALITY ignore EXTENSION E-DCH-Semi-PersistentScheduling-Information-
ResponseLCR PRESENCE optional } |
      ID id-DCH-MeasurementOccasion-Information
                                                    CRITICALITY reject
                                                                        EXTENSION DCH-MeasurementOccasion-Information
                                                                                                                                 PRESENCE optional }
      ID id-Multi-Carrier-EDCH-Response
                                                                                                                                 PRESENCE optional }
                                                    CRITICALITY ignore
                                                                        EXTENSION Multi-Carrier-EDCH-Information-Response
     ID id-MU-MIMO-InformationLCR
                                                                                                                                 PRESENCE optional },
                                                    CRITICALITY reject
                                                                        EXTENSION MU-MIMO-InformationLCR
    . . .
RL-LCR-InformationResponse-RL-AdditionRspTDD ::= SEQUENCE {
    rI.-ID
                                RL-ID.
    uRA-Information
                                URA-Information,
    sAI
                                SAI,
                                GA-Cell
    qA-Cell
                                            OPTIONAL,
    qA-AccessPointPosition
                                GA-AccessPointPosition OPTIONAL,
    ul-TimeSlot-ISCP-LCR-Info
                                UL-TimeSlot-ISCP-LCR-Info,
    maxUL-SIR
                                UL-SIR,
    minUL-SIR
                                UL-SIR.
    pCCPCH-Power
                                PCCPCH-Power,
    maximumAllowedULTxPower
                                MaximumAllowedULTxPower,
    maximumDLTxPower
                                DL-Power,
    minimumDLTxPower
                                DL-Power,
    alphaValue
                                AlphaValue,
    ul-PhysCH-SF-Variation
                                UL-PhysCH-SF-Variation,
    synchronisationConfiguration
                                        SynchronisationConfiguration,
    secondary-LCR-CCPCH-Info-TDD
                                        Secondary-LCR-CCPCH-Info-TDD
                                                                                             OPTIONAL,
    ul-CCTrCH-LCR-Information
                                        UL-CCTrCH-LCR-InformationList-RL-AdditionRspTDD
                                                                                             OPTIONAL,
    dl-CCTrCH-LCR-Information
                                        DL-CCTrCH-LCR-InformationList-RL-AdditionRspTDD
                                                                                             OPTIONAL,
    dCH-InformationResponse
                                        DCH-InformationResponseList-RL-AdditionRspTDD
                                                                                             OPTIONAL,
                                        DSCH-LCR-InformationResponse-RL-AdditionRspTDD
    dsch-LCR-InformationResponse
```

```
usch-LCR-InformationResponse
                                      USCH-LCR-InformationResponse-RL-AdditionRspTDD OPTIONAL,
   neighbouring-UMTS-CellInformation
                                          Neighbouring-UMTS-CellInformation OPTIONAL,
   neighbouring-GSM-CellInformation
                                          Neighbouring-GSM-CellInformation
                                                                                  OPTIONAL.
   iE-Extensions
                                          OPTIONAL.
RL-LCR-InformationResponseList-RL-AdditionRspTDD-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-GA-CellAdditionalShapes
                                             CRITICALITY ignore EXTENSION GA-CellAdditionalShapes
                                                                                                                PRESENCE optional }
     ID id-HCS-Prio
                                              CRITICALITY ignore EXTENSION HCS-Prio
                                                                                                                PRESENCE optional }
                                                                                                                PRESENCE optional }
   { ID id-UL-TimingAdvanceCtrl-LCR
                                              CRITICALITY ignore EXTENSION UL-TimingAdvanceCtrl-LCR
   -- Mandatory for 1.28Mcps TDD only
   { ID id-PowerControlGAP
                                              CRITICALITY ignore EXTENSION ControlGAP
                                                                                                                PRESENCE optional } |
   -- Applicable to 1.28Mcps TDD only
   { ID id-UARFCNforNt
                                              CRITICALITY ignore EXTENSION UARFON
                                                                                                                PRESENCE optional } |
   -- Applicable to 1.28Mcps TDD only
     ID id-Neighbouring-E-UTRA-CellInformation
                                             CRITICALITY ignore EXTENSION Neighbouring-E-UTRA-CellInformation
                                                                                                                PRESENCE optional } |
     ID id-IdleIntervalInformation
                                             CRITICALITY ignore EXTENSION IdleIntervalInformation
                                                                                                                PRESENCE optional }
   PRESENCE optional },
   . . .
UL-CCTrCH-LCR-InformationList-RL-AdditionRspTDD ::= ProtocolIE-Single-Container {{UL-CCTrCH-LCR-InformationListIEs-RL-AdditionRspTDD }}
UL-CCTrCH-LCR-InformationListIEs-RL-AdditionRspTDD RNSAP-PROTOCOL-IES ::= {
   PRESENCE mandatory }
UL-CCTrCH-LCR-InformationListIE-RL-AdditionRspTDD ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHsLCR)) OF UL-CCTrCH-LCR-InformationItem-RL-AdditionRspTDD
UL-CCTrCH-LCR-InformationItem-RL-AdditionRspTDD ::= SEQUENCE {
   cCTrCH-ID
                            CCTrCH-ID,
   ul-DPCH-LCR-Information
                                   UL-DPCH-LCR-InformationList-RL-AdditionRspTDD
                                                                                 OPTIONAL,
   iE-Extensions
                               ProtocolExtensionContainer { {UL-CCTrCH-LCR-InformationItem-RL-AdditionRspTDD-ExtIEs} } OPTIONAL,
UL-CCTrCH-LCR-InformationItem-RL-AdditionRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UL-DPCH-LCR-InformationList-RL-AdditionRspTDD ::= ProtocolIE-Single-Container { {UL-DPCH-LCR-InformationListIEs-RL-AdditionRspTDD} }
UL-DPCH-LCR-InformationListIEs-RL-AdditionRspTDD RNSAP-PROTOCOL-IES ::= {
   { ID id-UL-DPCH-LCR-InformationItem-RL-AdditionRspTDD
                                                        CRITICALITY ignore TYPE UL-DPCH-LCR-InformationItem-RL-AdditionRspTDD PRESENCE
mandatory }
UL-DPCH-LCR-InformationItem-RL-AdditionRspTDD ::= SEQUENCE {
   repetitionPeriod
                               RepetitionPeriod,
   repetitionLength
                               RepetitionLength,
                               TDD-DPCHOffset,
   tDD-DPCHOffset
```

```
uL-TimeslotLCR-Information
                                UL-TimeslotLCR-Information,
   iE-Extensions
                                ProtocolExtensionContainer { {UL-DPCH-LCR-InformationItem-RL-AdditionRspTDD-ExtIEs} } OPTIONAL,
UL-DPCH-LCR-InformationItem-RL-AdditionRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-CCTrCH-LCR-InformationList-RL-AdditionRspTDD ::= ProtocolIE-Single-Container {{DL-CCTrCH-LCR-InformationListIEs-RL-AdditionRspTDD}}
DL-CCTrCH-LCR-InformationListIEs-RL-AdditionRspTDD RNSAP-PROTOCOL-IES ::= {
   PRESENCE mandatory }
DL-CCTrCH-LCR-InformationListIE-RL-AdditionRspTDD ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHsLCR)) OF DL-CCTrCH-LCR-InformationItem-RL-AdditionRspTDD
DL-CCTrCH-LCR-InformationItem-RL-AdditionRspTDD ::= SEQUENCE {
   cCTrCH-ID
                            CCTrCH-ID,
   dl-DPCH-LCR-Information DL-DPCH-LCR-InformationList-RL-AdditionRspTDD
                                                                           OPTIONAL,
                            ProtocolExtensionContainer { {DL-CCTrCH-LCR-InformationItem-RL-AdditionRspTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
DL-CCTrCH-LCR-InformationItem-RL-AdditionRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-DPCH-LCR-InformationList-RL-AdditionRspTDD ::= ProtocolIE-Single-Container { {DL-DPCH-LCR-InformationListIEs-RL-AdditionRspTDD} }
DL-DPCH-LCR-InformationListIEs-RL-AdditionRspTDD RNSAP-PROTOCOL-IES ::= {
   { ID id-DL-DPCH-LCR-InformationItem-RL-AdditionRspTDD
                                                         CRITICALITY ignore TYPE DL-DPCH-LCR-InformationItem-RL-AdditionRspTDD PRESENCE
mandatory }
DL-DPCH-LCR-InformationItem-RL-AdditionRspTDD ::= SEQUENCE {
   repetitionPeriod
                                RepetitionPeriod,
   repetitionLength
                                RepetitionLength,
   tDD-DPCHOffset
                                TDD-DPCHOffset,
   dL-TimeslotLCR-Information
                                DL-TimeslotLCR-Information,
   tSTD-Indicator
                                TSTD-Indicator,
                                ProtocolExtensionContainer { {DL-DPCH-LCR-InformationItem-RL-AdditionRspTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
DL-DPCH-LCR-InformationItem-RL-AdditionRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DCH-InformationResponseList-RL-AdditionRspTDD ::= ProtocolIE-Single-Container {{DCH-InformationResponseListIEs-RL-AdditionRspTDD}}
DCH-InformationResponseListIEs-RL-AdditionRspTDD RNSAP-PROTOCOL-IES ::= {
```

```
DSCH-LCR-InformationResponse-RL-AdditionRspTDD ::= ProtocolIE-Single-Container {{DSCH-LCR-InformationList-RL-AdditionRspTDD}}
DSCH-LCR-InformationList-RL-AdditionRspTDD RNSAP-PROTOCOL-IES ::= {
    { ID id-DSCH-LCR-InformationListIEs-RL-AdditionRspTDD
                                                                CRITICALITY ignore TYPE DSCH-LCR-InformationListIEs-RL-AdditionRspTDD PRESENCE
mandatory }
DSCH-LCR-InformationListIEs-RL-AdditionRspTDD ::= SEQUENCE (SIZE(0..maxNoOfDSCHsLCR)) OF DSCH-LCR-InformationItem-RL-AdditionRspTDD
DSCH-LCR-InformationItem-RL-AdditionRspTDD ::= SEQUENCE {
    dsch-ID
                            DSCH-ID,
    dSCH-FlowControlInformation
                                    DSCH-FlowControlInformation,
    bindingID
                           BindingID OPTIONAL,
    transportLayerAddress TransportLayerAddress
                                                   OPTIONAL,
    transportFormatManagement TransportFormatManagement,
    iE-Extensions
                            ProtocolExtensionContainer { {DSCH-LCR-InformationItem-RL-AdditionRspTDD-ExtIEs} } OPTIONAL,
    . . .
DSCH-LCR-InformationItem-RL-AdditionRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
USCH-LCR-InformationResponse-RL-AdditionRspTDD ::= ProtocolIE-Single-Container {{USCH-LCR-InformationList-RL-AdditionRspTDD}}
USCH-LCR-InformationList-RL-AdditionRspTDD RNSAP-PROTOCOL-IES ::= {
    { ID id-USCH-LCR-InformationListIEs-RL-AdditionRspTDD
                                                                CRITICALITY ignore TYPE USCH-LCR-InformationListIEs-RL-AdditionRspTDD PRESENCE
mandatory }
USCH-LCR-InformationListIEs-RL-AdditionRspTDD ::= SEQUENCE (SIZE(0..maxNoOfUSCHsLCR)) OF USCH-LCR-InformationItem-RL-AdditionRspTDD
USCH-LCR-InformationItem-RL-AdditionRspTDD ::= SEQUENCE {
    usch-ID
                                USCH-ID,
    transportFormatManagement TransportFormatManagement,
    diversityIndication
                                DiversityIndication-RL-AdditionRspTDD2
                                                                            OPTIONAL,
    iE-Extensions
                                ProtocolExtensionContainer { {USCH-LCR-InformationItem-RL-AdditionRspTDD-ExtIEs} } OPTIONAL,
    . . .
USCH-LCR-InformationItem-RL-AdditionRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RL-InformationResponse-RL-AdditionRspTDD768 ::= SEQUENCE {
    rL-ID
                                        RL-ID,
    uRA-Information
                                        URA-Information
                                                            OPTIONAL,
    SAT
                                        SAI,
    qA-Cell
                                        GA-Cell
                                                    OPTIONAL,
    gA-AccessPointPosition
                                        GA-AccessPointPosition OPTIONAL,
    ul-TimeSlot-ISCP-Info
                                        UL-TimeSlot-ISCP-Info,
    minUL-SIR
                                        UL-SIR,
```

```
maxUL-SIR
                                    UL-SIR,
   maximumAllowedULTxPower
                                    MaximumAllowedULTxPower,
   maximumDLTxPower
                                    DL-Power.
   minimumDLTxPower
                                    DL-Power,
   pCCPCH-Power
                                    PCCPCH-Power,
   timingAdvanceApplied
                                    TimingAdvanceApplied,
   alphaValue
                                    AlphaValue,
   ul-PhysCH-SF-Variation
                                    UL-PhysCH-SF-Variation,
   synchronisationConfiguration
                                    SynchronisationConfiguration,
   secondary-CCPCH-Info-TDD768
                                    Secondary-CCPCH-Info-TDD768
                                                                                OPTIONAL,
   ul-CCTrCHInformation768
                                    UL-CCTrCHInformationList-RL-AdditionRspTDD768
                                                                                    OPTIONAL,
   dl-CCTrCHInformation768
                                    DL-CCTrCHInformationList-RL-AdditionRspTDD768
                                                                                    OPTIONAL,
                                    DCH-Information-RL-AdditionRspTDD
   dCH-Information
                                                                                OPTIONAL,
   dSCH-InformationResponse
                                    DSCH-InformationResponse-RL-AdditionRspTDD
                                                                                OPTIONAL,
   uSCH-InformationResponse
                                    USCH-InformationResponse-RL-AdditionRspTDD
                                                                                OPTIONAL,
   neighbouring-UMTS-CellInformation
                                    Neighbouring-UMTS-CellInformation OPTIONAL,
   neighbouring-GSM-CellInformation
                                    Neighbouring-GSM-CellInformation OPTIONAL,
   qA-CellAdditionalShapes
                                    GA-CellAdditionalShapes
                                                                  OPTIONAL,
                                    HCS-Prio
   hCS-Prio
                                                                  OPTIONAL,
   iE-Extensions
                                    ProtocolExtensionContainer { {RL-InformationResponse-RL-AdditionRspTDD768-ExtIEs} } OPTIONAL,
RL-InformationResponse-RL-AdditionRspTDD768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-Neighbouring-E-UTRA-CellInformation
                                               CRITICALITY ignore EXTENSION Neighbouring-E-UTRA-CellInformation
                                                                                                                    PRESENCE optional } |
    PRESENCE optional },
   . . .
UL-CCTrCHInformationList-RL-AdditionRspTDD768 ::= ProtocolIE-Single-Container {{UL-CCTrCHInformationListIEs-RL-AdditionRspTDD768}}
UL-CCTrCHInformationListIEs-RL-AdditionRspTDD768 RNSAP-PROTOCOL-IES ::= {
    PRESENCE mandatory }
UL-CCTrCHInformationListIE-RL-AdditionRspTDD768 ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHs)) OF UL-CCTrCHInformationItem-RL-AdditionRspTDD768
UL-CCTrCHInformationItem-RL-AdditionRspTDD768 ::= SEQUENCE {
   cCTrCH-ID
                             CCTrCH-ID,
   ul-DPCH-Information768
                                    UL-DPCH-InformationList-RL-AdditionRspTDD768
                                                                                    OPTIONAL,
                                 ProtocolExtensionContainer { {UL-CCTrCHInformationItem-RL-AdditionRspTDD768-ExtIEs} } OPTIONAL,
   iE-Extensions
UL-CCTrCHInformationItem-RL-AdditionRspTDD768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UL-DPCH-InformationList-RL-AdditionRspTDD768 ::= ProtocolIE-Single-Container { {UL-DPCH-InformationListIEs-RL-AdditionRspTDD768} }
UL-DPCH-InformationListIEs-RL-AdditionRspTDD768 RNSAP-PROTOCOL-IES ::= {
   { ID id-UL-DPCH-InformationItem-RL-AdditionRspTDD
                                                      CRITICALITY ignore TYPE UL-DPCH-InformationItem-RL-AdditionRspTDD768 PRESENCE
mandatory }
```

```
UL-DPCH-InformationItem-RL-AdditionRspTDD768 ::= SEQUENCE
   repetitionPeriod
                                     RepetitionPeriod,
   repetitionLength
                                     RepetitionLength,
   tDD-DPCHOffset
                                     TDD-DPCHOffset,
   uL-Timeslot-Information768
                                     UL-Timeslot-Information768.
   iE-Extensions
                                     ProtocolExtensionContainer { {UL-DPCH-InformationItem-RL-AdditionRspTDD768-ExtIEs} } OPTIONAL,
UL-DPCH-InformationItem-RL-AdditionRspTDD768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-CCTrCHInformationList-RL-AdditionRspTDD768 ::= ProtocolIE-Single-Container {{DL-CCTrCHInformationListIEs-RL-AdditionRspTDD768}}
DL-CCTrCHInformationListIEs-RL-AdditionRspTDD768 RNSAP-PROTOCOL-IES ::= {
    PRESENCE mandatory }
DL-CCTrCHInformationListIE-RL-AdditionRspTDD768 ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHs)) OF DL-CCTrCHInformationItem-RL-AdditionRspTDD768
DL-CCTrCHInformationItem-RL-AdditionRspTDD768 ::= SEQUENCE {
   cCTrCH-ID
                                     CCTrCH-ID,
   dl-DPCH-Information768
                                     DL-DPCH-InformationList-RL-AdditionRspTDD768
                                                                                       OPTIONAL,
   cCTrCH-Maximum-DL-Power
                                     DL-Power
                                                 OPTIONAL, -- this is a DCH type CCTrCH power
                                                 OPTIONAL, -- this is a DCH type CCTrCH power
   cCTrCH-Minimum-DL-Power
                                     DL-Power
                                     ProtocolExtensionContainer { {DL-CCTrCHInformationItem-RL-AdditionRspTDD768-ExtIEs} } OPTIONAL,
   iE-Extensions
   . . .
DL-CCTrCHInformationItem-RL-AdditionRspTDD768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-DPCH-InformationList-RL-AdditionRspTDD768 ::= ProtocolIE-Single-Container { {DL-DPCH-InformationListIEs-RL-AdditionRspTDD768 } }
DL-DPCH-InformationListIEs-RL-AdditionRspTDD768 RNSAP-PROTOCOL-IES ::= {
   { ID id-DL-DPCH-InformationItem-RL-AdditionRspTDD768
                                                            CRITICALITY ignore TYPE DL-DPCH-InformationItem-RL-AdditionRspTDD768 PRESENCE
mandatory }
DL-DPCH-InformationItem-RL-AdditionRspTDD768 ::= SEQUENCE
   repetitionPeriod
                                 RepetitionPeriod,
   repetitionLength
                                 RepetitionLength,
   tDD-DPCHOffset
                                 TDD-DPCHOffset,
   dL-Timeslot-Information768
                                 DL-Timeslot-Information768,
   iE-Extensions
                                 ProtocolExtensionContainer { {DL-DPCH-InformationItem-RL-AdditionRspTDD768-ExtIEs} } OPTIONAL,
DL-DPCH-InformationItem-RL-AdditionRspTDD768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
***************
-- RADIO LINK ADDITION FAILURE FDD
  *****************
RadioLinkAdditionFailureFDD ::= SEOUENCE {
   protocolIEs
                                  ProtocolIE-Container
                                                             {{RadioLinkAdditionFailureFDD-IEs}},
                                  ProtocolExtensionContainer {{RadioLinkAdditionFailureFDD-Extensions}}
   protocolExtensions
                                                                                                                       OPTIONAL,
RadioLinkAdditionFailureFDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-CauseLevel-RL-AdditionFailureFDD
                                                                                             TYPE CauseLevel-RL-AdditionFailureFDD
                                                             CRITICALITY
                                                                             ignore
                   PRESENCE
                              mandatory }|
    { ID id-CriticalityDiagnostics
                                          CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                             PRESENCE optional
                                                                                                                   },
CauseLevel-RL-AdditionFailureFDD ::= CHOICE {
   generalCause
                      GeneralCauseList-RL-AdditionFailureFDD,
                      RLSpecificCauseList-RL-AdditionFailureFDD,
   rLSpecificCause
    . . .
GeneralCauseList-RL-AdditionFailureFDD ::= SEQUENCE {
                                              ProtocolExtensionContainer { { GeneralCauseItem-RL-AdditionFailureFDD-ExtIEs} }
   iE-Extensions
   OPTIONAL,
    . . .
GeneralCauseItem-RL-AdditionFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RLSpecificCauseList-RL-AdditionFailureFDD ::= SEQUENCE {
   unsuccessful-RL-InformationRespList-RL-AdditionFailureFDD
                                                                 UnsuccessfulRL-InformationResponseList-RL-AdditionFailureFDD,
    successful-RL-InformationRespList-RL-AdditionFailureFDD
                                                                 SuccessfulRL-InformationResponseList-RL-AdditionFailureFDD OPTIONAL,
   iE-Extensions
                                              ProtocolExtensionContainer { { RLSpecificCauseItem-RL-AdditionFailureFDD-ExtIEs} }
   OPTIONAL,
    . . .
RLSpecificCauseItem-RL-AdditionFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UnsuccessfulRL-InformationResponseList-RL-AdditionFailureFDD ::= SEQUENCE (SIZE (1..maxNrOfRLs-1)) OF ProtocolIE-Single-Container {
{UnsuccessfulRL-InformationResponse-RL-AdditionFailureFDD-IEs} }
```

```
UnsuccessfulRL-InformationResponse-RL-AdditionFailureFDD-IES RNSAP-PROTOCOL-IES ::= {
    { ID id-UnsuccessfulRL-InformationResponse-RL-AdditionFailureFDD
                                                                        CRITICALITY ignore TYPE UnsuccessfulRL-InformationResponse-RL-
AdditionFailureFDD
                        PRESENCE mandatory
UnsuccessfulRL-InformationResponse-RL-AdditionFailureFDD ::= SEQUENCE {
    rL-ID
                                    RL-ID.
    cause
                                    Cause,
    iE-Extensions
                                    ProtocolExtensionContainer { {UnsuccessfulRL-InformationResponse-RL-AdditionFailureFDD-ExtIEs} } OPTIONAL,
UnsuccessfulRL-InformationResponse-RL-AdditionFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
SuccessfulRL-InformationResponseList-RL-AdditionFailureFDD ::= SEOUENCE (SIZE (0..maxNrOfRLs-2)) OF ProtocolIE-Single-Container { {SuccessfulRL-
InformationResponse-RL-AdditionFailureFDD-IEs}
SuccessfulRL-InformationResponse-RL-AdditionFailureFDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-SuccessfulRL-InformationResponse-RL-AdditionFailureFDD
                                                                        CRITICALITY ignore TYPE SuccessfulRL-InformationResponse-RL-
AdditionFailureFDD
                        PRESENCE mandatory }
SuccessfulRL-InformationResponse-RL-AdditionFailureFDD ::= SEQUENCE {
    rL-ID
                                        RL-ID.
    rL-Set-ID
                                        RL-Set-ID,
    uRA-Information
                                        URA-Information
                                                            OPTIONAL,
    sAI
                                        SAI,
    qA-Cell
                                        GA-Cell
                                                    OPTIONAL,
    qA-AccessPointPosition
                                        GA-AccessPointPosition
    received-total-wide-band-power
                                        Received-total-wide-band-power,
    not-Used-secondary-CCPCH-Info
                                                NULL
                                                            OPTIONAL,
    dl-CodeInformation
                                        DL-CodeInformationList-RL-AdditionFailureFDD,
    diversityIndication
                                        DiversityIndication-RL-AdditionFailureFDD.
    -- This IE represents both the Diversity Indication IE and the choice based on the diversity indication as described in
    -- the tabular message format in subclause 9.1.
    sSDT-SupportIndicator
                                        SSDT-SupportIndicator,
    minUL-SIR
                                        UL-SIR,
    maxUL-SIR
                                        UL-SIR,
                                        Closedlooptimingadjustmentmode OPTIONAL,
    closedlooptimingadjustmentmode
    maximumAllowedULTxPower
                                        MaximumAllowedULTxPower,
    maximumDLTxPower
                                        DL-Power,
    minimumDLTxPower
                                        DL-Power.
    neighbouring-UMTS-CellInformation
                                        Neighbouring-UMTS-CellInformation OPTIONAL,
                                        Neighbouring-GSM-CellInformation OPTIONAL,
    neighbouring-GSM-CellInformation
    primaryCPICH-Power
                                        PrimaryCPICH-Power,
    pC-Preamble
                                        PC-Preamble,
    sRB-Delay
                                        SRB-Delay,
    iE-Extensions
                                        ProtocolExtensionContainer { {SuccessfulRL-InformationResponse-RL-AdditionFailureFDD-ExtIEs} } OPTIONAL,
SuccessfulRL-InformationResponse-RL-AdditionFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
ID id-GA-CellAdditionalShapes
                                                    CRITICALITY ignore EXTENSION GA-CellAdditionalShapes
                                                                                                                      PRESENCE optional }
     ID id-DL-PowerBalancing-ActivationIndicator
                                                    CRITICALITY ignore EXTENSION DL-PowerBalancing-ActivationIndicator
                                                                                                                      PRESENCE optional }
     ID id-HCS-Prio
                                                    CRITICALITY ignore EXTENSION HCS-Prio
                                                                                                                      PRESENCE optional }
     ID id-Active-MBMS-Bearer-ServiceFDD-PFL
                                                    CRITICALITY ignore EXTENSION Active-MBMS-Bearer-Service-ListFDD-PFL
                                                                                                                      PRESENCE optional }
     ID id-EDCH-RLSet-Id
                                                    CRITICALITY ignore EXTENSION RL-Set-ID
                                                                                                                      PRESENCE optional }
     ID id-EDCH-FDD-DL-ControlChannelInformation
                                                    CRITICALITY ignore EXTENSION EDCH-FDD-DL-ControlChannelInformation
                                                                                                                      PRESENCE optional }
     ID id-Initial-DL-DPCH-TimingAdjustment
                                                    CRITICALITY ignore EXTENSION DL-DPCH-TimingAdjustment
                                                                                                                      PRESENCE optional }
     ID id-Neighbouring-E-UTRA-CellInformation
                                                    CRITICALITY ignore EXTENSION Neighbouring-E-UTRA-CellInformation
                                                                                                                      PRESENCE optional }
     ID id-HSDSCH-PreconfigurationInfo
                                                    CRITICALITY ignore EXTENSION HSDSCH-PreconfigurationInfo
                                                                                                                      PRESENCE optional }
     ID id-F-DPCH-SlotFormat
                                                    CRITICALITY ignore EXTENSION F-DPCH-SlotFormat
                                                                                                                      PRESENCE optional }
     ID id-Non-Serving-RL-Preconfig-Info
                                                    CRITICALITY ignore EXTENSION Non-Serving-RL-Preconfig-Info
                                                                                                                      PRESENCE optional } |
    ID id-Neighbouring-UMTS-CellInformation-Ext
                                                    CRITICALITY ignore EXTENSION Neighbouring-UMTS-CellInformation-Ext
                                                                                                                      PRESENCE optional },
DL-CodeInformationList-RL-AdditionFailureFDD ::= ProtocolIE-Single-Container {{ DL-CodeInformationListIEs-RL-AdditionFailureFDD }}
DL-CodeInformationListIEs-RL-AdditionFailureFDD RNSAP-PROTOCOL-IES ::= {
    PRESENCE mandatory }
DiversityIndication-RL-AdditionFailureFDD ::= CHOICE {
                                 Combining-RL-AdditionFailureFDD,
   combining
   nonCombining
                                 NonCombining-RL-AdditionFailureFDD
Combining-RL-AdditionFailureFDD ::= SEOUENCE {
   rL-ID
                             RL-ID.
                             ProtocolExtensionContainer { { CombiningItem-RL-AdditionFailureFDD-ExtIEs} } OPTIONAL,
   iE-Extensions
CombiningItem-RL-AdditionFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
     ID id-DCH-InformationResponse
                                        CRITICALITY ignore EXTENSION DCH-InformationResponse
                                                                                                        PRESENCE optional
    { ID id-EDCH-FDD-InformationResponse
                                        CRITICALITY ignore EXTENSION EDCH-FDD-InformationResponse
                                                                                                               PRESENCE optional
   . . .
NonCombining-RL-AdditionFailureFDD ::= SEQUENCE {
   dCH-InformationResponse
                             DCH-InformationResponse,
                                            ProtocolExtensionContainer { { NonCombiningItem-RL-AdditionFailureFDD-ExtIEs} } OPTIONAL,
   iE-Extensions
NonCombiningItem-RL-AdditionFailureFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-EDCH-FDD-InformationResponse
                                        CRITICALITY ignore EXTENSION EDCH-FDD-InformationResponse
                                                                                                               PRESENCE optional
                                                                                                                                    },
   . . .
RadioLinkAdditionFailureFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-HS-DSCH-serving-cell-change-informationResponse CRITICALITY ignore EXTENSION HS-DSCH-serving-cell-change-informationResponse
       PRESENCE optional |
    PRESENCE optional } |
```

```
{ ID id-Additional-HS-Cell-Change-Information-Response CRITICALITY ignore EXTENSION Additional-HS-Cell-Change-Information-Response-List
           PRESENCE optional } |
    { ID id-MAChs-ResetIndicator
                                                        CRITICALITY ignore EXTENSION MAChs-ResetIndicator
                          PRESENCE optional |
   { ID id-Additional-EDCH-Cell-Information-Response-RLAdd CRITICALITY ignore EXTENSION Additional-EDCH-Cell-Information-Response-RLAddList
   PRESENCE optional },
   . . .
   -- RADIO LINK ADDITION FAILURE TDD
  RadioLinkAdditionFailureTDD ::= SEQUENCE {
                                                           {{RadioLinkAdditionFailureTDD-IEs}},
   protocolIEs
                                 ProtocolIE-Container
                                 ProtocolExtensionContainer {{RadioLinkAdditionFailureTDD-Extensions}}
   protocolExtensions
                                                                                                                    OPTIONAL,
   . . .
RadioLinkAdditionFailureTDD-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-CauseLevel-RL-AdditionFailureTDD
                                            CRITICALITY ignore TYPE CauseLevel-RL-AdditionFailureTDD
                                                                                                          PRESENCE mandatory } |
     ID id-CriticalityDiagnostics
                                         CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                           PRESENCE optional
CauseLevel-RL-AdditionFailureTDD ::= CHOICE {
   generalCause
                      GeneralCauseList-RL-AdditionFailureTDD,
                      RLSpecificCauseList-RL-AdditionFailureTDD,
   rLSpecificCause
GeneralCauseList-RL-AdditionFailureTDD ::= SEQUENCE {
   cause
   iE-Extensions
                              ProtocolExtensionContainer { { GeneralCauseItem-RL-AdditionFailureTDD-ExtIEs} }
                                                                                                                 OPTIONAL,
GeneralCauseItem-RL-AdditionFailureTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RLSpecificCauseList-RL-AdditionFailureTDD ::= SEQUENCE {
   unsuccessful-RL-InformationRespItem-RL-AdditionFailureTDD
                                                            Unsuccessful-RL-InformationRespItem-RL-AdditionFailureTDD,
                                                            ProtocolExtensionContainer { { RLSpecificCauseItem-RL-AdditionFailureTDD-ExtIEs} }
   iE-Extensions
       OPTIONAL,
   . . .
RLSpecificCauseItem-RL-AdditionFailureTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
Unsuccessful-RL-InformationRespItem-RL-AdditionFailureTDD ::= ProtocolIE-Single-Container { {Unsuccessful-RL-InformationRespItemIE-RL-
AdditionFailureTDD} }
Unsuccessful-RL-InformationRespItemIE-RL-AdditionFailureTDD RNSAP-PROTOCOL-IES ::= {
          id-UnsuccessfulRL-InformationResponse-RL-AdditionFailureTDD
                                                                     CRITICALITY ignore
                                                                                                UnsuccessfulRL-InformationResponse-RL-
                                                                                         TYPE
AdditionFailureTDD PRESENCE mandatory}
UnsuccessfulRL-InformationResponse-RL-AdditionFailureTDD ::= SEQUENCE {
   rL-ID
                             RL-ID,
   cause
                             Cause,
                             ProtocolExtensionContainer { {UnsuccessfulRL-InformationResponse-RL-AdditionFailureTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
UnsuccessfulrL-InformationResponse-RL-AdditionFailureTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RadioLinkAdditionFailureTDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
-- RADIO LINK DELETION REQUEST
        RadioLinkDeletionRequest ::= SEQUENCE {
   protocolIEs
                                 ProtocolIE-Container
                                                          {{RadioLinkDeletionRequest-IEs}},
                                 ProtocolExtensionContainer {{RadioLinkDeletionRequest-Extensions}}
   protocolExtensions
                                                                                                               OPTIONAL,
   . . .
RadioLinkDeletionRequest-IEs RNSAP-PROTOCOL-IES ::= {
   PRESENCE mandatory
   . . .
                                        ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-Information-RL-DeletionRqst-
RL-InformationList-RL-DeletionRqst
IEs} }
RL-Information-RL-DeletionRqst-IEs RNSAP-PROTOCOL-IES ::= {
   { ID id-RL-Information-RL-DeletionRgst
                                        CRITICALITY notify TYPE RL-Information-RL-DeletionRqst
                                                                                                       PRESENCE mandatory
RL-Information-RL-DeletionRqst ::= SEQUENCE {
                             RL-ID,
   iE-Extensions
                             ProtocolExtensionContainer { {RL-Information-RL-DeletionRqst-ExtIEs} } OPTIONAL,
RL-Information-RL-DeletionRqst-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
RadioLinkDeletionRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    -- RADIO LINK DELETION RESPONSE
  *****************
RadioLinkDeletionResponse ::= SEQUENCE {
                                                         {{RadioLinkDeletionResponse-IEs}},
   protocolIEs
                                ProtocolIE-Container
   protocolExtensions
                                ProtocolExtensionContainer {{RadioLinkDeletionResponse-Extensions}}
                                                                                                              OPTIONAL,
RadioLinkDeletionResponse-IEs RNSAP-PROTOCOL-IES ::= {
   { ID id-CriticalityDiagnostics
                                       CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                        PRESENCE optional
                                                                                                             },
   . . .
RadioLinkDeletionResponse-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
-- RADIO LINK RECONFIGURATION PREPARE FDD
  RadioLinkReconfigurationPrepareFDD ::= SEQUENCE {
   protocolIEs
                                ProtocolIE-Container
                                                         {{RadioLinkReconfigurationPrepareFDD-IEs}},
   protocolExtensions
                                ProtocolExtensionContainer {{RadioLinkReconfigurationPrepareFDD-Extensions}}
                                                                                                                       OPTIONAL,
RadioLinkReconfigurationPrepareFDD-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-AllowedQueuingTime
                             CRITICALITY reject TYPE AllowedQueuingTime
                                                                                       PRESENCE optional
    { ID id-UL-DPCH-Information-RL-ReconfPrepFDD
                                                  CRITICALITY reject TYPE UL-DPCH-Information-RL-ReconfPrepFDD
   PRESENCE optional } |
   { ID id-DL-DPCH-Information-RL-ReconfPrepFDD
                                                      CRITICALITY reject TYPE DL-DPCH-Information-RL-ReconfPrepFDD
   PRESENCE optional } |
     ID id-FDD-DCHs-to-Modify
                                CRITICALITY reject TYPE FDD-DCHs-to-Modify
                                                                            PRESENCE optional
     ID id-DCHs-to-Add-FDD
                            CRITICALITY reject TYPE DCH-FDD-Information
                                                                            PRESENCE optional
     ID id-DCH-DeleteList-RL-ReconfPrepFDD
                                           CRITICALITY reject TYPE DCH-DeleteList-RL-ReconfPrepFDD
                                                                                                      PRESENCE optional
     ID id-RL-InformationList-RL-ReconfPrepFDD CRITICALITY reject TYPE RL-InformationList-RL-ReconfPrepFDD
                                                                                                     PRESENCE optional
   { ID id-Transmission-Gap-Pattern-Sequence-Information CRITICALITY reject TYPE Transmission-Gap-Pattern-Sequence-Information
                                                                                                                           PRESENCE
optional },
```

```
UL-DPCH-Information-RL-ReconfPrepFDD ::= SEQUENCE {
    ul-ScramblingCode
                                   UL-ScramblingCode
                                                           OPTIONAL.
    ul-SIRTarget
                                   UL-SIR
                                                           OPTIONAL,
    minUL-ChannelisationCodeLength MinUL-ChannelisationCodeLength OPTIONAL,
    maxNrOfUL-DPDCHs
                                   MaxNrOfUL-DPCHs
                                                           OPTIONAL
    -- This IE shall be present if minUL-ChannelisationCodeLength equals to 4 --,
    ul-PunctureLimit
                                   PunctureLimit
                                                           OPTIONAL,
    t FCS
                                   TFCS OPTIONAL,
    ul-DPCCH-SlotFormat
                                   UL-DPCCH-SlotFormat
                                                           OPTIONAL,
                                                           OPTIONAL,
    diversityMode
                                   DiversityMode
    not-Used-sSDT-CellIDLength
                                   NULL
                                               OPTIONAL,
    not-Used-s-FieldLength
                                   NULL
                                                   OPTIONAL,
    iE-Extensions
                                   ProtocolExtensionContainer { {UL-DPCH-Information-RL-ReconfPrepFDD-ExtIEs} } OPTIONAL,
UL-DPCH-Information-RL-ReconfPrepFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
    EXTENSION UL-DPDCHIndicatorEDCH PRESENCE optional
DL-DPCH-Information-RL-ReconfPrepFDD ::= SEQUENCE {
    t FCS
                                   TFCS OPTIONAL,
    dl-DPCH-SlotFormat
                                   DL-DPCH-SlotFormat
                                                           OPTIONAL,
    nrOfDLchannelisationcodes
                                   NrOfDLchannelisationcodes OPTIONAL,
    tFCI-SignallingMode
                                   TFCI-SignallingMode
                                                           OPTIONAL,
    tFCI-Presence
                                   TFCI-Presence
                                                           OPTIONAL
    -- This IE shall be present if DL DPCH Slot Format IE is from 12 to 16 --,
    multiplexingPosition
                                   MultiplexingPosition
                                                               OPTIONAL,
   limitedPowerIncrease
                                   LimitedPowerIncrease
                                                               OPTIONAL,
    iE-Extensions
                                   ProtocolExtensionContainer { {DL-DPCH-Information-RL-ReconfPrepFDD-ExtIEs} } OPTIONAL,
    . . .
DL-DPCH-Information-RL-ReconfPrepFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-DL-DPCH-Power-Information-RL-ReconfPrepFDD CRITICALITY reject EXTENSION DL-DPCH-Power-Information-RL-ReconfPrepFDD
                                                                                                                                     PRESENCE
optional
    . . .
DL-DPCH-Power-Information-RL-ReconfPrepFDD ::= SEQUENCE {
    powerOffsetInformation
                                           PowerOffsetInformation-RL-ReconfPrepFDD,
    fdd-TPC-DownlinkStepSize
                                           FDD-TPC-DownlinkStepSize,
    innerLoopDLPCStatus
                                           InnerLoopDLPCStatus,
    iE-Extensions
                                           ProtocolExtensionContainer { { DL-DPCH-Power-Information-RL-ReconfPrepFDD-ExtIEs } }
                                                                                                                                     OPTIONAL,
    . . .
DL-DPCH-Power-Information-RL-ReconfPrepFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
PowerOffsetInformation-RL-ReconfPrepFDD ::= SEQUENCE {
```

```
PowerOffset,
   pO1-ForTFCI-Bits
   pO2-ForTPC-Bits
                                          PowerOffset.
   pO3-ForPilotBits
                                          PowerOffset.
   iE-Extensions
                                          OPTIONAL.
PowerOffsetInformation-RL-ReconfPrepFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DCH-DeleteList-RL-ReconfPrepFDD
                                          ::= SEQUENCE (SIZE (0..maxNrOfDCHs)) OF DCH-DeleteItem-RL-ReconfPrepFDD
DCH-DeleteItem-RL-ReconfPrepFDD ::= SEOUENCE {
   dCH-ID
   iE-Extensions
                                   ProtocolExtensionContainer { {DCH-DeleteItem-RL-ReconfPrepFDD-ExtIEs} } OPTIONAL,
DCH-DeleteItem-RL-ReconfPrepFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RL-InformationList-RL-ReconfPrepFDD
                                          ::= SEQUENCE (SIZE (0..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-Information-RL-ReconfPrepFDD-
IEs} }
RL-Information-RL-ReconfPrepFDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-Information-RL-ReconfPrepFDD
                                              CRITICALITY reject TYPE RL-Information-RL-ReconfPrepFDD
                                                                                                             PRESENCE mandatory
RL-Information-RL-ReconfPrepFDD ::= SEQUENCE {
   rI.-ID
                              RL-ID,
   not-Used-sSDT-Indication
                                      NULL
                                                  OPTIONAL,
   not-Used-sSDT-CellIdentity
                                      NULL
                                                  OPTIONAL,
   transmitDiversitvIndicator
                                  TransmitDiversitvIndicator
                                                                  OPTIONAL,
    -- This IE shall be present if Diversity Mode IE is present in UL DPCH Information IE and is not equal to "none"
   iE-Extensions
                                   ProtocolExtensionContainer { {RL-Information-RL-ReconfPrepFDD-ExtIEs} } OPTIONAL,
RL-Information-RL-ReconfPrepFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-DLReferencePower
                                              CRITICALITY ignore EXTENSION DL-Power
                                                                                                                                   PRESENCE
optional }|
    { ID id-RL-Specific-DCH-Info
                                              CRITICALITY ignore EXTENSION RL-Specific-DCH-Info
                                                                                                                                   PRESENCE
optional }
     ID id-DL-DPCH-TimingAdjustment
                                              CRITICALITY reject EXTENSION DL-DPCH-TimingAdjustment
                                                                                                                           PRESENCE optional } |
     ID id-Phase-Reference-Update-Indicator
                                              CRITICALITY ignore EXTENSION Phase-Reference-Update-Indicator PRESENCE optional }
     ID id-RL-Specific-EDCH-Information
                                              CRITICALITY reject EXTENSION RL-Specific-EDCH-Information
                                                                                                                    PRESENCE optional }
     ID id-EDCH-RL-Indication
                                              CRITICALITY reject EXTENSION EDCH-RL-Indication
                                                                                                                                   PRESENCE
optional }|
     ID id-HSDSCH-PreconfigurationSetup
                                              CRITICALITY ignore EXTENSION HSDSCH-PreconfigurationSetup
                                                                                                                           PRESENCE optional }
     ID id-Non-Serving-RL-Preconfig-Setup
                                              CRITICALITY ignore EXTENSION Non-Serving-RL-Preconfig-Setup
                                                                                                                    PRESENCE optional }
                                                                                                                    PRESENCE optional },
    { ID id-Non-Serving-RL-Preconfig-Removal
                                              CRITICALITY ignore EXTENSION Non-Serving-RL-Preconfig-Setup
```

```
RadioLinkReconfigurationPrepareFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-HSDSCH-FDD-Information
                                                            CRITICALITY reject EXTENSION HSDSCH-FDD-Information
    PRESENCE optional } |
    { ID id-HSDSCH-Information-to-Modify
                                                            CRITICALITY reject EXTENSION HSDSCH-Information-to-Modify
    PRESENCE optional }
    { ID id-HSDSCH-MACdFlows-to-Add
                                                            CRITICALITY reject EXTENSION HSDSCH-MACdFlows-Information
    PRESENCE optional } |
    { ID id-HSDSCH-MACdFlows-to-Delete
                                                            CRITICALITY reject EXTENSION HSDSCH-MACdFlows-to-Delete
    PRESENCE optional } |
    { ID id-HSPDSCH-RL-ID
                                                            CRITICALITY reject EXTENSION RL-ID
                PRESENCE optional |
    { ID id-EDPCH-Information
                                                            CRITICALITY reject EXTENSION EDPCH-Information-RLReconfPrepare-FDD
           PRESENCE optional |
    { ID id-EDCH-FDD-Information
                                                            CRITICALITY reject EXTENSION EDCH-FDD-Information
    PRESENCE optional } |
    { ID id-EDCH-FDD-Information-To-Modify
                                                            CRITICALITY reject EXTENSION EDCH-FDD-Information-To-Modify
    PRESENCE optional } |
    { ID id-EDCH-MACdFlows-To-Add
                                                            CRITICALITY reject EXTENSION EDCH-MACdFlows-Information
    PRESENCE optional } |
    { ID id-EDCH-MACdFlows-To-Delete
                                                            CRITICALITY reject EXTENSION EDCH-MACdFlows-To-Delete
    PRESENCE optional } |
    { ID id-Serving-EDCHRL-Id
                                                            CRITICALITY reject EXTENSION EDCH-Serving-RL
           PRESENCE optional }
     ID id-F-DPCH-Information-RL-ReconfPrepFDD
                                                            CRITICALITY reject EXTENSION F-DPCH-Information-RL-ReconfPrepFDD PRESENCE optional | |
                                                            CRITICALITY ignore EXTENSION Fast-Reconfiguration-Mode
    { ID id-Fast-Reconfiguration-Mode
    PRESENCE optional } |
    { ID id-CPC-Information
                                                            CRITICALITY reject EXTENSION CPC-Information
           PRESENCE optional |
    { ID id-Additional-HS-Cell-Information-RL-Reconf-Prep
                                                            CRITICALITY reject EXTENSION Additional-HS-Cell-Information-RL-Reconf-Prep
    PRESENCE optional } |
    { ID id-UE-AggregateMaximumBitRate
                                                            CRITICALITY ignore EXTENSION UE-AggregateMaximumBitRate
    PRESENCE optional }
    { ID id-Additional-EDCH-Cell-Information-RL-Reconf-Prep CRITICALITY reject EXTENSION Additional-EDCH-Cell-Information-RL-Reconf-Prep
        PRESENCE optional },
    . . .
Additional-HS-Cell-Information-RL-Reconf-Prep ::= SEQUENCE (SIZE (1..maxNrOfHSDSCH-1)) OF Additional-HS-Cell-Information-RL-Reconf-Prep-ItemIEs
Additional-HS-Cell-Information-RL-Reconf-Prep-ItemIEs ::=SEOUENCE{
    hSPDSCH-RL-ID
                                                    RL-ID,
    c-ID
                                                    C-ID
                                                                                                         OPTIONAL,
    hS-DSCH-FDD-Secondary-Serving-Information
                                                    HS-DSCH-FDD-Secondary-Serving-Information
                                                                                                         OPTIONAL,
    hS-DSCH-Secondary-Serving-Information-To-Modify HS-DSCH-Secondary-Serving-Information-To-Modify
                                                                                                         OPTIONAL,
    hS-HS-DSCH-Secondary-Serving-Remove
                                                    HS-DSCH-Secondary-Serving-Remove OPTIONAL,
                                    ProtocolExtensionContainer { { Additional-HS-Cell-Information-RL-Reconf-Prep-ItemIEs-ExtIEs} } OPTIONAL,
    iE-Extensions
Additional-HS-Cell-Information-RL-Reconf-Prep-ItemIEs-ExtIEs
                                                                RNSAP-PROTOCOL-EXTENSION ::= {
```

```
Additional-EDCH-Cell-Information-RL-Reconf-Prep ::=SEQUENCE{
    setup-Or-ConfigurationChange-Or-Removal-Of-EDCH-On-secondary-UL-Frequency
                                                                                                      Setup-Or-ConfigurationChange-Or-Removal-
Of-EDCH-On-secondary-UL-Frequency,
   iE-Extensions
                                   ProtocolExtensionContainer { Additional-EDCH-Cell-Information-RL-Reconf-Prep-ExtIEs} } OPTIONAL,
Additional-EDCH-Cell-Information-RL-Reconf-Prep-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
F-DPCH-Information-RL-ReconfPrepFDD ::= SEQUENCE {
   powerOffsetInformation
                                  PowerOffsetInformation-F-DPCH-RL-ReconfPrepFDD,
   fdd-dl-TPC-DownlinkStepSize
                                  FDD-TPC-DownlinkStepSize,
   limitedPowerIncrease
                                  LimitedPowerIncrease,
   innerLoopDLPCStatus
                                  InnerLoopDLPCStatus,
                                  ProtocolExtensionContainer { { F-DPCH-Information-RL-ReconfPrepFDD-ExtIEs} }
   iE-Extensions
   OPTIONAL,
F-DPCH-Information-RL-ReconfPrepFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-F-DPCH-SlotFormatSupportRequest CRITICALITY reject
                                                                          EXTENSION F-DPCH-SlotFormatSupportRequest
                                                                                                                            PRESENCE optional
                                                                                             PRESENCE optional },
    { ID id-F-DPCH-SlotFormat
                                          CRITICALITY ignore EXTENSION F-DPCH-SlotFormat
PowerOffsetInformation-F-DPCH-RL-ReconfPrepFDD ::= SEQUENCE {
   po2-ForTPC-Bits
                                   PowerOffset,
    -- This IE shall be ignored by DRNS
   iE-Extensions
                                   ProtocolExtensionContainer { { PowerOffsetInformation-F-DPCH-RL-ReconfPrepFDD-ExtIEs} }
                                                                                                                                   OPTIONAL,
PowerOffsetInformation-F-DPCH-RL-ReconfPrepFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
-- RADIO LINK RECONFIGURATION PREPARE TDD
__ *********************
RadioLinkReconfigurationPrepareTDD ::= SEQUENCE {
   protocolIEs
                                  ProtocolIE-Container
                                                              {{RadioLinkReconfigurationPrepareTDD-IEs}},
                                  ProtocolExtensionContainer {{RadioLinkReconfigurationPrepareTDD-Extensions}}
                                                                                                                               OPTIONAL,
   protocolExtensions
RadioLinkReconfigurationPrepareTDD-IEs RNSAP-PROTOCOL-IES ::= {
```

```
ID id-AllowedQueuingTime
                                    CRITICALITY reject TYPE AllowedQueuingTime
                                                                                       PRESENCE optional
     PRESENCE
optional
    { ID id-UL-CCTrCH-InformationModifyList-RL-ReconfPrepTDD
                                                          CRITICALITY notify TYPE UL-CCTrCH-InformationModifyList-RL-ReconfPrepTDD
   PRESENCE optional
    { ID id-UL-CCTrCH-InformationDeleteList-RL-ReconfPrepTDD
                                                          CRITICALITY notify TYPE UL-CCTrCH-InformationDeleteList-RL-ReconfPrepTDD
   PRESENCE optional } |
   PRESENCE
optional } |
    { ID id-DL-CCTrCH-InformationModifyList-RL-ReconfPrepTDD
                                                          CRITICALITY notify TYPE DL-CCTrCH-InformationModifyList-RL-ReconfPrepTDD
   PRESENCE optional } |
    { ID id-DL-CCTrCH-InformationDeleteList-RL-ReconfPrepTDD
                                                          CRITICALITY notify TYPE DL-CCTrCH-InformationDeleteList-RL-ReconfPrepTDD
   PRESENCE optional } |
     ID id-TDD-DCHs-to-Modify
                                CRITICALITY reject TYPE TDD-DCHs-to-Modify
                                                                             PRESENCE optional
     ID id-DCHs-to-Add-TDD
                             CRITICALITY reject TYPE DCH-TDD-Information
                                                                            PRESENCE optional
     ID id-DCH-DeleteList-RL-ReconfPrepTDD
                                            CRITICALITY reject TYPE DCH-DeleteList-RL-ReconfPrepTDD
                                                                                                       PRESENCE optional
     ID id-DSCH-ModifyList-RL-ReconfPrepTDD
                                           CRITICALITY reject TYPE DSCH-ModifyList-RL-ReconfPrepTDD
                                                                                                              PRESENCE optional
     ID id-DSCHs-to-Add-TDD
                                CRITICALITY reject TYPE DSCH-TDD-Information
                                                                                    PRESENCE optional
     ID id-DSCH-DeleteList-RL-ReconfPrepTDD
                                           CRITICALITY reject TYPE DSCH-DeleteList-RL-ReconfPrepTDD
                                                                                                              PRESENCE optional
     ID id-USCH-ModifyList-RL-ReconfPrepTDD
                                           CRITICALITY reject TYPE USCH-ModifyList-RL-ReconfPrepTDD
                                                                                                              PRESENCE optional
     ID id-USCHs-to-Add
                             CRITICALITY reject TYPE USCH-Information
                                                                             PRESENCE optional
    { ID id-USCH-DeleteList-RL-ReconfPrepTDD
                                           CRITICALITY reject TYPE USCH-DeleteList-RL-ReconfPrepTDD
                                                                                                              PRESENCE optional
UL-CCTrCH-InformationAddList-RL-ReconfPrepTDD
                                               ::= SEQUENCE (SIZE (0..maxNrOfCCTrCHs)) OF ProtocolIE-Single-Container { {UL-CCTrCH-
AddInformation-RL-ReconfPrepTDD-IEs} }
UL-CCTrCH-AddInformation-RL-ReconfPrepTDD-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-UL-CCTrCH-AddInformation-RL-ReconfPrepTDD CRITICALITY notify TYPE UL-CCTrCH-AddInformation-RL-ReconfPrepTDD
                                                                                                                     PRESENCE mandatory
UL-CCTrCH-AddInformation-RL-ReconfPrepTDD ::= SEQUENCE {
   cCTrCH-ID
                             CCTrCH-ID,
   tFCS
                             TFCS,
   tFCI-Coding
                             TFCI-Coding,
   punctureLimit
                                 PunctureLimit,
   iE-Extensions
                                ProtocolExtensionContainer { {UL-CCTrCH-AddInformation-RL-ReconfPrepTDD-ExtIEs} } OPTIONAL,
   . . .
UL-CCTrCH-AddInformation-RL-ReconfPrepTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   { ID id-UL-SIRTarget
                                                                             PRESENCE optional } |
                             CRITICALITY reject
                                                   EXTENSION
                                                                  UL-SIR
   -- This IE shall be mandatory for 1.28Mcps TDD, not applicable for 3.84Mcps TDD or 7.68Mcps TDD.
    { ID id-TDD-TPC-UplinkStepSize-InformationAdd-LCR-RL-ReconfPrepTDD CRITICALITY reject EXTENSION TDD-TPC-UplinkStepSize-LCR
                                                                                                                           PRESENCE
    optional },
   -- Mandatory for 1.28Mcps TDD, not applicable to 3.84Mcps TDD or 7.68Mcps TDD
UL-CCTrCH-InformationModifyList-RL-ReconfPrepTDD
                                                  ::= SEQUENCE (SIZE (0..maxNrOfCCTrCHs)) OF ProtocolIE-Single-Container { {UL-CCTrCH-
ModifyInformation-RL-ReconfPrepTDD-IEs} }
```

```
UL-CCTrCH-ModifyInformation-RL-ReconfPrepTDD-IEs RNSAP-PROTOCOL-IES ::= {
   PRESENCE
mandatory }
UL-CCTrCH-ModifyInformation-RL-ReconfPrepTDD ::= SEQUENCE {
   cCTrCH-ID
                          CCTrCH-ID.
   t.FCS
                          TFCS
                                    OPTIONAL,
   tFCI-Coding
                         TFCI-Coding
                                              OPTIONAL.
   punctureLimit
                             PunctureLimit
                                                    OPTIONAL,
   iE-Extensions
                             ProtocolExtensionContainer { {UL-CCTrCH-ModifyInformation-RL-ReconfPrepTDD-ExtIEs} } OPTIONAL,
   . . .
UL-CCTrCH-ModifyInformation-RL-ReconfPrepTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   { ID id-UL-SIRTarget
                          CRITICALITY reject
                                              EXTENSION
                                                           UL-SIR
                                                                     PRESENCE optional } |
   -- This IE shall be applicable for 1.28Mcps TDD only.
   { ID id-TDD-TPC-UplinkStepSize-InformationModify-LCR-RL-ReconfPrepTDD CRITICALITY reject EXTENSION
                                                                                            TDD-TPC-UplinkStepSize-LCR
      PRESENCE optional },
   -- Applicable to 1.28Mcps TDD only
UL-CCTrCH-InformationDeleteList-RL-ReconfPrepTDD
                                            ::= SEOUENCE (SIZE (0..maxNrOfCCTrCHs)) OF ProtocolIE-Single-Container { {UL-CCTrCH-
DeleteInformation-RL-ReconfPrepTDD-IEs} }
UL-CCTrCH-DeleteInformation-RL-ReconfPrepTDD-IEs RNSAP-PROTOCOL-IES ::= {
   PRESENCE
mandatory }
UL-CCTrCH-DeleteInformation-RL-ReconfPrepTDD ::= SEQUENCE {
   cCTrCH-ID
                          CCTrCH-ID,
                             ProtocolExtensionContainer { {UL-CCTrCH-DeleteInformation-RL-ReconfPrepTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
   . . .
UL-CCTrCH-DeleteInformation-RL-ReconfPrepTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-CCTrCH-InformationAddList-RL-ReconfPrepTDD
                                         ::= SEQUENCE (SIZE (0..maxNrOfCCTrCHs)) OF ProtocolIE-Single-Container { {DL-CCTrCH-
AddInformation-RL-ReconfPrepTDD-IEs} }
DL-CCTrCH-AddInformation-RL-ReconfPrepTDD-IEs RNSAP-PROTOCOL-IES ::= {
   PRESENCE
mandatory }
DL-CCTrCH-InformationAddItem-RL-ReconfPrepTDD ::= SEQUENCE {
   cCTrCH-ID
                          CCTrCH-ID,
   tFCS
                          TFCS,
   tFCI-Coding
                          TFCI-Coding,
   punctureLimit
                             PunctureLimit,
```

```
cCTrCH-TPCList
                                   CCTrCH-TPCAddList-RL-ReconfPrepTDD OPTIONAL,
    iE-Extensions
                                   ProtocolExtensionContainer { {DL-CCTrCH-InformationAddItem-RL-ReconfPrepTDD-ExtIEs} } OPTIONAL,
DL-CCTrCH-InformationAddItem-RL-ReconfPrepTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-TDD-TPC-DownlinkStepSize-InformationAdd-RL-ReconfPrepTDD CRITICALITY reject EXTENSION TDD-TPC-DownlinkStepSize
                                                                                                                                      PRESENCE
    optional },
CCTrCH-TPCAddList-RL-ReconfPrepTDD ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHs)) OF CCTrCH-TPCAddItem-RL-ReconfPrepTDD
CCTrCH-TPCAddItem-RL-ReconfPrepTDD ::= SEOUENCE {
    cCTrCH-ID
   iE-Extensions
                                   ProtocolExtensionContainer { { CCTrCH-TPCAddItem-RL-ReconfPrepTDD-ExtIEs} } OPTIONAL,
CCTrCH-TPCAddItem-RL-ReconfPrepTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-CCTrCH-InformationModifyList-RL-ReconfPrepTDD
                                                      ::= SEQUENCE (SIZE (0..maxNrOfCCTrCHs)) OF ProtocolIE-Single-Container { {DL-CCTrCH-
ModifyInformation-RL-ReconfPrepTDD-IEs} }
DL-CCTrCH-ModifyInformation-RL-ReconfPrepTDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-DL-CCTrCH-InformationModifyItem-RL-ReconfPrepTDD CRITICALITY notify TYPE DL-CCTrCH-InformationModifyItem-RL-ReconfPrepTDD
    PRESENCE mandatory }
DL-CCTrCH-InformationModifyItem-RL-ReconfPrepTDD ::= SEQUENCE {
    cCTrCH-ID
                               CCTrCH-ID,
    tFCS
                               TFCS
                                           OPTIONAL,
    tFCI-Coding
                               TFCI-Coding
                                                       OPTIONAL,
   punctureLimit
                               PunctureLimit
                                                               OPTIONAL,
    cCTrCH-TPCList
                                   CCTrCH-TPCModifyList-RL-ReconfPrepTDD
                                                                               OPTIONAL,
                                   ProtocolExtensionContainer { {DL-CCTrCH-InformationModifyItem-RL-ReconfPrepTDD-ExtIEs} } OPTIONAL,
    iE-Extensions
DL-CCTrCH-InformationModifyItem-RL-ReconfPrepTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-TDD-TPC-DownlinkStepSize-InformationModify-RL-ReconfPrepTDD CRITICALITY reject
                                                                                                               TDD-TPC-DownlinkStepSize
                                                                                               EXTENSION
       PRESENCE optional },
    . . .
CCTrCH-TPCModifyList-RL-ReconfPrepTDD ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHs)) OF CCTrCH-TPCModifyItem-RL-ReconfPrepTDD
CCTrCH-TPCModifyItem-RL-ReconfPrepTDD
                                      ::= SEQUENCE {
    cCTrCH-ID
                                   CCTrCH-ID,
    iE-Extensions
                                   ProtocolExtensionContainer { { CCTrCH-TPCModifyItem-RL-ReconfPrepTDD-ExtIEs} } OPTIONAL,
```

```
CCTrCH-TPCModifyItem-RL-ReconfPrepTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-CCTrCH-InformationDeleteList-RL-ReconfPrepTDD
                                                       ::= SEOUENCE (SIZE (0..maxNrOfCCTrCHs)) OF ProtocolIE-Single-Container { {DL-CCTrCH-
DeleteInformation-RL-ReconfPrepTDD-IEs} }
DL-CCTrCH-DeleteInformation-RL-ReconfPrepTDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-DL-CCTrCH-InformationDeleteItem-RL-ReconfPrepTDD CRITICALITY notify TYPE DL-CCTrCH-InformationDeleteItem-RL-ReconfPrepTDD
    PRESENCE mandatory
DL-CCTrCH-InformationDeleteItem-RL-ReconfPrepTDD ::= SEOUENCE {
                               CCTrCH-ID,
    cCTrCH-ID
    iE-Extensions
                                    ProtocolExtensionContainer { {DL-CCTrCH-InformationDeleteItem-RL-ReconfPrepTDD-ExtIEs} } OPTIONAL,
DL-CCTrCH-InformationDeleteItem-RL-ReconfPrepTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DCH-DeleteList-RL-ReconfPrepTDD
                                            ::= SEOUENCE (SIZE (0..maxNrOfDCHs)) OF DCH-DeleteItem-RL-ReconfPrepTDD
DCH-DeleteItem-RL-ReconfPrepTDD ::= SEQUENCE {
    dCH-ID
    iE-Extensions
                                ProtocolExtensionContainer { {DCH-DeleteItem-RL-ReconfPrepTDD-ExtIEs} } OPTIONAL,
DCH-DeleteItem-RL-ReconfPrepTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DSCH-ModifyList-RL-ReconfPrepTDD ::= SEQUENCE (SIZE(0..maxNoOfDSCHs)) OF DSCH-ModifyItem-RL-ReconfPrepTDD
DSCH-ModifyItem-RL-ReconfPrepTDD ::= SEQUENCE {
   dSCH-ID
                                        DSCH-ID,
    dl-ccTrCHID
                                        CCTrCH-ID
                                                                        OPTIONAL,
    trChSourceStatisticsDescriptor
                                        TrCH-SrcStatisticsDescr OPTIONAL,
    transportFormatSet
                                        TransportFormatSet
                                                                        OPTIONAL,
    allocationRetentionPriority
                                        AllocationRetentionPriority
                                                                        OPTIONAL,
    schedulingPriorityIndicator
                                        SchedulingPriorityIndicator
                                                                        OPTIONAL,
                                        BLER
                                                                        OPTIONAL,
    transportBearerRequestIndicator
                                        TransportBearerRequestIndicator,
    iE-Extensions
                                    ProtocolExtensionContainer { {DSCH-ModifyItem-RL-ReconfPrepTDD-ExtIEs} } OPTIONAL,
DSCH-ModifyItem-RL-ReconfPrepTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-TrafficClass
                                           CRITICALITY ignore EXTENSION TrafficClass
                                                                                                                        PRESENCE optional
                                                                                                                                               } |
    { ID id-BindingID
                                            CRITICALITY ignore
                                                                    EXTENSION BindingID
                                                                                                          PRESENCE optional
    -- Shall be ignored if bearer establishment with ALCAP.
```

```
PRESENCE optional
    { ID id-TransportLayerAddress
                                            CRITICALITY ignore
                                                                     EXTENSION
                                                                                TransportLayerAddress
    -- Shall be ignored if bearer establishment with ALCAP.
    { ID id-TnlOos
                                            CRITICALITY ignore
                                                                     EXTENSION
                                                                                TnlOos
                                                                                                                         PRESENCE optional
    -- Shall be ignored if bearer establishment with ALCAP.
DSCH-DeleteList-RL-ReconfPrepTDD ::= SEQUENCE (SIZE(0..maxNoOfDSCHs)) OF DSCH-DeleteItem-RL-ReconfPrepTDD
DSCH-DeleteItem-RL-ReconfPrepTDD ::= SEQUENCE {
    dsch-ID
                                    ProtocolExtensionContainer { {DSCH-DeleteItem-RL-ReconfPrepTDD-ExtIEs} } OPTIONAL,
    iE-Extensions
DSCH-DeleteItem-RL-ReconfPrepTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
USCH-ModifyList-RL-ReconfPrepTDD ::= SEQUENCE (SIZE(0..maxNoOfUSCHs)) OF USCH-ModifyItem-RL-ReconfPrepTDD
USCH-ModifyItem-RL-ReconfPrepTDD ::= SEQUENCE {
    uSCH-ID
                                        USCH-ID,
    ul-ccTrCHID
                                        CCTrCH-ID
                                                                         OPTIONAL,
    trChSourceStatisticsDescriptor
                                        TrCH-SrcStatisticsDescr OPTIONAL,
    transportFormatSet
                                        TransportFormatSet
                                                                         OPTIONAL,
    allocationRetentionPriority
                                        AllocationRetentionPriority
                                                                         OPTIONAL,
    schedulingPriorityIndicator
                                        SchedulingPriorityIndicator
                                                                         OPTIONAL,
                                        BLER
                                                                         OPTIONAL,
                                        TransportBearerRequestIndicator,
    transportBearerRequestIndicator
    rb-Info
                                        RB-Info
                                                                         OPTIONAL,
    iE-Extensions
                                        ProtocolExtensionContainer { {USCH-ModifyItem-RL-ReconfPrepTDD-ExtIEs} } OPTIONAL,
    . . .
USCH-ModifyItem-RL-ReconfPrepTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-TrafficClass
                                    CRITICALITY ignore EXTENSION TrafficClass
                                                                                             PRESENCE optional
    { ID id-BindingID
                                    CRITICALITY ignore EXTENSION
                                                                                                 optional
                                                                    BindingID
                                                                                PRESENCE
    -- Shall be ignored if bearer establishment with ALCAP.
                                                                                                                                                } |
    { ID id-TransportLayerAddress
                                            CRITICALITY ignore
                                                                     EXTENSION
                                                                                TransportLayerAddress
                                                                                                                  PRESENCE
                                                                                                                                 optional
    -- Shall be ignored if bearer establishment with ALCAP.
    { ID id-TnlQos
                                        CRITICALITY
                                                        ignore
                                                                     EXTENSION
                                                                                Tn10os
                                                                                             PRESENCE
                                                                                                                  optional
    . . .
USCH-DeleteList-RL-ReconfPrepTDD ::= SEOUENCE (SIZE(0..maxNoOfUSCHs)) OF USCH-DeleteItem-RL-ReconfPrepTDD
USCH-DeleteItem-RL-ReconfPrepTDD ::= SEQUENCE {
    uSCH-ID
                                        USCH-ID.
    iE-Extensions
                                    ProtocolExtensionContainer { {USCH-DeleteItem-RL-ReconfPrepTDD-ExtIEs} } OPTIONAL,
USCH-DeleteItem-RL-ReconfPrepTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
RadioLinkReconfigurationPrepareTDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-PrimaryCCPCH-RSCP-RL-ReconfPrepTDD CRITICALITY ignore EXTENSION PrimaryCCPCH-RSCP
                                                                                                                    PRESENCE optional }
     ID id-DL-TimeSlot-ISCP-Info-RL-ReconfPrepTDD CRITICALITY ignore EXTENSION DL-TimeSlot-ISCP-Info
                                                                                                                    PRESENCE optional
     ID id-DL-Timeslot-ISCP-LCR-Information-RL-ReconfPrepTDD CRITICALITY ignore EXTENSION DL-TimeSlot-ISCP-LCR-Information PRESENCE optional
     ID id-HSDSCH-TDD-Information
                                              CRITICALITY reject EXTENSION HSDSCH-TDD-Information
                                                                                                                    PRESENCE optional
     ID id-HSDSCH-Information-to-Modify
                                              CRITICALITY reject EXTENSION HSDSCH-Information-to-Modify
                                                                                                                    PRESENCE optional}
     ID id-HSDSCH-MACdFlows-to-Add
                                              CRITICALITY reject EXTENSION HSDSCH-MACdFlows-Information
                                                                                                                    PRESENCE optional }
     ID id-HSDSCH-MACdFlows-to-Delete
                                              CRITICALITY reject EXTENSION HSDSCH-MACdFlows-to-Delete
                                                                                                                    PRESENCE optional}
                                              CRITICALITY reject EXTENSION RL-ID
                                                                                                                    PRESENCE optional}
     ID id-HSPDSCH-RL-ID
     ID id-PDSCH-RL-ID
                                              CRITICALITY ignore EXTENSION RL-ID
                                                                                                                    PRESENCE optional }
     ID id-UL-Synchronisation-Parameters-LCR
                                              CRITICALITY ignore EXTENSION UL-Synchronisation-Parameters-LCR
                                                                                                                    PRESENCE optional
-- Mandatory for 1.28Mcps TDD, Not Applicable to 3.84Mcps TDD or 7.68Mcps TDD
                                              CRITICALITY ignore EXTENSION RL-Information-RL-ReconfPrepTDD
     ID id-RL-Information-RL-ReconfPrepTDD
                                                                                                                    PRESENCE optional}
     ID id-PrimaryCCPCH-RSCP-Delta
                                              CRITICALITY ignore EXTENSION PrimaryCCPCH-RSCP-Delta
                                                                                                                    PRESENCE optional
     ID id-E-DCH-Information-Reconfig
                                                                                                                    PRESENCE optional
                                              CRITICALITY reject EXTENSION E-DCH-Information-Reconfig
     ID id-E-DCH-Serving-RL-ID
                                                                                                                    PRESENCE optional}
                                              CRITICALITY reject EXTENSION RL-ID
     ID id-E-DCH-768-Information-Reconfig
                                              CRITICALITY reject EXTENSION E-DCH-768-Information-Reconfig
                                                                                                                    PRESENCE optional}
     ID id-E-DCH-LCR-Information-Reconfig
                                              CRITICALITY reject EXTENSION E-DCH-LCR-Information-Reconfig
                                                                                                                    PRESENCE optional}
     ID id-NeedforIdleInterval
                                              CRITICALITY ignore EXTENSION NeedforIdleInterval
                                                                                                                    PRESENCE optional}
     TD id-CPC-InformationLCR
                                              CRITICALITY reject EXTENSION CPC-InformationLCR
                                                                                                                    PRESENCE optional}
                                                                                                                    PRESENCE optional }
     ID id-RNTI-Allocation-Indicator
                                              CRITICALITY ignore EXTENSION RNTI-Allocation-Indicator
                                                                                                                    PRESENCE optional
     ID id-DCH-MeasurementType-Indicator
                                              CRITICALITY reject EXTENSION DCH-MeasurementType-Indicator
     ID id-Multi-Carrier-EDCH-Reconfigure
                                              CRITICALITY reject EXTENSION Multi-Carrier-EDCH-Reconfigure
                                                                                                                    PRESENCE optional }
     ID id-MU-MIMO-Indicator
                                              CRITICALITY reject EXTENSION MU-MIMO-Indicator
                                                                                                                    PRESENCE optional },
RL-Information-RL-ReconfPrepTDD ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF RL-InformationIE-RL-ReconfPrepTDD
RL-InformationIE-RL-ReconfPrepTDD ::= SEQUENCE {
   rL-ID
   rL-Specific-DCH-Info
                                      RL-Specific-DCH-Info
                                                                      OPTIONAL,
   iE-Extensions
                                      OPTIONAL,
RL-InformationIE-RL-ReconfPrepTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
-- RADIO LINK RECONFIGURATION READY FDD
RadioLinkReconfigurationReadyFDD ::= SEQUENCE {
   protocolIEs
                                   ProtocolIE-Container
                                                             {{RadioLinkReconfigurationReadyFDD-IEs}},
   protocolExtensions
                                  ProtocolExtensionContainer {{RadioLinkReconfigurationReadyFDD-Extensions}}
                                                                                                                             OPTIONAL,
```

```
RadioLinkReconfigurationReadyFDD-IES RNSAP-PROTOCOL-IES ::= {
   { ID id-RL-InformationResponseList-RL-ReconfReadyFDD
                                                      CRITICALITY ignore TYPE RL-InformationResponseList-RL-ReconfReadyFDD
   PRESENCE optional } |
   { ID id-CriticalityDiagnostics
                                       CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                        PRESENCE optional
   . . .
                                               ::= SEQUENCE (SIZE (0..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-InformationResponse-
RL-InformationResponseList-RL-ReconfReadyFDD
RL-ReconfReadyFDD-IEs} }
RL-InformationResponse-RL-ReconfReadyFDD-IES RNSAP-PROTOCOL-IES ::= {
   PRESENCE mandatory }
RL-InformationResponseItem-RL-ReconfReadyFDD ::= SEQUENCE
   rL-ID
                                    RL-ID,
                                    UL-SIR
   max-UL-SIR
                                                                                                                    OPTIONAL,
   min-UL-STR
                                    III.-STR
                                                                                                                    OPTIONAL,
   maximumDLTxPower
                                    DL-Power
                                                                                                                    OPTIONAL,
   minimumDLTxPower
                                    DL-Power
                                                                                                                    OPTIONAL,
   not-Used-secondary-CCPCH-Info
                                                                                                                    OPTIONAL,
   dl-CodeInformationList
                                    DL-CodeInformationList-RL-ReconfReadyFDD
                                                                                                                    OPTIONAL,
   dCHInformationResponse
                                    DCH-InformationResponseList-RL-ReconfReadyFDD
                                                                                                                    OPTIONAL,
   not-Used-dSCHsToBeAddedOrModified
                                                                                                                    OPTIONAL,
   iE-Extensions
                                    ProtocolExtensionContainer { {RL-InformationResponseItem-RL-ReconfReadyFDD-ExtIEs} }
                                                                                                                    OPTIONAL,
RL-InformationResponseItem-RL-ReconfReadyFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   { ID id-DL-PowerBalancing-UpdatedIndicator
                                                  CRITICALITY ignore EXTENSION DL-PowerBalancing-UpdatedIndicator
   PRESENCE optional }
   PRESENCE
optional }|
    { ID id-Secondary-CPICH-Information-Change
                                                  CRITICALITY ignore EXTENSION Secondary-CPICH-Information-Change
   PRESENCE optional } |
   { ID id-EDCH-FDD-InformationResponse
                                                  CRITICALITY ignore EXTENSION EDCH-FDD-InformationResponse
       PRESENCE optional }
   { ID id-EDCH-RLSet-Id
                                                  CRITICALITY ignore EXTENSION RL-Set-ID
                  PRESENCE optional }
   { ID id-EDCH-FDD-DL-ControlChannelInformation
                                                  CRITICALITY ignore EXTENSION EDCH-FDD-DL-ControlChannelInformation
   PRESENCE optional } |
   { ID id-F-DPCH-SlotFormat
                                                  CRITICALITY ignore EXTENSION F-DPCH-SlotFormat
              PRESENCE optional }
   { ID id-HSDSCH-PreconfigurationInfo
                                                  CRITICALITY ignore EXTENSION HSDSCH-PreconfigurationInfo
       PRESENCE optional } |
   { ID id-Non-Serving-RL-Preconfig-Info
                                                  CRITICALITY ignore EXTENSION Non-Serving-RL-Preconfig-Info
       PRESENCE optional },
DL-CodeInformationList-RL-ReconfReadyFDD ::= ProtocolIE-Single-Container {{ DL-CodeInformationListIEs-RL-ReconfReadyFDD }}
```

```
DL-CodeInformationListIEs-RL-ReconfReadyFDD RNSAP-PROTOCOL-IES ::= {
   PRESENCE mandatory
                                                       ::= ProtocolIE-Single-Container { {DCH-InformationResponseListIEs-RL-ReconfReadyFDD} }
DCH-InformationResponseList-RL-ReconfReadyFDD
DCH-InformationResponseListIEs-RL-ReconfReadyFDD RNSAP-PROTOCOL-IES ::= {
                                    CRITICALITY ignore TYPE DCH-InformationResponse
    { ID id-DCH-InformationResponse
                                                                                        PRESENCE mandatory
RadioLinkReconfigurationReadyFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-HSDSCH-RNTI
                                            CRITICALITY ignore
                                                                  EXTENSION HSDSCH-RNTI
   PRESENCE optional }
     ID id-HSDSCH-FDD-Information-Response
                                            CRITICALITY ignore
                                                                                                                     PRESENCE optional } |
                                                                  EXTENSION HSDSCH-FDD-Information-Response
    { ID id-MAChs-ResetIndicator
                                            CRITICALITY ignore
                                                                  EXTENSION MAChs-ResetIndicator
   PRESENCE optional } |
     ID id-Fast-Reconfiguration-Permission
                                            CRITICALITY ignore
                                                                  EXTENSION Fast-Reconfiguration-Permission
                                                                                                                     PRESENCE optional }
     ID id-Continuous-Packet-Connectivity-HS-SCCH-Less-Information-Response
                                                                             CRITICALITY ignore
                                                                                                       EXTENSION Continuous-Packet-
Connectivity-HS-SCCH-Less-Information-Response
                                                PRESENCE optional }
    EXTENSION Additional-HS-Cell-RL-Reconf-Response
                                                                                                                            PRESENCE
optional }|
    { ID id-Additional-EDCH-Cell-Information-ResponseRLReconf
                                                              CRITICALITY ignore EXTENSION Additional-EDCH-Cell-Information-Response-
RLReconf-List
                     PRESENCE optional },
Additional-HS-Cell-RL-Reconf-Response ::= SEQUENCE (SIZE (1..maxNrOfHSDSCH-1)) OF Additional-HS-Cell-RL-Reconf-Response-ItemIEs
Additional-HS-Cell-RL-Reconf-Response-ItemIEs
                                           ::=SEOUENCE{
   hSPDSCH-RL-ID
                                                   RL-ID,
   hSDSCH-RNTI
                                                   HSDSCH-RNTI,
   hS-DSCH-FDD-Secondary-Serving-Information-Response HS-DSCH-FDD-Secondary-Serving-Information-Response,
                                 ProtocolExtensionContainer { { Additional-HS-Cell-RL-Reconf-Response-ItemIEs-ExtIEs} } OPTIONAL.
Additional-HS-Cell-RL-Reconf-Response-ItemIEs-ExtIEs
                                                  RNSAP-PROTOCOL-EXTENSION ::= {
-- RADIO LINK RECONFIGURATION READY TDD
  *****************
RadioLinkReconfigurationReadyTDD ::= SEQUENCE {
   protocolIEs
                                ProtocolIE-Container
                                                          {{RadioLinkReconfigurationReadyTDD-IEs}},
                                 ProtocolExtensionContainer {{RadioLinkReconfigurationReadyTDD-Extensions}}
   protocolExtensions
                                                                                                                      OPTIONAL,
```

```
RadioLinkReconfigurationReadyTDD-IES RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-InformationResponse-RL-ReconfReadyTDD
                          CRITICALITY ignore TYPE RL-InformationResponse-RL-ReconfReadyTDD
                                                                                            PRESENCE optional
    --This RL-InformationResponse-RL-ReconfReadyTDD is for the first RL repetition in the list.
    --Repetitions 2 and on are defined in Multiple-RL-InformationResponse-RL-ReconfReadyTDD.
    { ID id-CriticalityDiagnostics
                                          CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                              PRESENCE optional
    . . .
RL-InformationResponse-RL-ReconfReadyTDD ::= SEOUENCE {
   rI.-ID
                                  RL-ID,
   max-UL-SIR
                                  UL-SIR
                                                  OPTIONAL,
   min-UL-SIR
                                  UL-SIR
                                                  OPTIONAL,
   maximumDLTxPower
                                  DL-Power
                                                  OPTIONAL,
   minimumDLTxPower
                                  DL-Power
                                                  OPTIONAL,
    secondary-CCPCH-Info-TDD
                                  Secondary-CCPCH-Info-TDD
                                                             OPTIONAL,
    ul-CCTrCH-Information
                                  UL-CCTrCH-InformationList-RL-ReconfReadyTDD
                                                                                 OPTIONAL,
   dl-CCTrCH-Information
                                  DL-CCTrCH-InformationList-RL-ReconfReadyTDD OPTIONAL,
                                  DCH-InformationResponseList-RL-ReconfReadyTDD
    dCHInformationResponse
                                                                                OPTIONAL,
                                  DSCHToBeAddedOrModified-RL-ReconfReadyTDD
    dSCHsToBeAddedOrModified
                                                                            OPTIONAL,
    uSCHsToBeAddedOrModified
                                  USCHToBeAddedOrModified-RL-ReconfReadyTDD
                                                                            OPTIONAL,
                                  ProtocolExtensionContainer { {RL-InformationResponse-RL-ReconfReadyTDD-ExtIEs} }
   iE-Extensions
                                                                                                                   OPTIONAL,
RL-InformationResponse-RL-ReconfReadyTDD-ExtIES RNSAP-PROTOCOL-EXTENSION ::=
    { ID id-UL-TimingAdvanceCtrl-LCR
                                                         CRITICALITY ignore EXTENSION UL-TimingAdvanceCtrl-LCR
    PRESENCE optional } |
    --For 1.28Mcps TDD only
    { ID id-secondary-LCR-CCPCH-Info-TDD
                                                          CRITICALITY ignore EXTENSION Secondary-LCR-CCPCH-Info-TDD
                                                                                                                                  PRESENCE
optional }|
    --For 1.28Mcps TDD only
    { ID id-secondary-CCPCH-Info-RL-ReconfReadyTDD768
                                                          CRITICALITY ignore EXTENSION Secondary-CCPCH-Info-TDD768
                                                                                                                                  PRESENCE
optional }
   { ID id-UARFCNforNt
                                                          CRITICALITY ignore EXTENSION UARFON
                                                                                                                                  PRESENCE
optional },
    -- Applicable to 1.28Mcps TDD only
    . . .
                                                  ::= ProtocolIE-Single-Container {{UL-CCTrCHInformationListIEs-RL-ReconfReadyTDD}}}
UL-CCTrCH-InformationList-RL-ReconfReadyTDD
UL-CCTrCHInformationListIEs-RL-ReconfReadyTDD RNSAP-PROTOCOL-IES ::= {
    PRESENCE mandatory }
UL-CCTrCHInformationListIE-RL-ReconfReadyTDD ::= SEQUENCE (SIZE (0..maxNrOfCCTrCHs)) OF UL-CCTrCH-InformationItem-RL-ReconfReadyTDD
UL-CCTrCH-InformationItem-RL-ReconfReadyTDD ::= SEQUENCE {
    cCTrCH-ID
                                  CCTrCH-ID,
   ul-DPCH-AddInformation
                                  UL-DPCH-InformationAddList-RL-ReconfReadyTDD
                                                                                        OPTIONAL,
    --For 3.84Mcps TDD only
    ul-DPCH-ModifyInformation
                                  UL-DPCH-InformationModifyList-RL-ReconfReadyTDD
                                                                                            OPTIONAL,
```

```
ul-DPCH-DeleteInformation
                                  UL-DPCH-InformationDeleteList-RL-ReconfReadyTDD
                                                                                           OPTIONAL,
   iE-Extensions
                                  ProtocolExtensionContainer { {UL-CCTrCH-InformationItem-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
UL-CCTrCH-InformationItem-RL-ReconfReadyTDD-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-UL-DPCH-LCR-InformationAddListIE-RL-ReconfReadyTDD
                                                                 CRITICALITY ignore
                                                                                       EXTENSION UL-DPCH-LCR-InformationAddList-RL-
ReconfReadyTDD
                  PRESENCE optional }
    --For 1.28Mcps TDD only
    { ID id-UL-DPCH-InformationAddListIE-RL-ReconfReadyTDD768
                                                                CRITICALITY ignore
                                                                                       EXTENSION UL-DPCH-InformationAddList-RL-
ReconfReadyTDD768
                      PRESENCE optional },
    --For 7.68Mcps TDD only
UL-DPCH-LCR-InformationAddList-RL-ReconfReadyTDD ::= SEQUENCE {
   repetitionPeriod
                                  RepetitionPeriod,
   repetitionLength
                                  RepetitionLength,
    tDD-DPCHOffset
                                  TDD-DPCHOffset,
                                  UL-TimeslotLCR-Information,
   uL-TimeslotLCR-Info
   iE-Extensions
                                  ProtocolExtensionContainer { {UL-DPCH-LCR-InformationAddItem-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
    . . .
UL-DPCH-LCR-InformationAddItem-RL-ReconfReadyTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UL-DPCH-InformationAddList-RL-ReconfReadyTDD ::= ProtocolIE-Single-Container {{UL-DPCH-InformationAddListIEs-RL-ReconfReadyTDD}}
UL-DPCH-InformationAddListIEs-RL-ReconfReadyTDD RNSAP-PROTOCOL-IES ::= {
    PRESENCE optional }
UL-DPCH-InformationAddListIE-RL-ReconfReadyTDD ::= SEQUENCE {
   repetitionPeriod
                                  RepetitionPeriod,
   repetitionLength
                                  RepetitionLength,
    tDD-DPCHOffset
                                  TDD-DPCHOffset,
   rxTimingDeviationForTA
                                  RxTimingDeviationForTA
                                                                 OPTIONAL,
   uL-Timeslot-Information
                                  UL-Timeslot-Information,
                                  ProtocolExtensionContainer { {UL-DPCH-InformationAddItem-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
UL-DPCH-InformationAddItem-RL-ReconfReadyTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-RxTimingDeviationForTAext
                                         CRITICALITY ignore
                                                                EXTENSION RxTimingDeviationForTAext
                                                                                                           PRESENCE optional },
    . . .
UL-DPCH-InformationAddList-RL-ReconfReadyTDD768 ::= SEQUENCE {
   repetitionPeriod
                                  RepetitionPeriod,
   repetitionLength
                                  RepetitionLength,
                                  TDD-DPCHOffset,
    tDD-DPCHOffset
```

```
rxTimingDeviationForTA768
                                   RxTimingDeviationForTA768
                                                                    OPTIONAL,
   uL-Timeslot-Information768
                                   UL-Timeslot-Information768.
                                ProtocolExtensionContainer { {UL-DPCH-InformationAddItem-RL-ReconfReadyTDD768-ExtIEs} } OPTIONAL,
   iE-Extensions
UL-DPCH-InformationAddItem-RL-ReconfReadyTDD768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UL-DPCH-InformationModifyList-RL-ReconfReadyTDD ::= ProtocolIE-Single-Container {{UL-DPCH-InformationModifyListIEs-RL-ReconfReadyTDD}}
UL-DPCH-InformationModifyListIEs-RL-ReconfReadyTDD RNSAP-PROTOCOL-IES ::= {
   PRESENCE mandatory }
UL-DPCH-InformationModifyListIE-RL-ReconfReadyTDD::= SEQUENCE
   repetitionPeriod
                                RepetitionPeriod
                                                         OPTIONAL,
   repetitionLength
                                RepetitionLength
                                                         OPTIONAL,
   tDD-DPCHOffset
                                TDD-DPCHOffset
                                                         OPTIONAL.
   uL-Timeslot-InformationModifyList-RL-ReconfReadyTDD
                                                         UL-Timeslot-InformationModifyList-RL-ReconfReadyTDD
                                                                                                                         OPTIONAL,
   --For 3.84Mcps TDD only
   iE-Extensions
                                ProtocolExtensionContainer { {UL-DPCH-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
UL-DPCH-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   { ID id-UL-Timeslot-LCR-InformationModifyList-RL-ReconfReadyTDD CRITICALITY ignore
                                                                                  EXTENSION UL-TimeslotLCR-InformationModifyList-RL-
ReconfReadyTDD
                 PRESENCE optional }
   --For 1.28Mcps TDD only
   ReconfReadyTDD768
                     PRESENCE optional },
   --For 7.68Mcps TDD only
UL-TimeslotLCR-InformationModifyList-RL-ReconfReadyTDD::= SEQUENCE ( SIZE (1..maxNrOfTsLCR)) OF UL-TimeslotLCR-InformationModifyItem-RL-
ReconfReadyTDD
UL-TimeslotLCR-InformationModifyItem-RL-ReconfReadyTDD ::= SEQUENCE {
   timeSlotLCR
                                TimeSlotLCR.
   midambleShiftLCR
                                MidambleShiftLCR
                                                         OPTIONAL,
   t.FCI-Presence
                                TFCI-Presence
                                                     OPTIONAL,
   tDD-uL-Code-LCR-Information
                                   TDD-UL-Code-LCR-InformationModifyList-RL-ReconfReadyTDD
   iE-Extensions
                                ProtocolExtensionContainer { {UL-TimeslotLCR-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
   . . .
TDD-UL-Code-LCR-InformationModifyList-RL-ReconfReadyTDD::= SEQUENCE ( SIZE (1..maxNrOfDPCHsLCR)) OF TDD-UL-Code-LCR-InformationModifyItem-RL-
ReconfReadyTDD
TDD-UL-Code-LCR-InformationModifyItem-RL-ReconfReadyTDD ::= SEQUENCE {
   dPCH-ID
                                DPCH-ID,
```

```
tDD-ChannelisationCodeLCR
                                      TDD-ChannelisationCodeLCR
                                                                      OPTIONAL,
   iE-Extensions
                                   ProtocolExtensionContainer { {TDD-UL-Code-LCR-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
TDD-UL-Code-LCR-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    reject EXTENSION TDD-UL-DPCH-TimeSlotFormat-LCR
PRESENCE optional },
UL-TimeslotLCR-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UL-Timeslot-InformationModifyList-RL-ReconfReadyTDD::= SEQUENCE ( SIZE (1..maxNrOfTS)) OF UL-Timeslot-InformationModifyItem-RL-ReconfReadyTDD
UL-Timeslot-InformationModifyItem-RL-ReconfReadyTDD ::= SEOUENCE
   timeSlot
                                  TimeSlot,
   midambleShiftAndBurstType
                                              MidambleShiftAndBurstType
                                                                                 OPTIONAL.
    tFCI-Presence
                                  TFCI-Presence
                                                          OPTIONAL,
                               TDD-UL-Code-InformationModifyList-RL-ReconfReadyTDD
   uL-Code-Information
                                                                                         OPTIONAL,
                                   ProtocolExtensionContainer { {UL-Timeslot-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
    . . .
UL-Timeslot-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
TDD-UL-Code-InformationModifyList-RL-ReconfReadyTDD::= SEOUENCE ( SIZE (1..maxNrOfDPCHs)) OF TDD-UL-Code-InformationModifyItem-RL-ReconfReadyTDD
TDD-UL-Code-InformationModifyItem-RL-ReconfReadyTDD ::= SEQUENCE {
   dPCH-ID
                                  DPCH-ID,
    tDD-ChannelisationCode
                                  TDD-ChannelisationCode
                                                              OPTIONAL,
   iE-Extensions
                                  ProtocolExtensionContainer { {TDD-UL-Code-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
TDD-UL-Code-InformationModifyItem-RL-ReconfReadyTDD-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
UL-Timeslot-InformationModifyList-RL-ReconfReadyTDD768::= SEQUENCE ( SIZE (1..maxNrOfTS)) OF UL-Timeslot-InformationModifyItem-RL-ReconfReadyTDD768
UL-Timeslot-InformationModifyItem-RL-ReconfReadyTDD768 ::= SEQUENCE {
   timeSlot
                                  TimeSlot,
   midambleShiftAndBurstType768
                                  MidambleShiftAndBurstType768
                                                                         OPTIONAL,
                                  TFCI-Presence
                                                          OPTIONAL,
    tFCI-Presence
   uL-Code-Information768
                                  TDD-UL-Code-InformationModifyList-RL-ReconfReadyTDD768
                                                                                             OPTIONAL,
                                  ProtocolExtensionContainer { {UL-Timeslot-InformationModifyItem-RL-ReconfReadyTDD768-ExtIEs} } OPTIONAL,
   iE-Extensions
    . . .
```

```
UL-Timeslot-InformationModifyItem-RL-ReconfReadyTDD768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
TDD-UL-Code-InformationModifyList-RL-ReconfReadyTDD768::= SEQUENCE ( SIZE (1..maxNrOfDPCHs768)) OF TDD-UL-Code-InformationModifyItem-RL-
ReconfReadyTDD768
TDD-UL-Code-InformationModifyItem-RL-ReconfReadyTDD768 ::= SEQUENCE {
                                DPCH-ID,
   tDD-ChannelisationCode768
                                TDD-ChannelisationCode768
                                                            OPTIONAL,
                                ProtocolExtensionContainer { {TDD-UL-Code-InformationModifyItem-RL-ReconfReadyTDD768-ExtIEs} } OPTIONAL,
   iE-Extensions
   . . .
TDD-UL-Code-InformationModifyItem-RL-ReconfReadyTDD768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UL-DPCH-InformationDeleteList-RL-ReconfReadyTDD ::= ProtocolIE-Single-Container {{UL-DPCH-InformationDeleteListIEs-RL-ReconfReadyTDD}}
UL-DPCH-InformationDeleteListIEs-RL-ReconfReadyTDD RNSAP-PROTOCOL-IES ::= {
   PRESENCE mandatory }
UL-DPCH-InformationDeleteListIE-RL-ReconfReadyTDD ::= SEQUENCE (SIZE (0..maxNrOfDPCHs)) OF UL-DPCH-InformationDeleteItem-RL-ReconfReadyTDD
UL-DPCH-InformationDeleteItem-RL-ReconfReadyTDD ::= SEQUENCE {
   dPCH-ID
                            DPCH-ID,
                                ProtocolExtensionContainer { {UL-DPCH-InformationDeleteList-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
UL-DPCH-InformationDeleteList-RL-ReconfReadyTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
                                              ::= ProtocolIE-Single-Container {{DL-CCTrCHInformationListIEs-RL-ReconfReadyTDD}}}
DL-CCTrCH-InformationList-RL-ReconfReadyTDD
DL-CCTrCHInformationListIEs-RL-ReconfReadyTDD RNSAP-PROTOCOL-IES ::= {
   PRESENCE mandatory }
DL-CCTrCHInformationListIE-RL-ReconfReadyTDD ::= SEQUENCE (SIZE (0..maxNrOfCCTrCHs)) OF DL-CCTrCH-InformationItem-RL-ReconfReadyTDD
DL-CCTrCH-InformationItem-RL-ReconfReadyTDD ::= SEQUENCE {
   cCTrCH-ID
                                CCTrCH-ID,
                                DL-DPCH-InformationAddList-RL-ReconfReadyTDD
   dl-DPCH-AddInformation
                                                                                  OPTIONAL,
   --For 3.84Mcps TDD only
   dl-DPCH-ModifyInformation
                                DL-DPCH-InformationModifyList-RL-ReconfReadyTDD
                                                                                  OPTIONAL,
   dl-DPCH-DeleteInformation
                                DL-DPCH-InformationDeleteList-RL-ReconfReadyTDD
                                                                                  OPTIONAL,
                                ProtocolExtensionContainer { {DL-CCTrCH-InformationItem-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
```

```
DL-CCTrCH-InformationItem-RL-ReconfReadyTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-DL-DPCH-LCR-InformationAddListIE-RL-ReconfReadyTDD CRITICALITY ignore
                                                                                                          DL-DPCH-LCR-InformationAddList-RL-
                                                                                            EXTENSION
                   PRESENCE optional |
ReconfReadyTDD
    --For 1.28Mcps TDD only
    { ID id-CCTrCH-Maximum-DL-Power-RL-ReconfReadyTDD
                                                                    CRITICALITY ignore
                                                                                            EXTENSION DL-Power
    PRESENCE optional }
    -- Applicable to 3.84Mcps TDD and 7.68Mcps TDD only, this is a DCH type CCTrCH power
    { ID id-CCTrCH-Minimum-DL-Power-RL-ReconfReadyTDD
                                                                    CRITICALITY ignore
                                                                                            EXTENSION DL-Power
    PRESENCE optional
    -- Applicable to 3.84Mcps TDD and 7.68Mcps TDD only, this is a DCH type CCTrCH power
    { ID id-DL-DPCH-InformationAddListIE-RL-ReconfReadyTDD768
                                                                    CRITICALITY ignore
                                                                                            EXTENSION DL-DPCH-InformationAddList-RL-
ReconfReadyTDD768
                                       PRESENCE optional |
    --For 7.68Mcps TDD only
    { ID id-DL-DPCH-InformationDeleteList768-RL-ReconfReadyTDD
                                                                    CRITICALITY ignore
                                                                                            EXTENSION DL-DPCH-InformationDeleteList768-RL-
ReconfReadyTDD
                   PRESENCE optional },
    . . .
DL-DPCH-LCR-InformationAddList-RL-ReconfReadyTDD ::= SEQUENCE {
                                    RepetitionPeriod,
   repetitionPeriod
                                    RepetitionLength,
   repetitionLength
                                    TDD-DPCHOffset,
    tDD-DPCHOffset
    dL-TimeslotLCR-Info
                                    DL-TimeslotLCR-Information,
    iE-Extensions
                                    ProtocolExtensionContainer { {DL-DPCH-LCR-InformationAddItem-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
    . . .
DL-DPCH-LCR-InformationAddItem-RL-ReconfReadyTDD-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
DL-DPCH-InformationAddList-RL-ReconfReadyTDD ::= ProtocolIE-Single-Container {{DL-DPCH-InformationAddListIEs-RL-ReconfReadyTDD}}
DL-DPCH-InformationAddListIEs-RL-ReconfReadyTDD RNSAP-PROTOCOL-IES ::= {
    { ID id-DL-DPCH-InformationAddListIE-RL-ReconfReadyTDD CRITICALITY ignore TYPE DL-DPCH-InformationAddListIE-RL-ReconfReadyTDD
    PRESENCE mandatory }
DL-DPCH-InformationAddListIE-RL-ReconfReadyTDD ::= SEQUENCE {
                                    RepetitionPeriod,
    repetitionPeriod
    repetitionLength
                                    RepetitionLength,
    tDD-DPCHOffset
                                    TDD-DPCHOffset,
    dL-Timeslot-Information
                                    DL-Timeslot-Information,
   iE-Extensions
                                    ProtocolExtensionContainer { {DL-DPCH-InformationAddItem-RL-ReconfReadvTDD-ExtIEs} } OPTIONAL.
DL-DPCH-InformationAddItem-RL-ReconfReadyTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
DL-DPCH-InformationAddList-RL-ReconfReadyTDD768 ::= SEQUENCE {
   repetitionPeriod
                                RepetitionPeriod,
   repetitionLength
                                RepetitionLength.
   tDD-DPCHOffset
                                TDD-DPCHOffset.
   dL-Timeslot-Information768
                                DL-Timeslot-Information768.
                                ProtocolExtensionContainer { {DL-DPCH-InformationAddItem-RL-ReconfReadyTDD768-ExtIEs} } OPTIONAL,
   iE-Extensions
   . . .
DL-DPCH-InformationAddItem-RL-ReconfReadyTDD768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-DPCH-InformationModifyList-RL-ReconfReadyTDD ::= ProtocolIE-Single-Container {{DL-DPCH-InformationModifyListIEs-RL-ReconfReadyTDD}}
DL-DPCH-InformationModifyListIEs-RL-ReconfReadyTDD RNSAP-PROTOCOL-IES ::= {
   PRESENCE mandatory }
DL-DPCH-InformationModifyListIE-RL-ReconfReadyTDD ::= SEQUENCE
   repetitionPeriod
                                RepetitionPeriod
                                                         OPTIONAL,
   repetitionLength
                                RepetitionLength
                                                         OPTIONAL,
   tDD-DPCHOffset
                                TDD-DPCHOffset
                                                         OPTIONAL,
   dL-Timeslot-InformationModifyList-RL-ReconfReadyTDD
                                                         DL-Timeslot-InformationModifyList-RL-ReconfReadyTDD
                                                                                                                         OPTIONAL,
   --For 3.84Mcps TDD only
                                ProtocolExtensionContainer { {DL-DPCH-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
   . . .
DL-DPCH-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   { ID id-DL-Timeslot-LCR-InformationModifyList-RL-ReconfReadyTDD CRITICALITY ignore
                                                                                  EXTENSION DL-TimeslotLCR-InformationModifyList-RL-
ReconfReadyTDD
                 PRESENCE optional }
   --For 1.28Mcps TDD only
   PRESENCE optional },
ReconfReadyTDD768
   --For 7.68Mcps TDD only
   . . .
DL-TimeslotLCR-InformationModifyList-RL-ReconfReadyTDD::= SEQUENCE ( SIZE (1..maxNrOfTsLCR)) OF DL-TimeslotLCR-InformationModifyItem-RL-
ReconfReadyTDD
DL-TimeslotLCR-InformationModifyItem-RL-ReconfReadyTDD ::= SEQUENCE {
   timeSlotLCR
                                TimeSlotLCR,
   midambleShiftLCR
                                MidambleShiftLCR
                                                         OPTIONAL,
   tFCI-Presence
                                TFCI-Presence
                                                     OPTIONAL,
   tDD-dL-Code-LCR-Information
                                TDD-DL-Code-LCR-InformationModifyList-RL-ReconfReadyTDD
                                                                                       OPTIONAL,
   iE-Extensions
                                ProtocolExtensionContainer { {DL-TimeslotLCR-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
TDD-DL-Code-LCR-InformationModifyList-RL-ReconfReadyTDD::= SEQUENCE ( SIZE (1..maxNrOfDPCHsLCR)) OF TDD-DL-Code-LCR-InformationModifyItem-RL-
ReconfReadyTDD
```

```
TDD-DL-Code-LCR-InformationModifyItem-RL-ReconfReadyTDD ::= SEQUENCE {
    dPCH-ID
                                  DPCH-ID.
    tDD-ChannelisationCodeLCR
                                  TDD-ChannelisationCodeLCR
                                                                OPTIONAL.
   iE-Extensions
                                  ProtocolExtensionContainer { {TDD-DL-Code-LCR-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
TDD-DL-Code-LCR-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-TDD-DL-DPCH-TimeSlotFormatModifyItem-LCR-RL-ReconfReadyTDD
                                                                       CRITICALITY reject
                                                                                                   EXTENSION TDD-DL-DPCH-TimeSlotFormat-LCR
       PRESENCE optional },
    . . .
DL-TimeslotLCR-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-Maximum-DL-Power-TimeslotLCR-InformationModifyItem-RL-ReconfReadyTDD
                                                                              CRITICALITY ignore
                                                                                                              DL-Power
                                                                                                                                PRESENCE
                                                                                                   EXTENSION
optional }
    { ID id-Minimum-DL-Power-TimeslotLCR-InformationModifyItem-RL-ReconfReadyTDD CRITICALITY ignore
                                                                                                   EXTENSION
                                                                                                              DL-Power
                                                                                                                                PRESENCE
optional },
DL-Timeslot-InformationModifyList-RL-ReconfReadyTDD::= SEQUENCE ( SIZE (1..maxNrOfTS)) OF DL-Timeslot-InformationModifyList-RL-ReconfReadyTDD
DL-Timeslot-InformationModifyItem-RL-ReconfReadyTDD ::= SEQUENCE
    timeSlot
                                  TimeSlot,
                                  MidambleShiftAndBurstType
   midambleShiftAndBurstType
                                                                    OPTIONAL,
    tFCI-Presence
                                  TFCI-Presence
                                                         OPTIONAL,
   dL-Code-Information
                                  TDD-DL-Code-InformationModifyList-RL-ReconfReadyTDD
                                                                                           OPTIONAL,
                                  ProtocolExtensionContainer { {DL-Timeslot-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
    . . .
DL-Timeslot-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
TDD-DL-Code-InformationModifyList-RL-ReconfReadyTDD::= SEOUENCE ( SIZE (1..maxNrOfDPCHs)) OF TDD-DL-Code-InformationModifyItem-RL-ReconfReadyTDD
TDD-DL-Code-InformationModifyItem-RL-ReconfReadyTDD ::= SEQUENCE
   dPCH-ID
                                  DPCH-ID,
    tDD-ChannelisationCode
                                  TDD-ChannelisationCode
                                                            OPTIONAL.
                                  ProtocolExtensionContainer { {TDD-DL-Code-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
TDD-DL-Code-InformationModifyItem-RL-ReconfReadyTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    PRESENCE optional },
    -- This IE shall not be used
DL-Timeslot-InformationModifyList-RL-ReconfReadyTDD768::= SEQUENCE ( SIZE (1..maxNrOfTS)) OF DL-Timeslot-InformationModifyItem-RL-ReconfReadyTDD768
```

```
DL-Timeslot-InformationModifyItem-RL-ReconfReadyTDD768 ::= SEQUENCE {
   timeSlot
                                 TimeSlot.
   midambleShiftAndBurstType768
                                 MidambleShiftAndBurstType768
                                                                       OPTIONAL.
   t.FCI-Presence
                                 TFCI-Presence
                                                        OPTIONAL.
   dL-Code-Information768
                                 TDD-DL-Code-InformationModifyList-RL-ReconfReadyTDD768
                                                                                            OPTIONAL.
   iE-Extensions
                                 ProtocolExtensionContainer { {DL-Timeslot-InformationModifyItem-RL-ReconfReadyTDD768-ExtIEs} } OPTIONAL,
DL-Timeslot-InformationModifyItem-RL-ReconfReadyTDD768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
TDD-DL-Code-InformationModifyList-RL-ReconfReadyTDD768::= SEQUENCE ( SIZE (1..maxNrOfDPCHs768)) OF TDD-DL-Code-InformationModifyItem-RL-
ReconfReadyTDD768
TDD-DL-Code-InformationModifyItem-RL-ReconfReadyTDD768 ::= SEQUENCE {
   dPCH-ID768
                                 DPCH-ID768,
   tDD-ChannelisationCode768
                                 TDD-ChannelisationCode768
                                                                OPTIONAL.
   iE-Extensions
                                  ProtocolExtensionContainer { {TDD-DL-Code-InformationModifyItem-RL-ReconfReadyTDD768-ExtIEs} } OPTIONAL,
TDD-DL-Code-InformationModifyItem-RL-ReconfReadyTDD768-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
DL-DPCH-InformationDeleteList-RL-ReconfReadyTDD ::= ProtocolIE-Single-Container {{DL-DPCH-InformationDeleteListIEs-RL-ReconfReadyTDD}}
DL-DPCH-InformationDeleteListIEs-RL-ReconfReadyTDD RNSAP-PROTOCOL-IES ::= {
    PRESENCE mandatory }
DL-DPCH-InformationDeleteListIE-RL-ReconfReadyTDD ::= SEQUENCE (SIZE (0..maxNrOfDPCHs)) OF DL-DPCH-InformationDeleteItem-RL-ReconfReadyTDD
DL-DPCH-InformationDeleteItem-RL-ReconfReadyTDD ::= SEQUENCE {
   dPCH-ID
                              DPCH-ID,
   iE-Extensions
                                  ProtocolExtensionContainer { {DL-DPCH-InformationDeleteList-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
DL-DPCH-InformationDeleteList-RL-ReconfReadyTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   . . .
DL-DPCH-InformationDeleteList768-RL-ReconfReadyTDD ::= SEQUENCE (SIZE (0..maxNrOfDPCHs768)) OF DL-DPCH-InformationDeleteItem768-RL-ReconfReadyTDD
DL-DPCH-InformationDeleteItem768-RL-ReconfReadyTDD ::= SEQUENCE {
   dPCH-ID768
                                 DPCH-ID768,
   iE-Extensions
                                  ProtocolExtensionContainer { {DL-DPCH-InformationDeleteList768-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
```

```
DL-DPCH-InformationDeleteList768-RL-ReconfReadyTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
                                                    ::= ProtocolIE-Single-Container { {DCH-InformationResponseListIEs-RL-ReconfReadyTDD} }
DCH-InformationResponseList-RL-ReconfReadyTDD
DCH-InformationResponseListIEs-RL-ReconfReadyTDD RNSAP-PROTOCOL-IES ::= {
   { ID id-DCH-InformationResponse
                                   CRITICALITY ignore TYPE DCH-InformationResponse
                                                                                    PRESENCE mandatory
DSCHToBeAddedOrModified-RL-ReconfReadyTDD
                                              ::= ProtocolIE-Single-Container { {DSCHToBeAddedOrModifiedIEs-RL-ReconfReadyTDD} }
DSCHTOBeAddedOrModifiedIEs-RL-ReconfReadvTDD RNSAP-PROTOCOL-IES ::= {
   PRESENCE mandatory }
DSCHTOBeAddedOrModifiedList-RL-ReconfReadyTDD ::= SEQUENCE (SIZE (0..maxNoOfDSCHs)) OF DSCHTOBeAddedOrModifiedItem-RL-ReconfReadyTDD
DSCHToBeAddedOrModifiedItem-RL-ReconfReadyTDD ::= SEQUENCE {
                        DSCH-ID,
   transportFormatManagement TransportFormatManagement,
   dSCH-FlowControlInformation DSCH-FlowControlInformation,
   bindingID
                        BindingID OPTIONAL,
   transportLayerAddress TransportLayerAddress OPTIONAL,
                        ProtocolExtensionContainer { {DSCHTOBeAddedOrModifiedItem-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
DSCHTOBeAddedOrModifiedItem-RL-ReconfReadyTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
USCHToBeAddedOrModified-RL-ReconfReadyTDD
                                             ::= ProtocolIE-Single-Container { { USCHTOBeAddedOrModifiedIEs-RL-ReconfReadyTDD}
}USCHTOBEAddedOrModifiedIEs-RL-ReconfReadyTDD RNSAP-PROTOCOL-IES ::= {
   PRESENCE mandatory }
USCHTOBeAddedOrModifiedList-RL-ReconfReadyTDD ::= SEQUENCE (SIZE (0..maxNoOfUSCHs)) OF USCHTOBeAddedOrModifiedItem-RL-ReconfReadyTDD
USCHToBeAddedOrModifiedItem-RL-ReconfReadyTDD ::= SEQUENCE {
   uSCH-ID
                        USCH-ID,
   transportFormatManagement TransportFormatManagement,
   bindingID
                        BindingID OPTIONAL,
   transportLayerAddress TransportLayerAddress OPTIONAL,
   iE-Extensions
                        ProtocolExtensionContainer { {USCHToBeAddedOrModifiedItem-RL-ReconfReadyTDD-ExtIEs} } OPTIONAL,
   . . .
USCHTOBeAddedOrModifiedItem-RL-ReconfReadyTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
RadioLinkReconfigurationReadyTDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-HSDSCH-RNTI
                                           CRITICALITY ignore EXTENSION HSDSCH-RNTI
                                                                                                              PRESENCE optional}
     ID id-DSCH-RNTI
                                            CRITICALITY ignore EXTENSION DSCH-RNTI
                                                                                                              PRESENCE optional}
     ID id-HSDSCH-TDD-Information-Response
                                           CRITICALITY ignore EXTENSION HSDSCH-TDD-Information-Response
                                                                                                              PRESENCE optional}
     ID id-MAChs-ResetIndicator
                                           CRITICALITY ignore EXTENSION MAChs-ResetIndicator
                                                                                                              PRESENCE optional}
     PRESENCE optional}|
-- This is for RL repetitions 2 and on in RL list.
                                                                                                              PRESENCE optional}
     ID id-E-DCH-Information-Response
                                            CRITICALITY ignore EXTENSION E-DCH-Information-Response
     ID id-E-DCH-768-Information-Response
                                            CRITICALITY ignore EXTENSION E-DCH-768-Information-Response
                                                                                                              PRESENCE optional}
                                                                                                              PRESENCE optional}
     ID id-E-DCH-LCR-Information-Response
                                            CRITICALITY ignore EXTENSION E-DCH-LCR-Information-Response
                                            CRITICALITY ignore EXTENSION ControlGAP
                                                                                                              PRESENCE optional }
    { ID id-PowerControlGAP
   -- Applicable to 1.28Mcps TDD only
     ID id-IdleIntervalInformation
                                           CRITICALITY ignore EXTENSION IdleIntervalInformation
                                                                                                              PRESENCE optional }
     ID id-ContinuousPacketConnectivity-DRX-Information-ResponseLCR
                                                                  CRITICALITY ignore EXTENSION ContinuousPacketConnectivity-DRX-Information-
              PRESENCE optional |
ResponseLCR
   { ID id-HS-DSCH-Semi-PersistentScheduling-Information-ResponseLCR
                                                                  CRITICALITY ignore EXTENSION HS-DSCH-Semi-PersistentScheduling-
                         PRESENCE optional |
Information-ResponseLCR
    { ID id-E-DCH-Semi-PersistentScheduling-Information-ResponseLCR
                                                                  CRITICALITY ignore EXTENSION E-DCH-Semi-PersistentScheduling-Information-
ResponseLCR
              PRESENCE optional |
     ID id-E-RNTI-For-FACH
                                            CRITICALITY ignore EXTENSION E-RNTI
                                                                                                              PRESENCE optional }
     ID id-H-RNTI-For-FACH
                                           CRITICALITY ignore EXTENSION HSDSCH-RNTI
                                                                                                              PRESENCE optional}
     ID id-DCH-MeasurementOccasion-Information CRITICALITY reject EXTENSION DCH-MeasurementOccasion-Information
                                                                                                              PRESENCE optional }
     ID id-Multi-Carrier-EDCH-Response
                                           CRITICALITY ignore EXTENSION Multi-Carrier-EDCH-Information-Response
                                                                                                              PRESENCE optional }
    ID id-MU-MIMO-InformationLCR
                                           CRITICALITY reject EXTENSION MU-MIMO-InformationLCR
                                                                                                              PRESENCE optional },
Multiple-RL-InformationResponse-RL-ReconfReadyTDD ::= SEQUENCE (SIZE (1..maxNrOfRLs-1)) OF RL-InformationResponse-RL-ReconfReadyTDD
  *****************
-- RADIO LINK RECONFIGURATION COMMIT
  RadioLinkReconfigurationCommit ::= SEOUENCE {
   protocolIEs
                                 ProtocolIE-Container
                                                          {{RadioLinkReconfigurationCommit-IEs}},
                                ProtocolExtensionContainer {{RadioLinkReconfigurationCommit-Extensions}}
   protocolExtensions
                                                                                                                    OPTIONAL,
RadioLinkReconfigurationCommit-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-CFN
                            CRITICALITY ignore TYPE CFN
                                                                         PRESENCE mandatory
     ID id-Active-Pattern-Sequence-Information CRITICALITY ignore TYPE Active-Pattern-Sequence-Information
                                                                                                               PRESENCE optional \,--FDD
only
RadioLinkReconfigurationCommit-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
   { ID id-Fast-Reconfiguration-Mode CRITICALITY reject EXTENSION Fast-Reconfiguration-Mode PRESENCE optional }, --FDD only
   . . .
```

```
******************
-- RADIO LINK RECONFIGURATION FAILURE
  ******************
RadioLinkReconfigurationFailure ::= SEQUENCE {
                                                            {{RadioLinkReconfigurationFailure-IEs}},
   protocolIEs
                                  ProtocolIE-Container
                                  ProtocolExtensionContainer {{RadioLinkReconfigurationFailure-Extensions}}
   protocolExtensions
                                                                                                                          OPTIONAL,
   . . .
RadioLinkReconfigurationFailure-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-CauseLevel-RL-ReconfFailure
                                         CRITICALITY ignore TYPE CauseLevel-RL-Reconffailure PRESENCE mandatory }
     ID id-CriticalityDiagnostics
                                         CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                             PRESENCE optional },
CauseLevel-RL-ReconfFailure ::= CHOICE {
                      GeneralCauseList-RL-ReconfFailure,
   generalCause
   rLSpecificCause
                      RLSpecificCauseList-RL-ReconfFailure,
    . . .
GeneralCauseList-RL-ReconfFailure ::= SEQUENCE {
   cause
                                             Cause,
                                             ProtocolExtensionContainer { { GeneralCauseItem-RL-ReconfFailure-ExtIEs} }
   iE-Extensions
   OPTIONAL,
    . . .
GeneralCauseItem-RL-ReconfFailure-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RLSpecificCauseList-RL-ReconfFailure ::= SEQUENCE {
   rL-ReconfigurationFailureList-RL-ReconfFailure
                                                     RL-ReconfigurationFailureList-RL-ReconfFailure
                                                                                                           OPTIONAL,
   iE-Extensions
                                                     ProtocolExtensionContainer { RLSpecificCauseItem-RL-ReconfFailure-ExtIEs} }
   OPTIONAL,
RLSpecificCauseItem-RL-ReconfFailure-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RL-ReconfigurationFailureList-RL-Reconffailure ::= SEQUENCE (SIZE (0..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-ReconfigurationFailure-RL-
ReconfFailure-IEs} }
RL-ReconfigurationFailure-RL-ReconfFailure-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-ReconfigurationFailure-RL-ReconfFail CRITICALITY ignore TYPE RL-ReconfigurationFailure-RL-ReconfFail
                                                                                                                  PRESENCE mandatory
```

```
RL-ReconfigurationFailure-RL-ReconfFail ::= SEQUENCE {
   rL-ID
                          RL-ID.
   cause
                          Cause,
   iE-Extensions
                          ProtocolExtensionContainer { {RL-ReconfigurationFailure-RL-ReconfFailure-ExtIEs} } OPTIONAL,
RL-ReconfigurationFailure-RL-ReconfFailure-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   EXTENSION Max-UE-DTX-Cycle
                                                                                  PRESENCE conditional },
   -- This IE shall be present if the Cause IE is set to "Continuous Packet Connectivity UE DTX Cycle not Available".
   . . .
RadioLinkReconfigurationFailure-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    ******************
-- RADIO LINK RECONFIGURATION CANCEL
    RadioLinkReconfigurationCancel ::= SEQUENCE {
   protocolIEs
                              ProtocolIE-Container
                                                     {{RadioLinkReconfigurationCancel-IEs}},
                              ProtocolExtensionContainer {{RadioLinkReconfigurationCancel-Extensions}}
   protocolExtensions
                                                                                                           OPTIONAL,
RadioLinkReconfigurationCancel-IEs RNSAP-PROTOCOL-IES ::= {
RadioLinkReconfigurationCancel-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
     ***************
-- RADIO LINK RECONFIGURATION REQUEST FDD
  RadioLinkReconfigurationRequestFDD ::= SEOUENCE {
                                                     {{RadioLinkReconfigurationRequestFDD-IEs}},
   protocolIEs
                              ProtocolIE-Container
                             ProtocolExtensionContainer {{RadioLinkReconfigurationRequestFDD-Extensions}}
   protocolExtensions
                                                                                                              OPTIONAL,
RadioLinkReconfigurationRequestFDD-IEs RNSAP-PROTOCOL-IES ::= {
    ID id-AllowedQueuingTime
                                                 CRITICALITY reject TYPE AllowedQueuingTime
                                                                                                              PRESENCE optional
```

```
ID id-UL-DPCH-Information-RL-ReconfRqstFDD
                                                         CRITICALITY reject TYPE UL-DPCH-Information-RL-ReconfRqstFDD
                                                                                                                               PRESENCE optional
     ID id-DL-DPCH-Information-RL-ReconfRqstFDD
                                                         CRITICALITY reject TYPE DL-DPCH-Information-RL-ReconfRqstFDD
                                                                                                                               PRESENCE optional
     ID id-FDD-DCHs-to-Modify
                                                         CRITICALITY reject TYPE FDD-DCHs-to-Modify
                                                                                                                               PRESENCE optional
     ID id-DCHs-to-Add-FDD
                                                         CRITICALITY reject TYPE DCH-FDD-Information
                                                                                                                               PRESENCE optional
     ID id-DCH-DeleteList-RL-ReconfRqstFDD
                                                         CRITICALITY reject TYPE DCH-DeleteList-RL-ReconfRqstFDD
                                                                                                                               PRESENCE optional
     ID id-Transmission-Gap-Pattern-Sequence-Information CRITICALITY reject TYPE Transmission-Gap-Pattern-Sequence-Information PRESENCE optional
UL-DPCH-Information-RL-ReconfRgstFDD ::= SEQUENCE {
   iE-Extensions
                                   ProtocolExtensionContainer { {UL-DPCH-Information-RL-ReconfRqstFDD-ExtIEs} } OPTIONAL,
    . . .
UL-DPCH-Information-RL-ReconfRqstFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    EXTENSION UL-DPDCHIndicatorEDCH
                                                                                              PRESENCE optional },
    . . .
DL-DPCH-Information-RL-ReconfRqstFDD ::= SEQUENCE {
    tFCS
                                   TFCS
                                          OPTIONAL,
    tFCI-SignallingMode
                                   TFCI-SignallingMode OPTIONAL,
   limitedPowerIncrease
                                   LimitedPowerIncrease
                                                         OPTIONAL,
                                   ProtocolExtensionContainer { {DL-DPCH-Information-RL-ReconfRqstFDD-ExtIEs} } OPTIONAL,
   iE-Extensions
DL-DPCH-Information-RL-ReconfRgstFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DCH-DeleteList-RL-ReconfRqstFDD
                                          ::= SEQUENCE (SIZE (0..maxNrOfDCHs)) OF DCH-DeleteItem-RL-ReconfRqstFDD
DCH-DeleteItem-RL-ReconfRqstFDD ::= SEQUENCE {
   dCH-ID
                                   DCH-ID.
                                   ProtocolExtensionContainer { {DCH-DeleteItem-RL-ReconfRqstFDD-ExtIEs} } OPTIONAL,
   iE-Extensions
DCH-DeleteItem-RL-ReconfRgstFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RadioLinkReconfigurationRequestFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-RL-ReconfigurationRequestFDD-RL-InformationList CRITICALITY ignore EXTENSION RL-ReconfigurationRequestFDD-RL-InformationList
    PRESENCE
               optional}|
```

```
{ ID id-DL-ReferencePowerInformation
                                                            CRITICALITY ignore EXTENSION DL-ReferencePowerInformation
    PRESENCE optional }|
     ID id-HSDSCH-FDD-Information
                                                    CRITICALITY reject EXTENSION HSDSCH-FDD-Information
                                                                                                                                PRESENCE optional } |
    ID id-HSDSCH-Information-to-Modify-Unsynchronised CRITICALITY reject
                                                                                EXTENSION HSDSCH-Information-to-Modify-Unsynchronised PRESENCE
optional}|
                                                                                                                                PRESENCE optional}
     ID id-HSDSCH-MACdFlows-to-Add
                                                                            EXTENSION HSDSCH-MACdFlows-Information
                                                    CRITICALITY reject
     ID id-HSDSCH-MACdFlows-to-Delete
                                                    CRITICALITY reject
                                                                            EXTENSION HSDSCH-MACdFlows-to-Delete
                                                                                                                                PRESENCE optional}
     ID id-HSPDSCH-RL-ID
                                                    CRITICALITY reject
                                                                            EXTENSION RL-ID
       PRESENCE optional |
    { ID id-EDPCH-Information-RLReconfRequest-FDD
                                                    CRITICALITY reject
                                                                            EXTENSION EDPCH-Information-RLReconfRequest-FDD
                                                                                                                                        PRESENCE
optional}|
    { ID id-EDCH-FDD-Information
                                                    CRITICALITY reject
                                                                            EXTENSION EDCH-FDD-Information
    PRESENCE optional }
    { ID id-EDCH-FDD-Information-To-Modify
                                                    CRITICALITY reject
                                                                            EXTENSION EDCH-FDD-Information-To-Modify
                                                                                                                                PRESENCE optional | |
    ID id-EDCH-MACdFlows-To-Add
                                                    CRITICALITY reject
                                                                            EXTENSION EDCH-MACdFlows-Information
                                                                                                                                        PRESENCE
optional}|
    { ID id-EDCH-MACdFlows-To-Delete
                                                    CRITICALITY reject
                                                                            EXTENSION EDCH-MACdFlows-To-Delete
                                                                                                                                        PRESENCE
optional}
    { ID id-Serving-EDCHRL-Id
                                                    CRITICALITY reject
                                                                            EXTENSION EDCH-Serving-RL
    PRESENCE optional } |
    { ID id-CPC-Information
                                                    CRITICALITY reject
                                                                            EXTENSION CPC-Information
    PRESENCE optional } |
    { ID id-NoOfTargetCellHS-SCCH-Order
                                                    CRITICALITY ignore
                                                                            EXTENSION NoOfTargetCellHS-SCCH-Order
                                                                                                                                        PRESENCE
optional}|
    { ID id-Additional-HS-Cell-Information-RL-Reconf-Req
                                                            CRITICALITY reject
                                                                                     EXTENSION Additional-HS-Cell-Information-RL-Reconf-Reg
           PRESENCE optional } |
    { ID id-UE-AggregateMaximumBitRate
                                                    CRITICALITY ignore
                                                                            EXTENSION UE-AggregateMaximumBitRate
                                                                                                                                        PRESENCE
optional }|
    { ID id-Additional-EDCH-Cell-Information-RL-Reconf-Req CRITICALITY reject EXTENSION Additional-EDCH-Cell-Information-RL-Reconf-Req
    PRESENCE optional },
    . . .
Additional-HS-Cell-Information-RL-Reconf-Req ::= SEQUENCE (SIZE (1..maxNrOfHSDSCH-1)) OF Additional-HS-Cell-Information-RL-Reconf-Req-ItemIEs
Additional-HS-Cell-Information-RL-Reconf-Reg-ItemIEs
                                                      ::=SEQUENCE{
    hSPDSCH-RL-ID
                                                    RL-ID,
                                                    C-ID
                                                                                                OPTIONAL,
    hS-DSCH-FDD-Secondary-Serving-Information
                                                    HS-DSCH-FDD-Secondary-Serving-Information
                                                                                                OPTIONAL,
    hS-DSCH-FDD-Secondary-Serving-Information-To-Modify-Unsynchronised
                                                                            HS-DSCH-FDD-Secondary-Serving-Information-To-Modify-Unsynchronised
    hS-DSCH-Secondary-Serving-Remove
                                                    HS-DSCH-Secondary-Serving-Remove
                                                                                        OPTIONAL,
                                    ProtocolExtensionContainer { { Additional-HS-Cell-Information-RL-Reconf-Req-ExtIEs} } OPTIONAL,
    iE-Extensions
Additional-HS-Cell-Information-RL-Reconf-Req-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Additional-EDCH-Cell-Information-RL-Reconf-Req ::=SEQUENCE{
    setup-Or-ConfigurationChange-Or-Removal-Of-EDCH-On-secondary-UL-Frequency
                                                                                    Setup-Or-ConfigurationChange-Or-Removal-Of-EDCH-On-secondary-
UL-Frequency,
   iE-Extensions
                                    ProtocolExtensionContainer { { Additional-EDCH-Cell-Information-RL-Reconf-Req-ExtIEs} } OPTIONAL,
```

```
Additional-EDCH-Cell-Information-RL-Reconf-Req-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RL-ReconfigurationRequestFDD-RL-InformationList ::= SEOUENCE (SIZE (0..maxNrOfRLs)) OF ProtocolIE-Single-Container {
   {RL-ReconfigurationRequestFDD-RL-Information-ListItem} }
RL-ReconfigurationRequestFDD-RL-Information-ListItem RNSAP-PROTOCOL-IES ::= {
   { ID id-RL-ReconfigurationRequestFDD-RL-Information-IEs CRITICALITY ignore TYPE RL-ReconfigurationRequestFDD-RL-Information-IEs PRESENCE
optional }
RL-ReconfigurationRequestFDD-RL-Information-IEs ::= SEQUENCE {
                         RL-ID,
   rL-Specific-DCH-Info
                         RL-Specific-DCH-Info OPTIONAL,
   iE-Extensions
                         RL-ReconfigurationRequestFDD-RL-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-RL-Specific-EDCH-Information
                                           CRITICALITY reject EXTENSION RL-Specific-EDCH-Information
                                                                                                              PRESENCE optional }
    ID id-EDCH-RL-Indication
                                            CRITICALITY reject EXTENSION EDCH-RL-Indication
                                                                                                                            PRESENCE
optional }
     ID id-HSDSCH-PreconfigurationSetup
                                                                                                                     PRESENCE optional } |
                                            CRITICALITY ignore EXTENSION HSDSCH-PreconfigurationSetup
     ID id-Non-Serving-RL-Preconfig-Setup
                                            CRITICALITY ignore EXTENSION Non-Serving-RL-Preconfig-Setup
                                                                                                              PRESENCE optional }
    ID id-Non-Serving-RL-Preconfig-Removal
                                                                                                              PRESENCE optional },
                                           CRITICALITY ignore EXTENSION Non-Serving-RL-Preconfig-Setup
  *****************
-- RADIO LINK RECONFIGURATION REQUEST TDD
  ····
RadioLinkReconfigurationRequestTDD ::= SEQUENCE {
   protocolIEs
                                 ProtocolIE-Container
                                                          {{RadioLinkReconfigurationRequestTDD-IEs}},
                                 ProtocolExtensionContainer {{RadioLinkReconfigurationRequestTDD-Extensions}}
   protocolExtensions
                                                                                                                        OPTIONAL,
RadioLinkReconfigurationRequestTDD-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-AllowedQueuingTime
                                    CRITICALITY reject TYPE AllowedQueuingTime
                                                                                        PRESENCE optional
     ID id-UL-CCTrCH-InformationModifyList-RL-ReconfRqstTDD
                                                          CRITICALITY notify TYPE UL-CCTrCH-InformationModifyList-RL-ReconfRqstTDD
   PRESENCE optional
    { ID id-UL-CCTrCH-InformationDeleteList-RL-ReconfRqstTDD
                                                          CRITICALITY notify TYPE UL-CCTrCH-InformationDeleteList-RL-ReconfRqstTDD
   PRESENCE optional } |
   { ID id-DL-CCTrCH-InformationModifyList-RL-ReconfRqstTDD
                                                          CRITICALITY notify TYPE DL-CCTrCH-InformationModifyList-RL-ReconfRqstTDD
   PRESENCE optional
    { ID id-DL-CCTrCH-InformationDeleteList-RL-ReconfRqstTDD
                                                          CRITICALITY notify TYPE DL-CCTrCH-InformationDeleteList-RL-ReconfRqstTDD
   PRESENCE optional
```

```
ID id-TDD-DCHs-to-Modify
                            CRITICALITY reject TYPE TDD-DCHs-to-Modify
                                                                 PRESENCE optional
    ID id-DCHs-to-Add-TDD
                        CRITICALITY reject TYPE DCH-TDD-Information
                                                                 PRESENCE optional
    PRESENCE optional
UL-CCTrCH-InformationModifyList-RL-ReconfRgstTDD
                                           ::= SEOUENCE (SIZE (0..maxNrOfCCTrCHs)) OF ProtocolIE-Single-Container { {UL-CCTrCH-
InformationModifyList-RL-ReconfRqstTDD-IEs} }
UL-CCTrCH-InformationModifyList-RL-ReconfRqstTDD-IEs RNSAP-PROTOCOL-IES ::= {
   PRESENCE mandatory }
UL-CCTrCH-InformationModifyItem-RL-ReconfRqstTDD ::= SEQUENCE {
   cCTrCH-ID
                        CCTrCH-ID,
   t.FCS
                                  OPTIONAL,
                            ProtocolExtensionContainer { {UL-CCTrCH-InformationModifyItem-RL-ReconfRgstTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
UL-CCTrCH-InformationModifyItem-RL-ReconfRqstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  { ID id-UL-SIRTarget
                      CRITICALITY reject
                                         EXTENSION
                                                      UL-SIR
                                                               PRESENCE optional
   -- Applicable to 1.28Mcps TDD only
UL-CCTrCH-InformationDeleteList-RL-ReconfRgstTDD
                                           ::= SEOUENCE (SIZE (0..maxNrOfCCTrCHs)) OF ProtocolIE-Single-Container { {UL-CCTrCH-
InformationDeleteList-RL-ReconfRqstTDD-IEs} }
UL-CCTrCH-InformationDeleteList-RL-ReconfRqstTDD-IEs RNSAP-PROTOCOL-IES ::= {
   PRESENCE mandatory }
UL-CCTrCH-InformationDeleteItem-RL-ReconfRqstTDD ::= SEOUENCE {
   cCTrCH-ID
                        CCTrCH-ID,
                            ProtocolExtensionContainer { {UL-CCTrCH-InformationDeleteItem-RL-ReconfRqstTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
UL-CCTrCH-InformationDeleteItem-RL-ReconfRgstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-CCTrCH-InformationModifyList-RL-ReconfRqstTDD
                                           ::= SEQUENCE (SIZE (0..maxNrOfCCTrCHs)) OF ProtocolIE-Single-Container { {DL-CCTrCH-
InformationModifyList-RL-ReconfRqstTDD-IEs} }
DL-CCTrCH-InformationModifyList-RL-ReconfRqstTDD-IES RNSAP-PROTOCOL-IES ::= {
   PRESENCE mandatory }
DL-CCTrCH-InformationModifyItem-RL-ReconfRqstTDD ::= SEQUENCE {
```

```
cCTrCH-ID
                              CCTrCH-ID,
   + FCC
                              TFCS
                                         OPTIONAL.
   iE-Extensions
                                  ProtocolExtensionContainer { {DL-CCTrCH-InformationModifyItem-RL-ReconfRgstTDD-ExtIEs} } OPTIONAL,
DL-CCTrCH-InformationModifyItem-RL-ReconfRqstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-CCTrCH-InformationDeleteList-RL-ReconfRgstTDD
                                                    ::= SEQUENCE (SIZE (0..maxNrOfCCTrCHs)) OF ProtocolIE-Single-Container { {DL-CCTrCH-
InformationDeleteList-RL-ReconfRqstTDD-IEs} }
DL-CCTrCH-InformationDeleteList-RL-ReconfRqstTDD-IES RNSAP-PROTOCOL-IES ::= {
    PRESENCE mandatory }
DL-CCTrCH-InformationDeleteItem-RL-ReconfRgstTDD ::= SEQUENCE {
                              CCTrCH-ID,
   cCTrCH-ID
   iE-Extensions
                                  ProtocolExtensionContainer { {DL-CCTrCH-InformationDeleteItem-RL-ReconfRqstTDD-ExtIEs} } OPTIONAL,
DL-CCTrCH-InformationDeleteItem-RL-ReconfRqstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DCH-DeleteList-RL-ReconfRqstTDD
                                         ::= SEQUENCE (SIZE(0..maxNrOfDCHs)) OF DCH-DeleteItem-RL-ReconfRqstTDD
DCH-DeleteItem-RL-ReconfRqstTDD ::= SEQUENCE {
   dCH-ID
                              DCH-ID,
   iE-Extensions
                                  ProtocolExtensionContainer { {DCH-DeleteItem-RL-ReconfRqstTDD-ExtIEs} } OPTIONAL,
DCH-DeleteItem-RL-ReconfRqstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RadioLinkReconfigurationRequestTDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
  { ID id-RL-ReconfigurationRequestTDD-RL-Information CRITICALITY ignore EXTENSION Multiple-RL-ReconfigurationRequestTDD-RL-Information
    PRESENCE optional }
     ID id-HSDSCH-TDD-Information
                                                                                                                  PRESENCE optional } |
                                             CRITICALITY reject EXTENSION HSDSCH-TDD-Information
     ID id-HSDSCH-Information-to-Modify-Unsynchronised CRITICALITY reject EXTENSION HSDSCH-Information-to-Modify-Unsynchronised
                                                                                                                                PRESENCE
optional}|
     ID id-HSDSCH-MACdFlows-to-Add
                                             CRITICALITY reject EXTENSION HSDSCH-MACdFlows-Information
                                                                                                                  PRESENCE optional }
     ID id-HSDSCH-MACdFlows-to-Delete
                                             CRITICALITY reject EXTENSION HSDSCH-MACdFlows-to-Delete
                                                                                                                  PRESENCE optional}
     ID id-HSPDSCH-RL-ID
                                             CRITICALITY reject EXTENSION RL-ID
                                                                                                                  PRESENCE optional }
                                                                                                                  PRESENCE optional}
     ID id-E-DCH-Information-Reconfig
                                             CRITICALITY reject EXTENSION E-DCH-Information-Reconfig
     ID id-E-DCH-Serving-RL-ID
                                             CRITICALITY reject EXTENSION RL-ID
                                                                                                                  PRESENCE optional}
     ID id-E-DCH-768-Information-Reconfig
                                             CRITICALITY reject EXTENSION E-DCH-768-Information-Reconfig
                                                                                                                  PRESENCE optional}
     ID id-E-DCH-LCR-Information-Reconfig
                                             CRITICALITY reject EXTENSION E-DCH-LCR-Information-Reconfig
                                                                                                                  PRESENCE optional}
                                                                                                                  PRESENCE optional }
     ID id-CPC-InformationLCR
                                             CRITICALITY reject EXTENSION CPC-InformationLCR
```

```
ID id-RNTI-Allocation-Indicator
                                              CRITICALITY ignore EXTENSION RNTI-Allocation-Indicator
                                                                                                                   PRESENCE optional }
     ID id-DCH-MeasurementType-Indicator
                                              CRITICALITY reject EXTENSION DCH-MeasurementType-Indicator
                                                                                                                   PRESENCE optional }
     ID id-Multi-Carrier-EDCH-Reconfigure
                                              CRITICALITY reject EXTENSION Multi-Carrier-EDCH-Reconfigure
                                                                                                                   PRESENCE optional}
     ID id-MU-MIMO-Indicator
                                              CRITICALITY reject EXTENSION MU-MIMO-Indicator
                                                                                                                   PRESENCE optional },
Multiple-RL-ReconfigurationRequestTDD-RL-Information ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF RL-ReconfigurationRequestTDD-RL-Information
RL-ReconfigurationRequestTDD-RL-Information ::= SEQUENCE {
   rL-ID
                           RL-ID,
    rL-Specific-DCH-Info
                          RL-Specific-DCH-Info OPTIONAL,
                           ProtocolExtensionContainer { { RL-ReconfigurationRequestTDD-RL-Information-ExtIEs} } OPTIONAL,
   iE-Extensions
RL-ReconfigurationRequestTDD-RL-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
           id-UL-Synchronisation-Parameters-LCR
                                                         CRITICALITY ignore
                                                                                 EXTENSION UL-Synchronisation-Parameters-LCR
               optional
                          } -- Mandatory for 1.28Mcps TDD, Not Applicable to 3.84Mcps TDD or 7.68Mcps TDD
    { ID id-NeedforIdleInterval
                                                     CRITICALITY ignore EXTENSION NeedforIdleInterval
                                                                                                                                  PRESENCE
optional },
      ****************
-- RADIO LINK RECONFIGURATION RESPONSE FDD
  ****************
RadioLinkReconfigurationResponseFDD ::= SEQUENCE {
                                                             {{RadioLinkReconfigurationResponseFDD-IEs}},
   protocolIEs
                                  ProtocolIE-Container
   protocolExtensions
                                  ProtocolExtensionContainer {{RadioLinkReconfigurationResponseFDD-Extensions}}
                                                                                                                               OPTIONAL,
RadioLinkReconfigurationResponseFDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-InformationResponseList-RL-ReconfRspFDD
                                                         CRITICALITY ignore TYPE RL-InformationResponseList-RL-ReconfRspFDD
    PRESENCE optional } |
    { ID id-CriticalityDiagnostics
                                          CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                              PRESENCE optional
                                                                                                                   },
    . . .
RL-InformationResponseList-RL-ReconfRspFDD
                                              ::= SEQUENCE (SIZE (0..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-InformationResponse-RL-
ReconfRspFDD-IEs} }
RL-InformationResponse-RL-ReconfRspFDD-IES RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-InformationResponseItem-RL-ReconfRspFDD
                                                         CRITICALITY ignore TYPE RL-InformationResponseItem-RL-ReconfRspFDD
                                                                                                                                  PRESENCE
mandatory }
RL-InformationResponseItem-RL-ReconfRspFDD ::= SEQUENCE {
                                  RL-ID,
   rL-ID
   max-UL-SIR
                                  UL-SIR
                                                  OPTIONAL,
```

```
min-UL-SIR
                                                   OPTIONAL,
                                   UL-SIR
   maximumDLTxPower
                                   DL-Power
                                                   OPTIONAL,
   minimumDLTxPower
                                   DL-Power
                                                   OPTIONAL.
   not-Used-secondary-CCPCH-Info
                                          NULL
                                                      OPTIONAL,
    dCHsInformationResponseList
                                   DCH-InformationResponseList-RL-ReconfRspFDD OPTIONAL,
                                          DL-CodeInformationList-RL-ReconfRspFDD OPTIONAL,
   dL-CodeInformationList-RL-ReconfResp
   iE-Extensions
                                   ProtocolExtensionContainer { {RL-InformationResponseItem-RL-ReconfRspFDD-ExtIEs} } OPTIONAL,
RL-InformationResponseItem-RL-ReconfRspFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-DL-PowerBalancing-UpdatedIndicator
                                                   CRITICALITY ignore EXTENSION DL-PowerBalancing-UpdatedIndicator
                                                                                                                                    PRESENCE
optional }|
    { ID id-EDCH-FDD-InformationResponse
                                                   CRITICALITY ignore EXTENSION EDCH-FDD-InformationResponse
    PRESENCE optional } |
    { ID id-EDCH-RLSet-Id
                                                   CRITICALITY ignore EXTENSION RL-Set-ID
           PRESENCE optional } |
     ID id-EDCH-FDD-DL-ControlChannelInformation
                                                  CRITICALITY ignore EXTENSION EDCH-FDD-DL-ControlChannelInformation
                                                                                                                             PRESENCE optional } |
     ID id-F-DPCH-SlotFormat
                                                   CRITICALITY ignore EXTENSION F-DPCH-SlotFormat
           PRESENCE optional } |
    { ID id-HSDSCH-PreconfigurationInfo
                                                   CRITICALITY ignore EXTENSION HSDSCH-PreconfigurationInfo
    PRESENCE optional }
    { ID id-Non-Serving-RL-Preconfig-Info
                                                   CRITICALITY ignore EXTENSION Non-Serving-RL-Preconfig-Info
    PRESENCE optional }.
DCH-InformationResponseList-RL-ReconfRspFDD
                                                      ::= ProtocolIE-Single-Container { {DCH-InformationResponseListIEs-RL-ReconfRspFDD} }
DCH-InformationResponseListIEs-RL-ReconfRspFDD RNSAP-PROTOCOL-IES ::= {
                                      CRITICALITY ignore TYPE DCH-InformationResponse
    { ID id-DCH-InformationResponse
                                                                                              PRESENCE mandatory
DL-CodeInformationList-RL-ReconfRspFDD ::= ProtocolIE-Single-Container {{ DL-CodeInformationListIEs-RL-ReconfRspFDD }}
DL-CodeInformationListIEs-RL-ReconfRspFDD RNSAP-PROTOCOL-IES ::= {
    PRESENCE optional }
RadioLinkReconfigurationResponseFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-HSDSCH-RNTI
                                               CRITICALITY ignore
                                                                      EXTENSION HSDSCH-RNTI
    PRESENCE optional }
     ID id-HSDSCH-FDD-Information-Response
                                                                                                                             PRESENCE optional }
                                               CRITICALITY ignore
                                                                      EXTENSION HSDSCH-FDD-Information-Response
    { ID id-MAChs-ResetIndicator
                                               CRITICALITY ignore
                                                                      EXTENSION MAChs-ResetIndicator
    PRESENCE optional } |
    { ID id-Continuous-Packet-Connectivity-HS-SCCH-Less-Information-Response
                                                                                          CRITICALITY ignore
                                                                                                                     EXTENSION Continuous-
Packet-Connectivity-HS-SCCH-Less-Information-Response
                                                                          PRESENCE optional } |
    { ID id-Additional-HS-Cell-Information-Response CRITICALITY ignore
                                                                          EXTENSION Additional-HS-Cell-Information-Response-List
    PRESENCE optional }
    { ID id-Additional-EDCH-Cell-Information-ResponseRLReconf
                                                                  CRITICALITY ignore EXTENSION Additional-EDCH-Cell-Information-Response-
                       PRESENCE optional },
RLReconf-List
    . . .
```

```
*****************
-- RADIO LINK RECONFIGURATION RESPONSE TDD
   ****************
RadioLinkReconfigurationResponseTDD ::= SEOUENCE {
                                                             {{RadioLinkReconfigurationResponseTDD-IEs}},
   protocolIEs
                                  ProtocolIE-Container
   protocolExtensions
                                  ProtocolExtensionContainer {{RadioLinkReconfigurationResponseTDD-Extensions}}
                                                                                                                                OPTIONAL,
RadioLinkReconfigurationResponseTDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-InformationResponse-RL-ReconfRspTDD
                                                     CRITICALITY ignore TYPE RL-InformationResponse-RL-ReconfRspTDD
                                                                                                                                   PRESENCE
optional
    --This RL-InformationResponse-RL-ReconfRspTDD is for the first RL repetition in the list.
    --Repetitions 2 and on are defined in Multiple-RL-InformationResponse-RL-ReconfRspTDD.
                                          CRITICALITY ignore TYPE CriticalityDiagnostics
    { ID id-CriticalityDiagnostics
                                                                                              PRESENCE optional
    . . .
RL-InformationResponse-RL-ReconfRspTDD ::= SEQUENCE {
   rI.-ID
                                  RL-ID,
   max-UL-SIR
                                  UL-SIR
                                                  OPTIONAL,
   min-UL-SIR
                                  UL-SIR
                                                  OPTIONAL,
   maximumDLTxPower
                                  DL-Power
                                                  OPTIONAL,
   minimumDLTxPower
                                  DL-Power
                                                  OPTIONAL,
   dCHsInformationResponseList
                                  DCH-InformationResponseList-RL-ReconfRspTDD OPTIONAL,
                                   ProtocolExtensionContainer { {RL-InformationResponse-RL-ReconfRspTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
RL-InformationResponse-RL-ReconfRspTDD-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-DL-CCTrCH-InformationList-RL-ReconfRspTDD CRITICALITY ignore EXTENSION DL-CCTrCH-InformationList-RL-ReconfRspTDD
                                                                                                                                   PRESENCE
optional }|
                                                      CRITICALITY ignore EXTENSION UL-TimingAdvanceCtrl-LCR
                                                                                                                    PRESENCE optional },
    { ID id-UL-TimingAdvanceCtrl-LCR
    --For 1.28Mcps TDD only
    . . .
DL-CCTrCH-InformationList-RL-ReconfRspTDD ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHs)) OF DL-CCTrCH-InformationItem-RL-ReconfRspTDD
DL-CCTrCH-InformationItem-RL-ReconfRspTDD ::= SEQUENCE {
   cCTrCH-ID
                                              CCTrCH-ID,
   dl-DPCH-ModifyInformation-LCR
                                              DL-DPCH-InformationModifyList-LCR-RL-ReconfRspTDD
                                                                                                             OPTIONAL,
    --For 1.28Mcps TDD only
    cCTrCH-Maximum-DL-Power
                                              DL-Power
                                                                     OPTIONAL,
    --For 3.84Mcps TDD and 7.68Mcps TDD only, this is a DCH type CCTrCH power
    cCTrCH-Minimum-DL-Power
                                              DL-Power
                                                                     OPTIONAL,
    --For 3.84Mcps TDD and 7.68Mcps TDD only, this is a DCH type CCTrCH power
                                              ProtocolExtensionContainer { | DL-CCTrCH-InformationItem-RL-ReconfRspTDD-ExtIEs} }
   iE-Extensions
   OPTIONAL,
```

```
DL-CCTrCH-InformationItem-RL-ReconfRspTDD-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
DL-DPCH-InformationModifyList-LCR-RL-ReconfRspTDD ::= ProtocolIE-Single-Container {{ DL-DPCH-InformationModifyListIEs-LCR-RL-ReconfRspTDD }}
DL-DPCH-InformationModifyListIEs-LCR-RL-ReconfRspTDD RNSAP-PROTOCOL-IES ::= {
    {ID id-DL-DPCH-InformationModifyItem-LCR-RL-ReconfRspTDD CRITICALITY ignore TYPE DL-DPCH-InformationModifyItem-LCR-RL-ReconfRspTDD
    PRESENCE optional },
DL-DPCH-InformationModifyItem-LCR-RL-ReconfRspTDD ::= SEQUENCE {
  dL-Timeslot-LCR-InformationModifyList-RL-ReconfRqstTDD
                                                                DL-Timeslot-LCR-InformationModifyList-RL-ReconfRspTDD
                                                                                                                                       OPTIONAL.
  iE-ExtensionsProtocolExtensionContainer { { DL-DPCH-InformationModifyItem-LCR-RL-ReconfRspTDD-ExtIEs} }
                                                                                                                        OPTIONAL.
DL-DPCH-InformationModifyItem-LCR-RL-ReconfRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-Timeslot-LCR-InformationModifyList-RL-ReconfRspTDD ::= SEOUENCE (SIZE (1..maxNrOfDLTsLCR)) OF DL-Timeslot-LCR-InformationModifyItem-RL-
ReconfRspTDD
DL-Timeslot-LCR-InformationModifyItem-RL-ReconfRspTDD
                                                         ::= SEOUENCE {
    timeSlotLCR
                                            TimeSlotLCR,
    maxPowerLCR
                                            DL-Power
                                                        OPTIONAL,
    minPowerLCR
                                            DL-Power
                                                        OPTIONAL,
    iE-Extensions
                                            ProtocolExtensionContainer { { DL-Timeslot-LCR-InformationModifyItem-RL-ReconfRspTDD-ExtIEs} }
    OPTIONAL,
    . . .
DL-Timeslot-LCR-InformationModifyItem-RL-ReconfRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DCH-InformationResponseList-RL-ReconfRspTDD
                                                        ::= ProtocolIE-Single-Container { {DCH-InformationResponseListIEs-RL-ReconfRspTDD} }
DCH-InformationResponseListIEs-RL-ReconfRspTDD RNSAP-PROTOCOL-IES ::= {
    { ID id-DCH-InformationResponse CRITICALITY ignore TYPE DCH-InformationResponse
                                                                                        PRESENCE optional
RadioLinkReconfigurationResponseTDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-HSDSCH-RNTI
                                                CRITICALITY ignore EXTENSION HSDSCH-RNTI
                                                                                                                        PRESENCE optional}
     ID id-HSDSCH-TDD-Information-Response
                                                CRITICALITY ignore EXTENSION HSDSCH-TDD-Information-Response
                                                                                                                        PRESENCE optional}
     ID id-MAChs-ResetIndicator
                                                CRITICALITY ignore EXTENSION MAChs-ResetIndicator
                                                                                                                        PRESENCE optional}
     ID id-RL-ReconfigurationResponseTDD-RL-Information
                                                         CRITICALITY ignore EXTENSION Multiple-RL-InformationResponse-RL-ReconfRspTDD
    PRESENCE optional } |
     ID id-E-DCH-Information-Response
                                                CRITICALITY ignore EXTENSION E-DCH-Information-Response
                                                                                                                        PRESENCE optional }
     ID id-E-DCH-768-Information-Response
                                                                                                                        PRESENCE optional}
                                                CRITICALITY ignore EXTENSION E-DCH-768-Information-Response
    { ID id-E-DCH-LCR-Information-Response
                                                CRITICALITY ignore EXTENSION E-DCH-LCR-Information-Response
                                                                                                                        PRESENCE optional }
```

```
PRESENCE optional } |
    { ID id-PowerControlGAP
                                              CRITICALITY ignore EXTENSION ControlGAP
    -- Applicable to 1.28Mcps TDD only
     ID id-IdleIntervalInformation
                                              CRITICALITY ignore EXTENSION IdleIntervalInformation
                                                                                                                    PRESENCE optional}
     ID id-ContinuousPacketConnectivity-DRX-Information-ResponseLCR
                                                                      CRITICALITY ignore EXTENSION ContinuousPacketConnectivity-DRX-Information-
ResponseLCR PRESENCE optional } |
    { ID id-HS-DSCH-Semi-PersistentScheduling-Information-ResponseLCR
                                                                      CRITICALITY ignore EXTENSION HS-DSCH-Semi-PersistentScheduling-
Information-ResponseLCR PRESENCE optional} |
    { ID id-E-DCH-Semi-PersistentScheduling-Information-ResponseLCR
                                                                      CRITICALITY ignore EXTENSION E-DCH-Semi-PersistentScheduling-Information-
ResponseLCR PRESENCE optional } |
     ID id-E-RNTI-For-FACH
                                              CRITICALITY ignore EXTENSION E-RNTI
                                                                                                                    PRESENCE optional }
     ID id-H-RNTI-For-FACH
                                              CRITICALITY ignore EXTENSION HSDSCH-RNTI
                                                                                                                    PRESENCE optional}
                                                                                                                    PRESENCE optional}
     ID id-DCH-MeasurementOccasion-Information CRITICALITY reject EXTENSION DCH-MeasurementOccasion-Information
     ID id-Multi-Carrier-EDCH-Response
                                              CRITICALITY ignore EXTENSION Multi-Carrier-EDCH-Information-Response
                                                                                                                    PRESENCE optional }
    ID id-MU-MIMO-InformationLCR
                                              CRITICALITY reject EXTENSION MU-MIMO-InformationLCR
                                                                                                                    PRESENCE optional }.
Multiple-RL-InformationResponse-RL-ReconfRspTDD ::= SEQUENCE (SIZE (1..maxNrOfRLs-1)) OF RL-InformationResponse-RL-ReconfRspTDD
--Includes the 2<sup>nd</sup> through the max number of radio link information repetitions.
   *****************
-- RADIO LINK FAILURE INDICATION
  ******************
RadioLinkFailureIndication ::= SEQUENCE {
   protocolIEs
                                   ProtocolIE-Container
                                                              {{RadioLinkFailureIndication-IEs}},
   protocolExtensions
                                  ProtocolExtensionContainer {{RadioLinkFailureIndication-Extensions}}
                                                                                                                       OPTIONAL,
RadioLinkFailureIndication-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-Reporting-Object-RL-FailureInd CRITICALITY ignore TYPE Reporting-Object-RL-FailureInd
                                                                                                             PRESENCE mandatory
    . . .
Reporting-Object-RL-FailureInd ::= CHOICE {
                          RL-RL-FailureInd,
   rL
   rL-Set
                          RL-Set-RL-FailureInd, --FDD only
    . . . ,
    cCTrCH
                          CCTrCH-RL-FailureInd --TDD only
                          ::= SEOUENCE {
RL-RL-FailureInd
   rL-InformationList-RL-FailureInd
                                          RL-InformationList-RL-FailureInd,
   iE-Extensions
                                          ProtocolExtensionContainer { { RLItem-RL-FailureInd-ExtIEs} } OPTIONAL.
RLItem-RL-FailureInd-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-Information-RL-FailureInd-IEs}
RL-InformationList-RL-FailureInd
RL-Information-RL-FailureInd-IES RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-Information-RL-FailureInd
                                                CRITICALITY ignore TYPE RL-Information-RL-FailureInd
                                                                                                                 PRESENCE mandatory
RL-Information-RL-FailureInd ::= SEQUENCE {
    cause
                                    ProtocolExtensionContainer { {RL-Information-RL-FailureInd-ExtIEs} } OPTIONAL,
    iE-Extensions
RL-Information-RL-FailureInd-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
RL-Set-RL-FailureInd
                                ::= SEOUENCE
   rL-Set-InformationList-RL-FailureInd
                                            RL-Set-InformationList-RL-FailureInd,
   iE-Extensions
                                            ProtocolExtensionContainer { { RL-SetItem-RL-FailureInd-ExtIEs} } OPTIONAL,
RL-SetItem-RL-FailureInd-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
                                                ::= SEOUENCE (SIZE (1..maxNrOfRLSets)) OF ProtocolIE-Single-Container { {RL-Set-Information-RL-
RL-Set-InformationList-RL-FailureInd
FailureInd-IEs} }
RL-Set-Information-RL-FailureInd-IES RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-Set-Information-RL-FailureInd
                                                   CRITICALITY ignore TYPE RL-Set-Information-RL-FailureInd
                                                                                                                         PRESENCE mandatory
RL-Set-Information-RL-FailureInd ::= SEQUENCE {
   rL-Set-ID
                                    RL-Set-ID,
    cause
    iE-Extensions
                                    ProtocolExtensionContainer { {RL-Set-Information-RL-FailureInd-ExtIEs} } OPTIONAL,
RL-Set-Information-RL-FailureInd-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RadioLinkFailureIndication-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
CCTrCH-RL-FailureInd ::= SEQUENCE {
                                                RL-ID,
    cCTrCH-InformationList-RL-FailureInd
                                                CCTrCH-InformationList-RL-FailureInd,
                                            ProtocolExtensionContainer { { CCTrCHItem-RL-FailureInd-ExtIEs } }
    iE-Extensions
                                                                                                                         OPTIONAL,
```

```
CCTrCHItem-RL-FailureInd-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
CCTrCH-InformationList-RL-FailureInd ::= SEOUENCE (SIZE (1..maxNrOfCCTrCHs)) OF ProtocolIE-Single-Container {{ CCTrCH-InformationItemIE-RL-
FailureInd}}
CCTrCH-InformationItemIE-RL-FailureInd RNSAP-PROTOCOL-IES ::= {
          id-CCTrCH-InformationItem-RL-FailureInd
                                                    CRITICALITY
                                                                  ignore
                                                                                TYPE CCTrCH-InformationItem-RL-FailureInd
   PRESENCE
             mandatory}
CCTrCH-InformationItem-RL-FailureInd ::= SEQUENCE {
   cCTrCH-ID
                                          CCTrCH-ID,
   cause
                                          Cause,
                                          iE-Extensions
                                                                                                                      OPTIONAL,
CCTrCH-InformationItem-RL-FailureInd-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
-- RADIO LINK PREEMPTION REQUIRED INDICATION
RadioLinkPreemptionRequiredIndication ::= SEQUENCE {
                               ProtocolIE-Container
                                                       {{RadioLinkPreemptionRequiredIndication-IEs}},
   protocolIEs
   protocolExtensions
                               ProtocolExtensionContainer {{RadioLinkPreemptionRequiredIndication-Extensions}}
                                                                                                                     OPTIONAL,
RadioLinkPreemptionRequiredIndication-IEs RNSAP-PROTOCOL-IES ::= {
   PRESENCE
optional },
   . . .
RL-InformationList-RL-PreemptRequiredInd
                                          ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-InformationItemIEs-RL-
PreemptRequiredInd} }
RL-InformationItemIEs-RL-PreemptRequiredInd RNSAP-PROTOCOL-IES ::= {
   { ID id-RL-InformationItem-RL-PreemptRequiredInd
                                                CRITICALITY ignore TYPE RL-InformationItem-RL-PreemptRequiredInd
                                                                                                                      PRESENCE
mandatory }
RL-InformationItem-RL-PreemptRequiredInd::= SEQUENCE {
   rL-ID
```

```
ProtocolExtensionContainer { {RL-Information-RL-PreemptRequiredInd-ExtIEs} } OPTIONAL,
   iE-Extensions
RL-Information-RL-PreemptRequiredInd-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   PreemptRequiredInd PRESENCE optional },
RadioLinkPreemptionRequiredIndication-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
   PreemptRequiredInd PRESENCE optional },
   . . .
HSDSCHMacdFlowSpecificInformationList-RL-PreemptRequiredInd ::= SEQUENCE (SIZE (1.. maxNrOfMACdFlows)) OF ProtocolIE-Single-Container {
{HSDSCHMacdFlowSpecificInformationItemIEs-RL-PreemptRequiredInd} }
HSDSCHMacdFlowSpecificInformationItemIEs-RL-PreemptRequiredInd RNSAP-PROTOCOL-IES ::= {
   PreemptRequiredInd PRESENCE mandatory }
HSDSCHMacdFlowSpecificInformationItem-RL-PreemptRequiredInd ::= SEQUENCE {
   hSDSCH-MACdFlow-ID
                                   HSDSCH-MACdFlow-ID,
                         ProtocolExtensionContainer { { HSDSCHMacdFlowSpecificInformation-RL-PreemptRequiredInd-ExtIEs} } OPTIONAL,
   iE-Extensions
HSDSCHMacdFlowSpecificInformation-RL-PreemptRequiredInd-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
EDCH-MacdFlowSpecificInformationList-RL-PreemptRequiredInd ::= SEQUENCE (SIZE (1.. maxNrOfEDCHMACdFlows)) OF ProtocolIE-Single-Container { {EDCH-
MacdFlowSpecificInformationItemIEs-RL-PreemptRequiredInd} }
EDCH-MacdFlowSpecificInformationItemIEs-RL-PreemptRequiredInd RNSAP-PROTOCOL-IES ::= {
   { ID id-EDCH-MacdFlowSpecificInformationItem-RL-PreemptRequiredInd
                                                          CRITICALITY ignore TYPE EDCH-MacdFlowSpecificInformationItem-RL-
PreemptRequiredInd PRESENCE mandatory }
EDCH-MacdFlowSpecificInformationItem-RL-PreemptRequiredInd ::= SEQUENCE {
   eDCH-MACdFlow-ID
                         EDCH-MACdFlow-ID,
   iE-Extensions
                         ProtocolExtensionContainer { { EDCH-MacdFlowSpecificInformation-RL-PreemptRequiredInd-ExtIEs} } OPTIONAL,
EDCH-MacdFlowSpecificInformation-RL-PreemptRequiredInd-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
__ ***********************
```

```
-- RADIO LINK RESTORE INDICATION
__ *********************
RadioLinkRestoreIndication ::= SEQUENCE {
   protocolIEs
                               ProtocolIE-Container
                                                       {{RadioLinkRestoreIndication-IEs}},
   protocolExtensions
                               ProtocolExtensionContainer {{RadioLinkRestoreIndication-Extensions}}
                                                                                                           OPTIONAL,
RadioLinkRestoreIndication-IEs RNSAP-PROTOCOL-IES ::= {
   PRESENCE mandatory
   . . .
Reporting-Object-RL-RestoreInd ::= CHOICE {
                       RL-RL-RestoreInd, --TDD only
   rL-Set
                       RL-Set-RL-RestoreInd, --FDD only
   . . . ,
   cCTrCH
                       CCTrCH-RL-RestoreInd --TDD only
RL-RL-RestoreInd ::= SEOUENCE {
   rL-InformationList-RL-RestoreInd
                                      RL-InformationList-RL-RestoreInd,
   iE-Extensions
                                      ProtocolExtensionContainer { { RLItem-RL-RestoreInd-ExtIEs} } OPTIONAL,
RLItem-RL-RestoreInd-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
                                      ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-Information-RL-RestoreInd-IEs}
RL-InformationList-RL-RestoreInd
RL-Information-RL-RestoreInd-IEs RNSAP-PROTOCOL-IES ::= {
   { ID id-RL-Information-RL-RestoreInd
                                     CRITICALITY ignore TYPE RL-Information-RL-RestoreInd
                                                                                                  PRESENCE mandatory
RL-Information-RL-RestoreInd ::= SEQUENCE {
   rL-ID
   iE-Extensions
                               ProtocolExtensionContainer { {RL-Information-RL-RestoreInd-ExtIEs} } OPTIONAL,
RL-Information-RL-RestoreInd-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
RL-Set-RL-RestoreInd ::= SEQUENCE {
   rL-Set-InformationList-RL-RestoreInd
                                      RL-Set-InformationList-RL-RestoreInd,
   iE-Extensions
                                      . . .
```

```
RL-SetItem-RL-RestoreInd-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RL-Set-InformationList-RL-RestoreInd
                                           ::= SEOUENCE (SIZE (1..maxNrOfRLSets)) OF ProtocolIE-Single-Container { {RL-Set-Information-RL-
RestoreInd-IEs} }
RL-Set-Information-RL-RestoreInd-IES RNSAP-PROTOCOL-IES ::= {
   { ID id-RL-Set-Information-RL-RestoreInd
                                              CRITICALITY ignore TYPE RL-Set-Information-RL-RestoreInd
                                                                                                             PRESENCE mandatory
RL-Set-Information-RL-RestoreInd ::= SEOUENCE {
   rL-Set-ID
   iE-Extensions
                                ProtocolExtensionContainer { {RL-Set-Information-RL-RestoreInd-ExtIEs} } OPTIONAL,
RL-Set-Information-RL-RestoreInd-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RadioLinkRestoreIndication-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
CCTrCH-RL-RestoreInd ::= SEQUENCE {
                                           RL-ID,
   cCTrCH-InformationList-RL-RestoreInd
                                           CCTrCH-InformationList-RL-RestoreInd,
   iE-Extensions
                                        ProtocolExtensionContainer { { CCTrCHItem-RL-RestoreInd-ExtIEs } }
                                                                                                             OPTIONAL,
CCTrCHItem-RL-RestoreInd-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
CCTrCH-InformationList-RL-RestoreInd ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHs)) OF ProtocolIE-Single-Container {{ CCTrCH-InformationItemIE-RL-
RestoreInd}}
CCTrCH-InformationItemIE-RL-RestoreInd RNSAP-PROTOCOL-IES ::= {
   TYPE CCTrCH-InformationItem-RL-RestoreInd
                                                                     ignore
   PRESENCE mandatory }
CCTrCH-InformationItem-RL-RestoreInd ::= SEOUENCE {
   cCTrCH-ID
   iE-Extensions
                                           OPTIONAL,
CCTrCH-InformationItem-RL-RestoreInd-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   . . .
```

```
-- DOWNLINK POWER CONTROL REQUEST
   *******************
DL-PowerControlRequest ::= SEQUENCE {
                                                            {{DL-PowerControlRequest-IEs}},
   protocolIEs
                                  ProtocolIE-Container
                                  ProtocolExtensionContainer {{DL-PowerControlRequest-Extensions}}
   protocolExtensions
                                                                                                                  OPTIONAL,
   . . .
DL-PowerControlRequest-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-PowerAdjustmentType
                                  CRITICALITY ignore
                                                                      TYPE PowerAdjustmentType
                                                                                                                        PRESENCE mandatory }
     ID id-DLReferencePower
                                           CRITICALITY ignore
                                                                                                                        PRESENCE conditional }
                                                                      TYPE DL-Power
    -- This IE shall be present if Power Adjustment Type IE equals to 'Common'
    { ID id-InnerLoopDLPCStatus
                                                                                                                        PRESENCE optional }
                                           CRITICALITY ignore
                                                                      TYPE InnerLoopDLPCStatus
    TYPE DL-ReferencePowerInformationList-DL-PC-Rqst
                                                                                                                       PRESENCE conditional }
    -- This IE shall be present if Power Adjustment Type IE equals to 'Individual'
   { ID id-MaxAdjustmentStep
                                           CRITICALITY ignore
                                                                      TYPE MaxAdjustmentStep
                                                                                                                        PRESENCE conditional }
    -- This IE shall be present if Power Adjustment Type IE equals to 'Common' or 'Individual'
    { ID id-AdjustmentPeriod
                                           CRITICALITY ignore
                                                                      TYPE AdjustmentPeriod
                                                                                                                        PRESENCE conditional
} |
    -- This IE shall be present if Power Adjustment Type IE equals to 'Common' or 'Individual'
   { ID id-AdjustmentRatio
                                           CRITICALITY ignore
                                                                      TYPE ScaledAdjustmentRatio
                                                                                                                        PRESENCE conditional
    -- This IE shall be present if Power Adjustment Type IE equals to 'Common' or 'Individual'
    . . .
DL-ReferencePowerInformationList-DL-PC-Rqst
                                                 ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { {DL-
ReferencePowerInformation-DL-PC-Rqst-IEs} }
DL-ReferencePowerInformation-DL-PC-Rgst-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-DL-ReferencePowerInformation-DL-PC-Rgst CRITICALITY ignore TYPE DL-ReferencePowerInformation-DL-PC-Rgst
                                                                                                                   PRESENCE mandatory
DL-ReferencePowerInformation-DL-PC-Rqst ::= SEQUENCE {
                              RL-ID,
   dl-Reference-Power
                              DL-Power,
   iE-Extensions
                              ProtocolExtensionContainer { {DL-ReferencePowerInformation-DL-PC-Rqst-ExtIEs} } OPTIONAL,
    . . .
DL-ReferencePowerInformation-DL-PC-Rqst-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-PowerControlRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::=
```

```
****************
-- DOWNLINK POWER TIMESLOT CONTROL REQUEST TDD
  ******************
DL-PowerTimeslotControlRequest ::= SEOUENCE {
                                                     {{DL-PowerTimeslotControlRequest-IEs}},
   protocolIEs
                             ProtocolIE-Container
   protocolExtensions
                             ProtocolExtensionContainer {{DL-PowerTimeslotControlRequest-Extensions}}
                                                                                                          OPTIONAL,
DL-PowerTimeslotControlRequest-IEs RNSAP-PROTOCOL-IES ::= {
   --Mandatory for 3.84Mcps TDD and 7.68 Mcps TDD only
   . . .
DL-PowerTimeslotControlRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
   EXTENSION DL-TimeSlot-ISCP-LCR-Information PRESENCE optional |
   -- Mandatory for 1.28Mcps TDD only
   { ID id-PrimCCPCH-RSCP-DL-PC-RgstTDD
                                           CRITICALITY ignore
                                                               EXTENSION PrimaryCCPCH-RSCP
   PRESENCE optional } |
   { ID id-PrimaryCCPCH-RSCP-Delta
                                           CRITICALITY ignore
                                                               EXTENSION PrimaryCCPCH-RSCP-Delta
   PRESENCE optional },
    ****************
-- PHYSICAL CHANNEL RECONFIGURATION REQUEST FDD
  ******************
PhysicalChannelReconfigurationRequestFDD ::= SEOUENCE {
                                                     {{PhysicalChannelReconfigurationRequestFDD-IEs}},
   protocolIEs
                             ProtocolIE-Container
   protocolExtensions
                              ProtocolExtensionContainer {{PhysicalChannelReconfigurationRequestFDD-Extensions}}
                                                                                                                  OPTIONAL,
   . . .
PhysicalChannelReconfigurationRequestFDD-IEs RNSAP-PROTOCOL-IES ::= {
   { ID id-RL-Information-PhyChReconfRgstFDD CRITICALITY reject TYPE RL-Information-PhyChReconfRgstFDD
                                                                                                    PRESENCE mandatory
RL-Information-PhyChReconfRqstFDD ::= SEQUENCE {
   rI.-ID
   dl-CodeInformation
                              DL-CodeInformationList-PhyChReconfRqstFDD,
   iE-Extensions
                              ProtocolExtensionContainer { {RL-Information-PhyChReconfRqstFDD-ExtIEs} } OPTIONAL,
```

```
RL-Information-PhyChReconfRqstFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   { ID id-F-DPCH-SlotFormat
                                        CRITICALITY ignore EXTENSION F-DPCH-SlotFormat
                                                                                         PRESENCE optional }.
DL-CodeInformationList-PhyChReconfRgstFDD
                                         ::= ProtocolIE-Single-Container { {DL-CodeInformationListIEs-PhyChReconfRqstFDD} }
DL-CodeInformationListIEs-PhyChReconfRqstFDD RNSAP-PROTOCOL-IES ::= {
   { ID id-FDD-DL-CodeInformation CRITICALITY notify TYPE FDD-DL-CodeInformation PRESENCE mandatory }
PhysicalChannelReconfigurationRequestFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
-- PHYSICAL CHANNEL RECONFIGURATION REQUEST TDD
  PhysicalChannelReconfigurationRequestTDD ::= SEQUENCE {
   protocolIEs
                                 ProtocolIE-Container
                                                          {{PhysicalChannelReconfigurationRequestTDD-IEs}},
                                 ProtocolExtensionContainer {{PhysicalChannelReconfigurationRequestTDD-Extensions}}
   protocolExtensions
                                                                                                                               OPTIONAL,
   . . .
PhysicalChannelReconfigurationRequestTDD-IEs RNSAP-PROTOCOL-IES ::= {
   PRESENCE mandatory
   . . .
RL-Information-PhyChReconfRqstTDD ::= SEQUENCE {
   rI.-ID
   ul-CCTrCH-Information
                             UL-CCTrCH-InformationList-PhyChReconfRqstTDD
                                                                          OPTIONAL,
   dl-CCTrCH-Information
                             DL-CCTrCH-InformationList-PhyChReconfRqstTDD
                                                                          OPTIONAL,
                             ProtocolExtensionContainer { {RL-Information-PhyChReconfRqstTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
RL-Information-PhyChReconfRqstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-HSPDSCH-Timeslot-InformationList-PhyChReconfRqstTDD
                                                                  CRITICALITY reject EXTENSION HSPDSCH-Timeslot-InformationList-
PhyChReconfRgstTDD
                     PRESENCE optional } |
   --For 3.84Mcps TDD only
    { ID id-HSPDSCH-Timeslot-InformationListLCR-PhyChReconfRqstTDD
                                                                  CRITICALITY reject EXTENSION HSPDSCH-Timeslot-InformationListLCR-
PhyChReconfRqstTDD PRESENCE optional }
   --For 1.28Mcps TDD only
    { ID id-HSPDSCH-Timeslot-InformationList-PhyChReconfRqstTDD768
                                                                  CRITICALITY reject EXTENSION HSPDSCH-Timeslot-InformationList-
PhyChReconfRqstTDD768
                         PRESENCE optional } |
   --For 7.68Mcps TDD only
   { ID id-UARFCNforNt
                                                                  CRITICALITY ignore EXTENSION UARFON
                                                                                                               PRESENCE optional },
   -- Applicable to 1.28Mcps TDD only
```

```
UL-CCTrCH-InformationList-PhyChReconfRgstTDD
                                                  ::= ProtocolIE-Single-Container { { UL-CCTrCH-InformationListIEs-PhyChReconfRqstTDD} }
UL-CCTrCH-InformationListIEs-PhyChReconfRgstTDD RNSAP-PROTOCOL-IES ::= {
    { ID id-UL-CCTrCH-InformationListIE-PhyChReconfRgstTDD
                                                              CRITICALITY reject TYPE UL-CCTrCH-InformationListIE-PhyChReconfRqstTDD
    PRESENCE mandatory }
UL-CCTrCH-InformationListIE-PhyChReconfRqstTDD ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHs)) OF UL-CCTrCH-InformationItem-PhyChReconfRqstTDD
UL-CCTrCH-InformationItem-PhyChReconfRqstTDD ::= SEQUENCE {
    cCTrCH-ID
                                   CCTrCH-ID,
    ul-DPCH-Information
                                  UL-DPCH-InformationList-PhyChReconfRgstTDD,
   iE-Extensions
                                   ProtocolExtensionContainer { {UL-CCTrCH-InformationItem-PhyChReconfRqstTDD-ExtIEs} } OPTIONAL,
UL-CCTrCH-InformationItem-PhyChReconfRqstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UL-DPCH-InformationList-PhyChReconfRqstTDD ::= ProtocolIE-Single-Container {{UL-DPCH-InformationListIEs-PhyChReconfRqstTDD}}
UL-DPCH-InformationListIEs-PhyChReconfRqstTDD RNSAP-PROTOCOL-IES ::= {
    { ID id-UL-DPCH-InformationItem-PhyChReconfRqstTDD CRITICALITY notify TYPE UL-DPCH-InformationItem-PhyChReconfRqstTDD
                                                                                                                                   PRESENCE
mandatory }
UL-DPCH-InformationItem-PhyChReconfRqstTDD ::= SEQUENCE {
    repetitionPeriod
                                  RepetitionPeriod
                                                          OPTIONAL,
    repetitionLength
                                  RepetitionLength
                                                          OPTIONAL,
    tDD-DPCHOffset
                                  TDD-DPCHOffset
                                                          OPTIONAL,
    uL-Timeslot-InformationList-PhyChReconfRqstTDD
                                                          UL-Timeslot-InformationList-PhyChReconfRqstTDD
                                                                                                                    OPTIONAL,
    --For 3.84Mcps TDD only
    iE-Extensions
                                   ProtocolExtensionContainer { {UL-DPCH-InformationItem-PhyChReconfRqstTDD-ExtIEs} } OPTIONAL,
UL-DPCH-InformationItem-PhyChReconfRqstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
    { ID id-UL-Timeslot-LCR-InformationList-PhyChReconfRqstTDD CRITICALITY reject
                                                                                     EXTENSION UL-TimeslotLCR-InformationList-
PhyChReconfRqstTDD
                       PRESENCE optional }
    --For 1.28Mcps TDD only
    EXTENSION UL-Timeslot-InformationList-
PhyChReconfRqstTDD768
                           PRESENCE optional },
    --For 7.68Mcps TDD only
    . . .
UL-TimeslotLCR-InformationList-PhyChReconfRqstTDD::= SEQUENCE ( SIZE (1..maxNrOfTsLCR)) OF UL-TimeslotLCR-InformationItem-PhyChReconfRqstTDD
UL-TimeslotLCR-InformationItem-PhyChReconfRqstTDD ::= SEQUENCE {
    timeSlotLCR
                                  TimeSlotLCR,
    midambleShiftLCR
                                   MidambleShiftLCR
                                                          OPTIONAL,
```

```
tFCI-Presence
                                  TFCI-Presence
                                                     OPTIONAL,
   uL-Code-LCR-Information
                                  TDD-UL-Code-LCR-Information
                                                                OPTIONAL.
   iE-Extensions
                                  ProtocolExtensionContainer { {UL-TimeslotLCR-InformationItem-PhyChReconfRqstTDD-ExtIEs} } OPTIONAL,
UL-TimeslotLCR-InformationItem-PhyChReconfRgstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-PLCCH-Information-PhyChReconfRqstTDD
                                                    CRITICALITY reject
                                                                            EXTENSION PLCCHinformation
                                                                                                                  PRESENCE optional },
UL-Timeslot-InformationList-PhyChReconfRqstTDD::= SEQUENCE ( SIZE (1..maxNrOfTS)) OF UL-Timeslot-InformationItem-PhyChReconfRqstTDD
UL-Timeslot-InformationItem-PhyChReconfRqstTDD ::= SEQUENCE {
    timeSlot
                                  TimeSlot,
   midambleShiftAndBurstType
                                             MidambleShiftAndBurstType
                                                                            OPTIONAL,
   tFCI-Presence
                                  TFCI-Presence
                                                     OPTIONAL,
   uL-Code-Information
                              TDD-UL-Code-Information
                                                         OPTIONAL,
   iE-Extensions
                                  ProtocolExtensionContainer { {UL-Timeslot-InformationItem-PhyChReconfRqstTDD-ExtIEs} } OPTIONAL,
UL-Timeslot-InformationItem-PhyChReconfRqstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
UL-Timeslot-InformationList-PhyChReconfRgstTDD768::= SEQUENCE ( SIZE (1..maxNrOfTS)) OF UL-Timeslot-InformationItem-PhyChReconfRgstTDD768
UL-Timeslot-InformationItem-PhyChReconfRqstTDD768 ::= SEQUENCE {
   timeSlot
                                  TimeSlot,
   midambleShiftAndBurstType768
                                 MidambleShiftAndBurstType768
                                                                    OPTIONAL,
   tFCI-Presence
                                  TFCI-Presence
                                                    OPTIONAL,
   uL-Code-Information768
                                  TDD-UL-Code-Information768
                                                                OPTIONAL,
                                  ProtocolExtensionContainer { {UL-Timeslot-InformationItem-PhyChReconfRqstTDD768-ExtIEs} } OPTIONAL,
   iE-Extensions
    . . .
UL-Timeslot-InformationItem-PhyChReconfRgstTDD768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
                                                 ::= ProtocolIE-Single-Container { {DL-CCTrCH-InformationListIEs-PhyChReconfRqstTDD} }
DL-CCTrCH-InformationList-PhyChReconfRqstTDD
DL-CCTrCH-InformationListIEs-PhyChReconfRqstTDD RNSAP-PROTOCOL-IES ::= {
    PRESENCE mandatory }
DL-CCTrCH-InformationListIE-PhyChReconfRqstTDD ::= SEQUENCE (SIZE (1..maxNrOfCCTrCHs)) OF DL-CCTrCH-InformationItem-PhyChReconfRqstTDD
DL-CCTrCH-InformationItem-PhyChReconfRqstTDD ::= SEQUENCE {
   cCTrCH-ID
                                  CCTrCH-ID,
   dl-DPCH-Information
                                  DL-DPCH-InformationList-PhyChReconfRqstTDD,
                                  ProtocolExtensionContainer { {DL-CCTrCH-InformationItem-PhyChReconfRqstTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
```

```
DL-CCTrCH-InformationItem-PhyChReconfRqstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-DPCH-InformationList-PhyChReconfRqstTDD ::= ProtocolIE-Single-Container {{DL-DPCH-InformationListIEs-PhyChReconfRqstTDD}}
DL-DPCH-InformationListIEs-PhyChReconfRqstTDD RNSAP-PROTOCOL-IES ::= {
    { ID id-DL-DPCH-InformationItem-PhyChReconfRqstTDD CRITICALITY notify TYPE DL-DPCH-InformationItem-PhyChReconfRqstTDD
                                                                                                                                         PRESENCE
mandatory }
DL-DPCH-InformationItem-PhyChReconfRgstTDD ::= SEQUENCE
    repetitionPeriod
                                                     RepetitionPeriod
                                                                                                                                           OPTIONAL,
    repetitionLength
                                                     RepetitionLength
                                                                                                                                           OPTIONAL,
    tDD-DPCHOffset
                                                     TDD-DPCHOffset
                                                                                                                                           OPTIONAL,
    dL-Timeslot-InformationList-PhyChReconfRqstTDD DL-Timeslot-InformationList-PhyChReconfRqstTDD
                                                                                                                                           OPTIONAL,
                                                     ProtocolExtensionContainer { {DL-DPCH-InformationItem-PhyChReconfRqstTDD-ExtIEs} }
    iE-Extensions
                                                                                                                                           OPTIONAL,
    . . .
DL-DPCH-InformationItem-PhyChReconfRgstTDD-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-DL-Timeslot-LCR-InformationList-PhyChReconfRqstTDD
                                                                     CRITICALITY reject
                                                                                             EXTENSION DL-TimeslotLCR-InformationList-
PhyChReconfRqstTDD
                        PRESENCE optional }
    --For 1.28Mcps TDD only
    { ID id-DL-Timeslot-InformationList-PhyChReconfRqstTDD768
                                                                     CRITICALITY reject
                                                                                             EXTENSION DL-Timeslot-InformationList-
                            PRESENCE optional },
PhyChReconfRqstTDD768
    --For 7.68Mcps TDD only
    . . .
DL-TimeslotLCR-InformationList-PhyChReconfRgstTDD::= SEQUENCE ( SIZE (1..maxNrOfTsLCR)) OF DL-TimeslotLCR-InformationItem-PhyChReconfRgstTDD
DL-TimeslotLCR-InformationItem-PhyChReconfRqstTDD ::= SEQUENCE {
    timeSlotLCR
                                    TimeSlotLCR,
                                    MidambleShiftLCR
    midambleShiftLCR
                                                            OPTIONAL,
    tFCI-Presence
                                    TFCI-Presence
                                                        OPTIONAL,
    dL-Code-LCR-Information
                                    TDD-DL-Code-LCR-Information
                                                                     OPTIONAL,
                                    ProtocolExtensionContainer { {DL-TimeslotLCR-InformationItem-PhyChReconfRqstTDD-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
DL-TimeslotLCR-InformationItem-PhyChReconfRgstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-Timeslot-InformationList-PhyChReconfRqstTDD::= SEQUENCE ( SIZE (1..maxNrOfTS)) OF DL-Timeslot-InformationItem-PhyChReconfRqstTDD
DL-Timeslot-InformationItem-PhyChReconfRqstTDD ::= SEQUENCE {
    timeSlot
                                    TimeSlot,
    midambleShiftAndBurstType
                                                MidambleShiftAndBurstType
                                                                                 OPTIONAL,
    tFCI-Presence
                                    TFCI-Presence
                                                        OPTIONAL,
```

```
dL-Code-Information
                                TDD-DL-Code-Information
                                                            OPTIONAL,
    iE-Extensions
                                    ProtocolExtensionContainer { {DL-Timeslot-InformationItem-PhyChReconfRqstTDD-ExtIEs} } OPTIONAL,
DL-Timeslot-InformationItem-PhyChReconfRqstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-Timeslot-InformationList-PhyChReconfRqstTDD768::= SEQUENCE ( SIZE (1..maxNrOfTS)) OF DL-Timeslot-InformationItem-PhyChReconfRqstTDD768
DL-Timeslot-InformationItem-PhyChReconfRqstTDD768 ::= SEQUENCE {
    timeSlot
                                    TimeSlot,
   midambleShiftAndBurstType768
                                  MidambleShiftAndBurstType768
                                                                        OPTIONAL,
    tFCI-Presence
                                    TFCI-Presence
                                                        OPTIONAL.
    dL-Code-Information768
                                    TDD-DL-Code-Information768
                                                                    OPTIONAL,
                                    ProtocolExtensionContainer { {DL-Timeslot-InformationItem-PhyChReconfRqstTDD768-ExtIEs} } OPTIONAL,
    iE-Extensions
DL-Timeslot-InformationItem-PhyChReconfRqstTDD768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HSPDSCH-Timeslot-InformationList-PhyChReconfRqstTDD ::= SEQUENCE (SIZE (1..maxNrOfDLTs)) OF HSPDSCH-Timeslot-InformationItem-PhyChReconfRqstTDD
HSPDSCH-Timeslot-InformationItem-PhyChReconfRqstTDD::= SEQUENCE {
    timeslot
                                                    TimeSlot,
    midambleShiftAndBurstType
                                                    MidambleShiftAndBurstType,
   iE-Extensions
                                                    ProtocolExtensionContainer { { HSPDSCH-Timeslot-InformationItem-PhyChReconfRqstTDD-ExtIEs } }
           OPTIONAL,
    . . .
HSPDSCH-Timeslot-InformationItem-PhyChReconfRqstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HSPDSCH-Timeslot-InformationListLCR-PhyChReconfRgstTDD::= SEQUENCE (SIZE (1..maxNrOfDLTsLCR)) OF HSPDSCH-Timeslot-InformationItemLCR-
PhyChReconfRastTDD
HSPDSCH-Timeslot-InformationItemLCR-PhyChReconfRqstTDD::= SEQUENCE {
    timeslotLCR
                                                TimeSlotLCR,
    midambleShiftLCR
                                                MidambleShiftLCR,
   iE-Extensions
                                                ProtocolExtensionContainer { { HSPDSCH-Timeslot-InformationItemLCR-PhyChReconfRqstTDD-ExtIEs } }
           OPTIONAL,
    . . .
HSPDSCH-Timeslot-InformationItemLCR-PhyChReconfRqstTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
HSPDSCH-Timeslot-InformationList-PhyChreconfRqstTDD768 ::= SEQUENCE (SIZE (1..maxNrOfDLTs)) OF HSPDSCH-Timeslot-InformationItem-
PhyChReconfRqstTDD768
HSPDSCH-Timeslot-InformationItem-PhyChReconfRqstTDD768::= SEQUENCE {
                                                 TimeSlot.
   midambleShiftAndBurstType768
                                                 MidambleShiftAndBurstType768,
   iE-Extensions
                                                 ProtocolExtensionContainer { { HSPDSCH-Timeslot-InformationItem-PhyChReconfRqstTDD768-ExtIEs }
           OPTIONAL,
HSPDSCH-Timeslot-InformationItem-PhyChReconfRqstTDD768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
PhysicalChannelReconfigurationRequestTDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
-- PHYSICAL CHANNEL RECONFIGURATION COMMAND
  *****************
PhysicalChannelReconfigurationCommand ::= SEQUENCE
                                                            {{PhysicalChannelReconfigurationCommand-IEs}},
   protocolIEs
                                 ProtocolIE-Container
   protocolExtensions
                                 ProtocolExtensionContainer {{PhysicalChannelReconfigurationCommand-Extensions}}
                                                                                                                               OPTIONAL,
PhysicalChannelReconfigurationCommand-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-CFN
                             CRITICALITY ignore TYPE CFN
                                                                           PRESENCE mandatory
    ID id-CriticalityDiagnostics
                                                                                            PRESENCE optional
                                    CRITICALITY ignore TYPE CriticalityDiagnostics
PhysicalChannelReconfigurationCommand-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
-- PHYSICAL CHANNEL RECONFIGURATION FAILURE
  *****************
PhysicalChannelReconfigurationFailure ::= SEQUENCE {
   protocolIEs
                                 ProtocolIE-Container
                                                            {{PhysicalChannelReconfigurationFailure-IEs}},
   protocolExtensions
                                 ProtocolExtensionContainer {{PhysicalChannelReconfigurationFailure-Extensions}}
                                                                                                                               OPTIONAL,
PhysicalChannelReconfigurationFailure-IEs RNSAP-PROTOCOL-IES ::= {
```

```
ID id-Cause
                                CRITICALITY ignore TYPE Cause
                                                                            PRESENCE mandatory } |
    ID id-CriticalityDiagnostics
                                        CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                         PRESENCE optional
PhysicalChannelReconfigurationFailure-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
-- RADIO LINK CONGESTION INDICATION
  RadioLinkCongestionIndication ::= SEOUENCE {
                                                         {{RadioLinkCongestionIndication-IEs}},
   protocolIEs
                                ProtocolIE-Container
                                ProtocolExtensionContainer {{RadioLinkCongestionIndication-Extensions}}
   protocolExtensions
                                                                                                                  OPTIONAL,
   . . .
RadioLinkCongestionIndication-IES RNSAP-PROTOCOL-IES ::= {
     ID id-CongestionCause
                                                                                                                PRESENCE optional } |
                              CRITICALITY ignore TYPE CongestionCause
     PRESENCE mandatory },
RL-InformationList-RL-CongestInd
                                       ::= SEOUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-InformationItemIEs-RL-
CongestInd } }
RL-InformationItemIEs-RL-CongestInd RNSAP-PROTOCOL-IES ::= {
   { ID id-RL-InformationItem-RL-CongestInd
                                               CRITICALITY ignore TYPE RL-InformationItem-RL-CongestInd
                                                                                                             PRESENCE mandatory
RL-InformationItem-RL-CongestInd ::= SEQUENCE {
                                    RL-ID,
   dCH-Rate-Information
                             DCH-Rate-Information-RL-CongestInd,
                            ProtocolExtensionContainer { {RL-Information-RL-CongestInd-ExtIEs} } OPTIONAL,
   iE-Extensions
DCH-Rate-Information-RL-CongestInd ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF ProtocolIE-Single-Container { {DCH-Rate-InformationItemIEs-RL-
CongestInd } }
DCH-Rate-InformationItemIEs-RL-CongestInd RNSAP-PROTOCOL-IES ::= {
     ID id-DCH-Rate-InformationItem-RL-CongestInd
                                                  CRITICALITY ignore TYPE DCH-Rate-InformationItem-RL-CongestInd
                                                                                                                    PRESENCE mandatory
DCH-Rate-InformationItem-RL-CongestInd ::= SEQUENCE {
                             DCH-ID,
   allowed-Rate-Information
                            Allowed-Rate-Information OPTIONAL,
   iE-Extensions
                             ProtocolExtensionContainer { {DCH-Rate-InformationItem-RL-CongestInd-ExtIEs} } OPTIONAL,
   . . .
```

```
DCH-Rate-InformationItem-RL-CongestInd-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RL-Information-RL-CongestInd-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   PRESENCE optional } |
                                               CRITICALITY ignore EXTENSION DCH-Indicator-For-E-DCH-HSDPA-Operation
   { ID id-DCH-Indicator-For-E-DCH-HSDPA-Operation
                        PRESENCE optional },
RadioLinkCongestionIndication-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
EDCH-MacdFlowSpecificInformationList-RL-CongestInd ::= SEQUENCE (SIZE (1.. maxNrOfEDCHMACdFlows)) OF ProtocolIE-Single-Container { {EDCH-
MacdFlowSpecificInformationItemIEs-RL-CongestInd} }
EDCH-MacdFlowSpecificInformationItemIEs-RL-CongestInd RNSAP-PROTOCOL-IES ::= {
   { ID id-EDCH-MacdFlowSpecificInformationItem-RL-CongestInd
                                                           CRITICALITY ignore TYPE EDCH-MacdFlowSpecificInformationItem-RL-CongestInd
   PRESENCE mandatory }
EDCH-MacdFlowSpecificInformationItem-RL-CongestInd ::= SEQUENCE {
   eDCH-MACdFlow-ID
                           EDCH-MACdFlow-ID,
                           ProtocolExtensionContainer { { EDCH-MacdFlowSpecificInformation-RL-CongestInd-ExtIEs} } OPTIONAL,
   iE-Extensions
EDCH-MacdFlowSpecificInformation-RL-CongestInd-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    *****************
-- UPLINK SIGNALLING TRANSFER INDICATION FDD
__ *********************
UplinkSignallingTransferIndicationFDD ::= SEQUENCE {
                                                       {{UplinkSignallingTransferIndicationFDD-IEs}},
   protocolIEs
                               ProtocolIE-Container
   protocolExtensions
                               ProtocolExtensionContainer {{UplinkSignallingTransferIndicationFDD-Extensions}}
                                                                                                                      OPTIONAL,
UplinkSignallingTransferIndicationFDD-IES RNSAP-PROTOCOL-IES ::= {
     ID id-UC-ID
                                                    CRITICALITY ignore TYPE UC-ID
                                                                                                               PRESENCE mandatory
     ID id-SAI
                                                    CRITICALITY ignore TYPE SAI
                                                                                                               PRESENCE mandatory
```

```
ID id-GA-Cell
                                                       CRITICALITY ignore
                                                                          TYPE GA-Cell
                                                                                                                      PRESENCE optional
     ID id-C-RNTI
                                                       CRITICALITY ignore
                                                                           TYPE C-RNTI
                                                                                                                      PRESENCE mandatory
     ID id-S-RNTI
                                                        CRITICALITY ignore
                                                                           TYPE S-RNTI
                                                                                                                       PRESENCE mandatory
     ID id-D-RNTI
                                                        CRITICALITY ignore
                                                                           TYPE D-RNTI
                                                                                                                       PRESENCE optional
     ID id-PropagationDelay
                                                       CRITICALITY ignore
                                                                           TYPE PropagationDelay
                                                                                                                      PRESENCE mandatory
     ID id-STTD-SupportIndicator
                                                       CRITICALITY ignore
                                                                           TYPE STTD-SupportIndicator
                                                                                                                      PRESENCE mandatory
                                                                                                                      PRESENCE mandatory }
    ID id-ClosedLoopModel-SupportIndicator
                                                       CRITICALITY ignore
                                                                           TYPE ClosedLoopModel-SupportIndicator
     ID id-L3-Information
                                                        CRITICALITY ignore
                                                                           TYPE L3-Information
                                                                                                                      PRESENCE mandatory
     ID id-CN-PS-DomainIdentifier
                                                        CRITICALITY ignore
                                                                           TYPE CN-PS-DomainIdentifier
                                                                                                                      PRESENCE optional
     ID id-CN-CS-DomainIdentifier
                                                                           TYPE CN-CS-DomainIdentifier
                                                                                                                      PRESENCE optional
                                                        CRITICALITY ignore
     ID id-IIRA-Information
                                                        CRITICALITY ignore
                                                                          TYPE URA-Information
                                                                                                                      PRESENCE optional
UplinkSignallingTransferIndicationFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-GA-CellAdditionalShapes
                                                        CRITICALITY ignore
                                                                           EXTENSION GA-CellAdditionalShapes
                                                                                                                      PRESENCE optional }
     ID id-DPC-Mode-Change-SupportIndicator
                                                        CRITICALITY ignore
                                                                           EXTENSION DPC-Mode-Change-SupportIndicator
                                                                                                                      PRESENCE optional }
     ID id-CommonTransportChannelResourcesInitialisationNotRequired CRITICALITY ignore
                                                                                                                      EXTENSION
CommonTransportChannelResourcesInitialisationNotRequired
                                                       PRESENCE optional } |
     ID id-CellCapabilityContainer-FDD
                                                       CRITICALITY ignore
                                                                           EXTENSION CellCapabilityContainer-FDD
                                                                                                                      PRESENCE optional }
     ID id-SNA-Information
                                                        CRITICALITY ignore
                                                                           EXTENSION SNA-Information
                                                                                                                       PRESENCE optional
     ID id-CellPortionID
                                                       CRITICALITY ignore
                                                                           EXTENSION CellPortionID
                                                                                                                      PRESENCE optional
     ID id-Active-MBMS-Bearer-ServiceFDD
                                                       CRITICALITY ignore
                                                                           EXTENSION Active-MBMS-Bearer-Service-ListFDD
                                                                                                                      PRESENCE optional}
                                                       CRITICALITY ignore
                                                                                                                       PRESENCE optional
     ID id-Inter-Frequency-Cell-List
                                                                           EXTENSION Inter-Frequency-Cell-List
     ID id-ExtendedPropagationDelay
                                                       CRITICALITY ignore EXTENSION ExtendedPropagationDelay
                                                                                                                      PRESENCE optional
     ID id-HSDSCH-RNTI
                                                        CRITICALITY ignore EXTENSION HSDSCH-RNTI
                                                                                                                      PRESENCE optional
     ID id-Multiple-PLMN-List
                                                       CRITICALITY ignore
                                                                           EXTENSION Multiple-PLMN-List
                                                                                                                      PRESENCE optional
     ID id-E-RNTI
                                                       CRITICALITY ignore EXTENSION E-RNTI
                                                                                                                      PRESENCE optional }
     ID id-Max-UE-DTX-Cycle
                                                       CRITICALITY ignore
                                                                         EXTENSION Max-UE-DTX-Cycle
                                                                                                                       PRESENCE
conditional }
   -- This IE shall be present if the Continuous Packet Connectivity DTX-DRX Support Indicator IE in Cell Capability Container FDD IE is set to 1.
     ID id-CellCapabilityContainerExtension-FDD
                                               CRITICALITY ignore EXTENSION CellCapabilityContainerExtension-FDD
                                                                                                                        PRESENCE optional } |
     ID id-Secondary-Serving-Cell-List CRITICALITY ignore EXTENSION Secondary-Serving-Cell-List
                                                                                                   PRESENCE optional } |
     -- UPLINK SIGNALLING TRANSFER INDICATION TDD
     ************************
```

```
UplinkSignallingTransferIndicationTDD ::= SEQUENCE {
    protocolIEs
                                    ProtocolIE-Container
                                                                {{UplinkSignallingTransferIndicationTDD-IEs}},
                                    ProtocolExtensionContainer {{UplinkSignallingTransferIndicationTDD-Extensions}}
    protocolExtensions
                                                                                                                                        OPTIONAL.
UplinkSignallingTransferIndicationTDD-IES RNSAP-PROTOCOL-IES ::= {
                                                                                                                                 PRESENCE mandatory }
    { ID id-UC-ID
                                                CRITICALITY ignore
                                                                        TYPE UC-ID
    { ID id-SAI
                                                                                                                                 PRESENCE mandatory }
                                                CRITICALITY ignore
                                                                        TYPE SAI
                                                                                                                                 PRESENCE optional }
    { ID id-GA-Cell
                                                CRITICALITY ignore
                                                                        TYPE GA-Cell
    { ID id-C-RNTI
                                                CRITICALITY ignore
                                                                        TYPE C-RNTI
                                                                                                                                 PRESENCE mandatory }
    { ID id-S-RNTI
                                                CRITICALITY ignore
                                                                        TYPE S-RNTI
                                                                                                                                 PRESENCE mandatory }
                                                                                                                                 PRESENCE optional }
    { ID id-D-RNTI
                                                CRITICALITY ignore
                                                                        TYPE D-RNTI
    { ID id-RxTimingDeviationForTA
                                                                        TYPE RxTimingDeviationForTA
                                                                                                                                 PRESENCE mandatory }
                                                CRITICALITY ignore
                                                                                                                                 PRESENCE mandatory }
    { ID id-L3-Information
                                                CRITICALITY ignore
                                                                        TYPE L3-Information
                                                                                                                                 PRESENCE optional }
    { ID id-CN-PS-DomainIdentifier
                                                CRITICALITY ignore
                                                                        TYPE CN-PS-DomainIdentifier
    { ID id-CN-CS-DomainIdentifier
                                                CRITICALITY ignore
                                                                        TYPE CN-CS-DomainIdentifier
                                                                                                                                 PRESENCE optional }
    { ID id-URA-Information
                                                CRITICALITY ignore
                                                                        TYPE URA-Information
                                                                                                                                 PRESENCE optional },
UplinkSignallingTransferIndicationTDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
      ID id-GA-CellAdditionalShapes
                                                CRITICALITY ignore
                                                                        EXTENSION GA-CellAdditionalShapes
                                                                                                                                 PRESENCE optional } |
     ID id-CommonTransportChannelResourcesInitialisationNotRequired
                                                                       CRITICALITY ignore
EXTENSION CommonTransportChannelResourcesInitialisationNotRequired
                                                                                                                                 PRESENCE optional }
                                                CRITICALITY ignore
                                                                                                                                 PRESENCE optional }
    { ID id-CellCapabilityContainer-TDD
                                                                        EXTENSION CellCapabilityContainer-TDD
    -- Applicable to 3.84Mcps TDD only
    { ID id-CellCapabilityContainer-TDD-LCR
                                                                        EXTENSION CellCapabilityContainer-TDD-LCR
                                                                                                                                 PRESENCE optional } |
                                                CRITICALITY ignore
    -- Applicable to 1.28Mcps TDD only
     ID id-SNA-Information
                                                CRITICALITY ignore
                                                                        EXTENSION SNA-Information
                                                                                                                                 PRESENCE optional }
      ID id-Active-MBMS-Bearer-ServiceTDD
                                                                                                                                 PRESENCE optional }
                                                CRITICALITY ignore
                                                                        EXTENSION Active-MBMS-Bearer-Service-ListTDD
     ID id-CellCapabilityContainer-TDD768
                                                CRITICALITY ignore
                                                                        EXTENSION CellCapabilityContainer-TDD768
                                                                                                                                 PRESENCE optional }
    -- Applicable to 7.68Mcps TDD only
      ID id-RxTimingDeviationForTA768
                                                CRITICALITY ignore
                                                                        EXTENSION RxTimingDeviationForTA768
                                                                                                                                 PRESENCE optional
      ID id-RxTimingDeviationForTAext
                                                CRITICALITY ignore
                                                                        EXTENSION RxTimingDeviationForTAext
                                                                                                                                 PRESENCE optional
      ID id-Multiple-PLMN-List
                                                                                                                                 PRESENCE optional }
                                                CRITICALITY ignore
                                                                        EXTENSION Multiple-PLMN-List
      ID id-HSDSCH-RNTI
                                                CRITICALITY ignore
                                                                        EXTENSION HSDSCH-RNTI
                                                                                                                                 PRESENCE optional
      ID id-E-RNTI
                                                CRITICALITY ignore
                                                                        EXTENSION E-RNTI
                                                                                                                                 PRESENCE optional }
      ID id-CellPortionLCRID
                                                CRITICALITY ignore
                                                                        EXTENSION CellPortionLCRID
                                                                                                                                 PRESENCE optional } |
     ID id-CellCapabilityContainerExtension-TDD-LCR CRITICALITY ignore EXTENSION CellCapabilityContainerExtension-TDD-LCR
                                                                                                                                 PRESENCE optional },
```

```
*****************
-- DOWNLINK SIGNALLING TRANSFER REQUEST
  ****************
DownlinkSignallingTransferRequest ::= SEOUENCE {
   protocolIEs
                                                           {{DownlinkSignallingTransferRequest-IEs}},
                                 ProtocolIE-Container
   protocolExtensions
                                 ProtocolExtensionContainer {{DownlinkSignallingTransferRequest-Extensions}}
                                                                                                                         OPTIONAL,
DownlinkSignallingTransferRequest-IEs RNSAP-PROTOCOL-IES ::= {
   { ID id-C-ID
                                     CRITICALITY ignore TYPE C-ID
                                                                                         PRESENCE mandatory }
   -- May be a GERAN cell identifier
   { ID id-D-RNTI
                                     CRITICALITY ignore TYPE D-RNTI
                                                                                         PRESENCE mandatory }
     ID id-L3-Information
                                     CRITICALITY ignore TYPE L3-Information
                                                                                         PRESENCE mandatory
    { ID id-D-RNTI-ReleaseIndication
                                     CRITICALITY ignore TYPE D-RNTI-ReleaseIndication
                                                                                           PRESENCE mandatory },
   . . .
DownlinkSignallingTransferRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
                                                                                                                PRESENCE optional }
     ID id-URA-ID
                                     CRITICALITY ignore
                                                           EXTENSION
                                                                      URA-ID
     ID id-MBMS-Bearer-Service-List
                                     CRITICALITY ignore
                                                           EXTENSION MBMS-Bearer-Service-List
                                                                                                                PRESENCE optional}
     ID id-Old-URA-ID
                                     CRITICALITY ignore
                                                           EXTENSION URA-ID
                                                                                                                PRESENCE optional }
   { ID id-SRNC-ID
                                     CRITICALITY ignore
                                                           EXTENSION RNC-ID
                                                                                                                PRESENCE conditional }
   -- This IE shall be present if the URA-ID IE or Old URA-ID IE is present.
   { ID id-Extended-SRNC-ID
                                     CRITICALITY reject
                                                           EXTENSION Extended-RNC-ID
                                                                                                                PRESENCE optional }
   { ID id-Enhanced-PCH-Capability
                                                                                                                PRESENCE optional },
                                     CRITICALITY ignore
                                                           EXTENSION Enhanced-PCH-Capability
   -- FDD and 1.28Mcps TDD only
-- RELOCATION COMMIT
__ ********************************
RelocationCommit ::= SEQUENCE {
                                                           {{RelocationCommit-IEs}},
   protocolIEs
                                 ProtocolIE-Container
                                 ProtocolExtensionContainer {{RelocationCommit-Extensions}}
   protocolExtensions
                                                                                                         OPTIONAL,
RelocationCommit-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-D-RNTI
                                 CRITICALITY ignore TYPE D-RNTI
                                                                              PRESENCE optional
                                         CRITICALITY ignore TYPE RANAP-RelocationInformation
    { ID id-RANAP-RelocationInformation
                                                                                                  PRESENCE optional
RelocationCommit-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
   . . .
```

```
-- PAGING REOUEST
   ******************
PagingRequest ::= SEQUENCE {
                                   ProtocolIE-Container
                                                              {{PagingRequest-IEs}},
    protocolIEs
                                   ProtocolExtensionContainer {{PagingRequest-Extensions}}
   protocolExtensions
                                                                                                           OPTIONAL,
    . . .
PagingRequest-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-PagingArea-PagingRgst
                                           CRITICALITY ignore TYPE PagingArea-PagingRqst
                                                                                                       PRESENCE mandatory
     ID id-SRNC-ID
                                           CRITICALITY ignore TYPE RNC-ID
                                                                                                       PRESENCE mandatory
                                                                                                                                 -- May be a BSC-
Id.
                                           CRITICALITY ignore TYPE S-RNTI
     ID id-S-RNTI
                                                                                                       PRESENCE mandatory
     ID id-IMSI
                                                                                                       PRESENCE mandatory
                                           CRITICALITY ignore TYPE IMSI
     ID id-DRXCycleLengthCoefficient
                                           CRITICALITY ignore TYPE DRXCycleLengthCoefficient
                                                                                                       PRESENCE mandatory
    ID id-CNOriginatedPage-PagingRgst
                                           CRITICALITY ignore TYPE CNOriginatedPage-PagingRqst
                                                                                                       PRESENCE optional
PagingArea-PagingRqst ::= CHOICE {
                           URA-PagingRgst, -- May be a GRA-ID.
    uRA
    cell
                           Cell-PagingRgst, -- UTRAN only
    . . .
URA-PagingRqst ::= SEQUENCE {
    uRA-ID
                               URA-ID,
                               ProtocolExtensionContainer { { URAItem-PagingRqst-ExtIEs} } OPTIONAL,
    iE-Extensions
URAItem-PagingRqst-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Cell-PagingRqst ::= SEQUENCE {
    c-ID
                               ProtocolExtensionContainer { { CellItem-PagingRqst-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
CellItem-PagingRqst-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
CNOriginatedPage-PagingRqst::= SEQUENCE {
    pagingCause
                               PagingCause,
    cNDomainType
                               CNDomainType,
```

```
pagingRecordType
                             PagingRecordType,
   iE-Extensions
                             ProtocolExtensionContainer { { CNOriginatedPage-PagingRgst-ExtIEs} } OPTIONAL,
CNOriginatedPage-PagingRqst-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
PagingRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::=
     ID id-Extended-SRNC-ID
                                    CRITICALITY reject
                                                          EXTENSION Extended-RNC-ID
                                                                                               PRESENCE optional } |
   { ID id-Enhanced-PCH-Capability
                                                                                               PRESENCE optional },
                                    CRITICALITY ignore
                                                          EXTENSION Enhanced-PCH-Capability
   -- FDD and 1.28Mcps TDD only
  DEDICATED MEASUREMENT INITIATION REQUEST
     DedicatedMeasurementInitiationRequest ::= SEQUENCE {
   protocolIEs
                                ProtocolIE-Container
                                                         {{DedicatedMeasurementInitiationRequest-IEs}},
                                ProtocolExtensionContainer {{DedicatedMeasurementInitiationRequest-Extensions}}
   protocolExtensions
                                                                                                                          OPTIONAL,
   . . .
DedicatedMeasurementInitiationRequest-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-MeasurementID
                                    CRITICALITY reject TYPE MeasurementID
                                                                                   PRESENCE mandatory } |
     PRESENCE mandatory }
     ID id-DedicatedMeasurementType
                                       CRITICALITY reject TYPE DedicatedMeasurementType
                                                                                               PRESENCE mandatory }
     ID id-MeasurementFilterCoefficient
                                       CRITICALITY reject TYPE MeasurementFilterCoefficient
                                                                                               PRESENCE optional }
     ID id-ReportCharacteristics
                                       CRITICALITY reject TYPE ReportCharacteristics
                                                                                               PRESENCE mandatory }
     ID id-CFNReportingIndicator
                                       CRITICALITY reject TYPE FNReportingIndicator
                                                                                               PRESENCE mandatory }
   { ID id-CFN
                                       CRITICALITY reject TYPE CFN
                                                                                               PRESENCE optional },
   . . .
DedicatedMeasurementObjectType-DM-Rqst ::= CHOICE {
                         RL-DM-Rast,
   rLS
                         RL-Set-DM-Rqst,
   allRL
                         All-RL-DM-Rgst,
   allRLS
                         All-RL-Set-DM-Rgst,
RL-DM-Rqst ::= SEQUENCE {
   rL-InformationList-DM-Rqst
                                RL-InformationList-DM-Rqst,
   iE-Extensions
                                ProtocolExtensionContainer { { RLItem-DM-Rqst-ExtIEs} } OPTIONAL,
   . . .
```

```
RLItem-DM-Rqst-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RL-InformationList-DM-Rgst
                                           ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-Information-DM-Rgst-IEs} }
RL-Information-DM-Rgst-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-InformationItem-DM-Rgst
                                           CRITICALITY reject TYPE RL-InformationItem-DM-Rqst
                                                                                                         PRESENCE mandatory
RL-InformationItem-DM-Rqst ::= SEQUENCE {
                               RL-ID,
    dPCH-ID
                               DPCH-ID
                                           OPTIONAL,
   iE-Extensions
                                    ProtocolExtensionContainer { {RL-InformationItem-DM-Rgst-ExtIEs} } OPTIONAL.
RL-InformationItem-DM-Rgst-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-HSSICH-Info-DM-Rgst
                                               CRITICALITY reject
                                                                                EXTENSION HSSICH-Info-DM-Rgst
    PRESENCE optional |
    -- TDD only
    { ID id-DPCH-ID768-DM-Rqst
                                               CRITICALITY reject
                                                                                EXTENSION DPCH-ID768
               PRESENCE optional |
    { ID id-HSSICH-Info-DM-Rgst-Extension
                                               CRITICALITY reject
                                                                               EXTENSION HSSICH-Info-DM-Rgst-Extension
                                                                                                                                       PRESENCE
optional},
    -- Applicable for 1.28Mcps TDD only when the HS-SICH ID IE is more than 31
HSSICH-Info-DM-Rgst ::= SEOUENCE (SIZE (1..maxNrOfHSSICHs)) OF HS-SICH-ID
HSSICH-Info-DM-Rqst-Extension ::= SEQUENCE (SIZE (1..maxNrOfHSSICHs)) OF HS-SICH-ID-Extension
RL-Set-DM-Rqst ::= SEQUENCE {
    rL-Set-InformationList-DM-Rgst RL-Set-InformationList-DM-Rgst,
   iE-Extensions
                                   ProtocolExtensionContainer { RL-SetItem-DM-Rqst-ExtIEs} } OPTIONAL,
RL-SetItem-DM-Rgst-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RL-Set-InformationList-DM-Rqst
                                               ::= SEQUENCE (SIZE (1..maxNrOfRLSets)) OF ProtocolIE-Single-Container { {RL-Set-Information-DM-
Rast-IEs} }
RL-Set-Information-DM-Rgst-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-Set-InformationItem-DM-Rqst
                                               CRITICALITY reject TYPE RL-Set-InformationItem-DM-Rqst
                                                                                                                        PRESENCE mandatory
RL-Set-InformationItem-DM-Rqst ::= SEQUENCE {
   rL-Set-ID
                                    RL-Set-ID,
    iE-Extensions
                                    ProtocolExtensionContainer { {RL-Set-InformationItem-DM-Rqst-ExtIEs} } OPTIONAL,
```

```
RL-Set-InformationItem-DM-Rgst-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
All-RL-DM-Rgst ::= NULL
All-RL-Set-DM-Rqst ::= NULL
DedicatedMeasurementInitiationRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-PartialReportingIndicator
                                                CRITICALITY ignore EXTENSION
                                                                              PartialReportingIndicator
   PRESENCE optional } |
   { ID
        id-MeasurementRecoveryBehavior
                                                CRITICALITY ignore EXTENSION
                                                                              MeasurementRecoveryBehavior
                                                                                                                              PRESENCE
optional }|
    { ID id-AlternativeFormatReportingIndicator
                                                CRITICALITY ignore EXTENSION
                                                                              AlternativeFormatReportingIndicator PRESENCE optional },
  DEDICATED MEASUREMENT INITIATION RESPONSE
DedicatedMeasurementInitiationResponse ::= SEQUENCE
                                                           {{DedicatedMeasurementInitiationResponse-IEs}},
   protocolIEs
                                 ProtocolIE-Container
   protocolExtensions
                                 ProtocolExtensionContainer {{DedicatedMeasurementInitiationResponse-Extensions}}
                                                                                                                              OPTIONAL,
DedicatedMeasurementInitiationResponse-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-MeasurementID
                                                CRITICALITY ignore TYPE MeasurementID
   PRESENCE mandatory } |
    PRESENCE optional }
    { ID id-CriticalityDiagnostics
                                                CRITICALITY ignore TYPE CriticalityDiagnostics
    PRESENCE optional },
DedicatedMeasurementObjectType-DM-Rsp ::= CHOICE {
   rLs
                         RL-DM-Rsp,
   rLS
                          RL-Set-DM-Rsp,
   allRL
                          RL-DM-Rsp,
   allRLS
                         RL-Set-DM-Rsp,
    . . .
RL-DM-Rsp ::= SEQUENCE {
   rL-InformationList-DM-Rsp
                                                RL-InformationList-DM-Rsp,
   iE-Extensions
                                 ProtocolExtensionContainer { { RLItem-DM-Rsp-ExtIEs} } OPTIONAL,
```

```
RLItem-DM-Rsp-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RL-Set-DM-Rsp ::= SEQUENCE {
   rL-Set-InformationList-DM-Rsp RL-Set-InformationList-DM-Rsp,
                                   ProtocolExtensionContainer { { RL-SetItem-DM-Rsp-ExtIEs} } OPTIONAL,
   iE-Extensions
RL-SetItem-DM-Rsp-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RL-InformationList-DM-Rsp
                                          ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-Information-DM-Rsp-IEs} }
RL-Information-DM-Rsp-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-InformationItem-DM-Rsp
                                          CRITICALITY ignore TYPE RL-InformationItem-DM-Rsp PRESENCE mandatory
RL-InformationItem-DM-Rsp ::= SEQUENCE {
    dPCH-ID
                               DPCH-ID
                                                   OPTIONAL,
    dedicatedMeasurementValue DedicatedMeasurementValue.
    iE-Extensions
                               ProtocolExtensionContainer { {RL-InformationItem-DM-Rsp-ExtIEs} } OPTIONAL,
RL-InformationItem-DM-Rsp-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    {ID id-HSSICH-Info-DM
                               CRITICALITY reject
                                                               EXTENSION HS-SICH-ID
                                                                                          PRESENCE optional } |
    -- TDD only
    { ID id-multiple-DedicatedMeasurementValueList-TDD-DM-Rsp CRITICALITY ignore EXTENSION Multiple-DedicatedMeasurementValueList-TDD-DM-Rsp
    PRESENCE optional }
    -- Applicable to 3.84Mcps TDD only. This list of dedicated measurement values is used for the 2<sup>nd</sup> and beyond measurements of a RL when multiple
dedicated measurement values need to be reported.
    { ID id-multiple-DedicatedMeasurementValueList-LCR-TDD-DM-Rsp CRITICALITY ignore EXTENSION Multiple-DedicatedMeasurementValueList-LCR-
TDD-DM-Rsp PRESENCE optional }
    -- Applicable to 1.28Mcps TDD only. This list of dedicated measurement values is used for the 2<sup>nd</sup> and beyond measurements of a RL when multiple
dedicated measurement values need to be reported.
    { ID id-multiple-HSSICHMeasurementValueList-TDD-DM-Rsp
                                                                       CRITICALITY ignore EXTENSION Multiple-HSSICHMeasurementValueList-TDD-DM-
Rsp PRESENCE optional } |
   -- TDD only. This list of HS-SICH measurement values is used for the 2<sup>nd</sup> and beyond measurements of a RL when multiple HS-SICH measurement
values need to be reported.
                                                                       CRITICALITY ignore EXTENSION Multiple-DedicatedMeasurementValueList-
    { ID id-multiple-DedicatedMeasurementValueList-TDD768-DM-Rsp
TDD768-DM-Rsp PRESENCE optional
    -- Applicable to 7.68Mcps TDD only. This list of dedicated measurement values is used for the 2nd and beyond measurements of a RL when multiple
dedicated measurement values need to be reported.
    { ID id-DPCH-ID768-DM-Rsp
                                                                       CRITICALITY ignore EXTENSION DPCH-ID768
                       PRESENCE optional |
                                                                       CRITICALITY ignore EXTENSION HS-SICH-ID-Extension
    { ID id-HS-SICH-ID-Extension
                   PRESENCE optional },
    -- Applicable for 1.28Mcps TDD only when the HS-SICH ID IE is more than 31
```

```
RL-Set-InformationList-DM-Rsp ::= SEQUENCE (SIZE (1..maxNrOfRLSets)) OF ProtocolIE-Single-Container { {RL-Set-Information-DM-Rsp-IEs} }
RL-Set-Information-DM-Rsp-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-Set-InformationItem-DM-Rsp
                                                CRITICALITY ignore TYPE RL-Set-InformationItem-DM-Rsp
                                                                                                                 PRESENCE mandatory
RL-Set-InformationItem-DM-Rsp ::= SEQUENCE {
                                    RL-Set-ID,
   rL-Set-ID
    dedicatedMeasurementValue
                                    DedicatedMeasurementValue,
                                                OPTIONAL,
    CFN
                                    CFN
    iE-Extensions
                                    ProtocolExtensionContainer { {RL-Set-InformationItem-DM-Rspns-ExtIEs} }
                                                                                                                 OPTIONAL,
RL-Set-InformationItem-DM-Rspns-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DedicatedMeasurementInitiationResponse-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
           id-MeasurementRecoverySupportIndicator
                                                        CRITICALITY ignore
                                                                                EXTENSION MeasurementRecoverySupportIndicator
                                                                                                                                        PRESENCE
optional
    },
    . . .
Multiple-DedicatedMeasurementValueList-TDD-DM-Rsp ::= SEQUENCE (SIZE (1.. maxNrOfDPCHsPerRL-1)) OF Multiple-DedicatedMeasurementValueItem-TDD-DM-
Multiple-DedicatedMeasurementValueItem-TDD-DM-Rsp ::= SEQUENCE {
    dPCH-ID
                                        DPCH-ID,
    dedicatedMeasurementValue
                                        DedicatedMeasurementValue,
   iE-Extensions
                                        ProtocolExtensionContainer { { Multiple-DedicatedMeasurementValueItem-TDD-DM-Rsp-ExtIEs} }
   OPTIONAL,
    . . .
Multiple-DedicatedMeasurementValueItem-TDD-DM-Rsp-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Multiple-DedicatedMeasurementValueList-LCR-TDD-DM-Rsp ::= SEOUENCE (SIZE (1.. maxNrOfDPCHsLCRPerRL-1)) OF Multiple-DedicatedMeasurementValueItem-
LCR-TDD-DM-Rsp
Multiple-DedicatedMeasurementValueItem-LCR-TDD-DM-Rsp ::= SEQUENCE {
    dPCH-ID
                                        DPCH-ID,
    dedicatedMeasurementValue
                                        DedicatedMeasurementValue,
                                        ProtocolExtensionContainer { { Multiple-DedicatedMeasurementValueItem-LCR-TDD-DM-Rsp-ExtIEs} }
    iE-Extensions
   OPTIONAL,
```

```
Multiple-DedicatedMeasurementValueItem-LCR-TDD-DM-Rsp-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Multiple-HSSICHMeasurementValueList-TDD-DM-Rsp ::= SEQUENCE (SIZE (1.. maxNrOfHSSICHs-1)) OF Multiple-HSSICHMeasurementValueItem-TDD-DM-Rsp
Multiple-HSSICHMeasurementValueItem-TDD-DM-Rsp ::= SEQUENCE {
   hsSTCH-TD
                                    HS-SICH-ID,
   dedicatedMeasurementValue
                                    DedicatedMeasurementValue,
   iE-Extensions
                                    ProtocolExtensionContainer { { Multiple-HSSICHMeasurementValueItem-TDD-DM-Rsp-ExtIEs} }
                                                                                                                           OPTIONAL,
   . . .
Multiple-HSSICHMeasurementValueItem-TDD-DM-Rsp-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
   { ID id-HS-SICH-ID-Extension
                                       CRITICALITY ignore
                                                                                                      PRESENCE optional },
                                                             EXTENSION HS-SICH-ID-Extension
   -- Applicable for 1.28Mcps TDD only when the HS-SICH ID IE is more than 31
   . . .
Multiple-DedicatedMeasurementValueList-TDD768-DM-Rsp ::= SEQUENCE (SIZE (1.. maxNrOfDPCHs768PerRL-1)) OF Multiple-DedicatedMeasurementValueItem-
TDD768-DM-Rsp
Multiple-DedicatedMeasurementValueItem-TDD768-DM-Rsp ::= SEQUENCE {
   dPCH-ID768
                                    DPCH-ID768.
   dedicatedMeasurementValue
                                    DedicatedMeasurementValue,
   iE-Extensions
                                    ProtocolExtensionContainer { { Multiple-DedicatedMeasurementValueItem-TDD768-DM-Rsp-ExtIEs} }
   OPTIONAL,
   . . .
Multiple-DedicatedMeasurementValueItem-TDD768-DM-Rsp-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    DEDICATED MEASUREMENT INITIATION FAILURE
     ********************
DedicatedMeasurementInitiationFailure ::= SEQUENCE {
   protocolIEs
                                ProtocolIE-Container
                                                         {{DedicatedMeasurementInitiationFailure-IEs}},
                                ProtocolExtensionContainer {{DedicatedMeasurementInitiationFailure-Extensions}}
   protocolExtensions
                                                                                                                          OPTIONAL,
   . . .
DedicatedMeasurementInitiationFailure-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-MeasurementID
                                    CRITICALITY ignore TYPE MeasurementID
                                                                                   PRESENCE mandatory } |
     ID id-Cause
                                CRITICALITY ignore TYPE Cause
                                                                            PRESENCE mandatory }
   PRESENCE optional
```

```
DedicatedMeasurementInitiationFailure-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-DedicatedMeasurementObjectType-DM-Fail CRITICALITY ignore EXTENSION DedicatedMeasurementObjectType-DM-Fail
                                                                                                                           PRESENCE optional
    },
    . . .
DedicatedMeasurementObjectType-DM-Fail ::= CHOICE {
                          RL-DM-Fail,
   rLS
                          RL-Set-DM-Fail,
   allRL
                          RL-DM-Fail,
                          RL-Set-DM-Fail,
   allRLS
    . . .
RL-DM-Fail ::= SEOUENCE {
   rL-unsuccessful-InformationRespList-DM-Fail
                                                  RL-Unsuccessful-InformationRespList-DM-Fail,
   rL-successful-InformationRespList-DM-Fail
                                                  RL-Successful-InformationRespList-DM-Fail
                                                                                                     OPTIONAL,
                                  iE-Extensions
    . . .
RLItem-DM-Fail-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RL-Set-DM-Fail ::= SEOUENCE {
   rL-Set-unsuccessful-InformationRespList-DM-Fail RL-Set-Unsuccessful-InformationRespList-DM-Fail,
   rL-Set-successful-InformationRespList-DM-Fail RL-Set-Successful-InformationRespList-DM-Fail
                                                                                                             OPTIONAL,
                                  ProtocolExtensionContainer { { RL-SetItem-DM-Fail-ExtIEs} } OPTIONAL,
   iE-Extensions
RL-SetItem-DM-Fail-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RL-Unsuccessful-InformationRespList-DM-Fail
                                                 ::= SEOUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-Unsuccessful-
InformationResp-DM-Fail-IEs} }
RL-Unsuccessful-InformationResp-DM-Fail-IES RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-Unsuccessful-InformationItem-DM-Fail
                                                    CRITICALITY ignore TYPE RL-Unsuccessful-InformationItem-DM-Fail
                                                                                                                                  PRESENCE
mandatory }
RL-Unsuccessful-InformationItem-DM-Fail ::= SEOUENCE {
   rL-ID
                              RL-ID,
   individualcause
                              Cause OPTIONAL,
   iE-Extensions
                              ProtocolExtensionContainer { {RL-Unsuccessful-InformationItem-DM-Fail-ExtIEs} } OPTIONAL,
RL-Unsuccessful-InformationItem-DM-Fail-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
RL-Successful-InformationRespList-DM-Fail
                                                   ::= SEOUENCE (SIZE (1..maxNrOfRLs-1)) OF ProtocolIE-Single-Container { {RL-Successful-
InformationResp-DM-Fail-IEs} }
RL-Successful-InformationResp-DM-Fail-IES RNSAP-PROTOCOL-IES ::= {
     ID id-RL-Successful-InformationItem-DM-Fail
                                                       CRITICALITY ignore TYPE RL-Successful-InformationItem-DM-Fail
                                                                                                                               PRESENCE mandatory
RL-Successful-InformationItem-DM-Fail ::= SEQUENCE {
    rL-ID
                               RL-ID,
    dPCH-ID
                               DPCH-ID
                                                    OPTIONAL,
    dedicatedMeasurementValue DedicatedMeasurementValue,
                                                    OPTIONAL.
                               ProtocolExtensionContainer { {RL-Successful-InformationItem-DM-Fail-ExtIEs} } OPTIONAL,
    iE-Extensions
RL-Successful-InformationItem-DM-Fail-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    {ID id-HSSICH-Info-DM
                                           CRITICALITY reject
                                                                                                                PRESENCE optional |
                                                                           EXTENSION HS-SICH-ID
    -- TDD only
    { ID id-HS-SICH-ID-Extension
                                           CRITICALITY ignore
                                                                           EXTENSION HS-SICH-ID-Extension
                                                                                                                               PRESENCE optional }.
    -- Applicable for 1.28Mcps TDD only when the HS-SICH ID IE is more than 31
                                                           ::= SEQUENCE (SIZE (1..maxNrOfRLSets)) OF ProtocolIE-Single-Container { {RL-Set-
RL-Set-Unsuccessful-InformationRespList-DM-Fail
Unsuccessful-InformationResp-DM-Fail-IEs} }
RL-Set-Unsuccessful-InformationResp-DM-Fail-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-Set-Unsuccessful-InformationItem-DM-Fail
                                                         CRITICALITY ignore TYPE RL-Set-Unsuccessful-InformationItem-DM-Fail
    PRESENCE mandatory }
RL-Set-Unsuccessful-InformationItem-DM-Fail ::= SEQUENCE {
    rL-Set-ID
                                   RL-Set-ID,
    individualcause
                                               OPTIONAL,
                                   Cause
    iE-Extensions
                                   ProtocolExtensionContainer { {RL-Set-Unsuccessful-InformationItem-DM-Failns-ExtIEs} } OPTIONAL,
RL-Set-Unsuccessful-InformationItem-DM-Failns-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
RL-Set-Successful-InformationRespList-DM-Fail
                                                           ::= SEQUENCE (SIZE (1..maxNrOfRLSets-1)) OF ProtocolIE-Single-Container { {RL-Set-
Successful-InformationResp-DM-Fail-IEs} }
RL-Set-Successful-InformationResp-DM-Fail-IES RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-Set-Successful-InformationItem-DM-Fail CRITICALITY ignore TYPE RL-Set-Successful-InformationItem-DM-Fail
                                                                                                                                       PRESENCE
mandatory }
```

```
RL-Set-Successful-InformationItem-DM-Fail ::= SEQUENCE {
   rL-Set-ID
                             RL-Set-ID.
   dedicatedMeasurementValue
                             DedicatedMeasurementValue,
                                             OPTIONAL.
                             ProtocolExtensionContainer { {RL-Set-Successful-InformationItem-DM-Failns-ExtIEs} } OPTIONAL,
   iE-Extensions
RL-Set-Successful-InformationItem-DM-Failns-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  -- DEDICATED MEASUREMENT REPORT
  ******************
DedicatedMeasurementReport ::= SEQUENCE {
   protocolIEs
                             ProtocolIE-Container
                                                   {{DedicatedMeasurementReport-IEs}},
                             ProtocolExtensionContainer {{DedicatedMeasurementReport-Extensions}}
   protocolExtensions
                                                                                                    OPTIONAL,
DedicatedMeasurementReport-IES RNSAP-PROTOCOL-IES ::= {
    ID id-MeasurementID
                                CRITICALITY ignore TYPE MeasurementID
                                                                          PRESENCE mandatory } |
   PRESENCE mandatory
   . . .
DedicatedMeasurementObjectType-DM-Rprt ::= CHOICE {
   rLs
                      RL-DM-Rprt,
   rLS
                      RL-Set-DM-Rprt,
                      RL-DM-Rprt,
   allRL
   allRLS
                      RL-Set-DM-Rprt,
RL-DM-Rprt ::= SEQUENCE {
   rL-InformationList-DM-Rprt
                             RL-InformationList-DM-Rprt,
   iE-Extensions
                             ProtocolExtensionContainer { RLItem-DM-Rprt-ExtIEs} } OPTIONAL,
   . . .
RLItem-DM-Rprt-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RL-Set-DM-Rprt ::= SEQUENCE {
   rL-Set-InformationList-DM-Rprt RL-Set-InformationList-DM-Rprt,
   iE-Extensions
```

```
RL-SetItem-DM-Rprt-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
                                           ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-Information-DM-Rprt-IEs} }
RL-InformationList-DM-Rprt
RL-Information-DM-Rprt-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-InformationItem-DM-Rprt
                                           CRITICALITY ignore TYPE RL-InformationItem-DM-Rprt
                                                                                                       PRESENCE mandatory
RL-InformationItem-DM-Rprt ::= SEQUENCE {
                               RL-ID,
    dPCH-ID
                               DPCH-ID
                                                   OPTIONAL,
    dedicatedMeasurementValueInformation
                                           DedicatedMeasurementValueInformation,
    iE-Extensions
                                   ProtocolExtensionContainer { {RL-InformationItem-DM-Rprt-ExtIEs} } OPTIONAL,
    . . .
RL-InformationItem-DM-Rprt-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    {ID id-HSSICH-Info-DM-Rprt
                                   CRITICALITY ignore
                                                                  EXTENSION HS-SICH-ID
                                                                                              PRESENCE optional } |
    -- TDD only
    { ID id-DPCH-ID768-DM-Rprt
                                       CRITICALITY ignore
                                                                      EXTENSION DPCH-ID768
                                                                                                                  PRESENCE optional } |
    { ID id-HS-SICH-ID-Extension
                                       CRITICALITY ignore
                                                                      EXTENSION HS-SICH-ID-Extension
                                                                                                                                     PRESENCE
optional},
    -- Applicable for 1.28Mcps TDD only when the HS-SICH ID IE is more than 31
                                              ::= SEQUENCE (SIZE (1..maxNrOfRLSets)) OF ProtocolIE-Single-Container { {RL-Set-Information-DM-
RL-Set-InformationList-DM-Rprt
Rprt-IEs} }
RL-Set-Information-DM-Rprt-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-Set-InformationItem-DM-Rprt
                                               CRITICALITY ignore TYPE RL-Set-InformationItem-DM-Rprt
                                                                                                                      PRESENCE mandatory
RL-Set-InformationItem-DM-Rprt ::= SEQUENCE {
                                   RL-Set-ID,
    dedicatedMeasurementValueInformation DedicatedMeasurementValueInformation,
    iE-Extensions
                                   ProtocolExtensionContainer { {RL-Set-InformationItem-DM-Rprt-ExtIEs} } OPTIONAL,
RL-Set-InformationItem-DM-Rprt-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
DedicatedMeasurementReport-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
         id-MeasurementRecoveryReportingIndicator
                                                          CRITICALITY ignore
                                                                                  EXTENSION MeasurementRecoveryReportingIndicator
    PRESENCE optional },
__ **********************
```

```
-- DEDICATED MEASUREMENT TERMINATION REQUEST
  ******************
DedicatedMeasurementTerminationRequest ::= SEOUENCE {
   protocolIEs
                              ProtocolIE-Container
                                                     {{DedicatedMeasurementTerminationRequest-IEs}},
                              ProtocolExtensionContainer {{DedicatedMeasurementTerminationRequest-Extensions}}
   protocolExtensions
                                                                                                                  OPTIONAL.
DedicatedMeasurementTerminationRequest-IES RNSAP-PROTOCOL-IES ::= {
   { ID id-MeasurementID
                                 CRITICALITY ignore TYPE MeasurementID
                                                                             PRESENCE mandatory },
   . . .
DedicatedMeasurementTerminationRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
  -- DEDICATED MEASUREMENT FAILURE INDICATION
  *****************
DedicatedMeasurementFailureIndication ::= SEQUENCE {
   protocolIEs
                              ProtocolIE-Container
                                                     {{DedicatedMeasurementFailureIndication-IEs}},
                              ProtocolExtensionContainer {{DedicatedMeasurementFailureIndication-Extensions}}
   protocolExtensions
                                                                                                                 OPTIONAL,
DedicatedMeasurementFailureIndication-IEs RNSAP-PROTOCOL-IES ::= {
    ID id-MeasurementID
                                 CRITICALITY ignore TYPE MeasurementID
                                                                             PRESENCE mandatory } |
   { ID id-Cause
                              CRITICALITY ignore TYPE Cause
                                                                       PRESENCE mandatory },
   . . .
DedicatedMeasurementFailureIndication-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
   PRESENCE
optional },
   . . .
DedicatedMeasurementObjectType-DM-Fail-Ind ::= CHOICE {
   rL
                       RL-DM-Fail-Ind,
   rLS
                       RL-Set-DM-Fail-Ind,
   allRL
                       RL-DM-Fail-Ind,
   allRLS
                       RL-Set-DM-Fail-Ind,
RL-DM-Fail-Ind ::= SEQUENCE {
   rL-unsuccessful-InformationRespList-DM-Fail-Ind
                                               RL-Unsuccessful-InformationRespList-DM-Fail-Ind,
```

```
ProtocolExtensionContainer { { RLItem-DM-Fail-Ind-ExtIEs} } OPTIONAL,
    iE-Extensions
RLItem-DM-Fail-Ind-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
RL-Set-DM-Fail-Ind ::= SEQUENCE {
   rL-Set-unsuccessful-InformationRespList-DM-Fail-Ind
                                                            RL-Set-Unsuccessful-InformationRespList-DM-Fail-Ind,
                                                            ProtocolExtensionContainer { { RL-SetItem-DM-Fail-Ind-ExtIEs} } OPTIONAL,
   iE-Extensions
    . . .
RL-SetItem-DM-Fail-Ind-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
RL-Unsuccessful-InformationRespList-DM-Fail-Ind
                                                       ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { {RL-Unsuccessful-
InformationResp-DM-Fail-Ind-IEs} }
RL-Unsuccessful-InformationResp-DM-Fail-Ind-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-Unsuccessful-InformationItem-DM-Fail-Ind
                                                            CRITICALITY ignore TYPE RL-Unsuccessful-InformationItem-DM-Fail-Ind
    PRESENCE mandatory }
RL-Unsuccessful-InformationItem-DM-Fail-Ind ::= SEQUENCE {
    rL-ID
                                RL-ID.
    individualcause
                                            OPTIONAL,
                                ProtocolExtensionContainer { {RL-Unsuccessful-InformationItem-DM-Fail-Ind-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
RL-Unsuccessful-InformationItem-DM-Fail-Ind-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
                                                                ::= SEQUENCE (SIZE (1..maxNrOfRLSets)) OF ProtocolIE-Single-Container { {RL-Set-
RL-Set-Unsuccessful-InformationRespList-DM-Fail-Ind
Unsuccessful-InformationResp-DM-Fail-Ind-IEs} }
RL-Set-Unsuccessful-InformationResp-DM-Fail-Ind-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-Set-Unsuccessful-InformationItem-DM-Fail-Ind
                                                             CRITICALITY ignore TYPE RL-Set-Unsuccessful-InformationItem-DM-Fail-Ind
    PRESENCE mandatory }
RL-Set-Unsuccessful-InformationItem-DM-Fail-Ind ::= SEQUENCE {
   rL-Set-ID
                                    RL-Set-ID,
    individualcause
                                                OPTIONAL,
                                    Cause
   iE-Extensions
                                    ProtocolExtensionContainer { {RL-Set-Unsuccessful-InformationItem-DM-Fail-Indns-ExtIEs} } OPTIONAL,
RL-Set-Unsuccessful-InformationItem-DM-Fail-Indns-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
```

```
COMMON TRANSPORT CHANNEL RESOURCES RELEASE REQUEST
CommonTransportChannelResourcesReleaseRequest ::= SEQUENCE {
                                 ProtocolIE-Container
                                                           {{CommonTransportChannelResourcesReleaseRequest-IEs}},
   protocolIEs
   protocolExtensions
                                 ProtocolExtensionContainer {{CommonTransportChannelResourcesReleaseRequest-Extensions}}
OPTIONAL,
   . . .
CommonTransportChannelResourcesReleaseRequest-IEs RNSAP-PROTOCOL-IES ::= {
                                CRITICALITY ignore TYPE D-RNTI
   { ID id-D-RNTI
                                                                               PRESENCE mandatory
CommonTransportChannelResourcesReleaseRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
         COMMON TRANSPORT CHANNEL RESOURCES REQUEST
  CommonTransportChannelResourcesRequest ::= SEQUENCE
   protocolIEs
                                                           {{CommonTransportChannelResourcesRequest-IEs}},
                                 ProtocolIE-Container
   protocolExtensions
                                 ProtocolExtensionContainer {{CommonTransportChannelResourcesRequest-Extensions}}
                                                                                                                               OPTIONAL,
CommonTransportChannelResourcesRequest-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-D-RNTI
                                             CRITICALITY reject TYPE D-RNTI
                                                                                                             PRESENCE mandatory }
     ID id-C-ID
                                                                                                             PRESENCE optional }
                                             CRITICALITY reject TYPE C-ID
     ID id-TransportBearerRequestIndicator
                                             CRITICALITY reject TYPE TransportBearerRequestIndicator
                                                                                                             PRESENCE mandatory } |
    ID id-TransportBearerID
                                                                                                             PRESENCE mandatory },
                                             CRITICALITY reject TYPE TransportBearerID
CommonTransportChannelResourcesRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-Permanent-NAS-UE-Identity
                                             CRITICALITY ignore EXTENSION Permanent-NAS-UE-Identity
                                                                                                            PRESENCE optional }
   { ID id-BindingID
                                             CRITICALITY ignore EXTENSION BindingID
                                                                                                            PRESENCE optional } |
   -- Shall be ignored if bearer establishment with ALCAP.
    { ID id-TransportLayerAddress
                                             CRITICALITY ignore EXTENSION TransportLayerAddress
                                                                                                             PRESENCE optional } |
   -- Shall be ignored if bearer establishment with ALCAP.
    { ID id-MBMS-Bearer-Service-List
                                             CRITICALITY notify EXTENSION MBMS-Bearer-Service-List
                                                                                                             PRESENCE optional }
     ID id-TnlOos
                                             CRITICALITY ignore EXTENSION TnlOos
                                                                                                             PRESENCE optional }
    { ID id-Enhanced-FACH-Support-Indicator
                                             CRITICALITY ignore EXTENSION Enhanced-FACH-Support-Indicator
                                                                                                             PRESENCE optional }
    -- FDD and 1.28Mcps TDD only
```

```
PRESENCE optional }
    { ID id-Common-EDCH-Support-Indicator
                                             CRITICALITY ignore EXTENSION Common-EDCH-Support-Indicator
    -- FDD only
     ID id-HSDSCH-Physical-Laver-Category
                                             CRITICALITY ignore EXTENSION HSDSCH-Physical-Layer-Category
                                                                                                              PRESENCE optional }|
    { ID id-UE-with-enhanced-HS-SCCH-support-indicator CRITICALITY ignore EXTENSION NULL
                                                                                                              PRESENCE optional },
    COMMON TRANSPORT CHANNEL RESOURCES RESPONSE FDD
  ****************
CommonTransportChannelResourcesResponseFDD ::= SEOUENCE {
   protocolIEs
                                  ProtocolIE-Container
                                                            {{CommonTransportChannelResourcesResponseFDD-IEs}},
   protocolExtensions
                                  ProtocolExtensionContainer {{CommonTransportChannelResourcesResponseFDD-Extensions}}
   OPTIONAL,
CommonTransportChannelResourcesResponseFDD-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-S-RNTI
                                 CRITICALITY ignore TYPE S-RNTI
                                                                                PRESENCE mandatory
     ID id-C-RNTI
                                                                               PRESENCE optional
                                  CRITICALITY ignore TYPE C-RNTI
     ID id-FACH-InfoForUESelectedS-CCPCH-CTCH-ResourceRspFDD CRITICALITY ignore TYPE FACH-InfoForUESelectedS-CCPCH-CTCH-ResourceRspFDD
    PRESENCE mandatory } |
     ID id-TransportLayerAddress
                                         CRITICALITY ignore TYPE TransportLayerAddress
                                                                                             PRESENCE optional
     ID id-BindingID
                                  CRITICALITY ignore TYPE BindingID
                                                                                   PRESENCE optional
    { ID id-CriticalityDiagnostics
                                         CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                             PRESENCE optional
    . . .
FACH-InfoForUESelectedS-CCPCH-CTCH-ResourceRspFDD ::= SEQUENCE
    fACH-FlowControlInformation
                                  FACH-FlowControlInformation-CTCH-ResourceRspFDD,
-- If the Enhanced FACH Information Response IE is included in the message, the FACH Flow Control Information IE shall be ignored.
                                  ProtocolExtensionContainer { {FACH-InfoForUESelectedS-CCPCH-CTCH-ResourceRspFDD-ExtIEs} } OPTIONAL.
   iE-Extensions
FACH-InfoForUESelectedS-CCPCH-CTCH-ResourceRspFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
FACH-FlowControlInformation-CTCH-ResourceRspFDD ::= ProtocolIE-Single-Container {{ FACH-FlowControlInformationIEs-CTCH-ResourceRspFDD }}
FACH-FlowControlInformationIEs-CTCH-ResourceRspFDD RNSAP-PROTOCOL-IES ::= {
    { ID id-FACH-FlowControlInformation CRITICALITY ignore TYPE FACH-FlowControlInformation PRESENCE mandatory
CommonTransportChannelResourcesResponseFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-C-ID
                                                            CRITICALITY ignore
                                                                                    EXTENSION C-ID
                                  PRESENCE mandatory }
    { ID id-Active-MBMS-Bearer-ServiceFDD
                                                            CRITICALITY ignore
                                                                                    EXTENSION Active-MBMS-Bearer-Service-ListFDD
           PRESENCE optional |
```

830

```
{ ID id-Enhanced-FACH-Information-ResponseFDD
                                                              CRITICALITY ignore
                                                                                      EXTENSION Enhanced-FACH-Information-ResponseFDD
           PRESENCE optional } |
     ID id-Common-EDCH-MAC-d-Flow-Specific-InformationFDD
                                                               CRITICALITY ignore
                                                                                      EXTENSION Common-EDCH-MAC-d-Flow-Specific-InformationFDD
       PRESENCE optional } |
    { ID id-E-RNTI CRITICALITY ignore EXTENSION E-RNTI
                                                           PRESENCE optional },
  COMMON TRANSPORT CHANNEL RESOURCES RESPONSE TDD
      *****************
CommonTransportChannelResourcesResponseTDD ::= SEQUENCE {
    protocolIEs
                                   ProtocolIE-Container
                                                              {{CommonTransportChannelResourcesResponseTDD-IEs}},
    protocolExtensions
                                   ProtocolExtensionContainer {{CommonTransportChannelResourcesResponseTDD-Extensions}}
    OPTIONAL,
    . . .
CommonTransportChannelResourcesResponseTDD-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-S-RNTI
                                   CRITICALITY ignore TYPE S-RNTI
                                                                                  PRESENCE mandatory
                                   CRITICALITY ignore TYPE C-RNTI
     ID id-C-RNTI
                                                                                  PRESENCE optional
     ID id-FACH-InfoForUESelectedS-CCPCH-CTCH-ResourceRspTDD CRITICALITY ignore TYPE FACH-InfoForUESelectedS-CCPCH-CTCH-ResourceRspTDD
    PRESENCE mandatory } |
     ID id-TransportLayerAddress
                                           CRITICALITY ignore TYPE TransportLayerAddress
                                                                                                PRESENCE optional
     ID id-BindingID
                                   CRITICALITY ignore TYPE BindingID
                                                                                      PRESENCE optional
    { ID id-CriticalityDiagnostics
                                           CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                                PRESENCE optional
FACH-InfoForUESelectedS-CCPCH-CTCH-ResourceRspTDD ::= SEQUENCE
    fACH-FlowControlInformation
                                   FACH-FlowControlInformation-CTCH-ResourceRspTDD,
                                   ProtocolExtensionContainer { {FACH-InfoForUESelectedS-CCPCH-CTCH-ResourceRspTDD-ExtIEs} } OPTIONAL.
    iE-Extensions
FACH-InfoForUESelectedS-CCPCH-CTCH-ResourceRspTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
FACH-FlowControlInformation-CTCH-ResourceRspTDD ::= ProtocolIE-Single-Container {{ FACH-FlowControlInformationIEs-CTCH-ResourceRspTDD }}
FACH-FlowControlInformationIEs-CTCH-ResourceRspTDD RNSAP-PROTOCOL-IES ::= {
    { ID id-FACH-FlowControlInformation CRITICALITY ignore TYPE
                                                                 FACH-FlowControlInformation PRESENCE mandatory
CommonTransportChannelResourcesResponseTDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-C-ID
                                                              CRITICALITY ignore
                                                                                                       C-ID
                                                                                      EXTENSION
                                   PRESENCE mandatory } |
    { ID id-Active-MBMS-Bearer-ServiceTDD
                                                               CRITICALITY ignore
                                                                                      EXTENSION Active-MBMS-Bearer-Service-ListTDD
           PRESENCE optional |
```

```
{ ID id-Enhanced-FACH-Information-ResponseLCR
                                                       CRITICALITY ignore
                                                                             EXTENSION Enhanced-FACH-Information-ResponseLCR
          PRESENCE optional } |
   { ID id-Common-EDCH-MAC-d-Flow-Specific-InformationLCR
                                                       CRITICALITY ignore
                                                                             EXTENSION Common-EDCH-MAC-d-Flow-Specific-InformationLCR
      PRESENCE optional },
   COMMON TRANSPORT CHANNEL RESOURCES FAILURE
  *****************
CommonTransportChannelResourcesFailure ::= SEQUENCE {
                                                       {{CommonTransportChannelResourcesFailure-IEs}},
   protocolIEs
                               ProtocolIE-Container
   protocolExtensions
                               ProtocolExtensionContainer {{CommonTransportChannelResourcesFailure-Extensions}}
                                                                                                                      OPTIONAL,
CommonTransportChannelResourcesFailure-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-S-RNTI
                                      CRITICALITY ignore TYPE S-RNTI
                                                                                     PRESENCE mandatory }
     ID id-Cause
                                      CRITICALITY ignore TYPE Cause
                                                                                     PRESENCE mandatory }
   ID id-CriticalityDiagnostics
                                                                                     PRESENCE optional },
                                      CRITICALITY ignore TYPE CriticalityDiagnostics
   . . .
CommonTransportChannelResourcesFailure-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
-- COMPRESSED MODE COMMAND
  ····
CompressedModeCommand ::= SEQUENCE {
                                                       {{CompressedModeCommand-IEs}},
   protocolIEs
                               ProtocolIE-Container
                               ProtocolExtensionContainer {{CompressedModeCommand-Extensions}}
   protocolExtensions
                                                                                                       OPTIONAL,
   . . .
CompressedModeCommand-IEs RNSAP-PROTOCOL-IES ::= {
   { ID id-Active-Pattern-Sequence-Information
                                             CRITICALITY ignore TYPE Active-Pattern-Sequence-Information
                                                                                                          PRESENCE mandatory },
   . . .
CompressedModeCommand-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
  -- ERROR INDICATION
```

```
ErrorIndication ::= SEQUENCE {
   protocolIEs
                                 ProtocolIE-Container
                                                         {{ErrorIndication-IEs}},
                                ProtocolExtensionContainer {{ErrorIndication-Extensions}}
   protocolExtensions
                                                                                                      OPTIONAL,
ErrorIndication-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-Cause CRITICALITY ignore TYPE Cause
                                                                            PRESENCE optional |
   { ID id-CriticalityDiagnostics
                                       CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                         PRESENCE optional
ErrorIndication-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-S-RNTI
                                CRITICALITY ignore EXTENSION S-RNTI
                                                                                    PRESENCE optional
    ID id-D-RNTI
                                CRITICALITY ignore EXTENSION D-RNTI
                                                                                    PRESENCE optional
   . . .
  *****************
  COMMON MEASUREMENT INITIATION REQUEST
        ****************
CommonMeasurementInitiationRequest ::= SEQUENCE {
                                               {{CommonMeasurementInitiationRequest-IEs}},
   protocolIEs
                         ProtocolIE-Container
   protocolExtensions
                         ProtocolExtensionContainer {{CommonMeasurementInitiationRequest-Extensions}}
                                                                                                             OPTIONAL,
   . . .
CommonMeasurementInitiationRequest-IEs RNSAP-PROTOCOL-IES ::= {
   { ID id-MeasurementID
                                        CRITICALITY reject TYPE
                                                                 MeasurementID
   PRESENCE mandatory }
   { ID id-CommonMeasurementObjectType-CM-Rqst CRITICALITY reject TYPE
                                                                     CommonMeasurementObjectType-CM-Rqst
                                                                                                             PRESENCE mandatory } |
    { ID id-CommonMeasurementType
                                        CRITICALITY reject TYPE
                                                                  CommonMeasurementType
   PRESENCE mandatory } |
   { ID id-MeasurementFilterCoefficient
                                        CRITICALITY reject TYPE
                                                                  MeasurementFilterCoefficient
   PRESENCE optional }
   -- UTRAN only
   { ID id-ReportCharacteristics
                                                                  ReportCharacteristics
                                        CRITICALITY reject TYPE
   PRESENCE mandatory } |
   { ID id-SFNReportingIndicator
                                        CRITICALITY reject TYPE
                                                                  FNReportingIndicator
   PRESENCE mandatory } |
   { ID id-SFN
                                        CRITICALITY reject TYPE
                                                                  SFN
   PRESENCE optional } |
   -- UTRAN only
   { ID id-CommonMeasurementAccuracy
                                        CRITICALITY reject TYPE
                                                                  CommonMeasurementAccuracy
   PRESENCE optional },
   -- UTRAN only
```

```
CommonMeasurementInitiationRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    ID id-MeasurementRecoveryBehavior
                                              CRITICALITY ignore EXTENSION MeasurementRecoveryBehavior
                                                                                                           PRESENCE optional
   -- UTRAN only
   { ID id-GANSS-Time-ID
                                              CRITICALITY ignore EXTENSION GANSS-Time-ID
                                                                                                          PRESENCE optional |
     PRESENCE optional },
CommonMeasurementObjectType-CM-Rgst ::= CHOICE {
   cell
                                Cell-CM-Rast,
   . . . .
   additional-CommonMeasurementObjectType-CM-Rgst Additional-CommonMeasurementObjectType-CM-Rgst
Cell-CM-Rast ::= SEQUENCE {
                                UC-ID,
   -- May be a GERAN cell identifier
   timeSlot
                                TimeSlot
                                              OPTIONAL,
                                                        --3.84Mcps TDD and 7.68Mcps TDD only
   timeSlotLCR
                               TimeSlotLCR
                                                       --1.28Mcps TDD only
                                              OPTIONAL,
                                              NeighbouringCellMeasurementInfo
   neighbouringCellMeasurementInformation
                                                                              OPTIONAL,
   -- UTRAN only
   iE-Extensions
                                ProtocolExtensionContainer { CellItem-CM-Rqst-ExtIEs} }
                                                                                      OPTIONAL,
NeighbouringCellMeasurementInfo ::= SEOUENCE (SIZE (1..maxNrOfMeasNCell)) OF
       CHOICE {
              neighbouring FDD Cell Measurement Information
                                                        NeighbouringFDDCellMeasurementInformation,
              neighbouringTDDCellMeasurementInformation
                                                        NeighbouringTDDCellMeasurementInformation,
              extension-neighbouringCellMeasurementInformation
                                                            Extension-neighbouringCellMeasurementInformation,
              extension-neighbouringCellMeasurementInformation768 Extension-neighbouringCellMeasurementInformation768
Extension-neighbouringCellMeasurementInformation
                                            ::= ProtocolIE-Single-Container {{ Extension-neighbouringCellMeasurementInformationIE }}
Extension-neighbouringCellMeasurementInformationIE RNSAP-PROTOCOL-IES ::= {
   { ID id-neighbouringTDDCellMeasurementInformationLCR
                                                   CRITICALITY reject TYPE NeighbouringTDDCellMeasurementInformationLCR
                                                                                                                        PRESENCE
mandatory },
Extension-neighbouringCellMeasurementInformation768 ::= ProtocolIE-Single-Container {{ Extension-neighbouringCellMeasurementInformation768IE }}
Extension-neighbouringCellMeasurementInformation768IE RNSAP-PROTOCOL-IES ::= {
   PRESENCE
mandatory },
   . . .
```

```
CellItem-CM-Rgst-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   { ID id-UARFCNforNt
                                   CRITICALITY ignore EXTENSION UARFON
                                                                                PRESENCE optional } |
   -- Applicable to 1.28Mcps TDD only
   { ID id-UPPCHPositionLCR
                                   CRITICALITY reject EXTENSION UPPCHPositionLCR
                                                                                PRESENCE optional },
   -- Applicable to 1.28Mcps TDD only
Additional-CommonMeasurementObjectType-CM-Rgst ::= ProtocolIE-Single-Container {{ Additional-CommonMeasurementObjectType-CM-RgstIE }}
Additional-CommonMeasurementObjectType-CM-RqstIE RNSAP-PROTOCOL-IES ::= {
   . . .
GSM-Cell-CM-Rgst ::= SEQUENCE {
                    iE-Extensions
                                                                             OPTIONAL,
GSMCell-CM-Rgst-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Extension-CommonMeasurementObjectType-CM-Rqst ::= ProtocolIE-Single-Container {{ Extension-CommonMeasurementObjectType-CM-RqstIE }}
Extension-CommonMeasurementObjectType-CM-RgstIE RNSAP-PROTOCOL-IES ::= {
   { ID id-GsmCellList-CM-Rqst
                              CRITICALITY ignore TYPE GsmCellList-CM-Rgst
                                                                         PRESENCE mandatory },
   . . .
GsmCellList-CM-Rqst ::= SEQUENCE (SIZE (1..maxNoOfGsmCell)) OF GsmCellItem-CM-Rqst
GsmCellItem-CM-Rqst ::= SEQUENCE {
   measurementID
                   MeasurementID,
   qsmCell
                        GSM-Cell-CM-Rast,
   iE-Extensions
                       ProtocolExtensionContainer { { GsmCellItem-CM-Rqst-ExtIEs} }
                                                                                    OPTIONAL.
GsmCellItem-CM-Rqst-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  COMMON MEASUREMENT INITIATION RESPONSE
  CommonMeasurementInitiationResponse ::= SEQUENCE {
   protocolIEs
                        ProtocolIE-Container
                                             {{CommonMeasurementInitiationResponse-IEs}},
                        ProtocolExtensionContainer {{CommonMeasurementInitiationResponse-Extensions}}
   protocolExtensions
                                                                                                         OPTIONAL,
   . . .
```

```
CommonMeasurementInitiationResponse-IEs RNSAP-PROTOCOL-IES ::= {
    ID id-MeasurementID
                                      CRITICALITY ignore TYPE MeasurementID
                                                                                                PRESENCE mandatory } |
    PRESENCE optional } |
                                                                                                PRESENCE optional }
   { ID id-SFN
                                      CRITICALITY ignore TYPE SFN
   -- UTRAN only
   { ID id-CriticalityDiagnostics
                                      CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                                PRESENCE optional } |
   { ID id-CommonMeasurementAccuracy
                                      CRITICALITY reject TYPE CommonMeasurementAccuracy
                                                                                                PRESENCE optional },
   -- UTRAN only
CommonMeasurementInitiationResponse-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
   -- UTRAN only
   optional},
   . . .
CommonMeasurementObjectType-CM-Rsp ::= CHOICE {
   cell
                         Cell-CM-Rsp,
   . . .
Cell-CM-Rsp ::= SEQUENCE {
   commonMeasurementValue
                                      CommonMeasurementValue,
                                      ProtocolExtensionContainer { { CellItem-CM-Rsp-ExtIEs} }
   iE-Extensions
                                                                                                OPTIONAL,
CellItem-CM-Rsp-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Extension-CommonMeasurementObjectType-CM-Rsp ::= ProtocolIE-Single-Container {{ Extension-CommonMeasurementObjectType-CM-RspIE }}
Extension-CommonMeasurementObjectType-CM-RspIE RNSAP-PROTOCOL-IES ::= {
   { ID id-GsmCellList-CM-Rsp CRITICALITY ignore TYPE GsmCellList-CM-Rsp PRESENCE mandatory },
   . . .
GsmCellList-CM-Rsp ::= SEQUENCE (SIZE (1..maxNoOfGsmCell)) OF GsmCellItem-CM-Rsp
GsmCellItem-CM-Rsp ::= SEOUENCE {
   measurementID
                                MeasurementID,
   commonMeasurementValue
                                CommonMeasurementValue
                                                          OPTIONAL,
   iE-Extensions
                                ProtocolExtensionContainer { GsmCellItem-CM-Rsp-ExtIEs} }
                                                                                          OPTIONAL,
GsmCellItem-CM-Rsp-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
*****************
  COMMON MEASUREMENT INITIATION FAILURE
  ******************
CommonMeasurementInitiationFailure ::= SEQUENCE {
                                           {{CommonMeasurementInitiationFailure-IEs}},
   protocolIEs
                       ProtocolIE-Container
                       ProtocolExtensionContainer {{CommonMeasurementInitiationFailure-Extensions}}
   protocolExtensions
                                                                                                     OPTIONAL,
   . . .
CommonMeasurementInitiationFailure-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-MeasurementID
                                 CRITICALITY ignore TYPE MeasurementID
                                                                             PRESENCE mandatory }
     ID id-Cause
                                 CRITICALITY ignore TYPE Cause
                                                                             PRESENCE mandatory }
                                                                             PRESENCE optional },
    ID id-CriticalityDiagnostics
                                 CRITICALITY ignore TYPE CriticalityDiagnostics
CommonMeasurementInitiationFailure-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
   PRESENCE optional },
   . . .
Extension-FailureMeasurementList ::= SEQUENCE (SIZE (1..maxNoOfGsmCell)) OF Extension-FailureMeasurementItem
Extension-FailureMeasurementItem ::= SEQUENCE {
   measurementID
                                 MeasurementID,
   cause
                                 Cause,
   iE-Extensions
                                 ProtocolExtensionContainer { { Extension-FailureMeasurementItem-ExtIEs} }
                                                                                                     OPTIONAL,
Extension-FailureMeasurementItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ***************
-- COMMON MEASUREMENT REPORT
  ******************
CommonMeasurementReport ::= SEQUENCE {
   protocolIEs
                       ProtocolIE-Container {{CommonMeasurementReport-IEs}},
   protocolExtensions
ProtocolExtensionContainer {{CommonMeasurementReport-Extensions}}
CommonMeasurementReport-IEs RNSAP-PROTOCOL-IES ::= {
    ID id-MeasurementID
                                        CRITICALITY ignore TYPE MeasurementID
                                                                                               PRESENCE mandatory }
     ID id-CommonMeasurementObjectType-CM-Rprt CRITICALITY ignore TYPE CommonMeasurementObjectType-CM-Rprt
                                                                                               PRESENCE mandatory }
   { ID id-SFN
                                                                                               PRESENCE optional },
                                        CRITICALITY ignore TYPE SFN
```

```
-- UTRAN only
CommonMeasurementReport-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
   { ID id-MeasurementRecoveryReportingIndicator
                                          CRITICALITY ignore EXTENSION MeasurementRecoveryReportingIndicator PRESENCE optional }
   -- UTRAN only
   PRESENCE optional },
   . . .
CommonMeasurementObjectType-CM-Rprt ::= CHOICE {
   cell
                             Cell-CM-Rprt,
   . . .
Cell-CM-Rprt ::= SEQUENCE {
   commonMeasurementValueInformation CommonMeasurementValueInformation,
                             ProtocolExtensionContainer {{ CellItem-CM-Rprt-ExtIEs }}
   iE-Extensions
                                                                                OPTIONAL,
   . . .
CellItem-CM-Rprt-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Extension-CommonMeasurementObjectType-CM-Rprt ::= ProtocolIE-Single-Container {{ Extension-CommonMeasurementObjectType-CM-RprtIE }}
Extension-CommonMeasurementObjectType-CM-RprtIE RNSAP-PROTOCOL-IES ::= {
   PRESENCE mandatory },
GsmCellList-CM-Rprt ::= SEQUENCE (SIZE (1..maxNoOfGsmCell)) OF GsmCellItem-CM-Rprt
GsmCellItem-CM-Rprt ::= SEQUENCE {
   measurementID
                                       MeasurementID,
   commonMeasurementValueInformation
                                       CommonMeasurementValueInformation,
   iE-Extensions
                                       ProtocolExtensionContainer { { GsmCellItem-CM-Rprt-ExtIEs} }
                                                                                                   OPTIONAL,
GsmCellItem-CM-Rprt-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  ******************
-- COMMON MEASUREMENT TERMINATION REQUEST
__ ********************************
CommonMeasurementTerminationRequest ::= SEQUENCE {
```

```
{{CommonMeasurementTerminationRequest-IEs}},
   protocolIEs
                       ProtocolIE-Container
   protocolExtensions
                       ProtocolExtensionContainer {{CommonMeasurementTerminationRequest-Extensions}}
                                                                                                      OPTIONAL,
CommonMeasurementTerminationRequest-IEs RNSAP-PROTOCOL-IES ::= {
         id-MeasurementID
                                                                                                            mandatory },
   { ID
                                 CRITICALITY
                                               ignore
                                                                TYPE
                                                                       Measurement.ID
                                                                                               PRESENCE
   . . .
CommonMeasurementTerminationRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
   . . .
Extension-TerminationMeasurementList ::= SEOUENCE (SIZE (1..maxNoOfGsmCell)) OF Extension-TerminationMeasurementItem
Extension-TerminationMeasurementItem ::= SEQUENCE {
   measurementID
                                 MeasurementID,
   iE-Extensions
                                 ProtocolExtensionContainer { { Extension-TerminationMeasurementItem-ExtIEs} } OPTIONAL,
Extension-TerminationMeasurementItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
-- COMMON MEASUREMENT FAILURE INDICATION
  *****************
CommonMeasurementFailureIndication ::= SEQUENCE {
   protocolIEs
                       ProtocolIE-Container
                                            {{CommonMeasurementFailureIndication-IEs}},
   protocolExtensions
                          ProtocolExtensionContainer {{CommonMeasurementFailureIndication-Extensions}}
                                                                                                                  OPTIONAL.
CommonMeasurementFailureIndication-IEs RNSAP-PROTOCOL-IES ::= {
    ID
         id-MeasurementID
                                 CRITICALITY ignore
                                                         TYPE
                                                                                   PRESENCE
                                                                                               mandatory
                                                                MeasurementID
   { ID
         id-Cause
                                 CRITICALITY ignore
                                                         TYPE
                                                                Cause
                                                                                   PRESENCE
                                                                                               mandatory
   . . .
CommonMeasurementFailureIndication-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
   PRESENCE
optional },
Extension-FailureIndicationMeasurementList ::= SEOUENCE (SIZE (1..maxNoOfGsmCell)) OF Extension-FailureIndicationMeasurementItem
Extension-FailureIndicationMeasurementItem ::= SEQUENCE {
```

```
measurementID
                                  MeasurementID,
   cause
                                  Cause.
   iE-Extensions
                                  ProtocolExtensionContainer { { Extension-FailureIndicationMeasurementItem-ExtIEs} }
                                                                                                                                 OPTIONAL.
Extension-FailureIndicationMeasurementItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
       ****************
-- INFORMATION EXCHANGE INITIATION REQUEST
__ *********************
InformationExchangeInitiationRequest ::= SEQUENCE {
                                                 {{InformationExchangeInitiationRequest-IEs}},
   protocolIEs
                          ProtocolIE-Container
                          ProtocolExtensionContainer {{InformationExchangeInitiationRequest-Extensions}}
   protocolExtensions
                                                                                                                   OPTIONAL,
InformationExchangeInitiationRequest-IEs RNSAP-PROTOCOL-IES ::= {
         id-InformationExchangeID
                                                         CRITICALITY reject
                                                                                TYPE
                                                                                        InformationExchangeID
   PRESENCE
               mandatory }|
           id-InformationExchangeObjectType-InfEx-Rqst
                                                                                        InformationExchangeObjectType-InfEx-Rqst
                                                         CRITICALITY reject
                                                                                TYPE
    PRESENCE
               mandatory }|
    { ID
          id-InformationType
                                                         CRITICALITY reject
                                                                                TYPE
                                                                                        InformationType
       PRESENCE mandatory
          id-InformationReportCharacteristics
                                                         CRITICALITY reject
                                                                                TYPE
                                                                                        InformationReportCharacteristics
                                                                                                                                 PRESENCE
   mandatory },
    . . .
InformationExchangeInitiationRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
InformationExchangeObjectType-InfEx-Rgst ::= CHOICE {
   cell
                                                         Cell-InfEx-Rqst,
    . . . ,
   extension-InformationExchangeObjectType-InfEx-Rqst
                                                         Extension-InformationExchangeObjectType-InfEx-Rqst
Cell-InfEx-Rqst ::= SEQUENCE {
                                  C-ID, --May be a GERAN cell identifier
   C - TD
   iE-Extensions
                                  ProtocolExtensionContainer { { CellItem-InfEx-Rqst-ExtIEs} } }
                                                                                                    OPTIONAL,
Cellitem-InfEx-Rqst-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
```

```
Extension-InformationExchangeObjectType-InfEx-Rgst ::= ProtocolIE-Single-Container {{ Extension-InformationExchangeObjectType-InfEx-RgstIE }}
Extension-InformationExchangeObjectType-InfEx-RgstIE RNSAP-PROTOCOL-IES ::= {
     ID id-GSM-Cell-InfEx-Rgst
                                                         CRITICALITY reject TYPE GSM-Cell-InfEx-Rqst
                                                                                                                           PRESENCE mandatory |
     ID id-MBMS-Bearer-Service-List
                                                         CRITICALITY reject TYPE MBMS-Bearer-Service-List
                                                                                                                           PRESENCE mandatory}
                                                                                                                                  PRESENCE
     ID id-MBMS-Bearer-Service-in-MBMS-Cell-InfEx-Rgst
                                                         CRITICALITY reject TYPE MBMS-Bearer-Service-in-MBMS-Cell-InfEx-Rqst
mandatory} |
    { ID id-MBMS-Cell-InfEx-Rqst
                                                         CRITICALITY reject TYPE MBMS-Cell-InfEx-Rqst
                                                                                                                           PRESENCE mandatory } |
    ID id-ANR-Cell-InfEx-Rqst
                                                         CRITICALITY reject TYPE ANR-Cell-InfEx-Rqst
                                                                                                                           PRESENCE mandatory
GSM-Cell-InfEx-Rgst ::= SEQUENCE {
                                  ProtocolExtensionContainer { GSMCellItem-InfEx-Rqst-ExtIEs} }
   iE-Extensions
                                                                                                            OPTIONAL,
GSMCellItem-InfEx-Rqst-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MBMS-Bearer-Service-in-MBMS-Cell-InfEx-Rgst ::= SEOUENCE (SIZE (1..maxNrOfCells)) OF MBMS-Bearer-Service-in-MBMS-Cell-Item-InfEx-Rgst
MBMS-Bearer-Service-in-MBMS-Cell-Item-InfEx-Rgst ::= SEQUENCE
   mBMS-Bearer-Service-List-InfEx-Rgst
                                                             MBMS-Bearer-Service-List-InfEx-Rgst,
                                  ProtocolExtensionContainer { MBMS-Bearer-Service-in-MBMS-Cell-Item-InfEx-Rgst-ExtIEs} }
   iE-Extensions
                                                                                                                                  OPTIONAL,
MBMS-Bearer-Service-in-MBMS-Cell-Item-InfEx-Rgst-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MBMS-Bearer-Service-List-InfEx-Rgst ::= SEQUENCE (SIZE (1..maxNrOfMBMSServices)) OF TMGI
MBMS-Cell-InfEx-Rast
                     ::= SEOUENCE (SIZE (1..maxNrOfCells)) OF C-ID
ANR-Cell-InfEx-Rgst
                     ::= SEQUENCE (SIZE (1..maxNrOfANRCells)) OF C-ID
-- INFORMATION EXCHANGE INITIATION RESPONSE
  *****************
InformationExchangeInitiationResponse ::= SEQUENCE {
   protocolIEs
                          ProtocolIE-Container
                                                  {{InformationExchangeInitiationResponse-IEs}},
   protocolExtensions
                          ProtocolExtensionContainer {{InformationExchangeInitiationResponse-Extensions}}
                                                                                                                    OPTIONAL,
    . . .
```

```
InformationExchangeInitiationResponse-IES RNSAP-PROTOCOL-IES ::= {
          id-InformationExchangeID
                                                       CRITICALITY ignore TYPE
                                                                                   InformationExchangeID
    PRESENCE
               mandatory }|
    { ID id-InformationExchangeObjectType-InfEx-Rsp CRITICALITY ignore TYPE
                                                                                   InformationExchangeObjectType-InfEx-Rsp
                                                                                                                                      PRESENCE
    optional }|
           id-CriticalityDiagnostics
                                                       CRITICALITY ignore TYPE
                                                                                   CriticalityDiagnostics
    { ID
    PRESENCE optional },
InformationExchangeInitiationResponse-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
InformationExchangeObjectType-InfEx-Rsp ::= CHOICE {
                               Cell-InfEx-Rsp,
    . . . ,
    extension-InformationExchangeObjectType-InfEx-Rsp
                                                           Extension-InformationExchangeObjectType-InfEx-Rsp
Cell-InfEx-Rsp ::= SEQUENCE {
    requestedDataValue
                                   RequestedDataValue,
                                   ProtocolExtensionContainer { { CellItem-InfEx-Rsp-ExtIEs} }
    iE-Extensions
                                                                                                        OPTIONAL,
CellItem-InfEx-Rsp-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Extension-InformationExchangeObjectType-InfEx-Rsp ::= ProtocolIE-Single-Container {{ Extension-InformationExchangeObjectType-InfEx-RspIE }}
Extension-InformationExchangeObjectType-InfEx-RspIE RNSAP-PROTOCOL-IES ::= {
     ID id-MBMS-Bearer-Service-List-InfEx-Rsp
                                                           CRITICALITY ignore TYPE MBMS-Bearer-Service-List-InfEx-Rsp
                                                                                                                              PRESENCE mandatory } |
     ID id-MBMS-Bearer-Service-in-MBMS-Cell-InfEx-Rsp
                                                           CRITICALITY ignore TYPE MBMS-Bearer-Service-in-MBMS-Cell-InfEx-Rsp PRESENCE mandatory
     ID id-MBMS-Cell-InfEx-Rsp
                                                           CRITICALITY ignore TYPE MBMS-Cell-InfEx-Rsp
                                                                                                                              PRESENCE mandatory}
     ID id-ANR-Cell-InfEx-Rsp
                                                           CRITICALITY ignore TYPE ANR-Cell-InfEx-Rsp
                                                                                                                              PRESENCE mandatory
MBMS-Bearer-Service-List-InfEx-Rsp ::= SEQUENCE (SIZE (1..maxNrOfMBMSServices)) OF MBMS-Bearer-ServiceItemIEs-InfEx-Rsp
MBMS-Bearer-ServiceItemIEs-InfEx-Rsp
                                       ::=SEQUENCE{
    tmai
           TMGI,
    requestedDataValue
                           RequestedDataValue,
                                   ProtocolExtensionContainer { { MBMS-Bearer-ServiceItem-InfEx-Rsp-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
```

```
MBMS-Bearer-ServiceItem-InfEx-Rsp-ExtIEs
                                       RNSAP-PROTOCOL-EXTENSION ::= {
MBMS-Bearer-Service-in-MBMS-Cell-InfEx-Rsp ::= SEQUENCE (SIZE (1..maxNrOfCells)) OF MBMS-Bearer-Service-in-MBMS-Cell-Item-InfEx-Rsp
MBMS-Bearer-Service-in-MBMS-Cell-Item-InfEx-Rsp ::= SEQUENCE {
                                C-ID,
   mBMS-Bearer-Service-List-InfEx-Rsp
                                                         MBMS-Bearer-Service-List-InfEx-Rsp,
                                ProtocolExtensionContainer { { MBMS-Bearer-Service-in-MBMS-Cell-Item-InfEx-Rsp-ExtIEs} }
   iE-Extensions
                                                                                                                         OPTIONAL,
MBMS-Bearer-Service-in-MBMS-Cell-Item-InfEx-Rsp-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MBMS-Cell-InfEx-Rsp ::= SEOUENCE (SIZE (1..maxNrOfCells)) OF MBMS-Cell-Item-InfEx-Rsp
MBMS-Cell-Item-InfEx-Rsp
                       ::= SEOUENCE {
   c-ID
                                C-ID,
   requestedDataValue
                                RequestedDataValue,
                                iE-Extensions
                                                                                                    OPTIONAL,
   . . .
MBMS-Cell-Item-Infex-Rsp-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
ANR-Cell-Infex-Rsp ::= SEQUENCE (SIZE (1..maxNrOfANRCells)) OF ANR-Cell-ItemIEs-Infex-Rsp
ANR-Cell-ItemIEs-InfEx-Rsp ::=SEQUENCE{
   c-ID
   requestedDataValue
                                RequestedDataValue,
   iE-Extensions
                                ProtocolExtensionContainer { { ANR-Cell-ItemIEs-InfEx-Rsp-ExtIEs} } OPTIONAL,
ANR-Cell-ItemIEs-InfEx-Rsp-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    *****************
-- INFORMATION EXCHANGE INITIATION FAILURE
  InformationExchangeInitiationFailure ::= SEQUENCE {
                                              {{InformationExchangeInitiationFailure-IEs}},
   protocolIEs
                        ProtocolIE-Container
   protocolExtensions
                        ProtocolExtensionContainer {{InformationExchangeInitiationFailure-Extensions}}
                                                                                                           OPTIONAL,
```

```
InformationExchangeInitiationFailure-IEs RNSAP-PROTOCOL-IES ::= {
    { ID
           id-InformationExchangeID
                                                   CRITICALITY
                                                                                   TYPE
                                                                                           InformationExchangeID
                                                                   ignore
    PRESENCE
               mandatory
    { ID
           id-Cause
                                                   CRITICALITY
                                                                                   TYPE
                                                                   ignore
                                                                                           Cause
           PRESENCE
                       mandatory }|
           id-CriticalityDiagnostics
                                                   CRITICALITY
                                                                                   TYPE
                                                                                           CriticalityDiagnostics
    { ID
                                                                   ignore
               optional },
    PRESENCE
InformationExchangeInitiationFailure-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
-- INFORMATION REPORT
__ ********************************
InformationReport ::= SEQUENCE {
    protocolIEs
                           ProtocolIE-Container
                                                   {{InformationReport-IEs}},
                           ProtocolExtensionContainer {{InformationReport-Extensions}}
   protocolExtensions
                                                                                               OPTIONAL.
InformationReport-IEs RNSAP-PROTOCOL-IES ::= {
           id-InformationExchangeID
                                                           CRITICALITY ignore
                                                                                       TYPE
                                                                                               InformationExchangeID
               PRESENCE
                           mandatory }|
    { ID
           id-InformationExchangeObjectType-InfEx-Rprt
                                                           CRITICALITY ignore
                                                                                       TYPE
                                                                                               InformationExchangeObjectType-InfEx-Rprt
    PRESENCE
               mandatory },
    . . .
InformationReport-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
InformationExchangeObjectType-InfEx-Rprt ::= CHOICE {
    cell
                                   Cell-InfEx-Rprt,
    . . . ,
    extension-InformationExchangeObjectType-InfEx-Rprt
                                                           Extension-InformationExchangeObjectType-InfEx-Rprt
Extension-InformationExchangeObjectType-InfEx-Rprt ::= ProtocolIE-Single-Container {{ Extension-InformationExchangeObjectType-InfEx-RprtIE }}
Extension-InformationExchangeObjectType-InfEx-RprtIE RNSAP-PROTOCOL-IES ::= {
    { ID id-MBMS-Bearer-Service-in-MBMS-Cell-InfEx-Rprt
                                                           CRITICALITY
                                                                           ignore
                                                                                       TYPE
                                                                                               MBMS-Bearer-Service-in-MBMS-Cell-InfEx-Rprt
       PRESENCE
                   mandatory}|
    { ID id-MBMS-Cell-InfEx-Rprt
                                                           CRITICALITY
                                                                           ignore
                                                                                       TYPE
                                                                                               MBMS-Cell-InfEx-Rprt
                       PRESENCE
                                   mandatory }
```

```
Cell-InfEx-Rprt ::= SEQUENCE {
   requestedDataValueInformation RequestedDataValueInformation,
                                 ProtocolExtensionContainer {{ CellItem-InfEx-Rprt-ExtIEs }}
   iE-Extensions
                                                                                                  OPTIONAL,
   . . .
CellItem-InfEx-Rprt-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MBMS-Bearer-Service-in-MBMS-Cell-InfEx-Rprt ::= SEOUENCE (SIZE (1..maxNrOfCells)) OF MBMS-Bearer-Service-in-MBMS-Cell-Item-InfEx-Rprt
MBMS-Bearer-Service-in-MBMS-Cell-Item-InfEx-Rprt
                                                ::= SEOUENCE
   mBMS-Bearer-Service-List-InfEx-Rprt
                                                            MBMS-Bearer-Service-List-InfEx-Rprt,
   iE-Extensions
                                 ProtocolExtensionContainer { { MBMS-Bearer-Service-in-MBMS-Cell-Item-InfEx-Rprt-ExtIEs} }
                                                                                                                               OPTIONAL,
MBMS-Bearer-Service-in-MBMS-Cell-Item-InfEx-Rprt-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MBMS-Bearer-Service-List-InfEx-Rprt ::= SEOUENCE (SIZE (1..maxNrOfMBMSServices)) OF MBMS-Bearer-Service-List-Item-InfEx-Rprt
MBMS-Bearer-Service-List-Item-InfEx-Rprt
                                         ::= SEQUENCE {
                          TMGI,
   requestedDataValueInformation RequestedDataValueInformation,
                                 iE-Extensions
                                                                                                                        OPTIONAL,
   . . .
MBMS-Bearer-Service-List-Item-InfEx-Rprt-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MBMS-Cell-Infex-Rprt ::= SEQUENCE (SIZE (1..maxNrOfCells)) OF MBMS-Cell-Item-Infex-Rprt
MBMS-Cell-Item-InfEx-Rprt ::= SEQUENCE {
                                 C-ID,
   requestedDataValueInformation RequestedDataValueInformation,
   iE-Extensions
                                 ProtocolExtensionContainer { { MBMS-Cell-Item-InfEx-Rprt-ExtIEs} }
                                                                                                         OPTIONAL,
MBMS-Cell-Item-Infex-Rprt-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
__ ********************
-- INFORMATION EXCHANGE TERMINATION REQUEST
  *****************
InformationExchangeTerminationRequest ::= SEQUENCE {
   protocolIEs
                                          {{InformationExchangeTerminationReguest-IEs}},
              ProtocolIE-Container
   protocolExtensions
                      ProtocolExtensionContainer {{InformationExchangeTerminationRequest-Extensions}}
                                                                                                  OPTIONAL,
InformationExchangeTerminationRequest-IEs RNSAP-PROTOCOL-IES ::= {
        id-InformationExchangeID
                                      CRITICALITY
                                                    ignore
                                                                    TYPE
                                                                           InformationExchangeID
                                                                                                               PRESENCE
   mandatory },
InformationExchangeTerminationRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
  ******************
-- INFORMATION EXCHANGE FAILURE INDICATION
  ******************
InformationExchangeFailureIndication ::= SEQUENCE {
                                          {{InformationExchangeFailureIndication-IEs}},
   protocolIEs
              ProtocolIE-Container
   protocolExtensions
                          ProtocolExtensionContainer {{InformationExchangeFailureIndication-Extensions}}
                                                                                                              OPTIONAL,
   . . .
InformationExchangeFailureIndication-IEs RNSAP-PROTOCOL-IES ::= {
   { ID id-InformationExchangeID
                               CRITICALITY ignore
                                                              TYPE
                                                                    InformationExchangeID
                                                                                                        PRESENCE
   mandatory }
   { ID id-Cause
                                                              TYPE
                                       CRITICALITY ignore
                                                                     Cause
                                                                                                               PRESENCE
   mandatory },
InformationExchangeFailureIndication-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
  ******************
-- RESET REQUEST
__ ********************************
ResetRequest ::= SEQUENCE {
```

```
{{ResetRequest-IEs}},
    protocolIEs
                           ProtocolIE-Container
   protocolExtensions
                           ProtocolExtensionContainer {{ResetRequest-Extensions}}
                                                                                       OPTIONAL.
ResetRequest-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-RNC-ID
                               CRITICALITY reject TYPE RNC-ID
                                                                   PRESENCE mandatory}
    ID id-ResetIndicator
                               CRITICALITY reject TYPE ResetIndicator
                                                                                   PRESENCE
                                                                                               mandatory },
ResetRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-Extended-RNC-ID
                                       CRITICALITY reject EXTENSION Extended-RNC-ID
                                                                                           PRESENCE optional },
   . . .
ResetIndicator ::= CHOICE {
                   ContextList-Reset,
    context
    all-contexts
                       NULL,
    contextGroup
                   ContextGroupList-Reset
ContextList-Reset ::= SEOUENCE {
    contextInfoList-Reset
                               ContextInfoList-Reset,
   iE-Extensions
                                           ProtocolExtensionContainer { (ContextItem-Reset-ExtIEs) }
                                                                                                                OPTIONAL,
ContextItem-Reset-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
ContextInfoList-Reset ::= SEQUENCE (SIZE (1.. maxResetContext)) OF ProtocolIE-Single-Container {{ ContextInfoItemIE-Reset }}
ContextInfoItemIE-Reset RNSAP-PROTOCOL-IES ::= {
    {ID id-ContextInfoItem-Reset
                                       CRITICALITY reject
                                                               TYPE ContextInfoItem-Reset
                                                                                                PRESENCE mandatory}
ContextInfoItem-Reset ::= SEOUENCE {
    contextType-Reset
                               ContextType-Reset,
                               ProtocolExtensionContainer { { ContextInfoItem-Reset-ExtIEs} } OPTIONAL,
   iE-Extensions
ContextInfoItem-Reset-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
ContextType-Reset ::= CHOICE {
    sRNTI
                   S-RNTI,
    dRNTI
                   D-RNTI,
```

```
ContextGroupList-Reset ::= SEQUENCE {
    contextGroupInfoList-Reset
                                   ContextGroupInfoList-Reset,
   iE-Extensions
                                   ProtocolExtensionContainer { {ContextGroupItem-Reset-ExtIEs} }
                                                                                                             OPTIONAL,
    . . .
ContextGroupItem-Reset-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
ContextGroupInfoList-Reset ::= SEQUENCE (SIZE (1.. maxResetContextGroup)) OF ProtocolIE-Single-Container {{ ContextGroupInfoItemIE-Reset }}
ContextGroupInfoItemIE-Reset RNSAP-PROTOCOL-IES ::= {
    {ID id-ContextGroupInfoItem-Reset
                                                                  TYPE ContextGroupInfoItem-Reset
                                                                                                              PRESENCE mandatory }
                                          CRITICALITY reject
ContextGroupInfoItem-Reset ::= SEQUENCE {
    s-RNTI-Group
                               S-RNTI-Group,
                               ProtocolExtensionContainer { { ContextGroupInfoItem-Reset-ExtIEs} }
   iE-Extensions
                                                                                                              OPTIONAL,
ContextGroupInfoItem-Reset-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
-- RESET RESPONSE
__ *********************
ResetResponse ::= SEQUENCE {
   protocolIEs
                           ProtocolIE-Container
                                                   {{ResetResponse-IEs}},
                          ProtocolExtensionContainer {{ResetResponse-Extensions}}
   protocolExtensions
                                                                                             OPTIONAL.
ResetResponse-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-RNC-ID
                               CRITICALITY ignore TYPE RNC-ID
                                                                  PRESENCE mandatory} |
    { ID id-CriticalityDiagnostics
                                       CRITICALITY
                                                      ignore
                                                                         CriticalityDiagnostics
                                                                                                              PRESENCE
                                                                                                                            optional},
    . . .
ResetResponse-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-Extended-RNC-ID
                                      CRITICALITY reject EXTENSION Extended-RNC-ID
                                                                                         PRESENCE optional },
-- RADIO LINK ACTIVATION COMMAND FDD
```

```
__ *********************
RadioLinkActivationCommandFDD ::= SEOUENCE {
   protocolIEs
                          ProtocolIE-Container
                                                 {{RadioLinkActivationCommandFDD-IEs}},
   protocolExtensions
                          ProtocolExtensionContainer {{RadioLinkActivationCommandFDD-Extensions}}
                                                                                                                  OPTIONAL.
RadioLinkActivationCommandFDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-DelayedActivationList-RL-ActivationCmdFDD
                                                         CRITICALITY ignore TYPE
                                                                                  DelayedActivationInformationList-RL-ActivationCmdFDD
       PRESENCE
                  mandatory },
    . . .
RadioLinkActivationCommandFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
DelayedActivationInformationList-RL-ActivationCmdFDD ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container
    { DelayedActivationInformation-RL-ActivationCmdFDD-IEs} }
DelayedActivationInformation-RL-ActivationCmdFDD-IES RNSAP-PROTOCOL-IES ::= {
    ID id-DelayedActivationInformation-RL-ActivationCmdFDD
                                                           CRITICALITY ignore TYPE DelayedActivationInformation-RL-ActivationCmdFDD
    PRESENCE optional
DelayedActivationInformation-RL-ActivationCmdFDD ::= SEQUENCE {
   rL-ID
                              RL-ID,
   delayed-activation-update
                              DelayedActivationUpdate,
                              ProtocolExtensionContainer { { DelayedActivationInformation-RL-ActivationCmdFDD-ExtIEs} } OPTIONAL,
   iE-Extensions
    . . .
DelayedActivationInformation-RL-ActivationCmdFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
-- RADIO LINK ACTIVATION COMMAND TDD
      ******************
RadioLinkActivationCommandTDD ::= SEQUENCE {
                          ProtocolIE-Container
                                                 {{RadioLinkActivationCommandTDD-IEs}},
   protocolIEs
   protocolExtensions
                          ProtocolExtensionContainer {{RadioLinkActivationCommandTDD-Extensions}}
                                                                                                                  OPTIONAL,
    . . .
RadioLinkActivationCommandTDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-DelayedActivationList-RL-ActivationCmdTDD
                                                         CRITICALITY ignore TYPE
                                                                                   DelayedActivationInformationList-RL-ActivationCmdTDD
       PRESENCE mandatory },
```

```
RadioLinkActivationCommandTDD-Extensions RNSAP-PROTOCOL-EXTENSION ::=
DelayedActivationInformationList-RL-ActivationCmdTDD ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container {
    { DelayedActivationInformation-RL-ActivationCmdTDD-IEs} }
DelayedActivationInformation-RL-ActivationCmdTDD-IES RNSAP-PROTOCOL-IES ::= {
     ID id-DelayedActivationInformation-RL-ActivationCmdTDD CRITICALITY ignore TYPE DelayedActivationInformation-RL-ActivationCmdTDD
   PRESENCE optional
DelayedActivationInformation-RL-ActivationCmdTDD ::= SEQUENCE {
   delayed-activation-update DelayedActivationUpdate,
                              ProtocolExtensionContainer { { DelayedActivationInformation-RL-ActivationCmdTDD-ExtIEs} } OPTIONAL,
   iE-Extensions
DelayedActivationInformation-RL-ActivationCmdTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     GERAN UPLINK SIGNALLING TRANSFER INDICATION
  ****************
GERANUplinkSignallingTransferIndication ::= SEQUENCE {
                                 ProtocolIE-Container
                                                            {{GERANUplinkSignallingTransferIndication-IEs}},
   protocolIEs
   protocolExtensions
                                  ProtocolExtensionContainer {{GERANUplinkSignallingTransferIndication-Extensions}}
                                                                                                                 OPTIONAL,
   . . .
GERANUplinkSignallingTransferIndication-IEs RNSAP-PROTOCOL-IES ::= {
   { ID id-UC-ID
                                     CRITICALITY ignore TYPE UC-ID
                                                                                          PRESENCE mandatory
   -- UC-Id may be GERAN cell identifier.
    { ID id-SAI
                                     CRITICALITY ignore TYPE SAI
                                                                                          PRESENCE mandatory
     ID id-S-RNTI
                                     CRITICALITY ignore TYPE S-RNTI
                                                                                          PRESENCE mandatory
     ID id-D-RNTI
                                     CRITICALITY ignore TYPE D-RNTI
                                                                                          PRESENCE optional
     ID id-L3-Information
                                     CRITICALITY ignore TYPE L3-Information
                                                                                          PRESENCE mandatory
     ID id-CN-PS-DomainIdentifier
                                     CRITICALITY ignore TYPE CN-PS-DomainIdentifier
                                                                                          PRESENCE optional
     ID id-CN-CS-DomainIdentifier
                                     CRITICALITY ignore TYPE CN-CS-DomainIdentifier
                                                                                          PRESENCE optional
    { ID id-URA-Information
                                     CRITICALITY ignore TYPE URA-Information
                                                                                          PRESENCE optional
   -- URA information may be GRA information
   . . .
GERANUplinkSignallingTransferIndication-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
```

```
__ *********************
-- RADIO LINK PARAMETER UPDATE INDICATION FDD
   ****************
RadioLinkParameterUpdateIndicationFDD ::= SEQUENCE {
                                                  {{RadioLinkParameterUpdateIndicationFDD-IEs}},
   protocolIEs
                          ProtocolIE-Container
   protocolExtensions
                           ProtocolExtensionContainer {{RadioLinkParameterUpdateIndicationFDD-Extensions}}
                                                                                                                   OPTIONAL,
RadioLinkParameterUpdateIndicationFDD-IEs RNSAP-PROTOCOL-IES ::= {
    { ID
          id-HSDSCH-FDD-Update-Information
                                                                 CRITICALITY ignore TYPE
                                                                                            HSDSCH-FDD-Update-Information
               optional}|
    PRESENCE
    { ID
          id-RL-ParameterUpdateIndicationFDD-RL-InformationList CRITICALITY ignore TYPE
                                                                                            RL-ParameterUpdateIndicationFDD-RL-InformationList
       PRESENCE optional },
RL-ParameterUpdateIndicationFDD-RL-InformationList ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF ProtocolIE-Single-Container { { RL-
ParameterUpdateIndicationFDD-RL-InformationList-IEs} }
RL-ParameterUpdateIndicationFDD-RL-InformationList-IES RNSAP-PROTOCOL-IES ::= {
    { ID id-RL-ParameterUpdateIndicationFDD-RL-Information-Item
                                                                 CRITICALITY ignore TYPE RL-ParameterUpdateIndicationFDD-RL-Information-Item
       PRESENCE mandatory }
RL-ParameterUpdateIndicationFDD-RL-Information-Item::= SEQUENCE {
                                      RL-ID,
   phase-Reference-Update-Indicator
                                      Phase-Reference-Update-Indicator
                                      ProtocolExtensionContainer { { RL-ParameterUpdateIndicationFDD-RL-Information-ExtIEs} } OPTIONAL,
   iE-Extensions
    . . .
RL-ParameterUpdateIndicationFDD-RL-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RadioLinkParameterUpdateIndicationFDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-E-DCH-FDD-Update-Information
                                                     CRITICALITY ignore EXTENSION E-DCH-FDD-Update-Information
                                                                                                                           PRESENCE optional |
    ID id-Additional-HS-Cell-Information-RL-Param-Upd CRITICALITY ignore EXTENSION Additional-HS-Cell-Information-RL-Param-Upd
                                                                                                                                  PRESENCE
optional}
    { ID id-Additional-EDCH-Cell-Information-RL-Param-Upd CRITICALITY ignore EXTENSION Additional-EDCH-Cell-Information-RL-Param-Upd
    PRESENCE optional } |
    { ID id-CPC-RecoveryReport
                                                      CRITICALITY ignore EXTENSION CPC-RecoveryReport
                                                                                                                           PRESENCE optional },
   . . .
Additional-HS-Cell-Information-RL-Param-Upd ::= SEQUENCE (SIZE (1..maxNrOfHSDSCH-1)) OF Additional-HS-Cell-Information-RL-Param-Upd-ItemIEs
Additional-HS-Cell-Information-RL-Param-Upd-ItemIEs ::=SEQUENCE{
```

```
hSPDSCH-RL-ID
                                                   RL-ID,
   hS-DSCH-FDD-Secondary-Serving-Update-Information
                                                 HS-DSCH-FDD-Secondary-Serving-Update-Information,
   iE-Extensions
                                 ProtocolExtensionContainer { { Additional-HS-Cell-Information-RL-Setup-ExtIEs} } OPTIONAL,
Additional-HS-Cell-Information-RL-Setup-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Additional-EDCH-Cell-Information-RL-Param-Upd ::= SEQUENCE (SIZE (1..maxNrOfEDCH-1)) OF Additional-EDCH-Cell-Information-RL-Param-Upd-ItemIEs
Additional-EDCH-Cell-Information-RL-Param-Upd-ItemIEs ::=SEQUENCE{
   additional-EDCH-FDD-Update-Information
                                                                         Additional-EDCH-FDD-Update-Information,
   iE-Extensions
                                 ProtocolExtensionContainer { { Additional-EDCH-FDD-Update-Information-ExtIEs} } OPTIONAL,
Additional-EDCH-FDD-Update-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
     -- RADIO LINK PARAMETER UPDATE INDICATION TDD
__ **********************
RadioLinkParameterUpdateIndicationTDD ::= SEQUENCE {
                                                {{RadioLinkParameterUpdateIndicationTDD-IEs}},
   protocolIEs
                         ProtocolIE-Container
                         ProtocolExtensionContainer {{RadioLinkParameterUpdateIndicationTDD-Extensions}}
   protocolExtensions
                                                                                                              OPTIONAL,
RadioLinkParameterUpdateIndicationTDD-IEs RNSAP-PROTOCOL-IES ::= {
   { ID
          id-HSDSCH-TDD-Update-Information
                                               CRITICALITY
                                                                         TYPE
                                                                                HSDSCH-TDD-Update-Information
                                                                                                                            PRESENCE
                                                              ignore
   optional},
   . . .
RadioLinkParameterUpdateIndicationTDD-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
-- UE MEASUREMENT INITIATION REQUEST
  ****************
UEMeasurementInitiationRequest ::= SEQUENCE {
   protocolIEs
                                 ProtocolIE-Container
                                                          {{UEMeasurementInitiationRequest-IEs}},
   protocolExtensions
                                 ProtocolExtensionContainer {{UEMeasurementInitiationRequest-Extensions}}
                                                                                                                     OPTIONAL,
   . . .
```

```
UEMeasurementInitiationRequest-IES RNSAP-PROTOCOL-IES ::= {
   { ID id-AllowedOueuingTime
                                       CRITICALITY reject TYPE AllowedOueuingTime
                                                                                                          PRESENCE optional
    ID id-MeasurementID
                                       CRITICALITY reject TYPE MeasurementID
                                                                                                          PRESENCE mandatory
    ID id-UEMeasurementType
                                       CRITICALITY reject TYPE UEMeasurementType
                                                                                                          PRESENCE mandatory
    ID id-UEMeasurementTimeslotInfoHCR
                                       CRITICALITY reject TYPE UEMeasurementTimeslotInfoHCR
                                                                                                   PRESENCE optional
    ID id-UEMeasurementTimeslotInfoLCR
                                       CRITICALITY reject TYPE UEMeasurementTimeslotInfoLCR
                                                                                                   PRESENCE optional
    ID id-MeasurementFilterCoefficient
                                       CRITICALITY reject TYPE MeasurementFilterCoefficient
                                                                                                   PRESENCE optional
    PRESENCE mandatory
    ID id-UEMeasurementParameterModAllow
                                       CRITICALITY reject TYPE UEMeasurementParameterModAllow
                                                                                                   PRESENCE mandatory
UEMeasurementInitiationRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
   { ID id-UEMeasurementTimeslotInfo768
                                              CRITICALITY reject EXTENSION UEMeasurementTimeslotInfo768
                                                                                                   PRESENCE optional },
    ****************
-- UE MEASUREMENT INITIATION RESPONSE
           ****************
UEMeasurementInitiationResponse ::= SEQUENCE {
   protocolIEs
                              ProtocolIE-Container
                                                    {{UEMeasurementInitiationResponse-IEs}},
                             ProtocolExtensionContainer {{UEMeasurementInitiationResponse-Extensions}}
   protocolExtensions
                                                                                                          OPTIONAL,
UEMeasurementInitiationResponse-IES RNSAP-PROTOCOL-IES ::= {
    ID id-MeasurementID
                                       CRITICALITY ignore TYPE MeasurementID
                                                                                                          PRESENCE mandatory
    ID id-MeasurementFilterCoefficient
                                       CRITICALITY reject TYPE MeasurementFilterCoefficient
                                                                                                   PRESENCE optional
    PRESENCE optional
    ID id-CriticalityDiagnostics
                                       CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                                          PRESENCE optional
UEMeasurementInitiationResponse-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
```

```
-- UE MEASUREMENT INITIATION FAILURE
__ *********************
UEMeasurementInitiationFailure ::= SEQUENCE {
   protocolIEs
                              ProtocolIE-Container
                                                     {{UEMeasurementInitiationFailure-IEs}},
   protocolExtensions
                            ProtocolExtensionContainer {{UEMeasurementInitiationFailure-Extensions}}
                                                                                                           OPTIONAL,
UEMeasurementInitiationFailure-IEs RNSAP-PROTOCOL-IES ::= {
    ID id-MeasurementID
                                     CRITICALITY ignore TYPE MeasurementID
                                                                                        PRESENCE mandatory
    ID id-Cause
                                     CRITICALITY ignore TYPE Cause
                                                                                        PRESENCE mandatory
   ID id-CriticalityDiagnostics
                              CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                        PRESENCE optional
UEMeasurementInitiationFailure-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
-- UE MEASUREMENT REPORT
    UEMeasurementReport ::= SEQUENCE {
                                                     {{UEMeasurementReport-IEs}},
   protocolIEs
                              ProtocolIE-Container
                              ProtocolExtensionContainer {{UEMeasurementReport-Extensions}}
   protocolExtensions
                                                                                                  OPTIONAL,
UEMeasurementReport-IEs RNSAP-PROTOCOL-IES ::= {
    ID id-MeasurementID
                                     CRITICALITY ignore TYPE MeasurementID
                                                                                               PRESENCE mandatory
   PRESENCE mandatory
UEMeasurementReport-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
-- UE MEASUREMENT TERMINATION REQUEST
__ *********************
UEMeasurementTerminationRequest ::= SEQUENCE {
                                                     {{UEMeasurementTerminationRequest-IEs}},
   protocolIEs
                              ProtocolIE-Container
   protocolExtensions
                              ProtocolExtensionContainer {{UEMeasurementTerminationRequest-Extensions}}
                                                                                                            OPTIONAL,
```

```
UEMeasurementTerminationRequest-IES RNSAP-PROTOCOL-IES ::= {
                                   CRITICALITY ignore TYPE MeasurementID
   { ID id-MeasurementID
                                                                                  PRESENCE mandatory }.
UEMeasurementTerminationRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
        ****************
-- UE MEASUREMENT FAILURE INDICATION
__ *********************
UEMeasurementFailureIndication ::= SEQUENCE {
   protocolIEs
                                ProtocolIE-Container
                                                         {{UEMeasurementFailureIndication-IEs}},
                                ProtocolExtensionContainer {{UEMeasurementFailureIndication-Extensions}}
   protocolExtensions
                                                                                                                  OPTIONAL,
UEMeasurementFailureIndication-IEs RNSAP-PROTOCOL-IES ::= {
                                   CRITICALITY ignore TYPE MeasurementID
   { ID id-MeasurementID
                                                                                   PRESENCE mandatory
                                    CRITICALITY ignore TYPE Cause
   { ID id-Cause
                                                                                   PRESENCE mandatory
   . . .
UEMeasurementFailureIndication-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
  *****************
-- IUR INVOKE TRACE
  *****************
IurInvokeTrace ::= SEQUENCE {
   protocolIEs
                                           ProtocolIE-Container
                                                                    {{IurInvokeTrace-IEs}},
                                           ProtocolExtensionContainer {{IurInvokeTrace-Extensions}}
   protocolExtensions
                                                                                                            OPTIONAL,
IurInvokeTrace-IEs RNSAP-PROTOCOL-IES ::= {
   { ID id-D-RNTI
                                           CRITICALITY ignore TYPE D-RNTI
                                                                                                                   PRESENCE optional
      } |
     ID id-TraceReference
                                           CRITICALITY ignore TYPE TraceReference
                                                                                                                   PRESENCE mandatory
     ID id-UEIdentity
                                           CRITICALITY ignore TYPE UEIdentity
                                                                                                                   PRESENCE mandatory
     ID id-TraceRecordingSessionReference
                                           CRITICALITY ignore TYPE TraceRecordingSessionReference
                                                                                                            PRESENCE mandatory
     ID id-ListOfInterfacesToTrace
                                           CRITICALITY ignore TYPE ListOfInterfacesToTrace
                                                                                                                   PRESENCE optional
      } |
```

```
ID id-TraceDepth
                                       CRITICALITY ignore TYPE TraceDepth
                                                                                                         PRESENCE mandatory
ListOfInterfacesToTrace ::= SEQUENCE (SIZE (1..maxNrOfInterfaces)) OF ProtocolIE-Single-Container {{ InterfacesToBeTracedItemIE }}
InterfacesToBeTracedItemIE RNSAP-PROTOCOL-IES ::= {
    ID id-InterfacesToTraceItem
                                       CRITICALITY ignore TYPE InterfacesToTraceItem
                                                                                                         PRESENCE mandatory
InterfacesToTraceItem ::= SEQUENCE {
   interface
                      ENUMERATED {iub, iur, ...},
   iE-Extensions
                      InterfacesToTraceItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
IurInvokeTrace-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
-- Extension for Release 10 to support MDT
   {ID id-MDT-Configuration
                                       CRITICALITY ignore EXTENSION MDT-Configuration
                                                                                      PRESENCE optional |
-- Extension for Release 10 to support MDT
   PRESENCE optional },
   -- IUR DEACTIVATE TRACE
__ *********************
IurDeactivateTrace ::= SEQUENCE {
                                       ProtocolIE-Container
                                                              {{IurDeactivateTrace-IEs}},
   protocolIEs
   protocolExtensions
                                       ProtocolExtensionContainer {{IurDeactivateTrace-Extensions}}
                                                                                            OPTIONAL,
IurDeactivateTrace-IEs RNSAP-PROTOCOL-IES ::= {
   { ID id-D-RNTI
                                       CRITICALITY ignore TYPE D-RNTI
                                                                                                         PRESENCE optional
    ID id-TraceReference
                                       CRITICALITY ignore TYPE TraceReference
                                                                                                         PRESENCE mandatory
IurDeactivateTrace-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
```

```
-- MBMS ATTACH COMMAND
__ ********************************
MBMSAttachCommand ::= SEQUENCE {
   protocolIEs
                       ProtocolIE-Container {{MBMSAttachCommand-IEs}},
                       ProtocolExtensionContainer {{MBMSAttachCommand-Extensions}}
   protocolExtensions
                                                                                  OPTIONAL.
MBMSAttachCommand-IEs RNSAP-PROTOCOL-IES ::= {
    ID id-MBMS-Bearer-Service-List
                                                             TYPE MBMS-Bearer-Service-List PRESENCE mandatory}
                                     CRITICALITY
                                                   ignore
    ID id-UE-State
                                     CRITICALITY
                                                   ignore
                                                                    UE-State
                                                                                         PRESENCE
                                                                                                      optional},
MBMSAttachCommand-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
-- MBMS DETACH COMMAND
  ******************
MBMSDetachCommand ::= SEQUENCE {
                                            {{MBMSDetachCommand-IEs}},
   protocolIEs
                       ProtocolIE-Container
                       ProtocolExtensionContainer {{MBMSDetachCommand-Extensions}}
   protocolExtensions
                                                                                  OPTIONAL,
   . . .
MBMSDetachCommand-IEs RNSAP-PROTOCOL-IES ::= {
    ID id-MBMS-Bearer-Service-List CRITICALITY
                                               ignore
                                                          TYPE MBMS-Bearer-Service-List PRESENCE
                                                                                                mandatory}
                                                                                                optional},
    ID id-UE-State
                                  CRITICALITY
                                               ignore
                                                          TYPE UE-State
                                                                                   PRESENCE
MBMSDetachCommand-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
  -- DIRECT INFORMATION TRANSFER
  DirectInformationTransfer ::= SEQUENCE {
   protocolIEs
                     ProtocolIE-Container
                                                {{DirectInformationTransfer-IEs}},
                     ProtocolExtensionContainer {{DirectInformationTransfer-Extensions}}
   protocolExtensions
                                                                                                      OPTIONAL,
```

```
DirectInformationTransfer-IEs RNSAP-PROTOCOL-IES ::= {
  { ID id-RNC-ID
                                CRITICALITY ignore TYPE RNC-ID
                                                                                PRESENCE mandatory}
  ID id-ProvidedInformation
                                CRITICALITY ignore TYPE ProvidedInformation
                                                                                PRESENCE mandatory },
DirectInformationTransfer-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
  { ID id-Extended-RNC-ID
                               CRITICALITY reject EXTENSION Extended-RNC-ID PRESENCE optional },
  . . .
 -- ENHANCED RELOCATION REQUEST
 ****************
EnhancedRelocationRequest ::= SEQUENCE {
                                          {{EnhancedRelocationRequest-IEs}},
  protocolIEs
           ProtocolIE-Container
                      ProtocolExtensionContainer {{EnhancedRelocationRequest-Extensions}}
  protocolExtensions
                                                                                 OPTIONAL,
EnhancedRelocationRequest-IEs RNSAP-PROTOCOL-IES ::= {
   ID id-Cause CRITICALITY reject TYPE Cause
                                                     PRESENCE mandatory
   -- This IE shall be present if the Relocation type IE is set to "UE involved in relocation of SRNS" --
  PRESENCE optional } |
             CRITICALITY reject TYPE S-RNTI PRESENCE mandatory } |
  PRESENCE
mandatory },
EnhancedRelocationRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
   ******************
-- ENHANCED RELOCATION RESPONSE
 ******************
EnhancedRelocationResponse ::= SEQUENCE {
  protocolIEs
                       ProtocolIE-Container
                                          {{EnhancedRelocationResponse-IEs}},
                       ProtocolExtensionContainer {{EnhancedRelocationResponse-Extensions}}
  protocolExtensions
                                                                                  OPTIONAL,
```

```
EnhancedRelocationResponse-IEs RNSAP-PROTOCOL-IES ::= {
   { ID id-RANAP-EnhancedRelocationInformationResponse
                                                   CRITICALITY ignore TYPE RANAP-EnhancedRelocationInformationResponse
   PRESENCE mandatory },
EnhancedRelocationResponse-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
       -- ENHANCED RELOCATION FAILURE
  ****************
EnhancedRelocationFailure ::= SEQUENCE {
   protocolIEs
                              ProtocolIE-Container
                                                      {{EnhancedRelocationFailure-IEs}},
                              ProtocolExtensionContainer {{EnhancedRelocationFailure-Extensions}}
   protocolExtensions
                                                                                                        OPTIONAL,
EnhancedRelocationFailure-IEs RNSAP-PROTOCOL-IES ::= {
    ID id-Cause
                   CRITICALITY ignore TYPE Cause
                                                             PRESENCE mandatory }
   { ID id-CriticalityDiagnostics
                                     CRITICALITY ignore TYPE CriticalityDiagnostics
                                                                                   PRESENCE optional
   . . .
EnhancedRelocationFailure-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
  *****************
-- ENHANCED RELOCATION CANCEL
  *****************
EnhancedRelocationCancel ::= SEQUENCE {
   protocolIEs
                              ProtocolIE-Container
                                                      {{EnhancedRelocationCancel-IEs}},
                              ProtocolExtensionContainer {{EnhancedRelocationCancel-Extensions}}
   protocolExtensions
                                                                                                       OPTIONAL,
EnhancedRelocationCancel-IEs RNSAP-PROTOCOL-IES ::= {
   { ID id-Cause
                   CRITICALITY ignore TYPE Cause
                                                             PRESENCE mandatory },
   . . .
EnhancedRelocationCancel-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
__ ***********************
```

```
-- ENHANCED RELOCATION SIGNALLING TRANSFER
  *****************
EnhancedRelocationSignallingTransfer ::= SEQUENCE {
   protocolIEs
                              ProtocolIE-Container
                                                       {{EnhancedRelocationSignallingTransfer-IEs}},
                              ProtocolExtensionContainer {{EnhancedRelocationSignallingTransfer-Extensions}}
   protocolExtensions
                                                                                                                   OPTIONAL,
EnhancedRelocationSignallingTransfer-IEs RNSAP-PROTOCOL-IES ::= {
   { ID id-L3-Information
                           CRITICALITY ignore TYPE L3-Information
                                                                            PRESENCE mandatory
   . . .
EnhancedRelocationSignallingTransfer-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
  -- ENHANCED RELOCATION RELEASE
  *****************
EnhancedRelocationRelease ::= SEQUENCE {
   protocolIEs
                               ProtocolIE-Container
                                                       {{EnhancedRelocationRelease-IEs}},
                              ProtocolExtensionContainer {{EnhancedRelocationRelease-Extensions}}
   protocolExtensions
                                                                                                         OPTIONAL,
EnhancedRelocationRelease-IEs RNSAP-PROTOCOL-IES ::= {
                              CRITICALITY ignore TYPE Released-CN-Domain
   { ID id-Released-CN-Domain
                                                                                   PRESENCE mandatory
   . . .
EnhancedRelocationRelease-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
-- MBSFN MCCH INFORMATION
__ ********************
MBSFNMCCHInformation ::= SEQUENCE {
   protocolIEs
               ProtocolIE-Container
                                             {{MBSFNMCCHInformation-IEs}},
   protocolExtensions ProtocolExtensionContainer {{MBSFNMCCHInformation-Extensions}}
                                                                                   OPTIONAL,
MBSFNMCCHInformation-IEs RNSAP-PROTOCOL-IES ::= {
```

```
ID id-MBSFN-Cluster-Identity CRITICALITY
                                                              TYPE MBSFN-Cluster-Identity PRESENCE
                                                                                                      mandatory} |
                                                  ignore
     ID id-MCCH-Message-List CRITICALITY
                                                          TYPE MCCH-Message-List PRESENCE mandatory}
                                              reject
     ID id-CFN CRITICALITY
                              reiect
                                          TYPE CFN PRESENCE
                                                              mandatory}
    { ID id-MCCH-Configuration-Info
                                          CRITICALITY
                                                          ignore
                                                                      TYPE
                                                                             MCCH-Configuration-Info
                                                                                                                            PRESENCE
    optional}|
    { ID id-MBSFN-Scheduling-Transmission-Time-Interval-Info-List CRITICALITY
                                                                                 ignore
                                                                                             TYPE MBSFN-Scheduling-Transmission-Time-Interval-
Info-List PRESENCE optional },
MBSFNMCCHInformation-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
  SECONDARY UL FREQUENCY REPORT
SecondaryULFrequencyReport ::= SEQUENCE {
   protocolIEs
                          ProtocolIE-Container
                                                  {{SecondaryULFrequencyReport-IEs}},
                          ProtocolExtensionContainer {{SecondaryULFrequencyReport-Extensions}}
   protocolExtensions
                                                                                                             OPTIONAL,
   . . .
SecondaryULFrequencyReport-IEs RNSAP-PROTOCOL-IES ::= {
   { ID id-ActivationInformation CRITICALITY
                                                              TYPE ActivationInformation
                                                                                             PRESENCE mandatory },
                                                  ignore
    . . .
SecondaryULFrequencyReport-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
  SECONDARY UL FREQUENCY UPDATE INDICATION
       ****************
SecondaryULFrequencyUpdateIndication ::= SEQUENCE {
                          ProtocolIE-Container
                                                  {{SecondaryULFrequencyUpdateIndication-IEs}},
   protocolIEs
   protocolExtensions
                           ProtocolExtensionContainer {{SecondaryULFrequencyUpdateIndication-Extensions}}
                                                                                                                    OPTIONAL,
SecondaryULFrequencyUpdateIndication-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-ActivationInformation CRITICALITY ignore
                                                              TYPE ActivationInformation
                                                                                             PRESENCE mandatory },
    . . .
SecondaryULFrequencyUpdateIndication-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
```

```
*****************
-- ENHANCED RELOCATION RESOURCE REQUEST
  *****************
EnhancedRelocationResourceRequest ::= SEQUENCE {
                        ProtocolIE-Container
   protocolIEs
                                                   {{ EnhancedRelocationResourceRequest-IEs}},
   protocolExtensions
                        ProtocolExtensionContainer
                                                 {{ EnhancedRelocationResourceRequest-Extensions}}
                                                                                                      OPTIONAL,
EnhancedRelocationResourceRequest-IEs RNSAP-PROTOCOL-IES ::= {
                                                                                   PRESENCE optional}
     ID id-IMSI
                                    CRITICALITY reject TYPE IMSI
     ID id-SourceID
                                    CRITICALITY ignore TYPE SourceID
                                                                                   PRESENCE mandatory
     ID id-TargetID
                                    CRITICALITY reject TYPE TargetID
                                                                                   PRESENCE mandatory
     ID id-ClassmarkInformation2
                                                                                   PRESENCE mandatory }
                                    CRITICALITY reject TYPE ClassmarkInformation2
     ID id-ClassmarkInformation3
                                    CRITICALITY ignore TYPE ClassmarkInformation3
                                                                                   PRESENCE mandatory }
   { ID id-SpeechVersion
                                    CRITICALITY ignore TYPE SpeechVersion
                                                                                   PRESENCE mandatory },
EnhancedRelocationResourceRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
  ENHANCED RELOCATION RESOURCE RESPONSE
  ****************
EnhancedRelocationResourceResponse ::= SEQUENCE {
   protocolIEs
                        ProtocolIE-Container
                                                   {{EnhancedRelocationResourceResponse-IEs}},
   protocolExtensions
                         ProtocolExtensionContainer
                                                 {{EnhancedRelocationResourceResponse-Extensions}}
                                                                                                      OPTIONAL,
EnhancedRelocationResourceResponse-IEs RNSAP-PROTOCOL-IES ::= {
     ID id-D-RNTI
                                       CRITICALITY ignore TYPE D-RNTI
                                                                                        PRESENCE mandatory }
     ID id-L3-Information
                                                                                        PRESENCE mandatory }
                                       CRITICALITY ignore TYPE L3-Information
     ID id-Cell-Capacity-Class-Value
                                       CRITICALITY ignore TYPE Cell-Capacity-Class-Value
                                                                                        PRESENCE optional } |
    ID id-LoadValue
                                       CRITICALITY ignore TYPE LoadValue
                                                                                        PRESENCE optional },
EnhancedRelocationResourceResponse-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
  ******************
```

```
-- ENHANCED RELOCATION RESOURCE FAILURE
EnhancedRelocationResourceFailure ::= SEQUENCE {
   protocolIEs
                         ProtocolIE-Container
                                                     {{EnhancedRelocationResourceFailure-IEs}},
   protocolExtensions
                         ProtocolExtensionContainer
                                                   {{EnhancedRelocationResourceFailure-Extensions}}
                                                                                                         OPTIONAL.
EnhancedRelocationResourceFailure-IEs RNSAP-PROTOCOL-IES ::= {
                                     CRITICALITY ignore TYPE Cause
                                                                                          PRESENCE mandatory } |
     ID id-Cell-Capacity-Class-Value CRITICALITY ignore TYPE Cell-Capacity-Class-Value
                                                                                          PRESENCE optional }
    { ID id-LoadValue
                                     CRITICALITY ignore TYPE LoadValue
                                                                                          PRESENCE optional },
   . . .
EnhancedRelocationResourceFailure-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
  ENHANCED RELOCATION RESOURCE RELEASE COMMAND
EnhancedRelocationResourceReleaseCommand ::= SEQUENCE {
                                                     {{EnhancedRelocationResourceReleaseCommand-IEs}},
   protocolIEs
                         ProtocolIE-Container
                                                   {{EnhancedRelocationResourceReleaseCommand-Extensions}} OPTIONAL,
   protocolExtensions
                          ProtocolExtensionContainer
EnhancedRelocationResourceReleaseCommand-IEs RNSAP-PROTOCOL-IES ::= {
   { ID id-Cause
                      CRITICALITY ignore TYPE Cause
                                                        PRESENCE mandatory },
   . . .
EnhancedRelocationResourceReleaseCommand-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
-- ENHANCED RELOCATION RESOURCE RELEASE COMPLETE
  ******************
EnhancedRelocationResourceReleaseComplete ::= SEQUENCE {
   protocolIEs
                         ProtocolIE-Container
                                                {{EnhancedRelocationResourceReleaseComplete-IEs}},
                          ProtocolExtensionContainer {{EnhancedRelocationResourceReleaseComplete-Extensions}}
   protocolExtensions
                                                                                                                OPTIONAL,
```

```
EnhancedRelocationResourceReleaseComplete-IEs RNSAP-PROTOCOL-IES ::= {
EnhancedRelocationResourceReleaseComplete-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
-- PRIVATE MESSAGE
__ *********************
PrivateMessage ::= SEQUENCE {
   privateIEs
                 PrivateIE-Container {{PrivateMessage-IEs}},
PrivateMessage-IEs RNSAP-PRIVATE-IES ::= {
    ****************
-- INFORMATION TRANSFER CONTROL REQUEST
        ******************
InformationTransferControlRequest ::= SEQUENCE {
                                                  {{ InformationTransferControlRequest-IEs}},
   protocolIEs
                ProtocolIE-Container
                      ProtocolExtensionContainer {{ InformationTransferControlRequest-Extensions}}
   protocolExtensions
                                                                                                     OPTIONAL,
   . . .
InformationTransferControlRequest-IES RNSAP-PROTOCOL-IES ::= {
   { ID id-Control-Type-InformationTransferControlReq CRITICALITY ignore TYPE Control-Type-InformationTransferControlReq
                                                                                                                   PRESENCE mandatory
InformationTransferControlRequest-Extensions RNSAP-PROTOCOL-EXTENSION ::= {
Control-Type-InformationTransferControlReq ::= CHOICE {
   suspension
                    Suspension-Control-Type,
                     Resume-Control-Type,
   resume
Suspension-Control-Type ::= SEQUENCE
   controlled-Object-Scope Controlled-Object-Scope,
                        ProtocolExtensionContainer {{ Suspension-Control-Type-ExtIEs}},
```

9.3.4 Information Element Definitions

```
__ *********************
-- Information Element Definitions
RNSAP-IEs {
itu-t (0) identified-organization (4) etsi (0) mobileDomain (0)
umts-Access (20) modules (3) rnsap (1) version1 (1) rnsap-IEs (2) }
DEFINITIONS AUTOMATIC TAGS ::=
BEGIN
IMPORTS
   maxCellSIB110rSIB12,
   maxNrOfFACHs,
   maxIBSEG,
   maxCellsMeas,
   maxNoOfDSCHs,
   maxNoOfUSCHs,
   maxNrOfDCHs,
   maxNrOfDL-Codes,
   maxNrOfDLTs,
   maxNrOfDLTsLCR,
   maxNrOfDPCHs,
    maxNrOfDPCHs768,
    maxNrOfDPCHsLCR,
    maxNrOfEDCH-HARQ-PO-QUANTSTEPs,
    maxNrOfEDCHHARQProcesses2msEDCH,
    maxNrOfBits-MACe-PDU-non-scheduled,
    maxNrOfEDPCCH-PO-QUANTSTEPs,
```

```
maxNrOfRefETFCI-PO-QUANTSTEPs,
maxNrOfRefETFCIs.
maxNrOfErrors.
maxNrOfFDDNeighboursPerRNC,
maxNrOfMACcshSDU-Length,
maxNrOfNeighbouringRNCs,
maxNrOfTDDNeighboursPerRNC,
maxNrOfLCRTDDNeighboursPerRNC,
maxNrOfTS,
maxNrOfTsLCR,
maxNrOfULTs,
maxNrOfULTsLCR,
maxNrOfGSMNeighboursPerRNC,
maxRateMatching,
maxNrOfPoints,
maxNoOfRB,
maxNrOfRLs,
maxNrOfTFCs,
maxNrOfTFs,
maxCTFC,
maxRNCinURA-1,
maxNrOfSCCPCHs,
maxNrOfSCCPCHs768,
maxTGPS,
maxTTI-Count,
maxNoGPSTypes,
maxNoSat,
maxNrOfActiveMBMSServices,
maxNrOfCells,
maxNrOfSNAs,
maxNrOfHAROProc,
maxNrOfHSSCCHCodes,
maxNrOfMACdFlows,
maxNrOfMACdFlows-1,
maxNrOfMACdPDUSize,
maxNrOfMBMSL3,
maxNrOfMCCHMessages,
maxNrOfEDCHMACdFlows,
maxNrOfEDCHMACdFlows-1,
maxNrOfEDCHMACdFlowsLCR,
maxNrOfEDCHMACdFlowsLCR-1,
maxNrOfMBMSServices,
maxNrOfPDUIndexes,
maxNrOfPDUIndexes-1,
maxNrOfPrioOueues,
maxNrOfPrioQueues-1,
maxNrOfSatAlmanac-maxNoSat,
maxNrOfGERANSI,
maxNrofSigSegERGHICH-1,
maxNrOfUEs,
maxNrOfAddFreq,
maxNrOfCellsPerFreq,
maxNoOfLogicalChannels,
maxNrOfRefBetas,
```

```
maxNrOfEAGCHCodes,
maxNrOfHS-DSCHTBSs.
maxNrOfHS-DSCHTBSs-HS-SCCHless.
maxHS-PDSCHCodeNrComp-1,
maxNrOfEHICHCodes.
maxGANSSSat,
maxNoGANSS,
maxSqnType,
maxNrOfBroadcastPLMNs,
maxHSDPAFrequency,
maxHSDPAFrequency-1,
maxFrequencyinCell,
maxFrequencyinCell-1,
maxGANSSSatAlmanac,
maxGANSSClockMod,
maxNrOfEDCHRLs,
maxNrOfEUTRANeighboursPerRNC,
maxEARFCN,
maxNrOfPreconfiguredNeighbours,
maxNrOfHSDSCH-1,
maxNrOfHSDSCH,
maxGANSS-1,
maxlengthMBMSconcatservlists,
maxNoOfTBSs-Mapping-HS-DSCH-SPS.
maxNoOfTBSs-Mapping-HS-DSCH-SPS-1,
maxNoOfHS-DSCH-TBSsLCR,
maxNoOfRepetition-Period-LCR,
maxNoOfRepetitionPeriod-SPS-LCR-1,
maxNoOf-HS-SICH-SPS,
maxNoOf-HS-SICH-SPS-1,
maxNoOfNon-HS-SCCH-Assosiated-HS-SICH,
maxNrOfEDCH-1,
maxNrOfDCHMeasurementOccasionPatternSequence,
maxNrOfULCarriersLCR-1,
maxNrOfCellIds,
maxNrOfRAIs,
maxNrOfLAIs,
maxNrOfExtendedNeighbouringRNCs,
maxFreqBandsTDD,
id-Allowed-Rate-Information,
id-AntennaColocationIndicator.
id-BindingID,
id-Cell-Capacity-Class-Value,
id-CellCapabilityContainer-FDD,
id-CellCapabilityContainer-TDD,
id-CellCapabilityContainer-TDD-LCR,
id-Continuous-Packet-Connectivity-HS-SCCH-Less-Information,
id-Continuous-Packet-Connectivity-HS-SCCH-Less-Information-Response,
id-Counting-Information,
id-CoverageIndicator,
id-DPC-Mode-Change-SupportIndicator,
id-E-DCH-Minimum-Set-E-TFCIValidityIndicator,
id-E-RGCH-E-HICH-ChannelisationCodeValidityIndicator,
```

```
id-Extended-Round-Trip-Time-Value,
id-ExtendedPropagationDelay,
id-Extended-SRNC-ID.
id-Extended-RNC-ID,
id-GERAN-Cell-Capability,
id-GERAN-Classmark.
id-Guaranteed-Rate-Information.
id-HARO-Preamble-Mode-Activation-Indicator,
id-HCS-Prio.
id-Inter-Frequency-Cell-Information,
id-Load-Value,
id-Load-Value-IncrDecrThres,
id-Neighbouring-GSM-CellInformation,
id-Neighbouring-UMTS-CellInformationItem,
id-neighbouring-LCR-TDD-CellInformation,
id-NRT-Load-Information-Value,
id-NRT-Load-Information-Value-IncrDecrThres,
id-OnModification.
id-Received-Total-Wideband-Power-Value,
id-Received-Total-Wideband-Power-Value-IncrDecrThres.
id-RT-Load-Value.
id-RT-Load-Value-IncrDecrThres,
id-SFNSFNMeasurementThresholdInformation.
id-SNA-Information,
id-TrafficClass.
id-Transmitted-Carrier-Power-Value.
id-Transmitted-Carrier-Power-Value-IncrDecrThres,
id-TUTRANGPSMeasurementThresholdInformation,
id-UL-Timeslot-ISCP-Value,
id-UL-Timeslot-ISCP-Value-IncrDecrThres,
maxNrOfLevels.
maxNrOfMeasNCell,
maxNrOfMeasNCell-1,
id-MessageStructure,
id-RestrictionStateIndicator,
id-Rx-Timing-Deviation-Value-LCR,
id-TransportLayerAddress,
id-Transmission-Mode-Information,
id-TypeOfError,
id-Angle-Of-Arrival-Value-LCR,
id-IPDL-TDD-ParametersLCR,
id-DSCH-InitialWindowSize,
id-Maximum-DL-Power-TimeslotLCR-InformationItem,
id-MBMS-Bearer-Service-Full-Address,
id-MBMS-Neighbouring-Cell-Information,
id-MBMS-RLC-Sequence-Number-Information,
id-MBSFN-Cluster-Identity,
id-MBSFN-Scheduling-Transmission-Time-Interval-Info-List,
id-MCCH-Configuration-Info,
id-MCCH-Message-List,
id-Minimum-DL-Power-TimeslotLCR-InformationItem,
id-HS-SICH-Reception-Quality,
id-HS-SICH-Reception-Quality-Measurement-Value,
id-HS-PDSCH-Code-Change-Grant,
```

```
id-HS-PDSCH-Code-Change-Indicator,
id-ExtendedGSMCellIndividualOffset.
id-Unidirectional-DCH-Indicator.
id-RTLoadValue.
id-RLC-Sequence-Number,
id-NRTLoadInformationValue.
id-Satellite-Almanac-Information-ExtItem.
id-TnlOos,
id-UpPTSInterferenceValue,
id-NACC-Related-Data,
id-HARO-Preamble-Mode,
id-User-Plane-Congestion-Fields-Inclusion,
id-FrequencyBandIndicator,
id-PLCCH-Information-UL-TimeslotLCR-Info.
id-CellCapabilityContainer-TDD768,
id-hSSCCH-TDD-Specific-InfoList-Response768,
id-hSPDSCH-TDD-Specific-InfoList-Response768,
id-Rx-Timing-Deviation-Value-768,
id-UEMeasurementValueTransmittedPowerList768,
id-UEMeasurementValueTimeslotISCPList768,
id-E-DCH-PowerOffset-for-SchedulingInfo,
id-Rx-Timing-Deviation-Value-ext,
id-TrCH-SrcStatisticsDescr.
id-eDCH-MACdFlow-Retransmission-Timer-LCR.
id-MIMO-ActivationIndicator,
id-MIMO-InformationResponse,
id-MIMO-Mode-Indicator,
id-MIMO-N-M-Ratio,
id-SixteenOAM-UL-Operation-Indicator,
id-E-AGCH-Table-Choice,
id-E-TFCI-Boost-Information,
id-E-DPDCH-PowerInterpolation,
id-HSDSCH-MACdPDUSizeFormat,
id-MaximumMACdPDU-SizeExtended,
id-GANSS-Common-Data,
id-GANSS-Information,
id-GANSS-Generic-Data,
id-TUTRANGANSSMeasurementThresholdInformation,
id-TUTRANGANSSMeasurementValueInformation,
id-HARO-MemoryPartitioningInfoExtForMIMO,
id-Ext-Reference-E-TFCI-PO,
id-Ext-Max-Bits-MACe-PDU-non-scheduled,
id-Multiple-PLMN-List,
id-TransportBearerNotSetupIndicator,
id-TransportBearerNotRequestedIndicator,
id-UARFCNforNt,
id-LCRTDD-uplink-Physical-Channel-Capability,
id-number-Of-Supported-Carriers,
id-HSSICH-SIRTarget,
id-HSSICH-TPC-StepSize,
id-tSN-Length,
id-HS-SICH-ID-Extension,
id-multipleFreq-HSPDSCH-InformationList-ResponseTDDLCR,
id-multicarrier-number,
```

```
id-UpPCH-InformationList-LCRTDD,
id-UpPCH-InformationItem-LCRTDD,
id-Max-UE-DTX-Cvcle.
id-Default-Serving-Grant-in-DTX-Cycle2,
id-SixtyfourOAM-UsageAllowedIndicator,
id-SixtyfourOAM-DL-UsageIndicator,
id-UE-Capabilities-Info,
id-Extended-E-DCH-LCRTDD-PhysicalLayerCategory,
id-Continuous-Packet-Connectivity-HS-SCCH-Less-Deactivate-Indicator,
id-E-DCH-MACdPDUSizeFormat,
id-E-PUCH-PowerControlGAP,
id-MaximumNumber-Of-Retransmission-For-SchedulingInfo-LCRTDD,
id-E-DCH-RetransmissionTimer-For-SchedulingInfo-LCRTDD,
id-HSDSCH-TBSizeTableIndicator,
id-E-DCH-DL-Control-Channel-Change-Information,
id-E-DCH-DL-Control-Channel-Grant-Information,
id-DGANSS-Corrections-Reg,
id-UE-with-enhanced-HS-SCCH-support-indicator,
id-EnhancedHSServingCC-Abort,
id-GANSS-Time-ID.
id-GANSS-AddIonoModelReq,
id-GANSS-EarthOrientParaReg,
id-GANSS-AddNavigationModelsReg.
id-GANSS-AddUTCModelsReg,
id-GANSS-AuxInfoReq,
id-GANSS-SBAS-ID,
id-GANSS-ID,
id-GANSS-Additional-Ionospheric-Model,
id-GANSS-Earth-Orientation-Parameters,
id-GANSS-Additional-Time-Models.
id-GANSS-Additional-Navigation-Models,
id-GANSS-Additional-UTC-Models,
id-GANSS-Auxiliary-Information,
id-GANSS-alm-keplerianNAVAlmanac,
id-GANSS-alm-keplerianReducedAlmanac,
id-GANSS-alm-keplerianMidiAlmanac,
id-GANSS-alm-keplerianGLONASS.
id-GANSS-alm-ecefSBASAlmanac,
id-Secondary-Serving-Cell-List,
id-MinimumReducedE-DPDCH-GainFactor,
id-E-AGCH-UE-Inactivity-Monitor-Threshold,
id-MACes-Maximum-Bitrate-LCR,
id-MultiCarrier-HSDSCH-Physical-Layer-Category,
id-MIMO-SFMode-For-HSPDSCHDualStream,
id-MIMO-SFMode-Supported-For-HSPDSCHDualStream,
id-MIMO-ReferenceSignal-InformationListLCR,
id-DL-RLC-PDU-Size-Format,
id-UE-SupportIndicatorExtension,
id-power-offset-for-S-CPICH-for-MIMO,
id-power-offset-for-S-CPICH-for-MIMO-Request-Indicator,
id-Dual-Band-Secondary-Serving-Cell-List,
id-Single-Stream-MIMO-ActivationIndicator,
id-Single-Stream-MIMO-Mode-Indicator,
```

RNSAP-PROTOCOL-EXTENSION

```
id-Additional-EDCH-Preconfiguration-Information,
    id-MulticellEDCH-Information.
    id-EDCH-Indicator.
    id-DiversityMode,
    id-TransmitDiversityIndicator,
    id-NonCellSpecificTxDiversity,
    id-CellCapabilityContainerExtension-FDD,
    id-HSDSCH-Physical-Layer-Category,
    id-TS0-HS-PDSCH-Indication-LCR,
    id-UE-TS0-CapabilityLCR,
    id-DGNSS-ValidityPeriod,
    id-UE-AggregateMaximumBitRate-Enforcement-Indicator,
    id-Out-of-Sychronization-Window,
    id-MulticellEDCH-RL-SpecificInformation,
    id-Continuous-Packet-Connectivity-DTX-DRX-Information,
    id-Additional-E-DCH-Non-Serving-RL-Preconfiguration-Setup,
    id-Additional-E-DCH-New-non-serving-RL-E-DCH-FDD-DL-Control-Channel-InfoList,
    id-OrdinalNumberOfFrequency,
    id-Multicell-EDCH-Restriction,
    id-CellListValidityIndicator,
    id-completeAlmanacProvided,
    id-ganss-Delta-T,
    id-CellCapabilityContainerExtension-TDD-LCR,
    id-SNPL-Carrier-Group-Indicator,
    id-HS-SCCH-Inactivity-Threshold-for-UE-DRX-Cycle-LCR-Ext,
    id-Measurement-Power-Offset,
    id-Multi-Carrier-E-DCH-LCRTDD-PhysicalLayerCategory,
    id-Neighbouring-UMTS-CellInformationExtensionItem,
    id-EventH,
    id-UMTS-Cells-Info,
    id-ANRReportIndication,
    id-ANR-Cell-Information,
    id-Affected-HSDSCH-Serving-Cell-List,
    id-Support-of-Dynamic-DTXDRX-Related-HS-SCCH-Order,
    id-UE-RF-Band-CapabilityLCR,
    id-PCI,
    id-TAC,
    id-PLMN-List
FROM RNSAP-Constants
    Criticality,
    ProcedureID,
    ProtocolIE-ID,
   TransactionID,
    TriggeringMessage
FROM RNSAP-CommonDataTypes
    ProtocolIE-Single-Container{},
    ProtocolExtensionContainer{},
    RNSAP-PROTOCOL-IES,
```

```
FROM RNSAP-Containers;
-- A
AccessPointName
                   ::= OCTET STRING (SIZE (1..255))
AckNack-RepetitionFactor ::= INTEGER (1..4,...)
-- Step: 1
Ack-Power-Offset ::= INTEGER (0..8,...)
-- According to mapping in TS 25.213 [21] subclause 4.2.1
ActivationInformation ::= SEQUENCE (SIZE (1..maxNrOfEDCH-1)) OF ActivationInformationItem
ActivationInformationItem ::= SEOUENCE {
    uU-ActivationState Uu-ActivationState,
                                                    ProtocolExtensionContainer { { ActivationInformationItem-ExtIEs} }
    iE-Extensions
   OPTIONAL,
    . . .
ActivationInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Active-MBMS-Bearer-Service-ListFDD ::= SEOUENCE (SIZE (1..maxNrOfActiveMBMSServices)) OF MBMS-Bearer-ServiceItemFDD
Active-MBMS-Bearer-Service-ListFDD-PFL ::= SEOUENCE (SIZE (1..maxNrOfActiveMBMSServices)) OF MBMS-Bearer-ServiceItemFDD-PFL
Active-MBMS-Bearer-Service-ListTDD ::= SEQUENCE (SIZE (1..maxNrOfActiveMBMSServices)) OF MBMS-Bearer-ServiceItemTDD
Active-MBMS-Bearer-Service-ListTDD-PFL ::= SEQUENCE (SIZE (1..maxNrOfActiveMBMSServices)) OF MBMS-Bearer-ServiceItemTDD-PFL
Active-Pattern-Sequence-Information ::= SEQUENCE {
    cMConfigurationChangeCFN
                                    CFN,
    transmission-Gap-Pattern-Sequence-Status Transmission-Gap-Pattern-Sequence-Status-List
                       ProtocolExtensionContainer { {Active-Pattern-Sequence-Information-ExtIEs} } OPTIONAL,
Active-Pattern-Sequence-Information-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
Additional-EDCH-Cell-Information-Response-RLAddList ::= SEQUENCE (SIZE (1..maxNrOfEDCH-1)) OF Additional-EDCH-Cell-Information-Response-RLAddList
ItemIEs
Additional-EDCH-Cell-Information-Response-RLAdd-ItemIEs ::=SEQUENCE{
    additional-EDCH-FDD-Information-Response
                                                                    Additional-EDCH-FDD-Information-Response-ItemIEs
                                                                                                                        OPTIONAL,
    additional-EDCH-Serving-Cell-Change-Information-Response-RLAdd
                                                                        E-DCH-Serving-cell-change-informationResponse
                                                                                                                                OPTIONAL,
                                    ProtocolExtensionContainer { { Additional-EDCH-Cell-Information-Response-RLAdd-ItemIEs-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
```

```
Additional-EDCH-Cell-Information-Response-RLAdd-ItemIEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Additional-EDCH-Setup-Info ::=SEOUENCE{
    multicell-EDCH-Transport-Bearer-Mode
                                                                            Multicell-EDCH-Transport-Bearer-Mode,
    additional-EDCH-Cell-Information-Setup
                                                                            Additional-EDCH-Cell-Information-Setup.
                                    ProtocolExtensionContainer { { Additional-EDCH-Setup-Info-ExtIEs} } OPTIONAL,
   iE-Extensions
Additional-EDCH-Setup-Info-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
ANRReportIndication ::= SEQUENCE {
    pLMN-Identity
                       PLMN-Identity,
   13-Information
                       L3-Information,
                       ProtocolExtensionContainer { {ANRReportIndication-ExtIEs} } OPTIONAL,
   iE-Extensions
ANRReportIndication-ExtIEs RNSAP-PROTOCOL-EXTENSION ::={
    . . .
Multicell-EDCH-Transport-Bearer-Mode ::= ENUMERATED {
    separate-Iur-Transport-Bearer-Mode,
    uL-Flow-Multiplexing-Mode
Additional-EDCH-Cell-Information-Setup ::= SEQUENCE (SIZE (1..maxNrOfEDCH-1)) OF Additional-EDCH-FDD-Setup-Cell-Information
Additional-EDCH-FDD-Setup-Cell-Information ::=SEQUENCE{
    additional-EDCH-UL-DPCH-Information-Setup
                                                                            Additional-EDCH-UL-DPCH-Information-Setup,
    additional-EDCH-RL-Specific-Information-To-Setup
                                                                            Additional-EDCH-RL-Specific-Information-To-Setup-List,
    additional-EDCH-FDD-Information
                                                                            Additional-EDCH-FDD-Information
                                                                            Additional-EDCH-F-DPCH-Information,
    additional-EDCH-F-DPCH-Information-Setup
    multicellEDCH-Information
                                                                            MulticellEDCH-Information
                                                                                                         OPTIONAL,
   iE-Extensions
                                    ProtocolExtensionContainer { { Additional-EDCH-FDD-Setup-Cell-Information-ExtIEs} } OPTIONAL,
Additional-EDCH-FDD-Setup-Cell-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
Additional-EDCH-UL-DPCH-Information-Setup ::=SEQUENCE{
   ul-ScramblingCode
                                            UL-ScramblingCode,
   ul-SIR-Target
                                            UL-SIR
                                                        OPTIONAL.
   iE-Extensions
                                    ProtocolExtensionContainer { Additional-EDCH-UL-DPCH-Information-Setup-ExtIEs} } OPTIONAL,
    . . .
```

873

```
Additional-EDCH-UL-DPCH-Information-Setup-ExtIEs
                                                    RNSAP-PROTOCOL-EXTENSION ::= {
Additional-EDCH-F-DPCH-Information ::=SEQUENCE{
    fdd-TPC-DownlinkStepSize
                                        FDD-TPC-DownlinkStepSize,
   limitedPowerIncrease
                                        LimitedPowerIncrease,
    innerLoopDLPCStatus
                                        InnerLoopDLPCStatus,
    f-DPCH-SlotFormatSupportRequest
                                        F-DPCH-SlotFormatSupportRequest
                                                                                OPTIONAL,
                                    ProtocolExtensionContainer { { Additional-EDCH-F-DPCH-Information-ExtIEs} } OPTIONAL,
    iE-Extensions
Additional-EDCH-F-DPCH-Information-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
Additional-EDCH-RL-Specific-Information-To-Setup-List ::= SEQUENCE (SIZE (1.. maxNrOfEDCHRLs)) OF Additional-EDCH-RL-Specific-Information-To-
Setup-ItemIEs
Additional-EDCH-RL-Specific-Information-To-Setup-ItemIEs
                                                            ::=SEOUENCE{
    eDCH-Additional-RL-ID
                                        RL-ID,
    c-TD
                                        C-TD
                                                            OPTIONAL,
    firstRLS-indicator
                                        FirstRLS-Indicator,
    propagationDelay
                                        PropagationDelay
                                                                        OPTIONAL,
    initialDL-transmissionPower
                                        DL-Power
                                                                OPTIONAL,
    primaryCPICH-EcNo
                                        PrimaryCPICH-EcNo
                                                                    OPTIONAL,
    e-AGCH-PowerOffset
                                        E-AGCH-PowerOffset
                                                                                    OPTIONAL,
    e-RGCH-PowerOffset
                                        E-RGCH-PowerOffset
                                                                                    OPTIONAL,
    e-HICH-PowerOffset
                                        E-HICH-PowerOffset
                                                                                    OPTIONAL,
    additional-EDCH-MAC-d-Flows-Specific-Info-List
                                                        Additional-EDCH-MAC-d-Flows-Specific-Info-List
                                                                                                                 OPTIONAL,
    multicellEDCH-RL-SpecificInformation
                                                MulticellEDCH-RL-SpecificInformation
                                                                                       OPTIONAL,
    iE-Extensions
                                        ProtocolExtensionContainer { { Additional-EDCH-RL-Specific-Information-To-Setup-ItemIEs-ExtIEs} } OPTIONAL,
Additional-EDCH-RL-Specific-Information-To-Setup-ItemIEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Additional-EDCH-Cell-Information-To-Add-List
                                                ::= SEQUENCE (SIZE (1.. maxNrOfEDCH-1)) OF Additional-EDCH-Cell-Information-To-Add-ItemIEs
Additional-EDCH-Cell-Information-To-Add-ItemIEs::=SEOUENCE{
    additional-EDCH-UL-DPCH-Information-Setup
                                                            Additional-EDCH-UL-DPCH-Information-Addition,
    additional-EDCH-RL-Specific-Information-To-Add-List
                                                            Additional-EDCH-RL-Specific-Information-To-Add-List,
    additional-EDCH-FDD-Information
                                                    Additional-EDCH-FDD-Information
                                                                                        OPTIONAL,
    multicellEDCH-Information
                                                    MulticellEDCH-Information
                                                                                    OPTIONAL,
    iE-Extensions
                                        ProtocolExtensionContainer { Additional-EDCH-Cell-Information-To-Add-ItemIEs-ExtIEs} } OPTIONAL,
    . . .
Additional-EDCH-Cell-Information-To-Add-ItemIEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
Additional-EDCH-UL-DPCH-Information-Addition ::=SEQUENCE{
    ul-SIR-Target
                                            UL-SIR.
    iE-Extensions
                                    ProtocolExtensionContainer { { Additional-EDCH-UL-DPCH-Information-Addition-ExtIEs} } OPTIONAL,
Additional-EDCH-UL-DPCH-Information-Addition-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Additional-EDCH-RL-Specific-Information-To-Add-List
                                                     ::= SEQUENCE (SIZE (1.. maxNrOfEDCHRLs)) OF Additional-EDCH-RL-Specific-Information-To-Add-
ItemIEs
Additional-EDCH-RL-Specific-Information-To-Add-ItemIEs ::=SEQUENCE{
    eDCH-Additional-RL-ID
                                       RL-ID,
    c-ID
                                       C-ID,
    primaryCPICH-EcNo
                                       PrimaryCPICH-EcNo
                                                                    OPTIONAL,
    e-AGCH-PowerOffset
                                       E-AGCH-PowerOffset
                                                                                    OPTIONAL,
    e-RGCH-PowerOffset
                                       E-RGCH-PowerOffset
                                                                                    OPTIONAL,
    e-HICH-PowerOffset
                                       E-HICH-PowerOffset
                                                                                    OPTIONAL,
    additional-EDCH-MAC-d-Flows-Specific-Info-List
                                                       Additional-EDCH-MAC-d-Flows-Specific-Info-List
                                                                                                                OPTIONAL,
                                               MulticellEDCH-RL-SpecificInformation
    multicellEDCH-RL-SpecificInformation
                                                                                            OPTIONAL,
                                       ProtocolExtensionContainer { { Additional-EDCH-RL-Specific-Information-To-Add-ItemIEs-ExtIEs} } OPTIONAL.
   iE-Extensions
Additional-EDCH-RL-Specific-Information-To-Add-ItemIEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
Additional-EDCH-RL-Specific-Information-To-Modify-List ::= SEQUENCE (SIZE (1..maxNrOfEDCHRLs)) OF Additional-EDCH-RL-Specific-Information-To-
Modify-ItemIEs
Additional-EDCH-RL-Specific-Information-To-Modify-ItemIEs ::=SEOUENCE{
    eDCH-Additional-RL-ID
                                       RL-ID,
    e-AGCH-PowerOffset
                                       E-AGCH-PowerOffset
                                                                                    OPTIONAL,
    e-RGCH-PowerOffset
                                       E-RGCH-PowerOffset
                                                                                    OPTIONAL,
    e-HICH-PowerOffset
                                       E-HICH-PowerOffset
                                                                                    OPTIONAL,
    additional-EDCH-MAC-d-Flows-Specific-Info-List
                                                       Additional-EDCH-MAC-d-Flows-Specific-Info-List
                                                                                                                OPTIONAL,
    multicellEDCH-RL-SpecificInformation
                                               MulticellEDCH-RL-SpecificInformation
                                                                                            OPTIONAL,
                                       ProtocolExtensionContainer { { Additional-EDCH-RL-Specific-Information-To-Modify-ItemIEs-ExtIEs} }
    iE-Extensions
OPTIONAL,
Additional-EDCH-RL-Specific-Information-To-Modify-ItemIEs-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
Additional-EDCH-FDD-Information ::=SEQUENCE{
    hARO-Process-Allocation-Scheduled-2ms-EDCH
                                                    HARO-Process-Allocation-2ms-EDCH
    OPTIONAL,
```

```
e-DCH-Maximum-Bitrate
                                                    E-DCH-Maximum-Bitrate
    OPTIONAL.
    e-DCH-Processing-Overload-Level
                                                    E-DCH-Processing-Overload-Level
    OPTIONAL,
    e-DCH-Min-Set-E-TFCI
                                                    E-TFCI
    OPTIONAL,
                                        ProtocolExtensionContainer { { Additional-EDCH-FDD-Information-ExtIEs} } OPTIONAL,
    iE-Extensions
Additional-EDCH-FDD-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Additional-EDCH-MAC-d-Flows-Specific-Info-List ::= SEOUENCE (SIZE (1..maxNrOfEDCHMACdFlows)) OF Additional-EDCH-MAC-d-Flows-Specific-Info
Additional-EDCH-MAC-d-Flows-Specific-Info ::= SEQUENCE {
    e-DCH-MACdFlow-ID
                                                    EDCH-MACdFlow-ID,
    bindingID
                                                    BindingID
    OPTIONAL,
    transportLayerAddress
                                                    TransportLayerAddress
    OPTIONAL,
                                                    ProtocolExtensionContainer { { Additional-EDCH-MAC-d-Flows-Specific-Info-ExtIEs} }
    iE-Extensions
       OPTIONAL,
Additional-EDCH-MAC-d-Flows-Specific-Info-ExtIEs
                                                    RNSAP-PROTOCOL-EXTENSION ::= {
Additional-EDCH-MAC-d-Flow-Specific-Information-Response-List::= SEQUENCE (SIZE (1..maxNrOfEDCHMACdFlows)) OF Additional-EDCH-MAC-d-Flows-Specific-
Info-Response
Additional-EDCH-MAC-d-Flows-Specific-Info-Response ::= SEQUENCE {
    e-DCH-MACdFlow-ID
                                            EDCH-MACdFlow-ID,
   bindingID
                                            BindingID
                                                                                                                                        OPTIONAL,
    transportLayerAddress
                                            TransportLayerAddress
                                                                                                                                        OPTIONAL,
                                            ProtocolExtensionContainer { { Additional-EDCH-MAC-d-Flows-Specific-Info-Response-ExtIEs}
    iE-Extensions
    OPTIONAL,
    . . .
Additional-EDCH-MAC-d-Flows-Specific-Info-Response-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
Additional-EDCH-Cell-Information-Response-List ::= SEQUENCE (SIZE (1..maxNrOfEDCH-1)) OF Additional-EDCH-FDD-Information-Response-ItemIEs
Additional-EDCH-FDD-Information-Response-ItemIEs
                                                    ::=SEQUENCE{
                                                                            EDCH-Additional-RL-Specific-Information-Response-List,
    eDCH-Additional-RL-Specific-Information-Response
   iE-Extensions
                                    ProtocolExtensionContainer { Additional-EDCH-FDD-Information-Response-ItemIEs-ExtIEs} } OPTIONAL,
```

```
Additional-EDCH-FDD-Information-Response-ItemIEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
EDCH-Additional-RL-Specific-Information-Response-List ::= SEQUENCE (SIZE (1..maxNrOfEDCHRLs)) OF EDCH-Additional-RL-Specific-Information-
Response-ItemIEs
EDCH-Additional-RL-Specific-Information-Response-ItemIEs
                                                             ::=SEQUENCE{
    eDCH-Additional-RL-ID
                                        RL-ID,
    received-total-wide-band-power
                                                    Received-total-wide-band-power,
    dL-PowerBalancing-ActivationIndicator
                                                    DL-PowerBalancing-ActivationIndicator OPTIONAL,
    rL-Set-ID
                                                    RL-Set-ID,
    e-DCH-RL-Set-ID
                                                    RL-Set-ID,
    eDCH-FDD-DL-ControlChannelInformation
                                                    EDCH-FDD-DL-ControlChannelInformation,
    dl-CodeInformation
                                                    FDD-DL-CodeInformation,
    additional-EDCH-MAC-d-Flow-Specific-Information-Response-List
    Additional-EDCH-MAC-d-Flow-Specific-Information-Response-List OPTIONAL,
    hARO-Process-Allocation-Scheduled-2ms-EDCH
                                                    HARO-Process-Allocation-2ms-EDCH
                                                                                             OPTIONAL,
    maxUL-SIR
                                                    UL-SIR,
    minUL-SIR
                                                    UL-SIR,
    maximumAllowedULTxPower
                                                    MaximumAllowedULTxPower,
    maximumDL-power
                                                    DL-Power,
    minimumDL-power
                                                    DL-Power,
    primaryScramblingCode
                                                    PrimaryScramblingCode
                                                                                             OPTIONAL,
    uL-UARFCN
                                                    UARFCN
                                                                                             OPTIONAL,
    dL-UARFCN
                                                    UARFCN
                                                                                             OPTIONAL,
    primaryCPICH-Power
                                                    PrimaryCPICH-Power,
    pC-Preamble
                                                    PC-Preamble,
    primary-CPICH-Usage-For-Channel-Estimation
                                                    Primary-CPICH-Usage-For-Channel-Estimation
                                                                                                  OPTIONAL,
    secondary-CPICH-Information
                                                    Secondary-CPICH-Information
                                                                                             OPTIONAL,
    f-DPCH-SlotFormat
                                                    F-DPCH-SlotFormat
                                                                                             OPTIONAL,
    iE-Extensions
                                    ProtocolExtensionContainer { { EDCH-Additional-RL-Specific-Information-Response-ItemIEs-ExtIEs} } OPTIONAL,
    . . .
EDCH-Additional-RL-Specific-Information-Response-ItemIEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Additional-EDCH-Cell-Information-Response-RLReconf-List::= SEQUENCE (SIZE (1..maxNrOfEDCH-1)) OF Additional-EDCH-FDD-Information-Response-RLReconf-
Items
Additional-EDCH-FDD-Information-Response-RLReconf-Items::=SEQUENCE{
    eDCH-Additional-RL-Specific-Information-Response
                                                                             EDCH-Additional-RL-Specific-Information-Response-List
    OPTIONAL,
    eDCH-Additional-RL-Specific-Modified-Information-Response
                                                                     EDCH-Additional-RL-Specific-Modified-Information-Response-List
    OPTIONAL,
    iE-Extensions
                                    ProtocolExtensionContainer { { Additional-EDCH-FDD-Information-Response-RLReconf-Items-ExtIEs} } OPTIONAL,
Additional-EDCH-FDD-Information-Response-RLReconf-Items-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
EDCH-Additional-RL-Specific-Modified-Information-Response-List ::= SEQUENCE (SIZE (1..maxNrOfEDCHRLs)) OF EDCH-Additional-RL-Specific-Modified-
Information-Response-ItemIEs
EDCH-Additional-RL-Specific-Modified-Information-Response-ItemIEs ::=SEQUENCE
    eDCH-Additional-RL-ID
    dL-PowerBalancing-UpdatedIndicator
                                                    DL-PowerBalancing-UpdatedIndicator
                                                                                            OPTIONAL,
    eDCH-FDD-DL-ControlChannelInformation
                                                    EDCH-FDD-DL-ControlChannelInformation
                                                                                                OPTIONAL,
    additional-EDCH-MAC-d-Flow-Specific-Information-Response-List
                                                                            Additional-EDCH-MAC-d-Flow-Specific-Information-Response-List
    OPTIONAL,
   hARO-Process-Allocation-Scheduled-2ms-EDCH
                                                    HARO-Process-Allocation-2ms-EDCH
                                                                                            OPTIONAL,
    maxUL-SIR
                                    UL-SIR
                                                OPTIONAL,
   minUL-SIR
                                    UL-SIR
                                                OPTIONAL,
    maximumDL-power
                                        DL-Power
                                                        OPTIONAL.
    minimumDL-power
                                        DI.-Power
                                                        OPTIONAL.
                                                                Primary-CPICH-Usage-For-Channel-Estimation
    primary-CPICH-Usage-For-Channel-Estimation
                                                                                                                                        OPTIONAL,
    secondary-CPICH-Information-Change
                                            Secondary-CPICH-Information-Change
                                                                                        OPTIONAL,
    f-DPCH-SlotFormat
                                        F-DPCH-SlotFormat
                                                                                     OPTIONAL,
    iE-Extensions
                                    ProtocolExtensionContainer { { EDCH-Additional-RL-Specific-Modified-Information-Response-ItemIEs-ExtIEs} }
OPTIONAL,
    . . .
EDCH-Additional-RL-Specific-Modified-Information-Response-ItemIEs-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
Additional-EDCH-Cell-Information-ConfigurationChange-List ::= SEQUENCE (SIZE (1..maxNrOfEDCH-1)) OF Additional-EDCH-ConfigurationChange-Info-
Additional-EDCH-ConfigurationChange-Info-ItemIEs
                                                    ::=SEOUENCE{
    additional-EDCH-UL-DPCH-Information-Modify
                                                                        Additional-EDCH-UL-DPCH-Information-Modify
                                                                                                                                OPTIONAL,
    additional-EDCH-RL-Specific-Information-To-Add
                                                                        Additional-EDCH-RL-Specific-Information-To-Add-List
                                                                                                                                        OPTIONAL,
    additional-EDCH-RL-Specific-Information-To-Modify
                                                                        Additional-EDCH-RL-Specific-Information-To-Modify-List OPTIONAL,
    additional-EDCH-FDD-Information-To-Modify
                                                                        Additional-EDCH-FDD-Information
                                                                                                                 OPTIONAL,
                                                                        Additional-EDCH-F-DPCH-Information
    additional-EDCH-F-DPCH-Information-Modify
                                                                                                                         OPTIONAL,
    multicellEDCH-Information
                                                                        MulticellEDCH-Information
                                                                                                         OPTIONAL,
                                    ProtocolExtensionContainer { Additional-EDCH-ConfigurationChange-Info-ItemIEs-ExtIEs} } OPTIONAL,
    iE-Extensions
Additional-EDCH-ConfigurationChange-Info-ItemIEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Additional-EDCH-UL-DPCH-Information-Modify
                                                ::=SEOUENCE {
    ul-ScramblingCode
                                            UL-ScramblingCode
                                                                OPTIONAL.
    ul-SIR-Target
                                                                OPTIONAL,
    iE-Extensions
                                            ProtocolExtensionContainer { { Additional-EDCH-UL-DPCH-Information-Modify-ExtIEs} } OPTIONAL,
Additional-EDCH-UL-DPCH-Information-Modify-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
```

```
Additional-EDCH-Cell-Information-Removal-List ::= SEQUENCE (SIZE (1..maxNrOfEDCH-1)) OF Additional-EDCH-Cell-Information-Removal-Info-ItemIEs
Additional-EDCH-Cell-Information-Removal-Info-ItemIEs ::=SEQUENCE{
        rL-on-Secondary-UL-Frequency
                                                                                                                             RL-on-Secondary-UL-Frequency,
        iE-Extensions
                                                                           ProtocolExtensionContainer { { Additional-EDCH-Cell-Information-Removal-Info-ItemIEs-ExtIEs} } OPTIONAL,
Additional-EDCH-Cell-Information-Removal-Info-ItemIEs-ExtIEs
                                                                                                                                     RNSAP-PROTOCOL-EXTENSION ::= {
RL-on-Secondary-UL-Frequency ::= ENUMERATED {
        remove,
Additional-EDCH-FDD-Update-Information ::=SEQUENCE{
        hARQ-Process-Allocation-Scheduled-2ms-EDCH
                                                                                                                                              HARO-Process-Allocation-2ms-EDCH
                                                                                                                                                                                                                                                                                          OPTIONAL,
        additional-EDCH-DL-Control-Channel-Change-Information
                                                                                                                                              Additional-EDCH-DL-Control-Channel-Change-Information-List
        OPTIONAL,
        iE-Extensions
                                                                           ProtocolExtensionContainer { { Additional-EDCH-FDD-Update-Information-ExtIEs} } OPTIONAL.
Additional-EDCH-FDD-Update-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Additional-EDCH-DL-Control-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Channel-Cha
Info-ItemIEs
Additional-EDCH-DL-Control-Channel-Change-Info-ItemIEs ::=SEQUENCE{
        eDCH-Additional-RL-ID
                                                                                  RL-ID,
                                                                                   ProtocolExtensionContainer { { Additional-EDCH-DL-Control-Channel-Change-Info-ItemIEs-ExtIEs} } OPTIONAL,
        iE-Extensions
Additional-EDCH-DL-Control-Channel-Change-Info-ItemIEs-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
AdditionalPreferredFrequency ::= SEQUENCE (SIZE (1..maxNrOfAddFreq)) OF AdditionalPreferredFrequencyItem
AdditionalPreferredFrequencyItem ::= SEQUENCE {
        dL-UARFCN
                                                                           UARFCN,
        correspondingCells
                                                                           CorrespondingCells,
        iE-Extensions
                                                                           ProtocolExtensionContainer { AdditionalPreferredFrequencyItem-ExtIEs} } OPTIONAL,
```

```
AdditionalPreferredFrequencyItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
AdjustmentPeriod
                           ::= INTEGER(1..256)
-- Unit Frame
AffectedUEInformationForMBMS
                               ::= SEOUENCE (SIZE (1..maxNrOfUEs)) OF S-RNTI
AllocationRetentionPriority ::= SEQUENCE {
    priorityLevel
                               PriorityLevel,
    pre-emptionCapability
                               Pre-emptionCapability,
    pre-emptionVulnerability
Pre-emptionVulnerability,
    iE-Extensions
                         ProtocolExtensionContainer { {AllocationRetentionPriority-ExtIEs} } OPTIONAL,
AllocationRetentionPriority-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Allowed-Rate-Information ::= SEOUENCE {
                           Allowed-Rate OPTIONAL,
    allowed-UL-Rate
    allowed-DL-Rate
                           Allowed-Rate OPTIONAL,
    iE-Extensions
                           ProtocolExtensionContainer { {Allowed-Rate-Information-ExtIEs} } OPTIONAL,
Allowed-Rate-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Allowed-Rate
                      ::= INTEGER (1..maxNrOfTFs)
-- "1": TFI 0, "2": TFI 1, "3": TFI 2, ...
AllowedOueuingTime
                         ::= INTEGER (1..60)
-- seconds
                           ::= INTEGER (0..8)
AlphaValue
-- Actual value = Alpha / 8
AlternativeFormatReportingIndicator ::= ENUMERATED {
   alternativeFormatAllowed,...
Angle-Of-Arrival-Value-LCR ::= SEQUENCE {
    aOA-LCR
                           AOA-LCR,
    aOA-LCR-Accuracy-Class AOA-LCR-Accuracy-Class,
                           ProtocolExtensionContainer { {Angle-Of-Arrival-Value-LCR-ExtIEs} } OPTIONAL,
    iE-Extensions
```

```
Angle-Of-Arrival-Value-LCR-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
ANR-Cell-Information
                        ::= SEOUENCE
    rNC-ID
                                     RNC-ID,
    1AC
                                    LAC
                                                                 OPTIONAL,
    rAC
                                    RAC
                                                                 OPTIONAL,
    aNR-FDD-CellInformation
                                     ANR-FDD-CellInformation
                                                                 OPTIONAL,
    aNR-TDD-CellInformation
                                     ANR-TDD-CellInformation
                                                                 OPTIONAL,
    aNR-LCR-TDD-CellInformation
                                     ANR-LCR-TDD-CellInformation OPTIONAL,
    extended-RNC-ID
                                     Extended-RNC-ID
                                                                 OPTIONAL,
                                     ProtocolExtensionContainer { { ANR-Cell-Information-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
ANR-Cell-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
ANR-FDD-CellInformation ::= SEQUENCE {
                                        PrimaryCPICH-Power
    primaryCPICH-Power
                                                                              OPTIONAL,
    txDiversitvIndicator
                                        TxDiversitvIndicator,
    sTTD-SupportIndicator
                                         STTD-SupportIndicator
                                                                             OPTIONAL,
    closedLoopModel-SupportIndicator
                                         ClosedLoopModel-SupportIndicator
                                                                             OPTIONAL,
    restrictionStateIndicator
                                        RestrictionStateIndicator
                                                                             OPTIONAL,
    dpc-ModeChangeSupportIndicator
                                        DPC-Mode-Change-SupportIndicator
                                                                             OPTIONAL,
    cellCapabilityContainerFDD
                                        CellCapabilityContainer-FDD
                                                                             OPTIONAL,
    sNA-Information
                                         SNA-Information
                                                                             OPTIONAL,
    frequencyBandIndicator
                                        FrequencyBandIndicator
                                                                             OPTIONAL,
    max-UE-DTX-Cycle
                                        Max-UE-DTX-Cycle
                                                                             OPTIONAL,
    aNR-Multiple-PLMN-List
                                         ANR-Multiple-PLMN-List
                                                                             OPTIONAL,
                                         Secondary-Serving-Cell-List
    secondaryServingCellList
                                                                             OPTIONAL,
    dualBandSecondaryServingCellList
                                         Secondary-Serving-Cell-List
                                                                              OPTIONAL,
    cellCapabilityContainerExtensionFDD CellCapabilityContainerExtension-FDD
                                                                                 OPTIONAL,
    iE-Extensions
                                         ProtocolExtensionContainer { { ANR-FDD-CellInformation-ExtIEs} } OPTIONAL,
ANR-FDD-CellInformation-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
ANR-TDD-CellInformation ::= SEQUENCE
    syncCase
                                     SyncCase,
    timeSlot
                                    TimeSlot
                                                                 OPTIONAL
    -- This IE shall be present if Sync Case = Case1 -- ,
    sCH-TimeSlot
                                     SCH-TimeSlot
                                                                 OPTIONAL
    -- This IE shall be present if Sync Case = Case2 -- ,
    sCTD-Indicator
                                    SCTD-Indicator,
    dPCHConstantValue
                                    DPCHConstantValue
                                                                 OPTIONAL,
    pCCPCH-Power
                                    PCCPCH-Power
                                                                 OPTIONAL,
    restrictionStateIndicator
                                     RestrictionStateIndicator
                                                                 OPTIONAL,
```

```
cellCapabilityContainerTDD
                                    CellCapabilityContainer-TDD OPTIONAL,
    -- Applicable to 3.84Mcps TDD only
    cellCapabilityContainerTDD768
                                    CellCapabilityContainer-TDD768 OPTIONAL,
    -- Applicable to 7.68Mcps TDD only
    sNA-Information
                                     SNA-Information
                                                                 OPTIONAL.
    aNR-Multiple-PLMN-List
                                    ANR-Multiple-PLMN-List
                                                                 OPTIONAL,
    iE-Extensions
                                    ProtocolExtensionContainer { { ANR-TDD-CellInformation-ExtIEs} } OPTIONAL,
ANR-TDD-CellInformation-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
ANR-LCR-TDD-CellInformation ::= SEQUENCE {
                                                SCTD-Indicator,
    sCTD-Indicator
    dPCHConstantValue
                                                DPCHConstantValue
                                                                                             OPTIONAL,
    pCCPCH-Power
                                                PCCPCH-Power
                                                                                             OPTIONAL,
    restrictionStateIndicator
                                                RestrictionStateIndicator
                                                                                             OPTIONAL,
    cellCapabilityContainerTDD-LCR
                                                CellCapabilityContainer-TDD-LCR
                                                                                             OPTIONAL,
    -- Applicable to 1.28Mcps TDD only
    sNA-Information
                                                SNA-Information
                                                                                             OPTIONAL,
    aNR-Multiple-PLMN-List
                                                ANR-Multiple-PLMN-List
                                                                                             OPTIONAL,
    cellCapabilityContainerExternsionTDD-LCR
                                                CellCapabilityContainerExtension-TDD-LCR
                                                                                             OPTIONAL,
    iE-Extensions
                                                ProtocolExtensionContainer { { ANR-LCR-TDD-CellInformation-ExtIEs} } OPTIONAL,
    . . .
ANR-LCR-TDD-CellInformation-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
ANR-Multiple-PLMN-List ::= SEOUENCE {
   list-Of-PLMNs
                       List-Of-PLMNs
                                                                                     OPTIONAL,
                        ProtocolExtensionContainer { { ANR-Multiple-PLMN-List-ExtIEs} } OPTIONAL,
    iE-Extensions
ANR-Multiple-PLMN-List-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
AOA-LCR ::= INTEGER (0..719)
-- Angle Of Arrival for 1.28Mcps TDD
AOA-LCR-Accuracy-Class ::= ENUMERATED {a,b,c,d,e,f,g,h,...}
AntennaColocationIndicator ::= ENUMERATED {
    co-located,
    . . .
```

```
BadSatellites ::= SEOUENCE {
    badSatelliteInformation
                                SEQUENCE (SIZE (1..maxNoSat)) OF
        SEQUENCE {
           badSAT-ID
                                        SAT-ID,
           iE-Extensions
                                        ProtocolExtensionContainer { { BadSatelliteInformation-ExtIEs} }
                                                                                                                OPTIONAL,
       },
                                ProtocolExtensionContainer { { BadSatellites-ExtIEs} }
    iE-Extensions
                                                                                            OPTIONAL,
BadSatelliteInformation-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
BadSatellites-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Band-Indicator ::= ENUMERATED {
   dcs1800Band,
   pcs1900Band,
BCC ::= BIT STRING (SIZE (3))
BCCH-ARFCN ::= INTEGER (0..1023)
BetaCD ::= INTEGER (0..15)
                       ::= OCTET STRING (SIZE (1..4,...))
-- If the Binding ID includes an UDP port, the UDP port is included in octet 1 and 2.
                       ::= INTEGER (-63..0)
BLER
-- Step 0.1 (Range -6.3..0). It is the Log10 of the BLER
SCTD-Indicator ::= ENUMERATED {
   active,
    inactive
BSIC ::= SEQUENCE {
    nCC
                NCC,
    bCC
                BCC
BundlingModeIndicator ::= ENUMERATED {
    bundling,
    no-bundling
```

```
BurstModeParameters ::= SEQUENCE {
   burstStart
                 INTEGER (0..15),
    burstLength INTEGER (10..25),
                    INTEGER (1..16),
    burstFreq
    iE-Extensions
                                ProtocolExtensionContainer { { BurstModeParameters-ExtIEs} }
                                                                                                   OPTIONAL,
BurstModeParameters-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
-- C
Cause ::= CHOICE {
    radioNetwork
                        CauseRadioNetwork,
                        CauseTransport,
    transport
    protocol
                        CauseProtocol,
    misc
                        CauseMisc,
    . . .
CauseMisc ::= ENUMERATED {
    control-processing-overload,
    hardware-failure,
    om-intervention,
    not-enough-user-plane-processing-resources,
    unspecified,
    . . .
CauseProtocol ::= ENUMERATED {
    transfer-syntax-error,
    abstract-syntax-error-reject,
    abstract-syntax-error-ignore-and-notify,
    message-not-compatible-with-receiver-state,
    semantic-error,
    unspecified,
    abstract-syntax-error-falsely-constructed-message,
CauseRadioNetwork ::= ENUMERATED {
    unknown-C-ID,
    cell-not-available,
    power-level-not-supported,
    ul-scrambling-code-already-in-use,
    dl-radio-resources-not-available,
    ul-radio-resources-not-available,
    measurement-not-supported-for-the-object,
    combining-resources-not-available,
    combining-not-supported,
```

```
reconfiguration-not-allowed,
requested-configuration-not-supported,
synchronisation-failure.
requested-tx-diversity-mode-not-supported,
measurement-temporaily-not-available,
unspecified,
invalid-CM-settings,
reconfiguration-CFN-not-elapsed,
number-of-DL-codes-not-supported,
dedicated-transport-channel-type-not-supported,
dl-shared-channel-type-not-supported,
ul-shared-channel-type-not-supported,
common-transport-channel-type-not-supported,
ul-spreading-factor-not-supported,
dl-spreading-factor-not-supported,
cm-not-supported,
transaction-not-supported-by-destination-node-b,
rl-already-activated-or-alocated,
. . . ,
number-of-UL-codes-not-supported,
cell-reserved-for-operator-use,
dpc-mode-change-not-supported,
information-temporarily-not-available,
information-provision-not-supported-for-the-object,
power-balancing-status-not-compatible,
delayed-activation-not-supported,
rl-timing-adjustment-not-supported,
unknown-RNTI,
measurement-repetition-rate-not-compatible,
ue-not-capable-of-support,
f-dpch-not-supported,
e-dch-not-supported,
continuous-packet-connectivity-dtx-drx-operation-not-supported,
continuous-packet-connectivity-hs-scch-less-operation-not-supported,
mimo-not-supported,
e-dch-tti2ms-not-supported,
continuous-packet-connectivity-DTX-DRX-operation-not-available,
continuous-packet-connectivity-UE-DTX-Cycle-not-available,
mimo-not-available,
sixteenOAM-UL-not-Supported,
hSDSCH-MACdPDU-SizeFormatNotSupported,
f-dpch-slot-format-operation-not-supported,
e-DCH-MACdPDU-SizeFormat-not-available,
e-DPCCH-Power-Boosting-not-supported,
trelocprep-expiry,
directed-retry,
no-Iu-CS-UP-relocation,
reduce-load-in-serving-cell,
relocation-cancelled,
relocation-desirable-for-radio-reasons,
resource-optimisation-relocation,
time-critical-relocation,
traffic-load-in-the-target-cell-higher-than-in-the-source-cell,
sixtyfourOAM-DL-and-MIMO-Combined-not-available,
```

```
multi-Cell-operation-not-available,
    multi-Cell-operation-not-supported,
    semi-Persistent-scheduling-not-supported,
    continuous-Packet-Connectivity-DRX-not-supported,
    continuous-Packet-Connectivity-DRX-not-available,
    enhanced-relocation-not-supported,
    relocation-not-supported-due-to-PUESBINE-feature,
    relocation-failure-in-target-RNC,
    relocation-target-not-allowed,
    requested-ciphering-and-or-integrity-protection-algorithms-not-supported,
    sixtyfourQAM-DL-and-MIMO-Combined-not-supported,
    tx-diversity-for-mimo-on-DL-control-channels-not-available,
    single-Stream-MIMO-not-supported,
    single-Stream-MIMO-not-available,
    multi-Cell-operation-with-MIMO-not-supported,
    multi-Cell-operation-with-MIMO-not-available,
    multi-Cell-EDCH-operation-not-supported,
    multi-Cell-EDCH-operation-not-available,
    multi-Cell-operation-with-Single-Stream-MIMO-not-supported,
    multi-Cell-operation-with-Single-Stream-MIMO-not-available,
    cellSpecificTxDiversityHandlingForMultiCellOperationNotAvailable,
    cellSpecificTxDiversityHandlingForMultiCellOperationNotSupported,
    frequencySpecificCompressedModeNotAvailable
CauseTransport ::= ENUMERATED {
    transport-resource-unavailable,
    unspecified,
CellBased::= SEOUENCE {
    cellIdList
                        CellIdList,
                        ProtocolExtensionContainer { {CellBased-ExtIEs} } OPTIONAL,
    iE-Extensions
CellBased-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
CellIdList ::= SEQUENCE (SIZE (1..maxNrOfCellIds)) OF
    Cell-Id
Cell-Id
            ::= INTEGER (0..268435455)
CellCapabilityContainer-FDD ::= BIT STRING (SIZE (32))
-- First bit: Flexible Hard Split Support Indicator
-- Second bit: Delayed Activation Support Indicator
-- Third bit: HS-DSCH Support Indicator
-- Fourth bit: DSCH Support Indicator
-- Fifth bit: F-DPCH Support Indicator
```

-- sixth bit: E-DCH Support Indicator -- Seventh bit: E-DCH TTI2ms Support Indicator -- Eighth bit: E-DCH 2sf2and2sf4 and all inferior SFs Support Indicator -- Ninth bit: E-DCH 2sf2 and all inferior SFs Support Indicator -- Tenth bit: E-DCH 2sf4 and all inferior SFs Support Indicator -- Eleventh bit: E-DCH sf4 and all inferior SFs Support Indicator -- Twelveth bit: E-DCH sf8 and all inferior SFs Support Indicator -- Thirteenth bit: E-DCH HARO IR Combining Support Indicator -- Fourteenth bit: E-DCH HARQ Chase Combining Support Indicator -- Fifteenth bit: Continuous Packet Connectivity DTX-DRX Support Indicator -- Sixteenth bit: Continuous Packet Connectivity HS-SCCH less Support Indicator -- Seventeenth bit: MIMO Support Indicator -- Eighteenth bit: SixteenQAM UL Support Indicator -- Nineteenth bit: Flexible MAC-d PDU Size Support Indicator -- Twentieth bit: F-DPCH Slot Format Support Indicator -- Twentyfirst bit: SixtyfourOAM DL Support Indicator -- Twentysecond bit: Flexible E-DCH MAC-d PDU Size Support Indicator -- Twentythird bit: E-DPCCH Power Boosting Support Indicator -- Twentyfourth bit: SixtyfourOAM DL and MIMO Combined Support Indicator -- Twentyfifth bit: Multi Cell Support Indicator Support Indicator -- Twentysixth bit: MBMS Support Indicator -- Twentyseventh bit: DRNS Support STTD on DL ctrl ch when the RL is in MIMO P-CPICH + S-CPICH cell -- Twentyeighth bit: Dual Band Support Indicator -- Twentyninth bit: Single Stream MIMO Support Indicator -- Thirtieth bit: Preferred Precoding Weight Set Restriction Support Indicator -- Note that undefined bits are considered as a spare bit and spare bits shall be set to 0 by the transmitter and shall be ignored by the receiver. CellCapabilityContainerExtension-FDD ::= BIT STRING (SIZE (128)) -- First bit: Cell Specific Tx Diversity Handling For Multi Cell Operation Support Indicator -- Second bit: Multi Cell and MIMO Support Indicator -- Third bit: Multi Cell and Single Stream MIMO Support Indicator -- Fourth bit: Multi Cell E-DCH Support Indicator -- Fifth bit: Separate Iub Transport Bearer Support Indicator -- Sixth bit: E-DCH UL Flow Multiplexing Support Indicator -- Seventh to eleventh bit: Maximum No of HSDPA Frequencies Support Indicator -- Twelfth bit: Dual Band and MIMO Support Indicator -- Thirteenth bit: 3 and 4 carrier HSDPA and MIMO Single Band Support Indicator -- Fourteenth bit: 3 and 4 carrier HSDPA and MIMO Dual Band Support Indicator -- Fifteenth bit : Dual Band and Single Stream MIMO Support Indicator -- Sixteenth bit : 3 and 4 carrier HSDPA and Single Stream MIMO Single Band Support Indicator -- Seventeenth bit : 3 and 4 carrier HSDPA and Single Stream MIMO Dual Band Support Indicator -- Eighteenth bit: Frequency specific Compressed Mode Support Indicator -- Note that undefined bits are considered as a spare bit and spare bits shall be set to 0 by the transmitter and shall be ignored by the receiver. CellCapabilityContainer-TDD ::= BIT STRING (SIZE (32)) -- First bit: Delayed Activation Support Indicator -- Second bit: HS-DSCH Support Indicator

887

- -- Third bit: DSCH Support Indicator
- -- The fourth bit: Flexible MAC-d PDU Size Support Indicator
- -- Fifth bit: MBMS Support Indicator
- -- Note that undefined bits are considered as a spare bit and spare bits shall be set to 0 by the transmitter and shall be ignored by the receiver.

```
CellCapabilityContainer-TDD-LCR ::= BIT STRING (SIZE (32))
-- First bit: Delayed Activation Support Indicator
-- Second bit: HS-DSCH Support Indicator
-- Third bit: DSCH Support Indicator
-- The fourth bit: Flexible MAC-d PDU Size Support Indicator
-- Note that undefined bits are considered as a spare bit and spare bits shall be set to 0 by the transmitter and shall be ignored by the receiver.
CellCapabilityContainerExtension-TDD-LCR ::= BIT STRING (SIZE (32))
-- First bit: Multi-Carrier E-DCH Operation Support Indicator
-- Second bit: Separate Iur Transport Bearer Support Indicator
-- Third bit: E-DCH UL flow Multiplexing Support Indicator
-- Note that undefined bits are considered as a spare bit and spare bits shall be set to 0 by the transmitter and shall be ignored by the receiver.
CellCapabilityContainer-TDD768 ::= BIT STRING (SIZE (32))
-- First bit: Delayed Activation Support Indicator
-- Second bit: HS-DSCH Support Indicator
-- Third bit: DSCH Support Indicator
-- The fourth bit: Flexible MAC-d PDU Size Support Indicator
-- Note that undefined bits are considered as a spare bit and spare bits shall be set to 0 by the transmitter and shall be ignored by the receiver.
C-TD
                       ::= INTEGER (0..65535)
CCTrCH-ID
                       ::= INTEGER (0..15)
Cell-Capacity-Class-Value ::= SEQUENCE {
       uplinkCellCapacityClassValue
                                            INTEGER(1..100,...),
        downlinkCellCapacityClassValue
                                            INTEGER(1..100,...)
CellIndividualOffset ::= INTEGER (-20..20)
CellListValidityIndicator ::= ENUMERATED {
    ignoreSecondaryServingCellList,
    ignoreDualBandSecondaryServingCellList.
    ignoreBoth
CellParameterID
                           ::= INTEGER (0..127,...)
CellPortionID ::= INTEGER (0..63,...)
CellPortionLCRID
                   ::= INTEGER (0..255,...)
CFN
                    ::= INTEGER (0..255)
CGI ::= SEOUENCE {
    lai
                    LAI,
    iE-Extensions ProtocolExtensionContainer { {CGI-ExtIEs} } OPTIONAL
LAI-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
```

```
CGI-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
ChannelCodingType ::= ENUMERATED {
    no-codingTDD,
    convolutional-coding,
    turbo-coding,
ChipOffset
                        ::= INTEGER (0..38399)
CI
                    ::= OCTET STRING (SIZE (2))
ClassmarkInformation2
                                ::= OCTET STRING
ClassmarkInformation3
                                ::= OCTET STRING
ClosedLoopModel-SupportIndicator
                                     ::= ENUMERATED {
    closedLoop-Model-Supported,
    closedLoop-Model-not-Supported
Closedlooptimingadjustmentmode ::= ENUMERATED {
    adj-1-slot,
    adj-2-slot,
    . . .
CodingRate ::= ENUMERATED {
    half,
    third,
CommonMeasurementAccuracy ::= CHOICE {
    \verb|tutrangPSMeasurementAccuracyClass|
                                             TUTRANGPSAccuracyClass,
    tUTRANGANSSMeasurementAccuracyClass
                                             TUTRANGANSSAccuracyClass
CommonMeasurementType ::= ENUMERATED {
    uTRAN-GPS-timing-of-cell-frames-for-UE-Positioning,
    sFN-SFN-observerd-time-difference,
    load,
    transmitted-carrier-power,
    received-total-wide-band-power,
    uplink-timeslot-iscp,
    rT-load,
```

```
nRT-load-Information,
    upPTSInterference,
    uTRAN-GANSS-timing-of-cell-frames-for-UE-Positioning
-- For measurements on the Iur-q interface, only load, RT Load and NRT Load information are requested.
CommonMeasurementValue ::= CHOICE {
    tUTRANGPSMeasurementValueInformation
                                            TUTRANGPSMeasurementValueInformation,
    sFNSFNMeasurementValueInformation
                                            SFNSFNMeasurementValueInformation,
    loadValue
                                            LoadValue,
    transmittedCarrierPowerValue
                                            INTEGER(0..100),
    receivedTotalWideBandPowerValue
                                            INTEGER(0..621),
    uplinkTimeslotISCPValue
                                            UL-TimeslotISCP,
    . . . ,
    extension-CommonMeasurementValue
                                            Extension-CommonMeasurementValue
Extension-CommonMeasurementValue
                                    ::= ProtocolIE-Single-Container {{ Extension-CommonMeasurementValueIE }}
Extension-CommonMeasurementValueIE RNSAP-PROTOCOL-IES ::= {
    { ID id-RTLoadValue
                                                         CRITICALITY ignore TYPE RTLoadValue
       PRESENCE mandatory }
    { ID id-NRTLoadInformationValue
                                                         CRITICALITY ignore TYPE NRTLoadInformationValue
    PRESENCE mandatory } |
    { ID id-UpPTSInterferenceValue
                                                         CRITICALITY reject TYPE UppTSInterferenceValue
    PRESENCE mandatory } |
    { ID id-TUTRANGANSSMeasurementValueInformation
                                                         CRITICALITY reject TYPE TUTRANGANSSMeasurementValueInformation PRESENCE mandatory }
-- For measurements on the Iur-g interface, only load, RT Load and NRT Load values are reported.
CommonMeasurementValueInformation ::= CHOICE {
    measurementAvailable
                                CommonMeasurementAvailable,
    measurementnotAvailable
                                NULL
CommonMeasurementAvailable::= SEQUENCE {
    commonMeasurementValue
                                CommonMeasurementValue,
                                    ProtocolExtensionContainer { { CommonMeasurementAvailableItem-ExtIEs} } 
    iE-Extensions
                                                                                                                          OPTIONAL,
    . . .
CommonMeasurementAvailableItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
CongestionCause ::= ENUMERATED {
    uTRAN-dynamic-resources,
    uTRAN-semistatic-resources,
CommonTransportChannelResourcesInitialisationNotRequired ::= ENUMERATED {
    not-Required
```

```
Common-EDCH-MAC-d-Flow-Specific-InformationFDD ::= SEOUENCE (SIZE (1..maxNrOfEDCHMACdFlows)) OF Common-EDCH-MAC-d-Flow-Specific-InformationFDDItem
Common-EDCH-MAC-d-Flow-Specific-InformationFDDItem ::= SEQUENCE {
    common-EDCH-MACdFlow-ID
                                                     EDCH-MACdFlow-ID,
    maximum-Number-of-Retransmissions-For-E-DCH
                                                    MaxNr-Retransmissions-EDCH,
    eDCH-HARO-PO-FDD
                                                     E-DCH-HARQ-PO-FDD,
    eDCH-MACdFlow-Multiplexing-List
                                                     E-DCH-MACdFlow-Multiplexing-List
                                                                                                                          OPTIONAL,
    common-E-DCHLogicalChannelInformation
                                                     Common-E-DCH-LogicalChannelInformation,
    iE-Extensions
                                                     ProtocolExtensionContainer { { Common-EDCH-MAC-d-Flow-Specific-InformationFDDItem-ExtIEs} }
                OPTIONAL,
    . . .
Common-EDCH-MAC-d-Flow-Specific-InformationFDDItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Common-EDCH-MAC-d-Flow-Specific-InformationLCR ::= SEQUENCE (SIZE (1..maxNrOfEDCHMACdFlowsLCR)) OF Common-EDCH-MAC-d-Flow-Specific-
InformationItemLCR
Common-EDCH-MAC-d-Flow-Specific-InformationItemLCR ::= SEQUENCE {
    common-EDCH-MACdFlow-ID-LCR
                                                     EDCH-MACdFlow-ID-LCR,
    maximum-Number-of-Retransmissions-For-E-DCH
                                                    MaxNr-Retransmissions-EDCH,
    eDCH-HARO-PO-TDD
                                                     E-DCH-HARO-PO-TDD,
    eDCH-MACdFlow-Multiplexing-List
                                                     E-DCH-MACdFlow-Multiplexing-List
                                                                                                                          OPTIONAL,
    common-E-DCHLogicalChannelInformation
                                                     Common-E-DCH-LogicalChannelInformation,
                                                     ProtocolExtensionContainer { { Common-EDCH-MAC-d-Flow-Specific-InformationItemLCR-ExtIEs} }
    iE-Extensions
                OPTIONAL,
    . . .
Common-EDCH-MAC-d-Flow-Specific-InformationItemLCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Common-E-DCH-LogicalChannelInformation ::= SEQUENCE (SIZE (1..maxNoOfLogicalChannels)) OF Common-E-DCH-LogicalChannelInformationItem
Common-E-DCH-LogicalChannelInformationItem ::= SEQUENCE {
                                    LogicalChannelID,
    logicalChannelId
    maximumMACdPDU-SizeExtended
                                    MAC-PDU-SizeExtended,
    iE-Extensions
                                    ProtocolExtensionContainer { { Common-E-DCH-LogicalChannelInformationItem-ExtIEs } }
    OPTIONAL,
    . . .
Common-E-DCH-LogicalChannelInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
Common-EDCH-Support-Indicator ::= NULL
CompleteAlmanacProvided ::= BOOLEAN
Continuous-Packet-Connectivity-DTX-DRX-Information ::= SEQUENCE {
    uE-DTX-DRX-Offset
                                                UE-DTX-DRX-Offset,
    enabling-Delay
                                                Enabling-Delay,
    dTX-Information
                                                DTX-Information,
    dRX-Information
                                                DRX-Information
                                                                                         OPTIONAL,
    iE-Extensions
                                                ProtocolExtensionContainer { { Continuous-Packet-Connectivity-DTX-DRX-Information-ExtIEs } }
       OPTIONAL,
    . . .
Continuous-Packet-Connectivity-DTX-DRX-Information-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
Continuous-Packet-Connectivity-DTX-DRX-Information-to-Modify ::= SEQUENCE {
                                                UE-DTX-DRX-Offset
    uE-DTX-DRX-Offset
                                                                                         OPTIONAL,
    enabling-Delay
                                                Enabling-Delay
                                                                                         OPTIONAL,
    dTX-Information-to-Modify
                                                DTX-Information-to-Modify
                                                                                         OPTIONAL,
                                                DRX-Information-to-Modify
    dRX-Information-to-Modify
                                                                                         OPTIONAL,
    iE-Extensions
                                                ProtocolExtensionContainer { Continuous-Packet-Connectivity-DTX-DRX-Information-to-Modify-ExtIEs
           OPTIONAL,
    . . .
Continuous-Packet-Connectivity-DTX-DRX-Information-to-Modify-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Continuous-Packet-Connectivity-HS-SCCH-Less-Information ::= SEQUENCE (SIZE (1..maxNrOfHS-DSCHTBSs-HS-SCCHless)) OF Continuous-Packet-Connectivity-
HS-SCCH-Less-InformationItem
Continuous-Packet-Connectivity-HS-SCCH-Less-InformationItem ::= SEQUENCE {
    transport-Block-Size-Index
                                            Transport-Block-Size-Index,
                                            HSPDSCH-Second-Code-Support,
    hSPDSCH-Second-Code-Support
                                            ProtocolExtensionContainer { { Continuous-Packet-Connectivity-HS-SCCH-Less-InformationItem-ExtIEs } }
    iE-Extensions
           OPTIONAL,
    . . .
Continuous-Packet-Connectivity-HS-SCCH-Less-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
Continuous-Packet-Connectivity-HS-SCCH-Less-Information-Response ::= SEQUENCE {
    hSPDSCH-First-Code-Index
                                            HSPDSCH-First-Code-Index,
   hSPDSCH-Second-Code-Index
                                            HSPDSCH-Second-Code-Index
                                                                                     OPTIONAL,
    iE-Extensions
                                            ProtocolExtensionContainer { { Continuous-Packet-Connectivity-HS-SCCH-Less-Information-Response-ExtIEs
           OPTIONAL,
    . . .
```

```
Continuous-Packet-Connectivity-HS-SCCH-Less-Information-Response-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
CorrespondingCells ::= SEOUENCE (SIZE (1..maxNrOfCellsPerFreq)) OF C-ID
CoverageIndicator ::= ENUMERATED {
    overlap,
    covers,
    containedIn,
CPC-Information ::= SEQUENCE
    continuous-Packet-Connectivity-DTX-DRX-Information
                                                                            Continuous-Packet-Connectivity-DTX-DRX-Information
            OPTIONAL,
    continuous-Packet-Connectivity-DTX-DRX-Information-to-Modify
                                                                            Continuous-Packet-Connectivity-DTX-DRX-Information-to-Modify
                                                                            Continuous-Packet-Connectivity-HS-SCCH-Less-Information
    continuous-Packet-Connectivity-HS-SCCH-Less-Information
        OPTIONAL,
                                                                             ProtocolExtensionContainer { { CPC-Information-ExtIEs} }
    iE-Extensions
       OPTIONAL,
CPC-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    {ID id-Continuous-Packet-Connectivity-HS-SCCH-Less-Deactivate-Indicator
                                                                                     CRITICALITY reject
                                                                                                                                 EXTENSION
Continuous-Packet-Connectivity-HS-SCCH-less-Deactivate-Indicator
                                                                            PRESENCE optional },
    . . .
CPC-RecoveryReport ::= ENUMERATED {
    initiated.
Continuous-Packet-Connectivity-HS-SCCH-less-Deactivate-Indicator ::= NULL
Counting-Information ::= SEQUENCE ( SIZE (1..maxNrOfFDDNeighboursPerRNC,...)) OF Counting-Information-List
Counting-Information-List ::= SEQUENCE {
    c-ID
                                        C-ID,
    counting-Result
                                        Counting-Result,
                                        ProtocolExtensionContainer { { Counting-Information-List-ExtIEs} } OPTIONAL,
    iE-Extensions
Counting-Information-List-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
Counting-Result ::= INTEGER (0..63)
CRC-Size
                        ::= ENUMERATED {
    v0.
    v8.
   v12,
    v16,
    v24.
    . . .
CriticalityDiagnostics ::= SEQUENCE {
    procedureID
                                    ProcedureID
                                                             OPTIONAL,
    triggeringMessage
                                    TriggeringMessage
                                                             OPTIONAL,
                                    Criticality
    procedureCriticality
                                                             OPTIONAL,
    transactionID
                                    TransactionID
                                                             OPTIONAL,
    iEsCriticalityDiagnostics
                                    CriticalityDiagnostics-IE-List OPTIONAL,
                                    ProtocolExtensionContainer { {CriticalityDiagnostics-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
CriticalityDiagnostics-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
CriticalityDiagnostics-IE-List ::= SEOUENCE (SIZE (1..maxNrOfErrors)) OF
    SEQUENCE {
       iECriticality
                                Criticality,
       iE-ID
                                ProtocolIE-ID,
       repetitionNumber
                                RepetitionNumber0
                                                        OPTIONAL,
       iE-Extensions
                                ProtocolExtensionContainer { {CriticalityDiagnostics-IE-List-ExtIEs} } OPTIONAL,
CriticalityDiagnostics-IE-List-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    ID id-MessageStructure
                                CRITICALITY ignore
                                                         EXTENSION MessageStructure
                                                                                         PRESENCE optional
   ID id-TypeOfError
                                CRITICALITY ignore
                                                         EXTENSION TypeOfError
                                                                                         PRESENCE mandatory
    . . .
MessageStructure ::= SEQUENCE (SIZE (1..maxNrOfLevels)) OF
    SEOUENCE {
       iE-ID
                                ProtocolIE-ID,
                                RepetitionNumber1
       repetitionNumber
                                                         OPTIONAL,
                                ProtocolExtensionContainer { {MessageStructure-ExtIEs} } OPTIONAL,
       iE-Extensions
MessageStructure-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
CN-CS-DomainIdentifier ::= SEQUENCE {
    pLMN-Identity
                       PLMN-Identity,
   1AC
                        LAC,
    iE-Extensions
                        ProtocolExtensionContainer { {CN-CS-DomainIdentifier-ExtIEs} } OPTIONAL
CN-CS-DomainIdentifier-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
CN-PS-DomainIdentifier ::= SEQUENCE {
    pLMN-Identity
                        PLMN-Identity,
   lac
                        LAC,
   rAC
    iE-Extensions
                        ProtocolExtensionContainer { {CN-PS-DomainIdentifier-ExtIEs} } OPTIONAL
CN-PS-DomainIdentifier-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
CNDomainType
               ::= ENUMERATED {
    cs-domain,
   ps-domain,
   i-care,
-- See in TS 25.331 [16]
CQI-DTX-Timer ::= ENUMERATED {v0, v1, v2, v4, v8, v16, v32, v64, v128, v256, v512, infinity}
    -- Unit subframe
ControlGAP ::= INTEGER (1..255)
CQI-Feedback-Cycle ::= ENUMERATED {v0, v2, v4, v8, v10, v20, v40, v80, v160,..., v16, v32, v64}
CQI-Power-Offset ::= INTEGER (0..8,...)
-- According to mapping in TS 25.213 [21] subclause 4.2.1
CQI-RepetitionFactor ::= INTEGER (1..4,...)
-- Step: 1
C-RNTI
                        ::= INTEGER (0..65535)
CodeRate ::= INTEGER (0..63)
CodeRate-short ::= INTEGER (0..10)
CPC-InformationLCR ::= SEQUENCE {
    continuousPacketConnectivity-DRX-InformationLCR
                                                                    ContinuousPacketConnectivity-DRX-InformationLCR
        OPTIONAL,
    continuousPacketConnectivity-DRX-Information-to-Modify-LCR
                                                                    ContinuousPacketConnectivity-DRX-Information-to-Modify-LCR
                                                                                                                                        OPTIONAL,
```

```
hS-DSCH-Semi-PersistentScheduling-Information-LCR
                                                                     HS-DSCH-Semi-PersistentScheduling-Information-LCR
    OPTIONAL,
    hS-DSCH-Semi-PersistentScheduling-Information-to-Modify-LCR
                                                                     HS-DSCH-Semi-PersistentScheduling-Information-to-Modify-LCR
                                                                                                                                         OPTIONAL.
   hS-DSCH-SPS-Deactivate-Indicator-LCR
                                                                     NULL
                                                                                 OPTIONAL,
    e-DCH-Semi-PersistentScheduling-Information-LCR
                                                                     E-DCH-Semi-PersistentScheduling-Information-LCR
        OPTIONAL,
    e-DCH-Semi-PersistentScheduling-Information-to-Modify-LCR
                                                                     E-DCH-Semi-PersistentScheduling-Information-to-Modify-LCR
                                                                                                                                         OPTIONAL.
    e-DCH-SPS-Deactivate-Indicator-LCR
                                                                                 OPTIONAL,
    iE-Extensions
                                                                     ProtocolExtensionContainer { { CPC-InformationLCR-ExtIEs} }
                                                                                                                                         OPTIONAL,
CPC-InformationLCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
ContinuousPacketConnectivity-DRX-InformationLCR ::= SEQUENCE {
    enabling-Delay
                                    Enabling-Delay,
    hS-SCCH-DRX-Information-LCR
                                    HS-SCCH-DRX-Information-LCR,
    e-AGCH-DRX-Information-LCR
                                    E-AGCH-DRX-Information-LCR
                                                                     OPTIONAL,
    iE-Extensions
                                     ProtocolExtensionContainer { {
                                                                   ContinuousPacketConnectivity-DRX-InformationLCR-ExtIEs } }
    OPTIONAL,
ContinuousPacketConnectivity-DRX-InformationLCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HS-SCCH-DRX-Information-LCR ::= SEQUENCE {
    hS-SCCH-UE-DRX-Cycle-LCR
                                                                 UE-DRX-Cycle-LCR,
   hS-SCCH-Inactivity-Threshold-for-UE-DRX-Cycle-LCR
                                                                 Inactivity-Threshold-for-UE-DRX-Cycle-LCR
                                                                                                                                  OPTIONAL,
   hS-SCCH-UE-DRX-Offset-LCR
                                                                 UE-DRX-Offset-LCR,
                                    ProtocolExtensionContainer { { HS-SCCH-DRX-Information-LCR-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
HS-SCCH-DRX-Information-LCR-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-HS-SCCH-Inactivity-Threshold-for-UE-DRX-Cycle-LCR-Ext
                                                                     CRITICALITY ignore EXTENSION Inactivity-Threshold-for-UE-DRX-Cycle-LCR-Ext
    PRESENCE optional },
    . . .
E-AGCH-DRX-Information-LCR ::= CHOICE {
    sameAsHS-SCCH
                                NULL,
    e-AGCH-DRX-Parameters
                                E-AGCH-DRX-Parameters,
    . . .
E-AGCH-DRX-Parameters ::= SEQUENCE {
    e-AGCH-UE-DRX-Cycle-LCR
                                                         UE-DRX-Cycle-LCR,
    e-AGCH-UE-Inactivity-Monitor-Threshold
                                                         E-AGCH-UE-Inactivity-Monitor-Threshold
                                                                                                           OPTIONAL,
    e-AGCH-UE-DRX-Offset-LCR
                                                         UE-DRX-Offset-LCR,
                                                         ProtocolExtensionContainer { { E-AGCH-DRX-Parameters-ExtIEs} } OPTIONAL,
    iE-Extensions
```

```
E-AGCH-DRX-Parameters-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
UE-DRX-Cycle-LCR ::= ENUMERATED \{v1, v2, v4, v8, v16, v32, v64, \ldots\}
    -- Unit subframe
UE-DRX-Offset-LCR ::= INTEGER (0..63)
    -- Unit subframe
Inactivity-Threshold-for-UE-DRX-Cycle-LCR ::= ENUMERATED {v1, v2, v4, v8, v16, v32, v64,...}
    -- Unit subframe
Inactivity-Threshold-for-UE-DRX-Cycle-LCR-Ext ::= ENUMERATED {v128, v256, v512,...}
    -- Unit subframe
E-AGCH-UE-Inactivity-Monitor-Threshold ::= ENUMERATED {v0, v1, v2, v4, v8, v16, v32, v64, v128, v256, v512, infinity,...}
    -- Unit subframe
ContinuousPacketConnectivity-DRX-Information-to-Modify-LCR ::= SEQUENCE {
    enabling-Delay
                                                Enabling-Delay
                                                                                         OPTIONAL,
    dRX-Information-to-Modify-LCR
                                                DRX-Information-to-Modify-LCR
                                                                                         OPTIONAL,
    iE-Extensions
                                                ProtocolExtensionContainer { { ContinuousPacketConnectivity-DRX-Information-to-Modify-LCR-ExtIEs }
                OPTIONAL,
ContinuousPacketConnectivity-DRX-Information-to-Modify-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DRX-Information-to-Modify-LCR ::= CHOICE
    modify
                    DRX-Information-to-Modify-Items-LCR,
    deactivate
                    NULL,
DRX-Information-to-Modify-Items-LCR ::= SEQUENCE
    hS-SCCH-DRX-Information-LCR
                                                HS-SCCH-DRX-Information-LCR
                                                                                     OPTIONAL,
    e-AGCH-DRX-Information-LCR
                                                E-AGCH-DRX-Information-LCR
                                                                                     OPTIONAL,
    iE-Extensions
                                                ProtocolExtensionContainer { {DRX-Information-to-Modify-Items-LCR-ExtIEs} } OPTIONAL,
    . . .
DRX-Information-to-Modify-Items-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
ContinuousPacketConnectivity-DRX-Information-ResponseLCR ::= SEQUENCE
                                                                                     OPTIONAL,
    enabling-Delay
                                            Enabling-Delay
    hS-SCCH-DRX-Information-ResponseLCR
                                            HS-SCCH-DRX-Information-ResponseLCR
                                                                                     OPTIONAL,
```

```
e-AGCH-DRX-Information-ResponseLCR
                                         E-AGCH-DRX-Information-ResponseLCR
                                                                              OPTIONAL,
   iE-Extensions
                                         ProtocolExtensionContainer { { ContinuousPacketConnectivity-DRX-Information-ResponseLCR-ExtIEs } }
       OPTIONAL.
ContinuousPacketConnectivity-DRX-Information-ResponseLCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HS-SCCH-DRX-Information-ResponseLCR ::= SEQUENCE {
   hS-SCCH-UE-DRX-Cycle-LCR
                                                           UE-DRX-Cycle-LCR
                                                                                  OPTIONAL,
   hS-SCCH-Inactivity-Threshold-for-UE-DRX-Cycle-LCR
                                                           Inactivity-Threshold-for-UE-DRX-Cycle-LCR
                                                                                                                OPTIONAL,
   hS-SCCH-UE-DRX-Offset-LCR
                                                           UE-DRX-Offset-LCR
                                                                                  OPTIONAL,
   iE-Extensions
                                 ProtocolExtensionContainer { { HS-SCCH-DRX-Information-ResponseLCR-ExtIEs} } OPTIONAL,
HS-SCCH-DRX-Information-ResponseLCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
   PRESENCE optional },
   . . .
E-AGCH-DRX-Information-ResponseLCR ::= CHOICE {
   sameAsHS-SCCH
                                     NULL,
   e-AGCH-DRX-Parameters-Response
                                     E-AGCH-DRX-Parameters-Response,
E-AGCH-DRX-Parameters-Response ::= SEQUENCE {
   e-AGCH-UE-DRX-Cycle-LCR
                                                UE-DRX-Cycle-LCR
                                                                                     OPTIONAL,
   e-AGCH-UE-Inactivity-Monitor-Threshold
                                                E-AGCH-UE-Inactivity-Monitor-Threshold OPTIONAL,
   e-AGCH-UE-DRX-Offset-LCR
                                                UE-DRX-Offset-LCR
                                                                                     OPTIONAL,
   iE-Extensions
                                                ProtocolExtensionContainer { { E-AGCH-DRX-Parameters-Response-ExtIEs} } OPTIONAL,
E-AGCH-DRX-Parameters-Response-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Controlled-Object-Scope ::= SEQUENCE{
   rNC-ID
                                         RNC-ID.
   extended-RNC-ID
                                         Extended-RNC-ID OPTIONAL,
   multiple-PLMN-List
                                         Multiple-PLMN-List OPTIONAL,
   umts-cell-Info
                                         UMTS-Cells-Info-List OPTIONAL,
   iE-Extensions
                                         ProtocolExtensionContainer { {Controlled-Object-Scope-ExtIEs} } OPTIONAL,
Controlled-Object-Scope-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
-- D
DATA-ID ::= INTEGER (0..3)
DCH-FDD-Information
                        ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF DCH-FDD-InformationItem
DCH-FDD-InformationItem ::= SEQUENCE {
    payloadCRC-PresenceIndicator
                                        PayloadCRC-PresenceIndicator,
    ul-FP-Mode
                                        UL-FP-Mode,
    toAWS
                                        ToAWS,
    toAWE
                                        ToAWE,
    dCH-SpecificInformationList
                                        DCH-Specific-FDD-InformationList,
    iE-Extensions
                                        ProtocolExtensionContainer { {DCH-FDD-InformationItem-ExtIEs} } OPTIONAL,
DCH-FDD-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-TnlOos
                            CRITICALITY
                                            ignore
                                                        EXTENSION TnlOos
                                                                                 PRESENCE
                                                                                             optional
    . . .
DCH-MeasurementOccasion-Information ::= SEOUENCE (SIZE (1.. maxNrOfDCHMeasurementOccasionPatternSequence)) OF DchMeasurementOccasionInformation-
DchMeasurementOccasionInformation-Item ::= SEQUENCE {
    pattern-Sequence-Identifier
                                                Pattern-Sequence-Identifier,
    status-Flag
                                                Status-Flag,
    measurement-Occasion-Pattern-Sequence-parameters
                                                                Measurement-Occasion-Pattern-Sequence-parameters
                                                                                                                                         OPTIONAL,
                                                ProtocolExtensionContainer { { DCH-MeasurementOccasion-Information-ExtIEs } }
    iE-Extensions
    OPTIONAL,
    . . .
DCH-MeasurementOccasion-Information-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
Measurement-Occasion-Pattern-Sequence-parameters ::= SEQUENCE {
    measurement-Occasion-Pattern-Sequence-parameters-k
                                                                         INTEGER(1..9),
   measurement-Occasion-Pattern-Sequence-parameters-offset
                                                                         INTEGER(0..511),
                                                                         INTEGER(1..512),
   measurement-Occasion-Pattern-Sequence-parameters-M-Length
    measurement-Occasion-Pattern-Sequence-parameters-Timeslot-Bitmap
                                                                         BIT STRING (SIZE (7)),
                                ProtocolExtensionContainer { { Measurement-Occasion-Pattern-Sequence-parameters-ExtIEs } } OPTIONAL,
    iE-Extensions
Measurement-Occasion-Pattern-Sequence-parameters-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DCH-MeasurementType-Indicator ::= BIT STRING (SIZE (5))
```

```
DCH-Specific-FDD-InformationList ::= SEOUENCE (SIZE (1..maxNrOfDCHs)) OF DCH-Specific-FDD-Item
DCH-Specific-FDD-Item ::=
                          SEQUENCE {
   4CH-TD
                                     DCH-ID.
   trCH-SrcStatisticsDescr
                                     TrCH-SrcStatisticsDescr,
   ul-transportFormatSet
                                     TransportFormatSet,
   dl-transportFormatSet
                                     TransportFormatSet,
   ul-BLER
                                     BLER,
   dl-BLER
                                     BLER,
   allocationRetentionPriority
                                     AllocationRetentionPriority,
    frameHandlingPriority
                                     FrameHandlingPriority,
   σE-Selector
                                     OE-Selector,
   dRACControl
                                     DRACControl,
   iE-Extensions
                                     ProtocolExtensionContainer { {DCH-FDD-SpecificItem-ExtIEs} } OPTIONAL,
DCH-FDD-SpecificItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-Guaranteed-Rate-Information
                                                                                                          PRESENCE optional
                                         CRITICALITY ignore EXTENSION Guaranteed-Rate-Information
     ID id-TrafficClass
                                         CRITICALITY ignore EXTENSION TrafficClass PRESENCE mandatory |
                                         CRITICALITY reject EXTENSION Unidirectional-DCH-Indicator
    { ID id-Unidirectional-DCH-Indicator
                                                                                                          PRESENCE optional
DCH-Indicator-For-E-DCH-HSDPA-Operation ::= ENUMERATED {
    dch-not-present
DCH-ID
                      ::= INTEGER (0..255)
DCH-InformationResponse ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF DCH-InformationResponseItem
DCH-InformationResponseItem ::= SEQUENCE {
   dCH-ID
                              DCH-ID,
   bindingID
                              BindingID
                                                     OPTIONAL,
   transportLayerAddress
                              TransportLayerAddress OPTIONAL,
                              ProtocolExtensionContainer { {DCH-InformationResponseItem-ExtIEs} } OPTIONAL,
   iE-Extensions
DCH-InformationResponseItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-Allowed-Rate-Information
                                             CRITICALITY ignore EXTENSION Allowed-Rate-Information
                                                                                                                                PRESENCE
optional
    PRESENCE optional
FDD only
DCH-TDD-Information
                      ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF DCH-TDD-InformationItem
DCH-TDD-InformationItem ::= SEQUENCE {
   payloadCRC-PresenceIndicator
                                     PayloadCRC-PresenceIndicator,
   ul-FP-Mode
                                     UL-FP-Mode,
```

```
toAWS
                                        ToAWS,
    t.oAWE
                                        TOAWE.
    dCH-SpecificInformationList
                                        DCH-Specific-TDD-InformationList.
                                        ProtocolExtensionContainer { {DCH-TDD-InformationItem-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
DCH-TDD-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-TnlOos
                                        CRITICALITY
                                                         ignore
                                                                     EXTENSION
                                                                                 Tnl0os
                                                                                             PRESENCE
                                                                                                           optional
                                                                                                                          },
    . . .
DCH-Specific-TDD-InformationList ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF DCH-Specific-TDD-Item
DCH-Specific-TDD-Item ::= SEQUENCE {
    dCH-ID
                                        DCH-ID.
    ul-cCTrCH-ID
                                        CCTrCH-ID, -- UL CCTrCH in which the DCH is mapped
    dl-cCTrCH-ID
                                        CCTrCH-ID, -- DL CCTrCH in which the DCH is mapped
    trCH-SrcStatisticsDescr
                                        TrCH-SrcStatisticsDescr,
                                        TransportFormatSet,
    ul-transportFormatSet
    dl-transportFormatSet
                                        TransportFormatSet,
    ul-BLER
                                        BLER,
    dl-BLER
                                        BLER,
    allocationRetentionPriority
                                        AllocationRetentionPriority,
    frameHandlingPriority
                                        FrameHandlingPriority,
    qE-Selector
                                        OE-Selector
                                                             OPTIONAL.
    -- This IE shall be present if DCH is part of set of Co-ordinated DCHs
                                        ProtocolExtensionContainer { {DCH-Specific-TDD-Item-ExtIEs} } OPTIONAL,
    iE-Extensions
DCH-Specific-TDD-Item-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
      ID id-Guaranteed-Rate-Information
                                            CRITICALITY ignore EXTENSION Guaranteed-Rate-Information
                                                                                                                  PRESENCE optional
      ID id-TrafficClass
                                            CRITICALITY ignore EXTENSION TrafficClass PRESENCE mandatory |
                                                                                                                  PRESENCE optional
     ID id-Unidirectional-DCH-Indicator
                                            CRITICALITY reject EXTENSION Unidirectional-DCH-Indicator
    . . .
DedicatedMeasurementType ::= ENUMERATED {
    sir,
    sir-error,
    transmitted-code-power,
    rSCP,
    rx-timing-deviation,
    round-trip-time,
    rx-timing-deviation-LCR,
    angle-Of-Arrival-LCR,
    hs-sich-quality,
    rx-timing-deviation-768,
    rx-timing-deviation-ext
```

```
DedicatedMeasurementValue ::= CHOICE {
    sIR-Value
                        SIR-Value.
    sIR-ErrorValue
                            SIR-Error-Value.
    transmittedCodePowerValue Transmitted-Code-Power-Value,
                        RSCP-Value, -- TDD only
    rxTimingDeviationValue Rx-Timing-Deviation-Value, -- 3.84Mcps TDD only
    roundTripTime
                        Round-Trip-Time-Value, -- FDD only
    extension-DedicatedMeasurementValue
                                            Extension-DedicatedMeasurementValue
Extension-DedicatedMeasurementValue ::= ProtocolIE-Single-Container {{ Extension-DedicatedMeasurementValueIE }}
Extension-DedicatedMeasurementValueIE RNSAP-PROTOCOL-IES ::= {
      ID id-Rx-Timing-Deviation-Value-LCR
                                                CRITICALITY reject TYPE Rx-Timing-Deviation-Value-LCR
                                                                                                                 PRESENCE mandatory } |
      ID id-Angle-Of-Arrival-Value-LCR
                                                CRITICALITY reject TYPE Angle-Of-Arrival-Value-LCR
                                                                                                                         PRESENCE mandatory } |
      ID id-HS-SICH-Reception-Ouality
                                                CRITICALITY reject TYPE HS-SICH-Reception-Quality-Value PRESENCE mandatory }
      ID id-Rx-Timing-Deviation-Value-768
                                                CRITICALITY reject TYPE Rx-Timing-Deviation-Value-768
                                                                                                                 PRESENCE mandatory } |
      ID id-Rx-Timing-Deviation-Value-ext
                                                CRITICALITY reject TYPE Rx-Timing-Deviation-Value-ext
                                                                                                                 PRESENCE mandatory }
     ID id-Extended-Round-Trip-Time-Value
                                                CRITICALITY reject TYPE Extended-Round-Trip-Time-Value
                                                                                                                 PRESENCE mandatory },
    . . .
DedicatedMeasurementValueInformation ::= CHOICE {
                                DedicatedMeasurementAvailable,
    measurementAvailable
    measurementnotAvailable
                                DedicatedMeasurementnotAvailable
DedicatedMeasurementAvailable::= SEOUENCE {
    dedicatedmeasurementValue
                                    DedicatedMeasurementValue,
    CFN
    ie-Extensions
                                    ProtocolExtensionContainer { { DedicatedMeasurementAvailableItem-ExtIEs} }
                                                                                                                         OPTIONAL,
DedicatedMeasurementAvailableItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DedicatedMeasurementnotAvailable ::= NULL
DelayedActivation ::= CHOICE {
                            CFN,
    separate-indication
                            NULL
DelayedActivationUpdate ::= CHOICE {
    activate
                    Activate-Info,
    deactivate
                    Deactivate-Info
Activate-Info ::= SEQUENCE {
    activation-type
                            Execution-Type,
    initial-dl-tx-power
                            DL-Power,
```

```
firstRLS-Indicator
                        FirstRLS-Indicator
                                                                           OPTIONAL, --FDD Only
   propagation-delay
                        PropagationDelay
                                                                           OPTIONAL, --FDD Only
   iE-Extensions
                        ProtocolExtensionContainer { { Activate-Info-ExtIEs} }
                                                                           OPTIONAL.
Activate-Info-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   Deactivate-Info ::= SEQUENCE {
   deactivation-type
                        Execution-Type,
   iE-Extensions
                        OPTIONAL,
Deactivate-Info-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Execution-Type ::= CHOICE {
   synchronised
   unsynchronised NULL
DeltaSIR
                    ::= INTEGER (0..30)
-- Step 0.1 dB, Range 0..3 dB.
DGANSSCorrections ::= SEOUENCE {
   dGANSS-ReferenceTime
                               INTEGER(0..119),
   dGANSS-Information
                               SEQUENCE (SIZE (1..maxSgnType)) OF SEQUENCE {
      qANSS-SignalId
                                  GANSS-Signal-ID
                                                                                                   OPTIONAL,
      gANSS-StatusHealth
                                  GANSS-StatusHealth,
-- The following IE shall be present if the StatusHealth IE value is not equal to "no data" or "invalid data"
      dGANSS-SignalInformation
                                  SEQUENCE (SIZE (1..maxGANSSSat)) OF SEQUENCE {
          satId
                                     INTEGER(0..63),
          qANSS-iod
                                     BIT STRING (SIZE (10)),
          udre
                                     UDRE,
          ganss-prc
                                     INTEGER (-2047..2047),
                                     INTEGER(-127..127),
          ganss-rrc
          ie-Extensions
                                     ProtocolExtensionContainer { { DGANSS-SignalInformationItem-ExtIEs } } OPTIONAL,
                                                                                                   OPTIONAL,
      ie-Extensions
                                  ProtocolExtensionContainer { { DGANSS-InformationItem-ExtIEs } }
                                                                                                   OPTIONAL,
                               ie-Extensions
                                                                                                   OPTIONAL,
```

```
DGANSSCorrections-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DGANSS-Corrections-Req ::= SEQUENCE {
   dGANSS-Signal-ID
                                     BIT STRING (SIZE (8)),
   ie-Extensions
                                     ProtocolExtensionContainer { { DGANSS-Corrections-Req-ExtIEs } }
                                                                                                             OPTIONAL,
DGANSS-Corrections-Req-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   {ID id-GANSS-ID
                              CRITICALITY ignore EXTENSION GANSS-ID
                                                                               PRESENCE
                                                                                          optional},
   . . .
DGANSS-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DGANSS-SignalInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    {ID id-DGNSS-ValidityPeriod CRITICALITY ignore EXTENSION DGNSS-ValidityPeriod
                                                                                  PRESENCE
                                                                                                             optional },
   . . .
DGANSSThreshold ::= SEQUENCE {
   pRCDeviation
                 PRCDeviation,
DGNSS-ValidityPeriod ::=
                                 SEQUENCE {
   udreGrowthRate
                                     UDREGrowthRate,
   udreValidityTime
                                     UDREValidityTime,
   iE-Extensions
                                     OPTIONAL,
DGNSS-ValidityPeriod-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DGPSCorrections ::= SEQUENCE {
   gPSTOW
                                         GPSTOW,
   gPS-Status-Health
                                         GPS-Status-Health,
   satellite-DGPSCorrections-Information SEQUENCE (SIZE (1..maxNoSat)) OF
```

```
SEQUENCE {
                                sAT-ID
                                                                                                                                    SAT-ID,
                                iode-daps
                                                                                                                                    BIT STRING (SIZE (8)),
                                uDRE
                                                                                                                                     PRC,
                                                                                                                                    Range-Correction-Rate,
                                range-Correction-Rate
                                iE-Extensions
                                                                                                                                    ProtocolExtensionContainer { { Satellite-DGPSCorrections-Information-ExtIEs} }
                                                                                                                                                                                                                                                                                                                                                                                     OPTIONAL,
                      },
           iE-Extensions
                                                                                                   OPTIONAL,
Satellite-DGPSCorrections-Information-Extles RNSAP-PROTOCOL-EXTENSION ::= {
            {ID id-DGNSS-ValidityPeriod CRITICALITY ignore EXTENSION DGNSS-ValidityPeriod PRESENCE
                                                                                                                                                                                                                                                                        optional},
DGPSCorrections-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DGPSThreshold ::= SEQUENCE {
           pRCDeviation
                                                                  PRCDeviation,
           iE-Extensions
                                                                  OPTIONAL,
DGPSThreshold-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DiscardTimer ::= ENUMERATED
\{v20, v40, v60, v80, v100, v120, v140, v160, v180, v200, v250, v300, v400, v500, v750, v1000, v1250, v1500, v1750, v2000, v2500, v3000, v3500, v4000, v4500, v5000, v7500, v1000, v10000, DiversityControlField
                                                                                        ::= ENUMERATED {
           may,
           must,
           must-not
DiversityMode
                                                                            ::= ENUMERATED {
           none,
           sTTD,
           closedLoopModel,
           not-used-closedLoopMode2,
```

```
DL-DPCH-SlotFormat
                           ::= INTEGER (0..16...)
DL-DPCH-TimingAdjustment ::= ENUMERATED {
    timing-advance,
    timing-delay
DI-Power
                       ::= INTEGER (-350..150)
-- Value = DL-Power / 10
-- Unit dB, Range -35dB .. +15dB, Step 0.1dB
DL-PowerBalancing-Information ::= SEQUENCE {
    powerAdjustmentType
                                       PowerAdjustmentType,
    dLReferencePower
                                       DL-Power
                                                       OPTIONAL,
    -- This IE shall be present if Power Adjustment Type IE equals to 'Common'
    dLReferencePowerList DL-ReferencePowerInformationList
    -- This IE shall be present if Power Adjustment Type IE equals to 'Individual'
                                       MaxAdjustmentStep
    maxAdjustmentStep
                                                               OPTIONAL,
    -- This IE shall be present if Power Adjustment Type IE equals to 'Common' or 'Individual'
    adjustmentPeriod
                                       AdjustmentPeriod
                                                               OPTIONAL,
    -- This IE shall be present if Power Adjustment Type IE equals to 'Common' or 'Individual'
                                       ScaledAdjustmentRatio OPTIONAL,
    adjustmentRatio
    -- This IE shall be present if Power Adjustment Type IE equals to 'Common' or 'Individual'
                                       ProtocolExtensionContainer { { DL-PowerBalancing-Information-ExtIEs } } OPTIONAL,
    iE-Extensions
    . . .
DL-PowerBalancing-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-ReferencePowerInformationList
                                       ::= SEQUENCE (SIZE (1..maxNrOfRLs)) OF DL-ReferencePowerInformationItem
DL-ReferencePowerInformationItem ::= SEOUENCE {
    rI.-ID
                               RL-ID,
    dl-Reference-Power
                               DL-Power,
    iE-Extensions
                               ProtocolExtensionContainer { {DL-ReferencePowerInformationItem-ExtIEs} } OPTIONAL,
DL-ReferencePowerInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-PowerBalancing-ActivationIndicator ::= ENUMERATED {
    dL-PowerBalancing-Activated
DL-PowerBalancing-UpdatedIndicator ::= ENUMERATED {
    dL-PowerBalancing-Updated
DL-ReferencePowerInformation
                              ::= SEOUENCE {
```

```
common-DL-ReferencePowerInformation
                                             DL-Power
                                                            OPTIONAL,
   individual-DL-ReferencePowerInformation
                                             DL-ReferencePowerInformationList
                                                                                   OPTIONAL.
   iE-Extensions
                                             ProtocolExtensionContainer { { DL-ReferencePowerInformation-ExtIEs } } OPTIONAL,
DL-ReferencePowerInformation-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
D-RNTI
                      ::= INTEGER (0..1048575)
D-RNTI-ReleaseIndication ::= ENUMERATED {
   release-D-RNTI,
   not-release-D-RNTI
DL-ScramblingCode
                         ::= INTEGER (0..15)
DL-FrameType ::= ENUMERATED {
   typeA,
   typeB,
DL-Timeslot-Information ::= SEQUENCE ( SIZE (1..maxNrOfTS)) OF DL-Timeslot-InformationItem
DL-Timeslot-InformationItem ::= SEQUENCE {
   timeSlot
                                 MidambleShiftAndBurstType,
   midambleShiftAndBurstType
   tFCI-Presence
                                 TFCI-Presence,
   dL-Code-Information
                                 TDD-DL-Code-Information,
   iE-Extensions
                                  ProtocolExtensionContainer { {DL-Timeslot-InformationItem-ExtIEs} } OPTIONAL,
DL-Timeslot-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-TimeslotLCR-Information ::= SEQUENCE (SIZE (1.. maxNrOfDLTsLCR)) OF DL-TimeslotLCR-InformationItem
DL-TimeslotLCR-InformationItem ::= SEQUENCE {
   timeSlotLCR
                                         TimeSlotLCR,
   midambleShiftLCR
                                         MidambleShiftLCR,
   tFCI-Presence
                                         TFCI-Presence,
   dL-Code-LCR-Information
                                     TDD-DL-Code-LCR-Information,
                                         ProtocolExtensionContainer { { DL-TimeslotLCR-InformationItem-ExtIEs} }
   iE-Extensions
                                                                                                                        OPTIONAL,
DL-TimeslotLCR-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   PRESENCE optional
                                                                                                                                      } |
   -- Applicable to 1.28Mcps TDD only
```

```
PRESENCE optional
   -- Applicable to 1.28Mcps TDD only
DL-Timeslot-Information768 ::= SEOUENCE ( SIZE (1..maxNrOfTS)) OF DL-Timeslot-InformationItem768
DL-Timeslot-InformationItem768 ::= SEQUENCE {
   timeSlot
                                  TimeSlot,
                                 MidambleShiftAndBurstType768,
   midambleShiftAndBurstType768
   tFCI-Presence
                                 TFCI-Presence,
   dL-Code-Information768
                                  TDD-DL-Code-Information768,
   iE-Extensions
                                  ProtocolExtensionContainer { {DL-Timeslot-InformationItem768-ExtIEs} } OPTIONAL,
   . . .
DL-Timeslot-InformationItem768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-TimeSlot-ISCP-Info ::= SEQUENCE (SIZE (1..maxNrOfDLTs)) OF DL-TimeSlot-ISCP-InfoItem
DL-TimeSlot-ISCP-InfoItem ::= SEQUENCE {
   timeSlot
                              TimeSlot,
   dL-TimeslotISCP
                              DL-TimeslotISCP,
   iE-Extensions
                              ProtocolExtensionContainer { { DL-TimeSlot-ISCP-InfoItem-ExtIEs} } OPTIONAL,
DL-TimeSlot-ISCP-InfoItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
DL-TimeSlot-ISCP-LCR-Information ::= SEQUENCE (SIZE (1..maxNrOfDLTsLCR)) OF DL-TimeSlot-ISCP-LCR-InfoItem
DL-TimeSlot-ISCP-LCR-InfoItem ::= SEQUENCE {
   timeSlotLCR
                                 TimeSlotLCR,
   dL-TimeslotISCP
                                  DL-TimeslotISCP,
   iE-Extensions
                                  ProtocolExtensionContainer { { DL-TimeSlot-ISCP-LCR-InfoItem-ExtIEs} } }
                                                                                                                 OPTIONAL,
DL-TimeSlot-ISCP-LCR-InfoItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DL-TimeslotISCP
                     ::= INTEGER (0..91)
-- According to mapping in TS 25.123 [24]
Downlink-Compressed-Mode-Method
                                ::= ENUMERATED {
   not-Used-puncturing,
   sFdiv2,
   higher-layer-scheduling,
```

```
DPC-Mode ::= ENUMERATED {
   mode0,
    mode1,
DPC-Mode-Change-SupportIndicator ::= ENUMERATED {
   dPC-ModeChangeSupported
DPCH-ID
                        ::= INTEGER (0..239)
DPCH-ID768 ::= INTEGER (0..479)
DPCHConstantValue ::= INTEGER (-10..10)
-- Unit dB, Step 1dB
               ::= ENUMERATED {
DRACControl
   not-Used-requested,
   not-requested
DRXCycleLengthCoefficient
                                        ::= INTEGER (3..9)
-- See in TS 25.331 [16]
DRX-Information ::= SEQUENCE {
    uE-DRX-Cycle
                                            UE-DRX-Cycle,
                                                                     Inactivity-Threshold-for-UE-DRX-Cycle,
    inactivity-Threshold-for-UE-DRX-Cycle
    inactivity-Threshold-for-UE-Grant-Monitoring
                                                                     Inactivity-Threshold-for-UE-Grant-Monitoring,
    uE-DRX-Grant-Monitoring
                                            UE-DRX-Grant-Monitoring,
    iE-Extensions
                                            ProtocolExtensionContainer { {DRX-Information-ExtIEs} } OPTIONAL,
    . . .
DRX-Information-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
DRX-Information-to-Modify ::= CHOICE {
    modify
                        DRX-Information-to-Modify-Items,
    deactivate
                    NULL,
    . . .
DRX-Information-to-Modify-Items ::= SEQUENCE
    uE-DRX-Cycle
                                            UE-DRX-Cycle
                                                                         OPTIONAL,
    inactivity-Threshold-for-UE-DRX-Cycle
                                                                     Inactivity-Threshold-for-UE-DRX-Cycle
                                                                                                                                         OPTIONAL,
    inactivity-Threshold-for-UE-Grant-Monitoring
                                                                     Inactivity-Threshold-for-UE-Grant-Monitoring
                                                                                                                                         OPTIONAL,
    uE-DRX-Grant-Monitoring
                                            UE-DRX-Grant-Monitoring
                                                                                 OPTIONAL,
    iE-Extensions
                                            ProtocolExtensionContainer { {DRX-Information-to-Modify-Items-ExtIEs} } OPTIONAL,
```

```
DRX-Information-to-Modify-Items-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DSCH-RNTI ::= INTEGER (0..65535)
DSCH-FlowControlInformation ::= SEOUENCE (SIZE(1..16)) OF DSCH-FlowControlItem
DSCH-FlowControlItem ::= SEQUENCE {
    dSCH-SchedulingPriority
                                       SchedulingPriorityIndicator,
   mAC-c-sh-SDU-Lengths
                                       MAC-c-sh-SDU-LengthList,
   iE-Extensions
                                       ProtocolExtensionContainer { {DSCH-FlowControlItem-ExtIEs} } OPTIONAL,
DSCH-FlowControlItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-DSCH-InitialWindowSize CRITICALITY ignore EXTENSION DSCH-InitialWindowSize PRESENCE optional },
    . . .
DSCH-ID
                      ::= INTEGER (0..255)
DSCH-InitialWindowSize
                               ::= INTEGER (1...255)
-- Number of MAC-c/sh SDUs.
-- 255 = Unlimited number of MAC-c/sh SDUs
DSCH-TDD-Information ::= SEQUENCE (SIZE (1..maxNoOfDSCHs)) OF DSCH-TDD-InformationItem
DSCH-TDD-InformationItem ::= SEQUENCE {
   dSCH-ID
                                       DSCH-ID,
   dl-ccTrCHID
                                       CCTrCH-ID, -- DL CCTrCH in which the DSCH is mapped
    trChSourceStatisticsDescriptor
                                       TrCH-SrcStatisticsDescr.
    transportFormatSet
                                       TransportFormatSet,
    allocationRetentionPriority
                                       AllocationRetentionPriority,
    schedulingPriorityIndicator
                                       SchedulingPriorityIndicator,
    bler
    iE-Extensions
                                       ProtocolExtensionContainer { {DSCH-TDD-InformationItem-ExtIEs} } OPTIONAL,
DSCH-TDD-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-TrafficClass
                                           CRITICALITY ignore EXTENSION TrafficClass
                                                                                                        PRESENCE mandatory } |
    { ID id-BindingID
                                                                                                    PRESENCE optional }
                                           CRITICALITY ignore EXTENSION BindingID
    -- Shall be ignored if bearer establishment with ALCAP.
    { ID id-TransportLayerAddress
                                           CRITICALITY ignore EXTENSION TransportLayerAddress
                                                                                                        PRESENCE optional
                                                                                                                               } |
    -- Shall be ignored if bearer establishment with ALCAP.
    { ID id-TnlQos
                                           CRITICALITY ignore EXTENSION TnlQos
                                                                                                        PRESENCE optional },
    -- Shall be ignored if bearer establishment with ALCAP.
```

```
DsField ::= BIT STRING (SIZE (8))
DTX-Cycle-2ms-Items ::= SEQUENCE {
   uE-DTX-Cycle1-2ms
                               UE-DTX-Cycle1-2ms,
   uE-DTX-Cycle2-2ms
                               UE-DTX-Cycle2-2ms,
   mAC-DTX-Cycle-2ms
                               MAC-DTX-Cycle-2ms,
   iE-Extensions
                                          OPTIONAL,
DTX-Cycle-2ms-Items-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DTX-Cycle-2ms-to-Modify-Items ::= SEQUENCE {
                               UE-DTX-Cycle1-2ms
   uE-DTX-Cycle1-2ms
                                                        OPTIONAL,
   uE-DTX-Cycle2-2ms
                               UE-DTX-Cycle2-2ms
                                                        OPTIONAL,
   mAC-DTX-Cycle-2ms
                               MAC-DTX-Cycle-2ms
                                                        OPTIONAL,
                                          iE-Extensions
                                                                                                                       OPTIONAL,
   . . .
DTX-Cycle-2ms-to-Modify-Items-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DTX-Cycle-10ms-Items ::= SEQUENCE {
   uE-DTX-Cycle1-10ms
                               UE-DTX-Cycle1-10ms,
   uE-DTX-Cycle2-10ms
                               UE-DTX-Cycle2-10ms,
   mAC-DTX-Cycle-10ms
                               MAC-DTX-Cycle-10ms,
                                          iE-Extensions
                                                                                                                 OPTIONAL,
   . . .
DTX-Cycle-10ms-Items-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DTX-Cycle-10ms-to-Modify-Items ::= SEQUENCE {
   uE-DTX-Cycle1-10ms
                               UE-DTX-Cycle1-10ms
                                                        OPTIONAL,
   uE-DTX-Cycle2-10ms
                               UE-DTX-Cycle2-10ms
                                                        OPTIONAL,
   mAC-DTX-Cycle-10ms
                               MAC-DTX-Cycle-10ms
                                                                                                                 OPTIONAL,
                                          ProtocolExtensionContainer { { DTX-Cycle-10ms-to-Modify-Items-ExtIEs} } }
   iE-Extensions
                                                                                                                       OPTIONAL,
   . . .
DTX-Cycle-10ms-to-Modify-Items-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DTX-Information ::= SEQUENCE {
   e-DCH-TTI-Length
                                   E-DCH-TTI-Length,
   inactivity-Threshold-for-UE-DTX-Cycle2
                                                     Inactivity-Threshold-for-UE-DTX-Cycle2,
```

OPTIONAL,

```
uE-DTX-Long-Preamble
                                        UE-DTX-Long-Preamble,
   mAC-Inactivity-Threshold
                                            MAC-Inactivity-Threshold
    cOI-DTX-Timer
                                COI-DTX-Timer.
    uE-DPCCH-burst1
                                UE-DPCCH-burst1,
    uE-DPCCH-burst2
                                UE-DPCCH-burst2.
                                ProtocolExtensionContainer { {DTX-Information-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
DTX-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
DTX-Information-to-Modify ::= CHOICE {
    modify
                         DTX-Information-to-Modify-Items,
    deactivate
                         NULL,
    . . .
DTX-Information-to-Modify-Items ::= SEQUENCE {
    e-DCH-TTI-Length-to-Modify
                                    E-DCH-TTI-Length-to-Modify
                                                                                 OPTIONAL,
    inactivity-Threshold-for-UE-DTX-Cycle2
                                                             Inactivity-Threshold-for-UE-DTX-Cycle2
                                    UE-DTX-Long-Preamble
    uE-DTX-Long-Preamble
                                                                         OPTIONAL,
    mAC-Inactivity-Threshold
                                        MAC-Inactivity-Threshold
                                                                                 OPTIONAL,
    cOI-DTX-Timer
                                    COI-DTX-Timer
                                                                         OPTIONAL,
    uE-DPCCH-burst1
                                    UE-DPCCH-burst1
                                                                         OPTIONAL,
    uE-DPCCH-burst2
                                    UE-DPCCH-burst2
                                                                         OPTIONAL,
                                    ProtocolExtensionContainer { {DTX-Information-to-Modify-Items-ExtIEs} } OPTIONAL,
    iE-Extensions
DTX-Information-to-Modify-Items-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
EARFCN ::= INTEGER (0..maxEARFCN)
EARFCN-Information ::= CHOICE {
    fDD
           EARFCN-FDD,
    tDD
            EARFCN,
    . . .
EARFCN-FDD ::= SEQUENCE {
    uL-EARFCN
                    EARFCN,
    dL-EARFCN
                    EARFCN
E-AGCH-Table-Choice ::= ENUMERATED{table16B, table16B-1, ...}
```

```
ECGI ::= SEQUENCE {
   pLMN-Identity
                          PLMN-Identity,
   e-UTRAN-Cell-ID
                          BIT STRING (SIZE (28)),
   iE-Extensions
                          ProtocolExtensionContainer { {ECGI-ExtIEs} } OPTIONAL,
ECGI-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
EDCH-DDI-Value ::= INTEGER (0..62)
EDCH-FDD-DL-ControlChannelInformation ::= SEOUENCE {
    eAGCH-ERGCH-EHICH-FDD-ScramblingCode
                                                     DL-ScramblingCode
                                                                                       OPTIONAL,
    eAGCH-ChannelisationCode
                                                     FDD-DL-ChannelisationCodeNumber
                                                                                       OPTIONAL,
   primary-e-RNTI
                                                     E-RNTI
                                                                                       OPTIONAL,
                                                     E-RNTI
                                                                                       OPTIONAL,
    secondary-e-RNTI
    eRGCH-EHICH-ChannelisationCode
                                                     FDD-DL-ChannelisationCodeNumber,
    eRGCH-SignatureSequence
                                                     ERGCH-SignatureSequence
                                                                                       OPTIONAL,
    eHICH-SignatureSequence
                                                     EHICH-SignatureSequence
                                                                                       OPTIONAL,
    serving-Grant-Value
                                                     E-Serving-Grant-Value
                                                                                       OPTIONAL,
   primary-Secondary-Grant-Selector
                                                     E-Primary-Secondary-Grant-Selector OPTIONAL,
    e-RGCH-Release-Indicator
                                                     E-RGCH-Release-Indicator
                                                                                       OPTIONAL,
   iE-Extensions
                                                     ProtocolExtensionContainer { { EDCH-FDD-DL-ControlChannelInformation-ExtIEs } }
       OPTIONAL,
    . . .
EDCH-FDD-DL-ControlChannelInformation-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    PRESENCE optional }
    { ID id-Default-Serving-Grant-in-DTX-Cycle2
                                                            CRITICALITY ignore EXTENSION E-Serving-Grant-Value
                          PRESENCE optional },
    . . .
E-RGCH-E-HICH-ChannelisationCodeValidityIndicator ::= ENUMERATED
    e-RGCH-E-HICH-Channelisation-Code-response-not-valid
EDCH-FDD-Information ::= SEQUENCE {
    eDCH-MACdFlows-Information
                                                 EDCH-MACdFlows-Information,
   hARO-Process-Allocation-Scheduled-2ms-EDCH
                                                 HARO-Process-Allocation-2ms-EDCH
       OPTIONAL.
    e-DCH-Maximum-Bitrate
                                                 E-DCH-Maximum-Bitrate
                                                                                                                         OPTIONAL,
   e-DCH-Processing-Overload-Level
                                                 E-DCH-Processing-Overload-Level
                                                                                                                         OPTIONAL,
    e-DCH-Reference-Power-Offset
                                                 E-DCH-Reference-Power-Offset
                                                                                                                         OPTIONAL,
   iE-Extensions
                                                 ProtocolExtensionContainer { { EDCH-FDD-Information-ExtIEs } }
                                                                                                                         OPTIONAL,
    . . .
EDCH-FDD-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-E-DCH-PowerOffset-for-SchedulingInfo
                                                     CRITICALITY ignore EXTENSION E-DCH-PowerOffset-for-SchedulingInfo
                                                                                                                         PRESENCE optional |
```

```
{ ID id-SixteenQAM-UL-Operation-Indicator
                                                     CRITICALITY reject EXTENSION SixteenQAM-UL-Operation-Indicator
                                                                                                                                 PRESENCE
optional}|
    { ID id-E-AGCH-Table-Choice
                                                     CRITICALITY ignore EXTENSION E-AGCH-Table-Choice
                                                                                                                  PRESENCE conditional }.
    -- The IE shall be present if the SixteenOAM UL Operation Indicator IE is set to "Activate"--
EDCH-FDD-InformationResponse ::= SEQUENCE {
    eDCH-MACdFlow-Specific-InformationResponse
                                                         EDCH-MACdFlow-Specific-InformationResponse,
   hARO-Process-Allocation-Scheduled-2ms-EDCH
                                                         HARO-Process-Allocation-2ms-EDCH
                          OPTIONAL,
                                                         ProtocolExtensionContainer { { EDCH-FDD-InformationResponse-ExtIEs } }
    iE-Extensions
   OPTIONAL,
    . . .
EDCH-FDD-InformationResponse-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
EDCH-MACdFlow-Specific-InformationResponse ::= SEQUENCE (SIZE (1..maxNrOfEDCHMACdFlows)) OF EDCH-MACdFlow-Specific-InformationResponseItem
EDCH-MACdFlow-Specific-InformationResponseItem ::= SEOUENCE {
    eDCH-MACdFlow-ID
                                                 EDCH-MACdFlow-ID,
   bindingID
                                                 BindingID
       OPTIONAL,
   transportLayerAddress
                                                 TransportLayerAddress
       OPTIONAL,
   hARO-Process-Allocation-NonSched-2ms-EDCH
                                                 HARO-Process-Allocation-2ms-EDCH
       OPTIONAL,
                              ProtocolExtensionContainer { {EDCH-MACdFlow-Specific-InformationResponseItem-ExtIEs} } OPTIONAL,
   iE-Extensions
    . . .
EDCH-MACdFlow-Specific-InformationResponseItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    PRESENCE optional
FDD only
EDCH-FDD-Information-To-Modify ::= SEQUENCE {
    eDCH-MACdFlow-Specific-Information
                                                 EDCH-MACdFlow-Specific-InfoToModifyList,
   hARQ-Process-Allocation-Scheduled-2ms-EDCH
                                                 HARO-Process-Allocation-2ms-EDCH
                   OPTIONAL,
    e-DCH-Maximum-Bitrate
                                                 E-DCH-Maximum-Bitrate
   OPTIONAL,
   e-DCH-Processing-Overload-Level
                                                 E-DCH-Processing-Overload-Level
   OPTIONAL,
    e-DCH-Reference-Power-Offset
                                                 E-DCH-Reference-Power-Offset
   OPTIONAL,
   mACeReset-Indicator
                                                 MACeReset-Indicator
   OPTIONAL,
```

```
ProtocolExtensionContainer { { EDCH-FDD-Information-To-Modify-ExtIEs } }
    iE-Extensions
    OPTIONAL.
EDCH-FDD-Information-To-Modify-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
{ ID id-E-DCH-PowerOffset-for-SchedulingInfo
                                                    CRITICALITY ignore EXTENSION
                                                                                    E-DCH-PowerOffset-for-SchedulingInfo
    PRESENCE optional } |
{ ID id-SixteenQAM-UL-Operation-Indicator
                                                    CRITICALITY reject EXTENSION
                                                                                    SixteenQAM-UL-Operation-Indicator
    PRESENCE optional }
{ ID id-E-DCH-MACdPDUSizeFormat
                                                    CRITICALITY reject EXTENSION
                                                                                    E-DCH-MACdPDUSizeFormat
    PRESENCE optional }
{ ID id-E-DCH-DL-Control-Channel-Grant-Information CRITICALITY ignore EXTENSION E-DCH-DL-Control-Channel-Grant-Information PRESENCE optional}
{ ID id-E-AGCH-Table-Choice
                                                    CRITICALITY ignore EXTENSION E-AGCH-Table-Choice
    PRESENCE conditional },
-- The IE shall be present if the SixteenQAM UL Operation Indicator IE is set to "Activate"--
E-DCH-FDD-Update-Information ::= SEQUENCE
    e-DCH-MACdFlow-Specific-UpdateInformation
                                                    E-DCH-MACdFlow-Specific-UpdateInformation
           OPTIONAL,
    hARQ-Process-Allocation-Scheduled-2ms-EDCH
                                                    HARQ-Process-Allocation-2ms-EDCH
                           OPTIONAL,
    iE-Extensions
                                                    ProtocolExtensionContainer { { E-DCH-FDD-Update-Information-ExtIEs } }
       OPTIONAL,
    . . .
E-DCH-FDD-Update-Information-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-E-DCH-DL-Control-Channel-Change-Information
                                                                CRITICALITY ignore EXTENSION E-DCH-DL-Control-Channel-Change-Information
        PRESENCE optional },
    . . .
E-DCH-MACdFlow-Specific-UpdateInformation ::= SEQUENCE (SIZE (1..maxNrOfEDCHMACdFlows)) OF E-DCH-MACdFlow-Specific-UpdateInformation-Item
E-DCH-MACdFlow-Specific-UpdateInformation-Item ::= SEQUENCE
    e-DCH-MACdFlow-ID
                                                    EDCH-MACdFlow-ID,
    hARO-Process-Allocation-NonSched-2ms-EDCH
                                                    HARO-Process-Allocation-2ms-EDCH
                            OPTIONAL,
                                                    ProtocolExtensionContainer { { E-DCH-MACdFlow-Specific-UpdateInformation-Item-ExtIEs} }
    iE-Extensions
    OPTIONAL,
E-DCH-MACdFlow-Specific-UpdateInformation-Item-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-DCH-DL-Control-Channel-Change-Information ::= SEQUENCE (SIZE (1..maxNrOfEDCHRLs)) OF E-DCH-DL-Control-Channel-Change-Information-Item
E-DCH-DL-Control-Channel-Change-Information-Item ::= SEQUENCE {
    e-DCH-RL-ID
                                            RL-ID,
```

```
ProtocolExtensionContainer { { E-DCH-DL-Control-Channel-Change-Information-Item-ExtIEs} } OPTIONAL,
    iE-Extensions
E-DCH-DL-Control-Channel-Change-Information-Item-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-DCH-DL-Control-Channel-Grant-Information ::= SEQUENCE (SIZE (1..maxNrOfEDCHRLs)) OF E-DCH-DL-Control-Channel-Grant-Information-Item
E-DCH-DL-Control-Channel-Grant-Information-Item ::= SEQUENCE {
    e-DCH-RL-ID
                                            RL-ID,
    iE-Extensions
                                            ProtocolExtensionContainer { { E-DCH-DL-Control-Channel-Grant-Information-Item-ExtIEs} } OPTIONAL,
E-DCH-DL-Control-Channel-Grant-Information-Item-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-DCH-Grant-Type-Information ::= CHOICE {
    e-DCH-Non-Scheduled-Transmission-Grant
                                                E-DCH-Non-Scheduled-Transmission-Grant-Items,
    e-DCH-Scheduled-Transmission-Grant
                                                NULL,
    . . .
E-DCH-HARO-PO-FDD ::= INTEGER (0.. maxNrOfEDCH-HARO-PO-OUANTSTEPs)
E-DCH-LogicalChannelInformation ::= SEQUENCE (SIZE (1..maxNoOfLogicalChannels)) OF E-DCH-LogicalChannelInformationItem
E-DCH-LogicalChannelInformationItem ::= SEQUENCE {
    logicalChannelId
                                    LogicalChannelID,
    schedulingPriorityIndicator
                                    SchedulingPriorityIndicator,
    schedulingInformation
                                    SchedulingInformation,
                                    MACes-Guaranteed-Bitrate
    mACes-GuaranteedBitRate
                                                                    OPTIONAL,
    eDCH-DDI-Value
                                    EDCH-DDI-Value,
    mACd-PDU-Size-List
                                    E-DCH-MACdPDU-SizeList,
                                    ProtocolExtensionContainer { { E-DCH-LogicalChannelInformationItem-ExtIEs } }
    iE-Extensions
                                                                                                                                        OPTIONAL,
    . . .
E-DCH-LogicalChannelInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
     ID id-MaximumMACdPDU-SizeExtended
                                            CRITICALITY reject
                                                                    EXTENSION
                                                                                MAC-PDU-SizeExtended
                                                                                                                 PRESENCE optional |
     ID id-MACes-Maximum-Bitrate-LCR
                                            CRITICALITY ignore
                                                                    EXTENSION
                                                                                MACes-Maximum-Bitrate-LCR
                                                                                                                         PRESENCE optional | --
1.28Mcps TDD only
    { ID id-UE-AggregateMaximumBitRate-Enforcement-Indicator
                                                                CRITICALITY ignore EXTENSION UE-AggregateMaximumBitRate-Enforcement-Indicator
    PRESENCE optional },
E-DCH-Maximum-Bitrate ::= INTEGER (0..5742,...,5743..11498)
```

```
E-DCH-PowerOffset-for-SchedulingInfo ::= INTEGER (0.. maxNrOfEDCH-HARO-PO-OUANTSTEPs)
E-DCH-Processing-Overload-Level ::= INTEGER (0..10,...)
E-DCH-Reference-Power-Offset ::= INTEGER (0.. maxNrOfEDCH-HARO-PO-QUANTSTEPs)
E-DCH-MACdPDU-SizeList ::= SEOUENCE (SIZE (1..maxNrOfMACdPDUSize)) OF E-DCH-MACdPDU-SizeListItem
E-DCH-MACdPDU-SizeListItem ::= SEOUENCE {
   mACdPDU-Size
                                    MACdPDU-Size,
                                    ProtocolExtensionContainer { { E-DCH-MACdPDU-SizeListItem-ExtIEs } }
    iE-Extensions
                                                                                                                        OPTIONAL,
E-DCH-MACdPDU-SizeListItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-DCH-MACdPDUSizeFormat ::= ENUMERATED {
    fixedMACdPDU-Size,
    flexibleMACdPDU-Size
E-DCH-LogicalChannelToModify ::= SEOUENCE (SIZE (1..maxNoOfLogicalChannels)) OF E-DCH-LogicalChannelToModifyItem
E-DCH-LogicalChannelToModifyItem ::= SEQUENCE {
    logicalChannelId
                                    LogicalChannelID,
    schedulingPriorityIndicator
                                    SchedulingPriorityIndicator
                                                                    OPTIONAL,
    schedulingInformation
                                    SchedulingInformation
                                                                    OPTIONAL,
    mACes-GuaranteedBitRate
                                    MACes-Guaranteed-Bitrate
                                                                    OPTIONAL,
                                    EDCH-DDI-Value
    eDCH-DDI-Value
                                                                    OPTIONAL,
    mACd-PDU-Size-List
                                    E-DCH-MACdPDU-SizeToModifyList,
   iE-Extensions
                                    ProtocolExtensionContainer { { E-DCH-LogicalChannelToModifyItem-ExtIEs } }
                                                                                                                                OPTIONAL,
E-DCH-LogicalChannelToModifyItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-MaximumMACdPDU-SizeExtended
                                            CRITICALITY reject
                                                                    EXTENSION
                                                                               MAC-PDU-SizeExtended
                                                                                                         PRESENCE optional |
     ID id-MACes-Maximum-Bitrate-LCR
                                            CRITICALITY ignore
                                                                    EXTENSION
                                                                                MACes-Maximum-Bitrate-LCR
                                                                                                                        PRESENCE optional \, --
1.28Mcps TDD only
E-DCH-MACdPDU-SizeToModifyList ::= SEOUENCE (SIZE (0..maxNrOfMACdPDUSize)) OF E-DCH-MACdPDU-SizeListItem
E-DCH-LogicalChannelToDelete ::= SEQUENCE (SIZE (1..maxNoOfLogicalChannels)) OF E-DCH-LogicalChannelToDeleteItem
E-DCH-LogicalChannelToDeleteItem ::= SEQUENCE {
    logicalChannelId
                                    LogicalChannelID,
```

```
ProtocolExtensionContainer { { E-DCH-LogicalChannelToDeleteItem-ExtIEs } }
    iE-Extensions
                                                                                                                                 OPTIONAL,
E-DCH-LogicalChannelToDeleteItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
LogicalChannelID ::= INTEGER (1..15)
EDCH-MACdFlow-ID ::= INTEGER (0..maxNrOfEDCHMACdFlows-1)
EDCH-MACdFlow-ID-LCR ::= INTEGER (0..maxNrOfEDCHMACdFlowsLCR-1)
EDCH-MACdFlows-Information ::= SEQUENCE {
                                                    EDCH-MACdFlow-Specific-InfoList,
    eDCH-MACdFlow-Specific-Information
                                                    ProtocolExtensionContainer { { EDCH-MACdFlow-Information-ExtIEs } }
    iE-Extensions
                                                                                                                                        OPTIONAL,
    . . .
E-DCH-MACdFlow-Multiplexing-List ::= BIT STRING ( SIZE(maxNrOfEDCHMACdFlows) )
EDCH-MACdFlow-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
EDCH-MACdFlow-Specific-InfoList ::= SEOUENCE (SIZE (1..maxNrOfEDCHMACdFlows)) OF EDCH-MACdFlow-Specific-InfoItem
EDCH-MACdFlow-Specific-InfoItem ::= SEQUENCE {
    eDCH-MACdFlow-ID
                                        EDCH-MACdFlow-ID,
    allocationRetentionPriority
                                        AllocationRetentionPriority
                                                                            OPTIONAL,
                                        Tnl0os
                                                                             OPTIONAL,
                                        PayloadCRC-PresenceIndicator,
    payloadCRC-PresenceIndicator
   maxNr-Retransmissions-EDCH
                                        MaxNr-Retransmissions-EDCH,
    trafficClass
                                        TrafficClass,
    eDCH-HARQ-PO-FDD
                                        E-DCH-HARQ-PO-FDD,
    eDCH-MACdFlow-Multiplexing-List
                                        E-DCH-MACdFlow-Multiplexing-List
                                                                            OPTIONAL,
    eDCH-Grant-Type-Information
                                        E-DCH-Grant-Type-Information
                                                                            OPTIONAL,
    bundlingModeIndicator
                                        BundlingModeIndicator
                                                                            OPTIONAL,
    eDCHLogicalChannelInformation
                                        E-DCH-LogicalChannelInformation,
                                        ProtocolExtensionContainer { { EDCH-MACdFlow-Specific-InfoItem-ExtIEs } }
    iE-Extensions
                                                                                                                                        OPTIONAL,
EDCH-MACdFlow-Specific-InfoItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    {ID id-TrCH-SrcStatisticsDescr CRITICALITY ignore EXTENSION TrCH-SrcStatisticsDescr PRESENCE optional },
    . . .
EDCH-MACdFlow-Specific-InfoToModifyList ::= SEQUENCE (SIZE (1..maxNrOfEDCHMACdFlows)) OF EDCH-MACdFlow-Specific-InfoToModifyItem
EDCH-MACdFlow-Specific-InfoToModifyItem ::= SEQUENCE {
    eDCH-MACdFlow-ID
                                        EDCH-MACdFlow-ID,
```

. . .

```
allocationRetentionPriority
                                        AllocationRetentionPriority
                                                                             OPTIONAL,
    transportBearerRequestIndicator
                                        TransportBearerRequestIndicator,
    tnlOoS
                                        TnlOos
                                                                             OPTIONAL.
    maxNr-Retransmissions-EDCH
                                        MaxNr-Retransmissions-EDCH
                                                                             OPTIONAL,
    trafficClass
                                        TrafficClass
                                                                             OPTIONAL,
                                        E-DCH-HARO-PO-FDD
    eDCH-HARO-PO-FDD
                                                                             OPTIONAL,
    eDCH-MACdFlow-Multiplexing-List
                                        E-DCH-MACdFlow-Multiplexing-List
                                                                             OPTIONAL,
                                        E-DCH-Grant-Type-Information
    eDCH-Grant-Type-Information
                                                                             OPTIONAL,
    bundlingModeIndicator
                                        BundlingModeIndicator
                                                                             OPTIONAL,
    eDCH-LogicalChannelToAdd
                                        E-DCH-LogicalChannelInformation
                                                                             OPTIONAL,
    eDCH-LogicalChannelToModify
                                        E-DCH-LogicalChannelToModify
                                                                             OPTIONAL,
    eDCH-LogicalChannelToDelete
                                        E-DCH-LogicalChannelToDelete
                                                                             OPTIONAL,
    iE-Extensions
                                        ProtocolExtensionContainer { { EDCH-MACdFlow-Specific-InfoToModifyItem-ExtIEs } }
    OPTIONAL,
    . . .
EDCH-MACdFlow-Specific-InfoToModifyItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
EDCH-MACdFlows-To-Delete ::= SEQUENCE (SIZE (1..maxNrOfEDCHMACdFlows)) OF EDCH-MACdFlows-To-Delete-Item
EDCH-MACdFlows-To-Delete-Item ::= SEOUENCE {
    eDCH-MACdFlow-ID
                                        EDCH-MACdFlow-ID,
    iE-Extensions
                                        ProtocolExtensionContainer { { EDCH-MACdFlows-To-Delete-Item-ExtIEs } }
                                                                                                                                 OPTIONAL,
    . . .
EDCH-MACdFlows-To-Delete-Item-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
EDCH-RL-Indication ::= ENUMERATED {
    eDCH,
    non-EDCH
E-DCH-Non-Scheduled-Transmission-Grant-Items ::= SEQUENCE {
    -- The following IE shall be ignored if id-Ext-Max-Bits-MACe-PDU-non-scheduled is present in E-DCH-Non-Scheduled-Transmission-Grant-Items-
ExtIEs
    maxBits-MACe-PDU-non-scheduled
                                                Max-Bits-MACe-PDU-non-scheduled,
                                                HARO-Process-Allocation-2ms-EDCH
    hARO-Process-Allocation-NonSched-2ms
                OPTIONAL.
    iE-Extensions
                                                ProtocolExtensionContainer { { E-DCH-Non-Scheduled-Transmission-Grant-Items-ExtIEs} }
    OPTIONAL,
    . . .
E-DCH-Non-Scheduled-Transmission-Grant-Items-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    -- The following IE shall be present if the maximum number of bits to be signalled exceeds maxNrOfBits-MACe-PDU-non-scheduled
    { ID id-Ext-Max-Bits-MACe-PDU-non-scheduled
                                                 CRITICALITY reject
                                                                             EXTENSION Ext-Max-Bits-MACe-PDU-non-scheduled
                                                                                                                                         PRESENCE
optional},
```

```
E-DCH-TFCI-Table-Index ::= INTEGER (0..1,...,2..7)
E-DCH-Serving-cell-change-informationResponse ::= SEQUENCE {
    e-DCH-serving-cell-outcome-choice
                                            E-DCH-serving-cell-change-choice,
    iE-Extensions
                                            ProtocolExtensionContainer { { E-DCH-serving-cell-change-informationResponse-ExtIEs} } OPTIONAL,
E-DCH-serving-cell-change-informationResponse-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-DCH-serving-cell-change-choice ::= CHOICE {
    e-DCH-serving-cell-change-successful
                                                E-DCH-serving-cell-change-successful,
    e-DCH-serving-cell-change-unsuccessful
                                                E-DCH-serving-cell-change-unsuccessful,
E-DCH-serving-cell-change-successful ::= SEQUENCE {
    e-DCH-RL-InformationList-Rsp
                                                    E-DCH-RL-InformationList-Rsp,
    iE-Extensions
                                                    ProtocolExtensionContainer { { E-DCH-serving-cell-change-successful-ExtIEs} } OPTIONAL,
    . . .
E-DCH-serving-cell-change-successful-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-DCH-RL-InformationList-Rsp ::= SEOUENCE (SIZE (0..maxNrOfRLs)) OF E-DCH-RL-InformationList-Rsp-Item
E-DCH-RL-InformationList-Rsp-Item ::= SEQUENCE {
    e-DCH-reconfigured-RL-Id
                                                RL-ID,
    e-DCH-FDD-DL-Control-Channel-Info
                                                EDCH-FDD-DL-ControlChannelInformation,
   iE-Extensions
                                                ProtocolExtensionContainer { { E-DCH-RL-InformationList-Rsp-Item-ExtIEs} } }
                                                                                                                                 OPTIONAL,
E-DCH-RL-InformationList-Rsp-Item-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-DCH-serving-cell-change-unsuccessful ::= SEQUENCE {
                                    ProtocolExtensionContainer { { E-DCH-serving-cell-change-unsuccessful-ExtIEs} } OPTIONAL,
    iE-Extensions
E-DCH-serving-cell-change-unsuccessful-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
E-DCH-TTI-Length ::= CHOICE {
   t.wo-ms
               DTX-Cycle-2ms-Items,
   ten-ms
               DTX-Cycle-10ms-Items,
E-DCH-TTI-Length-to-Modify ::= CHOICE {
               DTX-Cycle-2ms-to-Modify-Items,
               DTX-Cycle-10ms-to-Modify-Items,
   ten-ms
EDPCH-Information-FDD ::= SEOUENCE {
   maxSet-E-DPDCHs
                                                          Max-Set-E-DPDCHs,
   punctureLimit
                                                          PunctureLimit,
                                                             E-TFCS-Information,
   e-TFCS-Information
   e-TTI
                                                          E-TTI,
   e-DPCCH-PO
                                                          E-DPCCH-PO,
                                                          E-RGCH-2-IndexStepThreshold,
   e-RGCH-2-IndexStepThreshold
   e-RGCH-3-IndexStepThreshold
                                                          E-RGCH-3-IndexStepThreshold,
   hARQ-Info-for-E-DCH
                                                          HARQ-Info-for-E-DCH,
   hSDSCH-Configured-Indicator
                                                          HSDSCH-Configured-Indicator,
                                      ProtocolExtensionContainer { { EDPCH-Information-FDD-ExtIEs } }
   iE-Extensions
                                                                                                                    OPTIONAL,
EDPCH-Information-FDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-MinimumReducedE-DPDCH-GainFactor
                                                  CRITICALITY ignore EXTENSION MinimumReducedE-DPDCH-GainFactor
                                                                                                                    PRESENCE optional },
EDPCH-Information-RLReconfPrepare-FDD ::= SEQUENCE {
   maxSet-E-DPDCHs
                                              Max-Set-E-DPDCHs
                                                                      OPTIONAL,
   punctureLimit
                                              PunctureLimit
                                                                      OPTIONAL,
   e-TFCS-Information
                                              E-TFCS-Information
                                                                     OPTIONAL,
   e-TTI
                                              E-TTI
                                                                      OPTIONAL,
   e-DPCCH-PO
                                              E-DPCCH-PO
                                                                      OPTIONAL,
   e-RGCH-2-IndexStepThreshold
                                              E-RGCH-2-IndexStepThreshold
                                                                                 OPTIONAL,
    e-RGCH-3-IndexStepThreshold
                                              E-RGCH-3-IndexStepThreshold
                                                                                 OPTIONAL,
                                              HARO-Info-for-E-DCH
   hARO-Info-for-E-DCH
                                                                                 OPTIONAL,
                                              HSDSCH-Configured-Indicator
   hSDSCH-Configured-Indicator
                                                                                 OPTIONAL,
   iE-Extensions
                                      OPTIONAL,
EDPCH-Information-RLReconfPrepare-FDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-MinimumReducedE-DPDCH-GainFactor
                                                  CRITICALITY ignore EXTENSION MinimumReducedE-DPDCH-GainFactor
                                                                                                                    PRESENCE optional },
    . . .
EDPCH-Information-RLReconfRequest-FDD ::= SEQUENCE {
   maxSet-E-DPDCHs
                                                          Max-Set-E-DPDCHs
               OPTIONAL,
```

```
PunctureLimit
    punctureLimit
                OPTIONAL,
    e-TFCS-Information
                                                            E-TFCS-Information
                OPTIONAL,
                                                            E-TTI
    e-TTI
                OPTIONAL,
    e-DPCCH-PO
                                                            E-DPCCH-PO
    OPTIONAL,
    e-RGCH-2-IndexStepThreshold
                                                            E-RGCH-2-IndexStepThreshold
    OPTIONAL,
    e-RGCH-3-IndexStepThreshold
                                                            E-RGCH-3-IndexStepThreshold
                OPTIONAL,
    hARQ-Info-for-E-DCH
                                                            HARO-Info-for-E-DCH
                OPTIONAL,
    hSDSCH-Configured-Indicator
                                                            HSDSCH-Configured-Indicator
                OPTIONAL,
                                        ProtocolExtensionContainer { { EDPCH-Information-RLReconfRequest-FDD-ExtIEs } }
    iE-Extensions
                                                                                                                                        OPTIONAL,
EDPCH-Information-RLReconfRequest-FDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-MinimumReducedE-DPDCH-GainFactor
                                                    CRITICALITY ignore EXTENSION MinimumReducedE-DPDCH-GainFactor
                                                                                                                         PRESENCE optional },
E-DPCCH-PO ::= INTEGER (0..maxNrOfEDPCCH-PO-QUANTSTEPs)
E-DPDCH-PowerInterpolation ::= BOOLEAN
E-Primary-Secondary-Grant-Selector ::= ENUMERATED {
    primary,
    secondary
EHICH-SignatureSequence ::= INTEGER (0..maxNrofSigSeqERGHICH-1)
E-RGCH-Release-Indicator ::= ENUMERATED {e-RGCHreleased}
ERGCH-SignatureSequence ::= INTEGER (0..maxNrofSigSeqERGHICH-1)
E-Serving-Grant-Value ::= INTEGER (0..38)
E-RGCH-2-IndexStepThreshold ::= INTEGER (0..37)
E-RGCH-3-IndexStepThreshold ::= INTEGER (0..37)
EDCH-Serving-RL ::= CHOICE {
    e-DCH-Serving-RL-in-this-DRNS
                                            EDCH-Serving-RL-in-this-DRNS,
    e-DCH-Serving-RL-not-in-this-DRNS
                                            NULL,
    . . .
```

```
EDCH-Serving-RL-in-this-DRNS ::= SEQUENCE {
   e-DCH-Serving-RL-Id
                                  RL-ID.
   iE-Extensions
                                  ProtocolExtensionContainer { { EDCH-Serving-RL-in-this-DRNS-ExtIEs} }
                                                                                                               OPTIONAL.
EDCH-Serving-RL-in-this-DRNS-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Enhanced-FACH-Information-ResponseFDD ::= SEQUENCE {
    common-HS-DSCH-RNTI-priorityQueueInfo-EnhancedFACH
                                                                     PriorityQueue-InfoList-EnhancedFACH-PCH,
   dedicated-HS-DSCH-RNTI-priorityQueueInfo-EnhancedFACH
                                                                     PriorityQueue-InfoList-EnhancedFACH-PCH,
   priorityQueueInfo-EnhancedPCH
                                              PriorityQueue-InfoList-EnhancedFACH-PCH
                                                                                                                   OPTIONAL,
   hSDSCH-Initial-Capacity-Allocation
                                                         HSDSCH-Initial-Capacity-Allocation,
   hSDSCH-RNTI
                                                         HSDSCH-RNTI
               OPTIONAL,
                                      ProtocolExtensionContainer { { Enhanced-FACH-Information-ResponseFDD-ExtIEs } }
    iE-Extensions
                                                                                                                                  OPTIONAL,
Enhanced-FACH-Information-ResponseFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Enhanced-FACH-Information-ResponseLCR ::= SEQUENCE
    common-HS-DSCH-RNTI-priorityQueueInfo-EnhancedFACH
                                                                     PriorityOueue-InfoList-EnhancedFACH-PCH,
   dedicated-HS-DSCH-RNTI-priorityQueueInfo-EnhancedFACH
                                                                     PriorityOueue-InfoList-EnhancedFACH-PCH,
   priorityOueueInfo-EnhancedPCH
                                              PriorityOueue-InfoList-EnhancedFACH-PCH
                                                                                                                   OPTIONAL,
   hSDSCH-Initial-Capacity-Allocation
                                                         HSDSCH-Initial-Capacity-Allocation,
   hSDSCH-RNTI
                                                         HSDSCH-RNTI
               OPTIONAL,
   iE-Extensions
                                      OPTIONAL,
Enhanced-FACH-Information-ResponseLCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Enhanced-FACH-Support-Indicator ::= NULL
EnhancedHSServingCC-Abort ::= ENUMERATED {abortEnhancedHSServingCC,...}
Enhanced-PCH-Capability ::= ENUMERATED {
   enhanced-pch-capable,
    enhanced-pch-not-capable
E-RNTI ::= INTEGER (0..65535)
E-TFCI ::= INTEGER (0..127)
```

```
E-TFCI-BetaEC-Boost ::= INTEGER (0..127,...)
E-TFCI-Boost-Information ::= SEOUENCE {
   e-TFCI-BetaEC-Boost
                                                E-TFCI-BetaEC-Boost,
   uL-Delta-T2TP
                                                UL-Delta-T2TP
                                                                      OPTIONAL.
   -- This IE shall be present if the E-TFCI BetaEC Boost IE value is not set to 127.
                                                ProtocolExtensionContainer { { E-TFCI-Boost-Information-ExtIEs} }
                                                                                                                      OPTIONAL,
E-TFCI-Boost-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-TFCS-Information ::= SEQUENCE {
   e-DCH-TFCI-Table-Index
                                                       E-DCH-TFCI-Table-Index,
   e-DCH-Min-Set-E-TFCI
                                                E-TFCI,
   reference-E-TFCI-Information
                                                Reference-E-TFCI-Information,
                                                ProtocolExtensionContainer { {E-TFCS-Information-ExtIEs} }
   iE-Extensions
                                                                                                               OPTIONAL,
E-TFCS-Information-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
    PRESENCE
optional }|
   { ID id-E-TFCI-Boost-Information
                                                   CRITICALITY reject EXTENSION E-TFCI-Boost-Information
   PRESENCE optional } |
   { ID id-E-DPDCH-PowerInterpolation
                                                   CRITICALITY reject EXTENSION E-DPDCH-PowerInterpolation
       PRESENCE optional },
E-DCH-Minimum-Set-E-TFCIValidityIndicator ::= ENUMERATED {
   e-DCH-Minimum-Set-E-TFCI-response-not-valid
E-TTI ::= ENUMERATED {
   tti10,
   tti2
-- 10ms TTI, 2ms TTI
E-AGCH-PowerOffset ::= INTEGER (0..255,...)
-- PowerOffset = -32 + offset * 0.25
-- Unit dB, Range -32dB .. +31.75dB, Step +0.25dB
E-RGCH-PowerOffset ::= INTEGER (0..255,...)
-- PowerOffset = -32 + offset * 0.25
-- Unit dB, Range -32dB .. +31.75dB, Step +0.25dB
E-HICH-PowerOffset ::= INTEGER (0..255,...)
```

```
-- PowerOffset = -32 + offset * 0.25
-- Unit dB, Range -32dB .. +31.75dB, Step +0.25dB
Enhanced-PrimaryCPICH-EcNo
                                  ::= INTEGER (0..49)
EventA ::= SEQUENCE {
   measurementTreshold
                           MeasurementThreshold,
   measurementHysteresisTime MeasurementHysteresisTime
   iE-Extensions
                           ProtocolExtensionContainer { {EventA-ExtIEs} } OPTIONAL,
EventA-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
EventB ::= SEQUENCE {
   measurementTreshold
                           MeasurementThreshold,
   measurementHysteresisTime MeasurementHysteresisTime
                                                               OPTIONAL,
                           ProtocolExtensionContainer { {EventB-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
EventB-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
EventC ::= SEOUENCE {
   measurementIncreaseDecreaseThreshold MeasurementIncreaseDecreaseThreshold,
   measurementChangeTime
                               MeasurementChangeTime,
                           ProtocolExtensionContainer { {EventC-ExtIEs} } OPTIONAL,
   iE-Extensions
    . . .
EventC-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
EventD ::= SEOUENCE {
   measurementIncreaseDecreaseThreshold MeasurementIncreaseDecreaseThreshold,
   measurementChangeTime
                               MeasurementChangeTime,
                           ProtocolExtensionContainer { {EventD-ExtIEs} } OPTIONAL,
   iE-Extensions
EventD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
EventE ::= SEQUENCE {
   measurementThreshold1
                               MeasurementThreshold,
   measurementThreshold2
                               MeasurementThreshold
                                                               OPTIONAL,
   measurementHysteresisTime
                               MeasurementHysteresisTime
                                                               OPTIONAL,
```

```
reportPeriodicity
                                ReportPeriodicity
                                                             OPTIONAL,
    iE-Extensions
                            ProtocolExtensionContainer { {EventE-ExtIEs} } OPTIONAL,
EventE-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
EventF ::= SEOUENCE {
    measurementThreshold1
                                MeasurementThreshold,
    measurementThreshold2
                                MeasurementThreshold
                                                                 OPTIONAL,
                                MeasurementHysteresisTime
                                                                 OPTIONAL,
    measurementHysteresisTime
    reportPeriodicity
                            ReportPeriodicity
                                                         OPTIONAL,
    iE-Extensions
                            ProtocolExtensionContainer { {EventF-ExtIEs} } OPTIONAL,
EventF-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
EventH ::= SEQUENCE {
    measurementThreshold1
                                MeasurementThreshold,
    measurementThreshold2
                                MeasurementThreshold
                                                                 OPTIONAL,
    measurementHysteresisTime
                                MeasurementHysteresisTime
                                                                 OPTIONAL,
                                ReportPeriodicity
    reportPeriodicity
                                                                 OPTIONAL,
    measurementFluctuationRange INTEGER (0..100)
                                                                 OPTIONAL,
                                ProtocolExtensionContainer { {EventH-ExtIEs} } OPTIONAL,
    iE-Extensions
EventH-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Event1F-Parameters
                        ::= SEQUENCE {
                            MeasurementOuantity,
    measurementOuantity
    threshold
                            INTEGER(-120..165),
    . . .
                        ::= SEQUENCE {
Event1I-Parameters
    threshold
                            INTEGER(-120..-25),
    . . .
ExtendedGSMCellIndividualOffset ::= INTEGER (-50..-11 | 11..50)
E-DCH-Information ::= SEQUENCE {
    e-PUCH-Information
                                                 E-PUCH-Information,
    e-TFCS-Information-TDD
                                                E-TFCS-Information-TDD,
    e-DCH-MACdFlows-Information-TDD
                                                E-DCH-MACdFlows-Information-TDD,
    e-DCH-TDD-Information
                                                E-DCH-TDD-Information,
```

926

```
ProtocolExtensionContainer { { E-DCH-Information-ExtIEs} }
    iE-Extensions
                                                                                                                          OPTIONAL,
E-DCH-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-PUCH-Information ::= SEQUENCE {
   minCR
                                                CodeRate,
   maxCR
                                                CodeRate,
   harqInfo
                                                HARQ-Info-for-E-DCH,
   n-E-UCCH
                                                N-E-UCCH,
   iE-Extensions
                                                ProtocolExtensionContainer { { E-PUCH-Information-ExtIEs } }
                                                                                                                          OPTIONAL,
E-PUCH-Information-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
E-TFCS-Information-TDD ::= SEQUENCE {
    e-DCH-QPSK-RefBetaInfo
                                                E-DCH-QPSK-RefBetaInfo,
    e-DCH-sixteenOAM-RefBetaInfo
                                                E-DCH-sixteenOAM-RefBetaInfo,
                                                ProtocolExtensionContainer { { E-TFCS-Information-TDD-ExtIEs } }
    iE-Extensions
                                                                                                                          OPTIONAL,
    . . .
E-TFCS-Information-TDD-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
E-DCH-QPSK-RefBetaInfo ::= SEQUENCE (SIZE (1..maxNrOfRefBetas)) OF E-DCH-RefBeta-Item
E-DCH-sixteenOAM-RefBetaInfo ::= SEOUENCE (SIZE (1..maxNrOfRefBetas)) OF E-DCH-RefBeta-Item
E-DCH-RefBeta-Item ::= SEQUENCE {
    refCodeRate
                            CodeRate-short,
    refBeta
                            RefBeta
E-DCH-MACdFlows-Information-TDD ::= SEOUENCE (SIZE (1..maxNrOfEDCHMACdFlows)) OF E-DCH-MACdFlow-InfoTDDItem
E-DCH-MACdFlow-InfoTDDItem ::= SEQUENCE {
    e-DCH-MACdFlow-ID
                                                     EDCH-MACdFlow-ID,
                                                    AllocationRetentionPriority,
    allocationRetentionPriority
    tnl0os
                                                    Tnl0os
                                                                                 OPTIONAL,
    bindingID
                                                    BindingID
                                                                                 OPTIONAL,
    transportLayerAddress
                                                    TransportLayerAddress
                                                                                 OPTIONAL,
    payloadCRC-PresenceIndicator
                                                    PayloadCRC-PresenceIndicator,
    maximum-Number-of-Retransmissions-For-E-DCH
                                                    MaxNr-Retransmissions-EDCH,
    eDCH-HARO-PO-TDD
                                                    E-DCH-HARO-PO-TDD,
    eDCH-MACdFlow-Multiplexing-List
                                                    E-DCH-MACdFlow-Multiplexing-List
                                                                                                                          OPTIONAL,
    eDCH-Grant-TypeTDD
                                                     E-DCH-Grant-TypeTDD,
```

```
eDCHLogicalChannelInformation
                                                     E-DCH-LogicalChannelInformation,
    iE-Extensions
                                                     ProtocolExtensionContainer { { E-DCH-MACdFlow-InfoTDDItem-ExtIEs} } }
    OPTIONAL.
E-DCH-MACdFlow-InfoTDDItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-eDCH-MACdFlow-Retransmission-Timer-LCR CRITICALITY ignore
                                                                             EXTENSION E-DCH-MACdFlow-Retransmission-Timer-LCR
                                                                                                                                         PRESENCE
optional }|
    { ID id-TrafficClass
                                                    CRITICALITY ignore
                                                                             EXTENSION TrafficClass
    PRESENCE mandatory },
E-DCH-MACdFlow-Retransmission-Timer-LCR ::= ENUMERATED {
ms10, ms15, ms20, ms25, ms30, ms35, ms40, ms45, ms50, ms55, ms60, ms65, ms70, ms75, ms80, ms85, ms90,
ms95, ms100, ms110, ms120, ms140, ms160, ms200, ms240, ms280, ms320, ms400, ms480, ms560,...
E-DCH-HARQ-PO-TDD ::= INTEGER (0..6)
E-DCH-Grant-TypeTDD ::= ENUMERATED {
    scheduled,
    non-scheduled
E-DCH-TimeslotResource ::= BIT STRING (SIZE (13))
E-DCH-PowerResource ::= INTEGER(1..32)
TddE-PUCH-Offset ::= INTEGER(0..255)
E-DCH-TDD-Information ::= SEQUENCE {
    e-DCH-TDD-Maximum-Bitrate
                                                     E-DCH-TDD-Maximum-Bitrate
                                                                                                                          OPTIONAL,
    e-DCH-Processing-Overload-Level
                                                     E-DCH-Processing-Overload-Level
                                                                                                                          OPTIONAL,
    e-DCH-PowerOffset-for-SchedulingInfo
                                                     E-DCH-PowerOffset-for-SchedulingInfo
                                                                                                                          OPTIONAL,
                                                     ProtocolExtensionContainer { { E-DCH-TDD-Information-ExtIEs } }
    iE-Extensions
                                                                                                                          OPTIONAL,
E-DCH-TDD-Information-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
E-DCH-TDD-Maximum-Bitrate ::= INTEGER (0..9201,...)
E-DCH-Information-Reconfig ::= SEQUENCE {
    e-PUCH-Information
                                                 E-PUCH-Information
                                                                                                                      OPTIONAL,
    e-TFCS-Information-TDD
                                                E-TFCS-Information-TDD
                                                                                                                      OPTIONAL,
                                                E-DCH-MACdFlows-Information-TDD
    e-DCH-MACdFlows-to-Add
                                                                                                                     OPTIONAL,
    e-DCH-MACdFlows-to-Delete
                                                 EDCH-MACdFlows-To-Delete
                                                                                                                      OPTIONAL,
    e-DCH-Non-Scheduled-Grant-Info
                                                E-DCH-Non-Scheduled-Grant-Info
                                                                                                                     OPTIONAL,
    e-DCH-TDD-Information
                                                E-DCH-TDD-Information
                                                                                                                      OPTIONAL,
```

```
e-DCH-TDD-Information-to-Modify
                                                 E-DCH-TDD-Information-to-Modify
                                                                                                                      OPTIONAL,
    iE-Extensions
                                                 ProtocolExtensionContainer { { E-DCH-Information-Reconfig-ExtIEs} }
                                                                                                                          OPTIONAL.
E-DCH-Information-Reconfig-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-DCH-TDD-Information-to-Modify ::= SEOUENCE {
    e-DCH-TDD-Information-to-Modify-List
                                            E-DCH-TDD-Information-to-Modify-List
                                                                                     OPTIONAL,
    mACeReset-Indicator
                                            MACeReset-Indicator
                                                                                      OPTIONAL,
    iE-Extensions
                                            ProtocolExtensionContainer { { E-DCH-TDD-Information-to-Modify-ExtIEs } }
                                                                                                                                  OPTIONAL,
    . . .
E-DCH-TDD-Information-to-Modify-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
      ID id-E-DCH-MACdPDUSizeFormat
                                        CRITICALITY reject EXTENSION E-DCH-MACdPDUSizeFormat
                                                                                                                      PRESENCE optional } |
     ID id-UE-TS0-CapabilityLCR
                                                                                                                      PRESENCE optional },
                                        CRITICALITY ignore EXTENSION UE-TS0-CapabilityLCR
E-DCH-TDD-Information-to-Modify-List ::= SEQUENCE (SIZE (1..maxNrOfEDCHMACdFlows)) OF E-DCH-MACdFlow-ModifyTDDItem
E-DCH-MACdFlow-ModifyTDDItem ::= SEOUENCE {
    e-DCH-MACdFlow-ID
                                                     EDCH-MACdFlow-ID,
    allocationRetentionPriority
                                                     AllocationRetentionPriority
                                                                                      OPTIONAL.
    transportBearerRequestIndicator
                                                     TransportBearerRequestIndicator,
    bindingID
                                                     BindingID
                                                                                 OPTIONAL,
    transportLayerAddress
                                                     TransportLayerAddress
                                                                                 OPTIONAL,
    tnl0os
                                                     Tnl0os
                                                                                 OPTIONAL,
    maximum-Number-of-Retransmissions-For-E-DCH
                                                     MaxNr-Retransmissions-EDCH
                                                                                      OPTIONAL,
    eDCH-HARO-PO-TDD
                                                     E-DCH-HARO-PO-TDD
                                                                                                                  OPTIONAL,
    eDCH-MACdFlow-Multiplexing-List
                                                     E-DCH-MACdFlow-Multiplexing-List
                                                                                                                  OPTIONAL,
    eDCH-Grant-TypeTDD
                                                     E-DCH-Grant-TypeTDD
                                                                                                                  OPTIONAL,
                                                     E-DCH-LogicalChannelInformation
    e-DCH-LogicalChannelToAdd
                                                                                                                      OPTIONAL,
    e-DCH-LogicalChannelToModify
                                                     E-DCH-LogicalChannelToModify
                                                                                                                      OPTIONAL,
    e-DCH-LogicalChannelToDelete
                                                     E-DCH-LogicalChannelToDelete
                                                                                                                      OPTIONAL,
                                                     ProtocolExtensionContainer { {E-DCH-MACdFlow-ModifyTDDItem-ExtIEs } }
    iE-Extensions
                                                                                                                                  OPTIONAL,
E-DCH-MACdFlow-ModifyTDDItem-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-eDCH-MACdFlow-Retransmission-Timer-LCR
                                                                                 EXTENSION E-DCH-MACdFlow-Retransmission-Timer-LCR
                                                         CRITICALITY ignore
    PRESENCE optional } |
    { ID id-TrafficClass
                                                         CRITICALITY ignore
                                                                                 EXTENSION TrafficClass
           PRESENCE optional },
    . . .
E-DCH-Information-Response ::= SEQUENCE {
    e-DCH-TDD-MACdFlow-Specific-InformationResp
                                                     E-DCH-TDD-MACdFlow-Specific-InformationResp OPTIONAL,
    e-AGCH-Specific-Information-ResponseTDD
                                                     E-AGCH-Specific-InformationRespListTDD OPTIONAL,
    e-HICH-Information-Response
                                                     E-HICH-InformationResp OPTIONAL,
    e-DCH-Non-Scheduled-Grant-Info
                                                     E-DCH-Non-Scheduled-Grant-Info OPTIONAL,
```

```
e-RNTI
                                                     E-RNTI,
   iE-Extensions
                                                     ProtocolExtensionContainer { { E-DCH-Information-Response-ExtIEs } }
                                                                                                                                         OPTIONAL,
E-DCH-Information-Response-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-DCH-TDD-MACdFlow-Specific-InformationResp ::= SEQUENCE (SIZE (1..maxNrOfEDCHMACdFlows)) OF E-DCH-TDD-MACdFlow-Specific-InformationResp-Item
E-DCH-TDD-MACdFlow-Specific-InformationResp-Item ::= SEQUENCE {
    e-DCH-MacdFlow-Id
                                                     EDCH-MACdFlow-ID,
   bindingID
                                                     BindingID
                                                                                 OPTIONAL,
    transportLayerAddress
                                                    TransportLayerAddress
                                                                                 OPTIONAL,
    iE-Extensions
                                                     ProtocolExtensionContainer { { E-DCH-TDD-MACdFlow-Specific-InformationRespItem-ExtIEs } }
    OPTIONAL,
E-DCH-TDD-MACdFlow-Specific-InformationRespItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-AGCH-Specific-InformationRespListTDD ::= SEQUENCE (SIZE (1..maxNrOfEAGCHCodes)) OF E-AGCH-Specific-InformationResp-ItemTDD
E-AGCH-Specific-InformationResp-ItemTDD ::= SEQUENCE {
    timeslot
                                                     TimeSlot,
                                                     MidambleShiftAndBurstType,
    midambleShiftAndBurstType
    tDD-ChannelisationCode
                                                    TDD-ChannelisationCode,
                                                     ProtocolExtensionContainer { { E-AGCH-Specific-InformationResp-ItemTDD-ExtIEs } }
    iE-Extensions
    OPTIONAL,
    . . .
E-AGCH-Specific-InformationResp-ItemTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-HICH-InformationResp::= SEQUENCE {
    timeslot
                                                     TimeSlot,
    midambleShiftAndBurstType
                                                     MidambleShiftAndBurstType,
    tDD-ChannelisationCode
                                                     TDD-ChannelisationCode,
    e-HICH-TimeOffset
                                                     E-HICH-TimeOffset,
    iE-Extensions
                                                     ProtocolExtensionContainer { { E-HICH-InformationResp-ExtIEs } }
                                                                                                                                 OPTIONAL,
E-HICH-InformationResp-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
E-HICH-TimeOffset ::= INTEGER (4..44)
```

```
E-DCH-Non-Scheduled-Grant-Info ::= SEQUENCE {
    timeslotResource
                                                 E-DCH-TimeslotResource.
    powerResource
                                                 E-DCH-PowerResource.
    repetitionPeriod
                                                 RepetitionPeriod,
    repetitionLength
                                                 RepetitionLength,
    tddE-PUCH-Offset
                                                 TddE-PUCH-Offset,
    tdd-ChannelisationCode
                                                 TDD-ChannelisationCode.
    iE-Extensions
                                                 ProtocolExtensionContainer { { E-DCH-Non-Scheduled-Grant-Info-ExtIEs } }
                                                                                                                                          OPTIONAL,
E-DCH-Non-Scheduled-Grant-Info-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-DCH-768-Information ::= SEQUENCE {
    e-PUCH-Information
                                                 E-PUCH-Information,
    e-TFCS-Information-TDD
                                                 E-TFCS-Information-TDD,
    e-DCH-MACdFlows-Information-TDD
                                                 E-DCH-MACdFlows-Information-TDD,
    e-DCH-TDD-Information768
                                                 E-DCH-TDD-Information768,
                                                 ProtocolExtensionContainer { { E-DCH-768-Information-ExtIEs} }
    iE-Extensions
                                                                                                                          OPTIONAL,
E-DCH-768-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
E-DCH-TDD-Information768 ::= SEQUENCE {
                                                     E-DCH-TDD-Maximum-Bitrate768
    e-DCH-TDD-Maximum-Bitrate768
                                                                                                                          OPTIONAL,
    e-DCH-Processing-Overload-Level
                                                     E-DCH-Processing-Overload-Level
                                                                                                                          OPTIONAL,
    e-DCH-PowerOffset-for-SchedulingInfo
                                                     E-DCH-PowerOffset-for-SchedulingInfo
                                                                                                                          OPTIONAL,
                                                     ProtocolExtensionContainer { { E-DCH-TDD-Information768-ExtIEs } }
    iE-Extensions
                                                                                                                                  OPTIONAL,
    . . .
E-DCH-TDD-Information768-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
E-DCH-TDD-Maximum-Bitrate768 ::= INTEGER (0..17713,...)
E-DCH-768-Information-Reconfig ::= SEQUENCE {
    e-PUCH-Information
                                                 E-PUCH-Information
                                                                                                                      OPTIONAL,
    e-TFCS-Information-TDD
                                                 E-TFCS-Information-TDD
                                                                                                                      OPTIONAL,
    e-DCH-MACdFlows-to-Add
                                                 E-DCH-MACdFlows-Information-TDD
                                                                                                                      OPTIONAL,
    e-DCH-MACdFlows-to-Delete
                                                 EDCH-MACdFlows-To-Delete
                                                                                                                      OPTIONAL,
    e-DCH-Non-Scheduled-Grant-Info768
                                                 E-DCH-Non-Scheduled-Grant-Info768
                                                                                                                      OPTIONAL,
    e-DCH-TDD-Information768
                                                 E-DCH-TDD-Information768
                                                                                                                      OPTIONAL,
    e-DCH-TDD-Information-to-Modify
                                                 E-DCH-TDD-Information-to-Modify
                                                                                                                      OPTIONAL,
    iE-Extensions
                                                 ProtocolExtensionContainer { { E-DCH-768-Information-Reconfig-ExtIEs} } 
                                                                                                                                  OPTIONAL,
```

```
E-DCH-768-Information-Reconfig-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-DCH-768-Information-Response ::= SEQUENCE {
    e-DCH-TDD-MACdFlow-Specific-InformationResp
                                                     E-DCH-TDD-MACdFlow-Specific-InformationResp OPTIONAL,
    e-AGCH-Specific-Information-Response768TDD
                                                     E-AGCH-Specific-InformationRespList768TDD OPTIONAL,
    e-HICH-Information-Response768
                                                     E-HICH-InformationResp768 OPTIONAL,
    e-DCH-Non-Scheduled-Grant-Info768
                                                     E-DCH-Non-Scheduled-Grant-Info768
                                                                                         OPTIONAL,
    e-RNTI
                                                     E-RNTI,
    iE-Extensions
                                                     ProtocolExtensionContainer { { E-DCH-768-Information-Response-ExtIEs } }
                                                                                                                                         OPTIONAL,
    . . .
E-DCH-768-Information-Response-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-AGCH-Specific-InformationRespList768TDD ::= SEQUENCE (SIZE (1..maxNrOfEAGCHCodes)) OF E-AGCH-Specific-InformationResp-Item768TDD
E-AGCH-Specific-InformationResp-Item768TDD ::= SEQUENCE
    timeslot
    midambleShiftAndBurstType768
                                                     MidambleShiftAndBurstType768,
    tDD-ChannelisationCode768
                                                     TDD-ChannelisationCode768.
    iE-Extensions
                                                     ProtocolExtensionContainer { { E-AGCH-Specific-InformationResp-Item768TDD-ExtIEs } }
    OPTIONAL,
    . . .
E-AGCH-Specific-InformationResp-Item768TDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
E-HICH-InformationResp768::= SEQUENCE {
    timeslot
                                                     TimeSlot,
    midambleShiftAndBurstType768
                                                     MidambleShiftAndBurstType768,
    tDD-ChannelisationCode768
                                                     TDD-ChannelisationCode768,
    e-HICH-TimeOffset
                                                     E-HICH-TimeOffset,
    iE-Extensions
                                                     ProtocolExtensionContainer { { E-HICH-InformationResp768-ExtIEs } }
                                                                                                                                  OPTIONAL,
    . . .
E-HICH-InformationResp768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-DCH-Non-Scheduled-Grant-Info768 ::= SEOUENCE
    timeslotResource
                                                E-DCH-TimeslotResource,
    powerResource
                                                E-DCH-PowerResource,
    repetitionPeriod
                                                RepetitionPeriod,
    repetitionLength
                                                RepetitionLength,
    tddE-PUCH-Offset
                                                TddE-PUCH-Offset,
    tdd-ChannelisationCode768
                                                TDD-ChannelisationCode768,
    iE-Extensions
                                                ProtocolExtensionContainer { { E-DCH-Non-Scheduled-Grant-Info768-ExtIEs } }
                                                                                                                                         OPTIONAL,
```

```
E-DCH-Non-Scheduled-Grant-Info768-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
E-DCH-LCR-Information ::= SEQUENCE {
    e-PUCH-LCR-Information
                                                E-PUCH-LCR-Information,
    e-TFCS-Information-TDD
                                                E-TFCS-Information-TDD
    e-DCH-MACdFlows-Information-TDD
                                                E-DCH-MACdFlows-Information-TDD,
    e-DCH-LCR-TDD-Information
                                                E-DCH-LCR-TDD-Information.
                                                ProtocolExtensionContainer { { E-DCH-Information-LCR-ExtIEs} }
    iE-Extensions
                                                                                                                         OPTIONAL,
    . . .
E-DCH-Information-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-PUCH-LCR-Information ::= SEQUENCE {
   minCR
                                                CodeRate,
   maxCR
                                                CodeRate,
   hargInfo
                                                HARO-Info-for-E-DCH,
    pRxdesBase
                                                E-PUCH-PRXdesBase,
                                                TDD-TPC-UplinkStepSize-LCR,
    e-PUCH-TPC-Step-Size
    n-E-UCCH-LCR
                                                N-E-UCCH-LCR,
    iE-Extensions
                                                ProtocolExtensionContainer { { E-PUCH-Information-LCR-ExtIEs } }
                                                                                                                         OPTIONAL,
E-PUCH-Information-LCR-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-E-PUCH-PowerControlGAP
                                        CRITICALITY ignore
                                                                EXTENSION ControlGAP
                                                                                             PRESENCE optional
    . . .
E-PUCH-PRXdesBase ::= INTEGER(-112..-50)
--SETP=1
E-DCH-LCR-TDD-Information ::= SEQUENCE {
    e-DCH-Physical-Layer-Category-LCR
                                                E-DCH-Physical-Layer-Category-LCR
                                                                                                                     OPTIONAL,
    e-DCH-Processing-Overload-Level
                                                E-DCH-Processing-Overload-Level
                                                                                                                     OPTIONAL,
    e-DCH-PowerOffset-for-SchedulingInfo
                                                E-DCH-PowerOffset-for-SchedulingInfo
                                                                                                                     OPTIONAL,
    iE-Extensions
                                                ProtocolExtensionContainer { { E-DCH-LCR-TDD-Information-ExtIEs } }
                                                                                                                         OPTIONAL,
    . . .
E-DCH-LCR-TDD-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-Extended-E-DCH-LCRTDD-PhysicalLayerCategory
                                                                CRITICALITY reject EXTENSION Extended-E-DCH-LCRTDD-PhysicalLayerCategory
    PRESENCE optional }
    -- This IE shall be used if the E-DCH Physical Layer Category has a value larger than 5.
    { ID id-MaximumNumber-Of-Retransmission-For-SchedulingInfo-LCRTDD CRITICALITY ignore EXTENSION MaxNr-Retransmissions-EDCH
                                                                                                                                         PRESENCE
optional }|
```

```
{ ID id-E-DCH-RetransmissionTimer-For-SchedulingInfo-LCRTDD CRITICALITY ignore EXTENSION E-DCH-MACdFlow-Retransmission-Timer-LCR PRESENCE
optional }
    { ID id-E-AGCH-UE-Inactivity-Monitor-Threshold
                                                                CRITICALITY ignore
                                                                                    EXTENSION E-AGCH-UE-Inactivity-Monitor-Threshold
optional }
    { ID id-SNPL-Carrier-Group-Indicator
                                                                CRITICALITY reject EXTENSION SNPL-Carrier-Group-Indicator
                                                                                                                                         PRESENCE
optional }|
    { ID id-Multi-Carrier-E-DCH-LCRTDD-PhysicalLayerCategory
                                                                CRITICALITY reject EXTENSION Multi-Carrier-E-DCH-LCRTDD-PhysicalLayerCategory
    PRESENCE optional } |
    {ID id-UE-TS0-CapabilityLCR
                                                                CRITICALITY ignore EXTENSION UE-TSO-CapabilityLCR
                                                                                                                                 PRESENCE optional },
    . . .
E-DCH-Physical-Layer-Category-LCR ::= INTEGER (1..5)
Extended-E-DCH-LCRTDD-PhysicalLayerCategory ::= INTEGER (6,...)
Multi-Carrier-E-DCH-LCRTDD-PhysicalLayerCategory ::= INTEGER (1..8,...)
E-DCH-LCR-Information-Reconfig ::= SEQUENCE {
                                                E-PUCH-LCR-Information
    e-PUCH-LCR-Information
                                                                                                                     OPTIONAL.
    e-TFCS-Information-TDD
                                                E-TFCS-Information-TDD
                                                                                                                     OPTIONAL,
    e-DCH-MACdFlows-to-Add
                                                E-DCH-MACdFlows-Information-TDD
                                                                                                                     OPTIONAL,
    e-DCH-MACdFlows-to-Delete
                                                EDCH-MACdFlows-To-Delete
                                                                                                                     OPTIONAL,
    e-DCH-LCR-TDD-Information
                                                E-DCH-LCR-TDD-Information
                                                                                                                     OPTIONAL,
    e-DCH-TDD-Information-to-Modify
                                                E-DCH-TDD-Information-to-Modify
                                                                                                                     OPTIONAL,
    iE-Extensions
                                                ProtocolExtensionContainer { { E-DCH-Information-Reconfig-LCR-ExtIEs} }
                                                                                                                                 OPTIONAL.
E-DCH-Information-Reconfig-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
E-DCH-LCR-Information-Response ::= SEQUENCE {
    e-DCH-TDD-MACdFlow-Specific-InformationResp
                                                    E-DCH-TDD-MACdFlow-Specific-InformationResp OPTIONAL.
    e-AGCH-Specific-Information-Response-LCR-TDD
                                                    E-AGCH-Specific-InformationRespList-LCR-TDD OPTIONAL,
    e-HICH-Specific-Information-Response-LCR
                                                    E-HICH-Specific-InformationResp-LCR OPTIONAL,
    e-DCH-Non-Scheduled-Grant-Info-LCR
                                                    E-DCH-Non-Scheduled-Grant-Info-LCR OPTIONAL,
                                                    E-RNTI OPTIONAL,
    e-RNTI
    iE-Extensions
                                                     ProtocolExtensionContainer { { E-DCH-Information-Response-LCR-ExtIEs } }
                                                                                                                                         OPTIONAL,
E-DCH-Information-Response-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
E-AGCH-Specific-InformationRespList-LCR-TDD ::= SEQUENCE (SIZE (1..maxNrOfEAGCHCodes)) OF E-AGCH-Specific-InformationResp-Item-LCR-TDD
E-AGCH-Specific-InformationResp-Item-LCR-TDD ::= SEQUENCE {
    timeSlotLCR
                                                    TimeSlotLCR,
    midambleShiftLCR
                                                    MidambleShiftLCR,
    tDD-ChannelisationCode
                                                    TDD-ChannelisationCode,
```

```
ProtocolExtensionContainer { { E-AGCH-Specific-InformationResp-ItemTDD-LCR-ExtIEs } }
    iE-Extensions
   OPTIONAL,
    . . .
E-AGCH-Specific-InformationResp-ItemTDD-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-HICH-Specific-InformationResp-LCR::= SEQUENCE {
    e-HICH-Scheduled-InformationResp-LCR
                                                    E-HICH-Scheduled-InformationRespList-LCR-TDD
                                                                                                                     OPTIONAL,
    e-HICH-non-Scheduled-InformationResp-LCR
                                                    E-HICH-InformationResp-LCR
                                                                                                                     OPTIONAL,
    e-HICH-TimeOffset-lcr
                                                    E-HICH-TimeOffset-LCR,
                                                    ProtocolExtensionContainer { { E-HICH-Specific-InformationResp-LCR-ExtIEs } }
    iE-Extensions
    OPTIONAL,
E-HICH-Specific-InformationResp-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
E-HICH-Scheduled-InformationRespList-LCR-TDD ::= SEQUENCE (SIZE (1..maxNrOfEHICHCodes)) OF E-HICH-Scheduled-InformationResp-Item-LCR-TDD
E-HICH-Scheduled-InformationResp-Item-LCR-TDD ::= SEQUENCE {
    e-HICH-EI
                                                E-HICH-EI,
    e-HICH-Scheduled-InformationResp-LCR
                                                E-HICH-InformationResp-LCR,
                                                ProtocolExtensionContainer { { E-HICH-Scheduled-InformationResp-LCR-ExtIEs } }
    iE-Extensions
                                                                                                                                         OPTIONAL,
E-HICH-Scheduled-InformationResp-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-HICH-EI ::= INTEGER (0..3)
E-HICH-InformationResp-LCR::= SEQUENCE {
    timeSlotLCR
                                                    TimeSlotLCR,
   midambleShiftLCR
                                                    MidambleShiftLCR,
    tDD-ChannelisationCode
                                                    TDD-ChannelisationCode,
    signatureSequenceGroupIndex
                                                    SignatureSequenceGroupIndex,
    iE-Extensions
                                                    ProtocolExtensionContainer { { E-HICH-InformationResp-LCR-ExtIEs } }
                                                                                                                                         OPTIONAL,
E-HICH-InformationResp-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
E-HICH-TimeOffset-LCR ::= INTEGER (4..15)
E-DCH-SubframeNumber-LCR ::= ENUMERATED(s0,s1)
E-DCH-TimeslotResource-LCR ::= BIT STRING (SIZE (5))
E-DCH-Non-Scheduled-Grant-Info-LCR ::= SEOUENCE {
    timeslotResource-LCR
                                                E-DCH-TimeslotResource-LCR,
    powerResource
                                                E-DCH-PowerResource,
    repetitionPeriod
                                                RepetitionPeriod,
    repetitionLength
                                                RepetitionLength,
    subframenumber
                                                E-DCH-SubframeNumber-LCR,
    tddE-PUCH-Offset
                                                TddE-PUCH-Offset,
    tdd-ChannelisationCode
                                                TDD-ChannelisationCode,
    iE-Extensions
                                                ProtocolExtensionContainer { { E-DCH-Non-Scheduled-Grant-Info-LCR-ExtIEs } }
                                                                                                                                        OPTIONAL,
E-DCH-Non-Scheduled-Grant-Info-LCR-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
Enabling-Delay ::= ENUMERATED {v0, v1, v2, v4, v8, v16, v32, v64, v128}
-- Unit radio frame
Ext-Reference-E-TFCI-PO ::= INTEGER(30..31,...)
ExtendedPropagationDelay ::= INTEGER(255..1023)
Extended-RNC-ID
                                ::= INTEGER (4096..65535)
Extended-Round-Trip-Time-Value ::= INTEGER(32767..103041)
-- See also mapping in TS 25.133 [23]
Ext-Max-Bits-MACe-PDU-non-scheduled ::= INTEGER(19983..22978,...)
E-DCH-Semi-PersistentScheduling-Information-LCR ::= SEQUENCE {
    repetition-Period-List-LCR
                                            Repetition-Period-List-LCR,
    e-DCH-SPS-Indicator
                                            E-DCH-SPS-Indicator,
    e-DCH-SPS-Reservation-Indicator
                                            SPS-Reservation-Indicator
                                                                            OPTIONAL,
                                            ProtocolExtensionContainer { { E-DCH-Semi-PersistentScheduling-Information-LCR-ExtIEs } }
    iE-Extensions
    OPTIONAL,
    . . .
E-DCH-Semi-PersistentScheduling-Information-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-DCH-SPS-Indicator ::= BIT STRING (SIZE (16))
E-DCH-Semi-PersistentScheduling-Information-to-Modify-LCR ::= SEQUENCE {
```

```
repetition-Period-List-LCR
                                            Repetition-Period-List-LCR
                                                                             OPTIONAL,
    e-DCH-SPS-Indicator
                                            E-DCH-SPS-Indicator
                                                                             OPTIONAL,
    e-DCH-SPS-Reservation-Indicator
                                            SPS-Reservation-Indicator
                                                                             OPTIONAL.
                                            ProtocolExtensionContainer { { E-DCH-Semi-PersistentScheduling-Information-to-Modify-LCR-ExtIEs } }
    iE-Extensions
           OPTIONAL,
    . . .
E-DCH-Semi-PersistentScheduling-Information-to-Modify-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-DCH-Semi-PersistentScheduling-Information-ResponseLCR ::= SEQUENCE {
    initial-E-DCH-SPS-resource
                                                Initial-E-DCH-SPS-resource
                                                                                     OPTIONAL,
    e-DCH-SPS-HICH-Information
                                                E-DCH-SPS-HICH-Information
                                                                                     OPTIONAL,
    iE-Extensions
                                                ProtocolExtensionContainer { { E-DCH-Semi-PersistentScheduling-Information-ResponseLCR-ExtIEs } }
           OPTIONAL,
E-DCH-Semi-PersistentScheduling-Information-ResponseLCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Initial-E-DCH-SPS-resource ::= SEQUENCE {
    timeslot-Resource-Related-Information
                                                E-DCH-TimeslotResource-LCR.
    powerResource
                                                E-DCH-PowerResource,
    repetitionPeriodIndex
                                                RepetitionPeriodIndex,
    repetitionLength
                                                RepetitionLength,
                                                ENUMERATED {v0, v1},
    subframeNumber
    tddE-PUCH-Offset
                                                TddE-PUCH-Offset,
    tdd-ChannelisationCode
                                                TDD-ChannelisationCode,
    n-E-UCCHLCR
                                                N-E-UCCH-LCR,
                                                ProtocolExtensionContainer { { Initial-E-DCH-SPS-resource-ExtIEs } }
                                                                                                                                         OPTIONAL,
    iE-Extensions
Initial-E-DCH-SPS-resource-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
E-DCH-SPS-HICH-Information ::= SEOUENCE {
    e-HICH-Configuration
                                                E-HICH-Configuration,
    signatureSequenceGroupIndex
                                            SignatureSequenceGroupIndex,
    iE-Extensions
                                                ProtocolExtensionContainer { { E-DCH-SPS-HICH-Information-ExtIEs } }
                                                                                                                                         OPTIONAL,
E-DCH-SPS-HICH-Information-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
E-HICH-Configuration ::= CHOICE {
    same-As-Scheduled-E-HICH
                                        Same-As-Scheduled-E-HICH,
    explicit.
                                        E-HICH-InformationResp-ExplicitConfiguration-LCR,
    . . .
Same-As-Scheduled-E-HICH ::= SEQUENCE {
    e-HICH-EI
                                                E-HICH-EI,
E-HICH-InformationResp-ExplicitConfiguration-LCR ::= SEQUENCE {
    timeSlotLCR
                                                    TimeSlotLCR,
    midambleShiftLCR
                                                    MidambleShiftLCR,
    tDD-ChannelisationCode
                                                    TDD-ChannelisationCode,
                                                    ProtocolExtensionContainer { { E-HICH-InformationResp-ExplicitConfiguration-LCR-ExtIEs } }
   iE-Extensions
   OPTIONAL,
E-HICH-InformationResp-ExplicitConfiguration-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
-- F
FACH-FlowControlInformation ::= SEQUENCE (SIZE (1..16)) OF FACH-FlowControlInformationItem
FACH-FlowControlInformationItem ::= SEQUENCE {
                                    SchedulingPriorityIndicator,
    fACH-SchedulingPriority
   mAC-c-sh-SDU-Lengths
                                    MAC-c-sh-SDU-LengthList,
    fACH-InitialWindowSize
                                    FACH-InitialWindowSize,
    iE-Extensions
                                    ProtocolExtensionContainer { {FACH-FlowControlInformationItem-ExtIEs} } OPTIONAL,
    . . .
FACH-FlowControlInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
                                ::= INTEGER { unlimited(255) } (0..255)
FACH-InitialWindowSize
-- Number of frames MAC-c-sh SDUs.
-- 255 = Unlimited number of FACH data frames
FACH-InformationList ::= SEQUENCE (SIZE(0.. maxNrOfFACHs)) OF FACH-InformationItem
FACH-InformationItem ::= SEQUENCE {
    transportFormatSet
                                    TransportFormatSet,
    iE-Extensions
                                    ProtocolExtensionContainer { { FACH-InformationItem-ExtIEs} } OPTIONAL,
```

```
FACH-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Fast-Reconfiguration-Mode ::= ENUMERATED {fast,...}
Fast-Reconfiguration-Permission ::= ENUMERATED {allowed,...}
FDD-DCHs-to-Modify
                                ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF FDD-DCHs-to-ModifyItem
FDD-DCHs-to-ModifyItem ::= SEQUENCE {
    ul-FP-Mode
                                        UL-FP-Mode
                                                         OPTIONAL,
    toAWS
                                        ToAWS
                                                    OPTIONAL,
                                        TOAWE
                                                    OPTIONAL,
    t.oAWE
    transportBearerRequestIndicator
                                        TransportBearerRequestIndicator,
                                        FDD-DCHs-to-ModifySpecificInformationList,
    dCH-SpecificInformationList
                                        ProtocolExtensionContainer { {FDD-DCHs-to-ModifyItem-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
FDD-DCHs-to-ModifyItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-TnlQos
                                        CRITICALITY
                                                        ignore
                                                                     EXTENSION
                                                                                TnlQos PRESENCE optional
                                                                                                                  },
    . . .
FDD-DCHs-to-ModifySpecificInformationList ::= SEOUENCE (SIZE (1..maxNrOfDCHs)) OF FDD-DCHs-to-ModifySpecificItem
FDD-DCHs-to-ModifySpecificItem ::= SEQUENCE {
    dCH-ID
                                    DCH-ID,
    ul-TransportformatSet
                                    TransportFormatSet
                                                             OPTIONAL,
    dl-TransportformatSet
                                    TransportFormatSet
                                                             OPTIONAL,
    allocationRetentionPriority
                                    AllocationRetentionPriority
                                                                     OPTIONAL,
    frameHandlingPriority
                                    FrameHandlingPriority
                                                                OPTIONAL,
    not-Used-dRACControl
                                                NULL
                                                             OPTIONAL,
                                    ProtocolExtensionContainer { {FDD-DCHs-to-ModifySpecificItem-ExtIEs} } OPTIONAL,
    iE-Extensions
FDD-DCHs-to-ModifySpecificItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
      ID id-Guaranteed-Rate-Information
                                                CRITICALITY ignore
                                                                         EXTENSION Guaranteed-Rate-Information
                                                                                                                                 PRESENCE optional
      ID id-TrafficClass
                                                                         EXTENSION TrafficClass
                                                                                                                     PRESENCE optional }|
                                                CRITICALITY ignore
    { ID id-Unidirectional-DCH-Indicator
                                                CRITICALITY reject
                                                                         EXTENSION Unidirectional-DCH-Indicator
                                                                                                                     PRESENCE optional },
FDD-DL-ChannelisationCodeNumber
                                    ::= INTEGER (0..511)
-- According to the mapping in TS 25.213 [27]. The maximum value is equal to the DL spreading factor -1--
FDD-DL-CodeInformation ::= SEQUENCE (SIZE (1..maxNrOfDL-Codes)) OF FDD-DL-CodeInformationItem
FDD-DL-CodeInformationItem ::= SEQUENCE {
    dl-ScramblingCode
                                                                DL-ScramblingCode,
```

```
fDD-DL-ChannelisationCodeNumber
                                                                 FDD-DL-ChannelisationCodeNumber,
    transmission-Gap-Pattern-Sequence-ScramblingCode-Information
                                                                         Transmission-Gap-Pattern-Sequence-ScramblingCode-Information OPTIONAL,
                                            ProtocolExtensionContainer { {FDD-DL-CodeInformationItem-ExtIEs} } OPTIONAL,
    iE-Extensions
FDD-DL-CodeInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
FDD-TPC-DownlinkStepSize ::= ENUMERATED {
    step-size0-5,
    step-sizel,
    step-size1-5,
    step-size2,
SchedulingPriorityIndicator
                                        ::= INTEGER { lowest(0), highest(15) } (0..15)
F-DPCH-SlotFormat ::= INTEGER (0..9)
F-DPCH-SlotFormatSupportRequest ::= NULL
FirstRLS-Indicator ::= ENUMERATED {
    first-RLS,
    not-first-RLS
FNReportingIndicator ::= ENUMERATED {
    fN-reporting-required,
    fN-reporting-not-required
FPACH-Information ::= SEQUENCE
    timeSlotLCR
                                TimeSlotLCR.
    tDD-ChannelisationCodeLCR TDD-ChannelisationCodeLCR,
    midambleShiftLCR
                                MidambleShiftLCR,
    wΤ
                                INTEGER (1..4),
    . . .
FrameHandlingPriority
                                ::= INTEGER { lowest(0), highest(15) } (0..15)
FrameOffset
                        ::= INTEGER (0..255)
-- Frames
FrequencyBandIndicator
                            ::= ENUMERATED {
    bandI,
    bandII,
    bandIII,
    bandIV,
    bandV,
    bandVI,
```

```
bandVII,
    bandVIII,
    bandIX,
    bandX,
    bandXI,
    bandXII,
    bandXIII,
    bandXIV,
    bandXV,
    bandXVI,
    bandXVII,
    bandXVIII,
    bandXIX,
    bandXX,
    bandXXI,
    bandXXII,
    . . . ,
    reserved23,
    reserved24,
    bandXXV
-- G
GapLength
                        ::= INTEGER (1..14)
-- Unit Slot
GapDuration
                        ::= INTEGER (1..144,...)
-- Unit Frame
GA-Cell ::= SEQUENCE (SIZE (1..maxNrOfPoints)) OF
    SEQUENCE {
        cell-GAIgeographicalCoordinate
                                            GeographicalCoordinate,
                                ProtocolExtensionContainer { {GA-Cell-ExtIEs} } OPTIONAL,
        iE-Extensions
GA-Cell-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GA-CellAdditionalShapes ::= CHOICE {
    pointWithUncertainty
                                                     GA-PointWithUnCertainty,
    pointWithUncertaintyEllipse
                                                     GA-PointWithUnCertaintyEllipse,
    pointWithAltitude
                                                     GA-PointWithAltitude,
    pointWithAltitudeAndUncertaintyEllipsoid
                                                     GA-PointWithAltitudeAndUncertaintyEllipsoid,
    ellipsoidArc
                                                     GA-EllipsoidArc,
GA-AltitudeAndDirection ::= SEOUENCE {
    directionOfAltitude
                            ENUMERATED {height, depth},
    altitude
                            INTEGER (0..32767),
```

```
GA-EllipsoidArc ::= SEQUENCE {
    geographicalCoordinates
                                GeographicalCoordinate,
    innerRadius
                                INTEGER (0..65535),
    uncertaintyRadius
                                INTEGER (0..127),
    offsetAngle
                                INTEGER (0..179),
    includedAngle
                                INTEGER (0..179),
    confidence
                                INTEGER (0..127),
    iE-Extensions
                                ProtocolExtensionContainer { { GA-EllipsoidArc-ExtIEs} } OPTIONAL,
    . . .
GA-EllipsoidArc-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-AddClockModels ::= CHOICE {
    navClockModel
                                    GANSS-NAVclockModel,
    cnavClockModel
                                    GANSS-CNAVclockModel,
    glonassClockModel
                                    GANSS-GLONASSclockModel,
    sbasClockModel
                                    GANSS-SBASclockModel,
    . . .
GANSS-AddionoModelReg ::= BIT STRING (SIZE(2))
GANSS-AddNavigationModelsReg ::= BOOLEAN
GANSS-AddOrbitModels ::= CHOICE {
    navKeplerianSet
                                    GANSS-NavModel-NAVKeplerianSet,
    cnavKeplerianSet
                                    GANSS-NavModel-CNAVKeplerianSet,
    glonassECEF
                                    GANSS-NavModel-GLONASSecef,
    sbasECEF
                                    GANSS-NavModel-SBASecef,
GANSS-AddUTCModelsReq ::= BOOLEAN
GANSS-Additional-Ionospheric-Model ::= SEQUENCE {
    dataID
                                        BIT STRING (SIZE(2)),
    alpha-beta-parameters
                                        GPS-Ionospheric-Model,
    ie-Extensions
                                        ProtocolExtensionContainer { { GANSS-Additional-Ionospheric-Model-ExtIEs } }
                                                                                                                          OPTIONAL,
GANSS-Additional-Ionospheric-Model-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
GANSS-Additional-Navigation-Models ::= SEQUENCE {
```

```
ganss-Transmission-Time
                               GANSS-Transmission-Time,
   non-broadcastIndication
                               ENUMERATED { true }
                                                                                                                             OPTIONAL,
   ganssSatInfoNavList
                               Ganss-Sat-Info-AddNavList,
   ie-Extensions
                               ProtocolExtensionContainer { { GANSS-Additional-Navigation-Models-ExtIEs } } OPTIONAL,
GANSS-Additional-Navigation-Models-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-Additional-Time-Models ::= SEOUENCE (SIZE (1..maxGANSS-1)) OF GANSS-Time-Model
GANSS-Additional-UTC-Models ::= CHOICE {
   utcModel1
                       GANSS-UTCmodelSet1,
   utcModel2
                       GANSS-UTCmodelSet2,
                       GANSS-UTCmodelSet3,
   utcModel3
GANSS-Almanac ::= SEQUENCE {
   ganss-wk-number
                                   INTEGER(0..255),
   qANSS-AlmanacModel
                                   CHOICE {
       gANSS-keplerianParameters
                                       SEQUENCE {
                                           INTEGER(0..255),
           t-oa
           iod-a
                                           INTEGER(0..3),
           gANSS-SatelliteInformationKP
                                           GANSS-SatelliteInformationKP,
                                           ProtocolExtensionContainer { { GANSS-KeplerianParametersAlm-ExtIEs } } OPTIONAL,
           ie-Extensions
           . . .
       },
       . . . ,
       extension-GANSS-AlmanacModel
                                           Extension-GANSS-AlmanacModel
                                   ie-Extensions
                                                                                                                 OPTIONAL,
GANSS-KeplerianParametersAlm-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   . . .
Extension-GANSS-AlmanacModel
                               ::= ProtocolIE-Single-Container {{ Extension-GANSS-AlmanacModel-IE }}
Extension-GANSS-AlmanacModel-IE RNSAP-PROTOCOL-IES ::= {
    { ID id-GANSS-alm-keplerianNAVAlmanac
                                                                                      GANSS-alm-keplerianNAVAlmanac
                                                   CRITICALITY
                                                                              TYPE
                                                                  ignore
    PRESENCE
               mandatory}
    { ID id-GANSS-alm-keplerianReducedAlmanac
                                                   CRITICALITY
                                                                  ignore
                                                                              TYPE
                                                                                      GANSS-alm-keplerianReducedAlmanac
    PRESENCE
               mandatory} |
```

```
{ ID id-GANSS-alm-keplerianMidiAlmanac
                                                 CRITICALITY
                                                                            TYPE
                                                                                   GANSS-alm-keplerianMidiAlmanac
                                                                ignore
   PRESENCE
              mandatory}|
    { ID id-GANSS-alm-keplerianGLONASS
                                                 CRITICALITY
                                                                ignore
                                                                            TYPE
                                                                                   GANSS-alm-keplerianGLONASS
              mandatory}|
   PRESENCE
    { ID id-GANSS-alm-ecefSBASAlmanac
                                                 CRITICALITY
                                                                ignore
                                                                            TYPE
                                                                                   GANSS-alm-ecefSBASAlmanac
   PRESENCE
              mandatory}
GANSS-alm-keplerianNAVAlmanac ::= SEQUENCE {
                              INTEGER (0..255),
   sat-info-NAVkpList
                              GANSS-SAT-Info-Almanac-NAVkpList,
   ie-Extensions
                              OPTIONAL,
    . . .
GANSS-ALM-NAVKeplerianSet-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-alm-keplerianReducedAlmanac ::= SEQUENCE {
                              INTEGER (0..255),
   sat-info-REDkpList
                              GANSS-SAT-Info-Almanac-REDkpList,
                              ProtocolExtensionContainer { { GANSS-ALM-ReducedKeplerianSet-ExtIEs } }
   ie-Extensions
                                                                                                              OPTIONAL,
GANSS-ALM-ReducedKeplerianSet-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-alm-keplerianMidiAlmanac ::= SEQUENCE
                              INTEGER (0..255),
   sat-info-MIDIkpList
                              GANSS-SAT-Info-Almanac-MIDIkpList,
   ie-Extensions
                              ProtocolExtensionContainer { { GANSS-ALM-MidiAlmanacSet-ExtIEs } }
                                                                                                              OPTIONAL,
GANSS-ALM-MidialmanacSet-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-alm-keplerianGLONASS ::= SEQUENCE {
   sat-info-GLOkpList
                              GANSS-SAT-Info-Almanac-GLOkpList,
```

```
ProtocolExtensionContainer { GANSS-ALM-GlonassAlmanacSet-ExtIEs } }
    ie-Extensions
                                                                                                                   OPTIONAL,
GANSS-ALM-GlonassAlmanacSet-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-alm-ecefSBASAlmanac ::= SEQUENCE {
    sat-info-SBASecefList
                               GANSS-SAT-Info-Almanac-SBASecefList,
   ie-Extensions
                               ProtocolExtensionContainer { GANSS-ALM-ECEFsbasAlmanacSet-ExtIEs } }
                                                                                                                   OPTIONAL,
GANSS-ALM-ECEFsbasAlmanacSet-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-Almanac-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-completeAlmanacProvided CRITICALITY
                                                                                                                   optional},
                                                  ignore EXTENSION CompleteAlmanacProvided PRESENCE
    . . .
GANSS-Auxiliary-Information ::= CHOICE {
               GANSS-AuxInfoGANSS-ID1,
                                           -- This choice may only be present if GANSS ID indicates Modernized GPS
    ganssID1
    ganssID3
               GANSS-AuxInfoGANSS-ID3,
                                           -- This choice may only be present if GANSS ID indicates GLONASS
    . . .
GANSS-AuxInfoGANSS-ID1 ::= SEQUENCE (SIZE(1.. maxGANSSSat)) OF SEQUENCE {
                       INTEGER(0..63),
    signalsAvailable BIT STRING (SIZE(8)),
   ie-Extensions
                      ProtocolExtensionContainer { GANSS-AuxInfoGANSS-ID1-element-ExtIEs } } OPTIONAL,
GANSS-AuxInfoGANSS-ID1-element-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-AuxInfoGANSS-ID3 ::= SEQUENCE (SIZE(1.. maxGANSSSat)) OF SEQUENCE {
    svID
                       INTEGER(0..63),
    signalsAvailable BIT STRING (SIZE(8)),
    channelNumber
                       INTEGER (-7..13),
    ie-Extensions
                       ProtocolExtensionContainer { { GANSS-AuxInfoGANSS-ID3-element-ExtIEs } } OPTIONAL,
```

945

```
GANSS-AuxInfoGANSS-ID3-element-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-AuxInfoReg ::= BOOLEAN
GANSS-Clock-Model ::= SEOUENCE (SIZE (1..maxGANSSClockMod)) OF SEOUENCE {
                                        BIT STRING (SIZE (14)),
    t.-oc
    a-i2
                                        BIT STRING (SIZE (12)),
    a-i1
                                        BIT STRING (SIZE (18)),
    a-i0
                                        BIT STRING (SIZE (28)),
    t-qd
                                        BIT STRING (SIZE (10))
                                                                                                                    OPTIONAL,
    model-id
                                        INTEGER(0..1,...)
                                                                                                                    OPTIONAL,
    ie-Extensions
                                        ProtocolExtensionContainer { { GANSS-ClockModelItem-ExtIEs } }
                                                                                                                    OPTIONAL,
GANSS-ClockModelItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-CNAVclockModel ::= SEQUENCE {
    cnavToc
                      BIT STRING (SIZE (11)),
    cnavTop
                       BIT STRING (SIZE (11)),
    cnavURA0
                     BIT STRING (SIZE (5)),
    cnavURA1
                       BIT STRING (SIZE (3)),
    cnavURA2
                       BIT STRING (SIZE (3)),
    cnavAf2
                       BIT STRING (SIZE (10)),
    cnavAf1
                       BIT STRING (SIZE (20)),
    cnavAf0
                       BIT STRING (SIZE (26)),
    cnavTgd
                       BIT STRING (SIZE (13)),
                                                                                        OPTIONAL,
    cnavISC11cp
                       BIT STRING (SIZE (13))
    cnavISC11cd
                       BIT STRING (SIZE (13))
                                                                                        OPTIONAL,
    cnavISCl1ca
                       BIT STRING (SIZE (13))
                                                                                        OPTIONAL,
    cnavISC12c
                       BIT STRING (SIZE (13))
                                                                                        OPTIONAL,
                       BIT STRING (SIZE (13))
    cnavISC15i5
                                                                                        OPTIONAL,
                       BIT STRING (SIZE (13))
                                                                                        OPTIONAL,
    cnavISC15q5
    ie-Extensions
                       ProtocolExtensionContainer { { GANSS-CNAVclockModel-ExtIEs } } OPTIONAL,
GANSS-CNAVclockModel-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-Common-Data ::= SEQUENCE {
    ganss-Ionospheric-Model
                                        GANSS-Ionospheric-Model
    OPTIONAL,
    ganss-Rx-Pos
                                        GANSS-RX-Pos
    OPTIONAL,
    ie-Extensions
                                        ProtocolExtensionContainer { GANSS-Common-Data-ExtIEs } }
                                                                                                                    OPTIONAL,
```

```
GANSS-Common-Data-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-GANSS-Additional-Ionospheric-Model
                                                  CRITICALITY ignore EXTENSION GANSS-Additional-Ionospheric-Model
                                                                                                                   PRESENCE optional }
    { ID id-GANSS-Earth-Orientation-Parameters
                                                  CRITICALITY ignore EXTENSION GANSS-Earth-Orientation-Parameters
                                                                                                                   PRESENCE optional },
GANSS-CommonDataInfoReg ::= SEOUENCE {
   ionospheric-Model
                                      BOOLEAN
   OPTIONAL,
   ie-Extensions
                                      ProtocolExtensionContainer { GANSS-CommonDataInfoReq-ExtIEs } }
                                                                                                               OPTIONAL,
GANSS-CommonDataInfoReq-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    {ID id-GANSS-AddIonoModelReg
                                      CRITICALITY ignore EXTENSION
                                                                     GANSS-AddIonoModelReq
   PRESENCE optional }
    {ID id-GANSS-EarthOrientParaReq
                                      CRITICALITY ignore EXTENSION
                                                                     GANSS-EarthOrientParaReq
                                                                                                               PRESENCE optional } ,
GANSS-Data-Bit-Assistance ::= SEQUENCE {
                                      INTEGER (0..59,...),
    ganssTod
   dataBitAssistancelist
                                      GANSS-DataBitAssistanceList,
   ie-Extensions
                                      OPTIONAL,
    . . .
GANSS-Data-Bit-Assistance-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-DataBitAssistanceList ::= SEQUENCE (SIZE (1..maxGANSSSat)) OF GANSS-DataBitAssistanceItem
GANSS-DataBitAssistanceItem ::= SEQUENCE {
   satId
                                  INTEGER(0..63),
   dataBitAssistanceSqnList
                                  GANSS-DataBitAssistanceSgnList,
                                  ProtocolExtensionContainer { GANSS-DataBitAssistanceItem-ExtIEs } }
   ie-Extensions
                                                                                                               OPTIONAL,
    . . .
GANSS-DataBitAssistanceItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-DataBitAssistanceSqnList ::= SEQUENCE (SIZE (1..maxSqnType)) OF GANSS-DataBitAssistanceSqnItem
GANSS-DataBitAssistanceSgnItem ::= SEQUENCE {
```

```
ganss-SignalId
                          GANSS-Signal-ID,
   ganssDataBits
                          BIT STRING (SIZE (1..1024)),
   ie-Extensions
                          OPTIONAL,
GANSS-DataBitAssistanceSqnItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-Data-Bit-Assistance-RegItem ::= SEQUENCE {
   ganssTod
                                         INTEGER (0..86399),
   ganss-Data-Bit-Assistance-RegList
                                         GANSS-Data-Bit-Assistance-RegList,
   iE-Extensions
                                         ProtocolExtensionContainer { GANSS-Data-Bit-Assistance-RegItem-ExtIEs } } OPTIONAL,
   . . .
GANSS-Data-Bit-Assistance-Regitem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-Data-Bit-Assistance-ReqList ::= SEQUENCE {
   dGANSS-Signal-ID
                                     BIT STRING (SIZE (8)),
   ganss-DataBitInterval
                                     INTEGER(0..15),
   ganss-SatelliteInfo
                                     SEQUENCE (SIZE (1..maxGANSSSat)) OF INTEGER(0..63)
       OPTIONAL,
   iE-Extensions
                                         ProtocolExtensionContainer { { GANSS-Data-Bit-Assistance-ReqList-ExtIEs } } OPTIONAL,
GANSS-Data-Bit-Assistance-RegList-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-Delta-T ::= INTEGER(-128..127)
GANSS-DeltaUT1 ::= SEQUENCE {
   b1
                   BIT STRING (SIZE(11)),
                     BIT STRING (SIZE(10)),
                     ProtocolExtensionContainer { { GANSS-DeltaUT1-ExtIEs } }
   ie-Extensions
                                                                               OPTIONAL,
GANSS-DeltaUT1-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-Earth-Orientation-Parameters ::= SEQUENCE {
                   BIT STRING (SIZE (16)),
   teop
                      BIT STRING (SIZE (21)),
   pmX
                    BIT STRING (SIZE (15)),
   pmXdot
   Yma
                    BIT STRING (SIZE (21)),
   pmYdot
                     BIT STRING (SIZE (15)),
   deltaUT1
                      BIT STRING (SIZE (31)),
```

```
deltaUT1dot
                        BIT STRING (SIZE (19)),
    ie-Extensions
                        ProtocolExtensionContainer { GANSS-Earth-Orientation-Parameters-ExtIEs } }
                                                                                                                      OPTIONAL.
GANSS-Earth-Orientation-Parameters-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-EarthOrientParaReq ::= BOOLEAN
GANSS-GenericDataInfoRegList ::= SEOUENCE (SIZE(1..maxNoGANSS)) OF GANSS-GenericDataInfoRegItem
GANSS-GenericDataInfoRegItem ::= SEQUENCE {
    ganss-Id
                                                GANSS-ID
        OPTIONAL,
    ganss-Navigation-Model-And-Time-Recovery
                                                BOOLEAN
                                                                                                                                         OPTIONAL,
    ganss-Time-Model-GNSS-GNSS
                                                BIT STRING (SIZE (9))
                                                                                                                                         OPTIONAL,
    ganss-UTC-Model
                                                BOOLEAN
                                                                                                                                         OPTIONAL,
    ganss-Almanac
                                                BOOLEAN
                                                                                                                                         OPTIONAL,
    ganss-Real-Time-Integrity
                                                BOOLEAN
                                                                                                                                         OPTIONAL,
    ganss-Data-Bit-Assistance-Req
                                                GANSS-Data-Bit-Assistance-ReqItem
                                                                                                                                         OPTIONAL,
    ie-Extensions
                                                ProtocolExtensionContainer { GANSS-GenericDataInfoReqItem-ExtIEs } }
                                                                                                                                 OPTIONAL,
GANSS-GenericDataInfoReqItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    {ID id-GANSS-AddNavigationModelsReq CRITICALITY ignore EXTENSION
                                                                         GANSS-AddNavigationModelsReg
                                                                                                                          PRESENCE
                                                                                                                                         optional}
    {ID id-GANSS-AddUTCModelsReq
                                        CRITICALITY ignore EXTENSION
                                                                         GANSS-AddUTCModelsReq
                                                                                                                          PRESENCE
                                                                                                                                         optional}
    {ID id-GANSS-AuxInfoReq
                                        CRITICALITY ignore EXTENSION
                                                                         GANSS-AuxInfoReq
                                                                                                                          PRESENCE
                                                                                                                                         optional}
    -- The following IE shall be present if 'GANSS-ID' in 'GANSS-GenericDataInfoReqItem' is '0' (SBAS)
    {ID id-GANSS-SBAS-ID
                                        CRITICALITY ignore EXTENSION
                                                                         GANSS-SBAS-ID
                                                                                                                     optional } ,
                                                                                                 PRESENCE
    . . .
GANSS-Generic-Data ::= SEQUENCE (SIZE(1..maxNoGANSS)) OF GANSS-Generic-DataItem
GANSS-Generic-DataItem ::= SEQUENCE {
    ganss-Id
                                                GANSS-ID
        OPTIONAL,
    dganss-Correction
                                                DGANSSCorrections
        OPTIONAL,
    ganss-Navigation-Model-And-Time-Recovery
                                                GANSS-Navigation-Model-And-Time-Recovery
       OPTIONAL,
    ganss-Time-Model
                                                GANSS-Time-Model
        OPTIONAL,
    ganss-UTC-TIME
                                                GANSS-UTC-Model
        OPTIONAL,
    ganss-Almanac
                                                GANSS-Almanac
        OPTIONAL,
```

```
ganss-Real-Time-Integrity
                                           GANSS-Real-Time-Integrity
       OPTIONAL,
   ganss-Data-Bit-Assistance
                                           GANSS-Data-Bit-Assistance
       OPTIONAL,
                                           ie-Extensions
                                                                                                                    OPTIONAL,
GANSS-Generic-DataItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-GANSS-Additional-Time-Models
                                               CRITICALITY ignore EXTENSION GANSS-Additional-Time-Models
                                                                                                                    PRESENCE optional } |
                                                                                                             PRESENCE optional }
     ID id-GANSS-Additional-Navigation-Models
                                               CRITICALITY ignore EXTENSION GANSS-Additional-Navigation-Models
     ID id-GANSS-Additional-UTC-Models
                                               CRITICALITY ignore EXTENSION GANSS-Additional-UTC-Models
                                                                                                                           PRESENCE
optional }|
   { ID id-GANSS-Auxiliary-Information
                                               CRITICALITY ignore EXTENSION GANSS-Auxiliary-Information
                                                                                                                           PRESENCE
optional }
   -- The following element shall be present if 'GANSS-ID' in 'GANSS-Generic-DataItem' is '0' ('SBAS')
   { ID id-GANSS-SBAS-ID
                                                                                                             PRESENCE optional },
                                               CRITICALITY ignore EXTENSION GANSS-SBAS-ID
   . . .
GANSS-GLONASSclockModel ::= SEQUENCE {
   qloTau
                        BIT STRING (SIZE (22)),
   qloGamma
                         BIT STRING (SIZE (11)),
   qloDeltaTau
                         BIT STRING (SIZE (5))
                                                                                       OPTIONAL.
   ie-Extensions
                         OPTIONAL.
GANSS-GLONASSclockModel-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-ID ::= INTEGER(0..7,...)
GANSS-Information ::= SEQUENCE {
   gANSS-CommonDataInfoReq
                                    GANSS-CommonDataInfoReg
                                                                                                             OPTIONAL,
   gANSS-GenericDataInfoRegList
                                    GANSS-GenericDataInfoReqList
                                                                                                             OPTIONAL,
   ie-Extensions
                                    OPTIONAL,
GANSS-Information-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-Ionospheric-Model ::= SEQUENCE {
   alpha-zero-ionos
                                    BIT STRING (SIZE (12)),
   alpha-one-ionos
                                    BIT STRING (SIZE (12)),
   alpha-two-ionos
                                    BIT STRING (SIZE (12)),
   gANSS-IonosphereRegionalStormFlags GANSS-IonosphereRegionalStormFlags
                                                                                                         OPTIONAL.
                                    ProtocolExtensionContainer { { GANSS-Ionospheric-Model-ExtIEs } }
   ie-Extensions
                                                                                                         OPTIONAL,
```

```
GANSS-Ionospheric-Model-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-IonosphereRegionalStormFlags ::= SEQUENCE
    storm-flag-one
                                        BOOLEAN,
    storm-flag-two
                                        BOOLEAN,
    storm-flag-three
                                        BOOLEAN,
    storm-flag-four
                                        BOOLEAN.
    storm-flag-five
                                        BOOLEAN
    ie-Extensions
                                        ProtocolExtensionContainer { GANSS-IonosphereRegionalStormFlags-ExtIEs } } OPTIONAL,
GANSS-IonosphereRegionalStormFlags-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-NAVclockModel ::= SEQUENCE {
   navToc
                           BIT STRING (SIZE (16)),
   navaf2
                           BIT STRING (SIZE (8)),
                         BIT STRING (SIZE (16)),
   navaf1
   navaf0
                           BIT STRING (SIZE (22)),
    navTgd
                           BIT STRING (SIZE (8)),
                           ProtocolExtensionContainer { { GANSS-NAVclockModel-ExtIEs } }
    ie-Extensions
GANSS-NAVclockModel-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-Navigation-Model-And-Time-Recovery ::= SEQUENCE {
    ganss-Transmission-Time
                                GANSS-Transmission-Time,
    non-broadcastIndication
                                ENUMERATED{true}
                                                        OPTIONAL,
                                GANSS-Sat-Info-Nav,
    ganssSatInfoNav
    ie-Extensions
                               ProtocolExtensionContainer { GANSS-Navigation-Model-And-Time-Recovery-ExtIEs } } OPTIONAL,
GANSS-Navigation-Model-And-Time-Recovery-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
GANSS-NavModel-CNAVKeplerianSet ::= SEQUENCE {
    cnavTop
                           BIT STRING (SIZE (11)),
    cnavURAindex
                           BIT STRING (SIZE (5)),
```

952

```
cnavDeltaA
                                                                                 BIT STRING (SIZE (26)),
            cnavAdot.
                                                                            BIT STRING (SIZE (25)),
           cnavDeltaNo BIT STRING (SIZE (17)), cnavDeltaNoDot BIT STRING (SIZE (23)), cnavMo BIT STRING (SIZE (33)),

        cnavE
        BIT STRING (SIZE (33)),

        cnavOmega
        BIT STRING (SIZE (33)),

        cnavOMEGA0
        BIT STRING (SIZE (33)),

            cnavDeltaOmegaDot
cnavIo
                                                                                 BIT STRING (SIZE (17)),
                                                                                 BIT STRING (SIZE (33)),
        cnavio
cnavioDot
cnavCis
cnavCic
cnavCic
cnavCrs
cnavCrc
cnavCus
cnavCuc
BIT
STRING
SIZE
(24)),
cnavCuc
BIT
STRING
(SIZE
(21)),
cnavCuc
CnavCu
                                                           ProtocolExtensionContainer { { GANSS-NavModel-CNAVKeplerianSet-ExtIEs } }
            ie-Extensions
                                                                                                                                                                                                                                                                                                                                                          OPTIONAL,
GANSS-NavModel-CNAVKeplerianSet-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-NavModel-GLONASSecef ::= SEQUENCE {
            gloEn
                                            BIT STRING (SIZE (5)),
           qloP1
                                                                      BIT STRING (SIZE(2)),
BIT STRING (SIZE (1)),
            qloP2
            qloM
                                                                            BIT STRING (SIZE (2))
            OPTIONAL,
                                                               BIT STRING (SIZE (24),,
BIT STRING (SIZE (5)),
BIT STRING (SIZE (27)),
BIT STRING (SIZE (24)),
COURT (5)),
            gloX
            qloXdot
            aloXdotdot
            aloY
            gloYdot
            gloYdotdot
            gloZ
                                                                          BIT STRING (SIZE (27)),
                                                                        BIT STRING (SIZE (24)),
            gloZdot
            qloZdotdot
                                                                              BIT STRING (SIZE (5)),
                                                                                 ProtocolExtensionContainer { { GANSS-NavModel-GLONASSecef-ExtIEs } }
            ie-Extensions
                                                                                                                                                                                                                                                                                                                                                          OPTIONAL,
GANSS-NavModel-GLONASSecef-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-NavModel-NAVKeplerianSet ::= SEQUENCE {
            navURA
                                             BIT STRING (SIZE (4)),
                                                                           BIT STRING (SIZE (1)),
           navFitFlag
           navToe
                                                                               BIT STRING (SIZE (16)),
```

```
nav0mega
                             BIT STRING (SIZE (32)),
    navDeltaN
                             BIT STRING (SIZE (16)),
    navM0
                             BIT STRING (SIZE (32)),
    navOmegaADot
                          BIT STRING (SIZE (24)),
                           BIT STRING (SIZE (32)),
    navE
                     BIT STRING (SIZE (14)),
BIT STRING (SIZE (32)),
    navIDot
    navAPowerHalf
    navI0
                             BIT STRING (SIZE (32)),
    navOmegaA0
                             BIT STRING (SIZE (32)),
    navCrs
                             BIT STRING (SIZE (16)),
    navCis
                             BIT STRING (SIZE (16)),
    navCus
                          BIT STRING (SIZE (16)),
    navCrc
                          BIT STRING (SIZE (16)),
    navCic
                          BIT STRING (SIZE (16)),
    navCuc
                             BIT STRING (SIZE (16)),
                             ProtocolExtensionContainer { GANSS-NavModel-NAVKeplerianSet-ExtIEs } }
    ie-Extensions
                                                                                                                           OPTIONAL,
GANSS-NavModel-NAVKeplerianSet-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-NavModel-SBASecef ::= SEOUENCE {
    -- the following IE shall be present if 'GANSS-SBASclockModel' in 'GANSS-AddClockModels' is not included in 'Ganss-Sat-Info-AddNavList'
                         BIT STRING (SIZE (13))
                        BIT STRING (SIZE (4)),
BIT STRING (SIZE (30)),
    sbasAccuracy
    sbasXq
    sbasYq
                          BIT STRING (SIZE (30)),
                        BIT STRING (SIZE (25)),
BIT STRING (SIZE (17)),
BIT STRING (SIZE (17)),
BIT STRING (SIZE (18)),
    sbasZg
    sbasXqDot
    sbasYgDot
    sbasZgDot
                        BIT STRING (SIZE (10)),
BIT STRING (SIZE (10)),
    sbasXgDotDot
    sbagYgDotDot
    sbasZgDotDot
                             BIT STRING (SIZE (10)),
                             ProtocolExtensionContainer { GANSS-NavModel-SBASecef-ExtIEs } } OPTIONAL,
    ie-Extensions
GANSS-NavModel-SBASecef-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-Orbit-Model ::= CHOICE {
    gANSS-keplerianParameters
                                          SEOUENCE {
                                              BIT STRING (SIZE (14)),
        toe-nav
                                              BIT STRING (SIZE (32)),
        ganss-omega-nav
        delta-n-nav
                                           BIT STRING (SIZE (16)),
        m-zero-nav
                                              BIT STRING (SIZE (32)),
        omegadot-nav
                                              BIT STRING (SIZE (24)),
```

```
ganss-e-nav
                                            BIT STRING (SIZE (32)),
        idot-nav
                                            BIT STRING (SIZE (14)),
        a-sgrt-nav
                                            BIT STRING (SIZE (32)),
        i-zero-nav
                                            BIT STRING (SIZE (32)),
        omega-zero-nav
                                            BIT STRING (SIZE (32)),
        c-rs-nav
                                            BIT STRING (SIZE (16)),
        c-is-nav
                                            BIT STRING (SIZE (16)),
        c-us-nav
                                            BIT STRING (SIZE (16)),
        c-rc-nav
                                            BIT STRING (SIZE (16)),
        c-ic-nav
                                            BIT STRING (SIZE (16)),
        c-uc-nav
                                            BIT STRING (SIZE (16)),
        ie-Extensions
                                            ProtocolExtensionContainer { GANSS-KeplerianParametersOrb-ExtIEs } }
                                                                                                                          OPTIONAL,
    . . .
GANSS-KeplerianParametersOrb-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-Real-Time-Integrity ::= SEQUENCE (SIZE (1..maxGANSSSat)) OF SEQUENCE {
    bad-ganss-satId
                                        INTEGER(0..63),
    bad-ganss-signalId
                                        BIT STRING(SIZE(8))
                                                                                                                      OPTIONAL,
    ie-Extensions
                                        ProtocolExtensionContainer { { GANSS-RealTimeInformationItem-ExtIEs } }
                                                                                                                      OPTIONAL,
    . . .
GANSS-RealTimeInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-RX-Pos ::= SEQUENCE {
    latitudeSign
                            ENUMERATED{north, south},
    degreesOfLatitude
                            INTEGER(0..2147483647),
    degreesOfLongitude
                            INTEGER (-2147483648..2147483647),
    directionOfAltitude
                            ENUMERATED{height,depth},
    altitude
                            INTEGER(0..32767),
                            ProtocolExtensionContainer { { GANSS-RX-Pos-ExtIEs } } OPTIONAL,
    ie-Extensions
GANSS-RX-Pos-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-SatelliteInformationKP ::= SEQUENCE (SIZE (1..maxGANSSSatAlmanac)) OF SEQUENCE {
```

```
satId
                                        INTEGER(0..63),
    ganss-e-alm
                                        BIT STRING (SIZE (11)),
    ganss-delta-I-alm
                                       BIT STRING (SIZE (11)),
    ganss-omegadot-alm
                                       BIT STRING (SIZE (11)),
                                       BIT STRING (SIZE (4)),
    ganss-svhealth-alm
    ganss-delta-a-sgrt-alm
                                       BIT STRING (SIZE (17)),
    ganss-omegazero-alm
                                       BIT STRING (SIZE (16)),
    ganss-m-zero-alm
                                       BIT STRING (SIZE (16)),
    ganss-omega-alm
                                        BIT STRING (SIZE (16)),
    ganss-af-zero-alm
                                        BIT STRING (SIZE (14)),
    ganss-af-one-alm
                                       BIT STRING (SIZE (11)),
    ie-Extensions
                                        ProtocolExtensionContainer { { GANSS-SatelliteInformationKPItem-ExtIEs } } OPTIONAL,
GANSS-SatelliteInformationKPItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Ganss-Sat-Info-AddNavList ::= SEQUENCE (SIZE (1..maxGANSSSat)) OF SEQUENCE {
                               INTEGER (0..63),
    svHealth
                               BIT STRING (SIZE (6)),
    iod
                               BIT STRING (SIZE (11)),
    ganssAddClockModels
                                GANSS-AddClockModels,
    ganssAddOrbitModels
                                GANSS-AddOrbitModels,
                               ProtocolExtensionContainer { { Ganss-Sat-Info-AddNavList-ExtIEs } } OPTIONAL,
    ie-Extensions
Ganss-Sat-Info-AddNavList-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-SAT-Info-Almanac-GLOkpList ::= SEQUENCE (SIZE (1.. maxGANSSSatAlmanac)) OF SEQUENCE {
    aloAlmNA
                           BIT STRING (SIZE(11)),
    gloAlmnA
                           BIT STRING (SIZE(5)),
    qloAlmHA
                          BIT STRING (SIZE(5)),
    gloAlmLambdaA
                           BIT STRING (SIZE(21)),
    qloAlmTlambdaA
                           BIT STRING (SIZE(21)),
    qloAlmDeltaIA
                           BIT STRING (SIZE(18)),
    gloAkmDeltaTA
                           BIT STRING (SIZE(22)),
    gloAlmDeltaTdotA
                           BIT STRING (SIZE(7)),
    gloAlmEpsilonA
                           BIT STRING (SIZE(15)),
    gloAlmOmegaA
                           BIT STRING (SIZE(16)),
    gloAlmTauA
                            BIT STRING (SIZE(10)),
    gloAlmCA
                           BIT STRING (SIZE(1)),
    gloAlmMA
                           BIT STRING (SIZE(2))
    OPTIONAL,
    ie-Extensions
                            ProtocolExtensionContainer { GANSS-SAT-Info-Almanac-GLOkp-ExtIEs } }
                                                                                                                    OPTIONAL,
```

```
GANSS-SAT-Info-Almanac-GLOkp-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-SAT-Info-Almanac-MIDIkpList ::= SEQUENCE (SIZE (1.. maxGANSSSatAlmanac)) OF SEQUENCE {
    svID
                 INTEGER(0..63),
                          BIT STRING (SIZE (11)),
BIT STRING (SIZE (11)),
    midiAlmE
    midiAlmDeltaI
    midiAlmOmegaDot
                           BIT STRING (SIZE (11)),
    midiAlmSgrtA
                              BIT STRING (SIZE (17)),
    midiAlmOmega0
                              BIT STRING (SIZE (16)),
    midiAlmOmega
                              BIT STRING (SIZE (16)),
    midiAlmMo
                              BIT STRING (SIZE (16)),
    midiAlmaf0
                           BIT STRING (SIZE (11)),
    midiAlmaf1
                           BIT STRING (SIZE (10)),
                       BIT STRING (SIZE (1)),
BIT STRING (SIZE (1)),
BIT STRING (SIZE (1)).
    midiAlmL1Health
    midiAlmL2Health
    midiAlmL5Health
    ie-Extensions
                              ProtocolExtensionContainer { GANSS-SAT-Info-Almanac-MIDIkp-ExtIEs } }
                                                                                                                                 OPTIONAL.
GANSS-SAT-Info-Almanac-MIDIkp-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-SAT-Info-Almanac-NAVkpList ::= SEQUENCE (SIZE (1.. maxGANSSSatAlmanac)) OF SEQUENCE {
                 INTEGER(0..63),
    navAlmE
                              BIT STRING (SIZE (16)),
   navAlmDeltaI BIT STRING (SIZE (16)),
navAlmOMEGADOT BIT STRING (SIZE (16)),
navAlmSVHealth BIT STRING (SIZE (8)),
navAlmSqrtA BIT STRING (SIZE (24)),
navAlmOMEGAO BIT STRING (SIZE (24)),
    navAlmOmega
                            BIT STRING (SIZE (24)),
    navAlmMo
                              BIT STRING (SIZE (24)),
    navAlmaf0
                              BIT STRING (SIZE (11)),
    navAlmaf1
                              BIT STRING (SIZE (11)),
                              ProtocolExtensionContainer { GANSS-SAT-Info-Almanac-NAVkp-ExtIEs } }
    ie-Extensions
                                                                                                                                 OPTIONAL,
GANSS-SAT-Info-Almanac-NAVkp-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-SAT-Info-Almanac-REDkpList ::= SEQUENCE (SIZE (1.. maxGANSSSatAlmanac)) OF SEQUENCE {
    svID
                               INTEGER(0..63),
```

```
redAlmDeltaA
                           BIT STRING (SIZE (8)),
   redAlmOmega0
                           BIT STRING (SIZE (7)),
   redAlmPhi0
                           BIT STRING (SIZE (7)),
    redAlmL1Health
                           BIT STRING (SIZE (1)),
   redAlmL2Health
                           BIT STRING (SIZE (1)),
    redAlmL5Health
                           BIT STRING (SIZE (1)),
                           ProtocolExtensionContainer { GANSS-SAT-Info-Almanac-REDkp-ExtIEs } }
    ie-Extensions
                                                                                                                   OPTIONAL,
GANSS-SAT-Info-Almanac-REDkp-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-SAT-Info-Almanac-SBASecefList ::= SEQUENCE (SIZE (1.. maxGANSSSatAlmanac)) OF SEQUENCE {
    sbasAlmDataID BIT STRING (SIZE(2)),
    svID
                           INTEGER(0..63),
    sbasAlmHealth
                           BIT STRING (SIZE(8)),
    sbasAlmXg
                         BIT STRING (SIZE(15)),
    sbasAlmYq
                         BIT STRING (SIZE(15)),
    sbasAlmZg
                           BIT STRING (SIZE(9)),
    sbasAlmXqdot
                           BIT STRING (SIZE(3)),
    sbasAlmYqDot
                           BIT STRING (SIZE(3)),
    sbasAlmZqDot
                           BIT STRING (SIZE(4)),
                           BIT STRING (SIZE(11)),
    sbasAlmTo
                           ProtocolExtensionContainer { GANSS-SAT-Info-Almanac-SBASecef-ExtIEs } }
    ie-Extensions
                                                                                                                   OPTIONAL,
GANSS-SAT-Info-Almanac-SBASecef-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-Sat-Info-Nav ::= SEQUENCE (SIZE(1..maxGANSSSat)) OF SEQUENCE {
    satId
                               INTEGER(0..63),
    svHealth
                               BIT STRING (SIZE(5)),
    iod
                               BIT STRING (SIZE(10)),
    ganssClockModel
                               GANSS-Clock-Model,
    ganssOrbitModel
                               GANSS-Orbit-Model,
    ie-Extensions
                               ProtocolExtensionContainer { GANSS-Sat-Info-Nav-ExtIEs } } OPTIONAL,
GANSS-Sat-Info-Nav-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
GANSS-SBAS-ID ::= ENUMERATED
```

```
waas,
                              egnos,
                              msas,
                              gagan,
GANSS-SBASclockModel ::= SEQUENCE {
   sbasTo
                         BIT STRING (SIZE (13)),
   sbasAqfo
                         BIT STRING (SIZE (12)),
   sbasAqf1
                        BIT STRING (SIZE (8)),
   ie-Extensions
                         ProtocolExtensionContainer { { GANSS-SBASclockModel-ExtIEs } } OPTIONAL,
GANSS-SBASclockModel-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-Signal-ID ::= INTEGER(0..7,...)
GANSS-StatusHealth ::= ENUMERATED {
  udre-scale-1dot0,
  udre-scale-0dot75,
  udre-scale-0dot5,
  udre-scale-0dot3,
  udre-scale-0dot2,
  udre-scale-0dot1,
  no-data,
  invalid-data
GANSS-Time-ID ::= INTEGER(0..7,...)
GANSS-Time-Model ::= SEQUENCE {
   ganss-time-model-Ref-Time
                                     INTEGER(0..37799),
   ganss-t-a0
                                     INTEGER(-2147483648..2147483647),
   ganss-t-al
                                     INTEGER(-8388608..8388607)
                                                                                                             OPTIONAL,
                                     INTEGER(-64..63)
                                                                                                             OPTIONAL,
   ganss-t-a2
                                     ENUMERATED{gps,...,galileo,qzss,glonass},
   gnss-to-id
                                     INTEGER(0..8191)
   ganss-wk-number
                                                                                                             OPTIONAL,
   ie-Extensions
                                     ProtocolExtensionContainer { { GANSS-Time-Model-ExtIEs } }
                                                                                                             OPTIONAL,
GANSS-Time-Model-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    optional},
```

```
GANSS-Transmission-Time ::= SEQUENCE {
    ganssDay
                              INTEGER (0..8191)
   OPTIONAL,
    ganssTod
                              INTEGER(0..86399),
                              ProtocolExtensionContainer { GANSS-Transmission-Time-ExtIEs } }
   ie-Extensions
   OPTIONAL,
GANSS-Transmission-Time-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-UTC-Model ::= SEQUENCE {
                                     BIT STRING (SIZE (24)),
   a-one-utc
   a-zero-utc
                                     BIT STRING (SIZE (32)),
   t-ot-utc
                                     BIT STRING (SIZE (8)),
    w-n-t-ut.c
                                     BIT STRING (SIZE (8)),
   delta-t-ls-utc
                                     BIT STRING (SIZE (8)),
    w-n-lsf-utc
                                     BIT STRING (SIZE (8)),
    dn-utc
                                     BIT STRING (SIZE (8)),
    delta-t-lsf-utc
                                     BIT STRING (SIZE (8)),
   ie-Extensions
                                     ProtocolExtensionContainer { { GANSS-UTC-Model-ExtIEs } }
                                                                                                             OPTIONAL,
GANSS-UTC-Model-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
GANSS-UTCmodelSet1 ::= SEQUENCE {
   utcA0
                     BIT STRING (SIZE(16)),
   utcA1
                    BIT STRING (SIZE(13)),
    utcA2
                     BIT STRING (SIZE(7)),
   utcDeltaTls
                     BIT STRING (SIZE(8)),
   utcTot
                     BIT STRING (SIZE(16)),
    utcWNot
                     BIT STRING (SIZE(13)),
    utcWNlsf
                     BIT STRING (SIZE(8)),
   utcDN
                     BIT STRING (SIZE(4)),
    utcDeltaTlsf
                    BIT STRING (SIZE(8)),
    ie-Extensions
                     OPTIONAL,
GANSS-UTCmodelSet1-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-UTCmodelSet2 ::= SEQUENCE {
   nΑ
                      BIT STRING (SIZE(11)),
```

```
BIT STRING (SIZE(32)),
   tauC
   deltaUT1
                      GANSS-DeltaUT1
                                                                                 OPTIONAL,
   kр
                      BIT STRING (SIZE(2))
                                                                                 OPTIONAL,
   ie-Extensions
                      OPTIONAL.
GANSS-UTCmodelSet2-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GANSS-UTCmodelSet3 ::= SEOUENCE {
   utcA1wnt
                      BIT STRING (SIZE(24)),
   utcA0wnt
                      BIT STRING (SIZE(32)),
   utcTot
                     BIT STRING (SIZE(8)),
   utcWNt
                     BIT STRING (SIZE(8)),
   utcDeltaTls
                      BIT STRING (SIZE(8)),
   utcWNlsf
                      BIT STRING (SIZE(8)),
   ut.cDN
                      BIT STRING (SIZE(8)),
   utcDeltaTlsf
                      BIT STRING (SIZE(8)),
   utcStandardID
                      BIT STRING (SIZE(3)),
   ie-Extensions
                      OPTIONAL,
GANSS-UTCmodelSet3-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GA-PointWithAltitude ::= SEQUENCE {
   geographicalCoordinates
                             GeographicalCoordinate,
   altitudeAndDirection
                             GA-AltitudeAndDirection,
   iE-Extensions
                             ProtocolExtensionContainer { { GA-PointWithAltitude-ExtIEs} } OPTIONAL,
GA-PointWithAltitude-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GA-PointWithAltitudeAndUncertaintvEllipsoid ::= SEOUENCE {
   geographicalCoordinates
                             GeographicalCoordinate,
   altitudeAndDirection
                             GA-AltitudeAndDirection,
   uncertaintyEllipse
                             GA-UncertaintyEllipse,
   uncertaintyAltitude
                             INTEGER (0..127),
   confidence
                             INTEGER (0..127),
                             ProtocolExtensionContainer { { GA-PointWithAltitudeAndUncertaintyEllipsoid-ExtIEs} } OPTIONAL,
   iE-Extensions
   . . .
GA-PointWithAltitudeAndUncertaintyEllipsoid-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
GA-PointWithUnCertaintyEllipse ::= SEQUENCE {
    geographicalCoordinates
                               GeographicalCoordinate,
    uncertaintyEllipse
                               GA-UncertaintyEllipse,
    confidence
                               INTEGER (0..127),
                               ProtocolExtensionContainer { GA-PointWithUnCertaintyEllipse-ExtIEs} } OPTIONAL,
    iE-Extensions
GA-PointWithUnCertaintyEllipse-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GA-UncertaintyEllipse ::= SEQUENCE {
    uncertaintySemi-major
                               INTEGER (0..127),
    uncertaintySemi-minor
                               INTEGER (0..127),
    orientationOfMajorAxis
                               INTEGER (0..179), -- The values 90..179 shall not be used.
GA-PointWithUnCertainty ::=SEQUENCE {
                               GeographicalCoordinate,
    geographicalCoordinates
                         INTEGER (0..127),
    uncertaintyCode
                           ProtocolExtensionContainer { {GA-PointWithUnCertainty-ExtIEs} } OPTIONAL,
   iE-Extensions
GA-PointWithUnCertainty-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GA-AccessPointPosition ::= SEQUENCE {
    geographicalCoordinate
                               GeographicalCoordinate,
                           ProtocolExtensionContainer { {GA-AccessPoint-ExtIEs} } OPTIONAL,
   iE-Extensions
GA-AccessPoint-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GeographicalCoordinate ::= SEQUENCE {
   latitudeSign
                  ENUMERATED { north, south },
   latitude
                       INTEGER (0..8388607),
   longitude
                      INTEGER (-8388608..8388607),
                           ProtocolExtensionContainer { {GeographicalCoordinate-ExtIEs} } OPTIONAL,
   iE-Extensions
GeographicalCoordinate-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GERAN-Cell-Capability ::= BIT STRING (SIZE (16))
```

```
-- First bit: A/Gb mode --
-- Second bit: Iu mode --
-- Note: undefined bits are considered as a spare bit and spare bits shall be set to 0 by the transmitter and shall be ignored by the receiver. -
GERAN-Classmark ::=
                           OCTET STRING
   -- GERAN Classmark as defined in (38) --
GERAN-SI-Type ::= CHOICE {
   sI
                               GERAN-SystemInfo,
                              GERAN-SystemInfo,
   pSI
    . . .
GERAN-SystemInfo ::= SEQUENCE (SIZE (1..maxNrOfGERANSI)) OF
       SEQUENCE {
           gERAN-SI-block
                              OCTET STRING (SIZE (1..23)),
           iE-Extensions
                              OPTIONAL,
GERAN-SystemInfo-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GenericTrafficCategory ::= BIT STRING (SIZE (8))
GPS-Almanac ::= SEQUENCE {
   wn<sub>a</sub>-alm
                           BIT STRING (SIZE (8)),
    satellite-Almanac-Information
                                      SEQUENCE (SIZE (1..maxNoSat)) OF
       SEQUENCE {
           data-id
                              DATA-ID,
           sAT-ID
                              SAT-ID,
           gps-e-alm
                              BIT STRING (SIZE (16)),
                              BIT STRING (SIZE (8)),
           gps-toa-alm
           gps-delta-I-alm BIT STRING (SIZE (16)),
           omegadot-alm
                              BIT STRING (SIZE (16)),
           svhealth-alm
                              BIT STRING (SIZE (8)),
           gps-a-sgrt-alm
                              BIT STRING (SIZE (24)),
           omegazero-alm
                              BIT STRING (SIZE (24)),
           m-zero-alm
                              BIT STRING (SIZE (24)),
           gps-omega-alm
                              BIT STRING (SIZE (24)),
           gps-af-zero-alm
                              BIT STRING (SIZE (11)),
           gps-af-one-alm
                              BIT STRING (SIZE (11)),
                              ProtocolExtensionContainer { { Satellite-Almanac-Information-ExtIEs} }
           iE-Extensions
                                                                                                             OPTIONAL,
    -- This GPS-Almanac-Information is for the 1st 16 satellites
                          BIT STRING (SIZE (364))
    sVGlobalHealth-alm
                                                     OPTIONAL,
   iE-Extensions
                          ProtocolExtensionContainer { GPS-Almanac-ExtIEs} }
                                                                                     OPTIONAL,
Satellite-Almanac-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   . . .
```

```
GPS-Almanac-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-Satellite-Almanac-Information-ExtItem CRITICALITY ignore EXTENSION Satellite-Almanac-Information-ExtItem
                                                                                                                                      PRESENCE
    optional}|
    { ID id-completeAlmanacProvided
                                                   CRITICALITY ignore EXTENSION CompleteAlmanacProvided
    PRESENCE optional },
Satellite-Almanac-Information-ExtItem ::= SEQUENCE (SIZE (1..maxNrOfSatAlmanac-maxNoSat)) OF
       SEQUENCE {
           dATA-ID
                               DATA-ID,
           sAT-ID
                               SAT-ID,
           qps-e-alm
                               BIT STRING (SIZE (16)),
           qps-toa-alm
                               BIT STRING (SIZE (8)),
           gps-delta-I-alm BIT STRING (SIZE (16)),
           omegadot-alm BIT STRING (SIZE (16)),
           svhealth-alm
                               BIT STRING (SIZE (8)),
           gps-a-sqrt-alm
                               BIT STRING (SIZE (24)),
           omegazero-alm
                               BIT STRING (SIZE (24)),
           m-zero-alm
                               BIT STRING (SIZE (24)),
           gps-omega-alm
                               BIT STRING (SIZE (24)),
                               BIT STRING (SIZE (11)),
           gps-af-zero-alm
           gps-af-one-alm
                               BIT STRING (SIZE (11)),
           iE-Extensions
                               ProtocolExtensionContainer { { Satellite-Almanac-Information-ExtItemIEs} }
                                                                                                                       OPTIONAL,
-- Includes the GPS-Almanac-Information for the 17^{\rm th} through 32^{\rm nd} satellites.
Satellite-Almanac-Information-ExtItemIEs RNSAP-PROTOCOL-EXTENSION ::= {
GPSInformation ::= SEQUENCE (SIZE (1..maxNoGPSTypes)) OF
    SEOUENCE {
       gPSInformationItem
                               ENUMERATED {
           qPS-NavigationModel-and-TimeRecovery,
           qPS-Ionospheric-Model,
           qPS-UTC-Model,
           gPS-Almanac,
           gPS-RealTime-Integrity,
                               ProtocolExtensionContainer { { GPSInformation-ExtIEs} }
       iE-Extensions
                                                                                           OPTIONAL,
-- This IE shall be present if the Information Type IE indicates 'GPS Information'
GPSInformation-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GPS-Ionospheric-Model ::= SEQUENCE {
```

```
alpha-zero-ionos
                            BIT STRING (SIZE (8)),
    alpha-one-ionos
                            BIT STRING (SIZE (8)),
    alpha-two-ionos
                            BIT STRING (SIZE (8)),
    alpha-three-ionos
                            BIT STRING (SIZE (8)),
    beta-zero-ionos
                            BIT STRING (SIZE (8)),
    beta-one-ionos
                            BIT STRING (SIZE (8)),
    beta-two-ionos
                            BIT STRING (SIZE (8)),
    beta-three-ionos
                            BIT STRING (SIZE (8)),
    iE-Extensions
                            ProtocolExtensionContainer { { GPS-Ionospheric-Model-ExtIEs} }
                                                                                                  OPTIONAL,
GPS-Ionospheric-Model-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GPS-NavigationModel-and-TimeRecovery ::= SEQUENCE (SIZE (1..maxNoSat)) OF
    SEQUENCE {
        tx-tow-nav
                                        INTEGER (0..1048575),
        sAT-ID
                                        SAT-ID,
        tlm-message-nav
                                        BIT STRING (SIZE (14)),
       tlm-revd-c-nav
                                        BIT STRING (SIZE (2)),
       ho-word-nav
                                        BIT STRING (SIZE (22)),
        w-n-nav
                                        BIT STRING (SIZE (10)),
        ca-or-p-on-12-nav
                                        BIT STRING (SIZE (2)),
        user-range-accuracy-index-nav
                                        BIT STRING (SIZE (4)),
        sv-health-nav
                                        BIT STRING (SIZE (6)),
        iodc-nav
                                        BIT STRING (SIZE (10)),
       12-p-dataflag-nav
                                        BIT STRING (SIZE (1)),
        sfl-reserved-nav
                                        BIT STRING (SIZE (87)),
        t-qd-nav
                                        BIT STRING (SIZE (8)),
        t-oc-nav
                                        BIT STRING (SIZE (16)),
        a-f-2-nav
                                        BIT STRING (SIZE (8)),
       a-f-1-nav
                                        BIT STRING (SIZE (16)),
       a-f-zero-nav
                                        BIT STRING (SIZE (22)),
       c-rs-nav
                                        BIT STRING (SIZE (16)),
        delta-n-nav
                                        BIT STRING (SIZE (16)),
        m-zero-nav
                                        BIT STRING (SIZE (32)),
        c-uc-nav
                                        BIT STRING (SIZE (16)),
        qps-e-nav
                                        BIT STRING (SIZE (32)),
                                        BIT STRING (SIZE (16)),
        c-us-nav
        a-sgrt-nav
                                        BIT STRING (SIZE (32)),
        t-oe-nav
                                        BIT STRING (SIZE (16)),
        fit-interval-flag-nav
                                        BIT STRING (SIZE (1)),
        aodo-nav
                                        BIT STRING (SIZE (5)),
                                        BIT STRING (SIZE (16)),
        c-ic-nav
        omega-zero-nav
                                        BIT STRING (SIZE (32)),
       c-is-nav
                                        BIT STRING (SIZE (16)),
        i-zero-nav
                                        BIT STRING (SIZE (32)),
        c-rc-nav
                                        BIT STRING (SIZE (16)),
        gps-omega-nav
                                        BIT STRING (SIZE (32)),
        omegadot-nav
                                        BIT STRING (SIZE (24)),
        idot-nav
                                        BIT STRING (SIZE (14)),
        spare-zero-fill
                                        BIT STRING (SIZE (20)),
```

```
ProtocolExtensionContainer { GPS-NavigationModel-and-TimeRecoveryItem-ExtIEs} }
       iE-Extensions
                                                                                                                                OPTIONAL,
GPS-NavigationModel-and-TimeRecoveryItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GPS-RealTime-Integrity ::= CHOICE {
   badSatellites
                              BadSatellites,
   noBadSatellite
                              NULL
GPS-RX-POS ::= SEQUENCE {
    geographicalCoordinate
                              GeographicalCoordinate,
    altitudeAndDirection
                              GA-AltitudeAndDirection,
   iE-Extensions
                              ProtocolExtensionContainer { GPS-RX-POS-ExtIEs} } OPTIONAL,
GPS-RX-POS-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
GPS-Status-Health ::= ENUMERATED {
  udre-1-0.
  udre-0-75,
  udre-0-5,
  udre-0-3,
  udre-0-1,
  no-data,
  invalid-data
GPSTOW ::= INTEGER (0..604799)
GPS-UTC-Model ::= SEQUENCE {
    a-one-utc
                          BIT STRING (SIZE (24)),
   a-zero-utc
                          BIT STRING (SIZE (32)),
    t-ot-utc
                        BIT STRING (SIZE (8)),
    delta-t-ls-utc
                        BIT STRING (SIZE (8)),
   w-n-t-utc
                          BIT STRING (SIZE (8)),
   w-n-lsf-utc
                          BIT STRING (SIZE (8)),
    dn-utc
                          BIT STRING (SIZE (8)),
    delta-t-lsf-utc
                          BIT STRING (SIZE (8)),
                          iE-Extensions
                                                                                   OPTIONAL,
GPS-UTC-Model-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Guaranteed-Rate-Information ::= SEQUENCE {
```

```
guaranteed-UL-Rate
                                Guaranteed-Rate OPTIONAL,
    quaranteed-DL-Rate
                                Guaranteed-Rate OPTIONAL,
    iE-Extensions
                                ProtocolExtensionContainer { {Guaranteed-Rate-Information-ExtIEs} } OPTIONAL,
Guaranteed-Rate-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Guaranteed-Rate
                     ::= INTEGER (1..maxNrOfTFs)
-- "1": TFI 0, "2": TFI 1, "3": TFI 2, ...
-- H
HARO-Info-for-E-DCH ::= ENUMERATED {
   rv0,
   rvtable
HARQ-MemoryPartitioning ::= CHOICE {
    implicit
                    HARQ-MemoryPartitioning-Implicit,
    explicit
                    HARQ-MemoryPartitioning-Explicit,
    . . .
HARO-MemoryPartitioning-Implicit ::= SEOUENCE {
    number-of-Processes
                         INTEGER (1..8,...,12|14|16),
                               ProtocolExtensionContainer { { HARO-MemoryPartitioning-Implicit-ExtIEs } }
    iE-Extensions
                                                                                                                                OPTIONAL,
HARQ-MemoryPartitioning-Implicit-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HARQ-MemoryPartitioning-Explicit
                                  ::= SEQUENCE {
                                        HARO-MemoryPartitioningList,
    hARO-MemoryPartitioningList
                                        ProtocolExtensionContainer { { HARQ-MemoryPartitioning-Explicit-ExtIEs } }
    iE-Extensions
                                                                                                                                        OPTIONAL,
    . . .
HARQ-MemoryPartitioning-Explicit-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    {ID id-HARQ-MemoryPartitioningInfoExtForMIMO
                                                   CRITICALITY ignore EXTENSION HARQ-MemoryPartitioningInfoExtForMIMO PRESENCE optional },
    . . .
HARQ-MemoryPartitioningList ::= SEQUENCE (SIZE (1..maxNrOfHARQProc)) OF HARQ-MemoryPartitioningItem
HARQ-MemoryPartitioningInfoExtForMIMO ::= SEQUENCE (SIZE (4 | 6 | 8)) OF HARQ-MemoryPartitioningItem
HARQ-MemoryPartitioningItem ::= SEQUENCE {
    process-Memory-Size
                                        ENUMERATED {
                                        hms800, hms1600, hms2400, hms3200, hms4000,
```

```
hms4800, hms5600, hms6400, hms7200, hms8000,
                                        hms8800, hms9600, hms10400, hms11200, hms12000,
                                        hms12800, hms13600, hms14400, hms15200, hms16000,
                                        hms17600, hms19200, hms20800, hms22400, hms24000,
                                        hms25600, hms27200, hms28800, hms30400, hms32000,
                                        hms36000, hms40000, hms44000, hms48000, hms52000,
                                        hms56000, hms60000, hms64000, hms68000, hms72000,
                                        hms76000, hms80000, hms88000, hms96000, hms104000,
                                        hms112000, hms120000, hms128000, hms136000, hms144000,
                                        hms152000, hms160000, hms176000, hms192000, hms208000,
                                        hms224000, hms240000, hms256000, hms272000, hms288000,
                                        hms304000,...},
    iE-Extensions
                                        ProtocolExtensionContainer { { HARQ-MemoryPartitioningItem-ExtIEs } }
                                                                                                                                 OPTIONAL,
    . . .
HARO-MemoryPartitioningItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HARQ-Preamble-Mode ::= ENUMERATED {
  mode0,
  mode1
HARO-Process-Allocation-2ms-EDCH ::= BIT STRING ( SIZE(maxNrOfEDCHHAROProcesses2msEDCH) )
HARO-Preamble-Mode-Activation-Indicator ::=ENUMERATED
    hargPreambleModeSupported
HCS-Prio ::= INTEGER (0..7)
-- 0 = lowest priority, ...7 = highest priority
HSDSCH-Configured-Indicator ::= ENUMERATED {
    configured-HS-DSCH,
    no-configured-HS-DSCH
HSDSCH-FDD-Information ::= SEQUENCE {
    hSDSCH-MACdFlows-Information
                                                HSDSCH-MACdFlows-Information,
    uE-Capabilities-Info
                                                UE-Capabilities-Info,
    mAChs-Reordering-Buffer-Size-for-RLC-UM
                                                MAChsReorderingBufferSize-for-RLC-UM,
    cqiFeedback-CycleK
                                                CQI-Feedback-Cycle,
    cgiRepetitionFactor
                                                COI-RepetitionFactor
                                                                                             OPTIONAL,
    -- This IE shall be present if the CQI Feedback Cycle k IE is set to a value greater than 0.
    ackNackRepetitionFactor
                                                AckNack-RepetitionFactor,
    cqiPowerOffset
                                                COI-Power-Offset,
    ackPowerOffset
                                                Ack-Power-Offset,
    nackPowerOffset
                                                Nack-Power-Offset,
    hsscch-PowerOffset
                                                HSSCCH-PowerOffset
                                                                                             OPTIONAL,
    iE-Extensions
                                                ProtocolExtensionContainer { { HSDSCH-FDD-Information-ExtIEs } }
                                                                                                                                 OPTIONAL,
```

```
HSDSCH-FDD-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
{ ID id-HARO-Preamble-Mode
                                                     CRITICALITY ignore EXTENSION
                                                                                     HARO-Preamble-Mode
    PRESENCE optional } |
{ ID id-MIMO-ActivationIndicator
                                                     CRITICALITY reject EXTENSION
                                                                                     MIMO-ActivationIndicator
        PRESENCE optional } |
{ ID id-HSDSCH-MACdPDUSizeFormat
                                                     CRITICALITY reject EXTENSION
                                                                                     HSDSCH-MACdPDUSizeFormat
        PRESENCE optional } |
{ ID id-SixtyfourQAM-UsageAllowedIndicator
                                                     CRITICALITY ignore EXTENSION
                                                                                     SixtyfourQAM-UsageAllowedIndicator
                                                                                                                                         PRESENCE
optional}
{ ID id-UE-with-enhanced-HS-SCCH-support-indicator
                                                         CRITICALITY ignore EXTENSION
                                                                                        NULL
    PRESENCE optional } |
{ ID id-EnhancedHSServingCC-Abort
                                                     CRITICALITY reject EXTENSION
                                                                                     EnhancedHSServingCC-Abort
        PRESENCE optional } |
{ ID id-UE-SupportIndicatorExtension
                                                     CRITICALITY ignore EXTENSION
                                                                                     UE-SupportIndicatorExtension
    PRESENCE optional } |
{ ID id-power-offset-for-S-CPICH-for-MIMO-Request-Indicator
                                                                CRITICALITY ignore
                                                                                     EXTENSION PowerOffsetForSecondaryCPICHforMIMORequestIndicator
           PRESENCE optional } |
{ ID id-Single-Stream-MIMO-ActivationIndicator
                                                     CRITICALITY reject EXTENSION
                                                                                     Single-Stream-MIMO-ActivationIndicator
                                                                                                                                         PRESENCE
optional},
HSDSCH-FDD-Information-Response ::= SEOUENCE {
    hSDSCH-MACdFlow-Specific-InfoList-Response
                                                     HSDSCH-MACdFlow-Specific-InfoList-Response
                    OPTIONAL,
    hSSCCH-Specific-InfoList-Response
                                                     HSSCCH-FDD-Specific-InfoList-Response
                    OPTIONAL,
    hSPDSCH-and-HSSCCH-ScramblingCode
                                                     DL-ScramblingCode
    OPTIONAL,
    measurement-Power-Offset
                                                     Measurement-Power-Offset
                    OPTIONAL,
    hARQ-MemoryPartitioning
                                                     HARQ-MemoryPartitioning
                    OPTIONAL,
    iE-Extensions
                                                     ProtocolExtensionContainer { { HSDSCH-FDD-Information-Response-ExtIEs } }
                                                                                                                                         OPTIONAL,
HSDSCH-FDD-Information-Response-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
  ID id-User-Plane-Congestion-Fields-Inclusion
                                                     CRITICALITY ignore EXTENSION User-Plane-Congestion-Fields-Inclusion
                                                                                                                                 PRESENCE optional }
 ID id-HARQ-Preamble-Mode-Activation-Indicator
                                                     CRITICALITY ignore EXTENSION HARQ-Preamble-Mode-Activation-Indicator
                                                                                                                                 PRESENCE optional }
 ID id-MIMO-InformationResponse
                                                     CRITICALITY ignore EXTENSION MIMO-InformationResponse
                                                                                                                                 PRESENCE optional}
 ID id-SixtyfourQAM-DL-UsageIndicator
                                                     CRITICALITY ignore EXTENSION SixtyfourQAM-DL-UsageIndicator
                                                                                                                                 PRESENCE optional}
 ID id-HSDSCH-TBSizeTableIndicator
                                                     CRITICALITY ignore EXTENSION HSDSCH-TBSizeTableIndicator
                                                                                                                                 PRESENCE optional}
 ID id-power-offset-for-S-CPICH-for-MIMO
                                                    CRITICALITY ignore EXTENSION PowerOffsetForSecondaryCPICHforMIMO
                                                                                                                                 PRESENCE optional }
 ID id-Support-of-Dynamic-DTXDRX-Related-HS-SCCH-Order CRITICALITY ignore EXTENSION Support-of-Dynamic-DTXDRX-Related-HS-SCCH-Order PRESENCE
optional },
    . . .
HS-DSCH-FDD-Secondary-Serving-Information ::= SEQUENCE {
    hsscch-PowerOffset
                                                     HSSCCH-PowerOffset
                                                                                                                  OPTIONAL,
    sixtyfourQAM-UsageAllowedIndicator
                                                     SixtyfourQAM-UsageAllowedIndicator
                                                                                                                  OPTIONAL,
```

```
ProtocolExtensionContainer { { HS-DSCH-FDD-Secondary-Serving-Information-ExtIEs } }
    iE-Extensions
    OPTIONAL.
    . . .
HS-DSCH-FDD-Secondary-Serving-Information-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
{ID id-MIMO-ActivationIndicator
                                                CRITICALITY reject EXTENSION MIMO-ActivationIndicator
                                                                                                                         PRESENCE optional }

m ^{\hat{i}} ID id-Single-Stream-MIMO-ActivationIndicator CRITICALITY reject EXTENSION Single-Stream-MIMO-ActivationIndicator
                                                                                                                         PRESENCE optional)
                                                                                                                         PRESENCE optional)
{ID id-DiversityMode
                                                CRITICALITY reject EXTENSION DiversityMode
ID id-TransmitDiversitvIndicator
                                                CRITICALITY reject EXTENSION TransmitDiversityIndicator
                                                                                                                         PRESENCE optional)
ID id-power-offset-for-S-CPICH-for-MIMO-Request-Indicator CRITICALITY ignore EXTENSION PowerOffsetForSecondaryCPICHforMIMORequestIndicator
    PRESENCE optional } |
{ID id-OrdinalNumberOfFrequency
                                                CRITICALITY reject EXTENSION OrdinalNumberOfFrequency
                                                                                                                         PRESENCE optional },
    . . .
HS-DSCH-FDD-Secondary-Serving-Information-Response ::= SEQUENCE {
    hSSCCH-Specific-InfoList-Response
                                            HSSCCH-FDD-Specific-InfoList-Response
                                                                                                          OPTIONAL,
                                            DL-ScramblingCode
    hSPDSCH-and-HSSCCH-ScramblingCode
                                                                                                          OPTIONAL,
    measurement-Power-Offset
                                            Measurement-Power-Offset
                                                                                                          OPTIONAL,
    sixtyfourQAM-DL-UsageIndicator
                                            SixtyfourQAM-DL-UsageIndicator
                                                                                                          OPTIONAL,
    hSDSCH-TBSizeTableIndicator
                                            HSDSCH-TBSizeTableIndicator
                                                                                                          OPTIONAL,
    iE-Extensions
                                            ProtocolExtensionContainer { { HS-DSCH-FDD-Secondary-Serving-Information-Respons-ExtIEs } }
        OPTIONAL,
HS-DSCH-FDD-Secondary-Serving-Information-Respons-ExtlEs RNSAP-PROTOCOL-EXTENSION ::=
{ID id-MIMO-InformationResponse
                                            CRITICALITY ignore EXTENSION MIMO-InformationResponse
                                                                                                                  PRESENCE optional |
{ID id-power-offset-for-S-CPICH-for-MIMO
                                            CRITICALITY ignore EXTENSION PowerOffsetForSecondaryCPICHforMIMO
                                                                                                                  PRESENCE optional },
    . . .
HS-DSCH-Secondary-Serving-Information-To-Modify ::= SEQUENCE {
    hsscch-PowerOffset
                                                HSSCCH-PowerOffset
                                                                                                   OPTIONAL,
   hSSCCH-CodeChangeGrant
                                                HSSCCH-Code-Change-Grant
                                                                                                   OPTIONAL,
    sixtyfourQAM-UsageAllowedIndicator
                                                SixtyfourQAM-UsageAllowedIndicator
                                                                                                   OPTIONAL,
    iE-Extensions
                                                ProtocolExtensionContainer { { HS-DSCH-Secondary-Serving-Information-To-Modify-ExtIEs } }
    OPTIONAL,
    . . .
HS-DSCH-Secondary-Serving-Information-To-Modify-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
{ID id-MIMO-Mode-Indicator
                                            CRITICALITY reject EXTENSION MIMO-Mode-Indicator
                                                                                                                         PRESENCE optional }
{ID id-Single-Stream-MIMO-Mode-Indicator
                                            CRITICALITY reject EXTENSION Single-Stream-MIMO-Mode-Indicator
                                                                                                                         PRESENCE optional}
{ID id-DiversityMode
                                            CRITICALITY reject EXTENSION DiversityMode
                                                                                                                         PRESENCE optional }
{ID id-TransmitDiversitvIndicator
                                            CRITICALITY reject EXTENSION TransmitDiversityIndicator
                                                                                                                         PRESENCE optional }
-- This IE shall be present if Diversity Mode IE is present and is not set to "none"
{ID id-NonCellSpecificTxDiversity
                                            CRITICALITY reject EXTENSION NonCellSpecificTxDiversity
                                                                                                                         PRESENCE optional } |
ID id-power-offset-for-S-CPICH-for-MIMO-Request-Indicator CRITICALITY ignore EXTENSION PowerOffsetForSecondaryCPICHforMIMORequestIndicator
    PRESENCE optional } |
{ID id-OrdinalNumberOfFrequency
                                            CRITICALITY reject EXTENSION OrdinalNumberOfFrequency
                                                                                                                         PRESENCE optional },
```

```
HS-DSCH-FDD-Secondary-Serving-Information-To-Modify-Unsynchronised ::= SEQUENCE {
    hsscch-PowerOffset
                                                HSSCCH-PowerOffset
                                                                                                  OPTIONAL.
    sixtyfourOAM-UsageAllowedIndicator
                                                SixtyfourOAM-UsageAllowedIndicator
                                                                                                  OPTIONAL.
    iE-Extensions
                            ProtocolExtensionContainer { { HS-DSCH-FDD-Secondary-Serving-Information-To-Modify-Unsynchronised-ExtIEs } }
        OPTIONAL,
HS-DSCH-FDD-Secondary-Serving-Information-To-Modify-Unsynchronised-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
{ID id-MIMO-Mode-Indicator
                                                CRITICALITY reject EXTENSION MIMO-Mode-Indicator
                                                                                                                         PRESENCE optional }
{ID id-Single-Stream-MIMO-Mode-Indicator
                                                CRITICALITY reject EXTENSION Single-Stream-MIMO-Mode-Indicator
                                                                                                                         PRESENCE optional }
ID id-power-offset-for-S-CPICH-for-MIMO-Request-Indicator CRITICALITY ignore EXTENSION PowerOffsetForSecondaryCPICHforMIMORequestIndicator
    PRESENCE optional }
{ID id-OrdinalNumberOfFrequency
                                    CRITICALITY reject EXTENSION OrdinalNumberOfFrequency
                                                                                                  PRESENCE optional },
HS-DSCH-FDD-Secondary-Serving-Update-Information ::= SEQUENCE {
    hsSCCHCodeChangeIndicator
                                                HSSCCH-CodeChangeIndicator
                                                                                            OPTIONAL,
   hS-PDSCH-Code-Change-Indicator
                                                HS-PDSCH-Code-Change-Indicator
                                                                                            OPTIONAL,
    -- This IE shall never be included. If received it shall be ignored.
                                                ProtocolExtensionContainer { { HS-DSCH-FDD-Secondary-Serving-Update-Information-ExtIEs } }
    iE-Extensions
    OPTIONAL,
HS-DSCH-FDD-Secondary-Serving-Update-Information-Extles RNSAP-PROTOCOL-EXTENSION ::= {
HS-DSCH-Secondary-Serving-Cell-Change-Information-Response ::= SEQUENCE
    hS-DSCH-Secondary-Serving-cell-choice
                                                HS-DSCH-Secondary-Serving-cell-change-choice,
                                                ProtocolExtensionContainer { { HS-DSCH-Secondary-Serving-Cell-Change-Information-Response-ExtIEs }
    iE-Extensions
        OPTIONAL,
    . . .
HS-DSCH-Secondary-Serving-Cell-Change-Information-Response-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HS-DSCH-Secondary-Serving-cell-change-choice ::= CHOICE
    hS-Secondary-Serving-cell-change-successful
                                                        HS-Secondary-Serving-cell-change-successful,
    hS-Secondary-Serving-cell-change-unsuccessful
                                                        HS-Secondary-Serving-cell-change-unsuccessful,
HS-Secondary-Serving-cell-change-successful ::= SEQUENCE {
    hS-DSCH-FDD-Secondary-Serving-Information-Response
                                                            HS-DSCH-FDD-Secondary-Serving-Information-Response,
                                                            HSDSCH-RNTI,
    hSDSCH-RNTI
    iE-Extensions
                                        ProtocolExtensionContainer { { HS-Secondary-Serving-cell-change-successful-ExtIEs} } OPTIONAL,
```

```
HS-Secondary-Serving-cell-change-successful-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HS-Secondary-Serving-cell-change-unsuccessful ::= SEOUENCE {
    iE-Extensions
                                   ProtocolExtensionContainer { { HS-Secondary-Serving-cell-change-unsuccessful-ExtIEs} } OPTIONAL,
HS-Secondary-Serving-cell-change-unsuccessful-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HS-DSCH-Secondary-Serving-Remove ::= NULL
HSDSCH-Information-to-Modify ::= SEQUENCE
    hSDSCH-MACdFlow-Specific-InfoList-to-Modify
                                                    HSDSCH-MACdFlow-Specific-InfoList-to-Modify
                                                                                                        OPTIONAL,
    priorityOueue-Info-to-Modify
                                                    PriorityOueue-InfoList-to-Modify
                                                                                                        OPTIONAL,
    mAChs-Reordering-Buffer-Size-for-RLC-UM
                                                    MAChsReorderingBufferSize-for-RLC-UM
                                                                                                        OPTIONAL,
    cgiFeedback-CycleK
                                                    CQI-Feedback-Cycle
                                                                                                        OPTIONAL,
                                                                                                                       -- For FDD only
    cqiRepetitionFactor
                                                    CQI-RepetitionFactor
                                                                                                        OPTIONAL,
                                                                                                                       -- For FDD only
    ackNackRepetitionFactor
                                                    AckNack-RepetitionFactor
                                                                                                        OPTIONAL,
                                                                                                                       -- For FDD only
    cgiPowerOffset
                                                    COI-Power-Offset
                                                                                                        OPTIONAL,
                                                                                                                       -- For FDD only
    ackPowerOffset
                                                    Ack-Power-Offset
                                                                                                                       -- For FDD only
                                                                                                        OPTIONAL,
    nackPowerOffset
                                                   Nack-Power-Offset
                                                                                                                       -- For FDD only
                                                                                                        OPTIONAL,
    hsscch-PowerOffset
                                                    HSSCCH-PowerOffset
                                                                                                        OPTIONAL,
                                                                                                                       -- For FDD only
    hSSCCH-CodeChangeGrant
                                                   HSSCCH-Code-Change-Grant
                                                                                                        OPTIONAL,
    tDDAckNackPowerOffset
                                                   TDD-AckNack-Power-Offset
                                                                                                        OPTIONAL,
                                                                                                                       -- For TDD only
    iE-Extensions
                                                    OPTIONAL,
    . . .
HSDSCH-Information-to-Modify-ExtlEs RNSAP-PROTOCOL-EXTENSION ::=
{ ID id-HARQ-Preamble-Mode
                                       CRITICALITY ignore
                                                               EXTENSION
                                                                           HARO-Preamble-Mode
    PRESENCE optional } |
{ ID id-HS-PDSCH-Code-Change-Grant
                                                                                                                   PRESENCE optional } |
                                       CRITICALITY ignore
                                                               EXTENSION
                                                                           HS-PDSCH-Code-Change-Grant
     -- Applicable to FDD only
{ ID id-MIMO-Mode-Indicator
                                           CRITICALITY reject
                                                                   EXTENSION
                                                                               MIMO-Mode-Indicator
    PRESENCE optional } |
{ ID id-HSDSCH-MACdPDUSizeFormat
                                                                               HSDSCH-MACdPDUSizeFormat
                                                                                                                                      PRESENCE
                                           CRITICALITY reject
                                                                   EXTENSION
optional}|
{ ID id-SixtyfourOAM-UsageAllowedIndicator CRITICALITY ignore
                                                                               SixtyfourOAM-UsageAllowedIndicator
                                                                                                                       PRESENCE optional | |
                                                                   EXTENSION
{ ID id-UE-Capabilities-Info
                                           CRITICALITY ignore
                                                                   EXTENSION
                                                                               UE-Capabilities-Info
    PRESENCE optional | |
{ ID id-EnhancedHSServingCC-Abort
                                           CRITICALITY reject
                                                                   EXTENSION
                                                                               EnhancedHSServingCC-Abort
                                                                                                                                      PRESENCE
optional}|
{ ID id-UE-SupportIndicatorExtension
                                           CRITICALITY ignore
                                                                               UE-SupportIndicatorExtension
                                                                                                                               PRESENCE optional } |
                                                                   EXTENSION
{ ID id-power-offset-for-S-CPICH-for-MIMO-Request-Indicator
                                                               CRITICALITY ignore EXTENSION PowerOffsetForSecondaryCPICHforMIMORequestIndicator
           PRESENCE optional |
{ ID id-Single-Stream-MIMO-Mode-Indicator
                                          CRITICALITY reject
                                                                               Single-Stream-MIMO-Mode-Indicator PRESENCE optional },
                                                                   EXTENSION
```

```
HSDSCH-Information-to-Modify-Unsynchronised ::= SEQUENCE
    hSDSCH-MACdFlow-Specific-InfoList-to-Modify
                                                    HSDSCH-MACdFlow-Specific-InfoList-to-Modify
                                                                                                                         OPTIONAL.
                                                    PriorityOueue-InfoList-to-Modify-Unsynchronised
    priorityOueueInfotoModifyUnsynchronised
                                                                                                                         OPTIONAL.
    cqiPowerOffset
                                                    COI-Power-Offset
                                                                                     OPTIONAL,
                                                                                                -- For FDD only
    ackPowerOffset.
                                                    Ack-Power-Offset
                                                                                     OPTIONAL.
                                                                                                -- For FDD only
                                                    Nack-Power-Offset
    nackPowerOffset
                                                                                     OPTIONAL,
                                                                                                -- For FDD only
    hsscch-PowerOffset
                                                    HSSCCH-PowerOffset
                                                                                     OPTIONAL,
                                                                                                -- Only for FDD
                                                                                                -- For TDD only
    tDDAckNackPowerOffset
                                                    TDD-AckNack-Power-Offset
                                                                                     OPTIONAL,
                                                    ProtocolExtensionContainer { { HSDSCH-Information-to-Modify-Unsynchronised-ExtIEs } }
    iE-Extensions
        OPTIONAL,
    . . .
HSDSCH-Information-to-Modify-Unsynchronised-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
 ID id-HARO-Preamble-Mode
                                            CRITICALITY ignore
                                                                                                                     PRESENCE optional } |
                                                                    EXTENSION
                                                                                HARO-Preamble-Mode
 ID id-MIMO-Mode-Indicator
                                            CRITICALITY reject
                                                                                MIMO-Mode-Indicator
                                                                    EXTENSION
    PRESENCE optional |
{ ID id-SixtyfourQAM-UsageAllowedIndicator CRITICALITY ignore
                                                                                 SixtyfourOAM-UsageAllowedIndicator PRESENCE optional}
                                                                    EXTENSION
{ ID id-EnhancedHSServingCC-Abort
                                            CRITICALITY reject
                                                                    EXTENSION
                                                                                 EnhancedHSServingCC-Abort
                                                                                                                                        PRESENCE
optional}|
{ ID id-UE-SupportIndicatorExtension
                                                                                UE-SupportIndicatorExtension
                                            CRITICALITY ignore
                                                                    EXTENSION
                                                                                                                         PRESENCE optional |
 ID id-power-offset-for-S-CPICH-for-MIMO-Request-Indicator
                                                                CRITICALITY ignore EXTENSION PowerOffsetForSecondaryCPICHforMIMORequestIndicator
           PRESENCE optional |
{ ID id-Single-Stream-MIMO-Mode-Indicator
                                            CRITICALITY reject
                                                                                Single-Stream-MIMO-Mode-Indicator
                                                                                                                         PRESENCE optional },
                                                                    EXTENSION
HSDSCH-MACdFlow-ID ::= INTEGER (0..maxNrOfMACdFlows-1)
HSDSCH-MACdFlow-Specific-InfoList ::= SEQUENCE (SIZE (1..maxNrOfMACdFlows)) OF HSDSCH-MACdFlow-Specific-InfoItem
HSDSCH-MACdPDUSizeFormat ::= ENUMERATED {
    indexedMACdPDU-Size,
    flexibleMACdPDU-Size
HSDSCH-MACdFlow-Specific-InfoItem ::= SEQUENCE
    hSDSCH-MACdFlow-ID
                                        HSDSCH-MACdFlow-ID,
    allocationRetentionPriority
                                        AllocationRetentionPriority,
                                        TrafficClass,
    trafficClass
    bindingID
                                        BindingID
                                                                                 OPTIONAL,
    transportLayerAddress
                                        TransportLayerAddress
                                                                                 OPTIONAL,
    iE-Extensions
                                        ProtocolExtensionContainer { { HSDSCH-MACdFlow-Specific-InfoItem-ExtIEs } }
                                                                                                                                        OPTIONAL,
HSDSCH-MACdFlow-Specific-InfoItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    {ID id-TnlQos
                            CRITICALITY ignore
                                                    EXTENSION TnlQos PRESENCE optional } |
    {ID id-TrCH-SrcStatisticsDescr CRITICALITY ignore EXTENSION TrCH-SrcStatisticsDescr PRESENCE optional },
    . . .
```

```
HSDSCH-MACdFlow-Specific-InfoList-Response ::= SEQUENCE (SIZE (0..maxNrOfMACdFlows)) OF HSDSCH-MACdFlow-Specific-InfoItem-Response
HSDSCH-MACdFlow-Specific-InfoItem-Response ::= SEQUENCE {
   hSDSCH-MACdFlow-ID
                                        HSDSCH-MACdFlow-ID,
   bindingID
                                        BindingID
                                                                                 OPTIONAL.
    transportLayerAddress
                                        TransportLayerAddress
                                                                                 OPTIONAL,
    hSDSCH-Initial-Capacity-Allocation HSDSCH-Initial-Capacity-Allocation
                                                                                 OPTIONAL.
                                        ProtocolExtensionContainer { { HSDSCH-MACdFlow-Specific-InfoItem-Response-ExtIEs } }
    iE-Extensions
    OPTIONAL,
    . . .
HSDSCH-MACdFlow-Specific-InfoItem-Response-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HSDSCH-MACdFlow-Specific-InfoList-to-Modify ::= SEQUENCE (SIZE (1..maxNrOfMACdFlows)) OF HSDSCH-MACdFlow-Specific-InfoItem-to-Modify
HSDSCH-MACdFlow-Specific-InfoItem-to-Modify ::= SEOUENCE {
    hSDSCH-MACdFlow-ID
                                        HSDSCH-MACdFlow-ID,
    allocationRetentionPriority
                                        AllocationRetentionPriority
                                                                                 OPTIONAL,
    transportBearerRequestIndicator
                                        TransportBearerRequestIndicator,
    trafficClass
                                        TrafficClass
                                                                                 OPTIONAL,
    bindingID
                                        BindingID
                                                                                 OPTIONAL,
    transportLayerAddress
                                        TransportLayerAddress
                                                                                 OPTIONAL,
    iE-Extensions
                                        ProtocolExtensionContainer { { HSDSCH-MACdFlow-Specific-InfoItem-to-Modify-ExtIEs } }
    OPTIONAL,
    . . .
HSDSCH-MACdFlow-Specific-InfoItem-to-Modify-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
                            CRITICALITY ignore
                                                     EXTENSION TnlQos PRESENCE optional },
    {ID id-TnlQos
    . . .
HSDSCH-MACdFlows-Information ::= SEOUENCE {
   hSDSCH-MACdFlow-Specific-Info
                                                     HSDSCH-MACdFlow-Specific-InfoList,
    priorityOueue-Info
                                                     PriorityOueue-InfoList,
    iE-Extensions
                                                     ProtocolExtensionContainer { { HSDSCH-MACdFlows-Information-ExtIEs } }
    OPTIONAL,
    . . .
HSDSCH-MACdFlows-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HSDSCH-MACdFlows-to-Delete ::= SEQUENCE (SIZE (1..maxNrOfMACdFlows)) OF HSDSCH-MACdFlows-to-Delete-Item
HSDSCH-MACdFlows-to-Delete-Item ::= SEQUENCE {
   hsDSCH-MACdFlow-ID
                                        HSDSCH-MACdFlow-ID,
    iE-Extensions
                                        ProtocolExtensionContainer { { HSDSCH-MACdFlows-to-Delete-Item-ExtIEs} }
                                                                                                                          OPTIONAL,
    . . .
```

```
HSDSCH-MACdFlows-to-Delete-Item-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HSDSCH-Initial-Capacity-Allocation: = SEOUENCE (SIZE (1..maxNrOfPrioOueues)) OF HSDSCH-Initial-Capacity-AllocationItem
HSDSCH-Initial-Capacity-AllocationItem ::= SEQUENCE {
    schedulingPriorityIndicator
                                    SchedulingPriorityIndicator,
    maximum-MACdPDU-Size
                                   MACdPDU-Size,
   hSDSCH-InitialWindowSize
                                   HSDSCH-InitialWindowSize,
                                    ProtocolExtensionContainer { {HSDSCH-Initial-Capacity-AllocationItem-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
HSDSCH-Initial-Capacity-AllocationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
{ ID id-MaximumMACdPDU-SizeExtended
                                        CRITICALITY ignore
                                                                EXTENSION MAC-PDU-SizeExtended PRESENCE optional },
HSDSCH-InitialWindowSize
                                    ::= INTEGER (1..255)
-- Number of MAC-d PDUs.
HSDSCH-PreconfigurationInfo ::= SEQUENCE {
    setsOfHS-SCCH-Codes
                           SetsOfHS-SCCH-Codes,
    hARO-MemoryPartitioning
                                HARO-MemoryPartitioning,
    eDCH-FDD-DL-ControlChannelInformation
                                                EDCH-FDD-DL-ControlChannelInformation
                                                                                            OPTIONAL,
    hARO-Preamble-Mode-Activation-Indicator
                                                HARO-Preamble-Mode-Activation-Indicator
                                                                                            OPTIONAL,
                           MIMO-InformationResponse
    mIMO-N-M-Ratio
                                                            OPTIONAL,
    continuous-Packet-Connectivity-HS-SCCH-Less-Information-Response
                                                                        Continuous-Packet-Connectivity-HS-SCCH-Less-Information-Response
    OPTIONAL,
                                        ProtocolExtensionContainer { { HSDSCH-PreconfigurationInfo-ExtIEs} }
    iE-Extensions
                                                                                                                        OPTIONAL,
HSDSCH-PreconfigurationInfo-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
{ ID id-power-offset-for-S-CPICH-for-MIMO
                                                            CRITICALITY ignore EXTENSION PowerOffsetForSecondaryCPICHforMIMO
    PRESENCE optional }
{ ID id-Additional-EDCH-Preconfiguration-Information
                                                            CRITICALITY ignore EXTENSION Additional-EDCH-Preconfiguration-Information
    PRESENCE optional }
{ ID id-Support-of-Dynamic-DTXDRX-Related-HS-SCCH-Order
                                                            CRITICALITY ignore EXTENSION Support-of-Dynamic-DTXDRX-Related-HS-SCCH-Order
    PRESENCE optional },
Additional-EDCH-Preconfiguration-Information ::= SEQUENCE (SIZE (1..maxNrOfEDCH-1)) OF Additional-EDCH-Preconfiguration-Information-ItemIEs
Additional-EDCH-Preconfiguration-Information-ItemIEs
                                                       ::= SEOUENCE {
    eDCH-FDD-DL-ControlChannelInformation
                                                EDCH-FDD-DL-ControlChannelInformation,
    iE-Extensions
                                    ProtocolExtensionContainer { { Additional-EDCH-Preconfiguration-Information-ItemIEs-ExtIEs} } OPTIONAL,
```

```
Additional-EDCH-Preconfiguration-Information-ItemIEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HSDSCH-PreconfigurationSetup ::= SEOUENCE {
    mAChsResetScheme
                           MAChsResetScheme,
    hSDSCH-Physical-Layer-Category
                                        INTEGER (1..64,...),
   mAChs-Reordering-Buffer-Size-for-RLC-UM
                                                MAChsReorderingBufferSize-for-RLC-UM,
    secondaryServingCells
                                SecondaryServingCells
                                                                OPTIONAL,
    numPrimaryHS-SCCH-Codes
                                NumHS-SCCH-Codes
                                                            OPTIONAL,
    hARQ-Preamble-Mode
                           HARO-Preamble-Mode
                                                                    OPTIONAL,
    mIMO-ActivationIndicator
                                    MIMO-ActivationIndicator
                                                                        OPTIONAL,
    hSDSCH-MACdPDUSizeFormat
                                    HSDSCH-MACdPDUSizeFormat
                                                                        OPTIONAL,
    sixtyfourOAM-UsageAllowedIndicator
                                            SixtyfourOAM-UsageAllowedIndicator
                                                                                        OPTIONAL,
    uE-with-enhanced-HS-SCCH-support-indicator
                                                                OPTIONAL,
                                                    NULL
    continuous-Packet-Connectivity-HS-SCCH-Less-Information
                                                                    Continuous-Packet-Connectivity-HS-SCCH-Less-Information
                                                                                                                                        OPTIONAL,
                                        ProtocolExtensionContainer { { HSDSCHPreconfigurationSetup-ExtIEs } }
    iE-Extensions
                                                                                                                                OPTIONAL,
    . . .
HSDSCHPreconfigurationSetup-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
 ID id-UE-SupportIndicatorExtension
                                                        CRITICALITY ignore
                                                                                EXTENSION UE-SupportIndicatorExtension
                                                                                                                                PRESENCE optional } |
{ ID id-power-offset-for-S-CPICH-for-MIMO-Request-Indicator
                                                                CRITICALITY ignore EXTENSION PowerOffsetForSecondaryCPICHforMIMORequestIndicator
    PRESENCE optional },
HS-SCCH-PreconfiguredCodes
                                        ::= SEQUENCE (SIZE (1..maxNrOfHSSCCHCodes)) OF HS-SCCH-PreconfiguredCodesItem
HS-SCCH-PreconfiguredCodesItem ::= SEQUENCE {
   hS-SCCH-CodeNumber
                                HS-SCCH-CodeNumber,
                            ProtocolExtensionContainer { { HS-SCCH-PreconfiguredCodesItem-ExtIEs} } OPTIONAL,
   iE-Extensions
HS-SCCH-PreconfiguredCodesItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HS-SCCH-CodeNumber ::= INTEGER (0..127)
HSDSCH-RNTI ::= INTEGER (0..65535)
HS-DSCH-serving-cell-change-information ::= SEQUENCE {
    hS-PDSCH-RLID
                                RL-ID,
   hSDSCH-FDD-Information
                                HSDSCH-FDD-Information
    OPTIONAL,
                                ProtocolExtensionContainer { { HS-DSCH-serving-cell-change-information-ExtIEs} }
    iE-Extensions
                                                                                                                         OPTIONAL,
```

```
HS-DSCH-serving-cell-change-information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
{ ID id-Continuous-Packet-Connectivity-HS-SCCH-Less-Information CRITICALITY reject EXTENSION Continuous-Packet-Connectivity-HS-SCCH-Less-
              PRESENCE optional } |
PRESENCE optional },
HS-DSCH-serving-cell-change-informationResponse ::= SEQUENCE {
   hS-DSCH-serving-cell-choice
                                 HS-DSCH-serving-cell-change-choice,
   iE-Extensions
                                 ProtocolExtensionContainer { { HS-DSCH-serving-cell-change-informationResponse-ExtIEs} } OPTIONAL,
HS-DSCH-serving-cell-change-informationResponse-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HS-DSCH-serving-cell-change-choice ::= CHOICE {
   hS-serving-cell-change-successful
                                        HS-serving-cell-change-successful,
   hS-serving-cell-change-unsuccessful
                                        HS-serving-cell-change-unsuccessful,
HSDSCH-TBSizeTableIndicator ::= ENUMERATED {
   octet-aliqued
HS-serving-cell-change-successful ::= SEQUENCE {
                                    HSDSCH-FDD-Information-Response,
   hSDSCH-FDD-Information-Response
                                    HSDSCH-RNTI,
   hSDSCH-RNTI
   iE-Extensions
                                    ProtocolExtensionContainer { { HS-serving-cell-change-successful-ExtIEs} } OPTIONAL,
HS-serving-cell-change-successful-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
{ ID id-Continuous-Packet-Connectivity-HS-SCCH-Less-Information-Response
                                                                      CRITICALITY ignore EXTENSION Continuous-Packet-Connectivity-HS-SCCH-
Less-Information-Response
                             PRESENCE optional },
HS-serving-cell-change-unsuccessful ::= SEQUENCE {
                                 ProtocolExtensionContainer { { HS-serving-cell-change-unsuccessful-ExtIEs} } OPTIONAL,
   iE-Extensions
HS-serving-cell-change-unsuccessful-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
HSPDSCH-First-Code-Index ::= INTEGER (1..maxHS-PDSCHCodeNrComp-1)
    -- index of first HS-PDSCH code
HSPDSCH-Second-Code-Index ::= INTEGER (1..maxHS-PDSCHCodeNrComp-1)
    -- index of second HS-PDSCH code
HSPDSCH-Second-Code-Support ::= BOOLEAN
    -- true: applied, false: not applied
HSDSCH-TDD-Information ::= SEOUENCE {
    hSDSCH-MACdFlows-Information
                                                HSDSCH-MACdFlows-Information,
    uE-Capabilities-Info
                                                UE-Capabilities-Info.
    mAChs-Reordering-Buffer-Size-for-RLC-UM
                                                MAChsReorderingBufferSize-for-RLC-UM,
    tDD-AckNack-Power-Offset
                                                TDD-AckNack-Power-Offset,
                                                ProtocolExtensionContainer { { HSDSCH-TDD-Information-ExtIEs } }
    iE-Extensions
                                                                                                                                 OPTIONAL,
HSDSCH-TDD-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
{ ID id-HSDSCH-MACdPDUSizeFormat
                                    CRITICALITY reject
                                                            EXTENSION HSDSCH-MACdPDUSizeFormat PRESENCE optional | |
{ ID id-HSSICH-SIRTarget
                                    CRITICALITY ignore
                                                            EXTENSION UL-SIR
    PRESENCE optional } |
-- Applicable to 1.28Mcps TDD only
{ ID id-HSSICH-TPC-StepSize
                                                            EXTENSION TDD-TPC-UplinkStepSize-LCR
                                                                                                                     PRESENCE optional } |
                                    CRITICALITY ignore
-- Mandatory for 1.28Mcps TDD only
{ ID id-tSN-Length
                                    CRITICALITY reject
                                                            EXTENSION TSN-Length
                                                                                                  PRESENCE optional } |
-- Applicable for 1.28Mcps TDD when using multiple frequencies
{ ID id-MIMO-ActivationIndicator
                                                                                                                         PRESENCE optional },
                                    CRITICALITY reject
                                                            EXTENSION MIMO-ActivationIndicator
    . . .
HSDSCH-TDD-Information-Response ::= SEQUENCE {
   hSDSCH-MACdFlow-Specific-InfoList-Response
                                                    HSDSCH-MACdFlow-Specific-InfoList-Response
                                                                                                          OPTIONAL,
   hSSCCH-TDD-Specific-InfoList-Response
                                                    HSSCCH-TDD-Specific-InfoList-Response
                                                                                                          OPTIONAL,
    -- Not Applicable to 1.28Mcps TDD
   hSSCCH-TDD-Specific-InfoList-Response-LCR
                                                    HSSCCH-TDD-Specific-InfoList-Response-LCR
                                                                                                          OPTIONAL,
    -- Not Applicable to 3.84Mcps TDD or 7.68Mcps TDD. This HSSCCH Specific Information is for the first Frequency repetition, HSSCCH Specific
Information for Frequency repetitions 2 and on, should be defined in MultipleFreq-HSPDSCH-InformationList-ResponseTDDLCR
    hSPDSCH-TDD-Specific-InfoList-Response
                                                    HSPDSCH-TDD-Specific-InfoList-Response
                                                                                                          OPTIONAL,
    hSPDSCH-TDD-Specific-InfoList-Response-LCR
                                                    HSPDSCH-TDD-Specific-InfoList-Response-LCR
                                                                                                          OPTIONAL,
                                                    HARQ-MemoryPartitioning
   hARQ-MemoryPartitioning
                                                                                                          OPTIONAL,
    -- For 1.28Mcps TDD, this HARQ Memory Partitioning Information is for the first Frequency repetition, HARQ Memory Partitioning Information for
Frequency repetitions 2 and on, should be defined in MultipleFreq-HSPDSCH-InformationList-ResponseTDDLCR
                                                    ProtocolExtensionContainer { { HSDSCH-TDD-Information-Response-ExtIEs } }
    iE-Extensions
    OPTIONAL,
HSDSCH-TDD-Information-Response-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
{ ID id-User-Plane-Congestion-Fields-Inclusion
                                                                CRITICALITY ignore EXTENSION User-Plane-Congestion-Fields-Inclusion
           PRESENCE optional |
```

```
{ ID id-hSSCCH-TDD-Specific-InfoList-Response768
                                                              CRITICALITY ignore EXTENSION HSSCCH-TDD-Specific-InfoList-Response768
       PRESENCE optional } |
{ ID id-hSPDSCH-TDD-Specific-InfoList-Response768
                                                              CRITICALITY ignore EXTENSION HSPDSCH-TDD-Specific-InfoList-Response768
           PRESENCE optional |
{ ID id-UARFCNforNt
                                                              CRITICALITY ignore EXTENSION UARFON
                                       PRESENCE optional } |
-- Applicable to 1.28Mcps TDD when using multiple frequencies , This is the UARFCN for the first Frequency repetition
{ ID id-multipleFreq-HSPDSCH-InformationList-ResponseTDDLCR
                                                              CRITICALITY ignore EXTENSION MultipleFreq-HSPDSCH-InformationList-ResponseTDDLCR
PRESENCE optional } |
-- Applicable to 1.28Mcps TDD when using multiple frequencies ,This MultipleFreq-HSPDSCH-InformationList-ResponseTDDLCR is the HS-SCCH and HARQ
Memory Partitioning information for the 2<sup>nd</sup> and beyond HS-PDSCH frequencies
{ ID id-multicarrier-number
                                                              CRITICALITY ignore EXTENSION Multicarrier-Number
                           PRESENCE optional }
-- Applicable for 1.28Mcps TDD when using multiple frequencies
{ID id-MIMO-SFMode-For-HSPDSCHDualStream
                                                  CRITICALITY reject
                                                                          EXTENSION MIMO-SFMode-For-HSPDSCHDualStream
           PRESENCE optional } |
{ID id-MIMO-ReferenceSignal-InformationListLCR
                                                  CRITICALITY reject EXTENSION MIMO-ReferenceSignal-InformationListLCR
                                                                                                                                    PRESENCE
optional}
 ID id-TSO-HS-PDSCH-Indication-LCR CRITICALITY ignore
                                                          EXTENSION TS0-HS-PDSCH-Indication-LCR
                                                                                                              PRESENCE optional }
{ ID id-Out-of-Sychronization-Window
                                                      CRITICALITY reject
                                                                              EXTENSION Out-of-Sychronization-Window
   PRESENCE optional },
Multicarrier-Number ::= INTEGER (1..maxHSDPAFrequency)
HSPDSCH-TDD-Specific-InfoList-Response ::= SEOUENCE (SIZE (0..maxNrOfDLTs)) OF HSPDSCH-TDD-Specific-InfoItem-Response
HSPDSCH-TDD-Specific-InfoItem-Response ::= SEQUENCE {
    timeslot
                                                  TimeSlot,
   midambleShiftAndBurstType
                                                  MidambleShiftAndBurstType,
                                                  ProtocolExtensionContainer { { HSPDSCH-TDD-Specific-InfoItem-Response-ExtIEs } }
   iE-Extensions
   OPTIONAL,
HSPDSCH-TDD-Specific-InfoItem-Response-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HSPDSCH-TDD-Specific-InfoList-Response-LCR ::= SEQUENCE (SIZE (1.. maxNrOfDLTsLCR)) OF HSPDSCH-TDD-Specific-InfoItem-Response-LCR
HSPDSCH-TDD-Specific-InfoItem-Response-LCR ::= SEQUENCE {
   timeslotLCR
                                              TimeSlotLCR,
   midambleShiftLCR
                                              MidambleShiftLCR,
   iE-Extensions
                                              OPTIONAL,
HSPDSCH-TDD-Specific-InfoItem-Response-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
HSPDSCH-TDD-Specific-InfoList-Response768 ::= SEQUENCE (SIZE (0..maxNrOfDLTs)) OF HSPDSCH-TDD-Specific-InfoItem-Response768
HSPDSCH-TDD-Specific-InfoItem-Response768 ::= SEOUENCE {
    timeslot
                                                     TimeSlot,
   midambleShiftAndBurstType768
                                                     MidambleShiftAndBurstType768,
                                                     ProtocolExtensionContainer { { HSPDSCH-TDD-Specific-InfoItem-Response-768-ExtIEs } }
   iE-Extensions
       OPTIONAL.
    . . .
HSPDSCH-TDD-Specific-InfoItem-Response-768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HSSCCH-FDD-Specific-InfoList-Response ::= SEQUENCE (SIZE (0..maxNrOfHSSCCHCodes)) OF HSSCCH-FDD-Specific-InfoItem-Response
HSSCCH-FDD-Specific-InfoItem-Response ::= SEQUENCE {
    code-Number
                                                     INTEGER (0..127),
                                                     ProtocolExtensionContainer { { HSSCCH-FDD-Specific-InfoItem-Response-ExtIEs } }
    iE-Extensions
    OPTIONAL,
    . . .
HSSCCH-FDD-Specific-Infoltem-Response-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
HSSCCH-PowerOffset ::= INTEGER (0..255)
-- PowerOffset = -32 + offset * 0.25
-- Unit dB, Range -32dB .. +31.75dB, Step +0.25dB
HSSCCH-TDD-Specific-InfoList-Response ::= SEQUENCE (SIZE (0..maxNrOfHSSCCHCodes)) OF HSSCCH-TDD-Specific-InfoItem-Response
HSSCCH-TDD-Specific-InfoItem-Response ::= SEQUENCE {
    timeslot
                                                     TimeSlot,
   midambleShiftAndBurstType
                                                    MidambleShiftAndBurstType,
    tDD-ChannelisationCode
                                                    TDD-ChannelisationCode,
   hSSICH-Info
                                                     HSSICH-Info,
                                                     ProtocolExtensionContainer { { HSSCCH-TDD-Specific-InfoItem-Response-ExtIEs } }
    iE-Extensions
    OPTIONAL,
    . . .
HSSCCH-TDD-Specific-InfoItem-Response-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
HSSCCH-TDD-Specific-InfoList-Response-LCR ::= SEQUENCE (SIZE (0..maxNrOfHSSCCHCodes)) OF HSSCCH-TDD-Specific-InfoItem-Response-LCR
HSSCCH-TDD-Specific-InfoItem-Response-LCR ::= SEQUENCE {
    timeslotLCR
                                                TimeSlotLCR,
   midambleShiftLCR
                                                MidambleShiftLCR,
    first-TDD-ChannelisationCode
                                                TDD-ChannelisationCode,
    second-TDD-ChannelisationCode
                                            TDD-ChannelisationCode,
```

```
hSSICH-InfoLCR
                                                 HSSICH-InfoLCR,
    iE-Extensions
                                                 ProtocolExtensionContainer { { HSSCCH-TDD-Specific-InfoItem-Response-LCR-ExtIEs } }
    OPTIONAL,
HSSCCH-TDD-Specific-Infoltem-Response-LCR-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
HSSCCH-TDD-Specific-InfoList-Response768 ::= SEQUENCE (SIZE (0..maxNrOfHSSCCHCodes)) OF HSSCCH-TDD-Specific-InfoItem-Response768
HSSCCH-TDD-Specific-InfoItem-Response768 ::= SEQUENCE {
    timeslot
                                                     TimeSlot,
    midambleShiftAndBurstType768
                                                     MidambleShiftAndBurstType768,
    tDD-ChannelisationCode768
                                                     TDD-ChannelisationCode768,
    hSSICH-Info768
                                                     HSSICH-Info768,
                                                     ProtocolExtensionContainer { { HSSCCH-TDD-Specific-InfoItem-Response768-ExtIEs } }
    iE-Extensions
    OPTIONAL,
HSSCCH-TDD-Specific-InfoItem-Response768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
HSSICH-Info ::= SEQUENCE {
    hsSICH-ID
                                                     HS-SICH-ID,
    timeslot
                                                     TimeSlot,
    midambleShiftAndBurstType
                                                     MidambleShiftAndBurstType,
    tDD-ChannelisationCode
                                                     TDD-ChannelisationCode,
    iE-Extensions
                                                     ProtocolExtensionContainer { { HSSICH-Info-ExtIEs } }
                                                                                                                                  OPTIONAL,
    . . .
HSSICH-Info-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HSSICH-InfoLCR ::= SEQUENCE {
    hsSICH-ID
                                                     HS-SICH-ID,
    timeslotLCR
                                                     TimeSlotLCR,
    midambleShiftLCR
                                                     MidambleShiftLCR,
    tDD-ChannelisationCode
                                                 TDD-ChannelisationCode,
    iE-Extensions
                                                     ProtocolExtensionContainer { { HSSICH-Info-LCR-ExtIEs } }
                                                                                                                                  OPTIONAL,
HSSICH-Info-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-HS-SICH-ID-Extension
                                            CRITICALITY ignore
                                                                     EXTENSION HS-SICH-ID-Extension
                                                                                                           PRESENCE optional },
    -- Applicable for 1.28Mcps TDD only when the HS-SICH ID IE is more than 31
    . . .
```

OPTIONAL,

```
HSSICH-Info768 ::= SEQUENCE {
   hsSICH-ID
                                                    HS-SICH-ID,
    timeslot
                                                    TimeSlot.
    midambleShiftAndBurstType768
                                                    MidambleShiftAndBurstType768,
    tDD-ChannelisationCode768
                                                    TDD-ChannelisationCode768,
    iE-Extensions
                                                    ProtocolExtensionContainer { { HSSICH-Info-768-ExtIEs } }
    . . .
HSSICH-Info-768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HS-SICH-Reception-Quality-Value ::= SEQUENCE
    failed-HS-SICH
                               HS-SICH-failed,
    missed-HS-SICH
                                HS-SICH-missed,
    total-HS-SICH
                                HS-SICH-total,
                                ProtocolExtensionContainer { { HS-SICH-Reception-Quality-Value-ExtIEs} } OPTIONAL,
    iE-Extensions
HS-SICH-Reception-Quality-Value-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HS-SICH-failed ::= INTEGER (0..20)
HS-SICH-missed ::= INTEGER (0..20)
HS-SICH-total ::= INTEGER (0..20)
HS-SICH-Reception-Quality-Measurement-Value ::= INTEGER (0..20)
-- According to mapping in TS 25.133 [23]
HS-SICH-ID ::= INTEGER (0..31)
HS-SICH-ID-Extension ::= INTEGER (32..255,...)
HSSCCH-CodeChangeIndicator ::= ENUMERATED {
    hsSCCHCodeChangeNeeded
HSSCCH-Code-Change-Grant
                           ::= ENUMERATED {
    changeGranted
HS-PDSCH-Code-Change-Indicator ::= ENUMERATED {
    hsPDSCHCodeChangeNeeded
HS-PDSCH-Code-Change-Grant ::= ENUMERATED {
    changeGranted
```

```
HSDSCH-FDD-Update-Information ::= SEQUENCE {
    hsSCCHCodeChangeIndicator
                                                     HSSCCH-CodeChangeIndicator
                                                                                                 OPTIONAL,
    cgiFeedback-CycleK
                                                     COI-Feedback-Cvcle
                                                                                                 OPTIONAL.
    cgiRepetitionFactor
                                                     COI-RepetitionFactor
                                                                                                 OPTIONAL,
    ackNackRepetitionFactor
                                                     AckNack-RepetitionFactor
                                                                                                 OPTIONAL,
    cqiPowerOffset
                                                     COI-Power-Offset
                                                                                                 OPTIONAL,
    ackPowerOffset
                                                     Ack-Power-Offset
                                                                                                 OPTIONAL,
    nackPowerOffset
                                                     Nack-Power-Offset
                                                                                                 OPTIONAL,
    iE-Extensions
                                                     ProtocolExtensionContainer { { HSDSCH-FDD-Update-Information-ExtIEs } }
                                                                                                                                         OPTIONAL,
HSDSCH-FDD-Update-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
{ID id-HS-PDSCH-Code-Change-Indicator
                                            CRITICALITY ignore
                                                                     EXTENSION HS-PDSCH-Code-Change-Indicator
                                                                                                                      PRESENCE optional }.
HSDSCH-TDD-Update-Information ::= SEQUENCE {
    hsSCCHCodeChangeIndicator
                                                     HSSCCH-CodeChangeIndicator
                                                                                                 OPTIONAL,
    tDDAckNackPowerOffset
                                                     TDD-AckNack-Power-Offset
                                                                                                 OPTIONAL,
    iE-Extensions
                                                     ProtocolExtensionContainer { { HSDSCH-TDD-Update-Information-ExtIEs } }
                                                                                                                                         OPTIONAL,
    . . .
HSDSCH-TDD-Update-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MIMO-ReferenceSignal-InformationListLCR ::= SEOUENCE (SIZE (1..maxNrOfHSSCCHCodes)) OF HSSICH-ReferenceSignal-InformationLCR
HSSICH-ReferenceSignal-InformationLCR ::= SEQUENCE {
    midambleConfigurationLCR
                                    MidambleConfigurationLCR,
    midambleShift
                                    INTEGER (0..15),
    timeSlotLCR
                                    TimeSlotLCR,
    iE-Extensions
                                    ProtocolExtensionContainer { { HSSICH-ReferenceSignal-InformationLCR-ExtIEs } }
                                                                                                                                  OPTIONAL,
HSSICH-ReferenceSignal-InformationLCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HS-DSCH-Semi-PersistentScheduling-Information-LCR ::= SEQUENCE {
    transport-Block-Size-List
                                            Transport-Block-Size-List-LCR,
    repetition-Period-List-LCR
                                            Repetition-Period-List-LCR,
    hS-DSCH-SPS-Reservation-Indicator
                                            SPS-Reservation-Indicator
                                                                                     OPTIONAL,
   hS-DSCH-SPS-Operation-Indicator
                                            HS-DSCH-SPS-Operation-Indicator,
    iE-Extensions
                                            ProtocolExtensionContainer { { HS-DSCH-Semi-PersistentScheduling-Information-LCR-ExtIEs } }
        OPTIONAL,
    . . .
HS-DSCH-Semi-PersistentScheduling-Information-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
```

```
HSDSCH-Physical-Layer-Category ::= INTEGER (1..64)
Transport-Block-Size-List-LCR ::= SEOUENCE (SIZE (1..maxNoOfTBSs-Mapping-HS-DSCH-SPS)) OF Transport-Block-Size-Item-LCR
Transport-Block-Size-Item-LCR ::= SEQUENCE {
    transport-Block-Size-maping-Index-LCR
                                              Transport-Block-Size-maping-Index-LCR,
   transport-Block-Size-Index-LCR
                                              Transport-Block-Size-Index-LCR,
                                              ProtocolExtensionContainer { { Transport-Block-Size-Item-LCR-ExtIEs } }
   iE-Extensions
                                                                                                                                  OPTIONAL,
Transport-Block-Size-Item-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Transport-Block-Size-maping-Index-LCR ::= INTEGER (0..maxNoOfTBSs-Mapping-HS-DSCH-SPS-1)
Transport-Block-Size-Index-LCR ::= INTEGER (1..maxNoOfHS-DSCH-TBSsLCR)
TSO-HS-PDSCH-Indication-LCR ::= NULL
Repetition-Period-List-LCR ::= SEQUENCE (SIZE (1..maxNoOfRepetition-Period-LCR)) OF Repetition-Period-Item-LCR
Repetition-Period-Item-LCR ::= SEQUENCE {
   repetitionPeriodIndex
                              RepetitionPeriodIndex,
   repetitionPeriod
                              RepetitionPeriod,
   repetitionLength
                              RepetitionLength
                                                             OPTIONAL,
                              iE-Extensions
                                                                                                                    OPTIONAL,
    . . .
Repetition-Period-Item-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RepetitionPeriodIndex ::= INTEGER (0..maxNoOfRepetitionPeriod-SPS-LCR-1)
SPS-Reservation-Indicator ::= ENUMERATED {
   reserve
HS-DSCH-SPS-Operation-Indicator ::= CHOICE {
   logicalChannellevel
                              LogicalChannellevel,
   priorityQueuelevel
                              PriorityQueuelevel,
   . . .
LogicalChannellevel ::= BIT STRING (SIZE (16))
PriorityQueuelevel ::= BIT STRING (SIZE (8))
HS-DSCH-Semi-PersistentScheduling-Information-to-Modify-LCR ::= SEQUENCE {
```

```
transport-Block-Size-List
                                          Transport-Block-Size-List-LCR
                                                                                    OPTIONAL.
   repetition-Period-List-LCR
                                          Repetition-Period-List-LCR
                                                                                OPTIONAL,
   hS-DSCH-SPS-Reservation-Indicator
                                          SPS-Reservation-Indicator
                                                                                 OPTIONAL.
   hS-DSCH-SPS-Operation-Indicator
                                          HS-DSCH-SPS-Operation-Indicator
                                                                                OPTIONAL,
   iE-Extensions
                                          ProtocolExtensionContainer { { HS-DSCH-Semi-PersistentScheduling-Information-to-Modify-LCR-ExtIEs } }
                          OPTIONAL,
HS-DSCH-Semi-PersistentScheduling-Information-to-Modify-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HS-DSCH-Semi-PersistentScheduling-Information-ResponseLCR ::= SEQUENCE {
   hS-SICH-InformationList-for-HS-DSCH-SPS
                                              HS-SICH-InformationList-for-HS-DSCH-SPS,
   initial-HS-PDSCH-SPS-Resource
                                              Initial-HS-PDSCH-SPS-Resource
                                                                                    OPTIONAL,
   buffer-Size-for-HS-DSCH-SPS
                                              Process-Memory-Size
                                                                                    OPTIONAL,
   number-of-Processes-for-HS-DSCH-SPS
                                              Number-of-Processes-for-HS-DSCH-SPS
                                                                                    OPTIONAL,
   iE-Extensions
                                              OPTIONAL,
HS-DSCH-Semi-PersistentScheduling-Information-ResponseLCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HS-SICH-InformationList-for-HS-DSCH-SPS ::= SEQUENCE (SIZE (1..maxNoOf-HS-SICH-SPS)) OF HS-SICH-InformationItem-for-HS-DSCH-SPS
HS-SICH-InformationItem-for-HS-DSCH-SPS ::= SEQUENCE {
   hS-SICH-Mapping-Index
                                  HS-SICH-Mapping-Index
                                                                 OPTIONAL,
   hS-SICH-Type
                                  HS-SICH-Type,
                                  ProtocolExtensionContainer { { HS-SICH-InformationItem-for-HS-DSCH-SPS-ExtIEs } }
   iE-Extensions
                                                                                                                                 OPTIONAL,
    . . .
HS-SICH-InformationItem-for-HS-DSCH-SPS-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HS-SICH-Mapping-Index ::= INTEGER (0..maxNoOf-HS-SICH-SPS-1)
HS-SICH-Type ::= CHOICE {
   hS-SCCH-Associated-HS-SICH
                                      HS-SCCH-Associated-HS-SICH,
   non-HS-SCCH-Associated-HS-SICH
                                      Non-HS-SCCH-Associated-HS-SICH,
    . . .
HS-SCCH-Associated-HS-SICH ::= SEQUENCE {
   hsSICH-ID
                                      HS-SICH-ID,
   extended-HS-SICH-ID
                                      HS-SICH-ID-Extension
                                                                     OPTIONAL,
```

```
Non-HS-SCCH-Associated-HS-SICH::= SEQUENCE {
    non-HS-SCCH-Aassociated-HS-SICH-ID Non-HS-SCCH-Aassociated-HS-SICH-ID,
Non-HS-SCCH-Aassociated-HS-SICH-ID ::= INTEGER (0..255)
Initial-HS-PDSCH-SPS-Resource::= SEQUENCE {
                                                RepetitionPeriodIndex,
    repetitionPeriodIndex
    repetitionLength
                                                RepetitionLength
                                                                             OPTIONAL,
   hS-PDSCH-Offset
                                                TDD-PhysicalChannelOffset,
    hS-PDSCH-Midamble-Configuation
                                                MidambleShiftLCR,
    timeslot-Resource-Related-Information
                                                HS-DSCH-TimeslotResourceLCR,
    start.Code
                                                TDD-ChannelisationCode,
    endCode
                                                TDD-ChannelisationCode,
    transport-Block-Size-Index
                                                Transport-Block-Size-Index-LCR,
    modulationType
                                                ModulationSPS-LCR,
                                                HS-SICH-Mapping-Index,
    hS-SICH-Mapping-Index
    iE-Extensions
                                                ProtocolExtensionContainer { { Initial-HS-PDSCH-SPS-Resource-ExtIEs } }
                                                                                                                                         OPTIONAL,
Initial-HS-PDSCH-SPS-Resource-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
HS-DSCH-TimeslotResourceLCR ::= BIT STRING (SIZE (5))
ModulationSPS-LCR ::= ENUMERATED {
    qPSK,
    sixteenQAM,
Number-of-Processes-for-HS-DSCH-SPS ::= INTEGER (1..16)
-- I
IMEI
            ::= OCTET STRING (SIZE(8))
IMEISV
            ::= OCTET STRING (SIZE(8))
IMSI
            ::= OCTET STRING (SIZE(3..8))
Inactivity-Threshold-for-UE-DTX-Cycle2 ::= ENUMERATED {v1, v4, v8, v16, v32, v64, v128, v256}
-- Unit E-DCH TTI
Inactivity-Threshold-for-UE-DRX-Cycle ::= ENUMERATED {v0, v1, v2, v4, v8, v16, v32, v64, v128, v256, v512}
-- Unit subframe
Inactivity-Threshold-for-UE-Grant-Monitoring ::= ENUMERATED {v0, v1, v2, v4, v8, v16, v32, v64, v128, v256}
-- Unit E-DCH TTI
```

```
InformationAvailable::= SEQUENCE {
    requestedDataValue
                            RequestedDataValue,
    iE-Extensions
                            ProtocolExtensionContainer { { InformationAvailable-ExtIEs} }
                                                                                                 OPTIONAL,
    . . .
InformationAvailable-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
InformationExchangeID ::= INTEGER (0..1048575)
InformationNotAvailable ::= NULL
InformationReportCharacteristics ::= CHOICE {
    onDemand
                            PeriodicInformation,
    periodic
    onModification
                           OnModificationInformation,
InformationReportPeriodicity ::= CHOICE {
    min
                    INTEGER (1..60,...),
-- Unit min, Step 1min
                    INTEGER (1..24,...),
    hour
-- Unit hour, Step 1hour
InformationThreshold ::= CHOICE {
    dGPSThreshold
                        DGPSThreshold,
    . . . .
    dGANSSThreshold
                       DGANSSThreshold
InformationType ::= SEQUENCE {
    informationTypeItem
                            ENUMERATED {
        gA-AccessPointPositionwithAltitude,
        gA-AccessPointPosition,
        iPDLParameters,
        qPSInformation,
        dGPSCorrections,
        gPS-RX-POS,
        sFNSFN-GA-AccessPointPosition,
        cell-Capacity-Class,
        nACC-Related-Data,
        mBMSBearerServiceFullAddress,
        interFrequencyCellInformation,
        gANSSInformation,
```

```
dGANSSCorrections,
       qANSS-RX-Pos,
       mBMS-Counting-Information.
       mBMS-Transmission-Mode,
       mBMS-Neighbouring-Cell-Information,
       mBMS-RLC-Sequence-Number,
       aNR-Cell-Information
   gPSInformation
                             GPSInformation
                                                   OPTIONAL.
                             ProtocolExtensionContainer { { InformationType-ExtIEs} }
   iE-Extensions
                                                                                         OPTIONAL.
-- The GPS Information IE shall be present if the Information Exchange Type IE indicates 'GPS Information'
-- For information exchange on the Iur-q interface, only the Cell Capacity Class is used.
InformationType-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
-- The following IE shall be present if the Information Type Item IE indicates 'GANSS Information'
   { ID id-GANSS-Information
                                    CRITICALITY ignore EXTENSION GANSS-Information
                                                                                         PRESENCE conditional }
-- The following IE shall be present if the Information Type Item IE indicates 'DGANSS Corrections'
   { ID id-DGANSS-Corrections-Req
                                 CRITICALITY ignore EXTENSION DGANSS-Corrections-Req
                                                                                        PRESENCE conditional } |
-- The following IE shall be present if the Information Type Item IE indicates 'MBMS RLC Sequence Number'
   { ID id-MBMS-RLC-Sequence-Number-Information
                                                 CRITICALITY ignore EXTENSION MBMS-RLC-Sequence-Number-Information
                                                                                                                      PRESENCE conditional
},
Initial-DL-DPCH-TimingAdjustment-Allowed ::= ENUMERATED {
   initial-DL-DPCH-TimingAdjustment-Allowed
InnerLoopDLPCStatus
                     ::= ENUMERATED {active, inactive}
IPDLParameters ::= CHOICE {
   iPDL-FDD-Parameters
                             IPDL-FDD-Parameters,
   iPDL-TDD-Parameters
                             IPDL-TDD-Parameters,
                                                   --3.84Mcps TDD and 7.68Mcps TDD only
   extension-IPDLParameters
                             Extension-IPDLParameters
                        ::= ProtocolIE-Single-Container {{ Extension-IPDLParametersIE }}
Extension-IPDLParameters
Extension-IPDLParametersIE RNSAP-PROTOCOL-IES ::= {
   . . .
Inter-Frequency-Cell-List ::= SEQUENCE (SIZE (0..maxCellsMeas)) OF Inter-Frequency-Cell
Inter-Frequency-Cell ::= SEQUENCE {
   dL-UARFCN
                             UARFCN,
   uL-UARFCN
                             UARFCN
                                        OPTIONAL,
   primaryScramblingCode
                             PrimaryScramblingCode,
   iE-Extensions
                             OPTIONAL,
```

```
Inter-Frequency-Cell-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Inter-Frequency-Cell-Information ::= SEOUENCE {
   inter-Frequency-Cell-Information-SIB11
                                              Inter-Frequency-Cell-Information-SIB11,
                                              Inter-Frequency-Cell-Information-SIB12,
   inter-Frequency-Cell-Information-SIB12
                              ProtocolExtensionContainer { {Inter-Frequency-Cell-Information-ExtIEs } }
   iE-Extensions
                                                                                                             OPTIONAL,
    . . .
Inter-Frequency-Cell-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Inter-Frequency-Cell-Information-SIB11 ::= SEOUENCE (SIZE (0..2)) OF Inter-Frequency-Cells-Information-SIB11-Per-Indication
Inter-Frequency-Cell-Information-SIB12 ::= SEQUENCE (SIZE (0..2)) OF Inter-Frequency-Cells-Information-SIB12-Per-Indication
Inter-Frequency-Cells-Information-SIB11-Per-Indication ::= SEQUENCE {
   inter-Frequency-Cell-Indication-SIB11 Inter-Frequency-Cell-Indication,
   inter-Frequency-Cell-List-SIB11
                                    Inter-Frequency-Cell-SIB11-or-SIB12-List,
   iE-Extensions
                              ProtocolExtensionContainer { { Inter-Frequency-Cells-Information-SIB11-Per-Indication-ExtIEs } }
                                                                                                                                   OPTIONAL.
   . . .
Inter-Frequency-Cells-Information-SIB11-Per-Indication-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Inter-Frequency-Cells-Information-SIB12-Per-Indication ::= SEQUENCE {
   inter-Frequency-Cell-Indication-SIB12 Inter-Frequency-Cell-Indication,
   inter-Frequency-Cell-List-SIB12
                                      Inter-Frequency-Cell-SIB11-or-SIB12-List,
                              ProtocolExtensionContainer { { Inter-Frequency-Cells-Information-SIB12-Per-Indication-ExtIEs } }
   iE-Extensions
                                                                                                                                   OPTIONAL,
Inter-Frequency-Cells-Information-SIB12-Per-Indication-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
Inter-Frequency-Cell-Indication ::= INTEGER (0..1)
Inter-Frequency-Cell-SIB11-or-SIB12-List ::= SEQUENCE (SIZE (0..maxCellSIB11OrSIB12)) OF Inter-Frequency-Cell-SIB11-or-SIB12
Inter-Frequency-Cell-SIB11-or-SIB12 ::= SEQUENCE {
   interFrequencyCellID
                              InterFrequencyCellID,
   dL-UARFCN
                              UARFCN,
   uL-UARFCN
                               UARFCN
                                          OPTIONAL,
   primaryScramblingCode
                               PrimaryScramblingCode,
   iE-Extensions
                               OPTIONAL,
```

```
InterFrequencyCellID ::= INTEGER (0..31)
IPDL-FDD-Parameters ::= SEQUENCE {
   iPSpacingFDD
                                IPSpacingFDD,
   iPLength
                                IPLength,
   iPOffset
                                IPOffset,
                                Seed,
    seed
   burstModeParameters
                                BurstModeParameters
                                                        OPTIONAL,
   iE-Extensions
                                ProtocolExtensionContainer { { IPDL-FDD-Parameters-ExtIEs} }
                                                                                                  OPTIONAL,
    . . .
IPDL-FDD-Parameters-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
IPDL-TDD-Parameters ::= SEQUENCE {
   iPSpacingTDD
                                IPSpacingTDD,
   iPStart
                                IPStart,
   iPSlot
                                IPSlot,
                                IP-P-CCPCH,
   iP-P-CCPCH
   burstModeParameters
                                BurstModeParameters
                                                        OPTIONAL,
    iE-Extensions
                                ProtocolExtensionContainer { { IPDL-TDD-Parameters-ExtIEs} }
                                                                                                  OPTIONAL,
-- The BurstModeParameters IE shall be included if the Idle Periods are arranged in Burst Mode.
IPDL-TDD-Parameters-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
IPDL-TDD-ParametersLCR ::= SEQUENCE {
    iPSpacingTDD
                                IPSpacingTDD,
   iPStart
                                IPStart,
   iPSub
                                IPSub,
   burstModeParameters
                                BurstModeParameters
                                                        OPTIONAL,
                                ProtocolExtensionContainer { { IPDL-TDD-ParametersLCR-ExtIEs} } OPTIONAL,
   iE-Extensions
-- The BurstModeParameters IE shall be included if the Idle Periods are arranged in Burst Mode.
IPDL-TDD-ParametersLCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
IPLength ::= ENUMERATED {
    ipl5,
    ipl10,
```

```
IPMulticastAddress ::= OCTET STRING (SIZE (4..16))
IPOffset ::= INTEGER (0..9)
IP-P-CCPCH ::= ENUMERATED {
    switchOff-1-Frame,
    switchOff-2-Frames
IPSlot ::= INTEGER (0..14)
IPSpacingFDD ::= ENUMERATED {
   ipsF5,
    ipsF7,
    ipsF10,
    ipsF15,
    ipsF20,
    ipsF30,
    ipsF40,
   ipsF50,
    . . .
IPSpacingTDD ::= ENUMERATED {
   ipsT30,
   ipsT40,
   ipsT50,
    ipsT70,
    ipsT100,
    . . .
IPStart ::= INTEGER (0..4095)
IPSub ::= ENUMERATED {
   first,
    second,
    both
IdleIntervalInformation ::= SEQUENCE {
    idleIntervalInfo-k
                                                 INTEGER(2..3),
    idleIntervalInfo-offset
                                                 INTEGER(0..7),
-- J
-- K
-- L
LABased ::= SEQUENCE {
```

```
laiList
                       LAI-List,
    iE-Extensions
                       ProtocolExtensionContainer { {LABased-ExtIEs} } OPTIONAL,
LABased-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
           ::= SEQUENCE (SIZE (1..maxNrOfLAIs)) OF
LAI-List
   LAI
LAC
                    ::= OCTET STRING (SIZE (2)) -- (EXCEPT ('0000'H 'FFFE'H))
LAI
                SEQUENCE {
        ::=
       pLMN-Identity
                            PLMN-Identity,
       1AC
                           ProtocolExtensionContainer { {LAI-ExtIEs} } OPTIONAL,
       iE-Extensions
LimitedPowerIncrease ::= ENUMERATED {
    used,
    not-used
List-Of-PLMNs ::= SEQUENCE (SIZE (1..maxNrOfBroadcastPLMNs)) OF PLMN-Identity
L3-Information
                          ::= BIT STRING
Load-Value-IncrDecrThres ::= INTEGER(0..100)
Load-Value ::= INTEGER(0..100)
LoadValue ::= SEQUENCE {
       uplinkLoadValue
                            INTEGER(0..100),
       downlinkLoadValue INTEGER(0..100)
LCRTDD-Uplink-Physical-Channel-Capability ::= SEQUENCE {
    maxTimeslotsPerSubFrame
                                       INTEGER(1..6),
                                        ENUMERATED{ts1, ts2, ts3, ts4,...},
    maxPhysChPerTimeslot
    iE-Extensions
                                       ProtocolExtensionContainer { { LCRTDD-Uplink-Physical-Channel-Capability-ExtIEs} } OPTIONAL,
LCRTDD-Uplink-Physical-Channel-Capability-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
-- M
           ::= CHOICE {
MlReport
```

```
periodic
                        MDT-Report-Parameters,
    event1F
                        Event1F-Parameters,
    . . .
M2Report ::= CHOICE {
    periodic
                        MDT-Report-Parameters,
    event1I
                        Event1I-Parameters,
MDT-Activation
                    ::= ENUMERATED {
                                     mdt-only,
                                     mdt-and-trace,
                                     ...}
MDTAreaScope
                    ::= CHOICE {
    cellbased
                        CellBased,
    labased
                        LABased,
    rabased
                        RABased,
    plmn-area-based
                        NULL,
MDT-Configuration ::= SEQUENCE {
       mdtActivation
                                        MDT-Activation,
        mdtAreaScope
                                        MDTAreaScope,
       m1report
                                        M1Report
                                                         OPTIONAL,
       m2report
                                        M2Report
                                                         OPTIONAL,
        m3report
                                        NULL
                                                         OPTIONAL,
                            ProtocolExtensionContainer { { MDT-Configuration-ExtIEs} } OPTIONAL,
        iE-Extensions
        . . .
MDT-Configuration-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MDT-Report-Parameters
                       ::= SEOUENCE {
    reportInterval
                            ReportInterval,
    reportAmount
                            ReportAmount,
    . . .
MeasurementQuantity
                        ::= ENUMERATED {
        cpichEcNo,
        cpichRSCP,
       pathloss,
                            ::= INTEGER (1..6)
MaxNrOfUL-DPCHs
MAC-c-sh-SDU-Length
                            ::= INTEGER (1..5000)
```

993

```
MAC-c-sh-SDU-LengthList ::= SEQUENCE(SIZE(1..maxNrOfMACcshSDU-Length)) OF MAC-c-sh-SDU-Length
MAC-DTX-Cycle-2ms ::= ENUMERATED \{v1, v4, v5, v8, v10, v16, v20\}
MAC-DTX-Cycle-10ms ::= ENUMERATED {v5, v10, v20}
MAC-ehs-Reset-Timer ::= ENUMERATED {v1, v2, v3, v4,...}
MAC-Inactivity-Threshold ::= ENUMERATED {v1, v2, v4, v8, v16, v32, v64, v128, v256, v512, infinity}
   -- Unit subframe
MACdPDU-Size ::= INTEGER (1..5000,...)
   -- In case of E-DCH value 8 and values not multiple of 8 shall not be used
MAC-PDU-SizeExtended ::= INTEGER (1..1504,...,1505)
   -- In case of E-DCH value 1 shall not be used
MACdPDU-Size-IndexList ::= SEOUENCE (SIZE (1..maxNrOfPDUIndexes)) OF MACdPDU-Size-IndexItem
MACdPDU-Size-IndexItem ::= SEQUENCE {
   sTD
                                      SID,
                                      MACdPDU-Size,
   mACdPDU-Size
                                      ProtocolExtensionContainer { { MACdPDU-Size-IndexItem-ExtIEs } }
   iE-Extensions
                                                                                                                   OPTIONAL,
MACdPDU-Size-IndexItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MACdPDU-Size-IndexList-to-Modify ::= SEOUENCE (SIZE (1..maxNrOfPDUIndexes)) OF MACdPDU-Size-IndexItem-to-Modify
MACdPDU-Size-IndexItem-to-Modify ::= SEQUENCE {
   mACdPDU-Size
                                      MACdPDU-Size,
   iE-Extensions
                                      OPTIONAL,
MACdPDU-Size-IndexItem-to-Modify-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MACes-Guaranteed-Bitrate ::= INTEGER (0..16777215,...,16777216...256000000)
MACes-Maximum-Bitrate-LCR ::= INTEGER (0..256000000,...)
MACeReset-Indicator ::= ENUMERATED {mACeReset}
MAChsGuaranteedBitRate ::= INTEGER (0..16777215,...,16777216..256000000)
MAChsReorderingBufferSize-for-RLC-UM ::= INTEGER (0..300,...)
-- Unit kBytes
```

```
::= ENUMERATED {v4, v6, v8, v12, v16, v24, v32,..., v64, v128}
MAC-hsWindowSize
MAChsResetScheme ::= ENUMERATED {
    always,
    interNodeB-change
MaximumAllowedULTxPower
                          ::= INTEGER (-50..33)
Max-Bits-MACe-PDU-non-scheduled ::= INTEGER(1..maxNrOfBits-MACe-PDU-non-scheduled)
MaxNrDLPhysicalchannels
                         ::= INTEGER (1..224)
-- 1.28Mcps TDD 97 - 224 are unused
MaxNrDLPhysicalchannels768 ::= INTEGER (1..448)
MaxNrDLPhysicalchannelsTS ::= INTEGER (1..16)
MaxNrDLPhysicalchannelsTS768
                              ::= INTEGER (1..32)
MaxNr-Retransmissions-EDCH ::= INTEGER (0..15)
MaxNrTimeslots
                           ::= INTEGER (1..14)
-- 1.28Mcps values 7-14 are unused
MaxNrULPhysicalchannels
                          ::= INTEGER (1..2)
Max-Set-E-DPDCHs ::= ENUMERATED {
    vN256, vN128, vN64, vN32, vN16, vN8, vN4, v2xN4, v2xN2, v2xN2plus2xN4,
    . . . ,
    v2xM2plus2xM4
-- Values releated to TS 25.212 [9]
Max-UE-DTX-Cycle ::= ENUMERATED {
    v5, v10, v20, v40, v64, v80, v128, v160,
MBMS-Bearer-Service-Full-Address ::= SEQUENCE {
                                           AccessPointName,
    accessPointName
    iPMulticastAddress
                                           IPMulticastAddress,
                                       ProtocolExtensionContainer { { MBMS-Bearer-Service-Full-Address-ExtIEs } }
    iE-Extensions
                                                                                                                                       OPTIONAL,
MBMS-Bearer-Service-Full-Address-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MBMS-Bearer-Service-List ::= SEQUENCE (SIZE (1..maxNrOfMBMSServices)) OF TMGI
```

994

```
MBMS-Bearer-ServiceItemFDD ::=SEQUENCE{
    tmgi TMGI,
    transmissionMode
                      TransmissionMode.
    iE-Extensions
                                   ProtocolExtensionContainer { { MBMS-Bearer-ServiceItemFDD-ExtIEs} } OPTIONAL,
MBMS-Bearer-ServiceItemFDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MBMS-Bearer-ServiceItemFDD-PFL ::=SEQUENCE{
    tmai
           TMGI,
    transmissionMode
                           TransmissionMode
                                               OPTIONAL,
   preferredFrequencyLayer
                               UARFCN
                                               OPTIONAL,
                                   ProtocolExtensionContainer { { MBMS-Bearer-ServiceItemFDD-PFL-ExtIEs} } OPTIONAL,
   iE-Extensions
MBMS-Bearer-ServiceItemFDD-PFL-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MBMS-Bearer-ServiceItemTDD ::=SEQUENCE{
          TMGI,
    tmqi
    transmissionMode
                       TransmissionMode,
   iE-Extensions
                                   ProtocolExtensionContainer { { MBMS-Bearer-ServiceItemTDD-ExtIEs} } OPTIONAL,
MBMS-Bearer-ServiceItemTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MBMS-Bearer-ServiceItemTDD-PFL ::=SEQUENCE{
    tmai
          TMGI,
    transmissionMode
                     TransmissionMode
                                           OPTIONAL,
   preferredFrequencyLayer
                               UARFCN
                                               OPTIONAL,
   iE-Extensions
                                   ProtocolExtensionContainer { { MBMS-Bearer-ServiceItemTDD-PFL-ExtIEs} } OPTIONAL,
MBMS-Bearer-ServiceItemTDD-PFL-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MBMSChannelTypeInfo ::= SEQUENCE {
    tMGI
                       TMGI,
   pTM-Cell-List
                       PTMCellList
                                       OPTIONAL,
   pTP-Cell-List
                      PTPCellList
                                       OPTIONAL,
   not-Provided-Cell-List NotProvidedCellList OPTIONAL,
   iE-Extensions ProtocolExtensionContainer { { MBMSChannelTypeInfo-ExtIEs} } OPTIONAL,
```

```
MBMSChannelTypeInfo-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MBMSChannelTypeCellList ::= SEQUENCE {
                                           C-ID.
    affectedUEInformationForMBMS
                                       AffectedUEInformationForMBMS
                                                                        OPTIONAL,
    iE-Extensions
                                       ProtocolExtensionContainer { { MBMSChannelTypeCellList-ExtIEs} } OPTIONAL,
MBMSChannelTypeCellList-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MBMSPreferredFregLayerInfo ::= SEQUENCE {
    preferredFrequencyLayerInfo
                                    PreferredFrequencyLayerInfo,
                                    ProtocolExtensionContainer { { MBMSPreferredFreqLayerInfo-ExtIEs} } OPTIONAL,
   iE-Extensions
    . . .
MBMSPreferredFreqLayerInfo-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
MBMS-Neighbouring-Cell-Information ::= SEQUENCE {
   mBMS-ConcatenatedServiceList
                                       MBMS-ConcatenatedServiceList,
   13-Information-1
                                       L3-Information OPTIONAL,
-- This IE contains MBMS COMMON P-T-M RB INFORMATION defined in TS 25.331 [16]
   13-Information-2
                                       L3-Information OPTIONAL,
-- This IE contains MBMS CURRENT CELL P-T-M RB INFORMATION defined in TS 25.331 [16]
   iE-Extensions
                                   ProtocolExtensionContainer { { MBMS-Neighbouring-Cell-Information-ExtIEs} } OPTIONAL,
MBMS-Neighbouring-Cell-Information-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
MBMS-ConcatenatedServiceList
                              ::= SEQUENCE (SIZE (1..maxlengthMBMSconcatservlists)) OF TMGI
MBMS-RLC-Sequence-Number-Information ::= SEQUENCE (SIZE (1..maxNrOfCells)) OF MBMS-RLC-Sequence-Number-Information-List
MBMS-RLC-Sequence-Number-Information-List ::= SEOUENCE {
    mBMS-Bearer-Service-List-RLC
                                                            MBMS-Bearer-Service-List-RLC.
    iE-Extensions
                                    ProtocolExtensionContainer { { MBMS-RLC-Sequence-Number-Information-List-ExtIEs} }
                                                                                                                               OPTIONAL,
MBMS-RLC-Sequence-Number-Information-List-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
MBMS-Bearer-Service-List-RLC::= SEQUENCE (SIZE (1..maxNrOfMBMSServices)) OF MBMS-Bearer-Service-List-RLCinfo
MBMS-Bearer-Service-List-RLCinfo
                                    ::= SEOUENCE {
                                    TMGI,
    tmqi
    time-Stamp
                                   Time-Stamp,
   iE-Extensions
                                    ProtocolExtensionContainer { MBMS-Bearer-Service-List-RLCinfo-ExtIEs} }
                                                                                                                        OPTIONAL.
MBMS-Bearer-Service-List-RLCinfo-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MBSFN-Cluster-Identity
                           ::= INTEGER (0..65535)
MCCH-Message-List ::= SEOUENCE (SIZE (1.. maxNrOfMCCHMessages)) OF L3-Information
MCCH-Configuration-Info ::= SEQUENCE {
    secondaryCCPCHSystemInformationMBMS
                                                Secondary-CCPCH-System-Information-MBMS,
                                                ProtocolExtensionContainer { {MCCH-Configuration-Info-ExtIEs } }
    ie-Extensions
                                                                                                                   OPTIONAL,
    . . .
MCCH-Configuration-Info-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
                                                   ::= BIT STRING
Secondary-CCPCH-System-Information-MBMS
MBSFN-Scheduling-Transmission-Time-Interval-Info-List :=
                                                                SEQUENCE (SIZE (1.. maxNrOfMBMSL3)) OF MBSFN-Scheduling-Transmission-Time-Interval-
Item
MBSFN-Scheduling-Transmission-Time-Interval-Item
                                                   ::= SEOUENCE {
    mbsfnSchedulingTransmissionTimeInterval
                                                MbsfnSchedulingTransmissionTimeInterval,
    ie-Extensions
                                                ProtocolExtensionContainer { { MBSFN-Scheduling-Transmission-Time-Interval-Item-ExtIEs } }
    OPTIONAL,
MBSFN-Scheduling-Transmission-Time-Interval-Item-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MbsfnSchedulingTransmissionTimeInterval ::= ENUMERATED {tti4, tti8, tti16, tti32, tti64, tti128, tti256}
MeasurementFilterCoefficient ::= ENUMERATED{k0, k1, k2, k3, k4, k5, k6, k7, k8, k9, k11, k13, k15, k17, k19,...}
-- Measurement Filter Coefficient to be used for measurement
```

```
MeasurementID
                       ::= INTEGER (0..1048575)
Measurement-Power-Offset ::= INTEGER(-12 .. 26)
-- Actual value = IE value * 0.5
MinimumSpreadingFactor
                      ::= INTEGER (1..16)
MinimumSpreadingFactor768
                          ::= INTEGER (1..32)
MultipleURAsIndicator ::= ENUMERATED {
   multiple-URAs-exist,
   single-URA-exists
MaxAdjustmentStep
                      ::= INTEGER(1..10)
-- Unit Slot
MeasurementChangeTime
                      ::= INTEGER (1..6000,...)
-- The MeasurementChangeTime gives the MeasurementChangeTime
-- in number of 10 ms periods.
-- E.g. Value 6000 means 60000ms(1min)
-- Unit is ms, Step is 10 ms
MeasurementHysteresisTime
                          ::= INTEGER (1..6000,...)
-- The MeasurementHysteresisTime gives the
-- MeasurementHysteresisTime in number of 10 ms periods.
-- E.g. Value 6000 means 60000ms(1min)
-- Unit is ms, Step is 10ms
                                    ::= CHOICE {
MeasurementIncreaseDecreaseThreshold
                              SIR-Value-IncrDecrThres,
   sir
   sir-error
                              SIR-Error-Value-IncrDecrThres,
   transmitted-code-power
                              Transmitted-Code-Power-Value-IncrDecrThres,
                              RSCP-Value-IncrDecrThres,
   round-trip-time
                              Round-Trip-Time-IncrDecrThres,
   extension-MeasurementIncreaseDecreaseThreshold
                                              Extension-MeasurementIncreaseDecreaseThreshold
Extension-MeasurementIncreaseDecreaseThreshold ::= ProtocolIE-Single-Container {{ Extension-MeasurementIncreaseDecreaseThresholdIE }}
Extension-MeasurementIncreaseDecreaseThresholdIE RNSAP-PROTOCOL-IES ::= {
    ID id-Load-Value-IncrDecrThres
                                 CRITICALITY reject TYPE Load-Value-IncrDecrThres PRESENCE mandatory } |
    PRESENCE mandatory } |
   PRESENCE mandatory } |
    PRESENCE mandatory } |
    ID id-RT-Load-Value-IncrDecrThres CRITICALITY reject TYPE RT-Load-Value-IncrDecrThres
                                                                               PRESENCE mandatory }
                                             CRITICALITY reject TYPE NRT-Load-Information-Value-IncrDecrThres
   { ID id-NRT-Load-Information-Value-IncrDecrThres
                                                                                                          PRESENCE mandatory
   { ID id-UpPTSInterferenceValue
                                 CRITICALITY reject TYPE UppTSInterferenceValue
                                                                                PRESENCE mandatory }
```

```
MeasurementRecoveryBehavior ::= NULL
MeasurementRecoveryReportingIndicator ::= NULL
MeasurementRecoverySupportIndicator ::= NULL
MeasurementThreshold
                              ::= CHOICE {
   cir
                                  SIR-Value,
   sir-error
                                  SIR-Error-Value,
                                  Transmitted-Code-Power-Value,
    transmitted-code-power
                                  RSCP-Value,
   rx-timing-deviation
                                  Rx-Timing-Deviation-Value,
   round-trip-time
                                  Round-Trip-Time-Value,
    extension-MeasurementThreshold Extension-MeasurementThreshold
Extension-MeasurementThreshold ::= ProtocolIE-Single-Container {{ Extension-MeasurementThresholdIE }}
Extension-MeasurementThresholdIE RNSAP-PROTOCOL-IES ::= {
    { ID id-TUTRANGPSMeasurementThresholdInformation
                                                     CRITICALITY reject TYPE TUTRANGPSMeasurementThresholdInformation
                                                                                                                                 PRESENCE
mandatory } |
    { ID id-SFNSFNMeasurementThresholdInformation
                                                     CRITICALITY reject TYPE SFNSFNMeasurementThresholdInformation
                                                                                                                                 PRESENCE
mandatory } |
    { ID id-Load-Value
                                                     CRITICALITY reject TYPE Load-Value
           PRESENCE mandatory } |
    { ID id-Transmitted-Carrier-Power-Value
                                                     CRITICALITY reject TYPE Transmitted-Carrier-Power-Value
    PRESENCE mandatory } |
                                                     CRITICALITY reject TYPE Received-Total-Wideband-Power-Value
    { ID id-Received-Total-Wideband-Power-Value
                                                                                                                                 PRESENCE
mandatory } |
    { ID id-UL-Timeslot-ISCP-Value
                                                     CRITICALITY reject TYPE UL-Timeslot-ISCP-Value
       PRESENCE mandatory } |
    { ID id-RT-Load-Value
                                                     CRITICALITY reject TYPE RT-Load-Value
           PRESENCE mandatory }
    { ID id-NRT-Load-Information-Value
                                                     CRITICALITY reject TYPE NRT-Load-Information-Value
    PRESENCE mandatory } |
    { ID id-Rx-Timing-Deviation-Value-LCR
                                                     CRITICALITY reject TYPE Rx-Timing-Deviation-Value-LCR
    PRESENCE mandatory |
     ID id-HS-SICH-Reception-Quality-Measurement-Value CRITICALITY reject TYPE HS-SICH-Reception-Quality-Measurement-Value PRESENCE mandatory
    { ID id-UpPTSInterferenceValue
                                                     CRITICALITY reject TYPE UpPTSInterferenceValue
       PRESENCE mandatory }
    { ID id-Rx-Timing-Deviation-Value-768
                                                     CRITICALITY reject TYPE Rx-Timing-Deviation-Value-768
    PRESENCE mandatory}
    { ID id-Rx-Timing-Deviation-Value-ext
                                                     CRITICALITY reject TYPE Rx-Timing-Deviation-Value-ext
    PRESENCE mandatory |
    { ID id-Extended-Round-Trip-Time-Value
                                                     CRITICALITY reject TYPE Extended-Round-Trip-Time-Value
    PRESENCE mandatory } |
    PRESENCE mandatory }
MidambleConfigurationBurstType1And3 ::=
                                          ENUMERATED {v4, v8, v16}
MidambleConfigurationBurstType2 ::=
                                      ENUMERATED {v3, v6}
```

```
MidambleConfigurationLCR ::=
                              ENUMERATED {v2, v4, v6, v8, v10, v12, v14, v16, ...}
MidambleShiftAndBurstType ::=
                                  CHOICE {
   type1
                                      SEOUENCE
       midambleConfigurationBurstType1And3
                                              MidambleConfigurationBurstTypelAnd3,
       midambleAllocationMode
                                          CHOICE {
           defaultMidamble
                                              NULL,
           commonMidamble
                                              NULL,
           ueSpecificMidamble
                                              MidambleShiftLong,
    type2
                                      SEOUENCE -
       midambleConfigurationBurstType2
                                          MidambleConfigurationBurstType2,
       midambleAllocationMode
                                          CHOICE {
           defaultMidamble
                                              NULL,
           commonMidamble
                                              NULL,
           ueSpecificMidamble
                                              MidambleShiftShort,
       },
                                      SEQUENCE
   type3
       midambleAllocationMode
                                      CHOICE {
           defaultMidamble
                                              NULL,
                                              MidambleShiftLong,
           ueSpecificMidamble
                                  INTEGER (0..15)
MidambleShiftLong ::=
MidambleShiftShort ::=
                                  INTEGER (0..5)
MidambleShiftLCR ::= SEQUENCE {
   midambleAllocationMode
                              MidambleAllocationMode,
   midambleShift
                              MidambleShiftLong
                                                     OPTIONAL,
       -- The IE shall be present if the Midamble Allocation Mode IE is set to "UE specific midamble".
    midambleConfigurationLCR
                              MidambleConfigurationLCR,
                              ProtocolExtensionContainer { {MidambleShiftLCR-ExtIEs} }
   iE-Extensions
                                                                                            OPTIONAL,
    . . .
MidambleAllocationMode ::= ENUMERATED {
   defaultMidamble,
   commonMidamble,
   uESpecificMidamble,
    . . .
```

```
MidambleShiftLCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MidambleShiftAndBurstType768 ::=
                                      CHOICE {
                                      SEOUENCE
       midambleConfigurationBurstType1And3
                                              MidambleConfigurationBurstType1And3,
       midambleAllocationMode
                                          CHOICE {
           defaultMidamble
                                              NULL,
           commonMidamble
                                              NULL,
           ueSpecificMidamble
                                              MidambleShiftLong,
   type2
                                      SEOUENCE
       midambleConfigurationBurstType2-768
                                              MidambleConfigurationBurstType2-768,
       midambleAllocationMode
                                          CHOICE {
           defaultMidamble
                                              NULL,
           commonMidamble
                                              NULL,
           ueSpecificMidamble
                                              MidambleShiftShort768,
       . . .
    type3
                                      SEQUENCE
       midamble Configuration Burst Type 1 And 3 Midamble Configuration Burst Type 1 And 3,
       midambleAllocationMode
                                      CHOICE {
           defaultMidamble
                                              NULL,
           ueSpecificMidamble
                                              MidambleShiftLong,
MidambleConfigurationBurstType2-768 ::=
                                          ENUMERATED {v4, v8}
MidambleShiftShort768 ::=
                                      INTEGER (0..7)
MIMO-ActivationIndicator
                          ::= NULL
MIMO-InformationResponse ::= SEQUENCE
   mIMO-PilotConfiguration
                                              MIMO-PilotConfiguration,
   mIMO-N-M-Ratio
                                              MIMO-N-M-Ratio,
    iE-Extensions
                                              OPTIONAL,
MIMO-InformationResponse-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
MIMO-Mode-Indicator ::= ENUMERATED {
    activate.
    deactivate
MIMO-N-M-Ratio ::= ENUMERATED \{v1-2, v2-3, v3-4, v4-5, v5-6, v6-7, v7-8, v8-9, v9-10, v1-1, \ldots\}
MIMO-PilotConfiguration ::= CHOICE {
    primary-and-secondary-CPICH
                                         MIMO-S-CPICH-Channelisation-Code,
   normal-and-diversity-primary-CPICH
                                         NULL,
    . . .
MIMO-S-CPICH-Channelisation-Code ::= INTEGER (0..255)
MinUL-ChannelisationCodeLength
                                  ::= ENUMERATED
    v4,
    v8,
    v16,
    v32,
    v64,
    v128,
    v256
MinimumReducedE-DPDCH-GainFactor ::= ENUMERATED {m8-15, m11-15, m15-15, m21-15, m30-15, m42-15, m60-15, m84-15,...}
ModifyPriorityQueue ::= CHOICE {
    addPriorityQueue
                              PriorityQueue-InfoItem-to-Add,
    modifyPriorityQueue
                              PriorityQueue-InfoItem-to-Modify,
   deletePriorityQueue
                              PriorityQueue-Id,
Modulation ::= ENUMERATED {
    qPSK,
    eightPSK,
MulticellEDCH-Information
                              ::= ProtocolIE-Single-Container { {MulticellEDCH-InformationItem} }
MulticellEDCH-InformationItem RNSAP-PROTOCOL-IES ::= {
    PRESENCE mandatory }
MulticellEDCH-InformationItemIEs::= SEQUENCE {
    dL-PowerBalancing-Information
                                         DL-PowerBalancing-Information
                                                                            OPTIONAL,
    minimumReducedE-DPDCH-GainFactor
                                         MinimumReducedE-DPDCH-GainFactor
                                                                                OPTIONAL,
    secondary-UL-Frequency-Activation-State
                                                 Secondary-UL-Frequency-Activation-State
                                                                                           OPTIONAL,
```

```
f-DPCH-SlotFormat
                             F-DPCH-SlotFormat
                                                    OPTIONAL,
   common-DL-ReferencePowerInformation
                                            DL-Power
                                                           OPTIONAL.
                      ProtocolExtensionContainer { { MulticellEDCH-InformationItemIEs-ExtIEs } } OPTIONAL,
   iE-Extensions
MulticellEDCH-InformationItemIEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
                                    ::= ProtocolIE-Single-Container { {MulticellEDCH-RL-SpecificInformationItem} }
MulticellEDCH-RL-SpecificInformation
MulticellEDCH-RL-SpecificInformationItem RNSAP-PROTOCOL-IES ::= {
   PRESENCE
mandatory }
MulticellEDCH-RL-SpecificInformationItemIEs::= SEQUENCE
   extendedPropagationDelay
                                 ExtendedPropagationDelay
                                                                  OPTIONAL,
   enhanced-PrimaryCPICH-EcNo
                                 Enhanced-PrimaryCPICH-EcNo
                                                                  OPTIONAL,
   dl-Reference-Power
                             DL-Power
                                                OPTIONAL,
   phase-Reference-Update-Indicator
                                        Phase-Reference-Update-Indicator
                                                                                 OPTIONAL,
   additional-e-DCH-DL-Control-Channel-Grant
                                                NULL
                                                                                 OPTIONAL,
                     ProtocolExtensionContainer { { MulticellEDCH-RL-SpecificInformationItemIEs-ExtIEs } } OPTIONAL,
   . . .
MulticellEDCH-RL-SpecificInformationItemIEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   . . .
Multicell-EDCH-Restriction ::= BOOLEAN
Multiple-PLMN-List ::= SEQUENCE {
   pLMN-Identity
                     PLMN-Identity,
   list-Of-PLMNs
                      List-Of-PLMNs
                                                                              OPTIONAL,
   iE-Extensions
                      ProtocolExtensionContainer { { Multiple-PLMN-List-ExtIEs} } OPTIONAL,
   . . .
Multiple-PLMN-List-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   . . .
MultiplexingPosition ::= ENUMERATED {
   fixed.
   flexible
MAChs-ResetIndicator ::= ENUMERATED{
   mAChs-NotReset
```

```
MultipleFreq-HSPDSCH-InformationList-ResponseTDDLCR ::= SEQUENCE (SIZE (1.. maxHSDPAFrequency-1)) OF MultipleFreq-HSPDSCH-InformationItem-
ResponseTDDLCR
--Includes the 2<sup>nd</sup> through the max number of frequency repetitions
MultipleFreq-HSPDSCH-InformationItem-ResponseTDDLCR ::= SEQUENCE{
    hSSCCH-TDD-Specific-InfoList-Response-LCR
                                                    HSSCCH-TDD-Specific-InfoList-Response-LCR
                                                                                                 OPTIONAL.
   hARQ-MemoryPartitioning
                                                    HARQ-MemoryPartitioning
                                                                                                 OPTIONAL.
    uARFCN
                                                    UARFCN,
    -- This is the UARFCN for the second and beyond Frequency repetition.
                                                    ProtocolExtensionContainer { { MultipleFreq-HSPDSCH-InformationItem-ResponseTDDLCR-ExtIEs } }
    iE-Extensions
        OPTIONAL,
    . . .
MultipleFreg-HSPDSCH-InformationItem-ResponseTDDLCR-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
MIMO-SFMode-For-HSPDSCHDualStream ::= ENUMERATED {
    sF1.
    sF1SF16
Multi-Carrier-EDCH-Info ::= SEQUENCE{
    multicarrier-EDCH-Transport-Bearer-Mode
                                                                     Multicarrier-EDCH-Transport-Bearer-Mode,
    multi-carrier-EDCH-Information
                                                                     Multi-Carrier-EDCH-Information,
                                    ProtocolExtensionContainer { { Multi-Carrier-EDCH-Info-ExtIEs} } OPTIONAL,
   iE-Extensions
Multi-Carrier-EDCH-Info-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Multicarrier-EDCH-Transport-Bearer-Mode ::= ENUMERATED {
    separate-Iur-Transport-Bearer-Mode,
    shared-Iur-Transport-Bearer-Mode
Multi-Carrier-EDCH-Information ::= SEQUENCE (SIZE (1..maxNrOfULCarriersLCR-1)) OF Multi-Carrier-EDCH-LCR-InformationItem
Multi-Carrier-EDCH-LCR-InformationItem ::=SEQUENCE{
    uARFCNforNt
                                                    UARFCN,
    sNPL-carrier-group-indicator
                                                    SNPL-Carrier-Group-Indicator
                                                                                         OPTIONAL,
                                                    E-PUCH-PRXdesBase,
   multi-Carrier-EDCH-MACdFlows-Information-TDD
                                                   Multi-Carrier-EDCH-MACdFlows-Information-TDD
                                                                                                                          OPTIONAL,
                                    ProtocolExtensionContainer { { Multi-Carrier-EDCH-LCR-InformationItem-ExtIEs} } OPTIONAL,
Multi-Carrier-EDCH-LCR-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
```

```
SNPL-Carrier-Group-Indicator ::= INTEGER (1..3)
-- for multi-carrier E-DCH operation 1.28Mcps TDD only
Multi-Carrier-EDCH-MACdFlows-Information-TDD ::= SEQUENCE (SIZE (1.. maxNrOfEDCHMACdFlows)) OF Multi-Carrier-EDCH-MACdFlows-Specific-Info
Multi-Carrier-EDCH-MACdFlows-Specific-Info ::= SEOUENCE {
    e-DCH-MACdFlow-ID
                                                    EDCH-MACdFlow-ID,
    bindingID
                                                    BindingID,
    transportLayerAddress
                                                    TransportLayerAddress,
                                                    ProtocolExtensionContainer { { Multi-Carrier-EDCH-MACdFlows-Specific-Info-ExtIEs} }
    iE-Extensions
           OPTIONAL,
    . . .
Multi-Carrier-EDCH-MACdFlows-Specific-Info-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
Multi-Carrier-EDCH-Reconfigure ::=SEQUENCE{
    continue-setup-change-Of-Multi-Carrier-EDCH
                                                                        Continue-Setup-Change-Multi-Carrier-EDCH,
                                    ProtocolExtensionContainer { { Multi-Carrier-EDCH-Reconfigure-ExtIEs} } OPTIONAL,
   iE-Extensions
    . . .
Multi-Carrier-EDCH-Reconfigure-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Continue-Setup-Change-Multi-Carrier-EDCH ::= CHOICE {
    continue
                           NULL,
                           Multi-Carrier-EDCH-Info,
    setup
                           Multi-Carrier-EDCH-Change-Info,
    change
Multi-Carrier-EDCH-Change-Info ::=SEQUENCE{
   multicarrier-EDCH-Transport-Bearer-Mode
                                                            Multicarrier-EDCH-Transport-Bearer-Mode
                                                                                                                 OPTIONAL,
    multi-carrier-EDCH-Information
                                                            Multi-Carrier-EDCH-Information
                                                                                                                 OPTIONAL,
                                                            Multi-Carrier-EDCH-Information-Removal-List
   multi-Carrier-EDCH-Information-Removal-List
                                                                                                                 OPTIONAL,
                                    ProtocolExtensionContainer { { Multi-Carrier-EDCH-Change-Info-ExtIEs} } OPTIONAL,
   iE-Extensions
Multi-Carrier-EDCH-Change-Info-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Multi-Carrier-EDCH-Information-Removal-List ::= SEQUENCE (SIZE (1..maxNrOfULCarriersLCR-1)) OF Multi-Carrier-EDCH-Information-Removal-Info-ItemIEs
Multi-Carrier-EDCH-Information-Removal-Info-ItemIEs ::=SEOUENCE{
    uARFCNforNt.
    iE-Extensions
                                    ProtocolExtensionContainer { { Multi-Carrier-EDCH-Information-Removal-Info-ItemIEs-ExtIEs} } OPTIONAL,
```

```
Multi-Carrier-EDCH-Information-Removal-Info-ItemIEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Multi-Carrier-EDCH-Information-Response ::= SEOUENCE (SIZE (1..maxNrOfULCarriersLCR-1)) OF Multi-Carrier-EDCH-LCR-Information-ResponseItem
Multi-Carrier-EDCH-LCR-Information-ResponseItem ::=SEQUENCE{
    uARFCNforNt
    e-DCH-TDD-MACdFlow-Specific-InformationResp
                                                    E-DCH-TDD-MACdFlow-Specific-InformationResp
                                                                                                          OPTIONAL,
    e-AGCH-Specific-Information-Response-LCR-TDD
                                                   E-AGCH-Specific-InformationRespList-LCR-TDD
                                                                                                         OPTIONAL,
    e-HICH-Scheduled-InformationResp-LCR
                                                    E-HICH-Scheduled-InformationRespList-LCR-TDD
                                                                                                         OPTIONAL,
    iE-Extensions
                                    ProtocolExtensionContainer { Multi-Carrier-EDCH-LCR-Information-ResponseItem-ExtIEs} } OPTIONAL,
Multi-Carrier-EDCH-LCR-Information-ResponseItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MU-MIMO-InformationLCR ::= SEQUENCE {
   mU-MIMO-Operation
                                                MU-MIMO-Operation,
    standalone-Midamble-Channel-Information
                                                Standalone-Midamble-Channel-Information OPTIONAL,
    iE-Extensions
                                        ProtocolExtensionContainer { { MU-MIMO-InformationLCR-ExtIEs} } OPTIONAL,
MU-MIMO-Operation ::= ENUMERATED {
    mU-MIMO-Used,
   mU-MIMO-Not-Used,
    . . .
MU-MIMO-Usage-Indicator ::= ENUMERATED {
    ul-Only,
    dl-Only,
    ul-and-dl
Standalone-Midamble-Channel-Information ::= SEQUENCE
    standalone-Midamble-Configuratnion Standalone-Midamble-Configuratnion,
    standalone-MidambleShift
                                        Standalone-MidambleShift,
    timeslotLCR
                                        TimeSlotLCR,
                                        Standalone-Midamble-RepetitionPeriod,
    repetitionPeriod
                                        Standalone-Midamble-Offset,
    offset
   referenceBeta
                                        ReferenceBeta
                                                                        OPTIONAL,
    iE-Extensions
                                        ProtocolExtensionContainer { { Standalone-Midamble-Channel-Information-ExtIEs} } OPTIONAL,
Standalone-Midamble-Configuratnion: = ENUMERATED {
    v2,
```

```
v4,
    v6,
    v8.
    v10,
    v12,
    v14,
    v16,
Standalone-MidambleShift ::= INTEGER (0..15)
Standalone-Midamble-RepetitionPeriod ::= ENUMERATED {
    v1,
    v2,
    v4,
    v8,
    v16,
    v32,
    v64,
Standalone-Midamble-Offset ::= INTEGER (0..63)
ReferenceBeta ::= INTEGER (-15..16)
Standalone-Midamble-Channel-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MU-MIMO-InformationLCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
MU-MIMO-Indicator ::= SEQUENCE {
    mU-MIMO-Usage-Indicator
                                            MU-MIMO-Usage-Indicator,
    standalone-Midamble-Channel-Indicator Standalone-Midamble-Channel-Indicator,
   iE-Extensions
                                            ProtocolExtensionContainer { { MU-MIMO-Indicator-ExtIEs} } OPTIONAL,
MU-MIMO-Indicator-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
NACC-Related-Data ::= SEQUENCE {
    gERAN-SI-Type
                                GERAN-SI-Type,
   iE-Extensions
                                ProtocolExtensionContainer { {NACC-Related-Data-ExtIEs} }
                                                                                                OPTIONAL,
```

```
NACC-Related-Data-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Nack-Power-Offset ::= INTEGER (0..8,...)
-- According to mapping in TS 25.213 [21] subclause 4.2.1
NCC ::= BIT STRING (SIZE (3))
Neighbouring-UMTS-CellInformation ::= SEQUENCE (SIZE (1..maxNrOfNeighbouringRNCs)) OF ProtocolIE-Single-Container {{ Neighbouring-UMTS-
CellInformationItemIE }}
Neighbouring-UMTS-CellInformation-Ext ::= SEQUENCE (SIZE (1..maxNrOfExtendedNeighbouringRNCs)) OF ProtocolIE-Single-Container {{ Neighbouring-UMTS-
CellInformationExtensionItemIE }}
Neighbouring-UMTS-CellInformationExtensionItemIE RNSAP-PROTOCOL-IES ::=
   PRESENCE
   mandatory }
Neighbouring-UMTS-CellInformationExtensionItem ::= SEQUENCE {
   rNC-ID
                                        RNC-ID,
   cN-PS-DomainIdentifier
                                        CN-PS-DomainIdentifier
                                                                             OPTIONAL,
   cN-CS-DomainIdentifier
                                        CN-CS-DomainIdentifier
                                                                             OPTIONAL,
   neighbouring-FDD-CellInformation
                                        Neighbouring-FDD-CellInformation
                                                                            OPTIONAL,
   neighbouring-TDD-CellInformation
                                        Neighbouring-TDD-CellInformation
                                                                            OPTIONAL,
   neighbouring-LCR-TDD-CellInformation
                                        Neighbouring-LCR-TDD-CellInformation
                                                                            OPTIONAL,
                                        Extended-RNC-ID
   extended-RNC-ID
                                                                            OPTIONAL,
   iE-Extensions
                                        ProtocolExtensionContainer { {Neighbouring-UMTS-CellInformationExtensionItem-ExtIEs} } OPTIONAL,
Neighbouring-UMTS-CellInformationExtensionItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Neighbouring-UMTS-CellInformationItemIE RNSAP-PROTOCOL-IES ::= {
    Neighbouring-UMTS-CellInformationItem
                                                                                                                           mandatory
Neighbouring-UMTS-CellInformationItem ::= SEQUENCE
   rNC-ID
                                        RNC-ID,
   cN-PS-DomainIdentifier
                                        CN-PS-DomainIdentifier
                                                                 OPTIONAL,
   cN-CS-DomainIdentifier
                                        CN-CS-DomainIdentifier
                                                                 OPTIONAL,
   neighbouring-FDD-CellInformation
                                        Neighbouring-FDD-CellInformation
                                                                         OPTIONAL,
   neighbouring-TDD-CellInformation
                                        Neighbouring-TDD-CellInformation
                                                                         OPTIONAL,
   iE-Extensions
                                        ProtocolExtensionContainer { {Neighbouring-UMTS-CellInformationItem-ExtIEs} } OPTIONAL,
Neighbouring-UMTS-CellInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
{ ID id-neighbouring-LCR-TDD-CellInformation
                                                            CRITICALITY ignore
                                                                                     EXTENSION
                                                                                                Neighbouring-LCR-TDD-CellInformation
    PRESENCE optional }
    { ID id-Extended-RNC-ID
                                                CRITICALITY reject EXTENSION Extended-RNC-ID
                                            PRESENCE optional },
Neighbouring-FDD-CellInformation ::= SEQUENCE ( SIZE (1..maxNrOfFDDNeighboursPerRNC,...)) OF Neighbouring-FDD-CellInformationItem
Neighbouring-FDD-CellInformationItem ::= SEOUENCE {
    C-TD
                                        C-ID,
    uARFCNforNu
                                        UARFCN,
    11ARFCNforNd
                                        UARFCN,
    frameOffset
                                        FrameOffset
                                                            OPTIONAL,
    primaryScramblingCode
                                        PrimaryScramblingCode,
    primaryCPICH-Power
                                        PrimaryCPICH-Power
                                                                OPTIONAL.
    cellIndividualOffset
                                        CellIndividualOffset
                                                                OPTIONAL,
    txDiversityIndicator
                                        TxDiversityIndicator,
    sTTD-SupportIndicator
                                        STTD-SupportIndicator
                                                                OPTIONAL,
    closedLoopModel-SupportIndicator
                                        ClosedLoopModel-SupportIndicator
                                                                            OPTIONAL,
    not-used-closedLoopMode2-SupportIndicator NULL
                                                        OPTIONAL,
                                        ProtocolExtensionContainer { { Neighbouring-FDD-CellInformationItem-ExtIEs} } OPTIONAL,
    iE-Extensions
Neighbouring-FDD-CellInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
      ID id-RestrictionStateIndicator
                                                                        EXTENSION RestrictionStateIndicator
                                                                                                                         PRESENCE optional }
                                                CRITICALITY ignore
      ID id-DPC-Mode-Change-SupportIndicator
                                                CRITICALITY ignore
                                                                        EXTENSION DPC-Mode-Change-SupportIndicator
                                                                                                                                PRESENCE optional } |
     ID id-CoverageIndicator
                                                CRITICALITY ignore
                                                                        EXTENSION CoverageIndicator
                                                                                                                                        PRESENCE
optional }
     ID id-AntennaColocationIndicator
                                                CRITICALITY ignore
                                                                        EXTENSION AntennaColocationIndicator
                                                                                                                         PRESENCE optional }
     ID id-HCS-Prio
                                                CRITICALITY ignore
                                                                        EXTENSION HCS-Prio
                                                                                                                                        PRESENCE
optional }|
     ID id-CellCapabilityContainer-FDD
                                                                        EXTENSION CellCapabilityContainer-FDD
                                                                                                                         PRESENCE optional }
                                                CRITICALITY ignore
     ID id-SNA-Information
                                                                        EXTENSION SNA-Information
                                                CRITICALITY ignore
                                                                                                                                        PRESENCE
optional }|
      ID id-FrequencyBandIndicator
                                                CRITICALITY ignore
                                                                        EXTENSION FrequencyBandIndicator
                                                                                                                         PRESENCE optional }
      ID id-Max-UE-DTX-Cycle
                                                CRITICALITY ignore
                                                                        EXTENSION Max-UE-DTX-Cycle
                                                                                                                                        PRESENCE
conditional }|
    -- This IE shall be present if the the fifteenth bit Continuous Packet Connectivity DTX-DRX Support Indicator in the Cell Capability Container
FDD IE is set to the value "1".
    { ID id-Multiple-PLMN-List
                                                CRITICALITY ignore
                                                                        EXTENSION Multiple-PLMN-List
                                                                                                                                        PRESENCE
optional }|
      ID id-Secondary-Serving-Cell-List
                                                CRITICALITY ignore
                                                                        EXTENSION Secondary-Serving-Cell-List
                                                                                                                 PRESENCE optional }
      ID id-Dual-Band-Secondary-Serving-Cell-List CRITICALITY ignore
                                                                        EXTENSION Secondary-Serving-Cell-List
                                                                                                                 PRESENCE optional }
-- This IE shall be present if the twenty-eighth bit Dual Band Support Indicator in the Cell Capability Container FDD IE is set to the value "1".
      ID id-CellCapabilityContainerExtension-FDD
                                                                        EXTENSION CellCapabilityContainerExtension-FDD
                                                    CRITICALITY ignore
                                                                                                                                PRESENCE optional } |
     ID id-CellListValidityIndicator
                                                                        EXTENSION CellListValidityIndicator
                                                CRITICALITY ignore
                                                                                                                         PRESENCE optional },
    . . .
NeighbouringFDDCellMeasurementInformation ::= SEOUENCE {
    uC-ID
                                        UC-ID,
    uARFCN
                                        UARFCN,
```

```
primaryScramblingCode
                                        PrimaryScramblingCode,
    iE-Extensions
                                        ProtocolExtensionContainer { { NeighbouringFDDCellMeasurementInformationItem-ExtIEs} } OPTIONAL,
NeighbouringFDDCellMeasurementInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Neighbouring-GSM-CellInformation ::= ProtocolIE-Single-Container {{ Neighbouring-GSM-CellInformationIE }}
Neighbouring-GSM-CellInformationIE RNSAP-PROTOCOL-IES ::= {
    { ID id-Neighbouring-GSM-CellInformation CRITICALITY ignore TYPE
                                                                            Neighbouring-GSM-CellInformationIEs PRESENCE
                                                                                                                                mandatory |
Neighbouring-GSM-CellInformationIEs ::= SEQUENCE ( SIZE (1..maxNrOfGSMNeighboursPerRNC,...)) OF Neighbouring-GSM-CellInformationItem
Neighbouring-GSM-CellInformationItem ::= SEQUENCE {
    cellIndividualOffset
                                        CellIndividualOffset
                                                                OPTIONAL,
    bSIC
                                        BSIC.
    band-Indicator
                                        Band-Indicator,
    bcch-arfcn
                                        BCCH-ARFCN,
    iE-Extensions
                                        ProtocolExtensionContainer { { Neighbouring-GSM-CellInformationItem-ExtIEs} } OPTIONAL,
Neighbouring-GSM-CellInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
    { ID id-CoverageIndicator
                                            CRITICALITY ignore
                                                                        EXTENSION CoverageIndicator
    PRESENCE optional } |
     ID id-AntennaColocationIndicator
                                            CRITICALITY ignore
                                                                        EXTENSION AntennaColocationIndicator
                                                                                                                                PRESENCE optional
     ID id-HCS-Prio
                                            CRITICALITY ignore
                                                                        EXTENSION HCS-Prio
    PRESENCE optional } |
                                            CRITICALITY ignore
    { ID id-SNA-Information
                                                                        EXTENSION SNA-Information
    PRESENCE optional } |
    { ID id-GERAN-Cell-Capability
                                            CRITICALITY ignore
                                                                        EXTENSION GERAN-Cell-Capability
                                                                                                                                        PRESENCE
optional } |
    { ID id-GERAN-Classmark
                                            CRITICALITY ignore
                                                                        EXTENSION GERAN-Classmark
    PRESENCE optional
    { ID id-ExtendedGSMCellIndividualOffset CRITICALITY ignore
                                                                        EXTENSION ExtendedGSMCellIndividualOffset
                                                                                                                        PRESENCE optional
                                                                                                                                               },
Neighbouring-TDD-CellInformation ::= SEOUENCE ( SIZE (1...maxNrOfTDDNeighboursPerRNC,...)) OF Neighbouring-TDD-CellInformationItem
Neighbouring-TDD-CellInformationItem ::= SEQUENCE {
    c-ID
                                    C-ID,
    uARFCNforNt
                                    UARFCN,
    frameOffset
                                    FrameOffset
                                                        OPTIONAL,
    cellParameterID
                                    CellParameterID,
    syncCase
                                    SyncCase,
    timeSlot
                                    TimeSlot
                                                        OPTIONAL
    -- This IE shall be present if Sync Case = Casel -- ,
```

```
sCH-TimeSlot
                                    SCH-TimeSlot
                                                            OPTIONAL
    -- This IE shall be present if Sync Case = Case2 -- ,
    sCTD-Indicator
                           SCTD-Indicator.
    cellIndividualOffset
                                   CellIndividualOffset
                                                            OPTIONAL.
    dPCHConstantValue
                                    DPCHConstantValue OPTIONAL.
                                    PCCPCH-Power
    pCCPCH-Power
                                                            OPTIONAL,
    iE-Extensions
                                    ProtocolExtensionContainer { { Neighbouring-TDD-CellInformationItem-ExtIEs} } OPTIONAL,
Neighbouring-TDD-CellInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-RestrictionStateIndicator
                                                    CRITICALITY ignore
                                                                                EXTENSION RestrictionStateIndicator
                                                                                                                                PRESENCE optional
    { ID id-CoverageIndicator
                                            CRITICALITY ignore
                                                                        EXTENSION CoverageIndicator
                                                                                                                                       PRESENCE
optional }|
     ID id-AntennaColocationIndicator
                                            CRITICALITY ignore
                                                                        EXTENSION AntennaColocationIndicator
                                                                                                                        PRESENCE optional
                                                                                                                                               } |
     ID id-HCS-Prio
                                            CRITICALITY ignore
                                                                        EXTENSION HCS-Prio
                                                                                                                                       PRESENCE
optional }|
     ID id-CellCapabilityContainer-TDD
                                                    CRITICALITY ignore EXTENSION CellCapabilityContainer-TDD
                                                                                                                                PRESENCE optional }
     ID id-SNA-Information
                                                    CRITICALITY ignore EXTENSION SNA-Information
                                                                                                                                       PRESENCE
optional }|
    { ID id-CellCapabilityContainer-TDD768
                                                        CRITICALITY ignore EXTENSION CellCapabilityContainer-TDD768
                                                                                                                                       PRESENCE
optional }|
    { ID id-Multiple-PLMN-List
                                            CRITICALITY ignore
                                                                        EXTENSION Multiple-PLMN-List
                                                                                                                                       PRESENCE
optional },
NeighbouringTDDCellMeasurementInformation ::= SEQUENCE {
    uC-ID
                                        UC-ID,
    uARFCN
                                        UARFCN,
                                        CellParameterID,
    cellParameterID
                                        TimeSlot
                                                                    OPTIONAL,
    midambleShiftAndBurstType
                                        MidambleShiftAndBurstType OPTIONAL,
                                        ProtocolExtensionContainer { { NeighbouringTDDCellMeasurementInformationItem-ExtIEs} } OPTIONAL,
    iE-Extensions
NeighbouringTDDCellMeasurementInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
NeighbouringTDDCellMeasurementInformationLCR ::= SEQUENCE {
    uC-ID
                                        UC-ID,
    uARFCN
                                        UARFCN,
    cellParameterID
                                        CellParameterID,
    timeSlotLCR
                                        TimeSlotLCR
                                                                    OPTIONAL,
    midambleShiftLCR
                                        MidambleShiftLCR
                                                                    OPTIONAL,
    iE-Extensions
                                        ProtocolExtensionContainer { { NeighbouringTDDCellMeasurementInformationLCRItem-ExtIEs} } OPTIONAL,
NeighbouringTDDCellMeasurementInformationLCRItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
NeighbouringTDDCellMeasurementInformation768 ::= SEQUENCE {
   uC-ID
                                     UC-ID,
   11ARFCN
                                     UARFCN.
   cellParameterID
                                     CellParameterID,
   timeSlot
                                     TimeSlot
                                                               OPTIONAL.
   midambleShiftAndBurstType768
                                     MidambleShiftAndBurstType768
                                                                   OPTIONAL.
                                     ProtocolExtensionContainer { { NeighbouringTDDCellMeasurementInformationItem768-ExtIEs} } OPTIONAL,
   iE-Extensions
NeighbouringTDDCellMeasurementInformationItem768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Neighbouring-LCR-TDD-CellInformation ::= SEQUENCE (SIZE (1.. maxNrOfLCRTDDNeighboursPerRNC,...)) OF Neighbouring-LCR-TDD-CellInformationItem
Neighbouring-LCR-TDD-CellInformationItem ::= SEQUENCE {
   c-ID
                                 C-ID,
   uARFCNforNt.
                                 UARFCN.
   frameOffset
                                 FrameOffset
                                                    OPTIONAL,
   cellParameterID
                                 CellParameterID,
   sCTD-Indicator
                          SCTD-Indicator,
   cellIndividualOffset
                                 CellIndividualOffset
                                                        OPTIONAL,
   dPCHConstantValue
                                 DPCHConstantValue OPTIONAL,
   pCCPCH-Power
                                 PCCPCH-Power
                                                        OPTIONAL,
   restrictionStateIndicator
                                 RestrictionStateIndicator
                                                               OPTIONAL,
                                 ProtocolExtensionContainer { { Neighbouring-LCR-TDD-CellInformationItem-ExtIEs} } OPTIONAL,
   iE-Extensions
Neighbouring-LCR-TDD-CellInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
                                                                                                                        PRESENCE optional}
     ID id-CoverageIndicator
                                         CRITICALITY ignore EXTENSION CoverageIndicator
     ID id-AntennaColocationIndicator
                                         CRITICALITY ignore EXTENSION AntennaColocationIndicator
                                                                                                                        PRESENCE optional}
     ID id-HCS-Prio
                                         CRITICALITY ignore EXTENSION HCS-Prio
                                                                                                                        PRESENCE optional}
     ID id-CellCapabilityContainer-TDD-LCR CRITICALITY ignore EXTENSION CellCapabilityContainer-TDD-LCR
                                                                                                                        PRESENCE optional }
     ID id-SNA-Information
                                         CRITICALITY ignore EXTENSION SNA-Information
                                                                                                                        PRESENCE optional }
     ID id-Multiple-PLMN-List
                                         CRITICALITY ignore EXTENSION Multiple-PLMN-List
                                                                                                                        PRESENCE optional }
     Neighbouring-E-UTRA-CellInformation ::= SEQUENCE ( SIZE (1..maxNrOfEUTRANeighboursPerRNC,...)) OF Neighbouring-E-UTRA-CellInformationItem
Neighbouring-E-UTRA-CellInformationItem ::= SEQUENCE {
                                     ECGI,
   eCGT
   eARFCN-Information
                                     EARFCN-Information,
   iE-Extensions
                                     ProtocolExtensionContainer { { Neighbouring-E-UTRA-CellInformationItem-ExtIEs} } OPTIONAL,
```

```
Neighbouring-E-UTRA-CellInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-PCI
                        CRITICALITY ignore EXTENSION PCI
                                                                                           PRESENCE optional }
     ID id-TAC
                                   CRITICALITY ignore EXTENSION TAC
                                                                                           PRESENCE optional}
    { ID id-PLMN-List
                                   CRITICALITY ignore EXTENSION PLMN-List
                                                                                           PRESENCE optional },
NonCellSpecificTxDiversity ::= ENUMERATED {
    txDiversity,
NotProvidedCellList ::= SEQUENCE (SIZE (1..maxNrOfCells)) OF MBMSChannelTypeCellList
NrOfDLchannelisationcodes ::= INTEGER (1..8)
NrOfTransportBlocks
                           ::= INTEGER (0..512)
NRT-Load-Information-Value-IncrDecrThres ::= INTEGER(0..3)
NRT-Load-Information-Value ::= INTEGER(0..3)
NRTLoadInformationValue ::= SEOUENCE {
       uplinkNRTLoadInformationValue
                                            INTEGER(0..3),
        downlinkNRTLoadInformationValue
                                            INTEGER(0..3)
N-E-UCCH ::= INTEGER (1..12)
N-E-UCCH-LCR ::= INTEGER (1..8)
Number-Of-Supported-Carriers ::= ENUMERATED {
    one-one-carrier,
    one-three-carrier,
    three-three-carrier,
    one-six-carrier,
    three-six-carrier,
    six-six-carrier,
    . . . ,
    one-two-carrier-discontiguous,
    two-two-carrier-discontiguous,
    one-two-carrier-contiguous,
    two-two-carrier-contiguous
NumHS-SCCH-Codes ::= INTEGER (1..maxNrOfHSSCCHCodes)
NoOfTargetCellHS-SCCH-Order::= INTEGER (1..30)
Non-Serving-RL-Preconfig-Setup ::= SEQUENCE {
    new-non-serving-RL-selection New-non-serving-RL-setup-selection,
    iE-Extensions
                           ProtocolExtensionContainer { {Non-Serving-RL-Preconfig-Setup-ExtIEs} } OPTIONAL,
    . . .
```

```
Non-Serving-RL-Preconfig-Setup-ExtIEs RNSAP-PROTOCOL-EXTENSION::= {
    Setup PRESENCE optional },
Additional-E-DCH-Non-Serving-RL-Preconfiguration-Setup ::= NULL
New-non-serving-RL-setup-selection ::= CHOICE {
   new-Serving-RL-in-DRNS
                                        NULL,
                                        NULL,
   new-Serving-RL-Not-in-DRNS
   new-Serving-RL-in-or-Not-in-DRNS
                                        NULL,
Non-Serving-RL-Preconfig-Info ::= SEQUENCE
                                                               EDCH-FDD-DL-ControlChannelInformation OPTIONAL,
   new-non-serving-RL-E-DCH-FDD-DL-ControlChannelInformation-A
   new-non-serving-RL-E-DCH-FDD-DL-ControlChannelInformation-B
                                                               EDCH-FDD-DL-ControlChannelInformation OPTIONAL,
                                                               EDCH-FDD-DL-ControlChannelInformation OPTIONAL,
   new-non-serving-RL-E-DCH-FDD-DL-ControlChannelInformation-C
                         ProtocolExtensionContainer { {Non-Serving-RL-Preconfig-Info-ExtIEs} } OPTIONAL,
   iE-Extensions
    . . .
Non-Serving-RL-Preconfig-Info-ExtIEs
                                    RNSAP-PROTOCOL-EXTENSION
    {ID id-Additional-E-DCH-New-non-serving-RL-E-DCH-FDD-DL-Control-Channel-InfoList
                                                                               CRITICALITY ignore
                                                                                                        EXTENSION Additional-E-DCH-New-non-
serving-RL-E-DCH-FDD-DL-Control-Channel-InfoList PRESENCE optional },
Additional-E-DCH-New-non-serving-RL-E-DCH-FDD-DL-Control-Channel-InfoList ::= SEQUENCE(SIZE(1.. maxNrOfEDCH-1)) OF SEQUENCE {
   new-non-serving-RL-E-DCH-FDD-DL-Control-Channel-Information-A EDCH-FDD-DL-ControlChannelInformation OPTIONAL,
   new-non-serving-RL-E-DCH-FDD-DL-Control-Channel-Information-B EDCH-FDD-DL-ControlChannelInformation OPTIONAL,
   new-non-serving-RL-E-DCH-FDD-DL-Control-Channel-Information-C EDCH-FDD-DL-ControlChannelInformation OPTIONAL,
                         ProtocolExtensionContainer { { Additional-E-DCH-New-non-serving-RL-E-DCH-FDD-DL-Control-Channel-InfoList-ExtIEs} }
OPTIONAL,
Additional-E-DCH-New-non-serving-RL-E-DCH-FDD-DL-Control-Channel-InfoList-ExtIEs
                                                                             RNSAP-PROTOCOL-EXTENSION ::=
NeedforIdleInterval ::= ENUMERATED {
    false
-- 0
OnModification ::= SEQUENCE {
```

```
measurementThreshold
                            MeasurementThreshold,
    iE-Extensions
                            ProtocolExtensionContainer { {OnModification-ExtIEs} } OPTIONAL,
OnModification-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
OnModificationInformation ::= SEQUENCE {
    informationThreshold
                          InformationThreshold
                                                    OPTIONAL,
                            ProtocolExtensionContainer { {OnModificationInformation-ExtIEs} } OPTIONAL,
    iE-Extensions
OnModificationInformation-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
OrdinalNumberOfFrequency ::= INTEGER (1..32,...)
Out-of-Sychronization-Window ::= ENUMERATED {
ms40,
ms80,
ms160,
ms320,
ms640,
-- P
PagingCause ::= ENUMERATED {
    terminating-conversational-call,
    terminating-streaming-call,
    terminating-interactive-call,
    terminating-background-call,
    terminating-low-priority-signalling,
    terminating-high-priority-signalling,
    terminating-cause-unknown
-- See in TS 25.331 [16]
PagingRecordType ::= ENUMERATED {
    imsi-gsm-map,
    tmsi-gsm-map,
    p-tmsi-gsm-map,
    imsi-ds-41,
    tmsi-ds-41,
    . . .
-- See in TS 25.331 [16]
```

1016

```
PartialReportingIndicator ::= ENUMERATED {
    partial-reporting-allowed
Pattern-Sequence-Identifier ::= INTEGER (1.. maxNrOfDCHMeasurementOccasionPatternSequence)
PayloadCRC-PresenceIndicator ::= ENUMERATED {
    crc-included,
    crc-not-included
PCCPCH-Power ::= INTEGER (-150..400,...)
-- PCCPCH-power = power * 10
-- If power <= -15 PCCPCH shall be set to -150
-- If power >= 40 PCCPCH shall be set to 400
-- Unit dBm, Range -15dBm .. +40 dBm, Step 0.1dBm
PCH-InformationList ::= SEQUENCE (SIZE(0..1)) OF PCH-InformationItem
PCH-InformationItem ::= SEQUENCE {
    transportFormatSet
                                    TransportFormatSet,
                                    ProtocolExtensionContainer { { PCH-InformationItem-ExtIEs} } OPTIONAL,
   iE-Extensions
    . . .
PCH-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
PCI ::= INTEGER (0..503,...)
PC-Preamble ::= INTEGER(0..7,...)
Periodic ::= SEQUENCE {
   reportPeriodicity
                            ReportPeriodicity,
   iE-Extensions
                            ProtocolExtensionContainer { {Periodic-ExtIEs} } OPTIONAL,
Periodic-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
PeriodicInformation ::= SEOUENCE {
    informationReportPeriodicity
                                        InformationReportPeriodicity,
                                        ProtocolExtensionContainer { {PeriodicInformation-ExtIEs} } OPTIONAL,
   iE-Extensions
PeriodicInformation-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
Permanent-NAS-UE-Identity ::= CHOICE {
    imsi
                IMSI.
    . . .
Phase-Reference-Update-Indicator ::= ENUMERATED {
    phase-reference-needs-to-be-changed
PLCCHsequenceNumber ::= INTEGER (0..14)
PLMN-Identity ::= OCTET STRING (SIZE(3))
PLMN-List ::= SEQUENCE (SIZE(0..maxNrOfBroadcastPLMNs)) OF PLMN-Identity
PowerAdjustmentType ::= ENUMERATED {
    none,
    common,
    individual
PowerOffset
                        ::= INTEGER (0..24)
PowerOffsetForSecondaryCPICHforMIMO ::= INTEGER (-6..0)
-- Unit dB, Range -10dB .. 5dB, Step +1dB
PowerOffsetForSecondaryCPICHforMIMORequestIndicator ::= NULL
PRC ::= INTEGER (-2047..2047)
--pseudo range correction; scaling factor 0.32 meters
PRCDeviation ::= ENUMERATED {
    prcd1,
    prcd2,
   prcd5,
    prcd10,
Pre-emptionCapability ::= ENUMERATED {
    shall-not-trigger-pre-emption,
    may-trigger-pre-emption
Pre-emptionVulnerability ::= ENUMERATED {
    not-pre-emptable,
    pre-emptable
PredictedSFNSFNDeviationLimit ::= INTEGER (1..256)
-- Unit chip, Step 1/16 chip, Range 1/16..16 chip
PredictedTUTRANGPSDeviationLimit ::= INTEGER (1..256)
-- Unit chip, Step 1/16 chip, Range 1/16..16 chip
```

```
PreferredFrequencyLayerInfo ::= SEQUENCE {
    defaultPreferredFrequency
    additionalPreferredFrequency
                                    AdditionalPreferredFrequency
                                                                    OPTIONAL.
    iE-Extensions
                                    ProtocolExtensionContainer { { PreferredFrequencyLayerInfo-ExtIEs} } OPTIONAL,
PreferredFrequencyLayerInfo-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
PrimaryCPICH-Power
                          ::= INTEGER (-100..500)
-- step 0.1 (Range -10.0..50.0) Unit is dBm
PrimaryCPICH-EcNo
                            ::= INTEGER (-30..30)
Primary-CPICH-Usage-For-Channel-Estimation ::= ENUMERATED
  primary-CPICH-may-be-used,
  primary-CPICH-shall-not-be-used
PrimaryCCPCH-RSCP
                            ::= INTEGER (0..91)
-- Mapping of Non Negative values according to maping in TS 25.123 [24]
PrimaryCCPCH-RSCP-Delta
                            ::= INTEGER (-5..-1,...)
-- Mapping of Negative values according to maping in TS 25.123 [24]
PrimaryScramblingCode
                                ::= INTEGER (0..511)
PriorityLevel
                            ::= INTEGER (0..15)
-- 0 = spare, 1 = highest priority, ...14 = lowest priority and 15 = no priority
PriorityQueue-Id ::= INTEGER (0..maxNrOfPrioQueues-1)
PriorityQueue-InfoList ::= SEQUENCE (SIZE (1..maxNrOfPrioQueues)) OF PriorityQueue-InfoItem
PriorityOueue-InfoItem ::= SEOUENCE {
    priorityOueue-Id
                                        PriorityOueue-Id,
    associatedHSDSCH-MACdFlow
                                        HSDSCH-MACdFlow-ID,
    schedulingPriorityIndicator
                                        SchedulingPriorityIndicator,
    t.1
                                        т1.
    discardTimer
                                        DiscardTimer
                                                                    OPTIONAL,
    mAC-hsWindowSize
                                        MAC-hsWindowSize.
    mAChsGuaranteedBitRate
                                        MAChsGuaranteedBitRate
                                                                    OPTIONAL,
    mACdPDU-Size-Index
                                        MACdPDU-Size-IndexList,
    rLC-Mode
                                        RLC-Mode,
                                        ProtocolExtensionContainer { { PriorityQueue-InfoItem-ExtIEs } }
    iE-Extensions
                                                                                                                         OPTIONAL,
    . . .
PriorityQueue-InfoItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
{ ID id-MaximumMACdPDU-SizeExtended
                                                                                                                     PRESENCE optional } |
                                        CRITICALITY reject
                                                                EXTENSION MAC-PDU-SizeExtended
{ ID id-DL-RLC-PDU-Size-Format
                                            CRITICALITY ignore
                                                                    EXTENSION DL-RLC-PDU-Size-Format
                                                                                                         PRESENCE optional |
```

```
{ ID id-UE-AggregateMaximumBitRate-Enforcement-Indicator
                                                             CRITICALITY ignore
                                                                                      EXTENSION
                                                                                                  UE-AggregateMaximumBitRate-Enforcement-Indicator
            PRESENCE optional },
PriorityOueue-InfoList-EnhancedFACH-PCH ::= SEOUENCE (SIZE (1..maxNrOfPrioOueues)) OF PriorityOueue-InfoItem-EnhancedFACH-PCH
PriorityOueue-InfoItem-EnhancedFACH-PCH ::= SEOUENCE {
    priorityQueue-Id
                                        PriorityQueue-Id,
    schedulingPriorityIndicator
                                         SchedulingPriorityIndicator,
                                        MAC-ehs-Reset-Timer,
    mAC-ehs-Reset-Timer
    discardTimer
                                        DiscardTimer
                                                                                  OPTIONAL,
    mAC-hsWindowSize
                                        MAC-hsWindowSize,
    maximum-MACdPDU-Size
                                        MAC-PDU-SizeExtended,
    iE-Extensions
                                        ProtocolExtensionContainer { { PriorityOueue-InfoItem-EnhancedFACH-PCH-ExtIEs } }
    OPTIONAL,
PriorityQueue-InfoItem-EnhancedFACH-PCH-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
PriorityQueue-InfoList-to-Modify ::= SEQUENCE (SIZE (1..maxNrOfPrioQueues)) OF ModifyPriorityQueue
PriorityOueue-InfoItem-to-Add ::= SEOUENCE {
    priorityOueue-Id
                                         PriorityOueue-Id,
    associatedHSDSCH-MACdFlow
                                        HSDSCH-MACdFlow-ID,
    schedulingPriorityIndicator
                                         SchedulingPriorityIndicator,
    t.1
    discardTimer
                                        DiscardTimer
                                                                                  OPTIONAL,
    mAC-hsWindowSize
                                        MAC-hsWindowSize,
    mAChsGuaranteedBitRate
                                        MAChsGuaranteedBitRate
                                                                                  OPTIONAL,
    mACdPDU-Size-Index
                                        MACdPDU-Size-IndexList,
    rLC-Mode
                                        RLC-Mode,
    iE-Extensions
                                         ProtocolExtensionContainer { { PriorityQueue-InfoItem-to-Add-ExtIEs } } 
                                                                                                                                  OPTIONAL,
PriorityQueue-InfoItem-to-Add-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
                                         CRITICALITY reject
 ID id-MaximumMACdPDU-SizeExtended
                                                                 EXTENSION MAC-PDU-SizeExtended
                                                                                                                      PRESENCE optional | |
{ ID id-DL-RLC-PDU-Size-Format
                                                                                                           PRESENCE optional },
                                             CRITICALITY ignore
                                                                                 DL-RLC-PDU-Size-Format
                                                                     EXTENSION
PriorityQueue-InfoItem-to-Modify ::= SEQUENCE {
    priorityQueue-Id
                                         PriorityQueue-Id,
    schedulingPriorityIndicator
                                         SchedulingPriorityIndicator
                                                                                  OPTIONAL,
    <del>+</del> 1
                                        т1
                                                                                  OPTIONAL,
    discardTimer
                                        DiscardTimer
                                                                                  OPTIONAL,
    mAC-hsWindowSize
                                        MAC-hsWindowSize
                                                                                  OPTIONAL,
    mAChsGuaranteedBitRate
                                        MAChsGuaranteedBitRate
                                                                                  OPTIONAL,
                                        MACdPDU-Size-IndexList-to-Modify
    mACdPDU-Size-Index-to-Modify
                                                                                              OPTIONAL,
```

```
ProtocolExtensionContainer { { PriorityQueue-InfoItem-to-Modify-ExtIEs } } }
    iE-Extensions
                                                                                                                                        OPTIONAL,
PriorityOueue-InfoItem-to-Modify-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
 ID id-MaximumMACdPDU-SizeExtended
                                        CRITICALITY reject
                                                                                                                     PRESENCE optional }
                                                                EXTENSION
                                                                            MAC-PDU-SizeExtended
{ ID id-DL-RLC-PDU-Size-Format.
                                        CRITICALITY ignore
                                                                            DL-RLC-PDU-Size-Format
                                                                                                          PRESENCE optional },
                                                                EXTENSION
PriorityQueue-InfoList-to-Modify-Unsynchronised ::= SEQUENCE (SIZE (0..maxNrOfPrioQueues)) OF PriorityQueue-InfoItem-to-Modify-Unsynchronised
PriorityQueue-InfoItem-to-Modify-Unsynchronised ::= SEQUENCE {
    priorityQueueId
                                        PriorityOueue-Id,
    schedulingPriorityIndicator
                                        SchedulingPriorityIndicator
                                                                                                                     OPTIONAL,
    discardTimer
                                        DiscardTimer
                                                                                                                     OPTIONAL,
    mAChsGuaranteedBitRate
                                        MAChsGuaranteedBitRate
                                                                                                                     OPTIONAL,
    iE-Extensions
                                        ProtocolExtensionContainer { { PriorityOueue-InfoItem-to-Modify-Unsynchronised-ExtIEs}
    OPTIONAL,
PriorityQueue-InfoItem-to-Modify-Unsynchronised-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
PropagationDelay
                            ::= INTEGER (0..255)
ProvidedInformation ::= SEQUENCE {
                           MBMSChannelTypeInfo
    mBMSChannelTypeInfo
                                                        OPTIONAL.
    mBMSPreferredFreqLayerInfo MBMSPreferredFreqLayerInfo
                                    ProtocolExtensionContainer { { ProvideInformation-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
ProvideInformation-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-UpPCH-InformationList-LCRTDD
                                            CRITICALITY ignore EXTENSION UpPCH-InformationList-LCRTDD
                                                                                                         PRESENCE optional |
    -- Applicable to 1.28Mcps TDD only
    { ID id-ANRReportIndication
                                                                                                          PRESENCE optional },
                                            CRITICALITY ignore EXTENSION ANRReportIndication
UppCH-InformationList-LCRTDD ::= SEQUENCE (SIZE (0.. maxFrequencyinCell)) OF ProtocolIE-Single-Container {{ UppCH-InformationItemIE-LCRTDD }}
UpPCH-InformationItemIE-LCRTDD RNSAP-PROTOCOL-IES ::= {
    { ID
           id-UpPCH-InformationItem-LCRTDD CRITICALITY ignore TYPE UpPCH-InformationItem-LCRTDD
                                                                                                                     PRESENCE mandatory },
    . . .
UpPCH-InformationItem-LCRTDD ::= SEQUENCE
    uARFCNforNt
                            UARFCN
                                                    OPTIONAL,
    uPPCHPositionLCR
                            UPPCHPositionLCR
                                                    OPTIONAL,
    iE-Extensions
                            ProtocolExtensionContainer { { UpPCH-InformationItem-LCRTDD-ExtIEs} }
                                                                                                                         OPTIONAL,
    . . .
```

```
UpPCH-InformationItem-LCRTDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
PunctureLimit
                           ::= INTEGER (0..15)
-- 0: 40%; 1: 44%; ... 14: 96%; 15: 100
-- 0 is not applicable for E-DPCH
PTMCellList ::= SEQUENCE (SIZE (1..maxNrOfCells)) OF MBMSChannelTypeCellList
PTPCellList ::= SEQUENCE (SIZE (1..maxNrofCells)) OF MBMSChannelTypeCellList
-- 0
OE-Selector ::= ENUMERATED {
    selected.
    non-selected
Process-Memory-Size ::= ENUMERATED {
                                        hms800, hms1600, hms2400, hms3200, hms4000,
                                        hms4800, hms5600, hms6400, hms7200, hms8000,
                                        hms8800, hms9600, hms10400, hms11200, hms12000,
                                        hms12800, hms13600, hms14400, hms15200, hms16000,
                                        hms17600, hms19200, hms20800, hms22400, hms24000,
                                        hms25600, hms27200, hms28800, hms30400, hms32000,
                                        hms36000, hms40000, hms44000, hms48000, hms52000,
                                        hms56000, hms60000, hms64000, hms68000, hms72000,
                                        hms76000, hms80000, hms88000, hms96000, hms104000,
                                        hms112000, hms120000, hms128000, hms136000, hms144000,
                                        hms152000, hms160000, hms176000, hms192000, hms208000,
                                        hms224000, hms240000, hms256000, hms272000, hms288000,
                                        hms304000,...}
-- R
RABased ::= SEOUENCE {
    raiList
                        ProtocolExtensionContainer { {RABased-ExtIEs} } OPTIONAL,
    iE-Extensions
RABased-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RAI-List
           ::= SEQUENCE (SIZE (1..maxNrOfRAIs)) OF
    RAI
```

```
ReportInterval
                        ::= ENUMERATED {
                            ms250,
                            ms500.
                            ms1000,
                            ms2000,
                            ms3000,
                            ms4000,
                            ms6000,
                            ms12000,
                            ms16000,
                            ms20000,
                            ms24000,
                            ms32000,
                            ms64000,
                            ...}
                        ::= ENUMERATED { n1, n2, n4, n8, n16, n32, n64, infinity, ... }
ReportAmount
RAC
                    ::= OCTET STRING (SIZE(1))
RAI ::= SEQUENCE {
   pLMN-Identity
                        PLMN-Identity,
   lac
                        LAC,
    rAC
                        RAC
RANAP-EnhancedRelocationInformationRequest
                                                ::= BIT STRING
RANAP-EnhancedRelocationInformationResponse
                                                ::= BIT STRING
RANAP-RelocationInformation
                                ::= BIT STRING
Range-Correction-Rate ::= INTEGER (-127..127)
-- scaling factor 0.032 m/s
RateMatchingAttribute
                                ::= INTEGER (1..maxRateMatching)
RB-Identity
                                ::= INTEGER (0..31)
RB-Info ::= SEOUENCE (SIZE(1..maxNoOfRB)) OF RB-Identity
Received-Total-Wideband-Power-Value ::= Received-total-wide-band-power
Received-Total-Wideband-Power-Value-IncrDecrThres ::= INTEGER(0..620)
-- Unit dB Step 0.1dB
-- e.g. value 100 means 10dB
Reference-E-TFCI-Information ::= SEQUENCE (SIZE (1..maxNrOfRefETFCIs)) OF Reference-E-TFCI-Information-Item
Reference-E-TFCI-Information-Item ::= SEQUENCE {
    reference-E-TFCI
                                    E-TFCI,
    -- The following IE shall be ignored if id-Ext-Reference-E-TFCI-PO is present in Reference-E-TFCI-Information-Item-ExtIEs
    reference-E-TFCI-PO
                                    Reference-E-TFCI-PO,
    iE-Extensions
                                    ProtocolExtensionContainer { { Reference-E-TFCI-Information-Item-ExtIEs} }
                                                                                                                         OPTIONAL,
```

```
Reference-E-TFCI-Information-Item-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    -- The following IE shall be present if the ref E-TFCI power offset to be signalled exceeds maxNrOfRefETFCI-PO-QUANTSTEPs
   { ID id-Ext-Reference-E-TFCI-PO
                                       CRITICALITY reject
                                                                EXTENSION Ext-Reference-E-TFCI-PO
                                                                                                                 PRESENCE optional },
    . . .
Reference-E-TFCI-PO ::= INTEGER (0.. maxNrOfRefETFCI-PO-QUANTSTEPs)
RefTFCNumber ::= INTEGER (0..15)
Released-CN-Domain ::= CHOICE {
   pSDomain
    cSDomain
                           NULL,
   pS-CSDomain
                           NULL,
RepetitionLength
                           ::= INTEGER (1..63)
RepetitionPeriod ::= ENUMERATED {
   v1,
    v2.
    v4,
    v8,
    v16,
    v32,
    v64
RepetitionNumber0 ::= INTEGER (0..255)
RepetitionNumber1 ::= INTEGER (1..256)
ReportCharacteristics ::= CHOICE {
    onDemand
                       NULL,
    periodic
                       Periodic,
                       EventA,
    eventA
    eventB
                       EventB,
                       EventC,
    eventC
                        EventD,
    eventD
                        EventE,
    eventE
    eventF
                        EventF,
    extension-ReportCharacteristics
                                        Extension-ReportCharacteristics
Extension-ReportCharacteristics ::= ProtocolIE-Single-Container {{ Extension-ReportCharacteristicsIE }}
Extension-ReportCharacteristicsIE RNSAP-PROTOCOL-IES ::= {
    { ID id-OnModification CRITICALITY reject TYPE OnModification
                                                                        PRESENCE mandatory } |
```

```
{ ID id-EventH
                            CRITICALITY reject TYPE EventH
                                                                        PRESENCE mandatory }
ReportPeriodicity ::= CHOICE {
                            INTEGER (1..6000,...),
-- The Report Periodicity gives the reporting periodicity in number of 10 ms periods.
-- E.g. value 6000 means 60000ms (i.e. 1min)
-- Unit ms, Step 10ms
    min
                    INTEGER (1..60,...),
-- Unit min, Step 1min
RequestedDataValue ::= SEOUENCE {
    qA-AccessPointPositionwithAltitude
                                                GA-AccessPointPositionwithOptionalAltitude OPTIONAL,
    i DDI.Darameters
                                                IPDLParameters
                                                                                            OPTIONAL,
    dGPSCorrections
                                                DGPSCorrections
                                                                                            OPTIONAL,
    gPS-NavigationModel-and-TimeRecovery
                                                GPS-NavigationModel-and-TimeRecovery
                                                                                            OPTIONAL,
    qPS-Ionospheric-Model
                                                GPS-Ionospheric-Model
                                                                                            OPTIONAL,
    qPS-UTC-Model
                                                GPS-UTC-Model
                                                                                            OPTIONAL,
    gPS-Almanac
                                                GPS-Almanac
                                                                                            OPTIONAL,
    gPS-RealTime-Integrity
                                                GPS-RealTime-Integrity
                                                                                            OPTIONAL,
    aPS-RX-POS
                                                GPS-RX-POS
                                                                                            OPTIONAL,
    sFNSFN-GA-AccessPointPosition
                                                GA-AccessPointPositionwithOptionalAltitude OPTIONAL,
                                                ProtocolExtensionContainer { { RequestedDataValue-ExtIEs} }
    iE-Extensions
                                                                                                                        OPTIONAL,
RequestedDataValue-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-Cell-Capacity-Class-Value
                                                    CRITICALITY ignore EXTENSION Cell-Capacity-Class-Value
                                                                                                                                PRESENCE optional }
     ID id-NACC-Related-Data
                                                    CRITICALITY ignore EXTENSION NACC-Related-Data
                                                                                                                                PRESENCE optional }
     ID id-MBMS-Bearer-Service-Full-Address
                                                    CRITICALITY ignore EXTENSION MBMS-Bearer-Service-Full-Address
                                                                                                                                PRESENCE optional }
     ID id-Inter-Frequency-Cell-Information
                                                    CRITICALITY ignore EXTENSION Inter-Frequency-Cell-Information
                                                                                                                                PRESENCE optional
     ID id-GANSS-Common-Data
                                                    CRITICALITY ignore EXTENSION GANSS-Common-Data
                                                                                                                                PRESENCE optional
     ID id-GANSS-Generic-Data
                                                    CRITICALITY ignore EXTENSION GANSS-Generic-Data
                                                                                                                                PRESENCE optional
                                                    CRITICALITY ignore EXTENSION Counting-Information
                                                                                                                                PRESENCE optional |
     ID id-Counting-Information
     ID id-Transmission-Mode-Information
                                                    CRITICALITY ignore EXTENSION Transmission-Mode-Information
                                                                                                                                PRESENCE optional }
     ID id-MBMS-Neighbouring-Cell-Information
                                                    CRITICALITY ignore EXTENSION MBMS-Neighbouring-Cell-Information
                                                                                                                                PRESENCE optional }
                                                    CRITICALITY ignore EXTENSION RLC-Sequence-Number
     ID id-RLC-Sequence-Number
                                                                                                                                PRESENCE optional }
     ID id-ANR-Cell-Information
                                                    CRITICALITY ignore EXTENSION ANR-Cell-Information
                                                                                                                                PRESENCE optional },
RequestedDataValueInformation ::= CHOICE {
    informationAvailable
                                InformationAvailable,
    informationNotAvailable
                                InformationNotAvailable
RestrictionStateIndicator ::= ENUMERATED {
    cellNotResevedForOperatorUse,
    cellResevedForOperatorUse,
    . . .
```

```
RL-ID
                  ::= INTEGER (0..31)
RL-Set-ID
                  ::= INTEGER (0..31)
RL-Specific-DCH-Info ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF RL-Specific-DCH-Info-Item
RL-Specific-DCH-Info-Item ::= SEQUENCE {
   dCH-id
                      DCH-ID,
   bindingID
                      BindingID OPTIONAL,
   -- Shall be ignored if bearer establishment with ALCAP.
   transportLayerAddress TransportLayerAddress
   -- Shall be ignored if bearer establishment with ALCAP.
                      iE-Extensions
   . . .
RL-Specific-DCH-Info-Item-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    PRESENCE optional
   }, -- FDD only
   . . .
RL-Specific-EDCH-Information ::= SEQUENCE {
   rL-Specific-EDCH-Info RL-Specific-EDCH-Info,
   e-AGCH-PowerOffset
                      E-AGCH-PowerOffset
                                                                                  OPTIONAL,
   e-RGCH-PowerOffset
                      E-RGCH-PowerOffset
                                                                                  OPTIONAL,
   e-HICH-PowerOffset
                      E-HICH-PowerOffset
                                                                                  OPTIONAL,
   iE-Extensions
                      OPTIONAL,
RL-Specific-EDCH-Information-Item-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
RL-Specific-EDCH-Info ::= SEOUENCE (SIZE (1..maxNrOfEDCHMACdFlows)) OF RL-Specific-EDCH-InfoItem
RL-Specific-EDCH-InfoItem ::= SEQUENCE {
   eDCH-MACdFlow-ID
                               EDCH-MACdFlow-ID,
   bindingID
                               BindingID
                                               OPTIONAL,
   -- Shall be ignored if bearer establishment with ALCAP.
   transportLayerAddress
                               TransportLayerAddress
                                                      OPTIONAL,
   -- Shall be ignored if bearer establishment with ALCAP.
   iE-Extensions
                      ProtocolExtensionContainer { RL-Specific-EDCH-Info-Item-ExtIEs} } OPTIONAL,
   . . .
RL-Specific-EDCH-Info-Item-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
    PRESENCE optional
   }, -- FDD only
```

```
RLC-Mode
           ::= ENUMERATED {
   rLC-AM.
   rLC-UM,
DL-RLC-PDU-Size-Format ::= ENUMERATED {
    fixed-RLC-PDU-Size,
    flexible-RLC-PDU-Size,
RLC-Sequence-Number
                     ::= INTEGER (0..127)
RNC-ID
                      ::= INTEGER (0..4095)
RNTI-Allocation-Indicator ::= ENUMERATED {
    true
Round-Trip-Time-IncrDecrThres ::= INTEGER(0..32766)
Round-Trip-Time-Value ::= INTEGER(0..32767)
-- According to mapping in TS 25.133 [23]
RSCP-Value ::= INTEGER (0..127)
-- According to mapping in TS 25.123 [24]
RSCP-Value-IncrDecrThres ::= INTEGER (0..126)
Received-total-wide-band-power
                                           ::= INTEGER (0..621)
-- According to mapping in TS 25.133 [23]
RT-Load-Value-IncrDecrThres ::= INTEGER(0..100)
RT-Load-Value ::= INTEGER(0..100)
RTLoadValue ::= SEOUENCE {
       uplinkRTLoadValue
                               INTEGER(0..100),
       downlinkRTLoadValue
                               INTEGER(0..100)
RxTimingDeviationForTA
                                  ::= INTEGER (0..127)
-- As specified in TS 25.435 [5], ch. 6.2.7.6
-- For 1.28Mcps TDD this IE must be set to 0.
RxTimingDeviationForTAext
                             ::= INTEGER (0..511)
-- As specified in TS 25.435 [5] [3.84 Mcps TDD only]
RxTimingDeviationForTA768
                                       ::= INTEGER (0.. 1023)
-- As specified in TS 25.435 [5]
Rx-Timing-Deviation-Value ::= INTEGER (0..8191)
--According to mapping in TS 25.123 [24][3.84Mcps TDD only]
```

```
Rx-Timing-Deviation-Value-ext ::= INTEGER (0..32767)
--According to mapping in TS 25.123 [24][3.84Mcps TDD only]
Rx-Timing-Deviation-Value-LCR ::= INTEGER (0..511)
--According to mapping in TS 25.123 [24][1.28Mcps TDD only]
Rx-Timing-Deviation-Value-768 ::= INTEGER (0..65535)
--According to mapping in TS 25.123 [24][7.68Mcps TDD only]
RefBeta ::= INTEGER (-15..16)
-- S
SAC
                    ::= OCTET STRING (SIZE (2))
SAI ::= SEQUENCE {
    pLMN-Identity
                        PLMN-Identity,
    lac
                        LAC,
                        SAC,
    sAC
    iE-Extensions
                        ProtocolExtensionContainer { {SAI-ExtIEs} } OPTIONAL
SAI-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
SAT-ID ::= INTEGER (0..63)
                            ::= INTEGER (0..6)
SCH-TimeSlot
ScaledAdjustmentRatio
                                ::= INTEGER(0..100)
-- AdjustmentRatio = ScaledAdjustmentRatio / 100
SchedulingInformation
                                ::= ENUMERATED {
   included,
   not-included
SecondaryServingCells ::= SEQUENCE (SIZE (1..maxNrOfHSDSCH-1)) OF SecondaryServingCellsItem
SecondaryServingCellsItem ::= SEQUENCE {
    secondaryC-ID
    numSecondaryHS-SCCH-Codes
                                    NumHS-SCCH-Codes
                                                            OPTIONAL,
    sixtyfourQAM-UsageAllowedIndicator
                                            SixtyfourQAM-UsageAllowedIndicator
                                                                                     OPTIONAL,
    iE-Extensions
                                                    ProtocolExtensionContainer { { SecondaryServingCellsItem-ExtIEs} }
    OPTIONAL,
    . . .
SecondaryServingCellsItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
{ID id-MIMO-ActivationIndicator
                                                            CRITICALITY ignore EXTENSION MIMO-ActivationIndicator
                                                                                                                                 PRESENCE optional }
{ID id-EDCH-Indicator
                                                            CRITICALITY ignore EXTENSION NULL
                                                                                                                                 PRESENCE optional }
```

```
{ID id-power-offset-for-S-CPICH-for-MIMO-Request-Indicator CRITICALITY ignore EXTENSION PowerOffsetForSecondaryCPICHforMIMORequestIndicator
    PRESENCE optional }
{ID id-OrdinalNumberOfFrequency
                                                            CRITICALITY ignore EXTENSION OrdinalNumberOfFrequency
                                                                                                                                 PRESENCE optional },
Secondary-CCPCH-Info-TDD::= SEQUENCE {
   dl-TFCS
                                            TFCS,
    tFCI-Coding
                                            TFCI-Coding,
    secondary-CCPCH-TDD-InformationList
                                            Secondary-CCPCH-TDD-InformationList,
    fACH-InformationList
                                            FACH-InformationList,
    pCH-InformationList
                                            PCH-InformationList,
    iE-Extensions
                                            ProtocolExtensionContainer { { Secondary-CCPCH-Info-TDD-ExtIEs} } OPTIONAL,
Secondary-CCPCH-Info-TDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Secondary-CPICH-Information ::= SEQUENCE {
  dl-ScramblingCode
                                            DL-ScramblingCode,
   fDD-DL-ChannelisationCodeNumber
                                            FDD-DL-ChannelisationCodeNumber,
  iE-Extensions
                                            ProtocolExtensionContainer { { Secondary-CPICH-Information-ExtIEs} } OPTIONAL,
    . . .
Secondary-CPICH-Information-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
Secondary-CPICH-Information-Change ::= CHOICE {
                                    Secondary-CPICH-Information,
new-secondary-CPICH
secondary-CPICH-shall-not-be-used NULL.
Secondary-LCR-CCPCH-Info-TDD::= SEQUENCE {
    dl-TFCS
                                            TFCS,
    tFCI-Coding
                                            TFCI-Coding,
    secondary-LCR-CCPCH-TDD-InformationList Secondary-LCR-CCPCH-TDD-InformationList,
    fACH-InformationList
                                            FACH-InformationList,
    pCH-InformationList
                                            PCH-InformationList,
   iE-Extensions
                                            ProtocolExtensionContainer { { Secondary-LCR-CCPCH-Info-TDD-ExtIEs} } OPTIONAL,
Secondary-LCR-CCPCH-Info-TDD-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Secondary-CCPCH-Info-TDD768::= SEQUENCE {
    dl-TFCS
                                            TFCS,
```

```
tFCI-Coding
                                            TFCI-Coding,
    secondary-CCPCH-TDD-InformationList768
                                                Secondary-CCPCH-TDD-InformationList768,
    fACH-InformationList
                                            FACH-InformationList.
    pCH-InformationList
                                            PCH-InformationList,
    iE-Extensions
                                            ProtocolExtensionContainer { { Secondary-CCPCH-Info-TDD768-ExtIEs} } OPTIONAL,
Secondary-CCPCH-Info-TDD768-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
Secondary-CCPCH-TDD-InformationList ::= SEQUENCE (SIZE(0.. maxNrOfSCCPCHs)) OF Secondary-CCPCH-TDD-InformationItem
Secondary-CCPCH-TDD-InformationItem ::= SEOUENCE {
    timeSlot
                                    TimeSlot,
    midambleShiftAndBurstType
                                    MidambleShiftAndBurstType,
    tFCI-Presence
                                    TFCI-Presence,
    secondary-CCPCH-TDD-Code-Information
                                                         Secondary-CCPCH-TDD-Code-Information,
    tDD-PhysicalChannelOffset
                                    TDD-PhysicalChannelOffset,
    repetitionLength
                                    RepetitionLength,
    repetitionPeriod
                                    RepetitionPeriod,
                                    ProtocolExtensionContainer { { Secondary-CCPCH-TDD-InformationItem-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
Secondary-CCPCH-TDD-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Secondary-LCR-CCPCH-TDD-InformationList ::= SEOUENCE (SIZE(0.. maxNrOfSCCPCHs)) OF Secondary-LCR-CCPCH-TDD-InformationItem
Secondary-LCR-CCPCH-TDD-InformationItem ::= SEQUENCE {
    timeSlotLCR
                                                TimeSlotLCR,
   midambleShiftLCR
                                                MidambleShiftLCR,
    tFCI-Presence
                                                TFCI-Presence,
    secondary-LCR-CCPCH-TDD-Code-Information
                                                Secondary-LCR-CCPCH-TDD-Code-Information,
    tDD-PhysicalChannelOffset
                                                TDD-PhysicalChannelOffset,
    repetitionLength
                                                RepetitionLength,
    repetitionPeriod
                                                RepetitionPeriod,
                                                ProtocolExtensionContainer { { Secondary-LCR-CCPCH-TDD-InformationItem-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
Secondary-LCR-CCPCH-TDD-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Secondary-CCPCH-TDD-InformationList768 ::= SEQUENCE (SIZE(0.. maxNrOfSCCPCHs768)) OF Secondary-CCPCH-TDD-InformationItem768
Secondary-CCPCH-TDD-InformationItem768 ::= SEQUENCE {
    timeSlot
                                    TimeSlot,
    midambleShiftAndBurstType768
                                        MidambleShiftAndBurstType768,
    tFCI-Presence
                                    TFCI-Presence,
```

```
secondary-CCPCH-TDD-Code-Information768
                                                        Secondary-CCPCH-TDD-Code-Information768,
    tDD-PhysicalChannelOffset
                                    TDD-PhysicalChannelOffset,
    repetitionLength
                                    RepetitionLength,
    repetitionPeriod
                                    RepetitionPeriod,
    iE-Extensions
                                    ProtocolExtensionContainer { Secondary-CCPCH-TDD-InformationItem768-ExtIEs} } OPTIONAL,
Secondary-CCPCH-TDD-InformationItem768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Secondary-CCPCH-TDD-Code-Information ::= SEQUENCE ( SIZE (1..maxNrOfSCCPCHs)) OF Secondary-CCPCH-TDD-Code-InformationItem
Secondary-CCPCH-TDD-Code-InformationItem ::= SEOUENCE {
    tDD-ChannelisationCode
                                    TDD-ChannelisationCode,
                                    ProtocolExtensionContainer { {Secondary-CCPCH-TDD-Code-InformationItem-ExtIEs} } OPTIONAL,
   iE-Extensions
Secondary-CCPCH-TDD-Code-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Secondary-LCR-CCPCH-TDD-Code-Information ::= SEQUENCE ( SIZE (1..maxNrOfSCCPCHs)) OF Secondary-LCR-CCPCH-TDD-Code-InformationItem
Secondary-LCR-CCPCH-TDD-Code-InformationItem ::= SEQUENCE {
    tDD-ChannelisationCodeLCR
                                    TDD-ChannelisationCodeLCR,
    s-CCPCH-TimeSlotFormat-LCR
                                    TDD-DL-DPCH-TimeSlotFormat-LCR,
                                    ProtocolExtensionContainer { {Secondary-LCR-CCPCH-TDD-Code-InformationItem-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
Secondary-LCR-CCPCH-TDD-Code-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Secondary-CCPCH-TDD-Code-Information768 ::= SEOUENCE ( SIZE (1..maxNrOfSCCPCHs768)) OF Secondary-CCPCH-TDD-Code-InformationItem768
Secondary-CCPCH-TDD-Code-InformationItem768 ::= SEOUENCE {
    tDD-ChannelisationCode768
                                        TDD-ChannelisationCode768,
                                    ProtocolExtensionContainer { Secondary-CCPCH-TDD-Code-InformationItem768-ExtIEs} } OPTIONAL,
   iE-Extensions
    . . .
Secondary-CCPCH-TDD-Code-InformationItem768-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
Secondary-Serving-Cell-List ::= SEQUENCE {
    possible-Secondary-Serving-Cell-List
                                                                Possible-Secondary-Serving-Cell-List,
    iE-Extensions
                                ProtocolExtensionContainer { { Secondary-Serving-Cell-List-ExtIEs } }
                                                                                                                 OPTIONAL,
    . . .
```

```
Secondary-Serving-Cell-List-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    {ID id-Multicell-EDCH-Restriction
                                            CRITICALITY ignore
                                                                    EXTENSION Multicell-EDCH-Restriction
                                                                                                                 PRESENCE optional },
    -- This IE shall never be included. If received it shall be ignored.
-- "maxNrOfHSDSCH-1" represents the maximum number of possible secondary serving cells for a Multi Cell/Dual-Band capable cell when it applies to
the range of "Possible-Secondary-Serving-Cell-List".
Possible-Secondary-Serving-Cell-List ::= SEQUENCE (SIZE (1..maxNrOfHSDSCH-1)) OF Possible-Secondary-Serving-Cell
Possible-Secondary-Serving-Cell ::= SEQUENCE {
    c-ID
    iE-Extensions
                                ProtocolExtensionContainer { { Possible-Secondary-Serving-Cell-ExtIEs } }
                                                                                                                                OPTIONAL,
Possible-Secondary-Serving-Cell-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    {ID id-Multicell-EDCH-Restriction
                                            CRITICALITY ignore EXTENSION Multicell-EDCH-Restriction
                                                                                                          PRESENCE optional },
    . . .
SecondInterleavingMode ::= ENUMERATED {
    frame-related,
    timeslot-related,
Secondary-UL-Frequency-Activation-State ::= ENUMERATED {
    activated,
    deactivated,
Seed ::= INTEGER (0..63)
Service-ID ::= OCTET STRING (SIZE (3))
SetsOfHS-SCCH-Codes ::= SEQUENCE (SIZE (1..maxNrOfHSDSCH)) OF SetsOfHS-SCCH-CodesItem
SetsOfHS-SCCH-CodesItem ::= SEQUENCE {
    hS-SCCH-PreconfiguredCodes
                                    HS-SCCH-PreconfiguredCodes,
    hSDSCH-RNTI
                        HSDSCH-RNTI,
   hSPDSCH-and-HSSCCH-ScramblingCode
                                            DL-ScramblingCode,
    sixtyfourQAM-DL-SupportIndicator
                                            SixtyfourQAM-DL-SupportIndicator
                                                                                     OPTIONAL,
    sixtyfourQAM-DL-UsageIndicator
                                        SixtyfourQAM-DL-UsageIndicator
                                                                            OPTIONAL,
    hSDSCH-TBSizeTableIndicator
                                    HSDSCH-TBSizeTableIndicator
                                                                            OPTIONAL,
    iE-Extensions
                                    ProtocolExtensionContainer { { SetsOfHS-SCCH-CodesItem-ExtIEs} } OPTIONAL,
SetsOfHS-SCCH-CodesItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
{ID id-MIMO-InformationResponse
                                                CRITICALITY ignore EXTENSION MIMO-InformationResponse
                                                                                                                         PRESENCE optional } |
{ID id-power-offset-for-S-CPICH-for-MIMO
                                                CRITICALITY ignore EXTENSION PowerOffsetForSecondaryCPICHforMIMO
                                                                                                                         PRESENCE optional }
{ID id-Measurement-Power-Offset
                                                    CRITICALITY ignore EXTENSION Measurement-Power-Offset
                                                                                                                                PRESENCE optional },
Setup-Or-ConfigurationChange-Or-Removal-Of-EDCH-On-secondary-UL-Frequency::= CHOICE {
                            Additional-EDCH-Setup-Info,
    configurationChange
                            Additional-EDCH-Cell-Information-ConfigurationChange-List,
    removal
                            Additional-EDCH-Cell-Information-Removal-List,
SFN ::= INTEGER (0..4095)
SFNSFN-FDD ::= INTEGER(0..614399)
SFNSFN-TDD ::= INTEGER(0..40961)
SFNSFN-TDD768 ::= INTEGER(0..81923)
GA-AccessPointPositionwithOptionalAltitude ::= SEQUENCE
    geographicalCoordinate
                                                GeographicalCoordinate,
    altitudeAndDirection
                                                GA-AltitudeAndDirection OPTIONAL,
                                                ProtocolExtensionContainer { { GA-AccessPointPositionwithOptionalAltitude-ExtIEs} } OPTIONAL,
    iE-Extensions
GA-AccessPointPositionwithOptionalAltitude-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
SFNSFNChangeLimit ::= INTEGER (1..256)
-- Unit chip, Step 1/16 chip, Range 1/16..16 chip
SFNSFNDriftRate ::= INTEGER (-100..100)
-- Unit chip/s, Step 1/256 chip/s, Range -100/256..+100/256 chip/s
SFNSFNDriftRateOuality ::= INTEGER (0..100)
-- Unit chip/s, Step 1/256 chip/s, Range 0..100/256 chip/s
SFNSFNMeasurementThresholdInformation::= SEQUENCE {
    sFNSFNChangeLimit
                                        SFNSFNChangeLimit
                                                                            OPTIONAL,
    predictedSFNSFNDeviationLimit
                                        PredictedSFNSFNDeviationLimit
                                                                            OPTIONAL,
   iE-Extensions
                                    ProtocolExtensionContainer { { SFNSFNMeasurementThresholdInformation-ExtIEs} }
                                                                                                                                OPTIONAL,
SFNSFNMeasurementThresholdInformation-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
SFNSFNMeasurementValueInformation ::= SEQUENCE {
```

```
successfull Neighbouring Cell SFNSFNObserved Time Difference Measurement Information
                                                                                     SEQUENCE (SIZE(1..maxNrOfMeasNCell)) OF
       SEQUENCE {
           uC-ID
                       UC-ID.
           sFNSFNValue
                                      SFNSFNValue,
           sFNSFNOuality
                                      SFNSFNOuality
                                                                     OPTIONAL.
           sFNSFNDriftRate
                                      SFNSFNDriftRate,
           sFNSFNDriftRateQuality
                                      SFNSFNDriftRateOuality
                                                                 OPTIONAL.
           sFNSFNTimeStampInformation SFNSFNTimeStampInformation,
           iE-Extensions
                                      ProtocolExtensionContainer { {
SuccessfullNeighbouringCellSFNSFNObservedTimeDifferenceMeasurementInformationItem-ExtIEs} }
                                                                                             OPTIONAL,
       },
   unsuccessfull Neighbouring Cell SFNSFNObserved Time Difference Measurement Information \\
                                                                                     SEOUENCE (SIZE(0..maxNrOfMeasNCell-1)) OF
       SEOUENCE {
           uC-ID
                       UC-ID,
           iE-Extensions
                              ProtocolExtensionContainer { { UnsuccessfullNeighbouringCellSFNSFNObservedTimeDifferenceMeasurementInformationItem-
ExtIEs } }
               OPTIONAL,
                       iE-Extensions
                                                                                                            OPTIONAL,
SFNSFNMeasurementValueInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
SuccessfullNeighbouringCellSFNSFNObservedTimeDifferenceMeasurementInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UnsuccessfullNeighbouringCellSFNSFNObservedTimeDifferenceMeasurementInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::=
SFNSFNOuality ::= INTEGER (0..255)
-- Unit chip, Step 1/16 chip, Range 0.. 255/16 chip
SFNSFNTimeStampInformation ::= CHOICE {
    sFNSFNTimeStamp-FDD
                           SFN,
   sFNSFNTimeStamp-TDD
                          SFNSFNTimeStamp-TDD,
    . . .
SFNSFNTimeStamp-TDD::= SEQUENCE {
   sFN
                       SFN,
    timeSlot
                       TimeSlot,
                                   ProtocolExtensionContainer { { SFNSFNTimeStamp-ExtIEs}} OPTIONAL,
   iE-Extensions
```

```
SFNSFNTimeStamp-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
SFNSFNValue ::= CHOICE {
    sFNSFN-FDD
                    SFNSFN-FDD,
    sFNSFN-TDD
                    SFNSFN-TDD,
                                    -- LCR & HCR TDD
    sFNSFN-TDD768
                        SFNSFN-TDD768
SID ::= INTEGER (0..maxNrOfPDUIndexes-1)
Single-Stream-MIMO-ActivationIndicator ::= NULL
Single-Stream-MIMO-Mode-Indicator ::= ENUMERATED {
   activate,
    deactivate
SIR-Error-Value
                       ::= INTEGER (0..125)
SIR-Error-Value-IncrDecrThres
                                        ::= INTEGER (0..124)
SIR-Value
                        ::= INTEGER (0..63)
-- According to mapping in TS 25.215 [11]/TS 25.225 [14]
SIR-Value-IncrDecrThres ::= INTEGER (0..62)
SixteenQAM-UL-Operation-Indicator ::= ENUMERATED {
    activate,
    deactivate
SixtyfourQAM-UsageAllowedIndicator ::= ENUMERATED {
    allowed,
    not-allowed
SixtyfourQAM-DL-SupportIndicator ::= ENUMERATED {
    sixtyfourQAM-DL-supported,
    sixtyfourQAM-DL-not-supported
SixtyfourQAM-DL-UsageIndicator ::= ENUMERATED {
    sixtyfourQAM-DL-used,
    sixtyfourQAM-DL-not-used
```

```
SignatureSequenceGroupIndex ::= INTEGER (0..19)
SNA-Information ::= SEQUENCE {
   pLMN-Identity PLMN-Identity,
  listOfSNAs
                       ListOfSNAs
                                                                        OPTIONAL,
  iE-Extensions
                       ProtocolExtensionContainer { { SNA-Information-ExtIEs} } OPTIONAL,
SNA-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
ListOfSNAs ::= SEQUENCE (SIZE (1.. maxNrOfSNAs)) OF SNACode
SNACode ::= INTEGER (0..65535)
SourceID ::= SAI
SpecialBurstScheduling ::= INTEGER (1..256)
SpeechVersion::= BIT STRING (SIZE (4))
S-RNTI
                       ::= INTEGER (0..1048575)
-- From 0 to 2^20-1
S-RNTI-Group
                        ::= SEQUENCE {
                            S-RNTI,
    sRNTI-BitMaskIndex
                            ENUMERATED {
       bl,
       b2,
       b3,
       b4,
        b5,
        b6,
        b7,
        b8,
        b9,
       b10,
       b11,
       b12,
       b13,
       b14,
       b15,
       b16,
       b17,
       b18,
       b19,...
SRB-Delay ::= INTEGER(0..7,...)
```

```
SSDT-SupportIndicator ::= ENUMERATED {
    not-Used-sSDT-supported,
    sSDT-not-supported
Standalone-Midamble-Channel-Indicator ::= ENUMERATED {
    used.
    not-used
Status-Flag ::= ENUMERATED {
    activate,
    deactivate
STTD-SupportIndicator ::= ENUMERATED {
    sTTD-Supported,
    sTTD-not-Supported
Support-8PSK ::= ENUMERATED {
    v8PSK-Supported
Support-PLCCH ::= ENUMERATED {
    vPLCCH-Supported
Support-of-Dynamic-DTXDRX-Related-HS-SCCH-Order ::= ENUMERATED {
    supported,
    not-supported
SyncCase ::= INTEGER (1..2,...)
SynchronisationConfiguration ::= SEQUENCE {
    n-INSYNC-IND
                  INTEGER (1..256),
                         INTEGER (1..256),
    n-OUTSYNC-IND
    t-RLFAILURE
                          INTEGER (0..255),
-- Unit seconds, Range Os .. 25.5s, Step 0.1s
    iE-Extensions
                         ProtocolExtensionContainer { { SynchronisationConfiguration-ExtIEs} }
                                                                                                        OPTIONAL,
    . . .
SynchronisationConfiguration-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
SYNC-UL-ProcParameters ::= SEQUENCE {
    maxSYNC-UL-transmissions
                                    ENUMERATED {v1, v2, v4, v8, ...},
                                    INTEGER (0..3, ...),
    powerRampStep
```

```
-- T
T1 ::= ENUMERATED \{v10, v20, v30, v40, v50, v60, v70, v80, v90, v100, v120, v140, v160, v200, v300, v400, ...\}
TAC ::= OCTET STRING (SIZE (2))
TargetID ::= CGI
TDD-AckNack-Power-Offset ::= INTEGER (-7..8,...)
-- Unit dB, Range -7dB .. +8dB, Step 1dB
TDD-ChannelisationCode
                                 ::= ENUMERATED {
    chCodeldiv1,
    chCode2div1,
    chCode2div2,
    chCode4div1,
    chCode4div2,
    chCode4div3,
    chCode4div4,
    chCode8div1,
    chCode8div2,
    chCode8div3,
    chCode8div4,
    chCode8div5,
    chCode8div6,
    chCode8div7,
    chCode8div8,
    chCode16div1,
    chCode16div2,
    chCode16div3,
    chCode16div4,
    chCode16div5.
    chCode16div6,
    chCode16div7,
    chCode16div8,
    chCode16div9,
    chCode16div10,
    chCode16div11,
    chCode16div12,
    chCode16div13,
    chCode16div14,
    chCode16div15,
    chCode16div16,
    . . .
TDD-ChannelisationCode768
                                      ::= ENUMERATED {
    chCodeldiv1,
    chCode2div1,
    chCode2div2,
    chCode4div1,
```

```
chCode4div2,
chCode4div3,
chCode4div4,
chCode8div1,
chCode8div2,
chCode8div3,
chCode8div4,
chCode8div5,
chCode8div6,
chCode8div7,
chCode8div8,
chCode16div1,
chCode16div2,
chCode16div3,
chCode16div4,
chCode16div5,
chCode16div6,
chCodel6div7,
chCode16div8,
chCode16div9,
chCode16div10,
chCode16div11,
chCode16div12,
chCode16div13,
chCode16div14,
chCode16div15,
chCode16div16,
chCode32div1,
chCode32div2,
chCode32div3,
chCode32div4,
chCode32div5,
chCode32div6,
chCode32div7,
chCode32div8.
chCode32div9,
chCode32div10,
chCode32div11,
chCode32div12,
chCode32div13,
chCode32div14,
chCode32div15,
chCode32div16,
chCode32div17,
chCode32div18,
chCode32div19,
chCode32div20,
chCode32div21,
chCode32div22,
chCode32div23,
chCode32div24,
chCode32div25,
chCode32div26,
chCode32div27,
```

```
chCode32div28,
    chCode32div29.
    chCode32div30.
    chCode32div31,
    chCode32div32,
TDD-ChannelisationCodeLCR ::= SEQUENCE {
    tDD-ChannelisationCode
                                    TDD-ChannelisationCode.
    modulation
                                    Modulation, -- Modulation options for 1.28Mcps TDD in contrast to 3.84Mcps TDD or 7.68Mcps TDD
    . . .
TDD-DCHs-to-Modify ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF TDD-DCHs-to-ModifyItem
TDD-DCHs-to-ModifyItem ::= SEQUENCE {
    ul-FP-Mode
                                        UL-FP-Mode OPTIONAL,
    toAWS
                                        ToAWS
                                                    OPTIONAL,
                                                    OPTIONAL,
    t.oAWE
                                        ToAWE
    transportBearerRequestIndicator
                                        TransportBearerRequestIndicator,
    dCH-SpecificInformationList
                                        TDD-DCHs-to-ModifySpecificInformationList,
    iE-Extensions
                                        ProtocolExtensionContainer { {TDD-DCHs-to-ModifyItem-ExtIEs} } OPTIONAL,
    . . .
TDD-DCHs-to-ModifyItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-TnlOos
                                        CRITICALITY
                                                        ignore
                                                                     EXTENSION
                                                                                TnlOos PRESENCE optional
                                                                                                                  },
    . . .
TDD-DCHs-to-ModifySpecificInformationList ::= SEQUENCE (SIZE (1..maxNrOfDCHs)) OF TDD-DCHs-to-ModifySpecificItem
TDD-DCHs-to-ModifySpecificItem ::= SEQUENCE {
   dCH-ID
                                    DCH-ID,
    ul-CCTrCH-ID
                                    CCTrCH-ID
                                                    OPTIONAL,
    dl-CCTrCH-ID
                                    CCTrCH-ID
                                                    OPTIONAL,
    ul-TransportformatSet
                                    TransportFormatSet OPTIONAL,
    dl-TransportformatSet
                                    TransportFormatSet OPTIONAL,
    allocationRetentionPriority
                                    AllocationRetentionPriority OPTIONAL,
    frameHandlingPriority
                                    FrameHandlingPriority OPTIONAL,
                                    ProtocolExtensionContainer { {TDD-DCHs-to-ModifySpecificItem-ExtIEs} } OPTIONAL,
    iE-Extensions
TDD-DCHs-to-ModifySpecificItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
      ID id-Guaranteed-Rate-Information
                                            CRITICALITY ignore EXTENSION Guaranteed-Rate-Information
                                                                                                                  PRESENCE optional
     ID id-TrafficClass
                                CRITICALITY ignore EXTENSION TrafficClass
                                                                                 PRESENCE optional },
    . . .
TDD-DL-Code-Information ::= SEQUENCE ( SIZE (1...maxNrOfDPCHs)) OF TDD-DL-Code-InformationItem
TDD-DL-Code-InformationItem ::= SEQUENCE {
```

```
dPCH-ID
                                    DPCH-ID,
    tDD-ChannelisationCode
                                    TDD-ChannelisationCode,
   iE-Extensions
                                    ProtocolExtensionContainer { {TDD-DL-Code-InformationItem-ExtIEs} } OPTIONAL,
TDD-DL-Code-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
TDD-DL-Code-LCR-Information ::= SEQUENCE (SIZE (1..maxNrOfDPCHsLCR)) OF TDD-DL-Code-LCR-InformationItem
TDD-DL-Code-LCR-InformationItem ::= SEQUENCE {
   dPCH-ID
                                            DPCH-ID,
    tdd-ChannelisationCodeLCR
                                            TDD-ChannelisationCodeLCR,
    tdd-DL-DPCH-TimeSlotFormat-LCR
                                            TDD-DL-DPCH-TimeSlotFormat-LCR,
                                            ProtocolExtensionContainer { { TDD-DL-Code-LCR-InformationItem-ExtIEs} }
   iE-Extensions
                                                                                                                                OPTIONAL,
TDD-DL-Code-LCR-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
TDD-DL-Code-Information768 ::= SEQUENCE ( SIZE (1..maxNrOfDPCHs768)) OF TDD-DL-Code-InformationItem768
TDD-DL-Code-InformationItem768 ::= SEQUENCE {
   dPCH-ID
                                    DPCH-ID,
    tDD-ChannelisationCode768
                                    TDD-ChannelisationCode768,
                                    ProtocolExtensionContainer { {TDD-DL-Code-InformationItem768-ExtIEs} } OPTIONAL,
   iE-Extensions
TDD-DL-Code-InformationItem768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
TDD-DL-DPCH-TimeSlotFormat-LCR ::= CHOICE {
                               OPSK-DL-DPCH-TimeSlotFormatTDD-LCR,
    qPSK
    eightPSK
                                EightPSK-DL-DPCH-TimeSlotFormatTDD-LCR,
QPSK-DL-DPCH-TimeSlotFormatTDD-LCR ::= INTEGER(0..24,...)
EightPSK-DL-DPCH-TimeSlotFormatTDD-LCR ::= INTEGER(0..24,...)
TDD-DPCHOffset ::= CHOICE {
   initialOffset
                       INTEGER (0..255),
   noinitialOffset
                       INTEGER (0..63)
TDD-PhysicalChannelOffset
                             ::= INTEGER (0..63)
```

```
TDD-TPC-DownlinkStepSize ::= ENUMERATED {
    step-sizel,
    step-size2,
    step-size3,
    . . .
TDD-TPC-UplinkStepSize-LCR ::= ENUMERATED {
    step-size1,
    step-size2,
    step-size3,
    . . .
TDD-UL-Code-Information ::= SEOUENCE ( SIZE (1...maxNrOfDPCHs)) OF TDD-UL-Code-InformationItem
TDD-UL-Code-InformationItem ::= SEQUENCE {
   dPCH-ID
    tDD-ChannelisationCode
                                    TDD-ChannelisationCode,
                                    ProtocolExtensionContainer { {TDD-UL-Code-InformationItem-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
TDD-UL-Code-InformationItem-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
TDD-UL-Code-LCR-Information ::= SEOUENCE (SIZE (1..maxNrOfDPCHsLCR)) OF TDD-UL-Code-LCR-InformationItem
TDD-UL-Code-LCR-InformationItem ::= SEQUENCE {
   dPCH-ID
                                            DPCH-ID,
    tdd-ChannelisationCodeLCR
                                            TDD-ChannelisationCodeLCR,
    tdd-UL-DPCH-TimeSlotFormat-LCR
                                            TDD-UL-DPCH-TimeSlotFormat-LCR,
                                            ProtocolExtensionContainer { { TDD-UL-Code-LCR-InformationItem-ExtIEs} }
    iE-Extensions
                                                                                                                                  OPTIONAL,
    . . .
TDD-UL-Code-LCR-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
TDD-UL-Code-Information768 ::= SEQUENCE ( SIZE (1..maxNrOfDPCHs768)) OF TDD-UL-Code-InformationItem768
TDD-UL-Code-InformationItem768 ::= SEQUENCE {
    dPCH-ID
                                    DPCH-ID,
    tDD-ChannelisationCode768
                                    TDD-ChannelisationCode768,
   iE-Extensions
                                    ProtocolExtensionContainer { {TDD-UL-Code-InformationItem768-ExtIEs} } OPTIONAL,
TDD-UL-Code-InformationItem768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
```

```
TDD-UL-DPCH-TimeSlotFormat-LCR ::= CHOICE {
    qPSK
                                QPSK-UL-DPCH-TimeSlotFormatTDD-LCR,
    eightPSK
                                EightPSK-UL-DPCH-TimeSlotFormatTDD-LCR,
OPSK-UL-DPCH-TimeSlotFormatTDD-LCR ::= INTEGER(0..69,...)
EightPSK-UL-DPCH-TimeSlotFormatTDD-LCR ::= INTEGER(0..24,...)
TFCI-Coding ::= ENUMERATED {
    v4,
    v8,
    v16,
    v32,
TFCI-Presence ::= ENUMERATED {
    present,
   not-present
TFCI-SignallingMode ::= ENUMERATED {
    normal,
    not-Used-split
-- The value "Not Used" shall not be used by the SRNC. The procedure shall be rejected by the DRNC if the value "Not Used" is received.
                    ::= INTEGER (0|15..269)
TGD
-- 0 = Undefined, only one transmission gap in the transmission gap pattern sequence
TGPRC
                    ::= INTEGER (0..511)
-- 0 = infinity
TGPSID
                    ::= INTEGER (1.. maxTGPS)
TGSN
                    ::= INTEGER (0..14)
TimeSlot
                        ::= INTEGER (0..14)
TimeSlotLCR ::= INTEGER (0..6)
Time-Stamp ::= INTEGER (0..9999)
-- Unit: 10ms
TimingAdvanceApplied ::= ENUMERATED {
    yes,
    no
SynchronisationIndicator ::= ENUMERATED {
```

```
timingMaintainedSynchronisation,
      ::= SEOUENCE
                PLMN-Identity,
    plmn-id
    service-id Service-ID,
                                    ProtocolExtensionContainer { { TMGI-ExtIEs} }
    iE-Extensions
                                                                                         OPTIONAL,
TMGI-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
TnlOos ::= CHOICE {
    dsField
                                DsField,
    genericTrafficCategory
                                GenericTrafficCategory,
    . . .
ToAWE
                        ::= INTEGER (0..2559)
ToAWS
                        ::= INTEGER (0..1279)
TraceDepth
                                ::= ENUMERATED {
   minimum,
    medium,
    maximum,
TraceRecordingSessionReference ::= INTEGER (0..65535)
TraceReference
                                ::= OCTET STRING (SIZE (2..3))
TrafficClass ::= ENUMERATED {
    conversational,
    streaming,
    interactive,
    background,
Transmission-Gap-Pattern-Sequence-Information ::= SEQUENCE (SIZE (1..maxTGPS)) OF
    SEQUENCE {
        tGPSID
                        TGPSID,
        tGSN
                        TGSN,
        tGL1
                        GapLength,
        tGL2
                        GapLength
                                    OPTIONAL,
        tGD
                        TGD,
        tGPL1
                        GapDuration,
       not-to-be-used-1
                                    GapDuration OPTIONAL,
            -- This IE shall never be included in the SEQUENCE. If received it shall be ignored
```

```
uL-DL-mode
                      UL-DL-mode,
       downlink-Compressed-Mode-Method
                                        Downlink-Compressed-Mode-Method
                                                                          OPTIONAL.
           -- This IE shall be present if the value of the UL/DL mode IE is "DL only" or "UL/DL"
       uplink-Compressed-Mode-Method
                                        Uplink-Compressed-Mode-Method
                                                                          OPTIONAL,
           -- This IE shall be present if the value of the UL/DL mode IE is "UL only" or "UL/DL"
                          DL-FrameType,
       dL-FrameType
       delta-SIR1
                      DeltaSIR,
       delta-SIR-after1 DeltaSIR,
       delta-SIR2
                     DeltaSIR
                                 OPTIONAL,
       delta-SIR-after2 DeltaSIR
                                     OPTIONAL,
                             ProtocolExtensionContainer { {Transmission-Gap-Pattern-Sequence-Information-ExtIEs} } OPTIONAL,
       iE-Extensions
       . . .
Transmission-Gap-Pattern-Sequence-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Transmission-Gap-Pattern-Sequence-ScramblingCode-Information
                                                           ::= ENUMERATED{
  code-change,
  nocode-change
Transmission-Gap-Pattern-Sequence-Status-List ::= SEQUENCE (SIZE (0..maxTGPS)) OF
   SEQUENCE {
       tGPSID
                      TGPSID,
       tGPRC
                      TGPRC,
       tGCFN
                      CFN.
                          ProtocolExtensionContainer { { Transmission-Gap-Pattern-Sequence-Status-List-ExtIEs } } OPTIONAL,
       iE-Extensions
Transmission-Gap-Pattern-Sequence-Status-List-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
   . . .
Affected-HSDSCH-Serving-Cell-List ::= SEOUENCE (SIZE (0.. maxNrofHSDSCH)) OF C-ID
TransmissionMode
                  ::=ENUMERATED {
   p-t-p,
   p-t-m,
   not-provided,
Transmission-Mode-Information::= SEQUENCE ( SIZE (1..maxNrOfFDDNeighboursPerRNC,...)) OF Transmission-Mode-Information-List
Transmission-Mode-Information-List ::= SEQUENCE {
   C-TD
                                     C-ID,
   transmissionMode
                                     TransmissionMode,
   iE-Extensions
                                     ProtocolExtensionContainer { { Transmission-Mode-Information-List-ExtIEs} } OPTIONAL,
```

```
Transmission-Mode-Information-List-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
TransmissionTimeIntervalDynamic ::= ENUMERATED {
   msec-10.
   msec-20,
   msec-40,
   msec-80,
TransmissionTimeIntervalSemiStatic ::= ENUMERATED {
   msec-10,
   msec-20,
   msec-40,
    msec-80,
    dynamic,
TransmitDiversityIndicator ::= ENUMERATED {
    active,
    inactive
Transmitted-Carrier-Power-Value ::= INTEGER(0..100)
-- according to mapping in TS 25.133 [23] and TS 25.123 [24]
Transmitted-Carrier-Power-Value-IncrDecrThres ::= INTEGER(0..100)
-- according to mapping in TS 25.133 [23] and TS 25.123 [24]
Transport-Block-Size-Index ::= INTEGER(1..maxNrOfHS-DSCHTBSs)
TUTRANGANSS ::= SEQUENCE {
                    INTEGER(0..16383),
    1s
                    INTEGER(0..4294967295)
TUTRANGANSSAccuracyClass ::= ENUMERATED {
    ganssAccuracy-class-A,
    ganssAccuracy-class-B,
    ganssAccuracy-class-C,
    . . .
TUTRANGANSSMeasurementThresholdInformation ::= SEQUENCE {
    tUTRANGANSSChangeLimit
                                            INTEGER(1..256)
    OPTIONAL,
    predictedTUTRANGANSSDeviationLimit
                                            INTEGER(1..256)
    OPTIONAL,
    ie-Extensions
                            ProtocolExtensionContainer { { TUTRANGANSSMeasurementThresholdInformation-ExtlEs } }
```

```
TUTRANGANSSMeasurementThresholdInformation-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
TUTRANGANSSMeasurementValueInformation ::= SEQUENCE {
   tUTRANGANSS
                                  TUTRANGANSS,
   tUTRANGANSSQuality
                                  INTEGER(0..255)
   OPTIONAL,
    tUTRANGANSSDriftRate
                                  INTEGER(-50..50),
    tUTRANGANSSDriftRateOuality
                                  INTEGER (0..50)
   OPTIONAL,
   ie-Extensions
                                  OPTIONAL,
TUTRANGANSSMeasurementValueInformation-ExtlEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-GANSS-Time-ID
                                  CRITICALITY ignore
                                                         EXTENSION GANSS-Time-ID
                                                                                    PRESENCE
                                                                                                               optional},
    . . .
TUTRANGPS ::= SEQUENCE {
   ms-part
               INTEGER (0..16383),
   ls-part
               INTEGER (0..4294967295)
TUTRANGPSChangeLimit ::= INTEGER (1..256)
-- Unit chip, Step 1/16 chip, Range 1/16..16 chip
TUTRANGPSDriftRate ::= INTEGER (-50..50)
-- Unit chip/s, Step 1/256 chip/s, Range -50/256..+50/256 chip/s
TUTRANGPSDriftRateQuality ::= INTEGER (0..50)
-- Unit chip/s, Step 1/256 chip/s, Range 0..50/256 chip/s
TUTRANGPSAccuracyClass ::= ENUMERATED {
   accuracy-class-A,
   accuracy-class-B,
   accuracy-class-C,
TUTRANGPSMeasurementThresholdInformation ::= SEQUENCE
    tUTRANGPSChangeLimit
                                         TUTRANGPSChangeLimit
                                                                                OPTIONAL,
                                         PredictedTUTRANGPSDeviationLimit
   predictedTUTRANGPSDeviationLimit
                                                                                OPTIONAL,
   iE-Extensions
                                  ProtocolExtensionContainer { { TUTRANGPSMeasurementThresholdInformation-ExtIEs} }
                                                                                                                          OPTIONAL,
TUTRANGPSMeasurementThresholdInformation-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
TUTRANGPSMeasurementValueInformation ::= SEQUENCE {
       tUTRANGPS
                                        TUTRANGPS.
       tUTRANGPSOuality
                                        TUTRANGPSOuality
                                                                        OPTIONAL,
       tUTRANGPSDriftRate
                                        TUTRANGPSDriftRate,
       tUTRANGPSDriftRateOuality
                                        TUTRANGPSDriftRateOuality
                                                                        OPTIONAL,
       iEe-Extensions
                                        ProtocolExtensionContainer { { TUTRANGPSMeasurementValueInformationItem-ExtIEs} }
                                                                                                                                        OPTIONAL.
TUTRANGPSMeasurementValueInformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
TUTRANGPSQuality ::= INTEGER (0..255)
-- Unit chip, Step 1/16 chip, Range 0.. 255/16 chip
TransportBearerID
                        ::= INTEGER (0..4095)
TransportBearerRequestIndicator
                                    ::= ENUMERATED {
    bearer-requested,
    bearer-not-requested,
TransportBearerNotRequestedIndicator
                                            ::= ENUMERATED {
    transport-bearer-shall-not-be-established,
    transport-bearer-may-not-be-established
TransportBearerNotSetupIndicator
                                        ::= ENUMERATED {
    transport-bearer-not-setup
TransportBlockSize
                           ::= INTEGER (0..5000)
-- Unit is bits
TransportFormatCombination-Beta ::= CHOICE {
    signalledGainFactors SEOUENCE {
       betaC
                                BetaCD,
       betaD
                                BetaCD,
       refTFCNumber
                                RefTFCNumber
                                                OPTIONAL,
       iE-Extensions
                                ProtocolExtensionContainer { { SignalledGainFactors-ExtIEs} } OPTIONAL,
    refTFCNumber
                            RefTFCNumber,
SignalledGainFactors-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
TFCS ::= SEOUENCE
    tFCSvalues
                        CHOICE {
       no-Split-in-TFCI
                                    TFCS-TFCSList,
       not-Used-split-in-TFCI
                                    NULL,
       -- This choice shall never be made by the SRNC and the DRNC shall consider the procedure as failed if it is received.
                        ProtocolExtensionContainer { { TFCS-ExtIEs} }
    iE-Extensions
                                                                            OPTIONAL,
TFCS-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
TFCS-TFCSList ::= SEQUENCE (SIZE (1..maxNrOfTFCs)) OF
    SEQUENCE {
       CTFC
                            TFCS-CTFC,
       tFC-Beta
                       TransportFormatCombination-Beta
                                                            OPTIONAL,
       -- The IE shall be present if the TFCS concerns a UL DPCH [FDD - or PRACH channel in FDD]
                            ProtocolExtensionContainer { { TFCS-TFCSList-ExtIEs} }
       iE-Extensions
    . . .
TFCS-TFCSList-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
TFCS-CTFC ::= CHOICE {
   ctfc2bit
                                        INTEGER (0..3),
    ctfc4bit
                                        INTEGER (0..15),
   ctfc6bit
                                        INTEGER (0..63),
    ctfc8bit
                                        INTEGER (0..255),
    ctfc12bit
                                        INTEGER (0..4095),
    ctfc16bit
                                        INTEGER (0..65535),
    ctfcmaxbit
                                        INTEGER (0..maxCTFC)
TransportFormatSet ::= SEQUENCE {
    dynamicParts
                            TransportFormatSet-DynamicPartList,
    semi-staticPart
                            TransportFormatSet-Semi-staticPart,
    iE-Extensions
                            ProtocolExtensionContainer { TransportFormatSet-ExtIEs} } OPTIONAL,
    . . .
TransportFormatSet-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
TransportFormatSet-DynamicPartList ::= SEQUENCE (SIZE (1..maxNrOfTFs)) OF
    SEQUENCE {
       nrOfTransportBlocks
                                NrOfTransportBlocks,
```

```
transportBlockSize
                                TransportBlockSize
                                                        OPTIONAL
        -- This IE shall be present if nrOfTransportBlocks is greater than 0 --,
                            TransportFormatSet-ModeDP,
        iE-Extensions
                                ProtocolExtensionContainer { {TransportFormatSet-DynamicPartList-ExtIEs} } OPTIONAL,
TransportFormatSet-DynamicPartList-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
TransportFormatSet-ModeDP ::= CHOICE {
                       TDD-TransportFormatSet-ModeDP,
   notApplicable
                        NULL,
TDD-TransportFormatSet-ModeDP ::= SEQUENCE {
    transmissionTimeIntervalInformation
                                            TransmissionTimeIntervalInformation
                                                                                     OPTIONAL,
    -- This IE shall be present if the "Transmission Time Interval" of the "Semi-static Transport Format Information" is "dynamic". Otherwise it is
absent.
                                            ProtocolExtensionContainer { {TDD-TransportFormatSet-ModeDP-ExtIEs} } OPTIONAL,
    iE-Extensions
TDD-TransportFormatSet-ModeDP-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
TransmissionTimeIntervalInformation ::= SEQUENCE (SIZE (1..maxTTI-Count)) OF
    SEOUENCE {
                                    TransmissionTimeIntervalDynamic,
       transmissionTimeInterval
       iE-Extensions
                                ProtocolExtensionContainer { {TransmissionTimeIntervalInformation-ExtIEs} } OPTIONAL,
TransmissionTimeIntervalInformation-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Transmitted-Code-Power-Value ::= INTEGER (0..127)
-- According to mapping in TS 25.215 [11]/TS 25.225 [14]
Transmitted-Code-Power-Value-IncrDecrThres ::= INTEGER (0..112,...)
TransportFormatManagement ::= ENUMERATED {
    cell-based,
    ue-based,
    . . .
TransportFormatSet-Semi-staticPart ::= SEQUENCE {
    transmissionTime
                           TransmissionTimeIntervalSemiStatic,
    channelCoding
                            ChannelCodingType,
```

```
codingRate
                        CodingRate
                                                OPTIONAL
    -- This IE shall be present if channelCoding is 'convolutional' or 'turbo' --,
    rateMatcingAttribute
                                RateMatchingAttribute,
    cRC-Size
                        CRC-Size,
                        TransportFormatSet-ModeSSP,
    iE-Extensions
                            ProtocolExtensionContainer { {TransportFormatSet-Semi-staticPart-ExtIEs} } OPTIONAL,
TransportFormatSet-Semi-staticPart-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
TransportFormatSet-ModeSSP ::= CHOICE {
                    SecondInterleavingMode,
    notApplicable
                            NULL,
    . . .
TransportLayerAddress
                                ::= BIT STRING (SIZE(1..160, ...))
TrCH-SrcStatisticsDescr
                            ::= ENUMERATED {
    speech,
    rRC,
    unknown,
    . . .
TSN-Length ::= ENUMERATED {
    tsn-6bits,
    tsn-9bits
TSTD-Indicator ::= ENUMERATED {
    active,
    inactive
TSTD-Support-Indicator ::= ENUMERATED {
    tSTD-supported,
    tSTD-not-supported
TxDiversityIndicator
                       ::= ENUMERATED {
    true,
    false
TypeOfError ::= ENUMERATED {
   not-understood,
    missing,
    . . .
```

```
-- U
                        ::= INTEGER (0..16383,...)
-- Corresponds to: 0.0Hz..3276.6Mhz. See TS 25.105 [7], TS 25.101 [43]
UDRE ::= ENUMERATED {
    lessThan1,
    between1-and-4,
   between4-and-8,
    over8,
UDREGrowthRate ::=
                                    ENUMERATED {
                                        growth-1-point-5,
                                        growth-2,
                                        growth-4,
                                        growth-6,
                                        growth-8,
                                        growth-10,
                                        growth-12,
                                        growth-16
UDREValidityTime
                                    ENUMERATED {
                                        val-20sec,
                                        val-40sec.
                                        val-80sec,
                                        val-160sec,
                                        val-320sec,
                                        val-640sec,
                                        val-1280sec,
                                        val-2560sec }
UE-AggregateMaximumBitRate ::= SEQUENCE {
    uE-AggregateMaximumBitRateDownlink
                                            UE-AggregateMaximumBitRateDownlink OPTIONAL,
    uE-AggregateMaximumBitRateUplink
                                            UE-AggregateMaximumBitRateUplink
                                                                                OPTIONAL,
UE-AggregateMaximumBitRateDownlink
                                            ::= INTEGER (1..100000000)
-- Unit is bits per sec
UE-AggregateMaximumBitRateUplink
                                            ::= INTEGER (1..100000000)
-- Unit is bits per sec
UE-AggregateMaximumBitRate-Enforcement-Indicator ::= NULL
UE-Capabilities-Info ::= SEQUENCE {
    hSDSCH-Physical-Layer-Category
                                        INTEGER (1..64,...),
    iE-Extensions
                                        ProtocolExtensionContainer { { UE-Capabilities-Info-ExtIEs } }
                                                                                                                         OPTIONAL,
UE-Capabilities-Info-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
{ID id-LCRTDD-uplink-Physical-Channel-Capability
                                                             CRITICALITY ignore EXTENSION LCRTDD-Uplink-Physical-Channel-Capability
                                                                                                                                         PRESENCE
optional}|
    {ID id-number-Of-Supported-Carriers
                                                             CRITICALITY reject EXTENSION Number-Of-Supported-Carriers
                                                                                                                                 PRESENCE optional}
    {ID id-MIMO-SFMode-Supported-For-HSPDSCHDualStream
                                                             CRITICALITY ignore EXTENSION MIMO-SFMode-For-HSPDSCHDualStream
                                                                                                                                 PRESENCE optional }
    ID id-MultiCarrier-HSDSCH-Physical-Layer-Category
                                                             CRITICALITY ignore EXTENSION LCRTDD-HSDSCH-Physical-Layer-Category PRESENCE optional }
    ID id-UE-TS0-CapabilityLCR
                                                             CRITICALITY ignore EXTENSION UE-TSO-CapabilityLCR
                                                                                                                                 PRESENCE optional)
    {ID id-UE-RF-Band-CapabilityLCR
                                                             CRITICALITY ignore EXTENSION UE-RF-Band-CapabilityLCR
                                                                                                                                 PRESENCE
conditional },
UE-TS0-CapabilityLCR ::= ENUMERATED {
    tS0-Capable,
    tS0-Not-Capable
UE-RF-Band-CapabilityLCR ::= SEOUENCE (SIZE (1.. maxFreqBandsTDD)) OF Radio-Frequency-BandItem
Radio-Frequency-BandItem ::= SEQUENCE {
    radio-Frequency-Band
                                            Radio-Frequency-Band,
    iE-Extensions
                                            ProtocolExtensionContainer { { Radio-Frequency-BandItem-ExtIEs } }
                                                                                                                                 OPTIONAL,
    . . .
Radio-Frequency-Band ::= ENUMERATED {
    a,
    b,
    C,
    d,
    e,
    f,
    h,
    i,
    j,
    k,
    1,
    m,
    n,
    ο,
    p,
Radio-Frequency-BandItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
LCRTDD-HSDSCH-Physical-Layer-Category ::= INTEGER (1..64)
UE-DPCCH-burst1 ::= ENUMERATED {v1, v2, v5}
    -- Unit subframe
UE-DPCCH-burst2 ::= ENUMERATED {v1, v2, v5}
```

```
-- Unit subframe
UE-DRX-Cycle ::= ENUMERATED {v4, v5, v8, v10, v16, v20}
    -- Unit subframe
UE-DRX-Grant-Monitoring ::= BOOLEAN
    -- true: applied, false: not applied
UE-DTX-Cycle1-2ms ::= ENUMERATED \{v1, v4, v5, v8, v10, v16, v20\}
    -- Unit subframe
UE-DTX-Cycle1-10ms ::= ENUMERATED {v1, v5, v10, v20}
    -- Unit subframe
UE-DTX-Cycle2-2ms ::= ENUMERATED {v4, v5, v8, v10, v16, v20, v32, v40, v64, v80, v128, v160}
    -- Unit subframe
UE-DTX-Cycle2-10ms ::= ENUMERATED {v5, v10, v20, v40, v80, v160}
    -- Unit subframe
UE-DTX-DRX-Offset ::= INTEGER (0..159)
    -- Unit subframe
UE-DTX-Long-Preamble ::= ENUMERATED {v2, v4, v15}
    -- Units of slots
                            ::= CHOICE {
UEIdentity
    imsi
                IMSI,
    imei
                IMEI,
    imeisv
                IMEISV,
    . . .
UEMeasurementHysteresisTime ::= INTEGER (0..15)
    -- Unit dB
    -- Range 0..7.5 dB
    -- Step 0.5 dB
UEMeasurementParameterModAllow ::= ENUMERATED {
    parameterModificationAllowed,
UEMeasurementReportCharacteristics ::= CHOICE {
    periodic
                        UEMeasurementReportCharacteristicsPeriodic,
    event1h
                        UEMeasurementReportCharacteristicsEvent1h,
    event1i
                        UEMeasurementReportCharacteristicsEventli,
    event6a
                        UEMeasurementReportCharacteristicsEvent6a,
                        UEMeasurementReportCharacteristicsEvent6b,
    event6b
    event6c
                        UEMeasurementReportCharacteristicsEvent6c,
    event6d
                        UEMeasurementReportCharacteristicsEvent6d,
    . . . ,
```

```
extension-ReportCharacteristics
                                        UEMeasurementReportCharacteristics-Extension
UEMeasurementReportCharacteristicsEvent1h ::= SEQUENCE {
    uEMeasurementTreshold
                                UEMeasurementThreshold,
    uEMeasurementTimeToTrigger UEMeasurementTimeToTrigger,
    uEMeasurementHysteresisTime UEMeasurementHysteresisTime
                                ProtocolExtensionContainer { { UEMeasurementReportCharacteristicsEvent1h-ExtIEs} } OPTIONAL,
    iE-Extensions
UEMeasurementReportCharacteristicsEvent1h-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UEMeasurementReportCharacteristicsEventli ::= SEQUENCE {
    uEMeasurementTreshold
                                UEMeasurementThreshold,
    uEMeasurementTimeToTrigger UEMeasurementTimeToTrigger,
    uEMeasurementHysteresisTime UEMeasurementHysteresisTime,
                                ProtocolExtensionContainer { { UEMeasurementReportCharacteristicsEventli-ExtIEs} } OPTIONAL,
    iE-Extensions
    . . .
UEMeasurementReportCharacteristicsEventli-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UEMeasurementReportCharacteristicsEvent6a ::= SEQUENCE {
    uEMeasurementTreshold
                                UEMeasurementThreshold,
    uEMeasurementTimeToTrigger UEMeasurementTimeToTrigger,
    iE-Extensions
                                ProtocolExtensionContainer { { UEMeasurementReportCharacteristicsEvent6a-ExtIEs} } OPTIONAL,
UEMeasurementReportCharacteristicsEvent6a-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UEMeasurementReportCharacteristicsEvent6b ::= SEQUENCE
    uEMeasurementTreshold
                                UEMeasurementThreshold,
    uEMeasurementTimeToTrigger UEMeasurementTimeToTrigger,
    iE-Extensions
                                ProtocolExtensionContainer { { UEMeasurementReportCharacteristicsEvent6b-ExtIEs} } OPTIONAL,
    . . .
UEMeasurementReportCharacteristicsEvent6b-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UEMeasurementReportCharacteristicsEvent6c ::= SEQUENCE {
    uEMeasurementTimeToTrigger UEMeasurementTimeToTrigger,
    iE-Extensions
                                ProtocolExtensionContainer { { UEMeasurementReportCharacteristicsEvent6c-ExtIEs} } OPTIONAL,
```

```
UEMeasurementReportCharacteristicsEvent6c-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UEMeasurementReportCharacteristicsEvent6d ::= SEQUENCE {
    uEMeasurementTimeToTrigger UEMeasurementTimeToTrigger,
                                ProtocolExtensionContainer { { UEMeasurementReportCharacteristicsEvent6d-ExtIEs} } OPTIONAL,
    iE-Extensions
UEMeasurementReportCharacteristicsEvent6d-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UEMeasurementReportCharacteristicsPeriodic ::= SEQUENCE
    amountofReporting
                            UEMeasurementReportCharacteristicsPeriodicAmountofReporting,
    reportingInterval
                            UEMeasurementReportCharacteristicsPeriodicReportingInterval,
                            ProtocolExtensionContainer { {UEMeasurementReportCharacteristicsPeriodic-ExtIEs} } OPTIONAL,
    iE-Extensions
UEMeasurementReportCharacteristicsPeriodicAmountofReporting::= ENUMERATED {
    r1,
    r2,
    r4,
    r8,
    r16,
    r32,
    r64,
    rInfinity
UEMeasurementReportCharacteristicsPeriodicReportingInterval::= ENUMERATED {
    r250,
    r500,
    r1000,
    r2000,
    r3000,
    r4000,
    r6000,
    r8000,
    r12000,
    r16000,
    r20000,
   r24000,
   r28000,
   r32000,
    r64000
UEMeasurementReportCharacteristicsPeriodic-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

```
UEMeasurementReportCharacteristics-Extension ::= ProtocolIE-Single-Container {{ UEMeasurementReportCharacteristics-ExtensionIE }}
UEMeasurementReportCharacteristics-ExtensionIE RNSAP-PROTOCOL-IES ::= {
UEMeasurementThreshold
                               ::= CHOICE {
    timeslotISCP
                                   UEMeasurementThresholdDLTimeslotISCP,
    uETransmitPower
                                   UEMeasurementThresholdUETransmitPower,
    extension-UEMeasurementThreshold
                                        UEMeasurementThreshold-Extension
UEMeasurementThresholdDLTimeslotISCP ::=
                                            INTEGER(-115..-25)
UEMeasurementThresholdUETransmitPower ::=
                                            INTEGER(-50..33)
UEMeasurementThreshold-Extension ::= ProtocolIE-Single-Container {{ UEMeasurementThreshold-ExtensionIE }}
UEMeasurementThreshold-ExtensionIE RNSAP-PROTOCOL-IES ::= {
UEMeasurementTimeslotInfoHCR::= SEQUENCE (SIZE (1..maxNrOfTS)) OF UEMeasurementTimeslotInfoHCR-IEs
UEMeasurementTimeslotInfoHCR-IEs ::= SEOUENCE {
    timeSlot
                                    TimeSlot,
   burstType
                                   UEMeasurementTimeslotInfoHCRBurstType,
                                    ProtocolExtensionContainer { { UEMeasurementTimeslotInfoHCR-IEs-ExtIEs} }
   iE-Extensions
                                                                                                                        OPTIONAL,
    . . .
UEMeasurementTimeslotInfoHCRBurstType ::= ENUMERATED {
    type1,
    type2,
    type3,
    . . .
UEMeasurementTimeslotInfoHCR-IEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UEMeasurementTimeslotInfoLCR::= SEOUENCE (SIZE (1..maxNrOfTsLCR)) OF UEMeasurementTimeslotInfoLCR-IEs
UEMeasurementTimeslotInfoLCR-IEs ::= SEOUENCE {
    timeSlot
   iE-Extensions
                                    ProtocolExtensionContainer { { UEMeasurementTimeslotInfoLCR-IEs-ExtIEs} }
                                                                                                                        OPTIONAL,
UEMeasurementTimeslotInfoLCR-IEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
```

OPTIONAL,

```
UEMeasurementTimeslotInfo768::= SEQUENCE (SIZE (1..maxNrOfTS)) OF UEMeasurementTimeslotInfo768-IEs
UEMeasurementTimeslotInfo768-IEs ::= SEQUENCE {
    timeSlot
                                     TimeSlot,
    burstType
                                    UEMeasurementTimeslotInfo768BurstType,
    iE-Extensions
                                     ProtocolExtensionContainer { { UEMeasurementTimeslotInfo768-IEs-ExtIEs} }
    . . .
UEMeasurementTimeslotInfo768BurstType ::= ENUMERATED {
    type1,
    type2,
    type3,
    . . .
UEMeasurementTimeslotInfo768-IEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UEMeasurementTimeToTrigger ::= ENUMERATED {
    rO,
    r10.
    r20,
    r40,
    r60,
    r80,
    r100,
    r120,
    r160,
    r200,
    r240,
    r320,
    r640,
    r1280,
    r2560,
    r5000
UEMeasurementType ::= ENUMERATED {
    primary-CCPCH-RSCP,
    dL-Timeslot-ISCP,
    uE-Transmitted-power,
    . . .
UEMeasurementValue ::= CHOICE {
    uE-Transmitted-Power
                                UE-MeasurementValue-UE-Transmitted-Power,
    primary-CCPCH-RSCP
                                UE-MeasurementValue-Primary-CCPCH-RSCP,
    dL-Timeslot-ISCP
                                UE-MeasurementValue-DL-Timeslot-ISCP,
    . . . ,
```

```
extension-UEMeasurementValue
                                        UEMeasurementValue-Extension
UE-MeasurementValue-UE-Transmitted-Power ::= SEQUENCE {
    uEMeasurementTransmittedPowerListHCR
                                               UEMeasurementValueTransmittedPowerListHCR OPTIONAL.
-- Mandatory for 3.84Mcps TDD, Not applicable for 1.28Mcps TDD or 7.68Mcps TDD
    uEMeasurementTransmittedPowerListLCR
                                          UEMeasurementValueTransmittedPowerListLCR OPTIONAL,
-- Mandatory for 1.28Mcps TDD, Not applicable for 3.84Mcps TDD or 7.68Mcps TDD
    iE-Extensions
                                                ProtocolExtensionContainer { { UE-MeasurementValue-UE-Transmitted-Power-ExtIEs} }
    OPTIONAL,
    . . .
UE-MeasurementValue-UE-Transmitted-Power-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-UEMeasurementValueTransmittedPowerList768
                                                               CRITICALITY ignore EXTENSION UEMeasurementValueTransmittedPowerList768
        PRESENCE optional },
    . . .
UEMeasurementValueTransmittedPowerListHCR ::= SEOUENCE (SIZE (1..maxNrOfTS)) OF UEMeasurementValueTransmittedPowerListHCR-IEs
UEMeasurementValueTransmittedPowerListHCR-IEs ::= SEQUENCE {
    timeSlot
                                    TimeSlot,
    uETransmitPower
                                    INTEGER(0..104),
    -- mapping according to TS 25.123 [24], values 0..20 not used
                                                ProtocolExtensionContainer { { UEMeasurementValueTransmittedPowerListHCR-IEs-ExtIEs} }
    iE-Extensions
    OPTIONAL,
    . . .
UEMeasurementValueTransmittedPowerListHCR-IEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
UEMeasurementValueTransmittedPowerListLCR ::= SEOUENCE (SIZE (1..maxNrOfTsLCR)) OF UEMeasurementValueTransmittedPowerListLCR-IEs
UEMeasurementValueTransmittedPowerListLCR-IEs ::= SEQUENCE {
    timeSlotLCR
                                    TimeSlotLCR,
    uETransmitPower
                                    INTEGER(0..104),
    -- mapping according to TS 25.123 [24], values 0..20 not used
                                                ProtocolExtensionContainer { { UEMeasurementValueTransmittedPowerListLCR-IEs-ExtIEs} }
    iE-Extensions
    OPTIONAL,
    . . .
UEMeasurementValueTransmittedPowerListLCR-IEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UEMeasurementValueTransmittedPowerList768 ::= SEQUENCE (SIZE (1..maxNrOfTS)) OF UEMeasurementValueTransmittedPowerList768-IEs
UEMeasurementValueTransmittedPowerList768-IES ::= SEQUENCE {
    timeSlot
                                    TimeSlot,
    uETransmitPower
                                    INTEGER(0..104),
```

```
-- mapping according to TS 25.123 [24], values 0..20 not used
   iE-Extensions
                                                ProtocolExtensionContainer { { UEMeasurementValueTransmittedPowerList768-IEs-ExtIEs} }
    OPTIONAL.
    . . .
UEMeasurementValueTransmittedPowerList768-IEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UE-MeasurementValue-Primary-CCPCH-RSCP::= SEQUENCE
    primaryCCPCH-RSCP
                                        PrimaryCCPCH-RSCP
                                                                        OPTIONAL,
   primaryCCPCH-RSCP-Delta
                                        PrimaryCCPCH-RSCP-Delta
                                                                        OPTIONAL,
   iE-Extensions
                                        ProtocolExtensionContainer { { UE-MeasurementValue-Primary-CCPCH-RSCP-ExtIEs} }
                                                                                                                                OPTIONAL,
UE-MeasurementValue-Primary-CCPCH-RSCP-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UE-MeasurementValue-DL-Timeslot-ISCP ::= SEQUENCE {
    uEMeasurementTimeslotISCPListHCR
                                            UEMeasurementValueTimeslotISCPListHCR
                                                                                    OPTIONAL,
-- Mandatory for 3.84Mcps TDD, Not applicable for 1.28Mcps TDD or 7.68Mcps TDD
    uEMeasurementTimeslotISCPListLCR
                                            UEMeasurementValueTimeslotISCPListLCR
                                                                                    OPTIONAL,
-- Mandatory for 1.28Mcps TDD, Not applicable for 3.84Mcps TDD or 7.68Mcps TDD
    iE-Extensions
                                                ProtocolExtensionContainer { { UE-MeasurementValue-DL-Timeslot-ISCP-ExtIEs} }
                                                                                                                                        OPTIONAL,
    . . .
UE-MeasurementValue-DL-Timeslot-ISCP-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-UEMeasurementValueTimeslotISCPList768
                                                            CRITICALITY ignore EXTENSION UEMeasurementValueTimeslotISCPList768
    PRESENCE optional },
    . . .
UEMeasurementValueTimeslotISCPListHCR ::= SEOUENCE (SIZE (1..maxNrOfTS)) OF UEMeasurementValueTimeslotISCPListHCR-IEs
UEMeasurementValueTimeslotISCPListHCR-IEs ::= SEQUENCE {
    timeSlot
                                    TimeSlot,
    dL-TimeslotISCP
                                    DL-TimeslotISCP,
                                    ProtocolExtensionContainer { { UEMeasurementValueTimeslotISCPListHCR-IEs-ExtIEs} }
   iE-Extensions
                                                                                                                                OPTIONAL,
UEMeasurementValueTimeslotISCPListHCR-IEs-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UEMeasurementValueTimeslotISCPListLCR ::= SEQUENCE (SIZE (1..maxNrOfTsLCR)) OF UEMeasurementValueTimeslotISCPListLCR-IEs
UEMeasurementValueTimeslotISCPListLCR-IEs ::= SEOUENCE {
    timeSlotLCR
                                    TimeSlotLCR,
    dL-TimeslotISCP
                                    DL-TimeslotISCP,
```

```
ProtocolExtensionContainer { { UEMeasurementValueTimeslotISCPListLCR-IEs-ExtIEs} }
   iE-Extensions
                                                                                                                           OPTIONAL,
UEMeasurementValueTimeslotISCPListLCR-IES-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
UEMeasurementValueTimeslotISCPList768 ::= SEQUENCE (SIZE (1..maxNrOfTS)) OF UEMeasurementValueTimeslotISCPList768-IEs
UEMeasurementValueTimeslotISCPList768-IEs ::= SEQUENCE {
                                  TimeSlot,
   dL-TimeslotISCP
                                  DL-TimeslotISCP,
   iE-Extensions
                                  ProtocolExtensionContainer { { UEMeasurementValueTimeslotISCPList768-IEs-ExtIEs} }
                                                                                                                           OPTIONAL,
UEMeasurementValueTimeslotISCPList768-IES-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
                            UEMeasurementValue-Extension
UEMeasurementValue-ExtensionIE RNSAP-PROTOCOL-IES ::= {
UEMeasurementValueInformation ::= CHOICE {
   measurementAvailable
                              UEMeasurementValueInformationAvailable,
                              UEMeasurementValueInformationnotAvailable
   measurementnotAvailable
UEMeasurementValueInformationAvailable::= SEQUENCE {
   uEmeasurementValue
                              UEMeasurementValue,
   ie-Extensions
                              ProtocolExtensionContainer { { UEMeasurementValueInformationAvailableItem-ExtIEs} }
                                                                                                                           OPTIONAL,
UEMeasurementValueInformationAvailableItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UEMeasurementValueInformationnotAvailable ::= NULL
UE-SupportIndicatorExtension ::= BIT STRING (SIZE (32))
-- First bit: Different HS-SCCH In Consecutive TTIs Support Indicator
-- Second bit: HS-SCCH orders in HS-SCCH-less Operation Support Indicator
-- Third bit: RRC Rel-9 (onwards) handling of DL secondary HS-DSCH (de)activation state Support Indicator
-- Fourth bit: UE DTX/DRX related HS-SCCH orders uniform behavior indicator
-- Note that undefined bits are considered as a spare bit and spare bits shall be set to 0 by the transmitter and shall be ignored by the receiver.
UE-State ::= CHOICE {
   cell-fach-pch
                                                             Cell-Fach-Pch-State,
   ura-pch
                                                             Ura-Pch-State,
```

```
Cell-Fach-Pch-State ::= SEOUENCE {
    d-RNTI
                                    D-RNTI.
    iE-Extensions
                                    ProtocolExtensionContainer { { Cell-Fach-Pch-State-ExtIEs} }
                                                                                                         OPTIONAL,
Cell-Fach-Pch-State-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
Ura-Pch-State ::= SEOUENCE {
                                    RNC-ID,
    srnc-id
   ura-id
                                    URA-ID,
                                    ProtocolExtensionContainer { { Ura-Pch-State-ExtIEs} }
    iE-Extensions
Ura-Pch-State-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-Extended-SRNC-ID
                                                CRITICALITY reject EXTENSION Extended-RNC-ID
                                                                                                                         PRESENCE optional
UL-Delta-T2TP ::= INTEGER (0..6,...)
UL-DL-mode ::= ENUMERATED {
   ul-only,
    dl-only,
    both-ul-and-dl
UL-DPDCHIndicatorEDCH ::= ENUMERATED {
    uL-DPDCH-present,
    uL-DPDCH-not-present }
UL-Timeslot-Information::= SEQUENCE ( SIZE (1..maxNrOfTS)) OF UL-Timeslot-InformationItem
UL-Timeslot-InformationItem ::= SEQUENCE {
    timeSlot
                                    TimeSlot,
    midambleShiftAndBurstType
                                    MidambleShiftAndBurstType,
    tFCI-Presence
                                    TFCI-Presence,
    uL-Code-Information
                                    TDD-UL-Code-Information,
    iE-Extensions
                                    ProtocolExtensionContainer { {UL-Timeslot-InformationItem-ExtIEs} } OPTIONAL,
UL-Timeslot-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
```

```
UL-TimeslotLCR-Information ::= SEQUENCE (SIZE (1..maxNrOfULTsLCR)) OF UL-TimeslotLCR-InformationItem
UL-TimeslotLCR-InformationItem ::= SEQUENCE
    timeSlotLCR
                                          TimeSlotLCR,
   midambleShiftLCR
                                          MidambleShiftLCR.
    tFCI-Presence
                                          TFCI-Presence,
    uL-Code-LCR-InformationList
                                      TDD-UL-Code-LCR-Information,
                                          ProtocolExtensionContainer { { UL-TimeslotLCR-InformationItem-ExtIEs} }
   iE-Extensions
                                                                                                                            OPTIONAL,
UL-TimeslotLCR-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    PRESENCE optional },
                                                                         EXTENSION PLCCHinformation
   . . .
PLCCHinformation ::= SEQUENCE {
    tDD-ChannelisationCode
                                          TDD-ChannelisationCode,
    timeSlotLCR
                                          TimeSlotLCR,
   midambleShiftLCR
                                          MidambleShiftLCR,
    sequenceNumber
                                          PLCCHsequenceNumber,
   iE-Extensions
                                          ProtocolExtensionContainer { { PLCCHinformation-ExtIEs} }
                                                                                                                    OPTIONAL,
PLCCHinformation-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UL-Timeslot-Information768::= SEQUENCE ( SIZE (1..maxNrOfTS)) OF UL-Timeslot-InformationItem768
UL-Timeslot-InformationItem768 ::= SEQUENCE {
    timeSlot
                                  TimeSlot,
   midambleShiftAndBurstType768
                                      MidambleShiftAndBurstType768,
                                  TFCI-Presence,
    tFCI-Presence
    uL-Code-Information768
                                      TDD-UL-Code-Information768,
   iE-Extensions
                                  ProtocolExtensionContainer { {UL-Timeslot-InformationItem768-ExtIEs} } OPTIONAL,
UL-Timeslot-InformationItem768-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UL-TimeSlot-ISCP-Info ::= SEQUENCE (SIZE (1..maxNrOfULTs)) OF UL-TimeSlot-ISCP-InfoItem
UL-TimeSlot-ISCP-InfoItem ::= SEQUENCE {
   timeSlot
                              TimeSlot,
   uL-TimeslotISCP
                              UL-TimeslotISCP.
   iE-Extensions
                               ProtocolExtensionContainer { { UL-TimeSlot-ISCP-InfoItem-ExtIEs} } OPTIONAL,
UL-TimeSlot-ISCP-InfoItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    . . .
```

```
UL-TimeSlot-ISCP-LCR-Info ::= SEQUENCE (SIZE (1..maxNrOfULTsLCR)) OF UL-TimeSlot-ISCP-LCR-InfoItem
UL-TimeSlot-ISCP-LCR-InfoItem ::= SEOUENCE {
    timeSlotLCR
                                   TimeSlotLCR,
    iSCP
                                    UL-Timeslot-ISCP-Value,
                                    ProtocolExtensionContainer { { UL-TimeSlot-ISCP-LCR-InfoItem-ExtIEs} }
    iE-Extensions
                                                                                                                        OPTIONAL,
UL-TimeSlot-ISCP-LCR-InfoItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UL-Timeslot-ISCP-Value ::= UL-TimeslotISCP
UL-Timeslot-ISCP-Value-IncrDecrThres ::= INTEGER(0..126)
-- Unit dB. Step 0.5dB
-- e.g. Value 100 means 50dB
UL-TimingAdvanceCtrl-LCR ::= SEQUENCE {
    sync-UL-codes-bitmap
                                                BIT STRING (SIZE(8)),
    fPACH-info
                                                FPACH-Information,
    prxUpPCHdes
                                                INTEGER (-120 .. -58, ...),
    syncUL-procParameter
                                                SYNC-UL-ProcParameters,
                                                INTEGER (1..32),
    mMax
Uplink-Compressed-Mode-Method ::= ENUMERATED {
    sFdiv2,
    higher-layer-scheduling,
UL-SIR
                       ::= INTEGER (-82..173)
-- The UL-SIR gives the UL-SIR in number of 0.1 dB steps.
-- E.g. Value 173 means 17.3 dB
-- Unit dB. Step 0.1 dB.
UC-ID ::= SEOUENCE {
    rNC-ID
                        RNC-ID,
    c-ID
                        C-ID,
    iE-Extensions
                           ProtocolExtensionContainer { {UC-ID-ExtIEs} } OPTIONAL,
UC-ID-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-Extended-RNC-ID
                               CRITICALITY reject
                                                       EXTENSION Extended-RNC-ID PRESENCE optional },
UL-DPCCH-SlotFormat
                          ::= INTEGER (0..5,...)
```

```
UL-FP-Mode ::= ENUMERATED {
    normal.
    silent,
    . . .
UL-PhysCH-SF-Variation ::= ENUMERATED {
    sf-variation-supported,
    sf-variation-not-supported
UL-ScramblingCode ::= SEQUENCE {
    ul-ScramblingCodeNumber
                                UL-ScramblingCodeNumber,
    ul-ScramblingCodeLength
                                UL-ScramblingCodeLength,
    iE-Extensions
                            ProtocolExtensionContainer { {UL-ScramblingCode-ExtIEs} } OPTIONAL
UL-ScramblingCode-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UL-ScramblingCodeLength ::= ENUMERATED {
    short,
    long
UL-ScramblingCodeNumber
                                ::= INTEGER (0..16777215)
UL-Synchronisation-Parameters-LCR ::= SEQUENCE {
    uL-Synchronisation-StepSize
                                        UL-Synchronisation-StepSize,
    uL-Synchronisation-Frequency
                                            UL-Synchronisation-Frequency,
    iE-Extensions
                                    ProtocolExtensionContainer { { UL-Synchronisation-Parameters-LCR-ExtIEs } }
                                                                                                                         OPTIONAL,
UL-Synchronisation-Parameters-LCR-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
UL-Synchronisation-StepSize ::= INTEGER (1..8)
UL-Synchronisation-Frequency ::= INTEGER (1..8)
UL-TimeslotISCP
                        ::= INTEGER (0..127)
-- According to mapping in TS 25.225 [14]
UPPCHPositionLCR ::= INTEGER (0..127)
UpPTSInterferenceValue ::= INTEGER (0..127,...)
Unidirectional-DCH-Indicator
                                ::= ENUMERATED {
    downlink-DCH-only,
    uplink-DCH-only
```

```
URA-ID
                       ::= INTEGER (0..65535)
URA-Information ::= SEQUENCE {
    uRA-ID
                                        URA-ID,
   multipleURAsIndicator
                                        MultipleURAsIndicator,
   rNCsWithCellsInTheAccessedURA-List RNCsWithCellsInTheAccessedURA-List OPTIONAL,
    iE-Extensions
                                        ProtocolExtensionContainer { {URA-Information-ExtIEs} } OPTIONAL,
URA-Information-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
    { ID id-Extended-RNC-ID
                                                CRITICALITY reject EXTENSION Extended-RNC-ID
                                                                                                                 PRESENCE optional },
    . . .
RNCsWithCellsInTheAccessedURA-List ::= SEOUENCE (SIZE (1..maxRNCinURA-1)) OF RNCsWithCellsInTheAccessedURA-Item
RNCsWithCellsInTheAccessedURA-Item ::= SEOUENCE {
   rNC-TD
                                    RNC-ID,
                                    ProtocolExtensionContainer { {RNCsWithCellsInTheAccessedURA-Item-ExtIEs} } OPTIONAL,
   iE-Extensions
RNCsWithCellsInTheAccessedURA-Item-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
USCH-ID
                       ::= INTEGER (0..255)
USCH-Information ::= SEQUENCE (SIZE (1..maxNoOfUSCHs)) OF USCH-InformationItem
USCH-InformationItem ::= SEQUENCE {
   uSCH-ID
                                        USCH-ID,
    ul-CCTrCH-ID
                                        CCTrCH-ID,
    trChSourceStatisticsDescriptor
                                        TrCH-SrcStatisticsDescr,
    transportFormatSet
                                        TransportFormatSet,
    allocationRetentionPriority
                                        AllocationRetentionPriority,
    schedulingPriorityIndicator
                                        SchedulingPriorityIndicator,
    rb-Info
                                        RB-Info,
                                        ProtocolExtensionContainer { {USCH-InformationItem-ExtIEs} } OPTIONAL,
    iE-Extensions
USCH-InformationItem-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
     ID id-TrafficClass
                                            CRITICALITY ignore EXTENSION TrafficClass
                                                                                                  PRESENCE mandatory | |
    { ID id-BindingID
                                            CRITICALITY ignore EXTENSION BindingID
                                                                                                  PRESENCE optional |
    -- Shall be ignored if bearer establishment with ALCAP.
    { ID id-TransportLayerAddress
                                            CRITICALITY ignore EXTENSION TransportLayerAddress PRESENCE optional |
    -- Shall be ignored if bearer establishment with ALCAP.
    { ID id-TnlOos
                                            CRITICALITY ignore EXTENSION TnlOos
                                                                                                  PRESENCE optional },
```

```
Usefulness-Of-Battery-Optimization ::= ENUMERATED {can-benefit, cannot-benefit}
User-Plane-Congestion-Fields-Inclusion
                                            ::= ENUMERATED { shall-be-included }
Uu-ActivationState ::= ENUMERATED {
    activated,
    de-activated,
UMTS-Cells-Info-List ::= SEQUENCE (SIZE (0..maxNrOfCells)) OF ProtocolIE-Single-Container { (UMTS-Cells-Info-IEs} }
UMTS-Cells-Info-IEs RNSAP-PROTOCOL-IES ::= {
    { ID id-UMTS-Cells-Info CRITICALITY ignore TYPE UMTS-Cell-Info
                                                                        PRESENCE optional }
UMTS-Cell-Info ::= SEOUENCE{
                                        C-ID,
                                        ProtocolExtensionContainer { { UMTS-Cell-Info-ExtIEs} } OPTIONAL,
    iE-Extensions
UMTS-Cell-Info-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
-- X
-- Z
END
```

9.3.5 Common Definitions

```
-- Extension constants
__ *********************
maxPrivateIEs
                                          INTEGER ::= 65535
maxProtocolExtensions
                                          INTEGER ::= 65535
maxProtocolIEs
                                          INTEGER ::= 65535
-- Common Data Types
__ ********************
Criticality
              ::= ENUMERATED { reject, ignore, notify }
              ::= ENUMERATED { optional, conditional, mandatory }
Presence
PrivateIE-ID ::= CHOICE {
   local
                    INTEGER (0.. maxPrivateIEs),
   global
                     OBJECT IDENTIFIER
ProcedureCode
               ::= INTEGER (0..255)
ProcedureID ::= SEQUENCE {
                         ProcedureCode,
   procedureCode
   ddMode
                     ENUMERATED { tdd, fdd, common, ... }
ProtocolIE-ID
              ::= INTEGER (0..maxProtocolIEs)
TransactionID
              ::= CHOICE {
   shortTransActionId INTEGER (0..127),
   longTransActionId INTEGER (0..32767)
TriggeringMessage ::= ENUMERATED { initiating-message, successful-outcome, unsuccessful-outcome, outcome }
END
```

9.3.6 Constant Definitions

```
DEFINITIONS AUTOMATIC TAGS ::=
BEGIN
IMPORTS
   ProcedureCode,
   ProtocolIE-ID
FROM RNSAP-CommonDataTypes;
  ****************
  Elementary Procedures
  *****************
id-commonTransportChannelResourcesInitialisation
                                                          ProcedureCode ::= 0
                                                          ProcedureCode ::= 1
id-commonTransportChannelResourcesRelease
id-compressedModeCommand
                                                          ProcedureCode ::= 2
id-downlinkPowerControl
                                                          ProcedureCode ::= 3
id-downlinkPowerTimeslotControl
                                                          ProcedureCode ::= 4
id-downlinkSignallingTransfer
                                                          ProcedureCode ::= 5
id-errorIndication
                                                          ProcedureCode ::= 6
id-dedicatedMeasurementFailure
                                                          ProcedureCode ::= 7
id-dedicatedMeasurementInitiation
                                                          ProcedureCode ::= 8
id-dedicatedMeasurementReporting
                                                          ProcedureCode ::= 9
id-dedicatedMeasurementTermination
                                                          ProcedureCode ::= 10
id-paging
                                                          ProcedureCode ::= 11
id-physicalChannelReconfiguration
                                                          ProcedureCode ::= 12
                                                          ProcedureCode ::= 13
id-privateMessage
id-radioLinkAddition
                                                          ProcedureCode ::= 14
id-radioLinkCongestion
                                                          ProcedureCode ::= 34
id-radioLinkDeletion
                                                          ProcedureCode ::= 15
id-radioLinkFailure
                                                          ProcedureCode ::= 16
id-radioLinkPreemption
                                                          ProcedureCode ::= 17
                                                          ProcedureCode ::= 18
id-radioLinkRestoration
                                                          ProcedureCode ::= 19
id-radioLinkSetup
id-relocationCommit
                                                          ProcedureCode ::= 20
id-synchronisedRadioLinkReconfigurationCancellation
                                                          ProcedureCode ::= 21
                                                          ProcedureCode ::= 22
id-synchronisedRadioLinkReconfigurationCommit
id-synchronisedRadioLinkReconfigurationPreparation
                                                          ProcedureCode ::= 23
id-unSynchronisedRadioLinkReconfiguration
                                                          ProcedureCode ::= 24
id-uplinkSignallingTransfer
                                                          ProcedureCode ::= 25
id-commonMeasurementFailure
                                                          ProcedureCode ::= 26
id-commonMeasurementInitiation
                                                          ProcedureCode ::= 27
id-commonMeasurementReporting
                                                          ProcedureCode ::= 28
id-commonMeasurementTermination
                                                          ProcedureCode ::= 29
                                                          ProcedureCode ::= 30
id-informationExchangeFailure
id-informationExchangeInitiation
                                                          ProcedureCode ::= 31
id-informationReporting
                                                          ProcedureCode ::= 32
id-informationExchangeTermination
                                                          ProcedureCode ::= 33
id-reset
                                                          ProcedureCode ::= 35
id-radioLinkActivation
                                                          ProcedureCode ::= 36
id-gERANuplinkSignallingTransfer
                                                          ProcedureCode ::= 37
id-radioLinkParameterUpdate
                                                          ProcedureCode ::= 38
```

```
id-uEMeasurementFailure
                                                           ProcedureCode ::= 39
id-uEMeasurementInitiation
                                                           ProcedureCode ::= 40
id-uEMeasurementReporting
                                                           ProcedureCode ::= 41
id-uEMeasurementTermination
                                                           ProcedureCode ::= 42
id-iurDeactivateTrace
                                                           ProcedureCode ::= 43
id-iurInvokeTrace
                                                           ProcedureCode ::= 44
id-mBMSAttach
                                                           ProcedureCode ::= 45
id-mBMSDetach
                                                           ProcedureCode ::= 46
id-directInformationTransfer
                                                           ProcedureCode ::= 48
id-enhancedRelocation
                                                           ProcedureCode ::= 49
id-enhancedRelocationCancel
                                                           ProcedureCode ::= 50
                                                           ProcedureCode ::= 51
id-enhancedRelocationSignallingTransfer
id-enhancedRelocationRelease
                                                           ProcedureCode ::= 52
id-mBSFNMCCHInformation
                                                           ProcedureCode ::= 53
id-secondaryULFrequencyReporting
                                                           ProcedureCode ::= 54
id-secondaryULFrequencyUpdate
                                                           ProcedureCode ::= 55
                                                           ProcedureCode ::= 56
id-informationTransferControl
                                                           ProcedureCode ::= 60
id-enhancedRelocationResourceAllocation
id-enhancedRelocationResourceRelease
                                                           ProcedureCode ::= 61
-- Lists
__ **********************
maxCellSIB11OrSIB12
                                       INTEGER ::= 32
maxCellsMeas
                                       INTEGER ::= 8
                                       INTEGER ::= 256
maxRateMatching
                                       INTEGER ::= 10
maxNoOfDSCHs
maxNoOfDSCHsLCR
                                       INTEGER ::= 10
maxNoOfRB
                                       INTEGER ::= 32
maxNoOfUSCHs
                                       INTEGER ::= 10
maxNoOfUSCHsLCR
                                       INTEGER ::= 10
maxNrOfTFCs
                                       INTEGER ::= 1024
maxNrOfTFs
                                       INTEGER ::= 32
maxNrOfCCTrCHs
                                       INTEGER ::= 16
maxNrOfCCTrCHsLCR
                                       INTEGER ::= 16
                                       INTEGER ::= 128
maxNrOfDCHs
maxNrOfDL-Codes
                                       INTEGER ::= 8
maxNrOfDPCHs
                                       INTEGER ::= 240
maxNrOfDPCHsPerRL-1
                                       INTEGER ::= 239 -- maxNrofCCTrCH*maxNrOfULTs-1
maxNrOfDPCHsLCR
                                       INTEGER ::= 240
maxNrOfDPCHsLCRPerRL-1
                                       INTEGER ::= 95 -- maxNrofCCTrCH*maxNrOfULTsLCR-1
maxNrOfDPCHs768
                                       INTEGER ::= 480
maxNrOfDPCHs768PerRL-1
                                       INTEGER ::= 479
maxNrOfErrors
                                       INTEGER ::= 256
maxNrOfMACcshSDU-Length
                                       INTEGER ::= 16
maxNrOfMBMSServices
                                       INTEGER ::= 128
maxNrOfActiveMBMSServices
                                       INTEGER ::= 256
                                       INTEGER ::= 15
maxNrOfPoints
maxNrOfRLs
                                       INTEGER ::= 16
maxNrOfRLSets
                                       INTEGER ::= maxNrOfRLs
                                       INTEGER ::= 15 -- maxNrOfRLSets - 1
maxNrOfRLSets-1
```

```
INTEGER ::= 15 -- maxNrOfRLs - 1
maxNrOfRLs-1
                                        INTEGER ::= 14 -- maxNrOfRLs - 2
maxNrOfRLs-2
maxNrOfUEs
                                        INTEGER ::= 4096
maxNrOfULTs
                                        INTEGER ::= 15
maxNrOfULTsLCR
                                        INTEGER ::= 6
                                        INTEGER ::= 15
maxNrOfDLTs
maxNrOfDLTsLCR
                                        INTEGER ::= 6
maxRNCinURA-1
                                        INTEGER ::= 15
maxTTT-Count
                                        INTEGER ::= 4
                                        INTEGER ::= 16777215
maxCTFC
maxNrOfNeighbouringRNCs
                                        INTEGER ::= 10
maxNrOfFDDNeighboursPerRNC
                                        INTEGER ::= 256
maxNrOfGSMNeighboursPerRNC
                                        INTEGER ::= 256
maxNrOfTDDNeighboursPerRNC
                                        INTEGER ::= 256
maxNrOfFACHs
                                        INTEGER ::= 8
maxNrOfLCRTDDNeighboursPerRNC
                                        INTEGER ::= 256
                                        INTEGER ::= 16
maxIBSEG
maxNrOfSCCPCHs
                                        INTEGER ::= 8
maxNrOfSCCPCHs768
                                        INTEGER ::= 16
maxTGPS
                                        INTEGER ::= 6
maxNrOfTS
                                        INTEGER ::= 15
maxNrOfLevels
                                        INTEGER ::= 256
maxNrOfTsLCR
                                        INTEGER ::= 6
maxNoSat
                                        INTEGER ::= 16
maxNoGPSTypes
                                        INTEGER ::= 8
maxNrOfMeasNCell
                                        INTEGER ::= 96
maxNrOfMeasNCell-1
                                        INTEGER ::= 95
                                                        -- maxNrOfMeasNCell - 1
maxResetContext
                                        INTEGER ::= 250
maxResetContextGroup
                                        INTEGER ::= 32
                                        INTEGER ::= 8
maxNrOfHAROProc
maxNrOfHSSCCHCodes
                                        INTEGER ::= 4
maxNrOfHSSICHs
                                        INTEGER ::= 4
maxNrOfHSSICHs-1
                                        INTEGER ::= 3
maxNrOfMACdFlows
                                        INTEGER ::= 8
maxNrOfMACdFlows-1
                                        INTEGER ::= 7
                                                         -- maxNrOfMACdFlows - 1
maxNrOfMACdPDUSize
                                        INTEGER ::= 32
maxNrOfPDUIndexes
                                        INTEGER ::= 8
                                        INTEGER ::= 7
                                                         -- maxNrOfPDUIndexes - 1
maxNrOfPDUIndexes-1
maxNrOfPrioOueues
                                        INTEGER ::= 8
maxNrOfPrioOueues-1
                                        INTEGER ::= 7 -- maxNrOfPrioOueues - 1
maxNrOfSNAs
                                         INTEGER ::= 65536
maxNrOfSatAlmanac-maxNoSat
                                        INTEGER ::= 16
maxNrOfGERANSI
                                        INTEGER ::= 8
maxNrOfInterfaces
                                        INTEGER ::= 16
maxNrofSiqSeqERGHICH-1
                                        INTEGER ::= 39
maxNrOfCells
                                        INTEGER ::= 65536
maxNrOfAddFreq
                                        INTEGER ::= 8
maxNrOfCellsPerFreq
                                        INTEGER ::= 65536
maxNrOfEDCHMACdFlows-1
                                        INTEGER ::= 7
maxNrOfEDCH-HARO-PO-OUANTSTEPs
                                        INTEGER ::= 6
maxNrOfEDPCCH-PO-QUANTSTEPs
                                        INTEGER ::= 8
maxNrOfEDCHHARQProcesses2msEDCH
                                        INTEGER ::= 8
maxNrOfBits-MACe-PDU-non-scheduled
                                        INTEGER ::= 19982
maxNrOfRefETFCIs
                                        INTEGER ::= 8
```

```
maxNrOfRefETFCI-PO-QUANTSTEPs
                                        INTEGER ::= 29
maxNrOfEDCHMACdFlows
                                        INTEGER ::= 8
maxNoOfLogicalChannels
                                        INTEGER ::= 16 -- only maximum 15 can be used
maxNrOfRefBetas
                                        INTEGER ::= 8
maxNrOfEAGCHCodes
                                        INTEGER ::= 4
                                        INTEGER ::= 90
maxNrOfHS-DSCHTBSs
maxNrOfHS-DSCHTBSs-HS-SCCHless
                                        INTEGER ::= 4
                                        INTEGER ::= 15
maxHS-PDSCHCodeNrComp-1
maxNrOfEHICHCodes
                                        INTEGER ::= 4
maxGANSSSat
                                        INTEGER ::= 64
maxNoGANSS
                                        INTEGER ::= 8
maxSgnType
                                        INTEGER ::= 8
                                        INTEGER ::= 5
maxNrOfBroadcastPLMNs
maxHSDPAFrequency
                                        INTEGER ::= 8
maxHSDPAFrequency-1
                                        INTEGER ::= 7
maxFrequencyinCell
                                        INTEGER ::= 12
maxFrequencyinCell-1
                                        INTEGER ::= 11
maxGANSSSatAlmanac
                                        INTEGER ::= 36
maxGANSSClockMod
                                        INTEGER ::= 4
maxNrOfEDCHRLs
                                        INTEGER ::= 4
maxEARECN
                                        INTEGER ::= 65535
maxNrOfEUTRANeighboursPerRNC
                                        INTEGER ::= 256
maxNrOfMCCHMessages
                                        INTEGER ::= 5
maxNrOfMBMSL3
                                        INTEGER ::= 64
maxNrOfEDCHMACdFlowsLCR
                                        INTEGER ::= 256
maxNrOfEDCHMACdFlowsLCR-1
                                        INTEGER ::= 255
maxNrOfPreconfiguredNeighbours
                                        INTEGER ::= 256
maxNrOfHSDSCH-1
                                        INTEGER ::= 32
maxNrOfHSDSCH
                                        INTEGER ::= 33
maxGANSS-1
                                        INTEGER ::= 7
maxlengthMBMSconcatservlists
                                        INTEGER ::= 96
maxNoOfTBSs-Mapping-HS-DSCH-SPS
                                        INTEGER ::= 4
maxNoOfTBSs-Mapping-HS-DSCH-SPS-1
                                        INTEGER ::= 3
maxNoOfHS-DSCH-TBSsLCR
                                        INTEGER ::= 64
maxNoOfRepetition-Period-LCR
                                        INTEGER ::= 4
                                        INTEGER ::= 3
maxNoOfRepetitionPeriod-SPS-LCR-1
maxNoOf-HS-SICH-SPS
                                        INTEGER ::= 4
                                        INTEGER ::= 3
maxNoOf-HS-SICH-SPS-1
                                        INTEGER ::= 4
maxNoOfNon-HS-SCCH-Assosiated-HS-SICH
maxNrOfEDCH-1
                                        INTEGER ::= 32
maxNrOfDCHMeasurementOccasionPatternSequence
                                                INTEGER ::= 6
maxNrOfULCarriersLCR-1
                                        INTEGER ::= 5
maxNrOfCellIds
                                        INTEGER ::= 32
maxNrOfRAIs
                                        INTEGER ::= 8
maxNrOfLAIs
                                        INTEGER ::= 8
maxNrOfExtendedNeighbouringRNCs
                                        INTEGER ::= 64
maxNoOfGsmCell
                                        INTEGER ::= 128
maxNrOfANRCells
                                        INTEGER ::= 256
maxFregBandsTDD
                                        INTEGER ::= 16
```

⁻⁻ IEs

id-AllowedOueuingTime ProtocolIE-ID ::= 4 id-Allowed-Rate-Information ProtocolIE-ID ::= 42 id-AntennaColocationIndicator ProtocolIE-ID ::= 309 id-BindingID ProtocolIE-ID ::= 5 id-C-ID ProtocolIE-ID ::= 6 id-C-RNTT ProtocolTE-TD ::= 7 id-Cell-Capacity-Class-Value ProtocolIE-ID ::= 303 id-CFN ProtocolIE-ID ::= 8 id-CN-CS-DomainIdentifier ProtocolIE-ID ::= 9 id-CN-PS-DomainIdentifier ProtocolIE-ID ::= 10 id-Cause ProtocolIE-ID ::= 11 id-CoverageIndicator ProtocolIE-ID ::= 310 id-CriticalityDiagnostics ProtocolIE-ID ::= 20 id-ContextInfoItem-Reset ProtocolIE-ID ::= 211 id-ContextGroupInfoItem-Reset ProtocolIE-ID ::= 515 id-D-RNTI ProtocolIE-ID ::= 21 id-D-RNTI-ReleaseIndication ProtocolIE-ID ::= 22 id-DCHs-to-Add-FDD ProtocolTE-TD ::= 26 id-DCHs-to-Add-TDD ProtocolIE-ID ::= 27 id-DCH-DeleteList-RL-ReconfPrepFDD ProtocolIE-ID ::= 30 id-DCH-DeleteList-RL-ReconfPrepTDD ProtocolIE-ID ::= 31 id-DCH-DeleteList-RL-ReconfRgstFDD ProtocolIE-ID ::= 32 id-DCH-DeleteList-RL-ReconfRastTDD ProtocolIE-ID ::= 33 id-DCH-FDD-Information ProtocolIE-ID ::= 34 id-DCH-TDD-Information ProtocolIE-ID ::= 35 id-FDD-DCHs-to-Modify ProtocolIE-ID ::= 39 id-TDD-DCHs-to-Modify ProtocolIE-ID ::= 40 id-DCH-InformationResponse ProtocolIE-ID ::= 43 id-DCH-Rate-InformationItem-RL-CongestInd ProtocolIE-ID ::= 38 id-DL-CCTrCH-InformationAddItem-RL-ReconfPrepTDD ProtocolIE-ID ::= 44 id-DL-CCTrCH-InformationListIE-RL-ReconfReadyTDD ProtocolIE-ID ::= 45 id-DL-CCTrCH-InformationDeleteItem-RL-ReconfRgstTDD ProtocolIE-ID ::= 46 id-DL-CCTrCH-InformationItem-RL-SetupRgstTDD ProtocolIE-ID ::= 47 id-DL-CCTrCH-InformationListIE-PhyChReconfRqstTDD ProtocolIE-ID ::= 48 id-DL-CCTrCH-InformationListIE-RL-AdditionRspTDD ProtocolIE-ID ::= 49 id-DL-CCTrCH-InformationListIE-RL-SetupRspTDD ProtocolIE-ID ::= 50 id-DL-CCTrCH-InformationAddList-RL-ReconfPrepTDD ProtocolIE-ID ::= 51 id-DL-CCTrCH-InformationDeleteList-RL-ReconfRqstTDD ProtocolIE-ID ::= 52 id-DL-CCTrCH-InformationList-RL-SetupRgstTDD ProtocolIE-ID ::= 53 id-FDD-DL-CodeInformation ProtocolIE-ID ::= 54 id-DL-DPCH-Information-RL-ReconfPrepFDD ProtocolIE-ID ::= 59 id-DL-DPCH-Information-RL-SetupRqstFDD ProtocolIE-ID ::= 60 id-DL-DPCH-Information-RL-ReconfRgstFDD ProtocolIE-ID ::= 61 id-DL-DPCH-InformationItem-PhvChReconfRgstTDD ProtocolIE-ID ::= 62 id-DL-DPCH-InformationItem-RL-AdditionRspTDD ProtocolIE-ID ::= 63 id-DL-DPCH-InformationItem-RL-SetupRspTDD ProtocolIE-ID ::= 64 id-DL-DPCH-TimingAdjustment ProtocolIE-ID ::= 278 id-DLReferencePower ProtocolIE-ID ::= 67 id-DLReferencePowerList-DL-PC-Rgst ProtocolIE-ID ::= 68 id-DL-ReferencePowerInformation-DL-PC-Rgst ProtocolIE-ID ::= 69 id-DPC-Mode ProtocolIE-ID ::= 12

```
id-DRXCycleLengthCoefficient
                                                                             ProtocolIE-ID ::= 70
id-DedicatedMeasurementObjectType-DM-Fail-Ind
                                                                            ProtocolIE-ID ::= 470
id-DedicatedMeasurementObjectType-DM-Fail
                                                                             ProtocolIE-ID ::= 471
id-DedicatedMeasurementObjectType-DM-Rprt
                                                                            ProtocolIE-ID ::= 71
id-DedicatedMeasurementObjectType-DM-Rgst
                                                                            ProtocolIE-ID ::= 72
id-DedicatedMeasurementObjectType-DM-Rsp
                                                                            ProtocolIE-ID ::= 73
id-DedicatedMeasurementType
                                                                             ProtocolIE-ID ::= 74
id-FACH-InfoForUESelectedS-CCPCH-CTCH-ResourceRspFDD
                                                                            ProtocolIE-ID ::= 82
id-FACH-InfoForUESelectedS-CCPCH-CTCH-ResourceRspTDD
                                                                            ProtocolTE-TD ::= 83
id-Guaranteed-Rate-Information
                                                                             ProtocolIE-ID ::= 41
id-TMST
                                                                            ProtocolIE-ID ::= 84
id-HCS-Prio
                                                                             ProtocolIE-ID ::= 311
id-L3-Information
                                                                             ProtocolIE-ID ::= 85
id-AdjustmentPeriod
                                                                             ProtocolIE-ID ::= 90
id-MaxAdjustmentStep
                                                                            ProtocolIE-ID ::= 91
id-MeasurementFilterCoefficient
                                                                             ProtocolIE-ID ::= 92
id-MessageStructure
                                                                             ProtocolIE-ID ::= 57
id-MeasurementID
                                                                             ProtocolIE-ID ::= 93
id-Neighbouring-GSM-CellInformation
                                                                             ProtocolIE-ID ::= 13
id-Neighbouring-UMTS-CellInformationItem
                                                                            ProtocolIE-ID ::= 95
id-NRT-Load-Information-Value
                                                                             ProtocolTE-TD ::= 305
id-NRT-Load-Information-Value-IncrDecrThres
                                                                            ProtocolIE-ID ::= 306
id-PagingArea-PagingRgst
                                                                             ProtocolIE-ID ::= 102
id-FACH-FlowControlInformation
                                                                             ProtocolIE-ID ::= 103
id-PartialReportingIndicator
                                                                             ProtocolIE-ID ::= 472
id-Permanent-NAS-UE-Identity
                                                                             ProtocolIE-ID ::= 17
id-PowerAdjustmentType
                                                                             ProtocolIE-ID ::= 107
id-RANAP-RelocationInformation
                                                                             ProtocolIE-ID ::= 109
id-RL-Information-PhyChReconfRgstFDD
                                                                            ProtocolIE-ID ::= 110
id-RL-Information-PhyChReconfRgstTDD
                                                                             ProtocolIE-ID ::= 111
id-RL-Information-RL-AdditionRgstFDD
                                                                             ProtocolIE-ID ::= 112
id-RL-Information-RL-AdditionRqstTDD
                                                                             ProtocolIE-ID ::= 113
id-RL-Information-RL-DeletionRgst
                                                                             ProtocolIE-ID ::= 114
id-RL-Information-RL-FailureInd
                                                                             ProtocolIE-ID ::= 115
id-RL-Information-RL-ReconfPrepFDD
                                                                             ProtocolIE-ID ::= 116
                                                                            ProtocolIE-ID ::= 117
id-RL-Information-RL-RestoreInd
id-RL-Information-RL-SetupRgstFDD
                                                                             ProtocolIE-ID ::= 118
id-RL-Information-RL-SetupRgstTDD
                                                                             ProtocolIE-ID ::= 119
id-RL-InformationItem-RL-CongestInd
                                                                             ProtocolIE-ID ::= 55
id-RL-InformationItem-DM-Rprt
                                                                             ProtocolIE-ID ::= 120
id-RL-InformationItem-DM-Rgst
                                                                             ProtocolIE-ID ::= 121
id-RL-InformationItem-DM-Rsp
                                                                             ProtocolIE-ID ::= 122
id-RL-InformationItem-RL-PreemptRequiredInd
                                                                            ProtocolIE-ID ::= 2
id-RL-InformationItem-RL-SetupRqstFDD
                                                                             ProtocolIE-ID ::= 123
id-RL-InformationList-RL-CongestInd
                                                                             ProtocolIE-ID ::= 56
id-RL-InformationList-RL-AdditionRgstFDD
                                                                            ProtocolIE-ID ::= 124
id-RL-InformationList-RL-DeletionRgst
                                                                            ProtocolIE-ID ::= 125
id-RL-InformationList-RL-PreemptRequiredInd
                                                                            ProtocolIE-ID ::= 1
id-RL-InformationList-RL-ReconfPrepFDD
                                                                             ProtocolIE-ID ::= 126
id-RL-InformationResponse-RL-AdditionRspTDD
                                                                            ProtocolIE-ID ::= 127
id-RL-InformationResponse-RL-ReconfReadyTDD
                                                                            ProtocolIE-ID ::= 128
id-RL-InformationResponse-RL-SetupRspTDD
                                                                             ProtocolIE-ID ::= 129
id-RL-InformationResponseItem-RL-AdditionRspFDD
                                                                            ProtocolIE-ID ::= 130
id-RL-InformationResponseItem-RL-ReconfReadyFDD
                                                                            ProtocolIE-ID ::= 131
```

id-RL-InformationResponseItem-RL-ReconfRspFDD	ProtocolIE-ID ::= 132
id-RL-InformationResponseItem-RL-SetupRspFDD	ProtocolIE-ID ::= 133
id-RL-InformationResponseList-RL-AdditionRspFDD	ProtocolIE-ID ::= 134
id-RL-InformationResponseList-RL-ReconfReadyFDD	ProtocolIE-ID ::= 135
id-RL-InformationResponseList-RL-ReconfRspFDD	ProtocolIE-ID ::= 136
id-RL-InformationResponse-RL-ReconfRspTDD	ProtocolIE-ID ::= 28
id-RL-InformationResponseList-RL-SetupRspFDD	ProtocolIE-ID ::= 137
id-RL-ReconfigurationFailure-RL-ReconfFail	ProtocolIE-ID ::= 141
id-RL-Set-InformationItem-DM-Rprt	ProtocolIE-ID ::= 143
id-RL-Set-InformationItem-DM-Rqst	ProtocolIE-ID ::= 144
id-RL-Set-InformationItem-DM-Rsp	ProtocolIE-ID ::= 145
id-RL-Set-Information-RL-FailureInd	ProtocolIE-ID ::= 146
id-RL-Set-Information-RL-RestoreInd	ProtocolIE-ID ::= 147
id-RL-Set-Successful-InformationItem-DM-Fail	ProtocolIE-ID ::= 473
id-RL-Set-Unsuccessful-InformationItem-DM-Fail	ProtocolIE-ID ::= 474
id-RL-Set-Unsuccessful-InformationItem-DM-Fail-Ind	ProtocolIE-ID ::= 475
id-RL-Successful-InformationItem-DM-Fail	ProtocolIE-ID ::= 476
id-RL-Unsuccessful-InformationItem-DM-Fail	ProtocolIE-ID ::= 477
id-RL-Unsuccessful-InformationItem-DM-Fail-Ind	ProtocolIE-ID ::= 478
id-ReportCharacteristics	ProtocolIE-ID ::= 152
id-Reporting-Object-RL-FailureInd	ProtocolIE-ID ::= 153
id-Reporing-Object-RL-RestoreInd	ProtocolIE-ID ::= 154
id-RT-Load-Value	ProtocolIE-ID ::= 307
id-RT-Load-Value-IncrDecrThres	ProtocolIE-ID ::= 308
id-S-RNTI	ProtocolIE-ID ::= 155
id-ResetIndicator	ProtocolIE-ID ::= 244
id-RNC-ID	ProtocolIE-ID ::= 245
id-SAI	ProtocolIE-ID ::= 156
id-SRNC-ID	ProtocolIE-ID ::= 157
id-SuccessfulRL-InformationResponse-RL-AdditionFailureFDD	ProtocolIE-ID ::= 159
id-SuccessfulRL-InformationResponse-RL-SetupFailureFDD	ProtocolIE-ID ::= 160
id-TransportBearerID	ProtocolIE-ID ::= 163
id-TransportBearerRequestIndicator	ProtocolIE-ID ::= 164
id-TransportLayerAddress	ProtocolIE-ID ::= 165
id-TypeOfError	ProtocolIE-ID ::= 140
id-UC-ID	ProtocolIE-ID ::= 166
id-UL-CCTrCH-AddInformation-RL-ReconfPrepTDD	ProtocolIE-ID ::= 167
id-UL-CCTrCH-InformationAddList-RL-ReconfPrepTDD	ProtocolIE-ID ::= 169
id-UL-CCTrCH-InformationItem-RL-SetupRqstTDD	ProtocolIE-ID ::= 171
id-UL-CCTrCH-InformationList-RL-SetupRqstTDD	ProtocolIE-ID ::= 172
id-UL-CCTrCH-InformationListIE-PhyChReconfRqstTDD	ProtocolIE-ID ::= 173
id-UL-CCTrCH-InformationListIE-RL-AdditionRspTDD	ProtocolIE-ID ::= 174
id-UL-CCTrCH-InformationListIE-RL-ReconfReadyTDD	ProtocolIE-ID ::= 175
id-UL-CCTrCH-InformationListIE-RL-SetupRspTDD	ProtocolIE-ID ::= 176
id-UL-DPCH-Information-RL-ReconfPrepFDD	ProtocolIE-ID ::= 177
id-UL-DPCH-Information-RL-ReconfRqstFDD	ProtocolIE-ID ::= 178
id-UL-DPCH-Information-RL-SetupRqstFDD	ProtocolIE-ID ::= 179
id-UL-DPCH-InformationItem-PhyChReconfRqstTDD	ProtocolIE-ID ::= 180
id-UL-DPCH-InformationItem-RL-AdditionRspTDD	ProtocolIE-ID ::= 181
id-UL-DPCH-InformationItem-RL-SetupRspTDD	ProtocolIE-ID ::= 182
id-UL-DPCH-InformationAddListIE-RL-ReconfReadyTDD	ProtocolIE-ID ::= 183
id-UL-SIRTarget	ProtocolIE-ID ::= 184
id-URA-Information	ProtocolIE-ID ::= 185
id-UnsuccessfulRL-InformationResponse-RL-AdditionFailureFDD	ProtocolIE-ID ::= 188
-	

id-UnsuccessfulRL-InformationResponse-RL-SetupFailureFDD	ProtocolIE-ID ::= 189
id-UnsuccessfulRL-InformationResponse-RL-SetupFailureTDD	ProtocolIE-ID ::= 190
id-Active-Pattern-Sequence-Information	ProtocolIE-ID ::= 193
id-AdjustmentRatio	ProtocolIE-ID ::= 194
id-CauseLevel-RL-AdditionFailureFDD	ProtocolIE-ID ::= 197
id-CauseLevel-RL-AdditionFailureTDD	ProtocolIE-ID ::= 198
id-CauseLevel-RL-ReconfFailure	ProtocolIE-ID ::= 199
id-CauseLevel-RL-SetupFailureFDD	ProtocolIE-ID ::= 200
id-CauseLevel-RL-SetupFailureTDD	ProtocolIE-ID ::= 201
id-DL-CCTrCH-InformationDeleteItem-RL-ReconfPrepTDD	ProtocolIE-ID ::= 205
id-DL-CCTrCH-InformationModifyItem-RL-ReconfPrepTDD	ProtocolIE-ID ::= 206
id-DL-CCTrCH-InformationModifyItem-RL-ReconfRqstTDD	ProtocolIE-ID ::= 207
id-DL-CCTrCH-InformationDeleteList-RL-ReconfPrepTDD	ProtocolIE-ID ::= 208
id-DL-CCTrCH-InformationModifyList-RL-ReconfPrepTDD	ProtocolIE-ID ::= 209
id-DL-CCTrCH-InformationModifyList-RL-ReconfRqstTDD	ProtocolIE-ID ::= 210
id-DL-DPCH-InformationAddListIE-RL-ReconfReadyTDD	ProtocolIE-ID ::= 212
id-DL-DPCH-InformationDeleteListIE-RL-ReconfReadyTDD	ProtocolIE-ID ::= 213
id-DL-DPCH-InformationModifyListIE-RL-ReconfReadyTDD	ProtocolIE-ID ::= 214
id-DSCHs-to-Add-TDD	ProtocolIE-ID ::= 215
id-Unused-ProtocolIE-ID-216	ProtocolIE-ID ::= 216
id-DSCH-DeleteList-RL-ReconfPrepTDD	ProtocolIE-ID ::= 217
id-Unused-ProtocolIE-ID-218	ProtocolIE-ID ::= 218
id-Unused-ProtocolIE-ID-219	ProtocolIE-ID ::= 219
id-DSCH-InformationListIE-RL-AdditionRspTDD	ProtocolIE-ID ::= 220
id-DSCH-InformationListIEs-RL-SetupRspTDD	ProtocolIE-ID ::= 221
id-DSCH-TDD-Information	ProtocolIE-ID ::= 222
id-Unused-ProtocolIE-ID-223	ProtocolIE-ID ::= 223
id-Unused-ProtocolIE-ID-226	ProtocolIE-ID ::= 226
id-DSCH-ModifyList-RL-ReconfPrepTDD	ProtocolIE-ID ::= 227
id-Unused-ProtocolIE-ID-228	ProtocolIE-ID ::= 228
id-Unused-ProtocolIE-ID-324	ProtocolIE-ID ::= 324
id-Unused-ProtocolIE-ID-229	ProtocolIE-ID ::= 229
id-DSCHToBeAddedOrModifiedList-RL-ReconfReadyTDD	ProtocolIE-ID ::= 230
id-Unused-ProtocolIE-ID-29	ProtocolIE-ID ::= 29
id-Unused-ProtocolIE-ID-225	ProtocolIE-ID ::= 225
id-GA-Cell	ProtocolIE-ID ::= 232
id-GA-CellAdditionalShapes	ProtocolIE-ID ::= 3
id-Unused-ProtocolIE-ID-246	ProtocolIE-ID ::= 246
id-Transmission-Gap-Pattern-Sequence-Information	ProtocolIE-ID ::= 255
id-UL-CCTrCH-DeleteInformation-RL-ReconfPrepTDD	ProtocolIE-ID ::= 256
id-UL-CCTrCH-ModifyInformation-RL-ReconfPrepTDD	ProtocolIE-ID ::= 257
id-UL-CCTrCH-InformationModifyItem-RL-ReconfRqstTDD	ProtocolIE-ID ::= 258
id-UL-CCTrCH-InformationDeleteList-RL-ReconfPrepTDD	ProtocolIE-ID ::= 259
id-UL-CCTrCH-InformationModifyList-RL-ReconfPrepTDD	ProtocolIE-ID ::= 260
id-UL-CCTrCH-InformationModifyList-RL-ReconfRqstTDD	ProtocolIE-ID ::= 261
id-UL-CCTrCH-InformationDeleteItem-RL-ReconfragstTDD	ProtocolIE-ID ::= 262
id-UL-CCTrCH-InformationDeleteList-RL-ReconfrqstTDD	ProtocoliE-ID ::= 263
id-UL-DPCH-InformationDeleteListIE-RL-ReconfReadyTDD	ProtocoliE-ID ::= 264
id-UL-DPCH-InformationModifyListIE-RL-ReconfReadyTDD	ProtocoliE-ID ::= 265
id-UnsuccessfulRL-InformationResponse-RL-AdditionFailureTDD	ProtocoliE-ID ::= 266
id-USCHs-to-Add	ProtocoliE-ID ::= 266 ProtocolIE-ID ::= 267
id-USCH-DeleteList-RL-ReconfPrepTDD	ProtocolIE-ID ::= 268
id-USCH-InformationListIE-RL-AdditionRspTDD	ProtocolIE-ID ::= 269
id-USCH-InformationListIEs-RL-SetupRspTDD	ProtocolIE-ID ::= 270

id-USCH-Information	ProtocolIE-ID ::= 271
id-USCH-ModifyList-RL-ReconfPrepTDD	ProtocolIE-ID ::= 272
id-USCHToBeAddedOrModifiedList-RL-ReconfReadyTDD	ProtocolIE-ID ::= 273
id-DL-Physical-Channel-Information-RL-SetupRqstTDD	ProtocolIE-ID ::= 274
id-UL-Physical-Channel-Information-RL-SetupRqstTDD	ProtocolIE-ID ::= 275
id-ClosedLoopModel-SupportIndicator	ProtocolIE-ID ::= 276
id-Unused-ProtocolIE-ID-277	ProtocolIE-ID ::= 277
id-STTD-SupportIndicator	ProtocolIE-ID ::= 279
id-CFNReportingIndicator	ProtocolIE-ID ::= 14
id-CNOriginatedPage-PagingRqst	ProtocolIE-ID ::= 23
id-InnerLoopDLPCStatus	ProtocolIE-ID ::= 24
id-PropagationDelay	ProtocolIE-ID ::= 25
id-RxTimingDeviationForTA	ProtocolIE-ID ::= 36
id-timeSlot-ISCP	ProtocolIE-ID ::= 37
id-CCTrCH-InformationItem-RL-FailureInd	ProtocolIE-ID ::= 15
id-CCTrCH-InformationItem-RL-RestoreInd	ProtocolIE-ID ::= 16
id-CommonMeasurementAccuracy	ProtocolIE-ID ::= 280
id-CommonMeasurementObjectType-CM-Rprt	ProtocolIE-ID ::= 281
id-CommonMeasurementObjectType-CM-Rqst	ProtocolIE-ID ::= 282
id-CommonMeasurementObjectType-CM-Rsp	ProtocolIE-ID ::= 283
id-CommonMeasurementType	ProtocolIE-ID ::= 284
id-CongestionCause	ProtocolIE-ID ::= 18
id-SFN	ProtocolIE-ID ::= 285
id-SFNReportingIndicator	ProtocolIE-ID ::= 286
id-InformationExchangeID	ProtocolIE-ID ::= 287
id-InformationExchangeObjectType-InfEx-Rprt	ProtocolIE-ID ::= 288
id-InformationExchangeObjectType-InfEx-Rqst	ProtocolIE-ID ::= 289
id-InformationExchangeObjectType-InfEx-Rsp	ProtocolIE-ID ::= 290
id-InformationReportCharacteristics	ProtocolIE-ID ::= 291
id-InformationType	ProtocolIE-ID ::= 292
id-neighbouring-LCR-TDD-CellInformation	ProtocolIE-ID ::= 58
id-DL-Timeslot-ISCP-LCR-Information-RL-SetupRqstTDD	ProtocolIE-ID ::= 65
id-RL-LCR-InformationResponse-RL-SetupRspTDD	ProtocolIE-ID ::= 66
id-UL-CCTrCH-LCR-InformationListIE-RL-SetupRspTDD	ProtocolIE-ID ::= 75
id-UL-DPCH-LCR-InformationItem-RL-SetupRspTDD	ProtocolIE-ID ::= 76
id-DL-CCTrCH-LCR-InformationListIE-RL-SetupRspTDD	ProtocolIE-ID ::= 77
id-DL-DPCH-LCR-InformationItem-RL-SetupRspTDD	ProtocolIE-ID ::= 78
id-DSCH-LCR-InformationListIEs-RL-SetupRspTDD	ProtocolIE-ID ::= 79
id-USCH-LCR-InformationListIEs-RL-SetupRspTDD	ProtocolIE-ID ::= 80
id-DL-Timeslot-ISCP-LCR-Information-RL-AdditionRqstTDD	ProtocolIE-ID ::= 81
id-RL-LCR-InformationResponse-RL-AdditionRspTDD	ProtocolIE-ID ::= 86
id-UL-CCTrCH-LCR-InformationListIE-RL-AdditionRspTDD	ProtocolIE-ID ::= 87
id-UL-DPCH-LCR-InformationItem-RL-AdditionRspTDD	ProtocolIE-ID ::= 88
id-DL-CCTrCH-LCR-InformationListIE-RL-AdditionRspTDD	ProtocolIE-ID ::= 89
id-DL-DPCH-LCR-InformationItem-RL-AdditionRspTDD	ProtocolIE-ID ::= 94
id-DSCH-LCR-InformationListIEs-RL-AdditionRspTDD	ProtocolIE-ID ::= 96
id-USCH-LCR-InformationListIEs-RL-AdditionRspTDD	ProtocolIE-ID ::= 97
id-UL-DPCH-LCR-InformationAddListIE-RL-ReconfReadyTDD	ProtocolIE-ID ::= 98
id-UL-Timeslot-LCR-InformationModifyList-RL-ReconfReadyTDD	ProtocolIE-ID ::= 100
id-DL-DPCH-LCR-InformationAddListIE-RL-ReconfReadyTDD	ProtocolIE-ID ::= 101
id-DL-Timeslot-LCR-InformationModifyList-RL-ReconfReadyTDD	ProtocolIE-ID ::= 104
id-UL-Timeslot-LCR-InformationList-PhyChReconfRqstTDD	ProtocolIE-ID ::= 105
id-DL-Timeslot-LCR-InformationList-PhyChReconfRqstTDD	ProtocolIE-ID ::= 106
id-timeSlot-ISCP-LCR-List-DL-PC-Rqst-TDD	ProtocolIE-ID ::= 138
-	

id-TSTD-Support-Indicator-RL-SetupRqstTDD	ProtocolIE-ID ::= 139
id-RestrictionStateIndicator	ProtocolIE-ID ::= 142
id-Load-Value	ProtocolIE-ID ::= 233
id-Load-Value-IncrDecrThres	ProtocolIE-ID ::= 234
id-OnModification	ProtocolIE-ID ::= 235
id-Received-Total-Wideband-Power-Value	ProtocolIE-ID ::= 236
id-Received-Total-Wideband-Power-Value-IncrDecrThres	ProtocolIE-ID ::= 237
id-SFNSFNMeasurementThresholdInformation	ProtocolIE-ID ::= 238
id-Transmitted-Carrier-Power-Value	ProtocolIE-ID ::= 239
id-Transmitted-Carrier-Power-Value-IncrDecrThres	ProtocolIE-ID ::= 240
id-TUTRANGPSMeasurementThresholdInformation	ProtocolIE-ID ::= 241
id-UL-Timeslot-ISCP-Value	ProtocolIE-ID ::= 242
id-UL-Timeslot-ISCP-Value-IncrDecrThres	ProtocolIE-ID ::= 243
id-Rx-Timing-Deviation-Value-LCR	ProtocolIE-ID ::= 293
id-DPC-Mode-Change-SupportIndicator	ProtocolIE-ID ::= 19
id-Unused-ProtocolIE-ID-247	ProtocolIE-ID ::= 247
id-Unused-ProtocolIE-ID-295	ProtocolIE-ID ::= 295
id-PrimaryCCPCH-RSCP-RL-ReconfPrepTDD	ProtocolIE-ID ::= 202
id-DL-TimeSlot-ISCP-Info-RL-ReconfPrepTDD	ProtocolIE-ID ::= 203
id-DL-Timeslot-ISCP-LCR-Information-RL-ReconfPrepTDD	ProtocolIE-ID ::= 204
id-DSCH-RNTI	ProtocolIE-ID ::= 249
id-DL-PowerBalancing-Information	ProtocolIE-ID ::= 296
id-DL-PowerBalancing-ActivationIndicator	ProtocolIE-ID ::= 297
id-DL-PowerBalancing-UpdatedIndicator	ProtocolIE-ID ::= 298
id-DL-ReferencePowerInformation	ProtocolIE-ID ::= 299
id-Enhanced-PrimaryCPICH-EcNo	ProtocolIE-ID ::= 224
id-IPDL-TDD-ParametersLCR	ProtocolIE-ID ::= 252
id-CellCapabilityContainer-FDD	ProtocolIE-ID ::= 300
id-CellCapabilityContainer-TDD	ProtocolIE-ID ::= 301
id-CellCapabilityContainer-TDD-LCR	ProtocolIE-ID ::= 302
id-RL-Specific-DCH-Info	ProtocolIE-ID ::= 317
id-RL-ReconfigurationRequestFDD-RL-InformationList	ProtocolIE-ID ::= 318
id-RL-ReconfigurationRequestFDD-RL-Information-IEs	ProtocolIE-ID ::= 319
id-RL-ReconfigurationRequestTDD-RL-Information	ProtocolIE-ID ::= 321
id-CommonTransportChannelResourcesInitialisationNotRequired	ProtocolIE-ID ::= 250
id-DelayedActivation	ProtocolIE-ID ::= 312
id-DelayedActivationList-RL-ActivationCmdFDD	ProtocolIE-ID ::= 313
id-DelayedActivationInformation-RL-ActivationCmdFDD	ProtocolIE-ID ::= 314
id-DelayedActivationList-RL-ActivationCmdTDD	ProtocolIE-ID ::= 315
id-DelayedActivationInformation-RL-ActivationCmdTDD	ProtocolIE-ID ::= 316
id-neighbouringTDDCellMeasurementInformationLCR	ProtocolIE-ID ::= 251
id-UL-SIR-Target-CCTrCH-InformationItem-RL-SetupRspTDD	ProtocolIE-ID ::= 150
id-UL-SIR-Target-CCTrCH-LCR-InformationItem-RL-SetupRspTDD	ProtocolIE-ID ::= 151
id-PrimCCPCH-RSCP-DL-PC-RgstTDD	ProtocolIE-ID ::= 451
id-HSDSCH-FDD-Information	ProtocoliE-ID ::= 451
id-HSDSCH-FDD-Information-Response	ProtocoliE-ID ::= 453
id-HSDSCH-FDD-Update-Information	ProtocoliE-ID ::= 466
id-HSDSCH-Information-to-Modify	ProtocoliE-ID ::= 456 ProtocolIE-ID ::= 456
id-HSDSCHMacdFlowSpecificInformationList-RL-PreemptRequiredInd	ProtocoliE-ID ::= 516
id-HSDSCHMacdFlowSpecificInformationLtst-RL-PreemptRequiredInd id-HSDSCHMacdFlowSpecificInformationItem-RL-PreemptRequiredInd	ProtocoliE-ID ::= 516 ProtocolIE-ID ::= 517
id-HSDSCH-RNTI	ProtocoliE-ID ::= 517 ProtocolIE-ID ::= 457
id-HSDSCH-TDD-Information	ProtocolIE-ID ::= 458
id-HSDSCH-TDD-Information-Response	ProtocolIE-ID ::= 459 ProtocolIE-ID ::= 467
id-HSDSCH-TDD-Update-Information	PIOCOCOTIE-ID ··= 46/

14 MODDON DI TD	Destaral III ID 463
id-HSPDSCH-RL-ID	ProtocolIE-ID ::= 463
id-HSDSCH-MACdFlows-to-Add	ProtocolIE-ID ::= 531
id-HSDSCH-MACdFlows-to-Delete	ProtocolIE-ID ::= 532
id-Angle-Of-Arrival-Value-LCR	ProtocolIE-ID ::= 148
id-TrafficClass id-Unused-ProtocolIE-ID-248	ProtocolIE-ID ::= 158
	ProtocolIE-ID ::= 248
id-Unused-ProtocolIE-ID-253 id-PDSCH-RL-ID	ProtocolIE-ID ::= 253
	ProtocolIE-ID ::= 323
id-TimeSlot-RL-SetupRspTDD	ProtocolIE-ID ::= 325
id-GERAN-Cell-Capability	ProtocolIE-ID ::= 468
id-GERAN-Classmark	ProtocolIE-ID ::= 469
id-DSCH-InitialWindowSize	ProtocolIE-ID ::= 480
id-UL-Synchronisation-Parameters-LCR	ProtocolIE-ID ::= 464
id-SNA-Information	ProtocolIE-ID ::= 479
id-MAChs-ResetIndicator	ProtocolIE-ID ::= 465
id-TDD-DL-DPCH-TimeSlotFormatModifyItem-LCR-RL-ReconfReadyTDD	ProtocolIE-ID ::= 481
id-TDD-UL-DPCH-TimeSlotFormatModifyItem-LCR-RL-ReconfReadyTDD	ProtocolIE-ID ::= 482
id-TDD-TPC-UplinkStepSize-LCR-RL-SetupRqstTDD	ProtocolIE-ID ::= 483
id-UL-CCTrCH-InformationList-RL-AdditionRqstTDD	ProtocolIE-ID ::= 484
id-UL-CCTrCH-InformationItem-RL-AdditionRqstTDD	ProtocolIE-ID ::= 485
id-DL-CCTrCH-InformationList-RL-AdditionRqstTDD	ProtocolIE-ID ::= 486
id-DL-CCTrCH-InformationItem-RL-AdditionRqstTDD	ProtocolIE-ID ::= 487
id-TDD-TPC-UplinkStepSize-InformationAdd-LCR-RL-ReconfPrepTDD	ProtocolIE-ID ::= 488
id-TDD-TPC-UplinkStepSize-InformationModify-LCR-RL-ReconfPrepTDD	ProtocolIE-ID ::= 489
id-TDD-TPC-DownlinkStepSize-InformationAdd-RL-ReconfPrepTDD	ProtocolIE-ID ::= 490
id-TDD-TPC-DownlinkStepSize-InformationModify-RL-ReconfPrepTDD	ProtocolIE-ID ::= 491
id-UL-TimingAdvanceCtrl-LCR	ProtocolIE-ID ::= 492
id-HSPDSCH-Timeslot-InformationList-PhyChReconfRqstTDD	ProtocolIE-ID ::= 493
id-HSPDSCH-Timeslot-InformationListLCR-PhyChReconfRqstTDD	ProtocolIE-ID ::= 494
id-HS-SICH-Reception-Quality	ProtocolIE-ID ::= 495
id-HS-SICH-Reception-Quality-Measurement-Value	ProtocolIE-ID ::= 496
id-HSSICH-Info-DM-Rprt	ProtocolIE-ID ::= 497
id-HSSICH-Info-DM-Rqst	ProtocolIE-ID ::= 498
id-HSSICH-Info-DM	ProtocolIE-ID ::= 499
id-CCTrCH-Maximum-DL-Power-RL-SetupRspTDD	ProtocolIE-ID ::= 500
id-CCTrCH-Minimum-DL-Power-RL-SetupRspTDD	ProtocolIE-ID ::= 501
id-CCTrCH-Maximum-DL-Power-RL-AdditionRspTDD	ProtocolIE-ID ::= 502
id-CCTrCH-Minimum-DL-Power-RL-AdditionRspTDD	ProtocolIE-ID ::= 503
id-CCTrCH-Maximum-DL-Power-RL-ReconfReadyTDD	ProtocolIE-ID ::= 504
id-CCTrCH-Minimum-DL-Power-RL-ReconfReadyTDD	ProtocolIE-ID ::= 505
id-Maximum-DL-Power-TimeslotLCR-InformationModifyItem-RL-ReconfReadyTDD	ProtocolIE-ID ::= 506
id-Minimum-DL-Power-TimeslotLCR-InformationModifyItem-RL-ReconfReadyTDD	ProtocolIE-ID ::= 507
id-DL-CCTrCH-InformationList-RL-ReconfRspTDD	ProtocolIE-ID ::= 508
id-DL-DPCH-InformationModifyItem-LCR-RL-ReconfRspTDD	ProtocolIE-ID ::= 509
id-Maximum-DL-Power-TimeslotLCR-InformationItem	ProtocolIE-ID ::= 510
id-Minimum-DL-Power-TimeslotLCR-InformationItem	ProtocolIE-ID ::= 511
id-TDD-Support-8PSK	ProtocolIE-ID ::= 512
id-TDD-maxNrDLPhysicalchannels	ProtocolIE-ID ::= 513
id-ExtendedGSMCellIndividualOffset	ProtocolIE-ID ::= 514
id-RL-ParameterUpdateIndicationFDD-RL-InformationList	ProtocolIE-ID ::= 518
id-Primary-CPICH-Usage-For-Channel-Estimation	ProtocolIE-ID ::= 519
id-Secondary-CPICH-Information	ProtocolIE-ID ::= 520
id-Secondary-CPICH-Information-Change	ProtocolIE-ID ::= 521
id-Unused-ProtocolIE-ID-522	ProtocolIE-ID ::= 522

id-Unused-ProtocolIE-ID-523	ProtocolIE-ID ::= 523
id-RL-ParameterUpdateIndicationFDD-RL-Information-Item	ProtocolIE-ID ::= 524
id-Phase-Reference-Update-Indicator	ProtocolIE-ID ::= 525
id-Unidirectional-DCH-Indicator	ProtocolIE-ID ::= 526
id-RL-Information-RL-ReconfPrepTDD	ProtocolIE-ID ::= 527
id-Multiple-RL-InformationResponse-RL-ReconfReadyTDD	ProtocolIE-ID ::= 528
id-RL-ReconfigurationResponseTDD-RL-Information	ProtocolIE-ID ::= 529
id-Satellite-Almanac-Information-ExtItem	ProtocolIE-ID ::= 530
id-HSDSCH-Information-to-Modify-Unsynchronised	ProtocolIE-ID ::= 533
id-TnlQos	ProtocolIE-ID ::= 534
id-RTLoadValue	ProtocolIE-ID ::= 535
id-NRTLoadInformationValue	ProtocolIE-ID ::= 536
id-CellPortionID	ProtocolIE-ID ::= 537
id-UpPTSInterferenceValue	ProtocolIE-ID ::= 538
id-PrimaryCCPCH-RSCP-Delta	ProtocolIE-ID ::= 539
id-UEMeasurementType	ProtocolIE-ID ::= 540
id-UEMeasurementTimeslotInfoHCR	ProtocolIE-ID ::= 541
id-UEMeasurementTimeslotInfoLCR	ProtocolIE-ID ::= 542
id-UEMeasurementReportCharacteristics	ProtocolIE-ID ::= 543
id-UEMeasurementParameterModAllow	ProtocolIE-ID ::= 544
id-UEMeasurementValueInformation	ProtocolIE-ID ::= 545
id-InterfacesToTraceItem	ProtocolIE-ID ::= 546
id-ListOfInterfacesToTrace	ProtocolIE-ID ::= 547
id-TraceDepth	ProtocolIE-ID ::= 548
id-TraceRecordingSessionReference	ProtocolIE-ID ::= 549
id-TraceReference	ProtocolIE-ID ::= 550
id-UEIdentity	ProtocolIE-ID ::= 551
id-NACC-Related-Data	ProtocolIE-ID ::= 552
id-GSM-Cell-InfEx-Rqst	ProtocolIE-ID ::= 553
id-MeasurementRecoveryBehavior	ProtocolIE-ID ::= 554
id-MeasurementRecoveryReportingIndicator	ProtocolIE-ID ::= 555
id-MeasurementRecoverySupportIndicator	ProtocolIE-ID ::= 556
id-DL-DPCH-Power-Information-RL-ReconfPrepFDD	ProtocolIE-ID ::= 557
id-F-DPCH-Information-RL-ReconfPrepFDD	ProtocoliE-ID ::= 558
id-F-DPCH-Information-RL-SetupRqstFDD	ProtocolIE-ID ::= 559
id-MBMS-Bearer-Service-List	ProtocoliE-ID ::= 560
id-MBMS-Bearer-Service-List-InfEx-Rsp	ProtocoliE-ID ::= 561
id-Active-MBMS-Bearer-ServiceFDD	ProtocoliE-ID ::= 562
id-Active-MBMS-Bearer-ServiceTDD	ProtocoliE-ID ::= 563
id-Old-URA-ID	ProtocoliE-ID ::= 564
id-UE-State	ProtocolIE-ID ::= 568
id-UE-State id-URA-ID	ProtocoliE-ID ::= 568 ProtocoliE-ID ::= 569
id-HARQ-Preamble-Mode	ProtocolIE-ID ::= 571
id-SynchronisationIndicator	ProtocolIE-ID ::= 572
id-UL-DPDCHIndicatorEDCH	ProtocolIE-ID ::= 573
id-EDPCH-Information	ProtocolIE-ID ::= 574
id-RL-Specific-EDCH-Information	ProtocolIE-ID ::= 575
id-EDCH-RL-Indication	ProtocolIE-ID ::= 576
id-EDCH-FDD-Information	ProtocolIE-ID ::= 577
id-EDCH-RLSet-Id	ProtocolIE-ID ::= 578
id-Serving-EDCHRL-Id	ProtocolIE-ID ::= 579
id-EDCH-FDD-DL-ControlChannelInformation	ProtocolIE-ID ::= 580
id-EDCH-FDD-InformationResponse	ProtocolIE-ID ::= 581
id-EDCH-MACdFlows-To-Add	ProtocolIE-ID ::= 582

id-EDCH-FDD-Information-To-Modify	ProtocolIE-ID ::= 583
id-EDCH-MACdFlows-To-Delete	ProtocolIE-ID ::= 584
id-EDPCH-Information-RLReconfRequest-FDD	ProtocolIE-ID ::= 585
id-EDCH-MacdFlowSpecificInformationList-RL-PreemptRequiredInd	ProtocolIE-ID ::= 586
id-EDCH-MacdFlowSpecificInformationItem-RL-PreemptRequiredInd	ProtocolIE-ID ::= 587
id-EDCH-MacdFlowSpecificInformationList-RL-CongestInd	ProtocolIE-ID ::= 588
id-EDCH-MacdFlowSpecificInformationItem-RL-CongestInd	ProtocolIE-ID ::= 589
id-MBMS-Bearer-Service-Full-Address	ProtocolIE-ID ::= 590
id-Initial-DL-DPCH-TimingAdjustment	ProtocolIE-ID ::= 591
id-Initial-DL-DPCH-TimingAdjustment-Allowed	ProtocolIE-ID ::= 592
id-User-Plane-Congestion-Fields-Inclusion	ProtocolIE-ID ::= 593
id-HARQ-Preamble-Mode-Activation-Indicator	ProtocolIE-ID ::= 594
id-multiple-DedicatedMeasurementValueList-TDD-DM-Rsp	ProtocolIE-ID ::= 595
id-multiple-DedicatedMeasurementValueList-LCR-TDD-DM-Rsp	ProtocolIE-ID ::= 596
id-ProvidedInformation	ProtocolIE-ID ::= 597
id-Active-MBMS-Bearer-ServiceFDD-PFL	ProtocolIE-ID ::= 598
id-Active-MBMS-Bearer-ServiceTDD-PFL	ProtocolIE-ID ::= 599
id-FrequencyBandIndicator	ProtocolIE-ID ::= 600
id-Serving-cell-change-CFN	ProtocolIE-ID ::= 601
id-HS-DSCH-serving-cell-change-information	ProtocolIE-ID ::= 602
id-HS-DSCH-serving-cell-change-informationResponse	ProtocolIE-ID ::= 603
id-E-DCH-Serving-cell-change-informationResponse	ProtocolIE-ID ::= 604
id-secondary-LCR-CCPCH-Info-TDD	ProtocolIE-ID ::= 605
id-E-DCH-FDD-Update-Information	ProtocolIE-ID ::= 606
id-Inter-Frequency-Cell-List	ProtocolIE-ID ::= 607
id-Inter-Frequency-Cell-Information	ProtocolIE-ID ::= 608
id-multiple-HSSICHMeasurementValueList-TDD-DM-Rsp	ProtocolIE-ID ::= 609
id-TDD-Support-PLCCH	ProtocolIE-ID ::= 610
id-PLCCH-Information-UL-TimeslotLCR-Info	ProtocolIE-ID ::= 611
id-PLCCH-Information-PhyChReconfRqstTDD	ProtocolIE-ID ::= 612
id-TDD768-maxNrDLPhysicalchannelsTS	ProtocolIE-ID ::= 613
id-RL-InformationResponse-RL-AdditionRspTDD768	ProtocolIE-ID ::= 614
id-UL-CCTrCH-InformationListIE-RL-AdditionRspTDD768	ProtocolIE-ID ::= 615
id-DL-CCTrCH-InformationListIE-RL-AdditionRspTDD768	ProtocolIE-ID ::= 616
id-UL-DPCH-InformationItem-RL-AdditionRspTDD768	ProtocolIE-ID ::= 617
id-DL-DPCH-InformationItem-RL-AdditionRspTDD768	ProtocolIE-ID ::= 618
id-UL-DPCH-InformationAddListIE-RL-ReconfReadyTDD768	ProtocolIE-ID ::= 619
id-UL-Timeslot-InformationModifyList-RL-ReconfReadyTDD768	ProtocolIE-ID ::= 620
id-DL-DPCH-InformationAddListIE-RL-ReconfReadyTDD768	ProtocolIE-ID ::= 621
id-DL-Timeslot-InformationModifyList-RL-ReconfReadyTDD768	ProtocolIE-ID ::= 622
id-secondary-CCPCH-Info-RL-ReconfReadyTDD768	ProtocolIE-ID ::= 623
id-hSSCCH-TDD-Specific-InfoList-Response768	ProtocolIE-ID ::= 624
id-hSPDSCH-TDD-Specific-InfoList-Response768	ProtocolIE-ID ::= 625
id-HSPDSCH-Timeslot-InformationList-PhyChReconfRqstTDD768	ProtocolIE-ID ::= 626
id-UL-Timeslot-InformationList-PhyChReconfRgstTDD768	ProtocolIE-ID ::= 627
id-DL-Timeslot-InformationList-PhyChReconfRqstTDD768	ProtocolIE-ID ::= 628
id-CellCapabilityContainer-TDD768	ProtocolIE-ID ::= 629
id-multiple-DedicatedMeasurementValueList-TDD768-DM-Rsp	ProtocolIE-ID ::= 630
id-neighbouringTDDCellMeasurementInformation768	ProtocolIE-ID ::= 631
id-UEMeasurementTimeslotInfo768	ProtocolIE-ID ::= 632
id-Rx-Timing-Deviation-Value-768	ProtocoliE-ID ::= 633
id-UEMeasurementValueTransmittedPowerList768	ProtocoliE-ID ::= 633
id-UEMeasurementValueTimeslotISCPList768	ProtocoliE-ID ::= 634 ProtocolIE-ID ::= 635
id-RL-InformationResponse-RL-SetupRspTDD768	ProtocoliE-ID ::= 636
ia ku intolmactonkesponse ku secapkspibb/00	FIOCOCOTIE-ID ··- 030

id-UL-CCTrCH-InformationListIE-RL-SetupRspTDD768	ProtocolIE-ID ::= 637
id-DL-CCTrCH-InformationListIE-RL-SetupRspTDD768	ProtocolIE-ID ::= 638
id-UL-DPCH-InformationItem-RL-SetupRspTDD768	ProtocolIE-ID ::= 639
id-DL-DPCH-InformationItem-RL-SetupRspTDD768	ProtocolIE-ID ::= 640
id-TDD768-minimumSpreadingFactor-UL	ProtocolIE-ID ::= 641
id-TDD768-minimumSpreadingFactor-DL	ProtocolIE-ID ::= 642
id-TDD768-maxNrDLPhysicalchannels	ProtocolIE-ID ::= 643
id-DL-DPCH-InformationDeleteList768-RL-ReconfReadyTDD	ProtocolIE-ID ::= 644
id-DPCH-ID768-DM-Rsp	ProtocolIE-ID ::= 645
id-DPCH-ID768-DM-Rqst	ProtocolIE-ID ::= 646
id-DPCH-ID768-DM-Rprt	ProtocolIE-ID ::= 647
id-EDPCH-Information-RLAdditionReq-FDD	ProtocolIE-ID ::= 648
id-HSDSCH-Configured-Indicator	ProtocolIE-ID ::= 649
id-RxTimingDeviationForTAext	ProtocolIE-ID ::= 650
id-RxTimingDeviationForTA768	ProtocolIE-ID ::= 651
id-Rx-Timing-Deviation-Value-ext	ProtocolIE-ID ::= 652
id-E-DCH-PowerOffset-for-SchedulingInfo	ProtocolIE-ID ::= 653
id-TrCH-SrcStatisticsDescr	ProtocolIE-ID ::= 654
id-E-DCH-Information	ProtocolIE-ID ::= 655
id-E-DCH-Serving-RL-ID	ProtocolIE-ID ::= 656
id-E-DCH-Information-Reconfig	ProtocolIE-ID ::= 657
id-E-DCH-Information-Response	ProtocolIE-ID ::= 658
id-E-DCH-768-Information	ProtocolIE-ID ::= 659
id-E-DCH-768-Information-Reconfig	ProtocolIE-ID ::= 660
id-E-DCH-768-Information-Response	ProtocolIE-ID ::= 661
id-ExtendedPropagationDelay	ProtocolIE-ID ::= 662
id-Extended-Round-Trip-Time-Value	ProtocolIE-ID ::= 663
id-AlternativeFormatReportingIndicator	ProtocolIE-ID ::= 664
id-DCH-Indicator-For-E-DCH-HSDPA-Operation	ProtocolIE-ID ::= 665
id-E-RGCH-E-HICH-ChannelisationCodeValidityIndicator	ProtocolIE-ID ::= 666
id-E-DCH-Minimum-Set-E-TFCIValidityIndicator	ProtocolIE-ID ::= 667
id-Fast-Reconfiguration-Mode	ProtocolIE-ID ::= 668
id-Fast-Reconfiguration-Permission	ProtocolIE-ID ::= 669
id-Continuous-Packet-Connectivity-DTX-DRX-Information	ProtocolIE-ID ::= 670
id-Continuous-Packet-Connectivity-HS-SCCH-Less-Information	ProtocolIE-ID ::= 671
id-Continuous-Packet-Connectivity-HS-SCCH-Less-Information-Response	ProtocolIE-ID ::= 672
id-CPC-Information	ProtocolIE-ID ::= 673
id-MIMO-InformationResponse	ProtocolIE-ID ::= 675
id-E-DCH-LCR-Information	ProtocolIE-ID ::= 677
id-E-DCH-LCR-Information-Reconfig	ProtocolIE-ID ::= 678
id-E-DCH-LCR-Information-Response	ProtocolIE-ID ::= 679
id-HS-PDSCH-Code-Change-Grant	ProtocolIE-ID ::= 680
id-HS-PDSCH-Code-Change-Indicator	ProtocolIE-ID ::= 681
id-Extended-SRNC-ID	ProtocolIE-ID ::= 682
id-Extended-RNC-ID	ProtocolIE-ID ::= 683
id-SixtyfourQAM-DL-SupportIndicator	ProtocolIE-ID ::= 684
id-Enhanced-FACH-Support-Indicator	ProtocolIE-ID ::= 685
id-Enhanced-FACH-Information-ResponseFDD	ProtocolIE-ID ::= 686
id-HSDSCH-MACdPDUSizeFormat	ProtocolIE-ID ::= 690
id-MaximumMACdPDU-SizeExtended	ProtocolIE-ID ::= 691
id-F-DPCH-SlotFormat	ProtocolIE-ID ::= 692
id-F-DPCH-SlotFormatSupportRequest	ProtocolIE-ID ::= 693
id-eDCH-MACdFlow-Retransmission-Timer-LCR	ProtocolIE-ID ::= 694
id-Max-UE-DTX-Cycle	ProtocolIE-ID ::= 695

id-GANSS-Common-Data	ProtocolIE-ID ::= 699
id-GANSS-Information	ProtocolIE-ID ::= 700
id-GANSS-Generic-Data	ProtocolIE-ID ::= 701
${ t id-TUTRANGANSSMeasure}$ mentThresholdInformation	ProtocolIE-ID ::= 702
${ t id-TUTRANGANSSMeasurementValueInformation}$	ProtocolIE-ID ::= 703
id-Ext-Reference-E-TFCI-PO	ProtocolIE-ID ::= 705
id-Ext-Max-Bits-MACe-PDU-non-scheduled	ProtocolIE-ID ::= 706
id-HARQ-MemoryPartitioningInfoExtForMIMO	ProtocolIE-ID ::= 707
id-MIMO-ActivationIndicator	ProtocolIE-ID ::= 708
id-MIMO-Mode-Indicator	ProtocolIE-ID ::= 709
id-MIMO-N-M-Ratio	ProtocolIE-ID ::= 710
id-TransportBearerNotSetupIndicator	ProtocolIE-ID ::= 711
id-TransportBearerNotRequestedIndicator	ProtocolIE-ID ::= 712
id-PowerControlGAP	ProtocolIE-ID ::= 713
id-UARFCNforNt	ProtocolIE-ID ::= 714
id-LCRTDD-uplink-Physical-Channel-Capability	ProtocolIE-ID ::= 715
id-number-Of-Supported-Carriers	ProtocolIE-ID ::= 716
id-HSSICH-SIRTarget	ProtocolIE-ID ::= 717
id-HSSICH-TPC-StepSize	ProtocolIE-ID ::= 718
id-tSN-Length	ProtocolIE-ID ::= 719
id-HS-SICH-ID-Extension	ProtocolIE-ID ::= 720
id-HSSICH-Info-DM-Rqst-Extension	ProtocolIE-ID ::= 721
id-multipleFreq-HSPDSCH-InformationList-ResponseTDDLCR	ProtocolIE-ID ::= 722
id-multicarrier-number	ProtocolIE-ID ::= 723
id-UPPCHPositionLCR	ProtocolIE-ID ::= 724
id-UpPCH-InformationList-LCRTDD	ProtocolIE-ID ::= 725
id-UpPCH-InformationItem-LCRTDD	ProtocolIE-ID ::= 726
id-Multiple-PLMN-List	ProtocolIE-ID ::= 727
id-UE-Capabilities-Info	ProtocolIE-ID ::= 728
id-FrameOffset	ProtocolIE-ID ::= 729
id-ChipOffset	ProtocolIE-ID ::= 730
id-Enhanced-PCH-Capability	ProtocolIE-ID ::= 731
id-SixteenQAM-UL-Operation-Indicator	ProtocolIE-ID ::= 732
id-E-TFCI-Boost-Information	ProtocolIE-ID ::= 733
id-SixtyfourQAM-UsageAllowedIndicator	ProtocolIE-ID ::= 734
id-SixtyfourQAM-DL-UsageIndicator	ProtocolIE-ID ::= 735
id-Default-Serving-Grant-in-DTX-Cycle2	ProtocolIE-ID ::= 736
id-E-DPDCH-PowerInterpolation	ProtocolIE-ID ::= 737
id-Extended-E-DCH-LCRTDD-PhysicalLayerCategory	ProtocolIE-ID ::= 738
id-E-DCH-MACdPDUSizeFormat	ProtocolIE-ID ::= 739
id-Continuous-Packet-Connectivity-HS-SCCH-Less-Deactivate-Indicator	ProtocolIE-ID ::= 740
id-E-DCH-DL-Control-Channel-Change-Information	ProtocolIE-ID ::= 741
id-E-DCH-DL-Control-Channel-Grant-Information	ProtocolIE-ID ::= 742
id-MaximumNumber-Of-Retransmission-For-SchedulingInfo-LCRTDD	ProtocolIE-ID ::= 743
id-E-DCH-RetransmissionTimer-For-SchedulingInfo-LCRTDD	ProtocolIE-ID ::= 744
id-E-PUCH-PowerControlGAP	ProtocolIE-ID ::= 745
id-HSDSCH-TBSizeTableIndicator	ProtocolIE-ID ::= 746
id-UE-with-enhanced-HS-SCCH-support-indicator	ProtocolIE-ID ::= 747
id-DGANSS-Corrections-Req	ProtocolIE-ID ::= 748
id-E-AGCH-Table-Choice	ProtocolIE-ID ::= 749
id-RANAP-EnhancedRelocationInformationRequest	ProtocolIE-ID ::= 750
id-RANAP-EnhancedRelocationInformationResponse	ProtocolIE-ID ::= 751
id-Common-EDCH-MAC-d-Flow-Specific-InformationFDD	ProtocolIE-ID ::= 752
id-Common-EDCH-Support-Indicator	ProtocolIE-ID ::= 753

id-Beleased-CN-Domain		
idMBMS-Bearer-Service-in-MBMS-Cell-InfEx-Rap	id-E-RNTI	ProtocolIE-ID ::= 754
id-MBMS-Bearer-Service-in-MBMS-Cell-InfEx-Rspt	id-Released-CN-Domain	ProtocolIE-ID ::= 755
id-MBMS-Sell-InfEx-Rgst	id-MBMS-Bearer-Service-in-MBMS-Cell-InfEx-Rqst	ProtocolIE-ID ::= 756
id-MBMS-Cell-InfEx-Rep	id-MBMS-Bearer-Service-in-MBMS-Cell-InfEx-Rsp	ProtocolIE-ID ::= 757
id-MBMS-Cell-InfEx-Rept	id-MBMS-Bearer-Service-in-MBMS-Cell-InfEx-Rprt	ProtocolIE-ID ::= 758
id-MBMS-Cell-InfEx-Rpt	id-MBMS-Cell-InfEx-Rqst	ProtocolIE-ID ::= 759
id-MBMS-Cell-InfEx-Rpt	id-MBMS-Cell-InfEx-Rsp	ProtocolIE-ID ::= 760
id-Counting-Information		
id-Transmission-Mode-Information		
id-MBMS-Nel-Glbouring-Cell-Information	g and a second s	
id-HBMS-RLC_Sequence-Number		
id=Ric_Sequence_Number		
id-MeSFN-Cluster-Identity	-	
id-MESFN-Cluster-Identity ProtocolIE-ID ::= 769 id-MCCH-Configuration-Info ProtocolIE-ID ::= 770 id-MCCH-Message-List ProtocolIE-ID ::= 771 id-MBSFN-Scheduling-Transmission-Time-Interval-Info-List ProtocolIE-ID ::= 773 id-GANSS-AddlonoModelReq ProtocolIE-ID ::= 774 id-GANSS-AddlonoModelReq ProtocolIE-ID ::= 776 id-GANSS-AddlonoModelsReq ProtocolIE-ID ::= 776 id-GANSS-AddlonoModelsReq ProtocolIE-ID ::= 776 id-GANSS-AddlonoModelsReq ProtocolIE-ID ::= 776 id-GANSS-AddlonoModelsReq ProtocolIE-ID ::= 778 id-GANSS-AddlonoModelReq ProtocolIE-ID ::= 778 id-GANSS-AddlonomodelReq ProtocolIE-ID ::= 778 id-GANSS-AddlonomodelReq ProtocolIE-ID ::= 781 id-GANSS-Additional-Ionospheric-Model ProtocolIE-ID ::= 781 id-GANSS-Additional-Ine-Models ProtocolIE-ID ::= 781 id-GANSS-Additional-Time-Models ProtocolIE-ID ::= 782 id-GANSS-Additional-Navigation-Models ProtocolIE-ID ::= 783 id-GANSS-Additional-HS-ColP-GainFactor ProtocolIE-ID ::= 783 id-GANSS-Additional-HS-ColP-GainFactor ProtocolIE-ID ::= 786 id-MinimumReducedE-DP	-	
id-MCCH-Configuration-Info		
id-MCCH-Message-List ProtocolIE-ID ::= 771 id-GANSS-Time-ID ProtocolIE-ID ::= 772 id-GANSS-Time-ID ProtocolIE-ID ::= 773 id-GANSS-Time-ID ProtocolIE-ID ::= 773 id-GANSS-AddIonoModelReq ProtocolIE-ID ::= 775 id-GANSS-AddIonoModelReq ProtocolIE-ID ::= 775 id-GANSS-AddInomodelsReq ProtocolIE-ID ::= 775 id-GANSS-AddInomodelsReq ProtocolIE-ID ::= 776 id-GANSS-AddInomodelsReq ProtocolIE-ID ::= 776 id-GANSS-AddInomodelsReq ProtocolIE-ID ::= 776 id-GANSS-AddInomodelsReq ProtocolIE-ID ::= 778 id-GANSS-AddInomospheric-Model ProtocolIE-ID ::= 778 id-GANSS-SBAS-ID ProtocolIE-ID ::= 778 id-GANSS-BAS-ID ProtocolIE-ID ::= 780 id-GANSS-AddItional-Ionospheric-Model ProtocolIE-ID ::= 780 id-GANSS-Additional-Time-Models ProtocolIE-ID ::= 781 id-GANSS-Additional-Time-Models ProtocolIE-ID ::= 782 id-GANSS-Additional-Navigation-Models ProtocolIE-ID ::= 783 id-GANSS-Additional-UTC-Models ProtocolIE-ID ::= 784 id-GANSS-Additional-UTC-Models ProtocolIE-ID ::= 786 id-GANSS-Additional-UTC-Models ProtocolIE-ID ::= 786 id-MinimumReducedE-DPDCH-GainFactor ProtocolIE-ID ::= 786 id-MinimumReducedE-DPDCH-GainFactor ProtocolIE-ID ::= 786 id-MinimumReducedE-DPDCH-GainFactor ProtocolIE-ID ::= 788 id-GSNSCH-PreconfigurationSetup ProtocolIE-ID ::= 789 id-MSDSCH-PreconfigurationSetup ProtocolIE-ID ::= 789 id-MSDSCH-PreconfigurationSetup ProtocolIE-ID ::= 791 id-MoofTargetCelIR-SeCCH-Order ProtocolIE-ID ::= 792 id-Badditional-HS-Cell-Information-Response ProtocolIE-ID ::= 796 id-Additional-HS-Cell-Information-Response ProtocolIE-ID ::= 796 id-Additional-HS-Cell-Information-RL-Reconf-Prep ProtocolIE-ID ::= 796 id-Additional-HS-Cell-Information-RL-Reconf-Prep ProtocolIE-ID ::= 798 id-Additional-HS-Cell-Information-RL-Reconf-Req ProtocolIE-ID ::= 796 id-Additional-HS-Cell-Information-RL-Param-Upd ProtocolIE-ID ::= 801 id-Additional-HS-Cell-Information-RL-Reconf-Req ProtocolIE-ID ::= 801 id-Additional-HS-Cell-Infor		
id-MBSFN-Scheduling-Transmission-Time-Interval-Info-List ProtocolIE-ID ::= 772 id-GANSS-Tame-ID ProtocolIE-ID ::= 774 id-GANSS-AaddnonModelReq ProtocolIE-ID ::= 775 id-GANSS-AddNavigationModelsReq ProtocolIE-ID ::= 775 id-GANSS-AddNavigationModelsReq ProtocolIE-ID ::= 777 id-GANSS-AddNavigationModelsReq ProtocolIE-ID ::= 777 id-GANSS-AddItOndelsReq ProtocolIE-ID ::= 777 id-GANSS-AddItIonAl-Tonospheric-Model ProtocolIE-ID ::= 779 id-GANSS-DI ProtocolIE-ID ::= 780 id-GANSS-Barth-Orientation-Parameters ProtocolIE-ID ::= 780 id-GANSS-Additional-Time-Models ProtocolIE-ID ::= 781 id-GANSS-Additional-Time-Models ProtocolIE-ID ::= 783 id-GANSS-Additional-Tonospheric-Models ProtocolIE-ID ::= 784 id-GANSS-Additional-Tonospheric-Models ProtocolIE-ID ::= 783 id-GANSS-Additional-Time-Models ProtocolIE-ID ::= 784 id-GANSS-Additional-Models ProtocolIE-ID ::= 782 id-GANSS-Additional-Models <td< td=""><td></td><td></td></td<>		
id-GANSS-Time-ID	g .	
id-GANSS-BarthOrientParaReq id-GANSS-BarthOrientParaReq id-GANSS-AddNavigationModelsReq id-GANSS-AddNavigationModelsReq id-GANSS-AddNavigationModelsReq id-GANSS-AddNavigationModelsReq id-GANSS-AddNavigationModelsReq id-GANSS-AddNavigationModelsReq id-GANSS-AddNavigationModelsReq id-GANSS-BaNS-ID id-GANSS-BAS-ID id-GANSS-BAS-ID id-GANSS-ID id-GANSS-Additional-Ionospheric-Model id-GANSS-Additional-Ionospheric-Model id-GANSS-Additional-Ionospheric-Model id-GANSS-Additional-Ionospheric-Models id-GANSS-Additional-Ionospheric	~	
id-GANSS-EarthOrientParaReq id-GANSS-AddNavigationModelsReq id-GANSS-AddNavigationModelsReq id-GANSS-AddNavigationModelsReq id-GANSS-AuxInfoReq id-GANSS-BAS-ID id-GANSS-BAS-ID id-GANSS-BAS-ID id-GANSS-BAS-ID id-GANSS-AuxInfoReq id-GANSS-AuxInfoReq id-GANSS-ID id-GANSS-AuxInfoReq id-GANSS-AuxInfoReq id-GANSS-Additional-Ionospheric-Model id-GANSS-Additional-Ionospheric-Model id-GANSS-Additional-Ionospheric-Model id-GANSS-Additional-Time-Models id-GANSS-Additional-Time-Models id-GANSS-Additional-Nowigation-Models id-GANSS-Additional-Nowigation-Models id-GANSS-Additional-Ionospheric-Models id-GANSS-Additional-Ionospheric-Models id-GANSS-Additional-Ionospheric-Models id-GANSS-Additional-Ionospheric-Models id-GANSS-Additional-Ionospheric-Models id-GANSS-Additional-Ionospheric-Models id-GANSS-Additional-Ionospheric-Models id-GANSS-Additional-Ionospheric-Models id-GANSS-Auxiliary-Information id-GANSS-Auxiliary-Information information-ResponseLCR id-Common-EDCH-MAC-d-Plow-Specific-InformationLCR id-HSDSCH-PreconfigurationSetup id-HSDSCH-PreconfigurationSetup id-HSDSCH-PreconfigurationInfo id-HSDSCH-PreconfigurationInfo id-HSDSCH-Preconfiguration-RL-Setup id-Additional-HS-Cell-Information-RL-Setup id-Additional-HS-Cell-Information-RL-Setup id-Additional-HS-Cell-Information-RL-Setup id-Additional-HS-Cell-Information-RL-Setup id-Additional-HS-Cell-Information-RL-Setup id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Beonf-Req id-Additional-HS-Cell-Information-RL-Reconf-Reg id-Additional-HS-Cell-Information-RL-Reconf-Reg id-Additional-HS-Cell-Information-RL-Reconf-Reg id-Additional-HS-Cell-Information-RL-Rec	1d-GANSS-Time-ID	ProtocollE-ID ::= //3
id-GANSS-AddNavigationModelsReq	id-GANSS-AddIonoModelReq	ProtocolIE-ID ::= 774
id-GANSS-AddUTCModelsReq	id-GANSS-EarthOrientParaReq	ProtocolIE-ID ::= 775
id-GANSS-AuxInfoReq id-GANSS-BAS-ID id-GANSS-BAS-ID id-GANSS-BAS-ID id-GANSS-Additional-Ionospheric-Model id-GANSS-Additional-Ionospheric-Model id-GANSS-Additional-Time-Models id-GANSS-Additional-Time-Models id-GANSS-Additional-Navigation-Models id-GANSS-Additional-Navigation-Models id-GANSS-Additional-Time-Models id-GANSS-Additional-Time-Models id-GANSS-Additional-Navigation-Models id-GANSS-Additional-Navigation-Models id-GANSS-Additional-Navigation-Models id-GANSS-Additional-Navigation-Models id-GANSS-Additional-Navigation-Models id-GANSS-Additional-Navigation-Models id-GANSS-Auxiliary-Information ProtocolIE-ID ::= 784 id-GANSS-Additional-Navigation-Models id-GANSS-Auxiliary-Information ProtocolIE-ID ::= 786 id-GANSS-Auxiliary-Information-ResponseLCR id-Enhanced-FACH-Information-ResponseLCR id-Common-EDCH-MAC-d-Flow-Specific-InformationLCR id-Common-EDCH-MAC-d-Flow-Specific-InformationLCR id-SDSCH-PreconfigurationSetup id-HSDSCH-PreconfigurationInfo id-NoOfTargetCellHS-SCCH-Order ProtocolIE-ID ::= 789 id-Additional-HS-Cell-Information-RL-Setup id-Additional-HS-Cell-Information-RL-Setup id-Additional-HS-Cell-Information-RL-Setup id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Param-Upd id-Secondary-Serving-Cell-List id-MultiCarrier-HSDSCH-Physical-Layer-Category id-Additional-HS-Cell-Information ProtocolIE-ID ::= 802 id-MultiCarrier-HSDSCH-Physical-Layer-Category id-Id-Id-Interval Information id-Id-Id-Interval Information ProtocolIE-ID ::= 806 id-ContinuousPacketConnectivity-DRX-InformationLCR ProtocolIE-ID ::= 806 id-ContinuousPacketConnectivity-DRX-InformationLCR	id-GANSS-AddNavigationModelsReq	ProtocolIE-ID ::= 776
id-GANSS-BBAS-ID id-GANSS-ID id-GANSS-ID id-GANSS-Additional-Ionospheric-Model id-GANSS-Additional-Time-Models id-MinimumReducede-DPDCH-GainFactor id-MinimumReducede-DPDCH-GainFactor id-Enhanced-FACH-Information-ResponseLCR id-Enhanced-FACH-Information-ResponseLCR id-Enhanced-FACH-Information-ResponseLCR id-HSDSCH-PreconfigurationSetup id-HSDSCH-PreconfigurationInfo id-ModfTargetCellHS-SCCH-Order id-EnhancedHSServingCC-Abort ProtocolIE-ID ::= 791 id-NoOfTargetCellHS-SCCH-Order id-Additional-HS-Cell-Information-RL-Setup id-Addit	id-GANSS-AddUTCModelsReq	ProtocolIE-ID ::= 777
id-GANSS-ID id-GANSS-Additional-Ionospheric-Model id-GANSS-Additional-Tonospheric-Model id-GANSS-Additional-Time-Models id-GANSS-Additional-Time-Models id-GANSS-Additional-Navigation-Models id-GANSS-Additional-Navigation-Models id-GANSS-Additional-Tome-Models id-Additional-Tome-Models id-GANSS-Additional-Tome-Models id-Additional-Tome-Models id-Additional-Tome-Models id-Additional-Tome-Models id-Additional-Tome-Models id-Additional-Tome-Models id-Additional-Tome-Models id-Additional-Tome-Models id-Additional-Tome-Models id-Models id-Mod	id-GANSS-AuxInfoReq	ProtocolIE-ID ::= 778
id-GANSS-ID id-GANSS-Additional-Ionospheric-Model id-GANSS-Additional-Tonospheric-Model id-GANSS-Additional-Time-Models id-GANSS-Additional-Time-Models id-GANSS-Additional-Navigation-Models id-GANSS-Additional-Navigation-Models id-GANSS-Additional-Tome-Models id-Additional-Tome-Models id-GANSS-Additional-Tome-Models id-Additional-Tome-Models id-Additional-Tome-Models id-Additional-Tome-Models id-Additional-Tome-Models id-Additional-Tome-Models id-Additional-Tome-Models id-Additional-Tome-Models id-Additional-Tome-Models id-Models id-Mod	-	ProtocolIE-ID ::= 779
id-GANSS-Earth-Orientation-Parameters id-GANSS-Additional-Time-Models id-GANSS-Additional-Navigation-Models id-GANSS-Additional-Navigation-Models id-GANSS-Additional-UTC-Models id-GANSS-Additional-UTC-Models id-GANSS-Adxiliary-Information id-MinimumReducedE-DPDCH-GainFactor id-Enhanced-FACH-Information-ResponseLCR id-Common-EDCH-MAC-d-Flow-Specific-InformationLCR id-Common-EDCH-MAC-d-Flow-Specific-InformationLCR id-HSDSCH-PreconfigurationSetup id-HSDSCH-PreconfigurationSetup id-HSDSCH-PreconfigurationInfo id-NoofTargetCellHS-SCCH-Order id-Additional-HS-Cell-Information-RL-Setup id-Additional-HS-Cell-Information-Response id-Additional-HS-Cell-Information-Response id-Additional-HS-Cell-Information-RL-Addition id-Additional-HS-Cell-Information-RL-Addition id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Param-Upd id-Secondary-Serving-Cell-List id-MultiCarrier-HSDSCH-Physical-Layer-Category id-IdleIntervalInformation ProtocolIE-ID ::= 801 id-NeedforIdleInterval id-IdleIntervalConfigurationIndicator id-ContinuousPacketConnectivity-DRX-InformationLCR ProtocolIE-ID ::= 805 id-ContinuousPacketConnectivity-DRX-InformationLCR	id-GANSS-ID	
id-GANSS-Earth-Orientation-Parameters id-GANSS-Additional-Time-Models id-GANSS-Additional-Navigation-Models id-GANSS-Additional-Navigation-Models id-GANSS-Additional-UTC-Models id-GANSS-Additional-UTC-Models id-GANSS-Adxiliary-Information id-MinimumReducedE-DPDCH-GainFactor id-Enhanced-FACH-Information-ResponseLCR id-Common-EDCH-MAC-d-Flow-Specific-InformationLCR id-Common-EDCH-MAC-d-Flow-Specific-InformationLCR id-HSDSCH-PreconfigurationSetup id-HSDSCH-PreconfigurationSetup id-HSDSCH-PreconfigurationInfo id-NoofTargetCellHS-SCCH-Order id-Additional-HS-Cell-Information-RL-Setup id-Additional-HS-Cell-Information-Response id-Additional-HS-Cell-Information-Response id-Additional-HS-Cell-Information-RL-Addition id-Additional-HS-Cell-Information-RL-Addition id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Param-Upd id-Secondary-Serving-Cell-List id-MultiCarrier-HSDSCH-Physical-Layer-Category id-IdleIntervalInformation ProtocolIE-ID ::= 801 id-NeedforIdleInterval id-IdleIntervalConfigurationIndicator id-ContinuousPacketConnectivity-DRX-InformationLCR ProtocolIE-ID ::= 805 id-ContinuousPacketConnectivity-DRX-InformationLCR	id-GANSS-Additional-Ionospheric-Model	
id-GANSS-Additional-Time-Models ProtocolIE-ID ::= 783 id-GANSS-Additional-Navigation-Models ProtocolIE-ID ::= 785 id-GANSS-Additional-UTC-Models ProtocolIE-ID ::= 785 id-GANSS-Auxiliary-Information ProtocolIE-ID ::= 786 id-MinimumReducedE-DPDCH-GainFactor ProtocolIE-ID ::= 787 id-Enhanced-FACH-Information-ResponseLCR ProtocolIE-ID ::= 789 id-Common-EDCH-MAC-d-Flow-Specific-InformationLCR ProtocolIE-ID ::= 789 id-HSDSCH-PreconfigurationSetup ProtocolIE-ID ::= 790 id-HSDSCH-PreconfigurationInfo ProtocolIE-ID ::= 791 id-MOOfTargetCellHS-SCCH-Order ProtocolIE-ID ::= 792 id-EnhancedHSServingCC-Abort ProtocolIE-ID ::= 792 id-Additional-HS-Cell-Information-RL-Setup ProtocolIE-ID ::= 793 id-Additional-HS-Cell-Information-RL-Addition ProtocolIE-ID ::= 796 id-Additional-HS-Cell-Information-RL-Reconf-Prep ProtocolIE-ID ::= 797 id-Additional-HS-Cell-Information-RL-Reconf-Req ProtocolIE-ID ::= 799 id-Additional-HS-Cell-Information-RL-Param-Upd ProtocolIE-		
id-GANSS-Additional-Navigation-Models id-GANSS-Additional-UTC-Models ProtocolIE-ID ::= 784 id-GANSS-Auxiliary-Information ProtocolIE-ID ::= 786 id-GANSS-Auxiliary-Information ProtocolIE-ID ::= 786 id-MinimumReducedE-DPDCH-GainFactor ProtocolIE-ID ::= 787 id-Enhanced-FACH-Information-ResponseLCR ProtocolIE-ID ::= 788 id-Common-EDCH-MAC-d-Flow-Specific-InformationLCR ProtocolIE-ID ::= 789 id-HSDSCH-PreconfigurationSetup ProtocolIE-ID ::= 790 id-HSDSCH-PreconfigurationInfo ProtocolIE-ID ::= 791 id-NoOfTargetCellHS-SCCH-Order ProtocolIE-ID ::= 792 id-EnhancedHSServingCC-Abort ProtocolIE-ID ::= 792 id-Additional-HS-Cell-Information-RL-Setup ProtocolIE-ID ::= 794 id-Additional-HS-Cell-Information-Response ProtocolIE-ID ::= 795 id-Additional-HS-Cell-Information-Response ProtocolIE-ID ::= 796 id-Additional-HS-Cell-Information-Response ProtocolIE-ID ::= 796 id-Additional-HS-Cell-Information-Reconf-Prep id-Additional-HS-Cell-Information-Reconf-Req ProtocolIE-ID ::= 799 id-Additional-HS-Cell-Information-RL-Reconf-Req ProtocolIE-ID ::= 799 id-Additional-HS-Cell-Information-RL-Param-Upd ProtocolIE-ID ::= 800 id-Additional-HS-Cell-Information-RL-Param-Upd ProtocolIE-ID ::= 802 id-MultiCarrier-HSDSCH-Physical-Layer-Category ProtocolIE-ID ::= 802 id-MultiCarrier-HSDSCH-Physical-Layer-Category ProtocolIE-ID ::= 804 id-NeedforIdleInterval id-IdleIntervalConfigurationIndicator ProtocolIE-ID ::= 806 id-ContinuousPacketConnectivity-DRX-InformationLCR		
id-GANSS-Additional-UTC-Models id-GANSS-Auxiliary-Information id-MinimumReducedE-DPDCH-GainFactor id-Enhanced-FACH-Information-ResponseLCR id-Common-EDCH-MAC-d-Flow-Specific-InformationLCR id-HSDSCH-PreconfigurationInfo id-MinimumReducedE-DPDCH-GainFactor id-Enhanced-FACH-InformationInfo id-HSDSCH-PreconfigurationInfo id-HSDSCH-PreconfigurationInfo id-NOOfTargetCellHS-SCCH-Order id-EnhancedHSServingCC-Abort id-Additional-HS-Cell-Information-RE-Setup id-Additional-HS-Cell-Information-RE-Setup id-Additional-HS-Cell-Information-RE-Addition id-Additional-HS-Cell-Information-RE-Addition id-Additional-HS-Cell-Information-RE-Pacton-Prep id-Additional-HS-Cell-Information-RE-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Pacton-Response id-Additional-HS-Cell-Information-RL-Pacton-Prep id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Pacton-Prep id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Pacton-Prep id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Pacton-Pacton-Prep id-Additional-HS-Cell-Information-RL-Pacton-Pacton-Prep id-Additional-HS-Cell-Information-RL-Pacton-Pacton-Prep id-Additional-HS-Cell-Information-RL-Pacton-Pacton-Prep id-Additional-HS-Cell-Information-RL-Pacton-Pacton-Pacton-ProtocolIE-ID ::= 801 id-Secondary-Serving-Cell-List ProtocolIE-ID ::= 802 id-MultiCarrier-HSDSCH-Physical-Layer-Category id-Information ProtocolIE-ID ::= 803 id-IdleIntervalInformation ProtocolIE-ID ::= 804 id-NeedforIdleInterval id-IdleIntervalConfigurationIndicator id-ContinuousPacketConnectivity-DRX-InformationLCR		
id-GANSS-Auxiliary-InformationProtocolIE-ID::=786id-MinimumReducedE-DPDCH-GainFactorProtocolIE-ID::=787id-Enhanced-FACH-Information-ResponseLCRProtocolIE-ID::=788id-Common-EDCH-MAC-d-Flow-Specific-InformationLCRProtocolIE-ID::=798id-HSDSCH-PreconfigurationSetupProtocolIE-ID::=790id-HSDSCH-PreconfigurationInfoProtocolIE-ID::=791id-NoOfTargetCellHS-SCCH-OrderProtocolIE-ID::=792id-Radditional-HS-Cell-Information-RL-SetupProtocolIE-ID::=793id-Additional-HS-Cell-Information-ResponseProtocolIE-ID::=795id-Additional-HS-Cell-Information-RL-AdditionProtocolIE-ID::=795id-Additional-HS-Cell-Information-RL-Reconf-PrepProtocolIE-ID::=797id-Additional-HS-Cell-Information-RL-Reconf-PrepProtocolIE-ID::=799id-Additional-HS-Cell-RL-Reconf-ResponseProtocolIE-ID::=799id-Additional-HS-Cell-Information-RL-Param-UpdProtocolIE-ID::=800id-Additional-HS-Cell-Information-RL-Param-UpdProtocolIE-ID::=801id-Secondary-Serving-Cell-ListProtocolIE-ID::=803id-MultiCarrier-HSDSCH-Physical-Layer-CategoryProtocolIE-ID::=803id-IdleIntervalInformationProtocolIE-ID::=805id-NeedforIdleIntervalProtocolIE-ID::=805id-ContinuousPacketConnectivity-DRX-InformationLCRProtocolIE-ID::= <td>-</td> <td></td>	-	
id-MinimumReducedE-DPDCH-GainFactorProtocolIE-ID::=787id-Enhanced-FACH-Information-ResponseLCRProtocolIE-ID::=788id-Common-EDCH-MAC-d-Flow-Specific-InformationLCRProtocolIE-ID::=789id-HSDSCH-PreconfigurationSetupProtocolIE-ID::=799id-HSDSCH-PreconfigurationInfoProtocolIE-ID::=791id-NoOfTargetCellHS-SCCH-OrderProtocolIE-ID::=792id-EnhancedHSServingCC-AbortProtocolIE-ID::=793id-Additional-HS-Cell-Information-RL-SetupProtocolIE-ID::=794id-Additional-HS-Cell-Information-ResponseProtocolIE-ID::=794id-Additional-HS-Cell-Information-RL-AdditionProtocolIE-ID::=796id-Additional-HS-Cell-Change-Information-ResponseProtocolIE-ID::=797id-Additional-HS-Cell-Information-RL-Reconf-PrepProtocolIE-ID::=798id-Additional-HS-Cell-Information-RL-Reconf-ReqProtocolIE-ID::=799id-Additional-HS-Cell-Information-RL-Param-UpdProtocolIE-ID::=801id-Secondary-Serving-Cell-ListProtocolIE-ID::=802id-MultiCarrier-HSDSCH-Physical-Layer-CategoryProtocolIE-ID::=803id-IdleIntervalInformationProtocolIE-ID::=805id-NeedforIdleIntervalProtocolIE-ID::=805id-ContinuousPacketConnectivity-DRX-InformationLCRProtocolIE-ID::=806		
id-Enhanced-FACH-Information-ResponseLCRProtocolIE-ID::=788id-Common-EDCH-MAC-d-Flow-Specific-InformationLCRProtocolIE-ID::=789id-HSDSCH-PreconfigurationSetupProtocolIE-ID::=790id-HSDSCH-PreconfigurationInfoProtocolIE-ID::=791id-NOOfTargetCellHS-SCCH-OrderProtocolIE-ID::=792id-EnhancedHSServingCC-AbortProtocolIE-ID::=793id-Additional-HS-Cell-Information-RL-SetupProtocolIE-ID::=794id-Additional-HS-Cell-Information-ResponseProtocolIE-ID::=794id-Additional-HS-Cell-Information-RL-AdditionProtocolIE-ID::=796id-Additional-HS-Cell-Change-Information-ResponseProtocolIE-ID::=797id-Additional-HS-Cell-Information-RL-Reconf-PrepProtocolIE-ID::=798id-Additional-HS-Cell-RL-Reconf-ResponseProtocolIE-ID::=798id-Additional-HS-Cell-Information-RL-Param-UpdProtocolIE-ID::=800id-Secondary-Serving-Cell-ListProtocolIE-ID::=801id-MultiCarrier-HSDSCH-Physical-Layer-CategoryProtocolIE-ID::=802id-MultiCarrier-HSDSCH-Physical-Layer-CategoryProtocolIE-ID::=803id-IdleIntervalInformationProtocolIE-ID::=805id-NeedforIdleIntervalProtocolIE-ID::=805id-ContinuousPacketConnectivity-DRX-InformationLCRProtocolIE-ID::=806		
id-Common-EDCH-MAC-d-Flow-Specific-InformationLCRProtocolIE-ID::= 789id-HSDSCH-PreconfigurationSetupProtocolIE-ID::= 790id-HSDSCH-PreconfigurationInfoProtocolIE-ID::= 791id-NoofTargetCelHS-SCCH-OrderProtocolIE-ID::= 792id-EnhancedHSServingCC-AbortProtocolIE-ID::= 793id-Additional-HS-Cell-Information-RL-SetupProtocolIE-ID::= 793id-Additional-HS-Cell-Information-ResponseProtocolIE-ID::= 795id-Additional-HS-Cell-Information-RL-AdditionProtocolIE-ID::= 796id-Additional-HS-Cell-Information-RL-Reconf-PrepProtocolIE-ID::= 797id-Additional-HS-Cell-Information-RL-Reconf-PrepProtocolIE-ID::= 798id-Additional-HS-Cell-Information-RL-Reconf-ReqProtocolIE-ID::= 799id-Additional-HS-Cell-Information-RL-Param-UpdProtocolIE-ID::= 801id-Secondary-Serving-Cell-ListProtocolIE-ID::= 802id-MultiCarrier-HSDSCH-Physical-Layer-CategoryProtocolIE-ID::= 803id-IdleIntervalInformationProtocolIE-ID::= 804id-NeedforIdleIntervalProtocolIE-ID::= 804id-IdleIntervalConfigurationIndicatorProtocolIE-ID::= 805id-ContinuousPacketConnectivity-DRX-InformationLCRProtocolIE-ID::= 807		
id-HSDSCH-PreconfigurationSetupProtocolIE-ID::=790id-HSDSCH-PreconfigurationInfoProtocolIE-ID::=791id-NoOfTargetCellHS-SCCH-OrderProtocolIE-ID::=792id-EnhancedHSServingCC-AbortProtocolIE-ID::=793id-Additional-HS-Cell-Information-RL-SetupProtocolIE-ID::=794id-Additional-HS-Cell-Information-ResponseProtocolIE-ID::=795id-Additional-HS-Cell-Information-RL-AdditionProtocolIE-ID::=796id-Additional-HS-Cell-Change-Information-ResponseProtocolIE-ID::=797id-Additional-HS-Cell-Information-RL-Reconf-PrepProtocolIE-ID::=798id-Additional-HS-Cell-Information-RL-Reconf-ReqProtocolIE-ID::=799id-Additional-HS-Cell-Information-RL-Param-UpdProtocolIE-ID::=800id-Secondary-Serving-Cell-ListProtocolIE-ID::=802id-MultiCarrier-HSDSCH-Physical-Layer-CategoryProtocolIE-ID::=802id-IdleIntervalInformationProtocolIE-ID::=804id-NeedforIdleIntervalProtocolIE-ID::=805id-IdleIntervalConfigurationIndicatorProtocolIE-ID::=805id-ContinuousPacketConnectivity-DRX-InformationLCRProtocolIE-ID::=807	-	
id-HSDSCH-PreconfigurationInfo id-NoOfTargetCellHS-SCCH-Order id-EnhancedHSServingCC-Abort id-Additional-HS-Cell-Information-RL-Setup id-Additional-HS-Cell-Information-Response id-Additional-HS-Cell-Information-Response id-Additional-HS-Cell-Information-Response id-Additional-HS-Cell-Information-Response id-Additional-HS-Cell-Information-Response id-Additional-HS-Cell-Information-Response id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Param-Upd id-Additional-HS-Cell-Information-RL-Param-Upd id-Secondary-Serving-Cell-List id-MultiCarrier-HSDSCH-Physical-Layer-Category id-IdleIntervalInformation id-NeedforIdleInterval id-IdleIntervalConfigurationIndicator id-ContinuousPacketConnectivity-DRX-InformationLCR ProtocolIE-ID ::= 806 id-ContinuousPacketConnectivity-DRX-InformationLCR	-	
id-NoofTargetCellHS-SCCH-OrderProtocolIE-ID::= 792id-EnhancedHSServingCC-AbortProtocolIE-ID::= 793id-Additional-HS-Cell-Information-RL-SetupProtocolIE-ID::= 794id-Additional-HS-Cell-Information-ResponseProtocolIE-ID::= 795id-Additional-HS-Cell-Information-RL-AdditionProtocolIE-ID::= 796id-Additional-HS-Cell-Change-Information-ResponseProtocolIE-ID::= 797id-Additional-HS-Cell-Information-RL-Reconf-PrepProtocolIE-ID::= 798id-Additional-HS-Cell-Information-RL-Reconf-ReqProtocolIE-ID::= 799id-Additional-HS-Cell-Information-RL-Param-UpdProtocolIE-ID::= 800id-Secondary-Serving-Cell-ListProtocolIE-ID::= 801id-MultiCarrier-HSDSCH-Physical-Layer-CategoryProtocolIE-ID::= 802id-MultiCarrier-HSDSCH-Physical-Layer-CategoryProtocolIE-ID::= 804id-IdleIntervalInformationProtocolIE-ID::= 805id-IdleIntervalConfigurationIndicatorProtocolIE-ID::= 806id-ContinuousPacketConnectivity-DRX-InformationLCRProtocolIE-ID::= 807	-	
id-EnhancedHSServingCC-Abort id-Additional-HS-Cell-Information-RL-Setup id-Additional-HS-Cell-Information-Response id-Additional-HS-Cell-Information-Response id-Additional-HS-Cell-Information-RL-Addition id-Additional-HS-Cell-Information-RL-Addition id-Additional-HS-Cell-Change-Information-Response id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Param-Upd id-Secondary-Serving-Cell-List id-MultiCarrier-HSDSCH-Physical-Layer-Category id-IdleIntervalInformation id-NeedforIdleInterval id-IdleIntervalConfigurationIndicator id-ContinuousPacketConnectivity-DRX-InformationLCR ProtocolIE-ID ::= 806 id-ContinuousPacketConnectivity-DRX-InformationLCR	~	
id-Additional-HS-Cell-Information-RL-Setup id-Additional-HS-Cell-Information-Response id-Additional-HS-Cell-Information-RE-Addition id-Additional-HS-Cell-Information-RL-Addition id-Additional-HS-Cell-Change-Information-Response id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Param-Upd id-Secondary-Serving-Cell-List id-MultiCarrier-HSDSCH-Physical-Layer-Category id-IdleIntervalInformation id-NeedforIdleInterval id-IdleIntervalConfigurationIndicator id-ContinuousPacketConnectivity-DRX-InformationLCR ProtocolIE-ID ::= 806 id-ContinuousPacketConnectivity-DRX-InformationLCR		
id-Additional-HS-Cell-Information-Response id-Additional-HS-Cell-Information-RL-Addition id-Additional-HS-Cell-Change-Information-Response id-Additional-HS-Cell-Change-Information-Response id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Param-Upd id-Additional-HS-Cell-Information-RL-Param-Upd id-Secondary-Serving-Cell-List id-MultiCarrier-HSDSCH-Physical-Layer-Category id-IdleIntervalInformation id-NeedforIdleInterval id-IdleIntervalConfigurationIndicator id-ContinuousPacketConnectivity-DRX-InformationLCR ProtocolIE-ID ::= 806 id-ContinuousPacketConnectivity-DRX-InformationLCR		
id-Additional-HS-Cell-Information-RL-Addition ProtocolIE-ID ::= 796 id-Additional-HS-Cell-Change-Information-Response ProtocolIE-ID ::= 797 id-Additional-HS-Cell-Information-RL-Reconf-Prep ProtocolIE-ID ::= 798 id-Additional-HS-Cell-Information-RL-Reconf-Req ProtocolIE-ID ::= 799 id-Additional-HS-Cell-Information-RL-Peronf ProtocolIE-ID ::= 800 id-Additional-HS-Cell-Information-RL-Param-Upd ProtocolIE-ID ::= 801 id-Secondary-Serving-Cell-List ProtocolIE-ID ::= 802 id-MultiCarrier-HSDSCH-Physical-Layer-Category ProtocolIE-ID ::= 803 id-IdleIntervalInformation ProtocolIE-ID ::= 804 id-NeedforIdleInterval ProtocolIE-ID ::= 805 id-IdleIntervalConfigurationIndicator ProtocolIE-ID ::= 806 id-ContinuousPacketConnectivity-DRX-InformationLCR		
id-Additional-HS-Cell-Change-Information-ResponseProtocolIE-ID::= 797id-Additional-HS-Cell-Information-RL-Reconf-PrepProtocolIE-ID::= 798id-Additional-HS-Cell-Information-RL-Reconf-ReqProtocolIE-ID::= 799id-Additional-HS-Cell-RL-Reconf-ResponseProtocolIE-ID::= 800id-Additional-HS-Cell-Information-RL-Param-UpdProtocolIE-ID::= 801id-Secondary-Serving-Cell-ListProtocolIE-ID::= 802id-MultiCarrier-HSDSCH-Physical-Layer-CategoryProtocolIE-ID::= 803id-IdleIntervalInformationProtocolIE-ID::= 804id-NeedforIdleIntervalProtocolIE-ID::= 805id-IdleIntervalConfigurationIndicatorProtocolIE-ID::= 806id-ContinuousPacketConnectivity-DRX-InformationLCRProtocolIE-ID::= 807		
id-Additional-HS-Cell-Information-RL-Reconf-Prep id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-Information-RL-Reconf-Req id-Additional-HS-Cell-RL-Reconf-Response id-Additional-HS-Cell-Information-RL-Param-Upd id-Additional-HS-Cell-Information-RL-Param-Upd id-Secondary-Serving-Cell-List id-MultiCarrier-HSDSCH-Physical-Layer-Category id-IdleIntervalInformation id-NeedforIdleInterval id-IdleInterval id-IdleInterval id-IdleInterval id-IdleInterval ProtocolIE-ID ::= 804 id-IdleIntervalConfigurationIndicator id-ContinuousPacketConnectivity-DRX-InformationLCR ProtocolIE-ID ::= 807		
id-Additional-HS-Cell-Information-RL-Reconf-Req ProtocolIE-ID ::= 799 id-Additional-HS-Cell-RL-Reconf-Response ProtocolIE-ID ::= 800 id-Additional-HS-Cell-Information-RL-Param-Upd ProtocolIE-ID ::= 801 id-Secondary-Serving-Cell-List ProtocolIE-ID ::= 802 id-MultiCarrier-HSDSCH-Physical-Layer-Category ProtocolIE-ID ::= 803 id-IdleIntervalInformation ProtocolIE-ID ::= 804 id-IdleIntervalConfigurationIndicator ProtocolIE-ID ::= 806 id-ContinuousPacketConnectivity-DRX-InformationLCR	-	
id-Additional-HS-Cell-RL-Reconf-ResponseProtocolIE-ID::= 800id-Additional-HS-Cell-Information-RL-Param-UpdProtocolIE-ID::= 801id-Secondary-Serving-Cell-ListProtocolIE-ID::= 802id-MultiCarrier-HSDSCH-Physical-Layer-CategoryProtocolIE-ID::= 803id-IdleIntervalInformationProtocolIE-ID::= 804id-NeedforIdleIntervalProtocolIE-ID::= 805id-IdleIntervalConfigurationIndicatorProtocolIE-ID::= 806id-ContinuousPacketConnectivity-DRX-InformationLCRProtocolIE-ID::= 807	-	
id-Additional-HS-Cell-Information-RL-Param-UpdProtocolIE-ID ::= 801id-Secondary-Serving-Cell-ListProtocolIE-ID ::= 802id-MultiCarrier-HSDSCH-Physical-Layer-CategoryProtocolIE-ID ::= 803id-IdleIntervalInformationProtocolIE-ID ::= 804id-NeedforIdleIntervalProtocolIE-ID ::= 805id-IdleIntervalConfigurationIndicatorProtocolIE-ID ::= 806id-ContinuousPacketConnectivity-DRX-InformationLCRProtocolIE-ID ::= 807	id-Additional-HS-Cell-Information-RL-Reconf-Req	ProtocolIE-ID ::= 799
id-Secondary-Serving-Cell-List id-MultiCarrier-HSDSCH-Physical-Layer-Category id-IdleIntervalInformation id-NeedforIdleInterval id-IdleIntervalConfigurationIndicator id-ContinuousPacketConnectivity-DRX-InformationLCR ProtocolIE-ID ::= 805 id-ContinuousPacketConnectivity-DRX-InformationLCR ProtocolIE-ID ::= 806	id-Additional-HS-Cell-RL-Reconf-Response	ProtocolIE-ID ::= 800
id-MultiCarrier-HSDSCH-Physical-Layer-CategoryProtocolIE-ID::= 803id-IdleIntervalInformationProtocolIE-ID::= 804id-NeedforIdleIntervalProtocolIE-ID::= 805id-IdleIntervalConfigurationIndicatorProtocolIE-ID::= 806id-ContinuousPacketConnectivity-DRX-InformationLCRProtocolIE-ID::= 807	id-Additional-HS-Cell-Information-RL-Param-Upd	ProtocolIE-ID ::= 801
id-IdleIntervalInformation ProtocolIE-ID ::= 804 id-NeedforIdleInterval ProtocolIE-ID ::= 805 id-IdleIntervalConfigurationIndicator ProtocolIE-ID ::= 806 id-ContinuousPacketConnectivity-DRX-InformationLCR ProtocolIE-ID ::= 807	id-Secondary-Serving-Cell-List	ProtocolIE-ID ::= 802
<pre>id-NeedforIdleInterval id-IdleIntervalConfigurationIndicator id-ContinuousPacketConnectivity-DRX-InformationLCR</pre> <pre>ProtocolIE-ID ::= 805 id-ContinuousPacketConnectivity-DRX-InformationLCR</pre> <pre>ProtocolIE-ID ::= 807</pre>	id-MultiCarrier-HSDSCH-Physical-Layer-Category	ProtocolIE-ID ::= 803
<pre>id-NeedforIdleInterval id-IdleIntervalConfigurationIndicator id-ContinuousPacketConnectivity-DRX-InformationLCR ProtocolIE-ID ::= 806 ProtocolIE-ID ::= 807</pre>	id-IdleIntervalInformation	ProtocolIE-ID ::= 804
id-IdleIntervalConfigurationIndicator ProtocolIE-ID ::= 806 id-ContinuousPacketConnectivity-DRX-InformationLCR ProtocolIE-ID ::= 807	id-NeedforIdleInterval	
id-ContinuousPacketConnectivity-DRX-InformationLCR ProtocolIE-ID ::= 807		
	• • • • • • • • • • • • • • • • • • • •	

id-E-AGCH-UE-Inactivity-Monitor-Threshold	ProtocolIE-ID ::= 809
id-CPC-InformationLCR	ProtocolIE-ID ::= 810
id-E-DCH-Semi-PersistentScheduling-Information-LCR	ProtocolIE-ID ::= 811
id-HS-DSCH-Semi-PersistentScheduling-Information-LCR	ProtocolIE-ID ::= 812
id-HS-DSCH-Semi-PersistentScheduling-Information-ResponseLCR	ProtocolIE-ID ::= 813
id-E-DCH-Semi-PersistentScheduling-Information-ResponseLCR	ProtocolIE-ID ::= 814
id-MIMO-SFMode-For-HSPDSCHDualStream	ProtocolIE-ID ::= 815
id-MIMO-SFMode-Supported-For-HSPDSCHDualStream	ProtocolIE-ID ::= 816
id-MIMO-ReferenceSignal-InformationListLCR	ProtocolIE-ID ::= 817
id-GANSS-alm-keplerianNAVAlmanac	ProtocolIE-ID ::= 818
id-GANSS-alm-keplerianReducedAlmanac	ProtocolIE-ID ::= 819
id-GANSS-alm-keplerianMidiAlmanac	ProtocolIE-ID ::= 820
id-GANSS-alm-keplerianGLONASS	ProtocolIE-ID ::= 821
id-GANSS-alm-ecefSBASAlmanac	ProtocolIE-ID ::= 822
id-DL-RLC-PDU-Size-Format	ProtocolIE-ID ::= 823
id-MACes-Maximum-Bitrate-LCR	ProtocolIE-ID ::= 824
id-Single-Stream-MIMO-ActivationIndicator	ProtocolIE-ID ::= 825
id-Single-Stream-MIMO-Mode-Indicator	ProtocolIE-ID ::= 826
id-Dual-Band-Secondary-Serving-Cell-List	ProtocolIE-ID ::= 827
id-UE-AggregateMaximumBitRate	ProtocolIE-ID ::= 828
id-power-offset-for-S-CPICH-for-MIMO	ProtocolIE-ID ::= 829
id-power-offset-for-S-CPICH-for-MIMO-Request-Indicator	ProtocolIE-ID ::= 830
id-UE-SupportIndicatorExtension	ProtocolIE-ID ::= 831
id-ActivationInformation	ProtocolIE-ID ::= 835
id-CellPortionLCRID	ProtocolIE-ID ::= 836
id-Additional-EDCH-Cell-Information-RL-Setup-Req	ProtocolIE-ID ::= 837
id-Additional-EDCH-Cell-Information-Response	ProtocolIE-ID ::= 838
id-Additional-EDCH-Cell-Information-RL-Add-Req	ProtocolIE-ID ::= 839
id-Additional-EDCH-Cell-Information-Response-RLAdd	ProtocolIE-ID ::= 840
id-Additional-EDCH-Cell-Information-RL-Reconf-Prep	ProtocolIE-ID ::= 841
id-Additional-EDCH-Cell-Information-RL-Reconf-Req	ProtocolIE-ID ::= 842
id-Additional-EDCH-Cell-Information-RL-Param-Upd	ProtocolIE-ID ::= 843
id-Additional-EDCH-Preconfiguration-Information	ProtocolIE-ID ::= 844
id-MulticellEDCH-Information	ProtocolIE-ID ::= 845
id-Additional-EDCH-Cell-Information-ResponseRLReconf	ProtocolIE-ID ::= 854
id-EDCH-Indicator	ProtocolIE-ID ::= 855
id-DiversityMode	ProtocolIE-ID ::= 856
id-TransmitDiversityIndicator	ProtocolIE-ID ::= 857
id-NonCellSpecificTxDiversity	ProtocolIE-ID ::= 858
id-CellCapabilityContainerExtension-FDD	ProtocolIE-ID ::= 859
id-HSDSCH-Physical-Layer-Category	ProtocolIE-ID ::= 860
id-E-RNTI-For-FACH id-H-RNTI-For-FACH	ProtocolIE-ID ::= 861
	ProtocolIE-ID ::= 862
id-RNTI-Allocation-Indicator	ProtocolIE-ID ::= 863
id-UE-AggregateMaximumBitRate-Enforcement-Indicator	ProtocolIE-ID ::= 864
id-DCH-MeasurementOccasion-Information	ProtocolIE-ID ::= 865
id-DCH-MeasurementType-Indicator	ProtocolIE-ID ::= 866 ProtocolIE-ID ::= 867
id-Out-of-Sychronization-Window	
id-MulticellEDCH-RL-SpecificInformation	ProtocolIE-ID ::= 868
id-DGNSS-ValidityPeriod	ProtocolIE-ID ::= 869
id-TSO-HS-PDSCH-Indication-LCR	ProtocolIE-ID ::= 870 ProtocolIE-ID ::= 871
id-UE-TS0-CapabilityLCR id-Non-Serving-RL-Preconfig-Info	
id-Non-Serving-RL-Preconfig-Info id-Non-Serving-RL-Preconfig-Setup	ProtocolIE-ID ::= 872 ProtocolIE-ID ::= 873
TO MON-PETATING VITALECOUNTIA-BECOTA	FIOCOCOTIE-ID ··= 0/2

id-Non-Serving-RL-Preconfig-Removal	ProtocolIE-ID ::= 874
id-Additional-E-DCH-Non-Serving-RL-Preconfiguration-Setup	ProtocoliE-ID ::= 875
id-Additional-E-DCH-New-non-serving-RL-E-DCH-FDD-DL-Control-Channel-I	
id-CellListValidityIndicator	ProtocolIE-ID ::= 877
id-completeAlmanacProvided	ProtocoliE-ID ::= 878
id-ganss-Delta-T	ProtocoliE-ID ::= 879
id-OrdinalNumberOfFrequency	ProtocolIE-ID ::= 880
id-Multicell-EDCH-Restriction	ProtocolIE-ID ::= 882
id-CellCapabilityContainerExtension-TDD-LCR	ProtocolIE-ID ::= 883
id-Multi-Carrier-EDCH-Setup	ProtocoliE-ID ::= 884
id-Multi-Carrier-EDCH-Reconfigure	ProtocoliE-ID ::= 885
id-Multi-Carrier-EDCH-Response	ProtocoliE-ID ::= 886
id-SNPL-Carrier-Group-Indicator	ProtocolIE-ID ::= 887
id-MU-MIMO-InformationLCR	ProtocolIE-ID ::= 888
id-MU-MIMO-Indicator	ProtocoliE-ID ::= 889
id-HS-SCCH-Inactivity-Threshold-for-UE-DRX-Cycle-LCR-Ext	ProtocoliE-ID ::= 890
id-Usefulness-Of-Battery-Optimization	ProtocoliE-ID ::= 891
id-Multi-Carrier-E-DCH-LCRTDD-PhysicalLayerCategory	ProtocoliE-ID ::= 892
id-Measurement-Power-Offset	ProtocoliE-ID ::= 893
id-MDT-Configuration	ProtocoliE-ID ::= 894
id-Neighbouring-UMTS-CellInformation-Ext	ProtocolIE-ID ::= 895
id-Neighbouring-UMTS-CellInformationExtensionItem	ProtocoliE-ID ::= 896
id-Control-Type-InformationTransferControlReq	ProtocoliE-ID ::= 897
id-UMTS-Cells-Info	ProtocolIE-ID ::= 898
id-ANRReportIndication	ProtocolIE-ID ::= 899
id-ANR-Cell-InfEx-Rgst	ProtocolIE-ID ::= 900
id-ANR-Cell-InfEx-Rsp	ProtocoliE-ID ::= 901
id-ANR-Cell-Information	ProtocoliE-ID ::= 902
id-Trace-Collection-Entity-IP-Address	ProtocolIE-ID ::= 904
id-Affected-HSDSCH-Serving-Cell-List	ProtocolIE-ID ::= 905
id-Support-of-Dynamic-DTXDRX-Related-HS-SCCH-Order	ProtocolIE-ID ::= 909
id-CPC-RecoveryReport	ProtocolIE-ID ::= 910
id-UE-RF-Band-CapabilityLCR	ProtocolIE-ID ::= 913
id-PCI	ProtocolIE-ID ::= 939
id-TAC	ProtocolIE-ID ::= 940
id-PLMN-List	ProtocolIE-ID ::= 941
id-SpeechVersion	ProtocolIE-ID ::= 2048
id-SourceID	ProtocolIE-ID ::= 2049
id-TargetID	ProtocolIE-ID ::= 2050
id-ClassmarkInformation2	ProtocolIE-ID ::= 2051
id-ClassmarkInformation3	ProtocolIE-ID ::= 2052
id-GSM-Cell-CM-Rqst	ProtocolIE-ID ::= 2053
id-Extension-CommonMeasurementObjectType-CM-Rprt	ProtocolIE-ID ::= 2054
id-Extension-CommonMeasurementObjectType-CM-Rgst	ProtocolIE-ID ::= 2055
id-Extension-CommonMeasurementObjectType-CM-Rsp	ProtocolIE-ID ::= 2056
id-Extension-FailureIndicationMeasurementList	ProtocolIE-ID ::= 2057
id-Extension-FailureMeasurementList	ProtocolIE-ID ::= 2058
id-Extension-TerminationMeasurementList	ProtocolIE-ID ::= 2059
id-GsmCellList-CM-Rprt	ProtocolIE-ID ::= 2060
id-GsmCellList-CM-Rqst	ProtocolIE-ID ::= 2061
id-GsmCellList-CM-Rsp	ProtocolIE-ID ::= 2062
id-LoadValue	ProtocolIE-ID ::= 2063
id-EventH	ProtocolIE-ID ::= 2064

END

9.3.7 Container Definitions

```
-- Container definitions
RNSAP-Containers {
itu-t (0) identified-organization (4) etsi (0) mobileDomain (0)
umts-Access (20) modules (3) rnsap (1) version1 (1) rnsap-Containers (5) }
DEFINITIONS AUTOMATIC TAGS ::=
BEGIN
     ****************
-- IE parameter types from other modules.
IMPORTS
   maxPrivateIEs,
   maxProtocolExtensions,
   maxProtocolIEs,
   Criticality,
   Presence,
   PrivateIE-ID,
   ProtocolIE-ID
FROM RNSAP-CommonDataTypes;
  ******************
-- Class Definition for Protocol IEs
__ **********************
RNSAP-PROTOCOL-IES ::= CLASS {
                ProtocolIE-ID
                                            UNIQUE,
   &criticality
                       Criticality,
   &Value,
   &presence
                   Presence
WITH SYNTAX {
                 &id
   CRITICALITY
                    &criticality
   TYPE
                    &Value
   PRESENCE
                    &presence
```

```
__ *******************
-- Class Definition for Protocol IEs
__ **********************
RNSAP-PROTOCOL-IES-PAIR ::= CLASS {
   &id
              ProtocolIE-ID
                                       UNIQUE,
   &firstCriticality
                     Criticality,
   &FirstValue,
   &secondCriticality
                     Criticality,
   &SecondValue,
   &presence
                  Presence
WITH SYNTAX {
   ID
               &id
   FIRST CRITICALITY
                     &firstCriticality
   FIRST TYPE
                  &FirstValue
                     &secondCriticality
   SECOND CRITICALITY
                  &SecondValue
   SECOND TYPE
   PRESENCE
                  &presence
   -- Class Definition for Protocol Extensions
  *******************
RNSAP-PROTOCOL-EXTENSION ::= CLASS {
   &id
               ProtocolIE-ID
                                    UNIQUE,
   &criticality
                     Criticality,
   &Extension,
   &presence
               Presence
WITH SYNTAX {
  ID
               &id
                  &criticality
   CRITICALITY
                  &Extension
   EXTENSION
   PRESENCE
                  &presence
   -- Class Definition for Private IEs
__ **********************************
RNSAP-PRIVATE-IES ::= CLASS {
   &id
               PrivateIE-ID,
   &criticality
                     Criticality,
   &Value,
   &presence
               Presence
```

```
WITH SYNTAX {
   ID
                &id
   CRITICALITY
                   &criticality
                &Value
   PRESENCE
                   &presence
  Container for Protocol IEs
  ****************
ProtocolIE-Container {RNSAP-PROTOCOL-IES : IesSetParam} ::=
   SEQUENCE (SIZE (0..maxProtocolIEs)) OF
   ProtocolIE-Field {{IesSetParam}}
ProtocolIE-Single-Container {RNSAP-PROTOCOL-IES : IesSetParam} ::=
   ProtocolIE-Field {{IesSetParam}}
ProtocolIE-Field {RNSAP-PROTOCOL-IES : IesSetParam} ::= SEQUENCE {
   id RNSAP-PROTOCOL-IES.&id ({IesSetParam}),
                                                  ({IesSetParam}{@id}),
   criticality
              RNSAP-PROTOCOL-IES.&criticality
                                                    ({IesSetParam}{@id})
   value
                   RNSAP-PROTOCOL-IES.&Value
    ******************
-- Container for Protocol IE Pairs
ProtocolIE-ContainerPair {RNSAP-PROTOCOL-IES-PAIR : IesSetParam} ::=
   SEQUENCE (SIZE (0..maxProtocolIEs)) OF
   ProtocolIE-FieldPair {{IesSetParam}}
ProtocolIE-FieldPair {RNSAP-PROTOCOL-IES-PAIR : IesSetParam} ::= SEQUENCE {
       RNSAP-PROTOCOL-IES-PAIR.&id
                                             ({IesSetParam}),
   firstCriticality RNSAP-PROTOCOL-IES-PAIR.&firstCriticality ({IesSetParam}{@id}),
   firstValue RNSAP-PROTOCOL-IES-PAIR.&FirstValue ({IesSetParam}{@id}),
   secondCriticality RNSAP-PROTOCOL-IES-PAIR.&secondCriticality ({IesSetParam}{@id}),
   secondValue RNSAP-PROTOCOL-IES-PAIR. & SecondValue
                                                           ({IesSetParam}{@id})
     Container Lists for Protocol IE Containers
ProtocolIE-ContainerList {INTEGER : lowerBound, INTEGER : upperBound, RNSAP-PROTOCOL-IES : IesSetParam} ::=
   SEQUENCE (SIZE (lowerBound..upperBound)) OF
   ProtocolIE-Container {{IesSetParam}}
```

1089

```
ProtocolIE-ContainerPairList {INTEGER : lowerBound, INTEGER : upperBound, RNSAP-PROTOCOL-IES-PAIR : IesSetParam} ::=
   SEQUENCE (SIZE (lowerBound..upperBound)) OF
   ProtocolIE-ContainerPair {{IesSetParam}}
  *****************
-- Container for Protocol Extensions
       ProtocolExtensionContainer {RNSAP-PROTOCOL-EXTENSION : ExtensionSetParam} ::=
   SEQUENCE (SIZE (1..maxProtocolExtensions)) OF
   ProtocolExtensionField {{ExtensionSetParam}}
ProtocolExtensionField {RNSAP-PROTOCOL-EXTENSION : ExtensionSetParam} ::= SEQUENCE {
                RNSAP-PROTOCOL-EXTENSION.&id
                                                   ({ExtensionSetParam}),
                                                         ({ExtensionSetParam}{@id}),
   criticality
                   RNSAP-PROTOCOL-EXTENSION.&criticality
                                                         ({ExtensionSetParam}{@id})
   extensionValue
                       RNSAP-PROTOCOL-EXTENSION. & Extension
   -- Container for Private IEs
__ *******************
PrivateIE-Container {RNSAP-PRIVATE-IES : IesSetParam} ::=
   SEQUENCE (SIZE (1..maxPrivateIEs)) OF
   PrivateIE-Field {{IesSetParam}}
PrivateIE-Field {RNSAP-PRIVATE-IES : IesSetParam} ::= SEQUENCE {
               RNSAP-PRIVATE-IES.&id
                                            ({IesSetParam}),
   criticality
                    RNSAP-PRIVATE-IES.&criticality
                                                  ({IesSetParam}{@id}),
   value
                RNSAP-PRIVATE-IES.&Value
                                           ({IesSetParam}{@id})
END
```

9.4 Message Transfer Syntax

RNSAP shall use the ASN.1 Basic Packed Encoding Rules (BASIC-PER) Aligned Variant as transfer syntax as specified in ITU-T Rec. X.691 [20].

9.5 Timers

$T_{Preempt}$

 Specifies the maximum time that a DRNS may wait for pre-emption of resources for establishment or reconfiguration of Radio Links.

$T_{RELOCprep}$

- Specifies the maximum time for the Enhanced Relocation procedure in the SRNC.

Handling of Unknown, Unforeseen and Erroneous Protocol Data

10.1 General

Protocol Error cases can be divided into three classes:

- 1. Transfer Syntax Error;
- 2. Abstract Syntax Error;
- 3. Logical Error.

Protocol errors can occur in the following functions within a receiving node.




Figure 34: Protocol Errors in RNSAP

The information stated in subclauses 10.2, 10.3 and 10.4, to be included in the message used when reporting an error, is what at minimum shall be included. Other optional information elements within the message may also be included, if available. This is also valid for the case when the reporting is done with a response message. The latter is an exception to what is stated in subclause 4.1.

10.2 Transfer Syntax Error

A Transfer Syntax Error occurs when the receiver is not able to decode the received physical message. Transfer syntax errors are always detected in the process of ASN.1 decoding. If a Transfer Syntax Error occurs, the receiver should initiate Error Indication procedure with appropriate cause value for the Transfer Syntax protocol error.

Examples for Transfer Syntax Errors are:

- Violation of value ranges in ASN.1 definition of messages. E.g.: If an IE has a defined value range of 0 to 10 (ASN.1: INTEGER (0..10)), and 12 will be received, then this will be treated as a transfer syntax error;
- Violation in list element constraints. E.g.: If a list is defined as containing 1 to 10 elements, and 12 elements will be received, than this case will be handled as a transfer syntax error;
- Missing mandatory elements in ASN.1 SEQUENCE definitions (as sent by the originator of the message);
- Wrong order of elements in ASN.1 SEQUENCE definitions (as sent by the originator of the message).

10.3 Abstract Syntax Error

10.3.1 General

An Abstract Syntax Error occurs when the receiving functional RNSAP entity:

- 1. Receives IEs or IE groups that cannot be understood (unknown IE id);
- 2 Receives IEs for which the logical range is violated (e.g.: ASN.1 definition: 0 to 15, the logical range is 0 to 10 (values 11 to 15 are undefined), and 12 will be received; this case will be handled as an abstract syntax error using criticality information sent by the originator of the message);
- 3 Does not receive IEs or IE groups but according to the specified presence of the concerned object, the IEs or IE groups should have been present in the received message;
- 4 Receives IEs or IE groups that are defined to be part of that message in wrong order or with too many occurrences of the same IE or IE group;
- 5 receives IEs or IE groups but according to the conditional presence of the concerned object and the specified condition, the IEs or IE groups should not have been present in the received message.

Cases 1 and 2 (not comprehended IE/IE group) are handled based on received Criticality information. Case 3 (missing IE/IE group) is handled based on Criticality information and Presence information for the missing IE/IE group specified in the version of the specification used by the receiver. Case 4 (IEs or IE groups in wrong order or with too many occurrences) and Case 5 (erroneously present conditional IEs or IE groups) result in rejecting the procedure.

If an Abstract Syntax Error occurs, the receiver shall read the remaining message and shall then for each detected Abstract Syntax Error that belong to cases 1-3 act according to the Criticality Information and Presence Information for the IE/IE group due to which Abstract Syntax Error occurred in accordance with subclauses 10.3.4 and 10.3.5. The handling of cases 4 and 5 is specified in subclause 10.3.6.

10.3.2 Criticality Information

In the RNSAP messages there is criticality information set for individual IEs and/or IE groups. This criticality information instructs the receiver how to act when receiving an IE or an IE group that is not comprehended, i.e. the entire item (IE or IE group) which is not (fully or partially) comprehended shall be treated in accordance with its own criticality information as specified in subclause 10.3.4.

In addition, the criticality information is used in case of the missing IE/IE group abstract syntax error (see subclause 10.3.5).

The receiving node shall take different actions depending on the value of the Criticality Information. The three possible values of the Criticality Information for an IE/IE group are:

- 1. Reject IE;
- 2. Ignore IE and Notify Sender;
- 3. Ignore IE.

The following rules restrict when a receiving entity may consider an IE, an IE group or an EP not comprehended (not implemented), and when action based on criticality information is applicable:

- 1. IE or IE group: When one new or modified IE or IE group is implemented for one EP from a standard version, then other new or modified IEs or IE groups specified for that EP in that standard version shall be considered comprehended by a receiving entity (some may still remain unsupported).
- 2. EP: The comprehension of different Eps within a standard version or between different standard versions is not mandated. Any EP that is not supported may be considered not comprehended, even if another EP from that standard version is comprehended, and action based on criticality shall be applied.

10.3.3 Presence Information

For many IEs/IE groups which are optional according to the ASN.1 transfer syntax, RNSAP specifies separately if the presence of these IEs/IE groups is optional or mandatory with respect to RNS application by means of the presence field f the concerned object of class RNSAP-PROTOCOL-IES, RNSAP-PROTOCOL-IES-PAIR, RNSAP-PROTOCOL-EXTENSION or RNSAP-PRIVATE-IES.

The presence field of the indicated classes supports three values:

- 1. Optional;
- 2. Conditional;
- 3. Mandatory.

If an IE/IE group is not included in a received message and the presence of the IE/IE group is mandatory or the presence is conditional and the condition is true according to the version of the specification used by the receiver, an abstract syntax error occurs due to a missing IE/IE group.

If an IE/IE group is included in a received message and the presence of the IE/IE group is conditional and the condition is false according to the version of the specification used by the receiver, an abstract syntax error occurs due to this erroneously present conditional IE/IE group.

10.3.4 Not Comprehended IE/IE Group

10.3.4.1 Procedure ID

The receiving node shall treat the different types of received criticality information of the *Procedure ID* according to the following:

Reject IE:

- If a message is received with a *Procedure ID* marked with "*Reject IE*" which the receiving node does not comprehend, the receiving node shall reject the procedure using the Error Indication procedure.

Ignore IE and Notify Sender:

- If a message is received with a *Procedure ID* marked with "*Ignore IE and Notify Sender*" which the receiving node does not comprehend, the receiving node shall ignore the procedure and initiate the Error Indication procedure.

Ignore IE:

- If a message is received with a *Procedure ID* marked with "*Ignore IE*" which the receiving node does not comprehend, the receiving node shall ignore the procedure.

When using the Error Indication procedure to reject a procedure or to report an ignored procedure it shall include the *Procedure ID* IE, the *Triggering Message* IE, and the *Procedure Criticality* IE in the *Criticality Diagnostics* IE.

10.3.4.1A Type of Message

When the receiving node cannot decode the *Type of Message* IE, the Error Indication procedure shall be initiated with an appropriate cause value.

10.3.4.2 IEs Other Than the Procedure ID and Type of Message

The receiving node shall treat the different types of received criticality information of an IE/IE group other than the *Procedure ID* IE and *Type of Message* IE according to the following:

Reject IE:

- If a message *initiating* a procedure is received containing one or more IEs/IE groups marked with "*Reject IE*" which the receiving node does not comprehend; none of the functional requests of the message shall be executed. The receiving node shall reject the procedure and report the rejection of one or more IEs/IE groups using the message normally used to report unsuccessful outcome of the procedure. In case the information received in the initiating message was insufficient to determine a value for all IEs that are required to be present in the message used to report the unsuccessful outcome of the procedure, the receiving node shall instead terminate the procedure and initiate the Error Indication procedure.
- If a message *initiating* a procedure that does not have a message to report unsuccessful outcome is received containing one or more IEs/IE groups marked with "*Reject IE*" which the receiving node does not comprehend, the receiving node shall terminate the procedure and initiate the Error Indication procedure.
- If a *response* message is received containing one or more IEs/IE groups marked with "*Reject IE*, that the receiving node does not comprehend, the receiving node shall consider the procedure as unsuccessfully terminated and initiate local error handling.

Ignore IE and Notify Sender:

- If a message *initiating* a procedure is received containing one or more IEs/IE groups marked with "*Ignore IE and Notify Sender*" which the receiving node does not comprehend, the receiving node shall ignore the content of the not comprehended IEs/IE groups, continue with the procedure as if the not comprehended IEs/IE groups were not received (except for the reporting) using the understood IEs/IE groups, and report in the response message of the procedure that one or more IEs/IE groups have been ignored. In case the information received in the initiating message was insufficient to determine a value for all IEs that are required to be present in the response message, the receiving node shall instead terminate the procedure and initiate the Error Indication procedure.
- If a message *initiating* a procedure that does not have a message to report the outcome of the procedure is received containing one or more IEs/IE groups marked with "*Ignore IE and Notify Sender*" which the receiving node does not comprehend, the receiving node shall ignore the content of the not comprehended IEs/IE groups, continue with the procedure as if the not comprehended IEs/IE groups were not received (except for the reporting) using the understood IEs/IE groups, and initiate the Error Indication procedure to report that one or more IEs/IE groups have been ignored.
- If a response message is received containing one or more IEs/IE groups marked with "Ignore IE and Notify Sender" which the receiving node does not comprehend, the receiving node shall ignore the content of the not comprehended IEs/IE groups, continue with the procedure as if the not comprehended IEs/IE groups were not received (except for the reporting) using the understood IEs/IE groups and initiate the Error Indication procedure.

Ignore IE:

- If a message initiating a procedure is received containing one or more IEs/IE groups marked with "Ignore IE" which the receiving node does not comprehend, the receiving node shall ignore the content of the not comprehended IEs/IE groups and continue with the procedure as if the not comprehended IEs/IE groups were not received using the understood IEs/IE groups.
- If a *response* message is received containing one or more IEs/IE groups marked with "*Ignore IE*" which the receiving node does not comprehend, the receiving node shall ignore the content of the not comprehended IEs/IE groups and continue with the procedure as if the not comprehended IEs/IE groups were not received using the understood IEs/IE groups.

When reporting not comprehended IEs/IE groups marked with "Reject IE" or "Ignore IE and Notify Sender" using a response message defined for the procedure, the Information Element Criticality Diagnostics IE shall be included in the Criticality Diagnostics IE for each reported IE/IE group. In the Information Element Criticality Diagnostics IE the Repetition Number IE shall be included and in addition, if the not comprehended IE/IE group is not at message hierarchy level 1 (top level; see annex C) also the Message Structure IE shall be included.

When reporting not comprehended IEs/IE groups marked with "Reject IE" or "Ignore IE and Notify Sender" using the Error Indication procedure, the Procedure ID IE, the Triggering Message IE, Procedure Criticality IE, the Transaction ID IE, and the Information Element Criticality Diagnostics IE shall be included in the Criticality Diagnostics IE for each reported IE/IE group. In the Information Element Criticality Diagnostics IE the Repetition Number IE shall be included and in addition, if the not comprehended IE/IE group is not at message hierarchy level 1 (top level; see annex C) also the Message Structure IE shall be included.

10.3.5 Missing IE or IE Group

The receiving node shall treat the missing IE/IE group according to the criticality information for the missing IE/IE group in the received message specified in the version of this specification used by the receiver:

Reject IE:

- If a received message *initiating* a procedure is missing one or more IEs/IE groups with specified criticality "*Reject IE*"; none of the functional requests of the message shall be executed. The receiving node shall reject the procedure and report the missing IEs/IE groups using the message normally used to report unsuccessful outcome of the procedure. In case the information received in the initiating message was insufficient to determine a value for all IEs that are required to be present in the message used to report the unsuccessful outcome of the procedure, the receiving node shall instead terminate the procedure and initiate the Error Indication procedure.
- If a received message *initiating* a procedure that does not have a message to report unsuccessful outcome is missing one or more IEs/IE groups with specified criticality "*Reject IE*", the receiving node shall terminate the procedure and initiate the Error Indication procedure.
- If a received *response* message is missing one or more IEs/IE groups with specified criticality "*Reject IE*, the receiving node shall consider the procedure as unsuccessfully terminated and initiate local error handling.

Ignore IE and Notify Sender:

- If a received message *initiating* a procedure is missing one or more IEs/IE groups with specified criticality "Ignore IE and Notify Sender", the receiving node shall ignore that those IEs are missing and continue with the procedure based on the other IEs/IE groups present in the message and report in the response message of the procedure that one or more IEs/IE groups were missing. In case the information received in the initiating message was insufficient to determine a value for all IEs that are required to be present in the response message, the receiving node shall instead terminate the procedure and initiate the Error Indication procedure.
- If a received message *initiating* a procedure that does not have a message to report the outcome of the procedure is missing one or more IEs/IE groups with specified criticality "*Ignore IE and Notify Sender*", the receiving node shall ignore that those IEs are missing and continue with the procedure based on the other IEs/IE groups present in the message and initiate the Error Indication procedure to report that one or more IEs/IE groups were missing.
- If a received *response* message is missing one or more IEs/IE groups with specified criticality "*Ignore IE and Notify Sender*", the receiving node shall ignore that those IEs are missing and continue with the procedure based on the other IEs/IE groups present in the message and initiate the Error Indication procedure to report that one or more IEs/IE groups were missing.

Ignore IE:

- If a received message *initiating* a procedure is missing one or more IEs/IE groups with specified criticality "*Ignore IE*", the receiving node shall ignore that those IEs are missing and continue with the procedure based on the other IEs/IE groups present in the message.
- If a received *response* message is missing one or more IEs/IE groups with specified criticality "*Ignore IE*", the receiving node shall ignore that those IEs/IE groups are missing and continue with the procedure based on the other IEs/IE groups present in the message.

When reporting missing IEs/IE groups with specified criticality "Reject IE" or "Ignore IE and Notify Sender" using a response message defined for the procedure, the Information Element Criticality Diagnostics IE shall be included in the Criticality Diagnostics IE for each reported IE/IE group. In the Information Element Criticality Diagnostics IE the Repetition Number IE shall be included and in addition, if the missing IE/IE group is not at message hierarchy level 1 (top level; see annex C) also the Message Structure IE shall be included.

When reporting missing IEs/IE groups with specified criticality "Reject IE" or "Ignore IE and Notify Sender" using the Error Indication procedure, the Procedure ID IE, the Triggering Message IE, Procedure Criticality IE, the Transaction ID IE, and the Information Element Criticality Diagnostics IE shall be included in the Criticality Diagnostics IE for each reported IE/IE group. In the Information Element Criticality Diagnostics IE the Repetition Number IE shall be included and in addition, if the missing IE/IE group is not at message hierarchy level 1 (top level; see annex C) also the Message Structure IE shall be included.

10.3.6 IEs or IE Groups Received in Wrong Order or With Too Many Occurrences or Erroneously Present

If a message with IEs or IE groups in wrong order or with too many occurrences is received or if IEs or IE groups with a conditional presence are present when the condition is not met (i.e. erroneously present), the receiving node shall behave according to the following:

- If a message *initiating* a procedure is received containing IEs or IE groups in wrong order or with too many occurrences or erroneously present, none of the functional requests of the message shall be executed. The receiving node shall reject the procedure and report the cause value "Abstract Syntax Error (Falsely Constructed Message)" using the message normally used to report unsuccessful outcome of the procedure. In case the information received in the initiating message was insufficient to determine a value for all IEs that are required to be present in the message used to report the unsuccessful outcome of the procedure, the receiving node shall instead terminate the procedure and initiate the Error Indication procedure.
- If a message *initiating* a procedure that does not have a message to report unsuccessful outcome is received containing IEs or IE groups in wrong order or with too many occurrences or erroneously present, the receiving node shall terminate the procedure and initiate the Error Indication procedure, and use cause value "Abstract Syntax Error (Falsely Constructed Message)".
- If a *response* message is received containing IEs or IE groups in wrong order or with too many occurrences or erroneously present, the receiving node consider the procedure as unsuccessfully terminated and initiate local error handling.

When determining the correct order only the IEs specified in the specification version used by the receiver shall be considered.

10.4 Logical Error

Logical error situations occur when a message is comprehended correctly, but the information contained within the message is not valid (i.e. semantic error), or describes a procedure which is not compatible with the state of the receiver. In these conditions, the following behaviour shall be performed (unless otherwise specified) as defined by the class of the elementary procedure, irrespective of the criticality information of the IEs/IE groups containing the erroneous values.

Class 1:

Where the logical error occurs in a request message of a class 1 procedure, and the procedure has a message to report this unsuccessful outcome, this message shall be sent with an appropriate cause value. Typical cause values are:

Protocol Causes:

- 1. Semantic Error;
- 2. Message not Compatible with Receiver State.

Where the logical error is contained in a request message of a class 1 procedure, and the procedure does not have a message to report this unsuccessful outcome, the procedure shall be terminated and the Error Indication procedure shall be initiated with an appropriate cause value. The *Procedure ID* IE, the *Triggering Message* IE and the *Transaction ID* IE within the *Criticality Diagnostics* IE shall then be included in order to identify the message containing the logical error

Where the logical error exists in a response message of a class 1 procedure, the procedure shall be considered as unsuccessfully terminated and local error handling shall be initiated.

Class 2:

Where the logical error occurs in a message of a class 2 procedure, the procedure shall be terminated and the Error Indication procedure shall be initiated with an appropriate cause value. The *Procedure ID* IE, the *Triggering Message* IE and the *Transaction ID* IE within the *Criticality Diagnostics* IE shall then be included in order to identify the message containing the logical error.

10.5 Exceptions

The error handling for all the cases described hereafter shall take precedence over any other error handling described in the other subclauses of clause 10.

- If any type of error (Transfer Syntax Error, Abstract Syntax Error or Logical Error) is detected in the ERROR INDICATION message, it shall not trigger the Error Indication procedure in the receiving Node but local error handling.
- In case a response message or ERROR INDICATION message needs to be returned, but the information necessary to determine the receiver of that message is missing, the procedure shall be considered as unsuccessfully terminated and local error handling shall be initiated.

If an error that terminates a procedure occurs, the returned cause value shall reflect the error that caused the termination of the procedure even if one or more abstract syntax errors with criticality "ignore and notify" have earlier occurred within the same procedure.

Annex A (normative): Allocation and Pre-emption of Radio Links in the DRNS

A.1 Deriving Allocation Information for a Radio Link

A.1.1 Establishment of a New Radio Link

The Allocation Information for a Radio Link in the case of establishment of a new Radio Link shall be derived as follows:

- The latest received Allocation/Retention Priority IE for each transport channel shall be used.

Note: The *Allocation/Retention Priority* IE for a transport channel may have been received in a) the procedure that establishes the first Radio Link for the UE in the DRNS or

b) a procedure adding or modifying the transport channel.

- If the *Priority Level* IE in the *Allocation/Retention Priority* IE for all transport channels that are intended to use the Radio Link is set to "no priority", the pre-emption capability of the Radio Link shall be set to "shall not trigger pre-emption".
- If the *Priority Level* IE in the *Allocation/Retention Priority* IE for one or more of the transport channels that are intended to use the Radio Link is not set to "no priority", the allocation priority and the pre-emption capability of the Radio Link shall be set according to the following:
 - The transport channels that have the *Priority Level* IE in the *Allocation/Retention Priority* IE set to "no priority" shall be excluded when setting the allocation priority and pre-emption capability of a Radio Link.
 - The allocation priority for a Radio Link shall be set to highest priority level, given by the *Priority Level* IE in the *Allocation/Retention Priority* IE, for all non excluded transport channels that are intended to use the Radio Link.
 - If all non-excluded transport channels that are intended to use a Radio Link to be established have the preemption capability, given by the *Pre-emption Capability* IE in the *Allocation/Retention Priority* IE, set to "shall not trigger pre-emption", the pre-emption capability of the Radio Link shall be set to "shall not trigger pre-emption".

If one or more non-excluded transport channels that are intended to use the Radio Link to be established have the value of the *Pre-emption Capability* IE in the *Allocation/Retention Priority* IE set to "may trigger pre-emption", the pre-emption capability of the Radio Link shall be set to "may trigger pre-emption".

The derived allocation priority and pre-emption capability are only valid during this allocation/retention process.

A.1.2 Modification of an Existing Radio Link

The Allocation Information for a Radio Link in the case of modification of a Radio Link (addition or modification of transport channels using the Radio Link) shall be derived as follows:

- The latest received Allocation/Retention Priority IE for each transport channel shall be used.

Note: The Allocation/Retention Priority IE for a transport channel may have been received in

- a) the procedure that establishes the first Radio Link for the UE in the DRNS,
- b) a previous procedure adding or modifying the transport channel, or
- c) the current procedure adding or modifying the transport channel.
- If the *Priority Level* IE in the *Allocation/Retention Priority* IE for all transport channels to be added or modified in the Radio Link is set to "no priority", the pre-emption capability of the Radio Link to be modified shall be set to "shall not trigger pre-emption".

- If the *Priority Level* IE in the *Allocation/Retention Priority* IE for one or more of the transport channels to be added or modified in the Radio Link is not set to "no priority", the allocation priority of and the pre-emption capability of the Radio Link to be modified shall be set according to the following:
 - The transport channels to be added or modified that have the *Priority Level* IE in the *Allocation/Retention Priority* IE set to "no priority" shall be excluded when setting the allocation priority and pre-emption capability of a Radio Link to be modified.
 - The allocation priority for a Radio Link to be modified shall be set to highest priority level, given by the *Priority Level* IE in the *Allocation/Retention Priority* IE, for all the non-excluded transport channels that are to be added or modified.
 - If all non-excluded transport channels that are to be added or modified in the Radio Link have the preemption capability, given by the *Pre-emption Capability* IE in the *Allocation/Retention Priority* IE, set to "shall not trigger pre-emption", the pre-emption capability of the Radio Link to be modified shall be set to "shall not trigger pre-emption".
 - If one or more of the non-excluded transport channels to be added or modified in the Radio Link have the value of the *Pre-emption Capability* IE in the *Allocation/Retention Priority* IE set to "may trigger pre-emption", the pre-emption capability of the Radio Link to be modified shall be set to "may trigger pre-emption".

The derived allocation priority and pre-emption capability are only valid during this allocation/retention process.

A.2 Deriving Retention Information for a Radio Link

The Retention Information for an existing Radio Link shall be derived as follows:

- The latest received Allocation/Retention Priority IE for each transport channel shall be used.

Note: The *Allocation/Retention Priority* IE for a transport channel may have been received in a) the procedure that establishes the first Radio Link for the UE in the DRNS or b) a procedure adding or modifying the transport channel.

- If the *Priority Level* IE in the *Allocation/Retention Priority* IE for one or more transport channels using the Radio Link is set to "no priority", the pre-emption vulnerability of the Radio Link shall be set to "not pre-emptable".
- If the *Priority Level* IE in the *Allocation/Retention Priority* IE for all the transport channels using the Radio Link is not set to "no priority", the retention priority of the Radio Link and the pre-emption vulnerability of the Radio Link shall be set according to the following:
 - The retention priority for a Radio Link shall be set to highest priority level, given by the *Priority Level* IE in the *Allocation/Retention Priority* IE, for all transport channels that uses the Radio Link.
 - If all transport channels that uses the Radio Link have the pre-emption vulnerability, given by the *Pre-emption Vulnerability* IE in the *Allocation/Retention Priority* IE, set to "pre-emptable", the pre-emption vulnerability of the Radio Link shall be set to "pre-emptable".
 If one or more transport channels that uses the Radio Link have the value of the *Pre-emption Vulnerability* IE in the *Allocation/Retention Priority* IE set to "not pre-emptable", the pre-emption vulnerability of the Radio Link shall be set to "not pre-emptable".

The derived retention priority and pre-emption vulnerability are valid until they are changed, or until the Radio Link is deleted. When new transport channels are added to or deleted from the Radio Link or when existing transport channels are modified with regards to the *Allocation/Retention Priority* IE, the retention information shall be derived again according to above.

A.3 The Allocation/Retention Process

The DRNS shall establish or modify the resources for a Radio Link according to:

- The value of the Allocation Information (allocation priority and pre-emption capability) of the Radio to be established or modified. The Allocation Information is derived according to clause A.1.
- The value of the Retention Information (retention priority and pre-emption vulnerability) of existing Radio Links. The Retention Information derived according to clause A.2.
- The resource situation in the DRNS.

Whilst the process and the extent of the pre-emption functionality is operator dependent, the pre-emption indicators (pre-emption capability and pre-emption vulnerability) shall be treated as follows:

- -. If the pre-emption capability for a Radio Link to be established or modified is set to "may trigger preemption" and the resource situation so requires, the DRNS may trigger the pre-emption process in clause A.4 to free resources for this allocation request.
- -. If the pre-emption capability for a Radio Link to be established or modified is set to "shall not trigger pre-emption", then this allocation request shall not trigger the pre-emption process in clause A.4.
- -. If the pre-emption vulnerability for an existing Radio Link is set to "pre-emptable", then this Radio Link shall be included in the pre-emption process in clause A.4.
- -. If the pre-emption vulnerability for an existing Radio Link is set to "not pre-emptable", then this Radio Link shall not be included in the pre-emption process in clause A.4.

A.4 The Pre-emption Process

The pre-emption process shall only pre-empt Radio Links with lower retention priority than the allocation priority of the Radio Link to be established or modified. The Radio Links to be pre-empted shall be selected in ascending order of the retention priority.

When the pre-emption process detects that one or more Radio Links have to be pre-empted to free resources for a Radio Link(s) to be established or modified, the DRNS shall initiate the Radio Link Pre-emption procedure for all the UE Contexts having Radio Links selected for pre-emption and start the T_{Preempt} timer.

When enough resources are freed to establish or modify the Radio Link(s) according to the request, the DRNS shall stop the $T_{Preempt}$ timer and complete the procedure that triggered the pre-emption process in accordance with the "Successful Operation" subclause of the procedure.

If the $T_{Preempt}$ timer expires, the DRNS shall reject the procedure that triggered the pre-emption process and complete the procedure in accordance with the "Unsuccessful Operation" subclause of the procedure.

Annex B (informative): Measurement Reporting

When the *Report Characteristics* IE is set to "Event A" (figure B.1), the Measurement Reporting procedure is initiated when the measured entity rises above the requested threshold and stays there for the requested hysteresis time. If no hysteresis time is given, the value zero shall be used for the hysteresis time.




Figure B.1: Event A reporting with Hysteresis Time specified

When the *Report Characteristics* IE is set to "Event B" (figure B.2), the Measurement Reporting procedure is initiated when the measured entity falls below the requested threshold and stays there for the requested hysteresis time. If no hysteresis time is given, the value zero shall be used for the hysteresis time.




Figure B.2: Event B reporting with Hysteresis Time specified

When the *Report Characteristics* IE is set to "Event C" (figure B.3), the Measurement Reporting procedure is initiated always when the measured entity rises by an amount greater than the requested threshold within the requested time. The reporting in figure B.3 is initiated if the Rising Time T1 is less than the requested time.




Figure B.3: Event C reporting

When the *Report Characteristics* IE is set to "Event D" (figure B.4), the Measurement Reporting procedure is initiated always when the measured entity falls by an amount greater than the requested threshold within the requested time. The reporting in figure B.4 is initiated if the Falling Time T1 is less than the requested time.




Figure B.4: Event D reporting

When the *Report Characteristics* IE is set to "Event E" (figure B.5), the Measurement Reporting procedure (Report A) is initiated always when the measured entity rises above the "Measurement Threshold 1" and stays there for the "Measurement Hysteresis Time" (T1 in figure B.5). If *Report Periodicity* IE is provided DRNS shall also initiate Measurement Reporting procedure periodically. The periodic reporting continues although the measured entity falls below the "Measurement Threshold 1" and is terminated by the Report B.

When the Report A conditions have been met and the measured entity falls below the "Measurement Threshold 2" and stays there for the "Measurement Hysteresis Time" (T1) the Measurement Reporting procedure (Report B) is initiated and the periodic reporting is terminated.





Figure B.5: Event E reporting with Hysteresis Time specified and Periodic Reporting requested

When the *Report Characteristics* IE is set to "Event F" (figure B.6), the Measurement Reporting procedure (Report A) is initiated always when the measured entity falls below the "Measurement Threshold 1" and stays there for the "Measurement Hysteresis Time" (T1 in figure B.6). If *Report Periodicity* IE is provided DRNS shall also initiate Measurement Reporting procedure periodically. The periodic reporting continues although the measured entity rises above the "Measurement Threshold 1" and is terminated by the Report B.

When the Report A conditions have been met and the measured entity rises above the "Measurement Threshold 2" and stays there for the "Measurement Hysteresis Time" (T1) Measurement Reporting procedure (Report B) is initiated and the periodic reporting is terminated.



Measurement Reports

Figure B.6: Event F reporting with Hysteresis Time specified and Periodic Reporting requested

When the *Report Characteristics* IE is set to "Event H" (figure B.7), the Measurement Reporting procedure (Report A) is initiated when the measurement value of measured entity rises above the *Measurement Threshold 1* and stays above the threshold for the *Measurement Hysteresis Time* (T_1 in figure B.7).] The measurement value of measured entity in Report A substitutes the *Measurement Base value* for the consequent measurement reporting.

When the Report A conditions has been met and the measurement value of measured entity rises above or falls below the *Measurement Base Value* by *Measurement Fluctuation Range* (H₁ in figure B.7), and stays there for the *Measurement Hysteresis Time* (T_h in figure B.7) counting from the beginning of every *Report Periodicity*, the Measurement Reporting procedure (Report B or Report C) is initiated. The the measurement value of measured entity in (Report B or Report C) substitutes the *Measurement Base value* for the consequent measurement reporting.

When the Report A conditions have been met and the measurement value of measured entity falls below the *Measurement Threshold 2* and stays there for the *Measurement Hysteresis Time* (T_h in figure B.7), the Measurement Reporting procedure (Report D) is initiated and the reporting is terminated.




Figure B.7: Event H reporting with Hysteresis Time specified and Periodic Reporting requested

Annex C (informative): Guidelines for Usage of the Criticality Diagnostics IE

C.1 EXAMPLE MESSAGE Layout

Assume the following message format:

IE/Group Name	Presence	Range	IE Type	Semantics	Criticality	Assigned
			and	Description		Criticality
			Referenc			
			е			
Message Type	M				YES	reject
Transaction ID	M				_	
Α	M				YES	reject
В	M				YES	reject
>E		1 <maxe></maxe>			EACH	ignore
>>F		1 <maxf></maxf>			-	
>>>G		03,			EACH	ignore
>>H		1 <maxh></maxh>			EACH	ignore
>>>G		03,			EACH	ignore and notify
>>G	M				YES	reject
>>J		1 <maxj></maxj>			-	
>>>G		03,			EACH	reject
С	M				YES	reject
>K		1 <maxk></maxk>			EACH	ignore and notify
>>L		1 <maxl></maxl>			-	
>>>M	0				-	
D	M				YES	reject

Note 1. The IEs F, J, and L do not have assigned criticality. The IEs F, J, and L are consequently realised as the ASN.1 type SEQUENCE OF of "ordinary" ASN.1 type, e.g. INTEGER. On the other hand, the repeatable IEs with assigned criticality are realised as the ASN.1 type SEQUENCE OF of an IE object, e.g. ProtocolIE-Single-Container.

For the corresponding ASN.1 layout, see subclause C.4.

C.2 Example on a Received EXAMPLE MESSAGE

Assume further more that a received message based on the above tabular format is according to the figure below.





Figure C.1: Example of content of a received RNSAP message based on the EXAMPLE MESSAGE

C.3 Content of Criticality Diagnostics

C.3.1 Example 1



- a) IE ID IE
- b) Repetition Number IE


Figure C.2: Example of a received RNSAP message containing a not comprehended IE

If there is an error within the instance marked as grey in the IE G in the IE J shown in the figure C.2 above, this will be reported within the *Information Element Criticality Diagnostics* IE within the *Criticality Diagnostics* IE as follows:

IE name	Value	Comment
IE Criticality	reject	Criticality for IE on the reported level, i.e. level 4.
IE ID	id-G	IE ID from the reported level, i.e. level 4.
Repetition Number	11	Repetition number on the reported level, i.e. level 4. (Since the IE E (level 2) is the lowest level included in the <i>Message Structure</i> IE this is the eleventh occurrence of IE G within the IE E (level 2).
Type of Error	not underst ood	
Message Structur	e, first rep	etition
>IE ID	id-B	IE ID from level 1.
Message Structur	e, second	repetition
>IE ID	id-E	IE ID from the lowest level above the reported level, i.e. level 2.
>Repetition Number	3	Repetition number from the lowest level above the reported level, i.e. level 2.

- Note 2. The IE J on level 3 cannot be included in the *Message Structure* IE since they have no criticality of their own.
- Note 3. The repetition number of the reported IE indicates the number of repetitions of IE G received up to the detected erroneous repetition, counting all occurrences of the IE G below the same instance of the previous level with assigned criticality (instance 3 of IE E on level 2).

C.3.2 Example 2



- a) IE ID IE
- b) Repetition Number IE


Figure C.3: Example of a received RNSAP message containing a not comprehended IE

If there is an error within the second instance (marked as grey) in the sequence (IE L in the tabular format) on level 3 below IE K in the structure shown in the figure C.3 above, this will be reported within the *Information Element Criticality Diagnostics* IE within the *Criticality Diagnostics* IE as follows:

IE name	Value	Comment
IE Criticality	ignore	Criticality for IE on the reported level, i.e. level 2.
	and	
	notify	
IE ID	id-K	IE ID from the reported level, i.e. level 2.
Repetition	3	Repetition number on the reported level, i.e. level 2.
Number		
Type of Error	not	
	underst	
	ood	
Message Structur	re, <i>first rep</i> e	etition
>IE ID	id-C	IE ID from the lowest level above the reported level, i.e. level 1.

Note 4. The IE L on level 3 cannot be reported individually included in the *Message Structure* IE since it has no criticality of its own.

C.3.3 Example 3



Included in the Information Element Criticality Diagnostics IE:

- a) IE ID IE
- b) Repetition Number IE


Figure C.4: Example of a received RNSAP message containing a not comprehended IE

If there is an error within the instance marked as grey in the IE G in the IE H shown in the figure C.4 above, this will be reported within the *Information Element Criticality Diagnostics* IE within the *Criticality Diagnostics* IE as follows:

IE name	Value	Comment
IE Criticality	ignore	Criticality for IE on the reported level, i.e. level 4.
	and	
	notify	
IE ID	id-G	IE ID from the reported level, i.e. level 4.
Repetition	2	Repetition number on the reported level, i.e. level 4.
Number		
Type of Error	not	
	underst	
	ood	
Message Structur	e, first repe	etition
>IE ID	id-B	IE ID from level 1.
Message Structur	e, second	repetition
>IE ID	id-E	IE ID from level 2.
>Repetition	3	Repetition number from level 2.
Number		
Message Structur	e, third rep	petition
>IE ID	id-H	IE ID from the lowest level above the reported level, i.e. level 3.
>Repetition	1	Repetition number from the lowest level above the reported level, i.e. level 3.
Number		

Note 5. The repetition number of level 4 indicates the number of repetitions of IE G received up to the detected erroneous repetition, counted below the same instance of the previous level with assigned criticality (instance 1 of IE H on level 3).

C.3.4 Example 4



Included in the Information Element Criticality Diagnostics IE:

- a) IE ID IE
- b) Repetition Number IE


Figure C.5: Example of a received RNSAP message containing a not comprehended IE

If there is an error within the instance marked as grey in the IE G in the IE E shown in the figure C.5 above, this will be reported within the *Information Element Criticality Diagnostics* IE within the *Criticality Diagnostics* IE as follows:

IE name	Value	Comment
IE Criticality	reject	Criticality for IE on the reported level, i.e. level 3.
IE ID	id-G	IE ID from the reported level, i.e. level 3.
Repetition Number	5	Repetition number on the reported level, i.e. level 3. (Since the IE E (level 2) is the lowest level included in the <i>Message Structure</i> IE this is the fifth occurrence of IE G within the IE E (level 2).
Type of Error	not underst ood	
Message Structur	e, first rep	etition
>IE ID	id-B	IE ID from level 1.
Message Structur	e, second	repetition
>IE ID	id-E	IE ID from the lowest level above the reported level, i.e. level 2.
>Repetition Number	3	Repetition number from the lowest level above the reported level, i.e. level 2.

Note 6. The repetition number of the reported IE indicates the number of repetitions of IE G received up to the detected erroneous repetition, counting all occurrences of the IE G below the same instance of the previous level with assigned criticality (instance 3 of IE E on level 2).

C.3.5 Example 5



Included in the Information Element Criticality Diagnostics IE:

- a) IE ID IE
- b) Repetition Number IE

Figure C.6: Example of a received RNSAP message with a missing IE

If the instance marked as grey in the IE G in the IE E shown in the figure C.6 above, is missing this will be reported within the *Information Element Criticality Diagnostics* IE within the *Criticality Diagnostics* IE as follows:

IE name	Value	Comment
IE Criticality	reject	Criticality for IE on the reported level, i.e. level 3.
IE ID	id-G	IE ID from the reported level, i.e. level 3.
Repetition	4	Repetition number up to the missing IE on the reported level, i.e. level 3.
Number		(Since the IE E (level 2) is the lowest level included in the Message Structure IE there
		have been four occurrences of IE G within the IE E (level 2) up to the missing
		occurrence.
Type of Error	missing	
Message Structur	e, first repe	etition
>IE ID	id-B	IE ID from level 1.
Message Structur	e, second	repetition
>IE ID	id-E	IE ID from the lowest level above the reported level, i.e. level 2.
>Repetition	3	Repetition number from the lowest level above the reported level, i.e. level 2.
Number		

Note 7. The repetition number of the reported IE indicates the number of repetitions of IE G received up to but not including the missing occurrence, counting all occurrences of the IE G below the same instance of the previous level with assigned criticality (instance 3 of IE E on level 2).

C.4 ASN.1 of EXAMPLE MESSAGE

```
{ ID id-A CRITICALITY reject TYPE A PRESENCE mandatory}
    { ID id-B CRITICALITY reject TYPE B PRESENCE mandatory} { ID id-C CRITICALITY reject TYPE C PRESENCE mandatory}
    }
B ::= SEQUENCE {
                  E-List,
   iE-Extensions ProtocolExtensionContainer { {B-ExtIEs} } OPTIONAL,
B-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
E-List ::= SEQUENCE (SIZE (1..maxE)) OF ProtocolIE-Single-Container { {E-IEs} }
E-Ies RNSAP-PROTOCOL-IES ::= {
   { ID id-E CRITICALITY ignore TYPE E PRESENCE mandatory }
E ::= SEQUENCE {
                  F-List,
   f
   h
                  H-List,
                  G-List1,
                  J-List,
   iE-Extensions ProtocolExtensionContainer { {E-ExtIEs} } OPTIONAL,
}
E-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
F-List ::= SEQUENCE (SIZE (1..maxF)) OF F
F ::= SEQUENCE {
                  G-List2 OPTIONAL,
   iE-Extensions ProtocolExtensionContainer { {F-ExtIEs} } OPTIONAL,
}
F-ExtIES RNSAP-PROTOCOL-EXTENSION ::= {
G-List2 ::= SEQUENCE (SIZE (1..3, ...)) OF ProtocolIE-Single-Container { G2-IEs} }
G2-IES RNSAP-PROTOCOL-IES ::= {
   H-List ::= SEQUENCE (SIZE (1..maxH)) OF ProtocolIE-Single-Container { {H-IEs} }
H-Ies RNSAP-PROTOCOL-IES ::= {
   { ID id-H CRITICALITY ignore TYPE H PRESENCE mandatory }
H ::= SEQUENCE {
                  G-List3 OPTIONAL,
                                ProtocolExtensionContainer { {H-ExtIEs} } OPTIONAL,
   iE-Extensions
}
H-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
G-List3 ::= SEQUENCE (SIZE (1..3, ...)) OF ProtocolIE-Single-Container { {G3-IEs} }
G3-IEs RNSAP-PROTOCOL-IES ::= {
   { ID id-G CRITICALITY notify TYPE G PRESENCE mandatory }
G-List1 ::= ProtocolIE-Single-Container { {G1-IEs} }
```

```
G1-IES RNSAP-PROTOCOL-IES ::= {
   { ID id-G CRITICALITY reject TYPE G PRESENCE mandatory }
J-List ::= SEQUENCE (SIZE (1..maxJ)) OF J
J ::= SEQUENCE {
                   G-List4 OPTIONAL,
    iE-Extensions ProtocolExtensionContainer { {J-ExtIEs} } OPTIONAL,
}
J-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
 \texttt{G-List4} ::= \texttt{SEQUENCE} \ (\texttt{SIZE} \ (1...3, \ \ldots)) \ \texttt{OF} \ \texttt{ProtocolIE-Single-Container} \ \left\{ \ \texttt{G4-IEs} \ \right\} \ 
G4-IES RNSAP-PROTOCOL-IES ::= {
   { ID id-G CRITICALITY reject TYPE G PRESENCE mandatory }
C ::= SEQUENCE {
                    K-List,
    iE-Extensions ProtocolExtensionContainer { {C-ExtIEs} } OPTIONAL,
C-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
K-List ::= SEQUENCE (SIZE (1..maxK)) OF ProtocolIE-Single-Container { K-IEs} }
K-IES RNSAP-PROTOCOL-IES ::= {
   { ID id-K CRITICALITY notify TYPE K PRESENCE mandatory }
K ::= SEQUENCE {
                    L-List,
    iE-Extensions ProtocolExtensionContainer { {K-ExtIEs} } OPTIONAL,
}
K-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
L-List ::= SEQUENCE (SIZE (1..maxL)) OF L
L ::= SEQUENCE {
                   M OPTIONAL,
    iE-Extensions ProtocolExtensionContainer { {L-ExtIEs} } OPTIONAL,
}
L-ExtIEs RNSAP-PROTOCOL-EXTENSION ::= {
{\tt ExampleMessage-Extensions~RNSAP-PROTOCOL-EXTENSION~::=~\{}
```

Annex D (normative): DRNS Behaviour at SRNC or RNSAP Signalling Bearer Failure

This annex describes the DRNC actions in the event of SRNC or RNSAP Signalling Bearer failure when all or some of the UE Contexts related to the SRNC need to be removed in DRNC.

D.1 Detection of SRNC or RNSAP Signalling Bearer/Connection Failure

Termination of all or some of the UE Contexts in DRNC which are related to an SRNC may be triggered due to failure of SRNC, RNSAP Signalling Bearer or the Iur signalling connection of an UE(s).

D.1.1 Termination of all UE Contexts Related to a Specific SRNC

Termination of all UE Contexts in DRNC which are related to a specific SRNC is triggered if the RNSAP Signalling Bearer failure is detected by the RNSAP according to the procedure described in the sub-clause 4.5.1.5.1 of TS 25.420. By "all" UE Contexts, it means all Ues having dedicated and/or common channel resources.

D.1.2 Termination of Specific UE Context

Termination of a specific UE Context in DRNC is triggered for an UE which has dedicated transport channel resources according to the procedure described in the sub-clause 4.5.1.5.2 of TS 25.420.

D.2 DRNC Actions at UE Context Termination

When termination of the UE Context is required, the DRNC shall remove any common and/or dedicated radio resources related to the UE Context. The DRNC shall also initiate release of the dedicated or common user plane resources that were involved in these UE contexts. In addition, if it is possible the DRNC shall release the RRC connection.

Annex E (informative): Change History

Release 9 version created based on v8.6.0 9.0.0	TSG #	TSG Doc.	CR	Rev	Subject/Comment	New
18		-	-	-		
18	45	RP-090777	1521	2		
SP-090773 1536 1 Introduction of Dual-Band HSDPA 9.0.0	45				l e e e e e e e e e e e e e e e e e e e	
RP-090773 1536 1	45			2		
46 RP-091188 1540 . Introduction of Cell Portion for 1.28 Mcps TDD 9.1.0 46 RP-091186 1542 . Activation and deactivation of secondary carrier in non serving Node B 9.1.0 9.1.0 46 RP-091186 1542 . Activation and deactivation of secondary carrier in non serving Node B 9.1.0 9.1.0 46 RP-091180 1551 . Correction of a benomal conditions for Dual cell IR-SDSCH in RL Addition procedure 9.1.0 46 RP-091181 1558 . Correction of a benomal conditions for Dual cell IR-SDSCH in RL Addition procedure 9.1.0 46 RP-091181 1558 . MAC-e Reset Indicator for MAC-I Reset 9.1.0 46 RP-091178 1563 . Macy Repetition of Tell SUBPA 9.1.0 46 RP-091179 1567 . Further Corrections for DC-HSDPA 9.1.0 46 RP-091178 1573 . STTD is cell specific in Dual-Cell HSDPA 9.1.0 46 RP-091178 1573 . Correction of Re9 HSPA Capability into RNSAP 9.1.0 47 RP-100215 1576 . Addition of HS-DSCH physical layer category over lur 9.2.0 47 RP-100219 1577 . Addition of HS-DSCH physical layer category over lur 9.2.0 47 RP-100219 1576 . Addition of HS-DSCH physical lay	45					1
RP-091186 154-1 Single Stream MIMO for DC-HSDPA 9.1.0				-		
RP-091186 1542 - Activation and deactivation of secondary carrier in non serving Node B				1		1
RP-091180 1561 Correction of abnormal conditions for Dual cell HS-DSCH in RL Addition procedure 9.1.0				_		
RP-091181 1558 Clarification of the meaning of BIT STRING type IES for SPS operation for 1.28Mcps 9.1.0				1		1
TDD						
46 RP-091181 1588 1 MAC-e Reset Indicator for MAC-I Reset 9.1.0 46 R-P091179 1563 1 Wrong ref in tabular 9.1.0 46 RP-091179 1563 1 Wrong ref in tabular 9.1.0 46 RP-091180 1583 1 Wrong ref in tabular 9.1.0 46 RP-091181 1573 1 STTD is cell spedific in Dual-Cell HSDPA 9.1.0 46 RP-091179 1573 1 Removal of MAC-she format indicator 9.1.0 46 RP-091179 1573 1 Removal of MAC-she format indicator 9.1.0 47 RP-100215 1576 1 Introduction of Red HSPA Capability into RNSAP 9.1.0 47 RP-100215 1576 1 Introduction of Red HSPA Capability into RNSAP 9.2.0 47 RP-100215 1576 1 Addition of HS-DSCH physical layer category over lur 9.2.0 47 RP-100215 1576 1 Addition of HS-DSCH physical layer category over lur 9.2.0 47 RP-100218 1581 1 Correction for the description of E-DCH serving radio link IE for E-DCH semi-persistent 9.2.0 47 RP-100218 1585 1 Correction for the description of E-DCH serving radio link	10	141 001100	1001			0.1.0
46 RP-091182 1560 Further Corrections for DC-HSDPA 9.1.0 46 RP-091179 1563 STTD is cell specific in Dual-Cell HSDPA 9.1.0 46 RP-091186 1585 STTD is cell specific in Dual-Cell HSDPA 9.1.0 46 RP-091187 1571 Removal of MAC-ehs format indicator 9.1.0 46 RP-091179 1573 Removal of MAC-ehs format indicator 9.1.0 46 RP-091186 1574 1 Introduction of Leaf LAGCH Table Choice* 9.1.0 46 RP-091186 1574 1 Introduction of Rea HSPA Capability into RNSAP 9.1.0 47 RP-100215 1576 Addition of HS-DSCH physical layer category over lur 9.2.0 47 RP-100219 1577 1 E-RNTI Allocation for UE moves to Cell -FACH from Cell LDCH 9.2.0 47 RP-100219 1587 Addition of DC-HSDPA Capability in lur under the company o	46	RP-091181	1558	1		9.1.0
RP-091179 1563 1	46			-		
46 RP-0911791 5677 STTD is cell specific in Dual-Cell HSDPA 9.1.0 46 RP-091186 1568 2 Introduction of Dual Cell E-DCH mode of operation 9.1.0 46 RP-091186 1571 1571 Removal of MAC-ehs format indicator 9.1.0 46 RP-091186 1573 1573 Correction on IE*E-AGCH Table Choice* 9.1.0 47 RP-100219 1575 1576 Addition of HS-DSCH physical layer category over fur 9.2.0 47 RP-100219 1577 1 E-RNTI Allocation for UE moves to Cell FACH from Cell_DCH 9.2.0 47 RP-100219 1579 T E-RNTI Allocation for UE moves to Cell FACH from Cell_DCH 9.2.0 47 RP-100219 1581 S Correction of DC-HSDPA Capability in lur 9.2.0 47 RP-100218 1584 Correction of DC-HSDPA Capability in lur 9.2.0 47 RP-100219 1587 S Correction of Multi-cell Capability Report in lur 9.2.0 47 RP-100221 1587 S Correction of Multi-cell Capability Report in lur 9.2.0 47 RP-100221 1587 S Correction of Multi-cell Capability Report in lur 9.2.0 47 RP-100221 1589 S Correction of Multi-cell Capability Re	46			1		1
46 RP-091186 1563 2 Introduction of Dual Cell E-DCH mode of operation 9.1.0 46 RP-091197 1571 7 Removal of MAC-ehs format indicator 9.1.0 46 RP-091196 1574 1 Correction on IE "E-AGCH Table Choice" 9.1.0 47 RP-100215 1576 Addition of HS-DSCH physical layer category over lur 9.2.0 47 RP-100215 1577 E-RNT1 Allocation for UE moves to Cell "FACH from Cell" DCH 9.2.0 47 RP-100215 1578 Allow reconfiguration of Some les in RL Addition procedure 9.2.0 47 RP-100215 1581 Correction of DCH-ISDPA Capability in lur 9.2.0 47 RP-100218 1584 Correction of DCH-ISDPA Capability in lur 9.2.0 47 RP-100215 1586 Correction of DCH-ISDPA Capability in lur 9.2.0 47 RP-100215 1586 Correction of DCH-ISDPA Capability Report in lur 9.2.0 47 RP-100215 1586 Correction of Mill-cell Capability Report in lur 9.2.0 47 RP-100221 1591 3 Correction of Mill-cell Capability Report in lur 9.2.0 47 RP-100230 1583 2 Rep-100230 1583 2 Rep-100240 1592 2 Rep-100230 1583 2 Rep-100230 1583 2	46			-		
46 RP-091187 1571 Removal of MAC-ehs format indicator 9.1.0 46 RP-091196 1574 Introduction of Reg HSPA Capability into RNSAP 9.1.0 46 RP-091196 1574 Introduction of Reg HSPA Capability into RNSAP 9.1.0 47 RP-100219 1577 I Addition of HS-DSCH physical layer category over lur 9.2.0 47 RP-100219 1577 Addition of HS-DSCH physical layer category over lur 9.2.0 47 RP-100219 1587 Allow reconfiguration of some les in RL Addition procedure 9.2.0 47 RP-100218 1584 Correction of DC-HSDPA Capability in lur 9.2.0 47 RP-100218 1584 Correction of DC-HSDPA Capability in lur 9.2.0 47 RP-100220 1587 Combining E-DCH Radio Links within the RLS 9.2.0 47 RP-100230 1588 2 Introduction of HS-PDSCH resources on TS0 for 1.28Mcps TDD 9.2.0 47 RP-100230 1589 2 Rel-10024 Rel-10024 Rel-10024 Rel-10024 Rel-100230 1593 <	46			2		
ABC RP-091178 1573 Correction on IE "E-AGCH Table Choice" 9.1.0				_		
RP-00215 1574 1 Introduction of Re9 HSPA Capability into RNSAP 9.1.0						1
47 RP-100215 1576 Addition of HS-DSCH physical layer category over lur 9.2.0 47 RP-100215 1579 IS-RNT Allocation for UE moves to Cell FACH from Cell_DCH 9.2.0 47 RP-100218 1581 Correction of DC-HSDPA Capability in lur 9.2.0 47 RP-100215 1586 Correction for the description of E-DCH serving radio link IE for E-DCH semi-persistent operation 9.2.0 47 RP-100215 1586 Correction for the description of E-DCH serving radio link IE for E-DCH semi-persistent operation 9.2.0 47 RP-100215 1586 Correction of Multi-cell Capability Report in lur 9.2.0 47 RP-100220 1587 1 Correction of Multi-cell Capability Report in lur 9.2.0 47 RP-100230 1588 2 Introduction of HS-DSCH resources on T30 for 1.28Mcps TDD 9.2.0 47 RP-100230 1593 3 Addition of DGNSS Validity Period in RNSAP 9.2.0 47 RP-100230 1593 3 Addition of DGNSS Validity Period in RNSAP 9.2.0 47 RP-100218 1596 5 Introduction of UE Aggregate Maximum Bit Rate Enforcement Indicator 9.2.0 47 RP-100218 1596 5 Syncronization detection window configurat				1		
RP-100219 1577 1	47			•		
RP-100215 1579 Allow reconfiguration of some les in RL Addition procedure 9.2.0	47			1		
RP-100219 1581 Correction of DC-HSDPA Capability in Iur 9.2.0	47			·		1
RP-100215 1586						1
Operation						
RP-100220 1587 Correction of Multi-cell Capability Report in Iur 9.2.0	41	100210	1304			3.2.0
RP-100220 1587 Correction of Multi-cell Capability Report in Iur RP-100230 1588 2	47	RP-100215	1586			920
RP-100230 1588 2				1		1
RP-100217 1591 3				2		
RP-100230 1592 Z Rel-9 Flexible cell combinations in DC-HSDPA 9.2.0						1
477 RP-100230 1593 1 Addition of DGNSS Validity Period in RNSAP 9.2.0 477 RP-100229 1594 1 Introduction of UE Aggregate Maximum Bit Rate Enforcement Indicator 9.2.0 477 RP-100230 1597 2 Measurement occasion configuration in CPC for 1.28 Mcps TDD 9.2.0 477 RP-100216 1601 Correction for Procedural Text on E-RNTI Allocation at E-DCH Serving Cell Change 9.2.0 477 RP-100199 1604 Indication of Precoding Weight Set Restriction preference 9.2.0 477 RP-100229 1605 Rapporteur's update of RNSAP protocol 9.2.0 477 RP-100221 1608 Remove Cell Specific HARQ memory partitioning for DC HSDPA+MIMO and additional corrections for HS-DSCH preconfiguration 9.2.0 04/2010 Corrected a typo in ASN.1 to make it pass the syntax checker 9.2.1 04/2010 ToC Updated 9.2.2 04/2010 ToC Updated 9.2.2 04/2010 ToC Updated 9.2.2 04/2010 ToC Updated 9.2.2 04/2010 ToC Updated 9.2.0						
RP-100229 1594 1						1
477 RP-100218 1596 1 Syncronization detection window configuration in CPC for 1.28 Mcps TDD 9.2.0 477 RP-100230 1597 2 Measurement occasion configuration in CELL_DCH for 1.28Mcps TDD 9.2.0 477 RP-100199 1604 Indication of Precedding Weight Set Restriction preference 9.2.0 477 RP-100229 1605 Rapporteur's update of RNSAP protocol 9.2.0 477 RP-100221 1608 Remove Cell Specific HARQ memory partitioning for DC HSDPA+MIMO and additional corrections for HS-DSCH preconfiguration 9.2.0 477 RP-100221 1608 Remove Cell Specific HARQ memory partitioning for DC HSDPA+MIMO and additional corrections for HS-DSCH preconfiguration 9.2.0 04/2010 Corrected at typo in ASN.1 to make it pass the syntax checker 9.2.1 04/2010 ToC updated 9.2.2 04/2010 Correction of procedure text that appears to be duplicated and mis-placed 9.3.0 48 RP-100593 1622 Correction when the power offset for S-CPICH for MIMO is zero 9.3.0 48 RP-100594 1629 Correction when the power offset for S-CPICH for MIMO is zero 9				-		1
477 RP-100230 1597 2 Measurement occasion configuration in CELL_DCH for 1.28Mcps TDD 9.2.0 477 RP-100216 1601 Correction for Procedural Text on E-RNTI Allocation at E-DCH Serving Cell Change 9.2.0 477 RP-100229 1605 Rapporteur's update of RNSAP protocol 9.2.0 477 RP-100224 1606 3 Corrections to DC HSUPA 9.2.0 477 RP-100221 1608 3 Corrections to DC HSUPA 9.2.0 477 RP-100221 1608 Remove Cell Specific HARQ memory partitioning for DC HSDPA+MIMO and additional corrections for HS-DSCH preconfiguration 9.2.0 04/2010 Corrected a typo in ASN.1 to make it pass the syntax checker 9.2.1 04/2010 ToC updated 9.2.2 04/2010 Corrected a typo in ASN.1 to make it pass the syntax checker 9.2.1 04/2010 Corrected a typo in ASN.1 to make it pass the syntax checker 9.2.1 04/2010 Corrected a typo in ASN.1 to make it pass the syntax checker 9.2.1 04/2010 Correction for Enables fixed 9.2.0 04/2010 Correction for Enables fixe				1		
477 RP-100216 1601 Correction for Procedural Text on E-RNTI Allocation at E-DCH Serving Cell Change 9.2.0 477 RP-100199 1604 Indication of Precoding Weight Set Restriction preference 9.2.0 477 RP-100229 1605 Rapporteur's update of RNSAP protocol 9.2.0 477 RP-100221 1608 Corrections to DC HSUPA 9.2.0 477 RP-100221 1608 Remove Cell Specific HARQ memory partitioning for DC HSDPA+MIMO and additional corrections for HS-DSCH preconfiguration 9.2.0 04/2010 Corrected a typo in ASN.1 to make it pass the syntax checker 9.2.1 04/2010 ToC updated 9.2.2 04/2010 Corrected a typo in ASN.1 to make it pass the syntax checker 9.2.3 48 RP-100592 1618 1 CPC parameters missing for serving HS-DSCH RL change in RL Addition procedure 9.3.0 48 RP-100593 1622 Correction of procedure text that appears to be duplicated and mis-placed 9.3.0 48 RP-100594 1625 2 CQI Feedback Cycle k for DC-HSDPA and MIMO operation 9.3.0 48 RP-100994 <				2		1
477 RP-100199 1604 Indication of Precoding Weight Set Restriction preference 9.2.0 477 RP-100229 1605 Rapporteur's update of RNSAP protocol 9.2.0 477 RP-100221 1606 3 Corrections to DC HSUPA 9.2.0 477 RP-100221 1608 Remove Cell Specific HARQ memory partitioning for DC HSDPA+MIMO and additional occrrections for HS-DSCH preconfiguration 9.2.0 04/2010 Corrected a typo in ASN.1 to make it pass the syntax checker 9.2.1 04/2010 Corrected a typo in ASN.1 to make it pass the syntax checker 9.2.2 04/2010 Correction of procedure text that appears to be duplicated and miscentary of the pass of the						
47 RP-100229 1605 Rapporteur's update of RNSAP protocol 9.2.0 47 RP-100221 1608 Corrections to DC HSUPA 9.2.0 47 RP-100221 1608 Remove Cell Specific HARQ memory partitioning for DC HSDPA+MIMO and additional corrections for HS-DSCH preconfiguration 9.2.0 04/2010 Corrected a typo in ASN.1 to make it pass the syntax checker 9.2.1 04/2010 ToC updated 9.2.2 04/2010 Corrupted headers fixed 9.2.3 48 RP-100592 1618 CPC parameters missing for serving HS-DSCH RL change in RL Addition procedure 9.3.0 9.3.0 48 RP-100593 1622 Correction of procedure text that appears to be duplicated and mis-placed 9.3.0 48 RP-100594 1625 Correction when the power offset for S-CPICH for MIMO is zero 9.3.0 48 RP-100594 1629 Correction for Enhanced Serving Cell Change 9.3.0 49 RP-100904 1631 Carrification of 64 QAM usage at intra Node B serving HS-DSCH RL change 9.4.0 49 RP-100904 1634 Correction of procedure text for E-DCH SPS operation 9.4.0 49 RP-100909 1634 Correction of Procedure text for E-DCH SPS operation 9.4.0 49 RP-100904 1637 Correction of Procedure t						
477 RP-100224 1606 3 Corrections to DC HSUPA 9.2.0 477 RP-100221 1608 Remove Cell Specific HARQ memory partitioning for DC HSDPA+MIMO and additional corrections for HS-DSCH preconfiguration 9.2.0 04/2010 Corrected a typo in ASN.1 to make it pass the syntax checker 9.2.1 04/2010 ToC updated 9.2.2 04/2010 Correction of procedure text for E-DCH RL change in RL Addition procedure 9.2.3 48 RP-100592 1618 1 CPC parameters missing for serving HS-DSCH RL change in RL Addition procedure 9.3.0 48 RP-100593 1622 Correction of procedure text that appears to be duplicated and mis-placed 9.3.0 48 RP-100594 1625 2 CQI Feedback Cycle k for DC-HSDPA and MIMO operation 9.3.0 48 RP-100591 1629 Correction when the power offset for S-CPICH for MIMO is zero 9.3.0 48 RP-10094 1631 Correction of Enhanced Serving Cell Change 9.4.0 49 RP-100904 1633 1 Clarification of 64 QAM usage at intra Node B serving HS-DSCH RL change 9.4.0 <						
RP-100221 1608 Remove Cell Specific HARQ memory partitioning for DC HSDPA+MIMO and additional corrections for HS-DSCH preconfiguration 9.2.0				2		
Corrections for HS-DSCH preconfiguration				3		-
04/2010 Corrected a typo in ASN.1 to make it pass the syntax checker 9.2.1 04/2010 ToC updated 9.2.2 04/2010 Corrupted headers fixed 9.2.2 04/2010 Corrupted headers fixed 9.2.3 48 RP-100592 1618 1 CPC parameters missing for serving HS-DSCH RL change in RL Addition procedure 9.3.0 48 RP-100593 1622 Correction of procedure text that appears to be duplicated and mis-placed 9.3.0 48 RP-100594 1625 2 CQI Feedback Cycle k for DC-HSDPA and MIMO operation 9.3.0 48 RP-100591 1629 Correction when the power offset for S-CPICH for MIMO is zero 9.3.0 48 RP-100545 1631 Correction for Enhanced Serving Cell Change 9.3.0 49 RP-100904 1633 1 Clarification of 64 QAM usage at intra Node B serving HS-DSCH RL change 9.4.0 49 RP-100909 1634 2 Corrections to HSDPA secondary serving cell list handling 9.4.0 49 RP-100904 1641 Addition of UE with enhanced HS-SCCH support indicator IE for Cell_FACH	47	KF-100221	1000			9.2.0
04/2010 ToC updated 9.2.2 04/2010 Corrupted headers fixed 9.2.3 48 RP-100592 1618 1 CPC parameters missing for serving HS-DSCH RL change in RL Addition procedure 9.3.0 48 RP-100593 1622 Correction of procedure text that appears to be duplicated and mis-placed 9.3.0 48 RP-100594 1625 2 CQI Feedback Cycle k for DC-HSDPA and MIMO operation 9.3.0 48 RP-100591 1629 Correction when the power offset for S-CPICH for MIMO is zero 9.3.0 48 RP-100945 1631 Correction for Enhanced Serving Cell Change 9.3.0 49 RP-100904 1633 1 Clarification of 64 QAM usage at intra Node B serving HS-DSCH RL change 9.4.0 49 RP-100905 1637 2 Corrections to HSDPA secondary serving cell list handling 9.4.0 49 RP-100905 1637 Correction of procedure text for E-DCH SPS operation 9.4.0 49 RP-100904 1641 Addition of UE with enhanced HS-SCCH support indicator IE for Cell_FACH 9.4.0 49 RP-10	04/2010				Corrected a type in ASN 1 to make it page the cyptox checker	0.2.1
04/2010 Corrupted headers fixed 9.2.3 48 RP-100592 1618 1 CPC parameters missing for serving HS-DSCH RL change in RL Addition procedure 9.3.0 48 RP-100593 1622 Correction of procedure text that appears to be duplicated and mis-placed 9.3.0 48 RP-100594 1625 2 CQI Feedback Cycle k for DC-HSDPA and MIMO operation 9.3.0 48 RP-100591 1629 Correction when the power offset for S-CPICH for MIMO is zero 9.3.0 48 RP-100545 1631 Correction for Enhanced Serving Cell Change 9.3.0 49 RP-100904 1633 1 Clarification of 64 QAM usage at intra Node B serving HS-DSCH RL change 9.4.0 49 RP-100909 1634 2 Corrections to HSDPA secondary serving cell list handling 9.4.0 49 RP-100905 1637 Correction of procedure text for E-DCH SPS operation 9.4.0 49 RP-100901 1641 Addition of UE with enhanced HS-SCCH support indicator IE for Cell_FACH 9.4.0 49 RP-100911 1635 2 Introduction of AC-HSDPA						1
48 RP-100592 1618 1 CPC parameters missing for serving HS-DSCH RL change in RL Addition procedure 9.3.0 48 RP-100593 1622 Correction of procedure text that appears to be duplicated and mis-placed 9.3.0 48 RP-100594 1625 2 CQI Feedback Cycle k for DC-HSDPA and MIMO operation 9.3.0 48 RP-100594 1629 Correction when the power offset for S-CPICH for MIMO is zero 9.3.0 48 RP-100545 1631 Correction for Enhanced Serving Cell Change 9.3.0 49 RP-100904 1633 1 Clarification of 64 QAM usage at intra Node B serving HS-DSCH RL change 9.4.0 49 RP-100905 1637 Corrections to HSDPA secondary serving cell list handling 9.4.0 49 RP-100904 1641 Addition of UE with enhanced HS-SCCH support indicator IE for Cell_FACH 9.4.0 09/2010 - - Release 10 version created based on v9.4.0 10.0.0 49 RP-100911 1635 2 Introduction of 4C-HSDPA 10.0.0 49 RP-1010911 1635 2 I						
RP-100593 1622 Correction of procedure text that appears to be duplicated and mis-placed 9.3.0 RP-100594 1625 2 CQI Feedback Cycle k for DC-HSDPA and MIMO operation 9.3.0 RP-100591 1629 Correction when the power offset for S-CPICH for MIMO is zero 9.3.0 RP-100545 1631 Correction for Enhanced Serving Cell Change 9.3.0 RP-100904 1633 1 Clarification of 64 QAM usage at intra Node B serving HS-DSCH RL change 9.4.0 RP-100909 1634 2 Corrections to HSDPA secondary serving cell list handling 9.4.0 RP-100905 1637 Correction of procedure text for E-DCH SPS operation 9.4.0 RP-100904 1641 Addition of UE with enhanced HS-SCCH support indicator IE for Cell_FACH 9.4.0 RP-100901 1635 2 Introduction of 4C-HSDPA 10.0.0 RP-100910 1638 1 Small Technical Enhancements and Improvements for GNSS (RNSAP) 10.0.0 RP-101275 1642 Correction of AC-HSDPA secondary serving HS-DSCH RL change 10.1.0 RP-101276 1644 2 Introduction of MC-HSUPA to RNSAP 10.1.0 RP-101277 1644 2 Introduction of MU-MIMO to RNSAP 10.1.0 RP-101269 1647 Corrections to E-DCH MAC-d Flow Multiplexing for 1.28Mcps TDD 10.1.0 RP-101271 1652 1 Power Offset For S-CPICH for MIMO of secondary cell 10.1.0 RRP-101271 1652 1 Power Offset For S-CPICH for MIMO of secondary cell 10.1.0 MIMO		DD 100502	1610	1		1
48 RP-100594 1625 2 CQI Feedback Cycle k for DC-HSDPA and MIMO operation 9.3.0 48 RP-100591 1629 Correction when the power offset for S-CPICH for MIMO is zero 9.3.0 48 RP-100545 1631 Correction for Enhanced Serving Cell Change 9.3.0 49 RP-100904 1633 1 Clarification of 64 QAM usage at intra Node B serving HS-DSCH RL change 9.4.0 49 RP-100909 1634 2 Corrections to HSDPA secondary serving cell list handling 9.4.0 49 RP-100905 1637 Correction of procedure text for E-DCH SPS operation 9.4.0 49 RP-100904 1641 Addition of UE with enhanced HS-SCCH support indicator IE for Cell_FACH 9.4.0 49 RP-100910 1635 2 Introduction of evaluate dased on v9.4.0 10.0.0 49 RP-100911 1635 2 Introduction of 4C-HSDPA 10.0.0 49 RP-101275 1642 Correction of AC-HSDPA secondary serving HS-DSCH RL change 10.1.0 50 RP-101275 1642 Correction of NC-HSUPA to RNSAP				ı		1
RP-100591 1629 Correction when the power offset for S-CPICH for MIMO is zero 9.3.0 RP-100545 1631 Correction for Enhanced Serving Cell Change 9.3.0 RP-100904 1633 1 Clarification of 64 QAM usage at intra Node B serving HS-DSCH RL change 9.4.0 RP-100909 1634 2 Corrections to HSDPA secondary serving cell list handling 9.4.0 RP-100905 1637 Correction of procedure text for E-DCH SPS operation 9.4.0 RP-100904 1641 Addition of UE with enhanced HS-SCCH support indicator IE for Cell_FACH 9.4.0 RP-100904 1641 Addition of UE with enhanced HS-SCCH support indicator IE for Cell_FACH 9.4.0 RP-100911 1635 2 Introduction of 4C-HSDPA 10.0.0 RP-100910 1638 1 Small Technical Enhancements and Improvements for GNSS (RNSAP) 10.0.0 RP-101275 1642 Correction of 4C-HSDPA secondary serving HS-DSCH RL change 10.1.0 RP-101277 1644 2 Introduction of MC-HSDPA to RNSAP 10.1.0 RP-101269 1647 Corrections to E-DCH MAC-d Flow Multiplexing for 1.28Mcps TDD 10.1.0 RP-101269 1650 2 Correction of Inactivity Threshold for UE DRX Cycle for 1.28Mcps TDD 10.1.0 RP-101275 1657 1 Addition of simultaneous cell capability for Multi-Carrier HSDPA and Single Stream MIMO				2		
48 RP-100545 1631 Correction for Enhanced Serving Cell Change 9.3.0 49 RP-100904 1633 1 Clarification of 64 QAM usage at intra Node B serving HS-DSCH RL change 9.4.0 49 RP-100909 1634 2 Corrections to HSDPA secondary serving cell list handling 9.4.0 49 RP-100905 1637 Correction of procedure text for E-DCH SPS operation 9.4.0 49 RP-100904 1641 Addition of UE with enhanced HS-SCCH support indicator IE for Cell_FACH 9.4.0 09/2010 - - Release 10 version created based on v9.4.0 10.0.0 49 RP-100911 1635 2 Introduction of 4C-HSDPA 10.0.0 49 RP-100910 1638 1 Small Technical Enhancements and Improvements for GNSS (RNSAP) 10.0.0 50 RP-101275 1642 Correction of 4C-HSDPA secondary serving HS-DSCH RL change 10.1.0 50 RP-101274 1643 2 Introduction of MC-HSUPA to RNSAP 10.1.0 50 RP-101277 1644 2 Introduction of MU-MIMO to RNSAP						
RP-100904 1633 1 Clarification of 64 QAM usage at intra Node B serving HS-DSCH RL change 9.4.0 RP-100909 1634 2 Corrections to HSDPA secondary serving cell list handling 9.4.0 RP-100905 1637 Correction of procedure text for E-DCH SPS operation 9.4.0 RP-100904 1641 Addition of UE with enhanced HS-SCCH support indicator IE for Cell_FACH 9.4.0 RP-100904 1641 Addition of UE with enhanced HS-SCCH support indicator IE for Cell_FACH 9.4.0 RP-100911 1635 2 Introduction of 4C-HSDPA 10.0.0 RP-100910 1638 1 Small Technical Enhancements and Improvements for GNSS (RNSAP) 10.0.0 RP-101275 1642 Correction of 4C-HSDPA secondary serving HS-DSCH RL change 10.1.0 RP-101274 1643 2 Introduction of MC-HSDPA to RNSAP 10.1.0 RP-101277 1644 2 Introduction of MU-MIMO to RNSAP 10.1.0 RP-101269 1657 Corrections to E-DCH MAC-d Flow Multiplexing for 1.28Mcps TDD 10.1.0 RP-101271 1652 1 Power Offset For S-CPICH for MIMO of secondary cell 10.1.0 RP-101275 1657 1 Addition of simultaneous cell capability for Multi-Carrier HSDPA and Single Stream MIMO						
RP-100909 1634 2 Corrections to HSDPA secondary serving cell list handling 9.4.0 RP-100905 1637 Correction of procedure text for E-DCH SPS operation 9.4.0 RP-100904 1641 Addition of UE with enhanced HS-SCCH support indicator IE for Cell_FACH 9.4.0 RP-100910 Release 10 version created based on v9.4.0 10.0.0 RP-100911 1635 2 Introduction of 4C-HSDPA 10.0.0 RP-100910 1638 1 Small Technical Enhancements and Improvements for GNSS (RNSAP) 10.0.0 RP-101275 1642 Correction of 4C-HSDPA secondary serving HS-DSCH RL change 10.1.0 RP-101277 1644 2 Introduction of MC-HSUPA to RNSAP 10.1.0 RP-101279 1644 2 Introduction of MU-MIMO to RNSAP 10.1.0 RP-101269 1657 Corrections to E-DCH MAC-d Flow Multiplexing for 1.28Mcps TDD 10.1.0 RP-101271 1652 1 Power Offset For S-CPICH for MIMO of secondary cell 10.1.0 RP-101275 1657 1 Addition of simultaneous cell capability for Multi-Carrier HSDPA and Single Stream MIMO				1		
RP-100905 1637 Correction of procedure text for E-DCH SPS operation 9.4.0 RP-100904 1641 Addition of UE with enhanced HS-SCCH support indicator IE for Cell_FACH 9.4.0 RP-100910 Release 10 version created based on v9.4.0 10.0.0 RP-100910 1638 1 Small Technical Enhancements and Improvements for GNSS (RNSAP) 10.0.0 RP-101275 1642 Correction of 4C-HSDPA secondary serving HS-DSCH RL change 10.1.0 RP-101274 1643 2 Introduction of MC-HSUPA to RNSAP 10.1.0 RP-101277 1644 2 Introduction of MU-MIMO to RNSAP 10.1.0 RP-101269 1657 Corrections to E-DCH MAC-d Flow Multiplexing for 1.28Mcps TDD 10.1.0 RP-101271 1652 1 Power Offset For S-CPICH for MIMO of secondary cell 10.1.0 RP-101275 1657 1 Addition of simultaneous cell capability for Multi-Carrier HSDPA and Single Stream MIMO						
49 RP-100904 1641 Addition of UE with enhanced HS-SCCH support indicator IE for Cell_FACH 9.4.0 09/2010 - - - Release 10 version created based on v9.4.0 10.0.0 49 RP-100911 1635 2 Introduction of 4C-HSDPA 10.0.0 49 RP-100910 1638 1 Small Technical Enhancements and Improvements for GNSS (RNSAP) 10.0.0 50 RP-101275 1642 Correction of 4C-HSDPA secondary serving HS-DSCH RL change 10.1.0 50 RP-101274 1643 2 Introduction of MC-HSUPA to RNSAP 10.1.0 50 RP-101277 1644 2 Introduction of MU-MIMO to RNSAP 10.1.0 50 RP-101269 1647 Corrections to E-DCH MAC-d Flow Multiplexing for 1.28Mcps TDD 10.1.0 50 RP-101269 1650 2 Correction of Inactivity Threshold for UE DRX Cycle for 1.28Mcps TDD 10.1.0 50 RP-101271 1652 1 Power Offset For S-CPICH for MIMO of secondary cell 10.1.0 50 RP-101275 1657 1 Additio						
09/2010 - - - Release 10 version created based on v9.4.0 10.0.0 49 RP-100911 1635 2 Introduction of 4C-HSDPA 10.0.0 49 RP-100910 1638 1 Small Technical Enhancements and Improvements for GNSS (RNSAP) 10.0.0 50 RP-101275 1642 Correction of 4C-HSDPA secondary serving HS-DSCH RL change 10.1.0 50 RP-101274 1643 2 Introduction of MC-HSUPA to RNSAP 10.1.0 50 RP-101277 1644 2 Introduction of MU-MIMO to RNSAP 10.1.0 50 RP-101269 1647 Corrections to E-DCH MAC-d Flow Multiplexing for 1.28Mcps TDD 10.1.0 50 RP-101269 1650 2 Correction of Inactivity Threshold for UE DRX Cycle for 1.28Mcps TDD 10.1.0 50 RP-101271 1652 1 Power Offset For S-CPICH for MIMO of secondary cell 10.1.0 50 RP-101275 1657 1 Addition of simultaneous cell capability for Multi-Carrier HSDPA and Single Stream 10.1.0				-		
49 RP-100911 1635 2 Introduction of 4C-HSDPA 10.0.0 49 RP-100910 1638 1 Small Technical Enhancements and Improvements for GNSS (RNSAP) 10.0.0 50 RP-101275 1642 Correction of 4C-HSDPA secondary serving HS-DSCH RL change 10.1.0 50 RP-101274 1643 2 Introduction of MC-HSUPA to RNSAP 10.1.0 50 RP-101277 1644 2 Introduction of MU-MIMO to RNSAP 10.1.0 50 RP-101269 1647 Corrections to E-DCH MAC-d Flow Multiplexing for 1.28Mcps TDD 10.1.0 50 RP-101269 1650 2 Correction of Inactivity Threshold for UE DRX Cycle for 1.28Mcps TDD 10.1.0 50 RP-101271 1652 1 Power Offset For S-CPICH for MIMO of secondary cell 10.1.0 50 RP-101275 1657 1 Addition of simultaneous cell capability for Multi-Carrier HSDPA and Single Stream MIMO 10.1.0		117-100904	1041			
49 RP-100910 1638 1 Small Technical Enhancements and Improvements for GNSS (RNSAP) 10.0.0 50 RP-101275 1642 Correction of 4C-HSDPA secondary serving HS-DSCH RL change 10.1.0 50 RP-101274 1643 2 Introduction of MC-HSUPA to RNSAP 10.1.0 50 RP-101277 1644 2 Introduction of MU-MIMO to RNSAP 10.1.0 50 RP-101269 1647 Corrections to E-DCH MAC-d Flow Multiplexing for 1.28Mcps TDD 10.1.0 50 RP-101269 1650 2 Correction of Inactivity Threshold for UE DRX Cycle for 1.28Mcps TDD 10.1.0 50 RP-101271 1652 1 Power Offset For S-CPICH for MIMO of secondary cell 10.1.0 50 RP-101275 1657 1 Addition of simultaneous cell capability for Multi-Carrier HSDPA and Single Stream MIMO 10.1.0		- DD 100014	1625	-		
RP-101275 1642 Correction of 4C-HSDPA secondary serving HS-DSCH RL change 10.1.0 RP-101274 1643 2 Introduction of MC-HSUPA to RNSAP 10.1.0 RP-101277 1644 2 Introduction of MU-MIMO to RNSAP 10.1.0 RP-101269 1647 Corrections to E-DCH MAC-d Flow Multiplexing for 1.28Mcps TDD 10.1.0 RP-101269 1650 2 Correction of Inactivity Threshold for UE DRX Cycle for 1.28Mcps TDD 10.1.0 RP-101271 1652 1 Power Offset For S-CPICH for MIMO of secondary cell 10.1.0 RP-101275 1657 1 Addition of simultaneous cell capability for Multi-Carrier HSDPA and Single Stream MIMO						
RP-101274 1643 2 Introduction of MC-HSUPA to RNSAP 10.1.0 RP-101277 1644 2 Introduction of MU-MIMO to RNSAP 10.1.0 RP-101269 1647 Corrections to E-DCH MAC-d Flow Multiplexing for 1.28Mcps TDD 10.1.0 RP-101269 1650 2 Correction of Inactivity Threshold for UE DRX Cycle for 1.28Mcps TDD 10.1.0 RP-101271 1652 1 Power Offset For S-CPICH for MIMO of secondary cell 10.1.0 RP-101275 1657 1 Addition of simultaneous cell capability for Multi-Carrier HSDPA and Single Stream MIMO				1		
RP-101277 1644 2 Introduction of MU-MIMO to RNSAP 10.1.0				2		
50RP-1012691647Corrections to E-DCH MAC-d Flow Multiplexing for 1.28Mcps TDD10.1.050RP-10126916502Correction of Inactivity Threshold for UE DRX Cycle for 1.28Mcps TDD10.1.050RP-10127116521Power Offset For S-CPICH for MIMO of secondary cell10.1.050RP-10127516571Addition of simultaneous cell capability for Multi-Carrier HSDPA and Single Stream MIMO10.1.0						
RP-101269 1650 2 Correction of Inactivity Threshold for UE DRX Cycle for 1.28Mcps TDD 10.1.0 RP-101271 1652 1 Power Offset For S-CPICH for MIMO of secondary cell 10.1.0 RP-101275 1657 1 Addition of simultaneous cell capability for Multi-Carrier HSDPA and Single Stream MIMO 10.1.0						_
RP-101271 1652 1 Power Offset For S-CPICH for MIMO of secondary cell 10.1.0 RP-101275 1657 1 Addition of simultaneous cell capability for Multi-Carrier HSDPA and Single Stream 10.1.0 MIMO						
RP-101275 1657 1 Addition of simultaneous cell capability for Multi-Carrier HSDPA and Single Stream 10.1.0 MIMO						
MIMO						
50 RP-101275 1658 3 Throughput/Energy Savings tradeoff for Dual Band UEs 10.1.0				1	MIMO	
	50	RP-101275	1658	3	Throughput/Energy Savings tradeoff for Dual Band UEs	10.1.0

				,	
SP-49	SP-100629			Clarification on the use of References (TS 21.801 CR#0030)	10.2.0
51	RP-110222		1	Addition of Measurement Power Offset in ESCC procedure over lur	10.2.0
51	RP-110224			Addition of Multi-Carrier E-DCH capability IEs for MC-HSUPA to RNSAP	10.2.0
51	RP-110225		1	Correction related to "Power Offset For S-CPICH for MIMO"	10.2.0
51	RP-110224			Correction of SNPL carrier group indicator for 1.28 Mcps TDD Multi-Carrier E-DCH	10.2.0
51	RP-110228		1	Battery optimization - tabular/ASN.1 mismatch cleanup	10.2.0
51	RP-110230		1	Introduction of MDT	10.2.0
51	RP-110226	1669	5	Extension of maximum number neighbouring RNCs	10.2.0
52	RP-110688	1674	1	Clarification on the Range of Possible Secondary Serving Cell List	10.3.0
52	RP-110681	1677	1	Misalignment between message tabular and ASN.1 for Idle Interval Information IE	10.3.0
52	RP-110689	1678	3	Extend the Number of Supported Carriers for Multi-Carrier HSDPA for 1.28Mcps TDD	10.3.0
52	RP-110880	1681	4	Introduction of Enhancements of lur-g Interface	10.3.0
52	RP-110689		1	Correction of the dependency of RNSAP to a specific signalling transport network layer	10.3.0
52	RP-110693	1683	3	Introduction of information transfer control for UTRAN ANR related information	10.3.0
52	RP-110681	1685	1	UE support indicator for DL secondary HS-DSCH activation state according to RRC Rel-9	10.3.0
52	RP-110690	1686	1	Correction of abnormal condition text	10.3.0
52	RP-110686		1	Rapporteur's proposal following review of TS 25.423	10.3.0
52	RP-110693	1688	2	ANR Report Distribution using Direct Information Transfer procedure	10.3.0
52	RP-110693		2	ANR Neighbour cell configuration supported by Information Exchange Initiation procedure	10.3.0
52	RP-110685	1690		Reference review outcome in TS 25.423	10.3.0
53	RP-111194		1	Corrections to UMTS ANR	10.4.0
53	RP-111195	1699	1	Clarification on M1 and M2 in MDT Configuration over lur	10.4.0
53	RP-111195	1700	3	Clarification on MDT Recording Session Reference in MDT Configuration	10.4.0
53	RP-111195	1701	2	Area scope RAI list in MDT configuration	10.4.0
53	RP-111194	1706	-	Correction of Frequency Band Indicator, adding Band XXV	10.4.0
53	RP-111196	1708	1	Rapporteur corrections	10.4.0
53	RP-111196		-	Correction of some generic references to dated references	10.4.0
53	RP-111196	1710	1	Correction of the CELL_DCH Measurement Occasion Information for 1.28Mcps TDD	10.4.0
54	RP-111649	1715	2	Addition of TCE IP in IUR INVOKE TRACE	10.5.0
54	RP-111651	1718	1	Support for frequency specific compressed mode	10.5.0
54	RP-111645	1724	2	Support of dynamic HS-SCCH order for DTXDRX	10.5.0
55	RP-120231	1731	2	The role of RNC in RNSAP Reset procedure	10.6.0
55	RP-120234	1734	-	Correction of placement of Power Offset For S-CPICH for MIMO Request Indicator IE	10.6.0
56	RP-120815	1739	-	Clarification of the carrier capability for two-carrier HSDPA for 1.28Mcps TDD	10.7.0
56	RP-120744	1742	-	Clarification of the enhanced TS0 capability for 1.28Mcps TDD	10.7.0
57	RP-121131	1755		Corrections on Multicell E-DCH Restriction of Secondary cell list	10.8.0
59	RP-130224	1781	2	Addition of new information to neighbouring E-UTRA cell information element	10.9.0
59	RP-130205	1784	1	Adding enhanced serving cell change support for 4C-HSDPA	10.9.0
59	RP-130223		1	Erroneous addition of MDT configuration to lur	10.9.0

History

Document history					
V10.2.0	May 2011	Publication			
V10.3.0	July 2011	Publication			
V10.4.0	November 2011	Publication			
V10.5.0	January 2012	Publication			
V10.6.0	April 2012	Publication			
V10.7.0	August 2012	Publication			
V10.8.0	November 2012	Publication			
V10.9.0	April 2013	Publication			
V10.10.0	January 2014	Publication			